Electrical, Instrumentation and Controls Operation & Maintenance Manual

for the Iqaluit Wastewater Treatment Plant

Iqaluit, Nunavut

Expected Year of Completion: 2020

Original Scope: Design and upgrade existing Wastewater Treatment Plant to meet current and future demands.

This manual has been updated to include:

Date	Description of Change
2019-Mar-01	First Draft – Primary Treatment
2020-Jan-27	Second Draft – Primary Treatment, Secondary Treatment and Solids Handling.
2020-Apr-24	Final Compiled Manual

CHAPTER 1

TABLE OF CONTENTS

1. INTRODUCTION 1.1
1.1 USE OF THE MANUAL 1.1
1.2 PROJECT TEAM 1.1

CHAPTER 1

1. INTRODUCTION

1.1 USE OF THE MANUAL

The discussion in this document includes the background and design data for the Electrical, Instrumentation and Controls included in the Iqaluit Wastewater Treatment Plant only. Refer to the Architectural and Structural, Building Mechanical and Process Operation and Maintenance Manuals for information on those systems.

1.2 PROJECT TEAM

Project Owner:	**City of Iqaluit** Building 901, PO Box 460, Iqaluit, NU X0A 0H0 Matthew Hamp Project Manager
Project Management:	**Colliers Project Leaders** Suite 700, 150 Isabella Street Ottawa, ON K1S 1V7 Charles Kretch Project Manager
Consultant:	**Nunami Stantec Limited** 1880C Nobel House Iqaluit, NU X0A 0H0 Glenn Prosko Project Manager
Contractor:	**Kudik Construction Ltd** 1519 Federal Rd. Iqaluit, NU X0A 0H0 Sandra Rousseau Project Manager

CHAPTER 2

TABLE OF CONTENTS

2. INDEX

1. INTRODUCTION 1.1
1.1 USE OF THE MANUAL 1.1
1.2 PROJECT TEAM 1.1

CHAPTER 2 ..... 1.1

2. INDEX 2.1

CHAPTER 3 2-1

3. BACKGROUND AND DESIGN DATA 3-1
3.1 PRIOR FACILITIES 3-1
3.2 NEW FACILITIES 3-2
3.2.1 Electrical (General) 3-2
3.2.1.1 Electrical Wiring 3-2
3.2.1.2 Power Distribution Systems 3-2
3.2.1.3 Motor Control Centre – 1 (MCC-1) and 2 (MCC-2) 3-3
3.2.1.4 Distribution Panel 6B 3-3
3.2.1.5 Distribution Panel 2A 3-3
3.2.1.6 Distribution Panel 2B 3-3
3.2.1.7 Distribution Panel 2C 3-3
3.2.1.8 Distribution Panel 4A 3-3
3.2.2 Process Controls and Alarms 3-3
3.2.2.1 Wastewater Treatment Process Control 3-4
3.2.2.2 Telecommunications/Alarm Dialer 3-4
3.2.2.3 WWTP Gas Detection 3-5
3.2.2.4 Instrumentation and Controls Upgrades 3-5

4. SCHEMATICS AND FUNCTIONAL DATA 4.1
4.1 GENERAL 4.1
4.2 POWER DISTRIBUTION SCHEMATIC 4.1
4.3 INSTRUMENTS 4.3
4.4 MOTOR CONTROL CENTRE 4.17

5. COMPONENT DETAILS 5.1
5.1 GENERAL OVERVIEW 5.1
5.2 POWER DISTRIBUTION SYSTEM 5.1
5.3 PLC CONTROL SCHEMATIC 5.2
5.4 MOTOR CONTROL CENTRE 5.13

6. OPERATING PROCEDURES 6.1
6.1 GENERAL 6.1
6.2 FACILITY POWER AND STANDBY POWER SYSTEM 6.1
6.2.1 Controls 6.1
6.2.1.1 Generator 6.1
6.2.1.2 Transfer Switch 6.1
6.2.1.3 Ventilation Louvres 6.1
6.2.2 Emergency Generator 6.2
6.2.2.1 Automatic Operation 6.2
6.2.2.2 Manual Operation 6.2
6.2.2.3 Emergency Stop 6.2
6.2.3 Transfer Switch 6.2
6.2.3.1 Automatic Operation 6.2
6.2.3.2 Test 6.2
6.2.3.3 Alternate Test Procedure 6.2

7. MAINTENANCE PROCEDURES AND SERVICE INFORMATION 7.1
7.1 GENERAL 7.1
7.1.1 Keep It Clean 7.1
7.1.2 Keep It Tight 7.1
7.1.3 Renewal Parts 7.1
7.1.4 Parts and Equipment Ordering Procedure 7.2
7.1.5 Scheduled Preventive Maintenance Program 7.2
7.2 MAINTENANCE SCHEDULE 7.2
7.3 MAINTENANCE MANUALS 7.2
7.4 SPARE PARTS LIST 7.3

8. TESTING AND CERTIFICATION 8.1

9. MANUFACTURER DATA AND SERVICE INFORMATION 9.1

LIST OF APPENDICES

APPENDIX A – AS-BUILT DRAWINGS

APPENDIX B – APPROVED SHOP DRAWINGS

APPENDIX C – MAINTENANCE SCHEDULE

APPENDIX D – EQUIPMENT MAINTENANCE MANUALS

APPENDIX E – SPARE PART LIST

APPENDIX F – CONTACT SERVICE INFORMATION

APPENDIX G – WARRANTIES

CHAPTER 3

3. BACKGROUND AND DESIGN DATA

3.1 PRIOR FACILITIES

Wastewater management in Iqaluit dates back to 1964 when a sanitary sewer outfall, made of five pipes, discharged raw sewage directly onto the beaches of the community of Frobisher Bay, as it was called back then. Shoreline discharge of raw sewage lasted for 12 years when the construction of several lift stations provided the means to pump sewage to a macerator system at the head of Koojesse Inlet. At the same time, a holding pond was built on the tidal plain at the head of the inlet. This facility operated successfully for several decades. However, several overflow and breaching events demanded improvements in the earth structures, and the perimeter drainage of the facility. The lagoon performed well improvements in the earth structures, and the perimeter drainage of the facility. The lagoon performed well as a primary treatment facility, with a continuous discharge. Effluent quality from the lagoon systems varied significantly over the course of the year because the only process at work in the winter months was sedimentation. In the early 90's, regulatory expectations prompted the City to complete an engineering feasibility study on improving the treatment system. The first attempt to implement a secondary treatment for Iqaluit was a design-build contract that was awarded in 1998 to a contractor that selected a membrane bioreactor (MBR) process. Unfortunately, the inexperience of the design builder in northern wastewater treatment became evident by mid-1999. An evaluation of the incomplete sewage treatment plant was performed in 2002 towards conducting remedial work. Phase 1 of the remedial work involved building the primary treatment system in an addition to the original building, and this work was completed in 2006. The following upgrades were implemented at that time:

- All electrical systems installed within the facility were both code compliant and energy efficient. Electrical distribution was sized to accommodate the as-built requirements and future expansion of the treatment systems and/or pumping requirements of the facility.
- The plant electrical and controls system wiring was provided by Teck cabling or wiring contained in conduit.
- The electrical service was provided from the existing Main Distribution Panel (MDP), located in the lower level Motor Control Centre (MCC). Power was distributed from existing MDP through two 3P 200A circuit breakers. One breaker fed the MCC-2, located in Upper Level Electrical Room 3. The other breaker fed panel 6B and panel 2B also located in Upper Level Electrical Room 3. MCC-2 was configured to operate various process and mechanical equipment.
- A 347/600 V, 42-circuit distribution panel feeds the 347/600 V loads. The 347/600 V loads included exterior and interior lighting for WWTP, the headworks hoist and the hot FEW booster heater. A 3P-50A circuit breaker fed transformer TX 2, which feeds distribution panel 2B.

- A 120/208 V, 42-circuit distribution panel powered various single-phase headwork's components.
- The overall wastewater treatment process was controlled utilizing a Programmable Logic Controller (PLC) based on the Allen Bradley SLC 500 series. This PLC system included the Facility Control System and any related communication and operator interface components. The Human Machine Interface (HMI) operator interface system is provided by a single personal computer (PC), located in the plant office. The main control panel of the facility was located in Electrical Room 3. The PLC was remotely accessible via a modem in the HMI PC, and the corresponding Ethernet link between the PC and PLC.
- The WWTP had a dedicated phone line for the facility alarm dialer. When the facility is unoccupied, alarms requiring operator intervention were annunciated on both the PLC and to the operator via an auto dialer.
- The WWTP gas alarm detection system consisted of two LEL and two H2S detectors, a central control panel. Visual and audible annunciation were included in both the Headworks Room and on the building exterior.

3.2 NEW FACILITIES

3.2.1 Electrical (General)

All electrical systems installed within the new facility are both code compliant and energy efficient. Electrical distribution is sized to accommodate the as-built requirements and future expansion of the treatment systems and/or pumping requirements of the facility.

3.2.1.1 Electrical Wiring

The plant electrical and controls system wiring is provided by Teck cabling or wiring contained in conduit.

3.2.1.2 Power Distribution Systems

The electrical service for Phase 1 is provided from the new Main Distribution Panel (MDP), located in the Electrical Room #2 202. Power is distributed from new MDP through five circuit breakers. One 3P250A breaker feeds the new MCC-1, located in Electrical Room #2 202. The second 3P60A breaker feeds existing MCC-2, located in Electrical Room #1 209. Third 3P150A breaker feeds new CDP-1 located in Electrical Room #2 202 via new TX-1. Fourth 3P100A breaker feeds existing panel 6B located in Electrical Room #1 209. Last 3P200A breaker feeds new panel 4A Electrical Room #2 202 via TX-3. Central Distribution Panel CDP-1 feeds new panel 2C located in Generator Room, existing panel 2B located in Electrical Room #1 209 and new panel 2A located in Generator Room trough three 3P100A circuit breakers. Refer to electrical single line diagram E6031 at the end of Chapter 4 for detailed power distribution.

3.2.1.3 Motor Control Centre – 1 (MCC-1) and 2 (MCC-2)

MCC-1 and MCC-2 are configured to operate various process and mechanical equipment. Refer to Chapter 6 of the Process Operations and Maintenance Manual for the WWTP operating procedures relating to this equipment. Refer to MCC diagram E603 and Controls Table on E-8 at the end of Chapter 4 for details.

3.2.1.4 Distribution Panel 6B

A 347/600 V, 42-circuit distribution panel feeds the 347/600 V loads. The 347/600 V loads include exterior and interior lighting for WWTP. Refer to electrical panel schedule E608 at the end of Chapter 4 for details.

3.2.1.5 Distribution Panel 2A

A 120/208 V, 60-circuit distribution panel powers various single and three phase mechanical equipment.

Refer to electrical panel schedule E608 at the end of Chapter 4 for details.

3.2.1.6 Distribution Panel 2B

A 120/208 V, 42-circuit distribution panel powers various single and three phase WWTP components and mechanical equipment. Refer to electrical panel schedule E608 at the end of Chapter 4 for details.

3.2.1.7 Distribution Panel 2C

A 120/208 V, 42-circuit distribution panel powers various single and three phase WWTP components and mechanical equipment. Refer to electrical panel schedule E608 at the end of Chapter 4 for details.

3.2.1.8 Distribution Panel 4A

A 277/480 V, 42-circuit distribution panel powers various three phase process equipment. Refer to electrical panel schedule E608 at the end of Chapter 4 for details.

3.2.2 Process Controls and Alarms

The overall wastewater treatment process is controlled utilizing two (2) Main Programmable Logic Controllers (PLCs) based on the Allen Bradley ControlLogix series. This PLC system includes the Plant Control System equipment, vendor package integration, and any related communication and operator interface components. The Human Machine Interface (HMI) operator interface system is provided by a personal computer (PC) located in the plant office and a touch-panel monitor in the new electrical room. The two main control panels are located in Electrical Room 3 and outside Electrical Room 2 in the DAF area. The PLC system generates discrete output signals to the auto dialer for critical alarm reporting. The PLC and HMI is remotely

accessible via a VPN link of the Internet. The two (2) Main PLCs interact with Vendor PLCs which performs the equipment specific functions.

3.2.2.1 Wastewater Treatment Process Control

Phase 1 of the WWTP is controlled utilizing a PLC with an HMI. The overall WWTP is depicted on the Process and Instrumentation Diagrams (P&ID). The process that is used at the WWTP is Primary Treatment, which consists of the following unit processes:

- Raw Wastewater Pumping;
- Raw Sewage Screening;
- Primary Treatment (Filtration); and
- Solids Handling.

The primary treatment PLC interacts with the vendor PLCs (Primary Filter PLC, Fine Screen PLC, for detailed equipment control.

Phase 2 of the WWTP is controlled utilizing a PLC with an HMI. The process that is used at the WWTP for Secondary Treatment, consists of the following unit processes:

- Process Aeration Blowers;
- Moving Bed Biofilm Reactors;
- Dissolved Air Floatation Tanks complete with Whitewater Pumping;
- Belt Filter Press; and
- Polymer Injection for DAF and BFP systems.

The secondary treatment PLC interacts with the vendor PLCs (DAF PLC, BFP PLC) for detailed equipment control.

Refer to Drawings I101 through I207 in Appendix A of this Manual for the overall wastewater treatment process instrumentation schematic. Refer to Drawing PC-109 in Appendix A for information on local communications.

Refer to Chapter 6 of the Process Operations and Maintenance Manual for the WWTP operating procedures relating to this equipment.

3.2.2.2 Telecommunications/Alarm Dialer

The WWTP has a dedicated phone line for the facility alarm dialer. High priority alarms (operator-adjustable) will be annunciated on both the HMI and to the operator via an auto dialer.

3.2.2.3 WWTP Gas Detection

The WWTP gas alarm detection system consists of LEL and H_2S detectors throughout the process area. Visual beacons are located at the entry of any hazardous areas to alert operations to issues before entering a hazardous space. Visual and audible annunciation are also located within the hazardous spaces.

Blue beacons are used to indicate high levels of H2S and amber beacons are used to indicate high levels of methane (LEL). The beacons will illuminate in the room a gas event has been detected in and stay lit until the gas event has been cleared. The audible horn will be enabled in the room the gas event has been detected in but will silence when the alarm has been acknowledged via the plant SCADA system. The horn will re-enable on each new level of alarm (e.g. If the high alarm was silenced, a high-high will re-enable it).

Each gas detector is also fitted with a senor failure alarm. If any gas detector has an internal failure, an alarm is generated on the plant SCADA system.

Initial alarm limits for the gas detection are as follows:

Type of Gas	High	High-High
Methane (% LEL)	10%	20%
H_2S	2ppm	10ppm

Carbon Monoxide Detection has been added to the new Electrical Room 209.

3.2.2.4 Instrumentation and Controls Upgrades

The upgraded WWTP has a completely integrated instrumentation and controls system. The system is configured to ensure the reliable operation of the treatment process in a continuous automatic mode. Refer to the Iqaluit WWTP Process Control Narrative for further details regarding the control of the plant.

Refer to Section 4.3 for a list of installed instruments.

In general, the process control of the WWTP is controlled by two Programmable Logic Controllers (PLCs) that communicate with the field instruments/devices and vendor packages required to monitor and control each individual aspect of the treatment process. Plant systems will operate in Automatic, Remote Manual, or Local modes.

Operation Modes

Automatic - Automatic control will be performed by programmed logic within the PLC that controls the respective segments of the process. The automatic mode is invoked by placing the local selector switch or switches in the automatic position and enabling the programmed logic within the PLC network to provide control. Where local PLCs and operator interface terminals are utilized (with vendor supplied packaged equipment) the onboard interface terminal will be provided with a local/remote select via the operator interface.

Remote Manual - With the local switch in the automatic mode, the operator will have the option to manually control the equipment from the main operator work station or the plant floor operator interface terminals.

Local - Equipment can be manually controlled by placing the local selector switch in the hand or off position. Vendor supplied packaged equipment will be locally operable on manual mode by selecting local control and interacting with this equipment from the onboard interface terminal.

Plant Alarms

Plant alarms will be categorized into three groups – Safety, Major, and Minor. The categories are defined as follows:

- Safety alarms are conditions that are dangerous to personnel or property and require immediate response.
- Major alarms are conditions that require immediate attention.
- Minor alarms are conditions that do not require immediate attention.

Each category of alarm will have a resulting outcome with operator actions to manage the alarm condition (e.g. major alarms require immediate attention; minor alarm conditions should be noted but are non-urgent).

For vendor supplied packaged equipment, such as blowers, a separate discrete visual warning display, provided with the package, will be located at the equipment but integrated with the plant computer alarm system.

A safety alarm can be defined as a condition that could cause danger to life if not given the appropriate attention immediately. The alarm could be generated from; process equipment, combustible gas detection systems or fire detection systems. Safety alarms will be wired directly from the primary initiating device to the audible and visual warning devices installed at key locations around the plant (e.g. bells or horns, and warning units including access points in process areas). A discrete status contact will be taken from the primary sensor to the plant computer system to warn that a safety alarm has been initiated.

Plant Trend Data and Information Archive

The control system computing will be configured to allow the trending of pre-determined process variables. These trends will be operator configurable to allow the selection of trend variables, trend time bases, and the trend scale. The data required for process trending will be stored in a historian database for archive purposes. Archive data can also be retrieved and compiled to provide monthly or annual reports.

Plant Control System (PCS)

The plant control system (PCS) will utilize two PLCs and vendor package supplied PLCs based subsystems connected on an industrial control network to form a single integrated PCS. The PLCs, software, and communications network components are of a uniform manufacturer to ensure that the system will not require physical media or software protocol converters to operate.

System Hardware

The WWTP is currently fitted with Allen Bradley (Rockwell Automation) PLC and corresponding software systems. The design intent for the new WWTP is to standardize the entire site to Allen Bradley (Rockwell Automation) PLCs and corresponding software systems. This uniformity of technology manufacturer provides advantages in that both operations and maintenance personnel will need to train on, and be familiar with, only one technology platform. Two new operator machines will be provided as part of this work to provide redundant SCADA PCs for the operators.

System Software

The PCS will utilize several different pieces of software to provide the various system functions. New PLC logic will be developed and implemented using Rockwell Automation RSLogix 5000. The SCADA system will be replaced by Inductive Automation's Ignition software. Ignition is being utilized for the SCADA system throughout the City of Iqaluit and will provide compatibility and continuity throughout the water/wastewater system. This compatibility minimizes effort required to integrate the operator interface with the process control, allowing for better operator tools.

It is anticipated that the complete PCS will consist of several PLCs installed at the following locations:

- Headworks (new PLC)
- Screens / screenings conveyor/ washer compactor (Vendor package)
- Primary filter (vendor package)
- Secondary treatment (new PLC)
- Blower control (vendor package)
- DAF control (vendor package)
- BFP control (vendor package)
- Polymer injection systems (vendor packages)

PLC hardware and system software packages is standardized to ensure all systems can communicate and share equipment status and control information over a common platform. Where packaged equipment vendors cannot provide PLC based controls that are appropriately compatible with the plant PCS other alternatives will be pursued.

Control Panel UPS

Each PCS control panel will be equipped with an uninterruptable power supply (UPS). The UPS will keep the control system powered during momentary power outages. Each UPS generates alarms on loss of utility power, low battery, general fault, and UPS bypass.

System Communications

Individual PLCs will be networked together to form a complete plant automation system. The design approach will be to provide the control systems network using an Ethernet/IP protocol. This control network will be configured in a star topology using copper-based Category 6 Cabling. The size of the plant footprint will not require other media to address transmission distance restrictions. The PCS will also be connected to a plant information network. The plant information network will provide data connections for operator interface computers, operator interface terminals on the plant floor, engineering workstations, and the plant data historian.

Motor Control and Variable Frequency Drives

A large portion of the plant control will be provided through the control of electric drive motors. These motors will be fed from Motor Control Centers (MCCs) located in the headworks and the secondary treatment areas of the plant. Where variable frequency drives (VFDs) are required to provide a variable pumping or treatment equipment speed, they will be located within the MCCs to avoid the harsh environment of the plant floor. The control system interface for fixed speed motor starters and the variable frequency drives within the MCCs will be via Ethernet/IP communications protocol.

Process Instruments and Control Devices

Process measurement and control devices were specified to provide rugged, reliable, industrial quality components. These devices were selected with the intent to ensure that they have local vendor service and support. Where possible, devices such as flow meters, pressure, temperature, and level instruments were selected to correspond with the manufacturers/types that are currently installed in the WWTP.

Where instruments and control devices are to be installed in areas classified as hazardous atmospheres the devices were rated and installed to meet the appropriate code requirements.

Rated spaces such as the headworks area, where possible, have only the essential devices installed within the space.

The rated spaces were fitted with gas detection systems which will provide local, visual, and audible alarm signaling. The gas detection system will be provided as a complete certified system and will not rely on the plant PLCs or control network to operate. The gas detection system will however provide alarm information to the plant PCS so that operations staff will have all required alarm location information available without having to enter the space.

END OF CHAPTER 3

CHAPTER 4

4. SCHEMATICS AND FUNCTIONAL DATA

4.1 GENERAL

The following tables describe where the components to the various systems are located and the function that each performs. For each table, there are drawings that can be referenced, to better understand the flow of that part of the Water Treatment Plant.

4.2 POWER DISTRIBUTION SCHEMATIC

(Refer to Drawing E603 in Appendix A)

The following table identifies the components related to the power distribution system.

No.	Component	Location	Function Performed	Remarks
1	400A Main Distribution	Electrical room 202	Provides service to facility.	
2	400A Transfer Switch	Electrical room 202		
3	3P 100 Amp circuit breaker to Panel 6B	400A Main Distribution Panel	Protect circuit to MCC-2	
4	3P 150Amp circuit breaker to CDP-1	400A Main Distribution Panel	Protect circuit to MDP-1	
5	3P 60Amp circuit breaker to MCC-1	400A Main Distribution Panel	Protect circuit to MDP-1	
6	3P 200Amp circuit breaker to 4A	400A Main Distribution Panel	Protect circuit to MDP-1	
7	3P 250Amp circuit breaker to MCC-1	400A Main Distribution Panel	Protect circuit to MDP-1	
8	SPD	MDP-1, DCP-1, MCC-1, MCC-2	Power Condition Monitor	
9	Central Distribution Panel CDP-1	Electrical room 202		
10	3P 100A Sub breaker, Panel 2A	CDP-1	Protect circuit to panel 2A	
11	3P 100A Sub breaker, Panel 2B	CDP-1	Protect circuit to panel 2B	
12	3P 100A Sub breaker, Panel 2B	CDP-1	Protect circuit to panel 2C	

No.	Component	Location	Function Performed	Remarks
13	112.5kVATransformer to CDP-1	Electrical room 202	Provide power to panel CDP-1	
14	45kVA Transformer to Panel 4A	Electrical room 202	Provide power to panel 4A	
15	Distribution panel 2A	Generator room		
16	Distribution panel 2B	Electrical Room 209		
17	Distribution panel 2C	Generator room		
18	Distribution panel 4A	Electrical Room 202		
19	Distribution panel 6B	Electrical Room 209		
20	Motor Control Center #1	Electrical Room 202		
21	Motor Control Center #2	Electrical Room 209		

4.3 INSTRUMENTS

(Refer to Instrumentation Drawings in Appendix A)

The following table identifies the instruments used in the WWTP.

No.	Component	Location	Function Performed	Remarks
1	Flow Meter (FQIT-01-150)	RS Piping, Lower Floor	Measures influent flow into the Plant	Signals the PLC
2	Level Indicating Transmitter (LIT-01-100)	Mounted in the pump well	Indicates the wastewater level in the pump well	Signals the PLC
3	Level Switch (LSLL-01-111)	Mounted in the pump well	Indicates the low low wastewater level in the pump well	Signals the PLC
4	Level Switch (LSL-01-112)	Mounted in the pump well	Indicates the low wastewater level in the pump well	Signals the PLC
5	Level Switch (LSH-01-113)	Mounted in the pump well	Indicates the high wastewater level in the pump well	Signals the PLC
6	Level Switch (LSHH-01-114)	Mounted in the pump well	Indicates the high-high wastewater level in the pump well	Signals the PLC
7	Motorized Knife Gate Valve (KV-01-211)	Headworks Upper Floor	Control sewage to SCRN-02-210	PLC Controlled
8	Level Indicating Transmitter (LIT-01-211)	Mounted on coarse screen tank wall	Indicates the wastewater level in the screen channel SCRN-01-210	Signals the vendor PLC
9	Solenoid Valve (SV-01-120)	In coarse screen tankage	Controls the flow of wash water to SCRN-01-210	Vendor PLC Controlled
10	Solenoid Valve (SV-01-122)	In coarse screen tankage	Controls the flow of wash water to SCRN-01-210	Vendor PLC Controlled
11	Motorized Knife Gate Valve (KV-01-221)	Headworks Upper Floor	Control sewage to SCRN-02-220	PLC Controlled
12	Level Indicating Transmitter (LIT-01-221)	Mounted on coarse screen tank wall	Indicates the wastewater level in the screen channel SCRN-01-220	Signals the vendor PLC
13	Solenoid Valve (SV-01-124)	In coarse screen tankage	Controls the flow of wash water to SCRN-01-220	Vendor PLC Controlled

No.	Component	Location	Function Performed	Remarks
14	Solenoid Valve (SV-01-126)	In coarse screen tankage	Controls the flow of wash water to SCRN-01-220	Vendor PLC Controlled
15	Motorized Knife Gate Valve (KV-01-112)	Headworks Lower Floor	Control screening discharge to trailer	PLC Controlled
16	Motorized Knife Gate Valve (KV-01-112A)	Headworks Lower Floor	Control primary filter discharge to trailer	PLC Controlled
17	Solenoid Valve (SV-01-113)	Headworks Upper Floor	Drains primary filter PF-01-310	Vendor PLC Controlled
18	Solenoid Valve (SV-01-312)	Headworks Upper Floor	Controls flow of hot non-potable wash water to PF-01-310 & SP-01-330	Vendor PLC Controlled
19	Solenoid Valve (SV-01-322)	Headworks Upper Floor	Controls flow of cold non-potable wash water to PF-01-310	Vendor PLC Controlled
20	Motorized Knife Gate Valve (KV-01-111, FV-111)	Headworks Upper Floor	Controls flow to primary filter PF-01-310	PLC Controlled
21	Level Transmitter (LIT-01-115)	Headworks Upper Floor	Indicates level of primary filter PF-01-310	Vendor PLC Controlled
22	Pressure Transmitter (PT-01-116)	Headworks Upper Floor	Indicates air pressure to primary filter PF-01-310	Vendor PLC Controlled
23	Solenoid Valve (SV-01-123)	Headworks Upper Floor	Drains primary filter PF-01-320	Vendor PLC Controlled
24	Solenoid Valve (SV-01-313)	Headworks Upper Floor	Controls flow of hot non-potable wash water to PF-01-320 & SP-01-340	Vendor PLC Controlled
25	Solenoid Valve (SV-01-323)	Headworks Upper Floor	Controls flow of cold non-potable wash water to PF-01-320	Vendor PLC Controlled
26	Motorized Knife Gate Valve (KV-01-121, FV-121)	Headworks Upper Floor	Controls flow to primary filter PF-01-320	PLC Controlled
27	Level Transmitter (LIT-01-125)	Headworks Upper Floor	Indicates level of primary filter PF-01-320	Vendor PLC Controlled
28	Pressure Transmitter (PT-01-126)	Headworks Upper Floor	Indicates air pressure to primary filter PF-01-320	Vendor PLC Controlled
29	Motorized Knife Gate Valve (KV-01-001, FV-01-001)	Headworks Upper Floor	Diverts primary effluent overflow to outfall	PLC Controlled

No.	Component	Location	Function Performed	Remarks
30	Pressure Indicator (PI-02-217)	Headworks Upper Floor	Indicates air pressure	
31	Pressure Indicator (PI-02-227)	Headworks Upper Floor	Indicates air pressure	
32	Pressure Indicator (PI-107)	Secondary Treatment - Upper	Indicates air pressure	
33	Pressure Switch (PSL-108)	Secondary Treatment - Upper		Signal to PLC
34	Pressure Indicator (PI-02-117)	Secondary Treatment - Upper	Indicates air pressure	
35	Pressure Switch (PSH-02-118)	Secondary Treatment - Upper		Signal to PLC
36	Temperature Indicator (TI-02-119)	Secondary Treatment - Upper	Indicates air temperature	
37	Temperature Switch (TI-02-120)	Secondary Treatment - Upper		
38	Pressure Indicator (PI-02-142)	Secondary Treatment - Upper	Indicates air pressure	
39	Pressure Switch (PSL-02-143)	Secondary Treatment - Upper		Signal to PLC
40	Pressure Indicator (PI-02-127)	Secondary Treatment - Upper		
41	Pressure Switch (PSH-02-128)	Secondary Treatment - Upper		Signal to PLC
42	Temperature Indicator (TI-02-129)	Secondary Treatment - Upper	Indicates air temperature	
43	Temperature Switch (TI-02-130)	Secondary Treatment - Upper		
44	Pressure Indicator (PI-02-145)	Secondary Treatment - Upper		
45	Pressure Switch (PSL-02-146)	Secondary Treatment - Upper		Signal to PLC
46	Pressure Indicator (PI-02-137)	Secondary Treatment - Upper	Indicates air pressure	
47	Pressure Switch (PSH-02-138)	Secondary Treatment - Upper		Signal to PLC
48	Temperature Indicator (TI-02-139)	Secondary Treatment - Upper	Indicates air temperature	
49	Temperature Switch (TI-02-140)	Secondary Treatment - Upper		
50	Pressure transmitter (PIT-02-195)	Secondary Treatment - Upper	Indicates air pressure from blowers	Signal to PLC
51	Motorized Butterfly Valve (BFV-02-150)	Secondary Treatment - Upper	Isolates air supply to MBBR2	PLC Controlled
52	Flow meter (FQIT-02-152, FE-02-152)	Secondary Treatment - Upper	Measures air supply to MBBR2	Signal to PLC

No.	Component	Location	Function Performed	Remarks
53	Motorized Butterfly Valve (BFV-02-155)	Secondary Treatment - Upper	Isolates air supply to MBBR1	PLC Controlled
54	Flow meter (FQIT-02-156, FE-02-156)	Secondary Treatment - Upper	Measures air supply to MBBR1	Signal to PLC
55	Motorized Butterfly Valve (BFV-02-170)	Secondary Treatment - Upper	Isolates air supply to TWAS Tank	PLC Controlled
56	Flow meter (FQIT-02-172, FE-02-172)	Secondary Treatment - Upper	Measures air supply to TWAS Tank	Signal to PLC
57	Motorized Knife Gate Valve (KV-02-211, FV-02-211)	Secondary Treatment - Lower	Controls flow to MBBR T-02-210	PLC Controlled
58	Dissolved Oxygen Analyzers (AIT-02-211)	Mounted in the MBBR tank T-02-210	Measures dissolved oxygen concentration in MBBR1 Cell 1-1	Signal to PLC
59	Level Switch (LSH-02-213)	Mounted in the MBBR tank T-02-210	Alarms at high level in Cell 1-1	Signals to PLC
60	Dissolved Oxygen Analyzers (AIT-02-212)	Mounted in the MBBR tank T-02-210	Measures dissolved oxygen concentration in MBBR1 Cell 1-2	Signal to PLC
61	Level Switch (LSH-02-214)	Mounted in the MBBR tank T-02-210	Alarms at high level in Cell 1-2	Signals to PLC
62	Motorized Knife Gate Valve (KV-02-221, FV-221)	Secondary Treatment - Lower	Controls flow to MBBR T-02-220	PLC Controlled
63	Dissolved Oxygen Analyzers (AIT-02-221)	Mounted in the MBBR tank T-02-220	Measures dissolved oxygen concentration in MBBR2 Cell 2-1	Signal to PLC
64	Level Switch (LSH-02-223)	Mounted in the MBBR tank T-02-220	Alarms at high level in Cell 2-1	Signals to PLC
65	Dissolved Oxygen Analyzers (AIT-02-222)	Mounted in the MBBR tank T-02-220	Measures dissolved oxygen concentration in MBBR2 Cell 2-2	Signal to PLC
66	Level Switch (LSH-02-224)	Mounted in the MBBR tank T-02-210	Alarms at high level in Cell 2-2	Signals to PLC
67	Motorized Knife Gate Valve (KV-02-230, FV-230)	Secondary Treatment - Lower	Isolates mixed liquor to DAFs	
68	Motorized Valve (BFV-02-312, FV-312)	Secondary Treatment - Lower	Isolates DAF Tank 1 T02-310	PLC Controlled

No.	Component	Location	Function Performed	Remarks
69	Level Switch (LSH-02-330)	Mounted inside the DAF Tank	High Level in Zone 1 of DAF 1	Signals to Vendor PLC
70	Motorized Butterfly Valve (BFV-02-625)	Mounted inside the DAF Tank	Controls white water inlet to DAF 1	Vendor PLC Controlled
71	Level Transmitter (LIT-02-331)	Mounted inside the DAF Tank	Level in Zone 3 of DAF 1	Signals to Vendor PLC
72	Level Switch (LSH-02-332)	Mounted inside the DAF Tank	High Level in Zone 4 of DAF 1	Signals to Vendor PLC
73	Level Switch (LSL-02-333)	Mounted inside the DAF Tank	Low Level in Zone 4 of DAF 1	Signals to Vendor PLC
74	TSS Analyzer (AIT-02-334)	Mounted inside the DAF Tank	Indicated suspended solids in Zone 5 of DAF 1	Signals to Vendor PLC
75	Motorized Butterfly Valve (BFV-02-309)	Secondary Treatment - Lower	Isolates clarified water to white water pumps	
76	Motorized Butterfly Valve (BFV-02-310)	Secondary Treatment - Lower	Isolates clarified water to white water pumps	
77	Flow Transmitter (FQIT-02-317)	Secondary Treatment - Lower	Indicates flow to DAF 1 White water pumps	Signals to Vendor PLC
78	Flow indicator (FI-02-412)	Secondary Treatment - Lower	Air flow indication to P-02-410	
79	Pressure Indicator (PI-02-404)	Secondary Treatment - Lower	Indicates pressure on inlet to P-02-410	
80	Pressure Indicator (PI-02-409)	Secondary Treatment - Lower	Indicates pressure on outlet to P-02-410	
81	Flow indicator (FI-02-427)	Secondary Treatment - Lower	Air flow indication to P-02-420	
82	Pressure Indicator (PI-02-419)	Secondary Treatment - Lower	Indicates pressure on inlet to P-02-420	
83	Pressure Indicator (PI-02-424)	Secondary Treatment - Lower	Indicates pressure on outlet to P-02-420	
84	Flow Indicator (FI-02-442)	Secondary Treatment - Lower	Air flow indication to P-02-430	
85	Pressure Indicator (PI-02-434)	Secondary Treatment - Lower	Indicates pressure on inlet to P-02-430	

No.	Component	Location	Function Performed	Remarks
86	Pressure Indicator (PI-02-439)	Secondary Treatment - Lower	Indicates pressure on outlet to P-02-430	
87	Motorized Butterfly Valve (BFV-02-511)	Secondary Treatment - Lower	Isolates White water Strainer STR-05-510	Vendor PLC Controlled
88	Motorized Butterfly Valve (BFV-02-512)	Secondary Treatment - Lower	Isolates White water Strainer Drain	Vendor PLC Controlled
89	Pressure Indicator (PI-02-510)	Secondary Treatment - Lower	Indicates White water Strainer #1 Drain	
90	Motorized Butterfly Valve (BFV-02-521)	Secondary Treatment - Lower	Isolates White water Strainer STR-05-520	Vendor PLC Controlled
91	Motorized Butterfly Valve (BFV-02-522)	Secondary Treatment - Lower	Isolates White water Strainer Drain	Vendor PLC Controlled
92	Pressure Indicator (PI-02-520)	Secondary Treatment - Lower	Indicates White water Strainer #2 Drain	
93	Pressure Transmitter (PT-02-527)	Secondary Treatment - Lower	Pressure indication of DAF 1 Subnatant	Signals to Vendor PLC
94	Motorized Valve (BFV-02-332, FV-02-332)	Secondary Treatment - Lower	Isolates DAF Tank 2 T-02-320	PLC Controlled
95	Level Switch (LSH-02-340)	Mounted inside the DAF Tank	High Level in Zone 1 of DAF 2	Signals to Vendor PLC
96	Motorized Butterfly Valve (BFV-02-645)	Mounted inside the DAF Tank	Controls white water inlet to DAF 2	Vendor PLC Controlled
97	Level Transmitter (LIT-02-341)	Mounted inside the DAF Tank	Level in Zone 3 of DAF 2	Signals to Vendor PLC
98	Level Switch (LSH-02-342)	Mounted inside the DAF Tank	High Level in Zone 4 of DAF 2	Signals to Vendor PLC
99	Level Switch (LSL-02-343)	Mounted inside the DAF Tank	Low Level in Zone 4 of DAF 2	Signals to Vendor PLC
100	TSS Analyzer (AIT-02-344)	Mounted inside the DAF Tank	Indicated suspended solids in Zone 5 of DAF 2	Signals to Vendor PLC
101	Motorized Butterfly Valve (BFV-02-329)	Secondary Treatment - Lower	Isolates clarified water to white water pumps	
102	Motorized Butterfly Valve (BFV-02-330)	Secondary Treatment - Lower	Isolates clarified water to white water pumps	

No.	Component	Location	Function Performed	Remarks
103	Flow meter (FE-02-328)	Secondary Treatment - Lower	Final Effluent flowmeter	Signals to PLC
104	Flow meter (FE-02-327)	Secondary Treatment - Lower	Indicates flow to DAF 1 White water pumps	Signals to Vendor PLC
105	Flow indicator (FI-02-462)	Secondary Treatment - Lower	Air flow indication to P-02-440	
106	Pressure Indicator (PI-02-454)	Secondary Treatment - Lower	Indicates pressure on inlet to P-02-440	
107	Pressure Indicator (PI-02-459)	Secondary Treatment - Lower	Indicates pressure on outlet to P-02-440	
108	Flow indicator (FI-02-477)	Secondary Treatment - Lower	Air flow indication to P-02-450	
109	Pressure Indicator (PI-02-469)	Secondary Treatment - Lower	Indicates pressure on inlet to P-02-450	
110	Pressure Indicator (PI-02-474)	Secondary Treatment - Lower	Indicates pressure on outlet to P-02-450	
111	Flow Indicator (FI-02-492)	Secondary Treatment - Lower	Air flow indication to P-02-460	
112	Pressure Indicator (PI-02-484)	Secondary Treatment - Lower	Indicates pressure on inlet to P-02-460	
113	Pressure Indicator (PI-02-489)	Secondary Treatment - Lower	Indicates pressure on outlet to P-02-460	
114	Motorized Butterfly Valve (BFV-02-531, FV-02-531)	Secondary Treatment - Lower	Isolates White water Strainer STR-05-530	Vendor PLC Controlled
115	Motorized Butterfly Valve (BFV-02-532)	Secondary Treatment - Lower	Isolates White water Strainer Drain	Vendor PLC Controlled
116	Pressure Indicator (PI-02-530)	Secondary Treatment - Lower	Indicates White water Strainer #1 Drain	
117	Motorized Butterfly Valve (BFV-02-541, FV-02-541)	Secondary Treatment - Lower	Isolates White water Strainer STR-05-540	Vendor PLC Controlled
118	Motorized Butterfly Valve (BFV-02-542)	Secondary Treatment - Lower	Isolates White water Strainer Drain	Vendor PLC Controlled
119	Pressure Indicator (PI-02-540)	Secondary Treatment - Lower	Indicates White water Strainer #2 Drain	

No.	Component	Location	Function Performed	Remarks
120	Pressure Transmitter (PT-02-547)	Secondary Treatment - Lower	Pressure indication of DAF 2 Subnatant	Signals to Vendor PLC
121	Pressure Switch (PSL-04-711)	Chemical Dosing Upper	Low potable water pressure	Signals to Vendor PLC
122	Pressure Indicator (PSL-04-712)	Chemical Dosing Upper	Potable water pressure indication	Signals to Vendor PLC
123	Solenoid Valve (SV-04-713)	Chemical Dosing Upper	Control flow of potable water	Vendor PLC Controlled
124	Solenoid Valve (SV-04-714)	Chemical Dosing Upper	Control flow of potable water	Vendor PLC Controlled
125	Level Switch (LSL-04-710)	Chemical Dosing Upper	Vacuum conveyor VAC-04-710 Low Level	Signals to Vendor PLC
126	Level Transmitter (LIT-04-742)	Chemical Dosing Upper	T-04-740 Polymer Mixing Tank Level	Signals to Vendor PLC
127	Polymer Analyzer (AIT-04-741)	Chemical Dosing Upper	Polymer Indication of T-04-740	Signals to Vendor PLC
128	Temperature Indication (TIT-04-741)	Chemical Dosing Upper	Temperature Indication of T-04-740	Signals to Vendor PLC
129	Polymer Analyzer (AE-04-745)	Chemical Dosing Upper	Polymer Indication of T-04-750	Signals to Vendor PLC
130	Level Transmitter (LIT-04-746)	Chemical Dosing Upper	T-04-750 Polymer Mixing Tank Level	Signals to Vendor PLC
131	Motorized Butterfly Valve (BV-04-744)	Chemical Dosing Upper	DAF Polymer to Mixing Tank Isolation	Vendor PLC Controlled
132	Temperature Element (TE-04-769)	Chemical Dosing Upper	P-04-770 Motor Temperature Alarm	Signals to PLC
133	Pressure Switch (PSH-04-787)	Chemical Dosing Upper	P-04-770 Outlet Pressure Alarm	Signals to PLC
134	Temperature Element (TE-04-770)	Chemical Dosing Upper	P-04-780 Motor Temperature Alarm	Signals to PLC
135	Pressure Switch (PSH-04-793)	Chemical Dosing Upper	P-04-780 Outlet Pressure Alarm	Signals to PLC
136	Temperature Element (TE-04-771)	Chemical Dosing Upper	P-04-790 Motor Temperature Alarm	Signals to PLC
137	Pressure Switch (PSH-04-790)	Chemical Dosing Upper	P-04-790 Outlet Pressure Alarm	Signals to PLC
138	Solenoid Valve (SV-04-783)	Chemical Dosing Upper	Potable Water control for DAF 1 Polymer	Signals to Vendor PLC

No.	Component	Location	Function Performed	Remarks
139	Solenoid Valve (SV-04-784)	Chemical Dosing Upper	Potable Water control for DAF 2 Polymer	Signals to Vendor PLC
140	Flow Indicator (FI-04-785)	Chemical Dosing Upper	Potable Water flow indication for DAF 1 Polymer	Signals to Vendor PLC
141	Flow Indicator (FI-04-786)	Chemical Dosing Upper	Potable Water flow indication for DAF 2 Polymer	Signals to Vendor PLC
142	Flow Transmitter (FIT-04-798)	Chemical Dosing Upper	Flow Indication for Polymer Solution to DAF 1	Signals to PLC
143	Flow Transmitter (FIT-04-799)	Chemical Dosing Upper	Flow Indication for Polymer Solution to DAF 2	Signals to PLC
144	Pressure Indicator (PI-02-615)	Secondary Treatment Lower	Inlet Pressure of TWAS Pump P-02-610	
145	Pressure Indicator (PI-02-618)	Secondary Treatment Lower	Discharge Pressure Indication of TWAS Pump P-02-610	
146	Pressure Switch (PSH-619)	Secondary Treatment Lower	Discharge Pressure Indication of TWAS Pump P-02-610	Signals to PLC
147	Pressure Indicator (PI-02-635)	Secondary Treatment Lower	Indicates inlet pressure for pump P-02-620	
148	Pressure Indicator (PI-02-638)	Secondary Treatment Lower	Discharge Pressure Indication of TWAS Pump P-02-610	
149	Pressure Switch (PSH-02-639)	Secondary Treatment Lower	Discharge Pressure Indication of TWAS Pump P-02-610	Signals to PLC
150	Level Transmitter (LIT-03-111)	Solids Handling Lower	Indicates level for TWAS Tank 1 T-03-630	Signal to PLC
151	Level Switch (LSHH-03-112)	Solids Handling Lower	Indicates level for TWAS Tank 1 T-03-630	Signal to PLC
152	Level Switch (LSHH-03-113)	Solids Handling Lower	Indicates level for TWAS Tank 1 T-03-630	Signal to PLC
153	Level Transmitter (LIT-03-121)	Solids Handling Lower	Indicates level for TWAS Tank 1 T-03-630	Signal to PLC
154	Level Switch (LSHH-03-122)	Solids Handling Lower	Indicates level for TWAS Tank 1 T-03-630	Signal to PLC

No.	Component	Location	Function Performed	Remarks
155	Level Switch (LSHH-03-123)	Solids Handling Lower	Indicates level for TWAS Tank 1 T-03-630	Signal to PLC
156	Pressure Indicator (PI-03-664)	Solids Handling Lower	BFP Feed P-03-630 Inlet Pressure Indication	
157	Pressure Indicator (PI-03-668)	Solids Handling Lower	Discharge Pressure Indication BFP Feed Pump P-03-630	
158	Pressure Switch (PSH-03-669)	Solids Handling Lower	Discharge Pressure High BFP Feed Pump P-03-630	Signal to PLC
159	Pressure Transmitter (PDIT-03-640)	Solids Handling Lower	Differential Pressure between atmosphere and TWAS Tank	Signal to PLC
160	Pressure Indicator (PI-03-684)	Solids Handling Lower	BFP P-03-640 Inlet Pressure Indication	
161	Pressure Indicator (PI-03-688)	Solids Handling Lower	Discharge Pressure Indication BFP pump P-03-640	
162	Pressure Switch (PSH-689)	Solids Handling Lower	Discharge Pressure High BFP pump P-03-640	Signal to PLC
163	Flow Meter (FE-695, FM-03-695)	Solids Handling Lower	Flow Indication to Belt Filter Press BFP-03-650	Signal to PLC
164	Pressure Indicating Transmitter (PIT-03-606)	Solids Handling Lower	Measures the TWAS flow to belt filter press	Signals to Vendor PLC
165	Pressure Switch (PSL-04-911)	Chemical Dosing Upper	Indicates booster pump discharge pressure	Signals to Vendor PLC
166	Pressure Indicator (PI-04-912)	Chemical Dosing Upper	Indicates Potable Water Pressure for BFP Polymer System	
167	Solenoid Valve (SV-04-913)	Chemical Dosing Upper	Potable Water control to BFP Polymer Dosing System	Vendor PLC Controlled

No.	Component	Location	Function Performed	Remarks
168	Solenoid Valve (SV-04-914)	Chemical Dosing Upper	Potable Water control to BFP Polymer Dosing System	Vendor PLC Controlled
169	Level Switch (LSL-04-910)	Chemical Dosing Upper	Low Level Polymer Dosing Vacuum Conveyor	Signals to Vendor PLC
170	Temperature Transmitter (TIT-04-941)	Chemical Dosing Upper	BFP Polymer Mixing Tank Temperature Indication	Signals to Vendor PLC
171	Polymer Analyzer (AIT-04-941)	Chemical Dosing Upper	BFP Polymer Mixing Tank Polymer Indication	Signals to Vendor PLC
172	Level Transmitter (LIT-04-942)	Chemical Dosing Upper	BFP Polymer Mixing Tank Level Indication	Signals to Vendor PLC
173	Motorized Butterfly Valve (BV-04-944)	Chemical Dosing Upper	BFP Polymer to Mixing Tank Isolation	Vendor PLC Controlled
174	Polymer Analyzer (AE-04-945)	Chemical Dosing Upper	BFP Polymer Aging Tank Polymer Indication	Signals to Vendor PLC
175	Level Transmitter (LIT-04-946)	Chemical Dosing Upper	BFP Polymer Aging Tank Level Indication	Signals to Vendor PLC
176	Temperature Element (TE-04-966)	Chemical Dosing Upper	P-04-970 Temperature Alarm	Signals to Vendor PLC
177	Pressure Switch (PSH-04-987)	Chemical Dosing Upper	P-04-970 Discharge Pressure Alarm	Signals to Vendor PLC
178	Temperature Element (TE-04-967)	Chemical Dosing Upper	P-04-980 Temperature Alarm	Signals to Vendor PLC
179	Pressure Switch (PSH-04-990)	Chemical Dosing Upper	P-04-980 Discharge Pressure Alarm	Signals to Vendor PLC
180	Flow Meter (FIT-04-999, FM-04-999)	Chemical Dosing Upper	Measures polymer flow to belt filter press	Signal to PLC
181	Solenoid Valve (SV-04-982)	Chemical Dosing Upper	Isolates BFP polymer dosing pump	Signal to PLC
182	Flow Indicator (FI-04-963)	Chemical Dosing Upper	Indicates potable water to belt filter press	

No.	Component	Location	Function Performed	Remarks
183	Gas Analyzer (AIT-01-901)	Lower Headworks	H2S and LEL Indication	Signal to PLC
184	Gas Analyzer (AIT-01-902)	Lower Headworks	H2S and LEL Gas Detection	Signal to PLC
185	Horn (UA-01-940)	Lower Headworks	H2S and LEL Gas Detection Horn	Controlled by PLC
186	Beacon (UL-01-920A)	Lower Headworks	H2S Beacon	Signal to PLC
187	Beacon (UL-01-920B)	Lower Headworks	H2S Beacon	Signal to PLC
188	Beacon (UL-01-920C)	Lower Headworks	H2S Beacon	Signal to PLC
189	Beacon (UL-01-920D)	Lower Headworks	H2S Beacon	Signal to PLC
190	Beacon (UL-01-920E)	Lower Headworks	H2S Beacon	Signal to PLC
191	Beacon (UL-01-930A)	Lower Headworks	H2S Beacon	Signal to PLC
192	Beacon (UL-01-930B)	Lower Headworks	LEL Beacon	Signal to PLC
193	Beacon (UL-01-930C)	Lower Headworks	LEL Beacon	Signal to PLC
194	Beacon (UL-01-930D)	Lower Headworks	LEL Beacon	Signal to PLC
195	Beacon (UL-01-930E)	Lower Headworks	LEL Beacon	Signal to PLC
196	Temperature Transmitter (TT-01-950)	Lower Headworks	Temperature Indication	Signal to PLC
197	Gas Analyzer (AIT-01-903)	Upper Headworks	H2S and LEL Gas Detection	Signal to PLC
198	Gas Analyzer (AIT-01-904)	Upper Headworks	H2S and LEL Gas Detection	Signal to PLC
199	Horn (UA-01-941)	Upper Headworks	H2S and LEL Gas Detection Horn	Signal to PLC
200	Beacon (UL-01-921A)	Upper Headworks	H2S Beacon	Signal to PLC
201	Beacon (UL-01-921B)	Upper Headworks	H2S Beacon	Signal to PLC
202	Beacon (UL-01-921C)	Upper Headworks	H2S Beacon	Signal to PLC
203	Beacon (UL-01-931A)	Upper Headworks	LEL Beacon	Signal to PLC
204	Beacon (UL-01-931B)	Upper Headworks	LEL Beacon	Signal to PLC
205	Beacon (UL-01-931C)	Upper Headworks	LEL Beacon	Signal to PLC
206	Temperature Transmitter (TT-01-951)	Upper Headworks	Temperature Indication	Signal to PLC

No.	Component	Location	Function Performed	Remarks
207	Gas Analyzer (AIT-02-907)	MBBR	H2S Gas Detection	Signal to PLC
208	Gas Analyzer (AIT-02-909)	DAF 1 Upper	H2S Gas Detection	Signal to PLC
209	Gas Analyzer (AIT-02-908)	DAF 2 Upper	H2S Gas Detection	Signal to PLC
210	Gas Analyzer (AIT-02-905)	DAF 2 Lower	H2S Gas Detection	Signal to PLC
211	Temperature Transmitter (TT-0-954)	DAF	Temperature Indication	Signal to PLC
212	Beacon (UL-02-922A)	Lower Secondary Treatment	H2S Gas Beacon	Signal to PLC
213	Beacon (UL-02-922B)	Lower Secondary Treatment	H2S Gas Beacon	Signal to PLC
214	Beacon (UL-03-922C)	Lower Secondary Treatment	H2S Gas Beacon	Signal to PLC
215	Horn (UA-02-942)	Lower Secondary Treatment	H2S Gas Horn	Signal to PLC
216	Beacon (UL-02-923A)	Upper Secondary Treatment	H2S Gas Beacon	Signal to PLC
217	Beacon (UL-02-923B)	Upper Secondary Treatment	H2S Gas Beacon	Signal to PLC
218	Beacon (UL-02-923C)	Upper Secondary Treatment	H2S Gas Beacon	Signal to PLC
219	Beacon (UL-02-923D)	Upper Secondary Treatment	H2S Gas Beacon	Signal to PLC
220	Horn (UA-02-943)	Upper Secondary Treatment	H2S Gas Horn 1	Signal to PLC
221	Horn (UA-02-944)	Upper Secondary Treatment	H2S Gas Horn 2	Signal to PLC
222	Flow Transmitter (FQIT-04-300)		Incoming Potable Water Flow Indication	Signal to PLC
223	Temperature Transmitter (TT-02-952)	Electrical Room 202	Temperature Indication	Signal to PLC
224	Temperature Transmitter (TT-02-953)	Electrical Room 209	Temperature Indication	Signal to PLC

No.	Component	Location	Function Performed	Remarks
225	Gas Analyzer (AIT-02-801)	Electrical Room 209	CO Gas Detection	Signal to PLC
226	Gas Analyzer (AIT-03-910)	Press Room	H2S Gas Detection	Signal to PLC
227	Gas Analyzer (AIT-03-906)	BFP	H2S Gas Detection	Signal to PLC
228	Temperature Transmitter (TT-03-955)	BFP	Temperature Indication	Signal to PLC
	Smoke Detection (AS-01-960)		Smoke Detection	Signal to PLC

4.4 MOTOR CONTROL CENTRE

(Refer to Drawing E501 in Appendix A)

The following table identifies the components related to the motor control center.

Motor Control Centre - 1

No.	Component	Location	Function Performed	Remarks
1A	Incoming Lugs	MCC Cabinet	Connection to field devices.	
1U	SPARE	MCC Cabinet		Space for Future Expansion
2A	SPD	MCC Cabinet		Space for Future Expansion
2C	DAF-1 P-02-410	MCC Cabinet	Refer to Process O&M Manual.	
2G	DAF-1 P-02-420	MCC Cabinet	Refer to Process O&M Manual.	
2K	DAF-1 P-02-430	MCC Cabinet	Refer to Process O&M Manual.	Expansion
2O	SPARE	MCC Cabinet		Space for Future Expansion
2S	SPARE	MCC Cabinet		Space for Future Expansion
2W	SPARE	MCC Cabinet		Space for Future Expansion
3A	SPARE	MCC Cabinet		Space for Future Expansion
3E	SPARE	MCC Cabinet		Space for Future Expansion
3G	SPARE	MCC Cabinet		Space for Future Expansion
3K	BFP FEED PUMP P-03-640	MCC Cabinet	Refer to Process O&M Manual.	
3S	OUTPUT REACTOR FOR P-03-640	MCC Cabinet	Refer to Process O&M Manual.	
3V	SPARE	MCC Cabinet		Space for Future Expansion

No.	Component	Location	Function Performed	Remarks
4A	LINE REACTOR FOR B-102-130	MCC Cabinet	Refer to Process O&M Manual.	
4D	BLOWER 3 B-02-130	MCC Cabinet	Refer to Process O&M Manual.	
4N	OUTPUT REACTOR FOR B-02-130	MCC Cabinet	Refer to Process O&M Manual.	
4Q	SPARE	MCC Cabinet		Space for Future Expansion
4U	SPARE	MCC Cabinet		Space for Future Expansion
5A	LINE REACTOR FOR B-02-120	MCC Cabinet	Refer to Process O&M Manual.	
5D	BLOWER 2 B-02-120	MCC Cabinet	Refer to Process O&M Manual.	
5N	OUTPUT REACTOR FOR B-02-120	MCC Cabinet	Refer to Process O&M Manual.	
5Q	SPARE	MCC Cabinet		Space for Future Expansion
5U	SPARE	MCC Cabinet		Space for Future Expansion
6A	LINE REACTOR FOR B-02-110	MCC Cabinet	Refer to Process O&M Manual.	
6D	BLOWER 1 B-02-110	MCC Cabinet	Refer to Process O&M Manual.	
6N	OUTPUT REACTOR FOR B-02-110	MCC Cabinet	Refer to Process O&M Manual.	
6Q	SPARE	MCC Cabinet		Space for Future Expansion
6U	SPARE	MCC Cabinet		Space for Future Expansion
7A	TWAS PUMP 1 P-02-610	MCC Cabinet	Refer to Process O&M Manual.	
7I	OUTPUT REACTOR FOR P-610	MCC Cabinet	Refer to Process O&M Manual.	
7L	TWAS PUMP 2 P-02-620	MCC Cabinet	Refer to Process O&M Manual.	

No.	Component	Location	Function Performed	Remarks
7T	OUTPUT REACTOR FOR P-02-620	MCC Cabinet	Refer to Process O&M Manual.	
7W	SPACE	MCC Cabinet		Space for Future Expansion
8A	DAF -2 P-02-440	MCC Cabinet	Refer to Process O&M Manual.	
8E	DAF-2 P-02-450	MCC Cabinet	Refer to Process O&M Manual.	
8I	DAF-2 P-02-460	MCC Cabinet	Refer to Process O&M Manual.	
8M	SPACE	MCC Cabinet		Space for Future Expansion
8Q	SPACE	MCC Cabinet		Space for Future Expansion
8U	SPACE	MCC Cabinet		Space for Future Expansion
9A	DAF-1 SLUDGE SCRAPER DDR-02-311	MCC Cabinet	Refer to Process O&M Manual.	
9I	OUTPUT REACTOR FOR DDR-02-311	MCC Cabinet		
9L	DAF-2 SLUDGE SCRAPER DDR-02-321	MCC Cabinet	Refer to Process O&M Manual.	
9T	OUTPUT REACTOR FOR DDR-02-321	MCC Cabinet		
9W	SPACE	MCC Cabinet		Space for Future Expansion
10A	SPACE	MCC Cabinet		Space for Future Expansion
10C	SPACE	MCC Cabinet		Space for Future Expansion
10E	SPACE	MCC Cabinet		Space for Future Expansion
10I	BFP FEED PUMP 1 P-03-630	MCC Cabinet	Refer to Process O&M Manual.	

No.	Component	Location	Function Performed	Remarks
10Q	OTPUT REACTOR FOR P-03-630	MCC Cabinet		
10T	SPARE	MCC Cabinet		Space for Future Expansion
11A	SPARE	MCC Cabinet		Space for Future Expansion
11C	DAF PUMPS P-04-770	MCC Cabinet	Refer to Process O&M Manual.	
11E	DAF PUMPS P-04-780	MCC Cabinet	Refer to Process O&M Manual.	
11G	DAF PUMPS P-04-790	MCC Cabinet	Refer to Process O&M Manual.	
11I	SPARE	MCC Cabinet		Space for Future Expansion
11M	SPARE	MCC Cabinet		Space for Future Expansion
11Q	SPARE	MCC Cabinet		Space for Future Expansion
11U	SPARE	MCC Cabinet		Space for Future Expansion
12A	SPARE	MCC Cabinet		Space for Future Expansion
12E	BFP PUMPS P-04-970	MCC Cabinet	Refer to Process O&M Manual.	
12G	BFP PUMPS P-04-980	MCC Cabinet	Refer to Process O&M Manual.	
12I	SPARE	MCC Cabinet		Space for Future Expansion
12M	SPARE	MCC Cabinet		Space for Future Expansion
12Q	SPARE	MCC Cabinet		Space for Future Expansion
12U	SPARE	MCC Cabinet		Space for Future Expansion

Motor Control Centre - 2

No.	Component	Location	Function Performed	Remarks
1	Incoming Lugs	MCC Cabinet	Connection to field devices.	
2	AHU-3 SUPPLY	MCC Cabinet	Refer to Mechanical O&M Manual.	
3	AHU-3 RETURN	MCC Cabinet	Refer to Mechanical O&M Manual.	
4	SCR-01-210	MCC Cabinet	Refer to Process O&M Manual.	
5	SCR-01-220	MCC Cabinet	Refer to Process O&M Manual.	
6	SPD	MCC Cabinet		
7	SPARE	MCC Cabinet		Space for Future Expansion
8	SPARE	MCC Cabinet		Space for Future Expansion
9	SPARE	MCC Cabinet		Space for Future Expansion
10	SPARE	MCC Cabinet		Space for Future Expansion
11	SPARE	MCC Cabinet		Space for Future Expansion
12	SPARE	MCC Cabinet		Space for Future Expansion
13	SPARE	MCC Cabinet		Space for Future Expansion
14	AHU-2	MCC Cabinet	Refer to Mechanical O&M Manual.	
15	SPARE	MCC Cabinet		Space for Future Expansion
16	PUMP P-01-110	MCC Cabinet	Refer to Process O&M Manual.	
17	PUMP P-01-120	MCC Cabinet	Refer to Process O&M Manual.	
18	PUMP P-01-130	MCC Cabinet	Refer to Process O&M Manual.	

No.	Component	Location	Function Performed	Remarks
19	TERMINAL CONTROL SECTION	MCC Cabinet		

END OF CHAPTER

CHAPTER 5

5. COMPONENT DETAILS

5.1 GENERAL OVERVIEW

The following tables describe the components of the various systems and provide some basic details and settings. For each table, there are drawings that can be referenced to better understand in what part of the Water Treatment Plant the components are located.

5.2 POWER DISTRIBUTION SYSTEM

(Refer to Drawing E603 in Appendix A)

The following table identifies the components power distribution system.

No.	Component	Location	Function Performed	Remarks
1	400A Main Distribution Panel	Electrical Room 202	400A Main Bus Rating 347/600 Volts	
2	400A Transfer Switch	Electrical Room 202		
3	3P 100 Amp circuit breaker to Panel 6B	Electrical Room 202		100A/3P
4	3P 150Amp circuit breaker to CDP-1	Electrical Room 202		150A/3P
5	3P 60Amp circuit breaker to MCC-1	Electrical Room 202		60A/3P
6	3P 200Amp circuit breaker to 4A	Electrical Room 202		200A/3P
7	3P 250Amp circuit breaker to MCC-1	Electrical Room 202		250A/3P
8	SPD	Electrical Room 202		
9	Central Distribution Panel CDP-1	Electrical Room 202	400A Main Bus Rating 120/208 Volts	
10	3P 100A Sub breaker, Panel 2A	Electrical Room 202		100A/3P
11	3P 100A Sub breaker, Panel 2B	Electrical Room 202		100A/3P
12	3P 100A Sub breaker, Panel 2B	Electrical Room 202		100A/3P

No.	Component	Location	Function Performed	Remarks
13	112.5kVATransformer to CDP-1	Electrical Room 202		600Δ/208Y120
14	45kVA Transformer to Panel 4A	Electrical Room 202		600Δ/277Y480
15	Distribution panel 2A	Generator room		60 Circuits 225 Amperes 120/208 Volts
	Distribution panel 2B	Electrical room 209		42 Circuits 225 Amperes 120/208 Volts
	Distribution panel 2C	Generator room		42 Circuits 225 Amperes 120/208 Volts
	Distribution panel 4A	Upper headworks		42 Circuits 225 Amperes 277/480 Volts
	Distribution panel 6B	Electrical room 209		42 Circuits 250 Amperes 600Y/347 Volts
	Motor Control Center #1	Electrical Room 202		
	Motor Control Center #2	Electrical room 209		Existing

5.3 PLC CONTROL SCHEMATIC

(Refer to Drawing PC-101 to PC-222 in Appendix A)

The following table identifies the components related to the PLC Control Schematics.

No.	Component	Details	Settings	Remarks
1	Flow Meter (FQIT-150, FM-01-150)	Endress + Hauser, Promag W400-5W4C2HCKL7/0, 200 mm		Supplier: Endress + Hauser Canada
2	Level Indicating Transmitter (LIT-01-100)	SITRANS LUT-420		Supplier: Vision Solutions de Procedes
3	Level Switch (LSLL-01-111)	Xylem ENM-10 Level regulator		Supplier: Xylem
4	Level Switch (LSL-01-112)	Xylem ENM-10 Level regulator		Supplier: Xylem

No.	Component	Details	Settings	Remarks
5	Level Switch (LSH-01-113)	Xylem ENM-10 Level regulator		Supplier: Xylem
6	Level Switch (LSHH-01-114)	Xylem ENM-10 Level regulator		Supplier: Xylem
7	Motorized Knife Gate Valve (KV-01-211)	Orbinox Model Ex Series 10		Supplier: Controles Laurentide
8	Level Indicating Transmitter (LIT-01-211)	Ultrasonic level sensor CID1, Echomax ST-H, Siemens Hydroranger 200 level control (Vendor Package)		Supplier: Enviro-Care
9	Solenoid Valve (SV-01-120)	ASCO, 25 mm (Vendor package)		Supplier: Enviro-Care
10	Solenoid Valve (SV-01-122)	ASCO, 12 mm (Vendor package)		Supplier: Enviro-Care
11	Motorized Knife Gate Valve (KV-01-221)	Orbinox Model Ex Series 10		Supplier: Orbinox
12	Level Indicating Transmitter (LIT-01-221)	Ultrasonic level sensor CID1, Echomax ST-H, Siemens Hydroranger 200 level control (Vendor Package)		Supplier: Enviro-Care
13	Solenoid Valve (SV-01-124)	ASCO, 25 mm (Vendor package)		Supplier: Enviro-Care
14	Solenoid Valve (SV-01-126)	ASCO, 12 mm (Vendor package)		Supplier: Enviro-Care
15	Motorized Knife Gate Valve (KV-01-112)	Orbinox EX Series, 400 mm		Supplier: Controles Laurentide
16	Motorized Knife Gate Valve (KV-01-112A, FV-112a)	Orbinox EX Series, 200 mm		Supplier: Controles Laurentide
17	Solenoid Valve (SV-01-113)	Salness filter Model SF6000 (Vendor Package)		Supplier: Trojan Technologies
18	Solenoid Valve (SV-01-312)	*Salness filter Model SF6000 (Vendor Package)*		Supplier: Trojan Technologies
19	Motorized Knife Gate Valve (KV-01-121, FV-121)	Orbinox EX Series, 350 mm		Supplier: Controles Laurentide
20	Level Transmitter (LIT-01-125)	-		Supplier: -
21	Pressure Transmitter (PT-01-126)	-		Supplier: -
22	Solenoid Valve (SV-01-123)	Salness filter Model SF6000 (Vendor Package)		Supplier: Trojan Technologies
23	Solenoid Valve (SV-01-313)	Salness filter Model SF6000 (Vendor Package)		Supplier: Trojan Technologies

No.	Component	Details	Settings	Remarks
24	Solenoid Valve (SV-01-322)	Salness filter Model SF6000 (Vendor Package)		Supplier: Trojan Technologies
25	Solenoid Valve (SV-01-323)	Salness filter Model SF6000 (Vendor Package)		Supplier: Trojan Technologies
26	Motorized Knife Gate Valve (KV-01-111, FV-111)	Orbinox Model Ex Series 10		Supplier: Controles Laurentide
27	Level Transmitter (LIT-01-115)	-		Supplier: -
28	Pressure Transmitter (PT-01-116)	-		Supplier: -
29	Motorized Knife Gate Valve (KV-01-001, FV-001)	Orbinox EX Series, 250 mm		Supplier: Controles Laurentide
30	Pressure Switch (PSL-108)	Aerzen GM-15L, 25HP (vendor package)		Supplier: Veolia Water Technologies Canada
31	Pressure Switch (PSL-02-118)	Aerzen GM-15L, 25HP (vendor package)		Supplier: Veolia Water Technologies Canada
32	Pressure Switch (PSL-02-143)	Aerzen GM-15L, 25HP (vendor package)		Supplier: Veolia Water Technologies Canada
33	Pressure Switch (PSL-02-128)	Aerzen GM-15L, 25HP (vendor package)		Supplier: Veolia Water Technologies Canada
34	Pressure Switch (PSL-02-146)	Aerzen GM-15L, 25HP (vendor package)		Supplier: Veolia Water Technologies Canada
35	Pressure Switch (PSH-02-138)	Aerzen GM-15L, 25HP (vendor package)		Supplier: Veolia Water Technologies Canada
36	Pressure transmitter (PIT-02-195)	PMP55-56QX2/0		Supplier: Endress + Hauser Canada
37	Motorized Butterfly Valve (BFV-02-150)	Emerson Keystone K-LOK Series 36, 150 mm		Supplier: Controles Laurentide
38	Flow meter (FM-02-152, FE-02-152)	t-mass 651 651-20AAA0AD5RABABA		Supplier: Endress + Hauser Canada
39	Motorized Butterfly Valve (BFV-02-155)	Emerson Keystone K-LOK Series 36, 150 mm		Supplier: Controles Laurentide
40	Flow meter (FM-02-156, FE-02-156)	t-mass 651 651-20AAA0AD5RABABA		Supplier: Endress + Hauser Canada
41	Motorized Butterfly Valve (BFV-02-170)	Emerson Keystone K-LOK Series 36, 150 mm		Supplier: Controles Laurentide
42	Flow meter (FM-02-172, FE-02-172)	t-mass 651 651-20AAA0AD5RABABA		Supplier: Endress + Hauser Canada

No.	Component	Details	Settings	Remarks
43	Motorized Knife Gate Valve (KV-02-211, FV-211)	Orbinox EX Series, 350 mm		Supplier: Controles Laurentide
44	Dissolved Oxygen Analyzers (AIT-02-211)	Hach 9020000/LXV404.9900552 (Vendor Package)		Supplier: Veolia Water Technologies Canada
45	Level Switch (LSH-02-213)	Xylem ENM-10 Level regulator		Supplier: Xylem
46	Dissolved Oxygen Analyzers (AIT-02-212)	Hach 9020000/LXV404.9900552 (Vendor Package)		Supplier: Veolia Water Technologies Canada
47	Level Switch (LSH-02-214)	Xylem ENM-10 Level regulator		Supplier: Xylem
48	Motorized Knife Gate Valve (KV-02-221, FV-221)	Orbinox EX Series, 350 mm		Supplier: Controles Laurentide
49	Dissolved Oxygen Analyzers (AIT-02-221)	Hach 9020000/LXV404.9900552 (Vendor Package)		Supplier: Veolia Water Technologies Canada
50	Level Switch (LSH-02-223)	Xylem ENM-10 Level regulator		Supplier: Xylem
51	Dissolved Oxygen Analyzers (AIT-02-222)	Hach 9020000/LXV404.9900552 (Vendor Package)		Supplier: Veolia Water Technologies Canada
52	Level Switch (LSH-02-224)	Xylem ENM-10 Level regulator		Supplier: Xylem
53	Level Switch (LSH-02-330)	Xylem ENM-10 Level regulator		Supplier: Xylem
54	Motorized Valve (BFV-02-312, FV-312)	Keystone Series GR DN0350/NPS 14"		Supplier: Emerson
55	Motorized Butterfly Valve (BFV-02-625, FV-625)	Bray Series 31 (Vendor Package), 150 mm		Supplier: Veolia Water Technologies Canada
56	Level Transmitter (LIT-02-331)	Endress &Hauser (Vendor Package)		Supplier: Veolia Water Technologies Canada
57	Level Switch (LSH-02-332)	Xylem ENM-10 (Vendor Package)		Supplier: Veolia Water Technologies Canada
58	Level Switch (LSL-02-333)	Xylem ENM-10 (Vendor Package)		Supplier: Veolia Water Technologies Canada
59	TSS Analyzer (AIT-02-334)	Hach Solitax LXV328.99.10002 (Vendor Package)		Supplier: Veolia Water Technologies Canada

No.	Component	Details	Settings	Remarks
60	Flow meter (FE-02-317)	Endress & Hauser 50W80ULGA1RC2BAAW+1 (Vendor Package) 150 mm		Supplier: Veolia Water Technologies Canada
61	Motorized Butterfly Valve (BFV-02-511)	Bray Series 31 (Vendor Package), 150 mm		Supplier: Veolia Water Technologies Canada
62	Motorized Butterfly Valve (BFV-02-512)	Flow-tek 7108-3R-R-L (Vendor Package), 50 mm		Supplier: Veolia Water Technologies Canada
63	Motorized Butterfly Valve (BFV-02-521)	Bray Series 31 (Vendor Package), 150 mm		Supplier: Veolia Water Technologies Canada
64	Motorized Butterfly Valve (BFV-02-522)	Flow-tek 7108-3R-R-L (Vendor Package), 50 mm		Supplier: Veolia Water Technologies Canada
65	Pressure Transmitter (PT-02-527)	Endress & Hauser PMP51-CA21JD1PGDRKJA1 (Vendor Package)		Supplier: Veolia Water Technologies Canada
66	Motorized Valve (BFV-02-332, FV-332)	Keystone Series GR DN0350/NPS 14"		Supplier: Emerson
67	Motorized Butterfly Valve (BFV-02-645, FV-645)	Bray Series 31 (Vendor Package), 150 mm		Supplier: Veolia Water Technologies Canada
68	Level Transmitter (LIT-02-341)	Endress &Hauser (Vendor Package)		Supplier: Veolia Water Technologies Canada
69	Level Switch (LSH-02-342)	Xylem ENM-10 (Vendor Package)		Supplier: Veolia Water Technologies Canada
70	Level Switch (LSL-02-343)	Xylem ENM-10 (Vendor Package)		Supplier: Veolia Water Technologies Canada
71	TSS Analyzer (AIT-02-344)	Hach Solitax LXV328.99.10002 (Vendor Package)		Supplier: Veolia Water Technologies Canada
72	Flow meter (FE-02-328)	Secondary Treatment - Lower	Final Effluent flowmeter	Supplier:
73	Flow meter (FE-02-327)	Endress & Hauser 50W80ULGA1RC2BAAW+1 (Vendor Package), 150 mm		Supplier: Veolia Water Technologies Canada
74	Motorized Butterfly Valve (BFV-02-531)	Bray Series 31 (Vendor Package), 150 mm		Supplier: Veolia Water Technologies Canada

No.	Component	Details	Settings	Remarks
75	Motorized Butterfly Valve (BFV-02-532)	Flow-tek 7108-3R-R-L (Vendor Package), 50 mm		Supplier: Veolia Water Technologies Canada
76	Motorized Butterfly Valve (BFV-02-542)	Bray Series 31 (Vendor Package), 150 mm		Supplier: Veolia Water Technologies Canada
77	Motorized Butterfly Valve (BFV-02-542)	Flow-tek 7108-3R-R-L (Vendor Package), 50 mm		Supplier: Veolia Water Technologies Canada
78	Pressure Transmitter (PT-02-547)	Endress & Hauser PMP51-CA21JD1PGDRKJA1 (Vendor Package)		Supplier: Veolia Water Technologies Canada
79	Pressure Switch (PSL-04-711)	Allen Bradley 836T-T253J (Vendor Package)		Supplier: Veolia Water Technologies Canada
80	Pressure Switch (PSL-04-712)	Vendor Package		Supplier: Veolia Water Technologies Canada
81	Solenoid Valve (SV-04-713)	Tekno Valve ASCO 8345G001-120VAC (Vendor Package), 6 mm		Supplier: Veolia Water Technologies Canada
82	Solenoid Valve (SV-04-714)	Tekno Valve ASCO 8210G004-120VAC (Vendor Package), 25 mm		Supplier: Veolia Water Technologies Canada
83	Polymer Analyzer (AIT-04-741)	Hach LXV404.99.00552 (Vendor Package)		Supplier: Veolia Water Technologies Canada
84	Level Transmitter (LIT-04-742)	Endress & Hausser PMC21-CA1V1ECVXJJ (Vendor Package)		Supplier: Veolia Water Technologies Canada
85	Level Switch (LSL-04-710)	Vendor Package		Supplier: Veolia Water Technologies Canada
86	Temperature Indication (TIT-04-741)	Vendor Package		Supplier: Veolia Water Technologies Canada
87	Level Transmitter (LIT-04-746)	Endress & Hausser PMC21-CA1V1ECVXJJ (Vendor Package)		Supplier: Veolia Water Technologies Canada
88	Polymer Analyzer (AE-04-745)	Vendor Package		Supplier: Veolia Water Technologies Canada
89	Motorized Butterfly Valve (BFV-04-744)	Vendor Package		Supplier: Veolia Water Technologies Canada

No.	Component	Details	Settings	Remarks
90	Temperature Element (TE-04-769)	Vendor Package		Supplier: Veolia Water Technologies Canada
91	Pressure Switch (PSH-04-787)	Vendor Package		Supplier: Veolia Water Technologies Canada
92	Temperature Element (TE-04-770)	Vendor Package		Supplier: Veolia Water Technologies Canada
93	Pressure Switch (PSH-04-793)	Vendor Package		Supplier: Veolia Water Technologies Canada
94	Temperature Element (TE-04-771)	Vendor Package		Supplier: Veolia Water Technologies Canada
95	Pressure Switch (PSH-04-790)	Vendor Package		Supplier: Veolia Water Technologies Canada
96	Solenoid Valve (SV-04-783)	Tekno Valve ASCO 8210G094 (Vendor Package), 13 mm		Supplier: Veolia Water Technologies Canada
97	Solenoid Valve (SV-04-784)	Tekno Valve ASCO 8210G094 (Vendor Package), 13 mm		Supplier: Veolia Water Technologies Canada
98	Flow Indicator (FI-04-785)	Chemline FCA00401 (Vendor Package), 12 mm		Supplier: Veolia Water Technologies Canada
99	Flow Indicator (FI-04-786)	Chemline FCA00401 (Vendor Package), 12 mm		Supplier: Veolia Water Technologies Canada
100	Flow Transmitter (FIT-04-798)	Promag 50H08, DN08 5/16"		Supplier: Endress + Hauser Canada
101	Flow Transmitter (FIT-04-799)	Promag 50H08, DN08 5/16"		Supplier: Endress + Hauser Canada
102	Pressure Switch (PSH-02-619)	B-Series Switches		Supplier: Ashcroft
103	Pressure Switch (PSH-02-639)	B-Series Switches		Supplier: Ashcroft
104	Level Element (LE-03-111)	Endress + Hauser, Prosonic S FDU91-SN6AA		Supplier: Endress + Hauser Canada
105	Level Switch (LSHH-03-112)	Xylem ENM-10 Level regulator		Supplier: Xylem
106	Level Switch (LSHH-03-113)	Xylem ENM-10 Level regulator		Supplier: Xylem
107	Level Transmitter (LE-03-121)	Endress + Hauser, Prosonic S FDU91-SN6AA		Supplier: Endress + Hauser Canada

No.	Component	Details	Settings	Remarks
108	Level Switch (LSHH-03-122)	Xylem ENM-10 Level regulator		Supplier: Xylem
109	Level Switch (LSHH-03-123)	Xylem ENM-10 Level regulator		Supplier: Xylem
110	Pressure Switch (PSH-03-669)	B-Series Switches		Supplier: Ashcroft
111	Pressure Switch (PSH-03-689)	B-Series Switches		Supplier: Ashcroft
112	Pressure Differential Transmitter (PDIT-03-640)	Deltabar-PMD75		Supplier: Endress + Hauser Canada
113	Flow Meter (FE-695, FM-03-695)	Endress + Hauser Promag W400-5W4C3F-C6ALHA0DUA1K0A+Z1, 350 mm		Supplier: Endress + Hauser Canada
114	Pressure Indicating Transmitter (PIT-03-606)	Phoenix LC-1200LS (Vendor Package)		Supplier: Phoenix Process Equipment Co.
115	Pressure Switch (PSL-04-911)	Vendor Package		Supplier:
116	Solenoid Valve (SV-04-913)	Vendor Package		Supplier:
117	Solenoid Valve (SV-04-914)	Vendor Package		Supplier:
118	Level Switch (LSL-04-910)	Vendor Package		Supplier:
119	Temperature Transmitter (TIT-04-941)	Vendor Package		Supplier:
120	Polymer Analyzer (AIT-04-941)	Vendor Package		Supplier:
121	Level Transmitter (LIT-04-942)	Vendor Package		Supplier:
122	Motorized Butterfly Valve (BV-04-944)	Vendor Package		Supplier:
123	Polymer Analyzer (AE-04-945)	Vendor Package		Supplier:
124	Level Transmitter (LIT-04-946)	Vendor Package		Supplier:
125	Temperature Element (TE-04-966)	Vendor Package		Supplier:
126	Pressure Switch (PSH-04-987)	Vendor Package		Supplier:
127	Temperature Element (TE-04-967)	Vendor Package		Supplier:
128	Pressure Switch (PSH-04-990)	Vendor Package		Supplier:

No.	Component	Details	Settings	Remarks
129	Flow Meter (FIT-04-999, FM-04-999)	Promag 50H15, DN15 /2"		Supplier: Endress + Hauser Canada
130	Solenoid Valve (SV-04-982)	-		Supplier: -
131	Gas Analyzer (AIT-01-901)	Ultima X5000		Supplier: MSA
132	Gas Analyzer (AIT-01-902)	Ultima X5000		Supplier: MSA
133	Horn (UA-01-940)	Bulletin 855 Electronic Horn		Supplier: Rockwell Automation
134	Beacon (UL-01-920A)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
135	Beacon (UL-01-920B)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
136	Beacon (UL-01-920C)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
137	Beacon (UL-01-920D)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
138	Beacon (UL-01-920E)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
139	Beacon (UL-01-930A)	Amber LEL Pendant Mount		Supplier: Applied Strobe Technology
140	Beacon (UL-01-930B)	Amber LEL Pendant Mount		Supplier: Applied Strobe Technology
141	Beacon (UL-01-930C)	Amber LEL Pendant Mount		Supplier: Applied Strobe Technology
142	Beacon (UL-01-930D)	Amber LEL Pendant Mount		Supplier: Applied Strobe Technology
143	Beacon (UL-01-930E)	Amber LEL Pendant Mount		Supplier: Applied Strobe Technology
144	Temperature Transmitter (TT-01-950)	-		Supplier: -
145	Gas Analyzer (AIT-01-903)	Ultima X5000		Supplier: MSA
146	Gas Analyzer (AIT-01-904)	Ultima X5000		Supplier: MSA
147	Horn (UA-01-941)	Bulletin 855 Electronic Horn		Supplier: Rockwell Automation
148	Beacon (UL-01-921A)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
149	Beacon (UL-01-921B)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
150	Beacon (UL-01-921C)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology

No.	Component	Details	Settings	Remarks
151	Beacon (UL-01-931A)	Amber LEL Pendant Mount		Supplier: Applied Strobe Technology
152	Beacon (UL-01-931B)	Amber LEL Pendant Mount		Supplier: Applied Strobe Technology
153	Beacon (UL-01-931C)	Amber LEL Pendant Mount		Supplier: Applied Strobe Technology
154	Temperature Transmitter (TT-01-951)	-		Supplier: -
155	Gas Analyzer (AIT-02-907)	Ultima X5000		Supplier: MSA
156	Gas Analyzer (AIT-02-909)	Ultima X5000		Supplier: MSA
157	Gas Analyzer (AIT-02-908)	Ultima X5000		Supplier: MSA
158	Gas Analyzer (AIT-02-905)	Ultima X5000		Supplier: MSA
159	Temperature Transmitter (TT-0-954)	-		Supplier: -
160	Beacon (UL-02-922A)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
161	Beacon (UL-02-922B)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
162	Beacon (UL-03-922C)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
163	Horn (UA-02-942)	Bulletin 855 Electronic Horn		Supplier: Rockwell Automation
164	Beacon (UL-02-923A)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
165	Beacon (UL-02-923B)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
166	Beacon (UL-02-923C)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
167	Beacon (UL-02-923D)	Blue H2S Pendant Mount		Supplier: Applied Strobe Technology
168	Horn (UA-02-943)	Bulletin 855 Electronic Horn		Supplier: Rockwell Automation
169	Horn (UA-02-944)	Bulletin 855 Electronic Horn		Supplier: Rockwell Automation
170	Flow Transmitter (FQIT-04-300)	-		Supplier: -
171	Temperature Transmitter (TT-02-952)	-		Supplier: -

No.	Component	Details	Settings	Remarks
172	Temperature Transmitter (TT-02-953)	-		Supplier: -
173	Gas Analyzer (AIT-02-801)	Ultima X5000		Supplier: MSA
174	Gas Analyzer (AIT-03-910)	Ultima X5000		Supplier: MSA
175	Gas Analyzer (AIT-03-906)	Ultima X5000		Supplier: MSA
176	Temperature Transmitter (TT-03-955)	-		Supplier: -
	Smoke Detection (AS-01-960)	IO1000G		Supplier: Edwards United Technology

5.4 MOTOR CONTROL CENTRE

(Refer to Drawing E501 in Appendix A)

The following table identifies the components of the motor control centre.

Motor Control Centre - 1

No.	Component	Details	Setting	Remarks
1A	Incoming Lugs	MCC Cabinet		
1U	SPARE	MCC Cabinet		Space for Future Expansion
2A	SPD	MCC Cabinet		Space for Future Expansion
2C	DAF-1 P-02-410	MCC Cabinet	60A	
2G	DAF-1 P-02-420	MCC Cabinet	60A	
2K	DAF-1 P-02-430	MCC Cabinet	60A	Expansion
2O	SPARE	MCC Cabinet		Space for Future Expansion
2S	SPARE	MCC Cabinet		Space for Future Expansion
2W	SPARE	MCC Cabinet		Space for Future Expansion
3A	SPARE	MCC Cabinet		Space for Future Expansion
3E	SPARE	MCC Cabinet		Space for Future Expansion
3G	SPARE	MCC Cabinet		Space for Future Expansion
3K	BFP FEED PUMP P-03-640	MCC Cabinet	30A	
3S	OUTPUT REACTOR FOR P-03-640	MCC Cabinet		
3V	SPARE	MCC Cabinet		Space for Future Expansion
4A	LINE REACTOR FOR B-102-130	MCC Cabinet		
4D	BLOWER 3 B-02-130	MCC Cabinet	60A	

No.	Component	Details	Setting	Remarks
4N	OUTPUT REACTOR FOR B-02-130	MCC Cabinet		
4Q	SPARE	MCC Cabinet		Space for Future Expansion
4U	SPARE	MCC Cabinet		Space for Future Expansion
5A	LINE REACTOR FOR B-02-120	MCC Cabinet		
5D	BLOWER 2 B-02-120	MCC Cabinet	60A	
5N	OUTPUT REACTOR FOR B-02-120	MCC Cabinet		
5Q	SPARE	MCC Cabinet		Space for Future Expansion
5U	SPARE	MCC Cabinet		Space for Future Expansion
6A	LINE REACTOR FOR B-02-110	MCC Cabinet		
6D	BLOWER 1 B-02-110	MCC Cabinet	60A	
6N	OUTPUT REACTOR FOR B-02-110	MCC Cabinet		
6Q	SPARE	MCC Cabinet		Space for Future Expansion
6U	SPARE	MCC Cabinet		Space for Future Expansion
7A	TWAS PUMP 1 P-02-610	MCC Cabinet	30A	
7I	OUTPUT REACTOR FOR P-610	MCC Cabinet		
7L	TWAS PUMP 2 P-02-620	MCC Cabinet	30A	
7T	OUTPUT REACTOR FOR P-02-620	MCC Cabinet		
7W	SPACE	MCC Cabinet		Space for Future Expansion
8A	DAF -2 P-02-440	MCC Cabinet	60A	
8E	DAF-2 P-02-450	MCC Cabinet	60A	

No.	Component	Details	Setting	Remarks
8I	DAF-2 P-02-460	MCC Cabinet	60A	
8M	SPACE	MCC Cabinet		Space for Future Expansion
8Q	SPACE	MCC Cabinet		Space for Future Expansion
8U	SPACE	MCC Cabinet		Space for Future Expansion
9A	DAF-1 SLUDGE SCRAPER DDR-02-311	MCC Cabinet	30A	
9I	OUTPUT REACTOR FOR DDR-02-311	MCC Cabinet		
9L	DAF-2 SLUDGE SCRAPER DDR-02-321	MCC Cabinet	30A	
9T	OUTPUT REACTOR FOR DDR-02-321	MCC Cabinet		
9W	SPACE	MCC Cabinet		Space for Future Expansion
10A	SPACE	MCC Cabinet		Space for Future Expansion
10C	SPACE	MCC Cabinet		Space for Future Expansion
10E	SPACE	MCC Cabinet		Space for Future Expansion
10I	BFP FEED PUMP 1 P-03-630	MCC Cabinet	30A	
10Q	OTPUT REACTOR FOR P-03-630	MCC Cabinet		
10T	SPARE	MCC Cabinet		Space for Future Expansion
11A	SPARE	MCC Cabinet		Space for Future Expansion
11C	DAF PUMPS P-04-770	MCC Cabinet	30A	
11E	DAF PUMPS P-04-780	MCC Cabinet	30A	
11G	DAF PUMPS P-04-790	MCC Cabinet	30A	

No.	Component	Details	Setting	Remarks
11I	SPARE	MCC Cabinet		Space for Future Expansion
11M	SPARE	MCC Cabinet		Space for Future Expansion
11Q	SPARE	MCC Cabinet		Space for Future Expansion
11U	SPARE	MCC Cabinet		Space for Future Expansion
12A	SPARE	MCC Cabinet		Space for Future Expansion
12E	BFP PUMPS P-04-970	MCC Cabinet	30A	
12G	BFP PUMPS P-04-980	MCC Cabinet	30A	
12I	SPARE	MCC Cabinet		Space for Future Expansion
12M	SPARE	MCC Cabinet		Space for Future Expansion
12Q	SPARE	MCC Cabinet		Space for Future Expansion
12U	SPARE	MCC Cabinet		Space for Future Expansion

Motor Control Centre - 2

No.	Component	Details	Setting	Remarks
1	Incoming Lugs			
2	AHU-3 SUPPLY		15A	
3	AHU-3 RETURN		15A	
4	SCR-01-210		15A	
5	SCR-01-220		15A	
6	SPD		30A	
7	SPARE			Space for Future Expansion
8	SPARE			Space for Future Expansion

No.	Component	Details	Setting	Remarks
9	SPARE		15A	Space for Future Expansion
10	SPARE		15A	Space for Future Expansion
11	SPARE		15A	Space for Future Expansion
12	SPARE		15A	Space for Future Expansion
13	SPARE		15A	Space for Future Expansion
14	AHU-2		25A	
15	SPARE		15A	Space for Future Expansion
16	PUMP P-01-110		60A	
17	PUMP P-01-120		60A	
18	PUMP P-01-130		60A	
19	TERMINAL CONTROL SECTION			

END OF CHAPTER 5

CHAPTER 6

6. OPERATING PROCEDURES

6.1 GENERAL

The operations portion of this manual should be read in conjunction with Chapter 6 of the Process and Mechanical Operations and Maintenance Manuals. The operating procedures described in this section will relate to the WWTP Electrical and Controls systems.

6.2 FACILITY POWER AND STANDBY POWER SYSTEM

The WWTP facility is powered by existing local service. A Standby Generator automatically starts and assumes the full plant load on power failure. The power is switched by a Thomson Power System. Automatic louvers control the temperature in the Generator Room.

6.2.1 Controls

6.2.1.1 Generator

The generator has a control panel attached with control switches and monitoring indicators. The main control has a rotary switch to select between OFF RESET, AUTO, MANUAL START and COOLDOWN STOP. There is an E-stop that can be used to instantly stop and disconnect the generator from the electrical system.

There is a toggle switch labelled Panel Lights that can be used to supply light to the controls.

The Control Panel has a monitoring interface that displays monitored information and a set of LED lamps for alarm status. These are discussed in detail in the manufacturer's O&M Manual.

6.2.1.2 Transfer Switch

The transfer switch is located in the Electrical Room 202. It has a selector switch for AUTO and TEST, a green indicator lamp for Normal Power and a Red indicator lamp for Emergency Power. It also has a rotary handle that shows the present operating mode and that can be used for manual operation. The manual handle drives the switch when turned in the counter-clockwise direction and freewheels when turned in the clockwise direction. An indicator is located behind the handle and points to the present switch position (Normal, Off, Emergency, Off).

6.2.1.3 Ventilation Louvres

The ventilation louvers are controlled locally by a dedicated temperature controller. This is described in detail in the Building Mechanical O&M Manual.

6.2.2 Emergency Generator

6.2.2.1 Automatic Operation

With the selector switch in AUTO, the generator will start when line power fails. It operates until line power is restored. When line power is restored, it continues to run under no load for ___ minutes to allow the engine to cool down.

6.2.2.2 Manual Operation

The generator can be started manually by placing the selector switch in the MAN START position. The generator will run regardless of the line power condition. The generator is stopped by placing the selector switch in the COOL DOWN STOP position. The generator will go through a cool down cycle and then stop. If the generator has not been running under load, the switch can be set directly to the OFF RESET or AUTO position.

6.2.2.3 Emergency Stop

If the Emergency Stop button is pushed, the main breaker will be tripped and the generator will stop. Before the breaker can be reset, the selector switch must be set to the OFF RESET position. When the breaker is reset, the selector switch can then be set to the desired position.

6.2.3 Transfer Switch

6.2.3.1 Automatic Operation

With the selector switch in the AUTO position, the transfer switch will automatically switch to backup power on loss of line power. On return of line power, it will first switch to the Off position. If the power is stable, it continues on to the Normal position.

6.2.3.2 Test

When the selector switch is set to the TEST position, the Emergency Generator will start and the Transfer Switch will switch the load to the generator. When the switch is returned to the AUTO position, the switch returns the load to the normal line power. The generator shuts down after its Cool Down period.

6.2.3.3 Alternate Test Procedure

The system can be fully tested by opening the Main Incoming Breaker located to the right of the Transfer Switch. This simulates a power failure and tests all components of the system, including the power sensor. When the breaker is reset, the Transfer Switch returns the load to normal line power, and the generator shuts down after its Cool Down period.

END OF CHAPER 6

CHAPTER 7

7. MAINTENANCE PROCEDURES AND SERVICE INFORMATION

7.1 GENERAL

To ensure uninterrupted use, equipment should be regularly inspected, tested, and proper repairs made and recorded. The objective is to minimize equipment operating problems and prevent failures by making minor or necessary repairs before major difficulties occur. The importance of record keeping cannot be over-emphasized. Good maintenance protects the owner's interest with manufacturer warranties, continuity, or maintenance despite staff turnovers and equipment reliability track record.

Environmental and operating conditions are key elements affecting proper and reliable operation of equipment. Costly repairs can be minimized if the following items are attended to:

KEEP IT CLEAN

KEEP IT TIGHT

7.1.1 Keep It Clean

Day-to day accumulation of normal atmospheric particles, lint, metallic particles form mechanical equipment cause problems with equipment over a long period of time. An accumulation affects equipment reliability and operating life. ALL equipment should be regularly cleaned.

7.1.2 Keep It Tight

All contactors and control devices operate with high speed movement. This motion creates vibration that can loosen hardware and other parts. External vibration from equipment may cause the loosening of hardware and connections in any equipment. All hardware and connections should be tightened regularly. This simple procedure takes only a small amount of time and can save hours of searching for intermittent problems. All rotating equipment such as motors are affected by vibrations. This can cause alignment problems, which can result in bearing failures.

7.1.3 Renewal Parts

Availability of parts can be a major problem these days as distributors are keeping very low inventories in a move to economize. This may make any part a long delivery item. For this reason local distributors should be contacted and parts availability assessed.

Any critical part affecting the reliability of the system should be ordered, recorded and stored by the maintenance department.

7.1.4 Parts and Equipment Ordering Procedure

During the first year of operation, the Contractor should be contacted for any replacement parts required. This will ensure that parts covered by warranty will be replaced under warranty. Failure to contact the Contractor may result in difficulties in obtaining warranty replacement.

Following the first year of operation, it is recommended that the Contractor also be contacted as many of the suppliers have a wholesale only policy. If it is necessary to purchase parts directly from the original supplier, the following information is required.

Make

Model No.

Year of Installation

Installing Contractor

Description of Part Required (i.e. Fan Bearing)

Part No. if Available

When quoting a part number contained in manufacturer's catalogue, always provide the date of the catalogue you are referring to, as these numbers are often subject to change. The equipment supplier will have the latest edition of the manufacturer's catalogue.

If the original supplier is no longer in business, contact the contractor who will be able to suggest an alternate source of supply.

7.1.5 Scheduled Preventive Maintenance Program

Scheduled preventive maintenance is an effective means to improve services from systems and equipment. Where failure of equipment can result in shutdown, scheduled preventive maintenance is an economical alternative.

7.2 MAINTENANCE SCHEDULE

Maintenance to be conducted as per recommendations of components suppliers. **Appendix C** provide a suggested maintenance schedule.

7.3 MAINTENANCE MANUALS

For all maintenance and inspection schedules, please refer to the manuals provided by component suppliers (**Appendix D**) and manufacturers and as shown in maintenance schedule (**Appendix C**), shop drawings (**Appendix E**) and contact service information (**Appendix F**). Maintenance manuals of the following major process components are provided in **Appendix D**.

7.4 SPARE PARTS LIST

Spare part list is provided in **Appendix E**.

END OF CHAPTER 7

CHAPTER 8

8. TESTING AND CERTIFICATION

Testing records, certificates and warranties are provided in **Appendix G**.

CHAPTER 9

9. CONTACT SERVICE INFORMATION

Owner, consulting engineer, contractors and main suppliers contact service information is grouped in **Appendix F**.

APPENDIX

APPENDIX A

AS-BUILT DRAWINGS

STANTEC DRAWINGS SUPPLIED IN A SEPARATE BINDER

WWTP UPGRADE
IQALUIT - WASTE WATER PROJECT
CONTROL PANEL LCP-02-300
PROJET #5000218036

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
TITLE PAGE

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0001-AU-VWT	–	01 OF 06	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "D" 11x17
Mar 09, 2020 15:31:44 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EPL-0001-AU-VWT-001.dwg – sbouya

DESCRIPTION	DRAWING NUMBER
MAIN CONTROL PANEL LCP-02-300	
TITLE PAGE	5000218036-EPL-0001-AU-VWT-001
LEGEND & DRAWING LIST	5000218036-EPL-0001-AU-VWT-002
EXTERNAL LAYOUT	5000218036-EPL-0001-AU-VWT-003
INTERNAL LAYOUT	5000218036-EPL-0001-AU-VWT-004
TERMINAL LAYOUT	5000218036-EPL-0001-AU-VWT-005
BILL OF MATERIAL	5000218036-EPL-0001-AU-VWT-006
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-001
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-002
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-003
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-004
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-005
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-006
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-007
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-008
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-009
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-010
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-011
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-012
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-013
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-014
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-015
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-016
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-017
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-018
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-019
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-020
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-021
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-001
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-002
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-003
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-004
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-005
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-006
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-007
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-008
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-009
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-010
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-011
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-012
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-013
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-014
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-015
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-016
FIELS DIAGRAM	5000218036-EID-0001-AU-VWT-017

LEGEND

- LOW PRESSURE
- HIGH PRESSURE
- LOW LEVEL
- HIGH LEVEL
- LIMIT SWITCH
- LIMIT SWITCH
- LOW FLOW
- HIGH FLOW
- RELAY CONTACT
- RELAY CONTACT
- RELAY CONTACT
- ON DELAY TIMER
- OFF DELAY TIMER
- GROUND
- ISOLATED GROUND
- FUSE (POWER)
- FUSE (CONTROL)
- DISTRIBUTION BLOCK
- MAINTAINED TWO SELECTOR SWITCH
- MAINTAINED 3 POSITIONS SELECTOR SWITCH
- SPRING RETURN FROM LEFT 3 POSITIONS SELECTOR SWITCH
- SPRING RETURN FROM RIGHT 3 POSITIONS SELECTOR SWITCH
- SPRING RETURN FROM BOTH 3 POSITIONS SELECTOR SWITCH
- PUSH BUTTON
- PUSH BUTTON
- PULL BUTTON
- PULL BUTTON
- EMERGENCY STOP BUTTON
- POTENTIOMETER
- CURRENT TRANSFORMER
- THERMOSTAT
- THERMOSTAT
- 1 POLE CIRCUIT BREAKER
- COOLING FAN
- RECEPTACLE 120VAC WITH RJ45
- RECEPTACLE 120VAC DUPLEX
- PILOT LIGHT
- PUSH TO TEST PILOT LIGHT
- RELAY COIL
- RELAY COIL WITH SURGE SUPPRESSOR
- CONTACTOR COIL
- CONTACTOR COIL WITH SURGE SUPPRESSOR
- ALARM
- RESISTOR
- SOLENOID
- PULL CORD
- ZERO SPEED DETECTOR
- POWER BLOCK FOR FIELD WIRING
- TERMINAL
- WIRING JUNCTION
- KNIFE TERMINAL
- 3 POLES THERMAL MAGNETIC CIRCUIT BREAKER
- 3 POLES MAGNETIC CIRCUIT BREAKER
- 3 POLES FUSIBLE DISCONNECT SWITCH
- 3 POLES DISCONNECT SWITCH
- 3 POLES CONTACTOR
- 3 POLES OVERLOAD RELAY



WIRE COLOR CODE	
MINIMAL 16AWG GAUGE, XLPE WIRE TYPE.	
POWER 120VAC	BLACK
CONTROL 120VAC	RED
NEUTRAL	WHITE
24VDC	BLUE
0VDC	BLUE/WHITE
DRY CONTRACT	YELLOW, 14AWG
NON-ISOLATED GROUND	GREEN
ISOLATED GROUND	GREEN/YELLOW
TWISTED PAIR	(+) BLACK & (-) WHITE

WIRE NUMBER

XX XX XX
- LINE NUMBER
- PAGE NUMBER
- PANEL NUMBER

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE

ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE
CONTROL PANEL LCP-02-300
LEGEND & DRAWING LIST

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0001-AU-VWT	–	02 OF 06	5


BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:31:46 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EPL-0001-AU-VWT-002.dwg – sbouya


5000218036 Iqaluit WWTP

ENCLOSURE NEMA 4X–SS304 / 72H'' X 36W'' X 16D''
CSA APPROVAL





NAME–PLATES DETAILS :



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020–02–28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019–07–29	JC	RA	–	–
3	AS BUILT	2019–03–27	HZ	RA	–	–
2	FOR FABRICATION	2019–03–19	HZ	RA	–	–
1	FOR APPROVAL	2019–01–03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP–02–300
INTERNAL LAYOUT


CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036–EPL	0001–AU–VWT	–	03 OF 06	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:31:49 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000–DRAWINGS\LCP–02–300\REV 5\5000218036–EPL–0001–AU–VWT–003.dwg – sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
INTERNAL LAYOUT


CLIENT
WWTP UPGRADE
CITY OF IQALUIT


VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL –	0001-AU-VWT	–	04 OF 06	5


BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17
Mar 09, 2020 15:31:53 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000 DRAWINGS\LCP 02 300\REV 5\5000218036 EPL 0001 AU VWT 004.dwg – sbouyo


BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17



































TERMINAL DESCRIPTION
A) ID(WAD8)
B) WDU6
C) WDU4
D) WDK2.5
E) DLD2.5
F) FUSE WSI 4/2
G) FUSE WSI 4
H) FUSE KDKS 1/EN4
J) WTR 2.5
K) WDU 2.5

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTCTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
TERMINAL LAYOUT

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL	0001-AU-VWT	–	05 OF 06	5

Mar 09, 2020 15:31:56 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036-EPL-0001-AU-VWT-005.dwg - sbouya
Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EPL-0001-AU-VWT-005.dwg - sbouya

ITEM	DESCRIPTION	PART NUMBER	MANUF.	QTY	BY
1	NEMA 4X ENCLOSURE, SS304, DIM 72"H x 36"W x 16"D C/W CP7236, CMFKSS	CSD723616SSR	HOFFMAN	1	ENV
2	DATA POCKET 6"H x 6"W x 0.75"D	–	–	1	ENV
3	LED LIGHT 23 IN, 120V 10W C/W CABLE LS2-PC6 + SIMPLE OUTLET 120VAC 2963860 PHOENIX	LS2-239-4	PREMISE	1	ENV
4	DOOR SWITCH 1NO	FLKDS	HAMMOND	1	ENV
5	COOLING FILTER FAN NEMA12 120VAC C/W OUTLET FILTER RITTAL 3239.200 + 3239.080 (2X)	3239.110	RITTAL	1	ENV
6	COOLING THERMOSTAT 0@60DEG C, 1NO CONTACT	FGT-200	DBK	1	ENV
7	SAFETY RELAY 24VDC	440R-G23216	ALLEN-BRADLEY	1	ENV
8	UNMANAGED ETHERNET SWITCH, 8 PORT	IES-180B	WEIDMULLER	1	ENV
9	POWER SUPPLY 24VDC, 480W, 20AMP	1606XLS480EC	ALLEN-BRADLEY	1	ENV
10	GND LUG, COPPER	CB3536CY	PANDUIT	1	ENV
11	GND BAR, COPPER	4C-190	NSI	1	ENV
12	FUSE HOLDER 1 POLE TYPE CC C/W FUSE, ATMR-20(1X)	USCC1	MERSEN	1	ENV
13	2 POLES RELAY, 120VAC COIL C/W BASE 700-HN222	700-HK32A1	ALLEN-BRADLEY	A/R	ENV
14	BREAKER 1P, 277VCA, CURVE C, XA ACCORDING TO THE TERMINAL LAYOUT PAGE	M9FXXXX	SCHNEIDER	A/R	ENV
15	RELAY 2PDT COIL 24VDC C/W BASE 700-HN222	700-HK32Z24	ALLEN-BRADLEY	A/R	ENV
16	SIMPLE OUTLET, 120VAC	2963860	PHOENIX CONTACT	2	ENV
17	TERMINAL 2 LEVEL WDK 2.5 C/W END PLATE 1059100000	1021500000	WEIDMULLER	LOT	ENV
18	TERMINAL 3 LEVEL DLD 2.5 C/W END PLATE 1784210000	1784180000	WEIDMULLER	LOT	ENV
19	TERMINAL 600VAC/DC, 20A WDU 2.5 C/W END PLATE 1050000000	1020000000	WEIDMULLER	LOT	ENV
20	KNIFE TERMINAL 300VAC/DC, 10A, WTR 2.5 C/W END PLATE 1050000000	1855610000	WEIDMULLER	LOT	ENV
21	TERMINAL 1 LEVEL WDU 4 C/W END PLATE 1050000000	1020100000	WEIDMULLER	LOT	ENV
22	TERMINAL 1 LEVEL WDU 6 C/W SEPARATOR 1050100000	1020200000	WEIDMULLER	LOT	ENV
23	WHITE PILOT LIGHT, 30mm 120VAC	9001SKP38W31	SQUARE D	1	ENV
24	RED PILOT LIGHT, 30mm 24VDC	9001SKP35R31	SQUARE D	1	ENV
25	BLACK PUSH BUTTON, 30mm NEMA4X	9001SKR1U	SQUARE D	1	ENV
26	RED EMERGENCY STOP PUSH BUTTON, 30mm C/W CONTACT	9001SKR16H2	SQUARE D	1	ENV
27	END ANCHOR WEW 35/2	1061200000	WEIDMULLER	A/R	ENV
28	FUSE HOLDER ¼ X 1¼ WSI 4/2	1880430000	WEIDMULLER	A/R	ENV
29	FUSE TERMINAL C/W END PLATE WEIDMULLER 9532470000	9532440000	WEIDMULLER	A/R	ENV
30	FAST ACTING MINI FUSE 5X20MM 250VAC XA C/W SPARE	GMA-X	BUSSMANN	A/R	ENV
31	FUSE, FAST ACTING, 1/4 x 1-1/4, XA	AGC-X	BUSSMANN	A/R	ENV
32	FUSE, FAST ACTING, 1/4 x 1-1/4, XA	GDL-X	BUSSMANN	A/R	ENV
33	RELAY SPDT 10A 120VAC C/W BASE 700-HN221	700-HK36A1	ALLEN-BRADLEY	10	ENV

VEOLIA PARTS LIST

ITEM	DESCRIPTION	PART NUMBER	MANUF.	QTY	BY
100	PanelView Plus 7 Performance Terminal, Touch Screen, 12 WXGA 24VDC	2711P-T12W22D9P	ALLEN-BRADLEY	1	VEO
101	MODEM, 24VDC C/W ANTENNA EW40205, FLB3205-00/5 + SIM CARD	E-WON	FLEXY20500-00	1	VEO
102	PLC POWER SUPPLY 120VAC, 200VA	1769-PA4	ALLEN-BRADLEY	2	VEO
103					VEO
104	INPUT CARD, 16 PTS, 24VDC	1769-IQ16	ALLEN-BRADLEY	7	VEO
105	OUTPUT CARD, 16 PTS	1769-OW16	ALLEN-BRADLEY	3	VEO
106	ANALOG OUTPUT CARD, 8 PTS	1769-OF8C	ALLEN-BRADLEY	2	VEO
107	ANALOG INPUT CARD, 8PTS	1756-IF8	ALLEN-BRADLEY	2	VEO
108	PLC CPU	1769-L33ER	ALLEN-BRADLEY	1	VEO
109	LEFT END CAP	1769-ECL	ALLEN-BRADLEY	1	VEO
110	EXPANSION CABLE RIGHT TO LEFT CABLE	1769-CRR1	ALLEN-BRADLEY	1	VEO
111	UPS, 1500VA, 120VAC, 1PH	9SX1500	EATON	1	VEO
112	INTRINSICALLY SAFE CONTROLS	SERIES 27	WARRICK	2	VEO

Mar 09, 2020 15:31:58 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EPL-0001-AU-VWT-006.dwg - sbouya

BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS.. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.


DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
BILL OF MATERIAL

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL	0001-AU-VWT	–	06 OF 06	5





WIRING

VEOLIA

CUSTOMER

INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE

ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE

CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT

WWTP UPGRADE
CITY OF IQALUIT

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	01 OF 21	5

BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

Mar 09, 2020 15:31:59 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN_000–DRAWINGS\LCP–02–300\REV 5\5000218036–ELD–0001–AU–VWT–001.dwg – sbouya





REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	02 OF 21	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:01 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-002.dwg – sbouya



BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	03 OF 21	5

Mar 09, 2020 15:32:03 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-003.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	04 OF 21	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17
Mar 09, 2020 15:32:04 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-004.dwg – sbouya





REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	05 OF 21	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:06 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-005.dwg - sbouya

BAR = 1" AT PLOT SCALE
REF: 4
STD: "B" 11x17

Mar 09, 2020 15:32:08 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-006.dwg - sbouya

[010580]
24V1
010601
010602
010603
010604
010605
010606
010607
010608
010609
010610
010611
010612
010613
010614
010615
010616
010617
010618
010619
010620
010621
010622
010623
010624
010625
010626
010627
010628
010629
010630
010631
010632
010633
010634
010635
010636
010637
010638
24V1
010639
010640
[010641]

[010580]
0V1
0V1
[010641]

[010640]
010641
010642
24V1
010643
010644
010645
010646
010647
010648
010649
010650
010651
010652
010653
010654
010655
010656
010657
010658
010659
010660
010661
010662
010663
010664
010665
010666
010667
010668
010669
010670
010671
010672
010673
010674
010675
010676
010677
010678
010679
24V1
010680

[010640]
0V1
SPARE
0V1

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE: N/A	

TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	06 OF 21	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

010701
010702
010703
010704
010705
010706
010707
010708
010709
010710
010711
010712
010713
010714
010715
010716
010717
010718
010719
010720
010721
010722
010723
010724
010725
010726
010727
010728
010729
010730
010731
010732
010733
010734
010735
010736
010737
010738
010739
010740



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	-	07 OF 21	5

Mar 09, 2020 15:32:09 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-007.dwg - sbouya



RACK 00 SLOT 01 DIGITAL INPUT 1769-IQ16		
IN 0	I:001.00	ALARM RESET
IN 1	I:001.01	EMERGENCY STOP
IN 2	I:001.02	EMERGENCY STOP RELAY
IN 3	I:001.03	UPS ALARM
IN 4	I:001.04	POWER
IN 5	I:001.05	DAF 1 HIGH LEVEL SIGNAL LSH-02-330
IN 6	I:001.06	DAF 1 SUBNATANT VALVE OPEN SIGNAL OPEN STATUS ZSO-02-625
IN 7	I:001.07	DAF 1 SUBNATANT VALVE CLOSED SIGNAL CLOSE STATUS ZSC-02-625
		DC COM
IN 8	I:001.08	DAF 1 SLUDGE SCRAPPER REM HI-DDR-02-311
IN 9	I:001.09	DAF 1 SLUDGE SCRAPPER RUNNING YI-DDR-02-311
IN 10	I:001.10	DAF 1 SLUDGE SCRAPPER OVERLOAD UA-DDR-02-311
IN 11	I:001.11	DAF 1 HIGH LEVEL SLUDGE SIGNAL LSH-02-332
IN 12	I:001.12	SPARE
IN 13	I:001.13	DAF 1 SPIDFLOW CONTROL VALVE OPEN SIGNAL OPEN STATUS ZSO-02-309
IN 14	I:001.14	DAF 1 SPIDFLOW CONTROL VALVE CLOSED SIGNAL CLOSE STATUS ZSC-02-309
IN 15	I:001.15	DAF 1 SPIDFLOW CONTROL VALVE OPEN SIGNAL OPEN STATUS ZSO-02-310
		DC COM

BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

WIRING

VEOLIA

CUSTOMER

INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE

ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE: N/A	

TITLE

CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT


WWTP UPGRADE
CITY OF IQALUIT

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	08 OF 21	5

Mar 09, 2020 15:32:11 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-008.dwg – sbouya



RACK 00 SLOT 02 DIGITAL INPUT 1769-IQ16		
IN 0	I:002.00	DAF 1 SPIDFLOW CONTROL VALVE CLOSED SIGNAL CLOSE STATUS ZSC-02-310
IN 1	I:002.01	START - STOP SWITCH VFD DDR-02-311 SIGNAL HS-02-311
IN 2	I:002.02	DAF 1 WHITE WATER PUMP 1 REM HI-P-02-410
IN 3	I:002.03	DAF 1 WHITE WATER PUMP 1 RUNNING YI-P-02-410
IN 4	I:002.04	DAF 1 WHITE WATER PUMP 1 OVERLOAD UA-P-02-410
IN 5	I:002.05	ESD SWITCH FROM P-02-410 SIGNAL HS-ESD-02-410
IN 6	I:002.06	START - STOP SWITCH P-02-410 SIGNAL HS-02-410
IN 7	I:002.07	DAF 1 WHITE WATER PUMP 2 REM HI-P-02-420
		DC COM
IN 8	I:002.08	DAF 1 WHITE WATER PUMP 2 RUNNING YI-P-02-420
IN 9	I:002.09	DAF 1 WHITE WATER PUMP 2 OVERLOAD UA-P-02-420
IN 10	I:002.10	ESD SWITCH FROM P-02-420 SIGNAL HS-ESD-02-420
IN 11	I:002.11	START - STOP SWITCH P-02-420 SIGNAL HS-02-420
IN 12	I:002.12	DAF 1 WHITE WATER PUMP 3 REM HI-P-02-430
IN 13	I:002.13	DAF 1 WHITE WATER PUMP 3 RUNNING YI-P-02-430
IN 14	I:002.14	DAF 1 WHITE WATER PUMP 3 OVERLOAD UA-P-02-430
IN 15	I:002.15	ESD SWITCH FROM DDR-02-311 SIGNAL HS-ESD-DDR-02-311
		DC COM

BAR = 1" AT PLOT SCALE

REF: 4

STD: "B" 11x17

WIRING

VEOLIA

CUSTOMER

INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE: N/A	


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	09 OF 21	5

Mar 09, 2020 15:32:13 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-009.dwg - sbouya
5000218036 Iqaluit WWTP



RACK 00 SLOT 03
DIGITAL INPUT
1769-IQ16

IN 0	I:003.00	ESD SWITCH FROM P-02-430 SIGNAL HS-ESD-02-430
IN 1	I:003.01	START - STOP SWITCH P-02-430 SIGNAL HS-02-430
IN 2	I:003.02	DAF 1 WHITE WATER STRAINER 1 INPUT VALVE OPEN STATUS ZSO-02-511
IN 3	I:003.03	DAF 1 WHITE WATER STRAINER 1 INPUT VALVE CLOSE STATUS ZSC-02-511
IN 4	I:003.04	DAF 1 WHITE WATER STRAINER 1 OUT VALVE OPEN STATUS ZSO-02-512
IN 5	I:003.05	DAF 1 WHITE WATER STRAINER 1 OUT VALVE CLLOSE STATUS ZSC-02-512
IN 6	I:003.06	DAF 1 WHITE WATER STRAINER 2 INPUT VALVE OPEN STATUS ZSO-02-521
IN 7	I:003.07	DAF 1 WHITE WATER STRAINER 2 INPUT VALVE CLOSE STATUS ZSC-02-521
		DC COM
IN 8	I:003.08	DAF 1 WHITE WATER STRAINER 2 OUT VALVE OPEN STATUS ZSO-02-522
IN 9	I:003.09	DAF 1 WHITE WATER STRAINER 2 OUT VALVE CLOSE STATUS ZSC-02-522
IN 10	I:003.10	DAF 2 HIGH LEVEL SIGNAL LSH-02-340
IN 11	I:003.11	DAF 2 SUBNATANT VALVE OPEN SIGNAL OPEN STATUS ZSO-02-645
IN 12	I:003.12	DAF 2 SUBNATANT VALVE CLOSED SIGNAL CLOSE STATUS ZSC-02-645
IN 13	I:003.13	DAF 2 SLUDGE SCRAPPER REM HI-DDR-02-321
IN 14	I:003.14	DAF 2 SLUDGE SCRAPPER RUNNING YI-DDR-02-321
IN 15	I:003.15	DAF 2 SLUDGE SCRAPPER OVERLOAD UA-DDR-02-321
		DC COM

011001 011002 011003 011004 011005 011006 011007 011008 011009 011010 011011 011012 011013 011014 011015 011016 011017 011018 011019 011020 011021 011022 011023 011024 011025 011026 011027 011028 011029 011030 011031 011032 011033 011034 011035 011036 011037 011038 011039 011040

011041 011042 011043 011044 011045 011046 011047 011048 011049 011050 011051 011052 011053 011054 011055 011056 011057 011058 011059 011060 011061 011062 011063 011064 011065 011066 011067 011068 011069 011070 011071 011072 011073 011074 011075 011076 011077 011078 011079 011080

BAR = 1" AT PLOT SCALE

REF.: A6798A

STD: "B" 11x17

WIRING

- VEOLIA
- CUSTOMER
- INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	10 OF 21	5

Mar 09, 2020 15:32:14 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-010.dwg – sbouya



BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

WIRING

- VEOLIA
- CUSTOMER
- INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	11 OF 21	5

Mar 09, 2020 15:32:16 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-011.dwg - sbouya



RACK 00 SLOT 05 DIGITAL INPUT 1769-IQ16		
IN 0	I:005.00	ESD SWITCH FROM P-02-450 SIGNAL HS-ESD-02-450
IN 1	I:005.01	START - STOP SWITCH P-02-450 SIGNAL HS-02-450
IN 2	I:005.02	DAF 2 WHITE WATER PUMP 3 REM HI-P-02-460
IN 3	I:005.03	DAF 2 WHITE WATER PUMP 3 RUNNING YI-P-02-460
IN 4	I:005.04	DAF 2 WHITE WATER PUMP 3 OVERLOAD UA-P-02-460
IN 5	I:005.05	ESD SWITCH FROM P-02-460 SIGNAL HS-ESD-02-460
IN 6	I:005.06	START - STOP SWITCH P-02-460 SIGNAL HS-02-460
IN 7	I:005.07	DAF 2 WHITE WATER STRAINER 1 IN VALVE OPEN STATUS ZSO-02-531
		DC COM
IN 8	I:005.08	DAF 2 WHITE WATER STRAINER 1 IN VALVE CLOSE STATUS ZSC-02-531
IN 9	I:005.09	DAF 2 WHITE WATER STRAINER 1 OUT VALVE OPEN STATUS ZSO-02-532
IN 10	I:005.10	DAF 2 WHITE WATER STRAINER 1 OUT VALVE CLOSE STATUS ZSC-02-532
IN 11	I:005.11	DAF 2 WHITE WATER STRAINER 2 IN VALVE OPEN STATUS ZSO-02-541
IN 12	I:005.12	DAF 2 WHITE WATER STRAINER 2 IN VALVE CLOSE STATUS ZSC-02-541
IN 13	I:005.13	DAF 2 WHITE WATER STRAINER 2 OUT VALVE OPEN STATUS ZSO-02-542
IN 14	I:005.14	DAF 2 WHITE WATER STRAINER 2 OUT VALVE CLOSE STATUS ZSC-02-542
IN 15	I:005.15	SPARE
		DC COM

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17
Mar 09, 2020 15:32:19 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-012.dwg - sbouya

WIRING

VEOLIA
CUSTOMER
INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.


DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	-	12 OF 21	5



BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

WIRING

VEOLIA

CUSTOMER

INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	13 OF 21	5

Mar 09, 2020 15:32:21 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-013.dwg - sbouya



BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

WIRING

VEOLIA

CUSTOMER

INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	SG	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE

ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE

CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT


WWTP UPGRADE
CITY OF IQALUIT

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	14 OF 21	5

Mar 09, 2020 15:32:23 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-014.dwg – sbouya



5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–
REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN

WIRING

— — — — VEOLIA
———— CUSTOMER
———— INTERNAL WIRING

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	15 OF 21	5

REF: A6798A
BAR = 1" AT PLOT SCALE
STD: "B" 11x17

Mar 09, 2020 15:32:25 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-015.dwg – sbouya



WIRING

VEOLIA

CUSTOMER

INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	16 OF 21	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17
Mar 09, 2020 15:32:26 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-016.dwg - sbouya

BAR = 1" AT PLOT SCALE
REF: 4
STD: "B" 11x17

Mar 09, 2020 15:32:28 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-017.dwg - sbouya

RACK 00 SLOT 10
DIGITAL OUTPUT
1769-OW16

GENERAL ALARM LIGHT CMD ALIGHT	0:010:00	OUT 0	011704
GENERAL ALARM RELAY CMD ARELAY	0:010:01	OUT 1	011706
PLC E-STOP RESET CMD E_STOP_RESET	0:010:02	OUT 2	011708
GENERAL FAULT DAF 2 TO CPL-901 CMD XA-02-320	0:010:03	OUT 3	011710
RUN COMMAND DAF 2 TO CPL-901 CMD YI-02-320	0:010:04	OUT 4	011712
LOW LEVEL ALARM DAF 2 TO CPL-901 CMD LAL-02-343	0:010:05	OUT 5	011714
HIGH LEVEL ALARM DAF 2 TO CPL-901 CMD LAH-02-342	0:010:06	OUT 6	011716
HIGH LEVEL ALARM DAF 2 TO CPL-901 CMD LAH-02-340	0:010:07	OUT 7	011718
DC POWER			010176
DAF 1 WHITE WATER STRAINER 1 OUT VALVE CMD FV-02-512	0:010:08	OUT 8	011722
DAF 1 WHITE WATER STRAINER 2 OUT VALVE CMD FV-02-522	0:010:09	OUT 9	011724
DAF 2 WHITE WATER STRAINER 1 OUT VALVE CMD FV-02-532	0:010:10	OUT 10	011726
DAF 2 WHITE WATER STRAINER 2 OUT VALVE CMD FV-02-542	0:010:11	OUT 11	011728
SPARE	0:010:12	OUT 12	011730
SPARE	0:010:13	OUT 13	011732
SPARE	0:010:14	OUT 14	011734
SPARE	0:010:15	OUT 15	011736
DC POWER			010319A

120VAC [010177] 120VAC UPS [010319]

120VAC [010176]

011704 FU011704 GMA-1 011704A — IL011704 (R) — N

011706 FU011706 GMA-1 011706A — CR011706 — N — [011706]

CR011706 011706B / 011708B

011708 FU011708 GMA-1 011708A — CR011708 — N — [010532]

011710 FU011710 GMA-1 011710A — XA-02-320 — N

011712 FU011712 GMA-1 011712A — YI-02-320 — N

011714 FU011714 GMA-1 011714A — LAL-02-343 — N

011716 FU011716 GMA-1 011716A — LAH-02-342 — N

011718 FU011718 GMA-1 011718A — LAH-02-340 — N

N1 UPS [010319]

011722 FU011722 GMA-1 011722A — CR011722 — N1 — RELAY DAF 1 WHITE WATER STRAINER 1 OUT VALVE CMD FV-02-512

011724 FU011724 GMA-1 011724A — CR011724 — N1 — RELAY DAF 1 WHITE WATER STRAINER 2 OUT VALVE CMD FV-02-522

011726 FU011726 GMA-1 011726A — CR011726 — N1 — RELAY DAF 2 WHITE WATER STRAINER 1 OUT VALVE CMD FV-02-532

011728 FU011728 GMA-1 011728A — CR011728 — N1 — RELAY DAF 2 WHITE WATER STRAINER 2 OUT VALVE CMD FV-02-542

120VAC UPS [010325] — 010325

FU011722A GDL-2 011722B CR011722 011722C 011723 — 2(OPEN) 1(N) 3(CLOSE) FV-02-512 — N1

FU011724A GDL-2 011724B CR011724 011724C 011725 — 2(OPEN) 1(N) 3(CLOSE) FV-02-522 — N1

FU011726A GDL-2 011726B CR011726 011726C 011727 — 2(OPEN) 1(N) 3(CLOSE) FV-02-532 — N1

FU011728A GDL-2 011728B CR011728 011728C 011729 — 2(OPEN) 1(N) 3(CLOSE) FV-02-542 — N1

N1 UPS [010325] — N1

WIRING
VEOLIA
CUSTOMER
INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.


DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	17 OF 21	5





BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

WIRING

- VEOLIA
- CUSTOMER
- INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE

ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE

CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT


WWTP UPGRADE
CITY OF IQALUIT

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	18 OF 21	5

Mar 09, 2020 15:32:30 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-018.dwg – sbouya



BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

WIRING

- VEOLIA
- CUSTOMER
- INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	19 OF 21	5

Mar 09, 2020 15:32:31 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-019.dwg – sbouya



BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

WIRING

VEOLIA

CUSTOMER

INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTCTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT
WWTP UPGRADE
CITY OF IQALUIT


VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	20 OF 21	5

Mar 09, 2020 15:32:33 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-020.dwg - sbouya

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17





WIRING

— — — — VEOLIA
— - - - — CUSTOMER
——— INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT


VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	21 OF 21	5

Mar 09, 2020 15:32:35 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-ELD-0001-AU-VWT-021.dwg – sbouya

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:36 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-001.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS.. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING


CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0001-AU-VWT	-	01 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:38 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-002.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300 FIELD WIRING


CLIENT
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0001-AU-VWT	–	02 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:40 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-003.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING


CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0001-AU-VWT	–	03 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:42 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-004.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING


CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EID –	0001-AU-VWT	–	04 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:43 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-005.dwg – sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300 FIELD WIRING

CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0001-AU-VWT	–	05 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:45 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-006.dwg - sbouya

LCP-02-300		JB	FIELD	
RACK 00 SLOT 05				
011204			HS-ESD-02-450	ESD SWITCH FROM P-02-450 SIGNAL HS-ESD-02-450
010412				
011206			START STOP X0 HS-02-450	START - STOP SWITCH P-02-450 SIGNAL HS-02-450
010412				
011208			HI-P-02-460	DAF 2 WHITE WATER PUMP 3 REM HI-P-02-460
010412				
011210			YI-P-02-460	DAF 2 WHITE WATER PUMP 3 RUNNING YI-P-02-460
010412				
011212			UA-P-02-460	DAF 2 WHITE WATER PUMP 3 OVERLOAD UA-P-02-460
010412				
011214			HS-ESD-02-460	ESD SWITCH FROM P-02-460 SIGNAL HS-ESD-02-460
010412				
011216			START STOP X0 HS-02-460	START - STOP SWITCH P-02-460 SIGNAL HS-02-460
010412				
011218			ZSO-02-531	DAF 2 WHITE WATER STRAINER 1 IN VALVE OPEN STATUS ZSO-02-531
010412				
011222			ZSC-02-531	DAF 2 WHITE WATER STRAINER 1 IN VALVE CLOSE STATUS ZSC-02-531
010412				
011224			ZSO-02-532	DAF 2 WHITE WATER STRAINER 1 OUT VALVE OPEN STATUS ZSO-02-532
010412				
011226			ZSC-02-532	DAF 2 WHITE WATER STRAINER 1 OUT VALVE CLOSE STATUS ZSC-02-532
010412				
011228			ZSO-02-541	DAF 2 WHITE WATER STRAINER 2 IN VALVE OPEN STATUS ZSO-02-541
010412				
011230			ZSC-02-541	DAF 2 WHITE WATER STRAINER 2 IN VALVE CLOSE STATUS ZSC-02-541
010412				
011232			ZSO-02-542	DAF 2 WHITE WATER STRAINER 2 OUT VALVE OPEN STATUS ZSO-02-542
010412				
011234			ZSC-02-542	DAF 2 WHITE WATER STRAINER 2 OUT VALVE CLOSE STATUS ZSC-02-542
010412				
011236				
010412				

WIRING

- VEOLIA
- CLIENT
- INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	-	-
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	-	-
3	AS BUILT	2019-03-27	HZ	RA	-	-
2	FOR FABRICATION	2019-03-19	HZ	RA	-	-
1	FOR APPROVAL	2019-01-03	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
-	-
CHECKER	DATE
-	-
ENGINEER	DATE
-	-
SCALE:	N/A

TITLE

CONTROL PANEL LCP-02-300
FIELD WIRING


CLIENT

CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EID -	0001-AU-VWT	-	06 OF 17	5

LCP-02-300	JB	FIELD



WIRING

- VEOLIA
- CLIENT
- INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING

CLIENT
CITY OF IQALUIT


VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0001-AU-VWT	–	07 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:46 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-007.dwg – sbouya

LCP-02-300	JB	FIELD



WIRING

- VEOLIA
- CLIENT
- INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING

CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0001-AU-VWT	–	08 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:48 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-008.dwg – sbouya

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:51 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-009.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTCOID BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300 FIELD WIRING


CLIENT
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0001-AU-VWT	–	09 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:53 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-010.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING


CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EID –	0001-AU-VWT	–	10 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

LCP-02-300	JB	FIELD



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING

CLIENT
CITY OF IQALUIT


VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0001-AU-VWT	–	11 OF 17	5

Mar 09, 2020 15:32:53 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-011.dwg – sbouya

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:55 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-012.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTCIED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING


CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EID	0001-AU-VWT	–	12 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:57 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-013.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	-	-
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	-	-
3	AS BUILT	2019-03-27	HZ	RA	-	-
2	FOR FABRICATION	2019-03-19	HZ	RA	-	-
1	FOR APPROVAL	2019-01-03	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
-	-
CHECKER	DATE
-	-
ENGINEER	DATE
-	-
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING


CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EID	0001-AU-VWT	-	13 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:32:58 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-014.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTCIED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING

CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EID –	0001-AU-VWT	–	14 OF 17	5

LCP-02-300	JB	FIELD

RACK 01 SLOT 02

012105+

012105-

SH

012113+

012113-

SH

012121+

012121-

SH

012129+

012129-

SH

012145+

012145-

SH

012153+

012153-

SH

012161+

012161-

SH

012169+

012169-

SH

WIRING

- – – – – VEOLIA
- —·—·— CLIENT
- ——— INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE

CONTROL PANEL LCP-02-300
FIELD WIRING

CLIENT

CITY OF IQALUIT

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EID	0001-AU-VWT	–	15 OF 17	5

BAR = 1" AT PLOT SCALE


REF: A6798A

STD: "B" 11x17

Mar 09, 2020 15:33:00 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-015.dwg - sbouya

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:33:02 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-016.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING


CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0001-AU-VWT	–	16 OF 17	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 15:33:03 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 5\5000218036-EID-0001-AU-VWT-017.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-02-28	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-27	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
FIELD WIRING

CLIENT
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0001-AU-VWT	–	17 OF 17	5

WWTP UPGRADE
CITY OF IQALUIT
CONTROL JUNCTION BOX
JB-001 SPIDFLOW T-02 310
PROJECT: 5000218036

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUIILT || FIELD MODIFICATION	2020-03-05	SB	RA	–	–
4	AS BUIILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTCEID BY ALL APPLICABLE LWS, INCLUDING BUT NOT LMIED TO COPRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE: JB-001 SPIDFLOW T-02 310
CONTROL JUNCTION BOX
TITLE PAGE

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0002-AU-VWT	–	01 OF 05	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17
Mar 09, 2020 16:09:19 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\REV5\5000218036-EPL-0002-AU-VWT-001.dwg – sbouya

DRAWING LIST

DESCRIPTION	DRAWING NUMBER
CONTROL JUNCTION BOX JB-001	
TITLE PAGE	5000218036-EPL-0002-AU-VWT-001
LEGEND & DRAWING LIST	5000218036-EPL-0002-AU-VWT-002
EXTERNAL & INTERNAL LAYOUT	5000218036-EPL-0002-AU-VWT-003
BILL OF MATERIAL	5000218036-EPL-0002-AU-VWT-004
TERMINAL LAYOUT	5000218036-EPL-0002-AU-VWT-005
FIELD WIRING	5000218036-EID-0002-AU-VWT-001
FIELD WIRING	5000218036-EID-0002-AU-VWT-002


LEGEND


LOW PRESSURE
HIGH PRESSURE
LOW LEVEL
HIGH LEVEL
LIMIT SWITCH
LIMIT SWITCH
LOW FLOW
HIGH FLOW
RELAY CONTACT
RELAY CONTACT
RELAY CONTACT
ON DELAY TIMER
OFF DELAY TIMER
GROUND
ISOLATED GROUND
FUSE (POWER)
FUSE (CONTROL)
DISTRIBUTION BLOCK

MAINTAINED TWO SELECTOR SWITCH
MAINTAINED 3 POSITIONS SELECTOR SWITCH
SPRING RETURN FROM LEFT 3 POSITIONS SELECTOR SWITCH
SPRING RETURN FROM RIGHT 3 POSITIONS SELECTOR SWITCH
SPRING RETURN FROM BOTH 3 POSITIONS SELECTOR SWITCH
PUSH BUTTON
PUSH BUTTON
PULL BUTTON
PULL BUTTON
EMERGENCY STOP BUTTON
POTENTIOMETER
CURRENT TRANSFORMER
THERMOSTAT
THERMOSTAT
1 POLE CIRCUIT BREAKER


COOLING FAN
RECEPTACLE 120VAC WITH RJ45
RECEPTACLE 120VAC DUPLEX
PILOT LIGHT
PUSH TO TEST PILOT LIGHT
RELAY COIL
RELAY COIL WITH SURGE SUPPRESSOR
CONTACTOR COIL
CONTACTOR COIL WITH SURGE SUPPRESSOR
ALARM
RESISTOR
SOLENOID
PULL CORD
ZERO SPEED DETECTOR


POWER BLOCK FOR FIELD WIRING
TERMINAL
WIRING JUNCTION
KNIFE TERMINAL


3 POLES THERMAL MAGNETIC CIRCUIT BREAKER



3 POLES MAGNETIC CIRCUIT BREAKER

3 POLES FUSIBLE DISCONNECT SWITCH


3 POLES DISCONNECT SWITCH


3 POLES CONTACTOR


3 POLES OVERLOAD RELAY



1 POLE TRANSFORMER

WIRE COLOR CODE

MINIMAL 18AWG GAUGE	
POWER 120VAC	BLACK
CONTROL 120VAC	RED
NEUTRAL	WHITE
24VDC	BLUE
0VDC	BLUE/WHITE
DRY CONTRACT	YELLOW, 14AWG
NON-ISOLATED GROUND	GREEN
ISOLATED GROUND	GREEN/YELLOW
TWISTED PAIR	(+) BLACK & (-) WHITE

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUIILT || FIELD MODIFICATION	2020-03-05	SB	RA	-	-
4	AS BUIILT || FIELD MODIFICATION	2019-07-29	JC	RA	-	-
3	AS BUILT	2019-03-26	HZ	RA	-	-
2	FOR FABRICATION	2019-03-15	MR	RA	-	-
1	FOR APPROVAL	2019-01-09	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
-	-
CHECKER	DATE
-	-
ENGINEER	DATE
-	-
SCALE:	N/A

TITLE: JB-001 SPIDFLOW T-02 310
CONTROL JUNCTION BOX
LEGEND & DRAWING LIST

CLIENT: WWTP UPGRADE
CITY OF IQALUIT


VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL	0002-AU-VWT	-	02 OF 05	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 16:09:20 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\REV5\5000218036-EPL-0002-AU-VWT-002.dwg - sbouya

ENCLOSURE NEMA 4X–FIERGLASS / 14H'' X 12W'' X 6D'' (PJ14126RL)
cUL APPROVAL



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUIILT || FIELD MODIFICATION	2020–03–05	SB	RA	–	–
4	AS BUIILT || FIELD MODIFICATION	2019–07–29	JC	RA	–	–
3	AS BUILT	2019–03–26	HZ	RA	–	–
2	FOR FABRICATION	2019–03–15	MR	RA	–	–
1	FOR APPROVAL	2019–01–09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE: JB–001 SPIDFLOW T–02 310
CONTROL JUNCTION BOX
EXTERNAL & INTERNAL LAYOUT

CLIENT: WWTP UPGRADE
CITY OF IQALUIT


VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036–EPL	– 0002–AU–VWT	–	03 OF 05	5


BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17
Mar 09, 2020 16:09:22 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – Upgrade\DOC\DESSIN\000–DRAWINGS\JB–001\REV5\5000218036–EPL–0002–AU–VWT–003.dwg – sbouya
5000218036 Iqaluit WWTP

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 16:09:24 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\REV5\5000218036-EPL-0002-AU-VWT-004.dwg - sbouya







TERMINAL DESCRIPTION
A) ID(WAD8)
B) WDU6
C) WDU4
D) WDK2.5
E) DLD2.5
F) FUSE WSI 4/2
G) FUSE WSI 4
H) FUSE KDKS 1/EN4
J) WTR 2.5
K) WDU 2.5

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUIILT || FIELD MODIFICATION	2020-03-05	SB	RA	-	-
4	AS BUIILT || FIELD MODIFICATION	2019-07-29	JC	RA	-	-
3	AS BUILT	2019-03-26	HZ	RA	-	-
2	FOR FABRICATION	2019-03-15	MR	RA	-	-
1	FOR APPROVAL	2019-01-09	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	-	-
CHECKER	-	-
ENGINEER	-	-
SCALE:	N/A	

TITLE: JB-001 SPIDFLOW T-02 310 CONTROL JUNCTION BOX TERMINAL LAYOUT

CLIENT: WWTP UPGRADE CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL	0002-AU-VWT	-	04 OF 05	5

ITEM	DESCRIPTION	PART NUMBER	MANUF.	QTY	BY
1	NEMA 4X ENCLOSURE, C/W PAN 14R1311 DIM 14"H x 12"W x 6"D, FIBERGLASS REINFORCED POLYESTER	PJ14126RL	HAMMOND	1	ENV
2	TERMINAL 600VAC/DC, 20A WDU 2.5 C/W END PLATE 1050000000	1020000000	WEIDMULLER	A/R	ENV
3	TERMINAL 600VAC/DC, 30A WDU 4 C/W END PLATE 1050000000	1020100000	WEIDMULLER	A/R	ENV
4	TERMINAL 600VAC/DC, 50A WDU 6 C/W END PLATE 1050000000 OR SEPERATOR 1050100000	1020200000	WEIDMULLER	A/R	ENV
5	KNIFE TERMINAL 300VAC/DC, 10A, WTR 2.5 C/W END PLATE 1050000000	1855610000	WEIDMULLER	A/R	ENV
6	TERMINAL 2 LEVEL 300VAC/DC, 10A, WDK 2.5 C/W END PLATE 1059100000	1021500000	WEIDMULLER	A/R	ENV
7	TERMINAL 3 LEVEL 300VAC/DC, 10A, DLD 2.5 C/W END PLATE 1784210000	1784180000	WEIDMULLER	A/R	ENV
8	FUSE TERMINAL ¼ X 1¼, 300VAC/DC, 15A, WSI 4/2 C/W END PLATE 1880450000	1880430000	WEIDMULLER	A/R	ENV
9	FUSE TERMINAL 5 X 20mm, 300VAC/DC, 15A, WSI 4	1886580000	WEIDMULLER	A/R	ENV
10	FUSE TERMINAL 2 LEVEL 5 X 20mm, 300VAC/DC, 10A, KDKS 1/EN4 C/W END PLATE 9503330000	9503350000	WEIDMULLER	A/R	ENV
11	FUSE TERMINAL 2 LEVEL ¼ X 1¼, 300VAC/DC, 10A, KDKS 1/35DB C/W END PLATE 9532470000	9532440000	WEIDMULLER	A/R	ENV
12	END STOPPER WEW 35/2	1061200000	WEIDMULLER	A/R	ENV
13	COPPER GROUND BAR, #4-14	4C-190	NSI-INDUSTRIES	A/R	ENV
14	COPPER GROUND LUG, 600VAC, #6-14, STR	CB35-36-LY	PANDUIT	A/R	ENV

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUIILT || FIELD MODIFICATION	2020-03-05	SB	RA	–	–
4	AS BUIILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE: JB-001 SPIDFLOW T-02 310
CONTROL JUNCTION BOX
BILL OF MATERIAL

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA


VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0002-AU-VWT	–	05 OF 05	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17
Mar 09, 2020 16:09:25 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\REV5\5000218036-EPL-0002-AU-VWT-005.dwg – sbouya

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 16:09:27 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\REV5\5000218036-EID-0002-AU-VWT-001.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUIILT || FIELD MODIFICATION	2020-03-05	SB	RA	–	–
4	AS BUIILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE: JB-001 SPIDFLOW T-02 310 CONTROL JUNCTION BOX FIELD WIRING

CLIENT: WWTP UPGRADE CITY OF IQALUIT


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0002-AU-VWT	-	01 OF 02	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 16:09:29 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\REV5\5000218036-EID-0002-AU-VWT-002.dwg - sbouyo
5000218036 Iqaluit WWTP



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUIILT || FIELD MODIFICATION	2020-03-05	SB	RA	–	–
4	AS BUIILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: JB-001 SPIDFLOW T-02 310
CONTROL JUNCTION BOX
FIELD WIRING

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EID	0002-AU-VWT	–	02 OF 02	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

WWTP UPGRADE
CITY OF IQALUIT
CONTROL JUNCTION BOX
JB-001 SPIDFLOW T-02 310
PROJECT: 5000218036

Mar 09, 2020 16:06:57 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\REV5\5000218036-EPL-0002-AU-VWT-001.dwg - sbouya

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUIILT || FIELD MODIFICATION	2020-03-05	SB	RA	–	–
4	AS BUIILT || FIELD MODIFICATION	2019-07-29	JC	RA	–	–
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTCEID BY ALL APPLICABLE LWS, INCLUDING BUT NOT LMIED TO COPRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE: JB-001 SPIDFLOW T-02 310
CONTROL JUNCTION BOX
TITLE PAGE

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036	EPL – 0002-AU-VWT	–	01 OF 05	5

DRAWING LIST

DESCRIPTION	DRAWING NUMBER
CONTROL JUNCTION BOX JB-002 SPIDFLOW T-02-320	
TITLE PAGE	5000218036-EPL-0003-AU-VWT-001
LEGEND & DRAWING LIST	5000218036-EPL-0003-AU-VWT-002
EXTERNAL & INTERNAL LAYOUT	5000218036-EPL-0003-AU-VWT-003
BILL OF MATERIAL	5000218036-EPL-0003-AU-VWT-004
TERMINAL LAYOUT	5000218036-EPL-0003-AU-VWT-005
FIELD WIRING	5000218036-EID-0003-AU-VWT-001
FIELD WIRING	5000218036-EID-0003-AU-VWT-002

LEGEND


LOW PRESSURE
HIGH PRESSURE
LOW LEVEL
HIGH LEVEL
LIMIT SWITCH
LIMIT SWITCH
LOW FLOW
HIGH FLOW
RELAY CONTACT
RELAY CONTACT
RELAY CONTACT
ON DELAY TIMER
OFF DELAY TIMER
GROUND
ISOLATED GROUND
FUSE (POWER)
FUSE (CONTROL)
DISTRIBUTION BLOCK

MAINTAINED TWO SELECTOR SWITCH
MAINTAINED 3 POSITIONS SELECTOR SWITCH
SPRING RETURN FROM LEFT 3 POSITIONS SELECTOR SWITCH
SPRING RETURN FROM RIGHT 3 POSITIONS SELECTOR SWITCH
SPRING RETURN FROM BOTH 3 POSITIONS SELECTOR SWITCH
PUSH BUTTON
PUSH BUTTON
PULL BUTTON
PULL BUTTON
EMERGENCY STOP BUTTON
POTENTIOMETER
CURRENT TRANSFORMER
THERMOSTAT
THERMOSTAT
1 POLE CIRCUIT BREAKER

COOLING FAN
RECEPTACLE 120VAC WITH RJ45
RECEPTACLE 120VAC DUPLEX
PILOT LIGHT
PUSH TO TEST PILOT LIGHT
RELAY COIL
RELAY COIL WITH SURGE SUPPRESSOR
CONTACTOR COIL
CONTACTOR COIL WITH SURGE SUPPRESSOR
ALARM
RESISTOR
SOLENOID
PULL CORD
ZERO SPEED DETECTOR

POWER BLOCK FOR FIELD WIRING
TERMINAL
WIRING JUNCTION
KNIFE TERMINAL

3 POLES THERMAL MAGNETIC CIRCUIT BREAKER
3 POLES MAGNETIC CIRCUIT BREAKER
3 POLES FUSIBLE DISCONNECT SWITCH
3 POLES DISCONNECT SWITCH
3 POLES CONTACTOR
3 POLES OVERLOAD RELAY



1 POLE TRANSFORMER

WIRE COLOR CODE

MINIMAL 18AWG GAUGE	
POWER 120VAC	BLACK
CONTROL 120VAC	RED
NEUTRAL	WHITE
24VDC	BLUE
0VDC	BLUE/WHITE
DRY CONTRACT	YELLOW, 14AWG
NON-ISOLATED GROUND	GREEN
ISOLATED GROUND	GREEN/YELLOW
TWISTED PAIR	(+) BLACK & (-) WHITE

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-03-05	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-30	JC	RA	–	–
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: JB-002 SPIDFLOW T-02-320
CONTROL JUNCTION BOX
LEGEND & DRAWING LIST


CLIENT: WWTP UPGRADE
CITY OF IQALUIT


VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0003-AU-VWT	–	02 OF 05	5

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17
Mar 09, 2020 16:06:58 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-002\REV 5\5000218036-EPL-0003-AU-VWT-002.dwg – sbouya

ENCLOSURE NEMA 4X–FIERGLASS / 14H'' X 12W'' X 6D'' (PJ14126RL)
cUL APPROVAL





REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020–03–05	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019–07–30	JC	RA	–	–
3	AS BUILT	2019–03–26	HZ	RA	–	–
2	FOR FABRICATION	2019–03–19	HZ	RA	–	–
1	FOR APPROVAL	2019–01–09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: JB–002 SPIDFLOW T–02–320
CONTROL JUNCTION BOX
EXTERNAL & INTERNAL LAYOUT

CLIENT: WWTP UPGRADE
CITY OF IQALUIT


VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036–EPL	– 0003–AU–VWT	–	03 OF 05	5


BAR = 1" AT PLOT SCALE
REF: 4
STD: "B" 11x17
Mar 09, 2020 16:07:00 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000–DRAWINGS\JB–002\REV 5\5000218036–EPL–0003–AU–VWT–003.dwg – sbouya

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 16:07:02 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-002\REV 5\5000218036-EPL-0003-AU-VWT-004.dwg – sbouya







TERMINAL DESCRIPTION
A) ID(WAD8)
B) WDU6
C) WDU4
D) WDK2.5
E) DLD2.5
F) FUSE WSI 4/2
G) FUSE WSI 4
H) FUSE KDKS 1/EN4
J) WTR 2.5
K) WDU 2.5

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-03-05	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-30	JC	RA	–	–
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: JB–002 SPIDFLOW T–02–320
CONTROL JUNCTION BOX
TERMINAL LAYOUT

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036–EPL	0003–AU–VWT	–	04 OF 05	5

ITEM	DESCRIPTION	PART NUMBER	MANUF.	QTY	BY
1	NEMA 4X ENCLOSURE, C/W PAN 14R1311 DIM 14"H x 12"W x 6"D, FIBERGLASS REINFORCED POLYESTER	PJ14126RL	HAMMOND	1	ENV
2	TERMINAL 600VAC/DC, 20A WDU 2.5 C/W END PLATE 1050000000	1020000000	WEIDMULLER	A/R	ENV
3	TERMINAL 600VAC/DC, 30A WDU 4 C/W END PLATE 1050000000	1020100000	WEIDMULLER	A/R	ENV
4	TERMINAL 600VAC/DC, 50A WDU 6 C/W END PLATE 1050000000 OR SEPERATOR 1050100000	1020200000	WEIDMULLER	A/R	ENV
5	KNIFE TERMINAL 300VAC/DC, 10A, WTR 2.5 C/W END PLATE 1050000000	1855610000	WEIDMULLER	A/R	ENV
6	TERMINAL 2 LEVEL 300VAC/DC, 10A, WDK 2.5 C/W END PLATE 1059100000	1021500000	WEIDMULLER	A/R	ENV
7	TERMINAL 3 LEVEL 300VAC/DC, 10A, DLD 2.5 C/W END PLATE 1784210000	1784180000	WEIDMULLER	A/R	ENV
8	FUSE TERMINAL ¼ X 1¼, 300VAC/DC, 15A, WSI 4/2 C/W END PLATE 1880450000	1880430000	WEIDMULLER	A/R	ENV
9	FUSE TERMINAL 5 X 20mm, 300VAC/DC, 15A, WSI 4	1886580000	WEIDMULLER	A/R	ENV
10	FUSE TERMINAL 2 LEVEL 5 X 20mm, 300VAC/DC, 10A, KDKS 1/EN4 C/W END PLATE 9503330000	9503350000	WEIDMULLER	A/R	ENV
11	FUSE TERMINAL 2 LEVEL ¼ X 1¼, 300VAC/DC, 10A, KDKS 1/35DB C/W END PLATE 9532470000	9532440000	WEIDMULLER	A/R	ENV
12	END STOPPER WEW 35/2	1061200000	WEIDMULLER	A/R	ENV
13	COPPER GROUND BAR, #4-14	4C-190	NSI-INDUSTRIES	A/R	ENV
14	COPPER GROUND LUG, 600VAC, #6-14, STR	CB35-36-LY	PANDUIT	A/R	ENV

BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
5	AS BUILT || FIELD MODIFICATION	2020-03-05	SB	RA	–	–
4	AS BUILT || FIELD MODIFICATION	2019-07-30	JC	RA	–	–
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE
JB-002 SPIDFLOW T-02-320
CONTROL JUNCTION BOX
BILL OF MATERIAL

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0003-AU-VWT		–	05 OF 05	5

Mar 09, 2020 16:07:04 – G:\Projets A67XX\A6798A @ A6798D – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-002\REV 5\5000218036-EPL-0003-AU-VWT-005.dwg – sbouya

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 16:07:05 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-002\REV 5\5000218036-EID-0003-AU-VWT-001.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
4	AS BUILT || FIELD MODIFICATION	2020-03-05	SB	RA	-	-
3	AS BUILT	2019-03-26	HZ	RA	-	-
2	FOR FABRICATION	2019-03-19	MR	RA	-	-
1	FOR APPROVAL	2019-01-09	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTCTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
-	-
CHECKER	DATE
-	-
ENGINEER	DATE
-	-
SCALE:	N/A

TITLE
JB-002 SPIDFLOW T-02-320
CONTROL JUNCTION BOX
FIELD WIRING


CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036	EID - 0003-AU-VWT	-	01 OF 02	4

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

Mar 09, 2020 16:07:07 - G:\Projets A67XX\A6798A @ A6798D - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-002_REV 5\5000218036-EID-0003-AU-VWT-002.dwg - sbouya



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
4	AS BUILT || FIELD MODIFICATION	2020-03-05	SB	RA	–	–
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-19	HZ	RA	–	–
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE
JB-002 SPIDFLOW T-02-320
CONTROL JUNCTION BOX
FIELD WIRING

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0003-AU-VWT	–	02 OF 02	4

APPENDIX B

APPROVED SHOP DRAWINGS

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

Mark Cabana Rousseau P.Eng

DATE: Jul 12, 2018

Mécanique Nordique Plumbing Heating Ventillation

mecanique.nordique@hotmail.com

1255 Rue J.A.Bombardier
Lévis, Québec
G7A 2P4
Téléphone: 418-496-1109
Télécopieur: 418-496-3803

IQALUIT WWTP UPGRADE

DRAWING FOR APPROVAL

Ingineer : NUNAMI STANTEC

DRAWING #: AD-029

Section 25 30 02
Article 2.27.1
Plans M-601
Application : Wirings Conduit , Terminations , Boxes
Brand : Differents
Model : Differents
Revised # :
Supplyer : JOHNSON CONTROLS

Pages incl. 291
Date : **2018-07-12**
By : **Mécanique Nordique Inc.**

STANTEC PROJECT #: 110126045

SUBMITTAL # AD-029

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE 2018-07-30

BY Konrad Goluch

INSTALLATION TYPE
CLASS 0 : NO CLASSIFICATION

DRAWING REFERENCE : 3309-INST-1

1.1 E.M.T. SET-SCREW COUPLING
1.2 ELECTRICAL METALLIC TUBING E.M.T.
1.3 E.M.T. SET-SCREW FITTING
1.4 4 INCH. SQUARE BOXE COVER
1.5 4 INCH. SQUARE BOXE
1.6 UTILITY BOXE COVER
1.7 ARMOURED CABLE/FLEXIBLE CONDUIT-ONE SCREW FITTING
1.8 UTILITY BOXE
1.9 LIQUATITE FLEXIBLE CONDUIT
1.10 WIRE/CABLE TYPE

CATEGORY 1: WET LOCATION

DRAWING REFERENCE: 3309-INST-2

2.1 RIGID PVC CONDUIT COUPLING
2.2 PVC STRAP 2 HOLES
2.3 RIGID TUBING PVC CONDUIT
2.4 RIGID PVC CONDUIT TERMINAL ADAPTER
2.5 JUNCTION BOX WITH GASKET
2.6 UTILITY BOXE SINGLE GANG
2.7 LIQUIDTIGHT ZINC ALLOY FITTING
2.8 LIQUATITE FLEXIBLE CONDUIT STEEL

CLASS 1, ZONE 2 AND CATEGORY 1


DRAWING REFERENCE : 3309-INST-3

3.1 CONDULET CONDUIT OUTLET
3.2 VINYL INSULATED BUTT SPLICE
3.3 FS BOXE FSC
3.4 BLANK COVER GASKET
3.5 STAR TECK FITTING
3.6 WIRE/CABLE TYPE

tous droits réservés ©2017 copyright
service technique solution inc.

INSTALLATION TYPE FOR CLASS SHOWN:
- ☑ CLASS 0: NO CLASSIFICATION
- ☐ CATEGORY 1: WET LOCATION
- ☐ CLASS 1, ZONE2 AND CATEGORY 1

SUBMITTED FOR APPROVAL



CODE	DESCRIPTION					APPLICATION
8220	FT4	600V	20GA	2WIRES	NON-SHLD	CONTROL EQUIPMENT
8221	FT4	600V	20GA	3WIRES	NON-SHLD	CONTROL EQUIPMENT
8241	FT4	600V	22GA	3WIRES	SHLD	MSTP COMMUNICATION
8242	FT4	600V	22GA	4WIRES	SHLD	CONTROL EQUIPMENT
8190	FT4	600V	16GA	2WIRES	NON-SHLD	CONTROL EQUIPMENT 24VAC

SEE DATA SHEET FOR MORE DETAILS

CLIENT
SOCIÉTÉ DE CONTRÔLE JOHNSON S.E.C.
765 avenue Godin, Ville de Québec
QC, Canada G1M 2W8

PROJET
WASTEWATER TREATMENT PLANT UPG.
City of Iqaluit
NU, Canada

TITRE
INSTALLATION TYPE CLASSIFICATION AREA REF. E002

STS service technique solution
Service Technique Solution Inc.
2112 ave. de la Rivière-Jaune
Québec, QC
G2N 1T5
Tel.: (418) 849-4004
Fax: (418) 841-7820
R.B.Q. 5605-0495-01

REPRESENTANT	GERANT DE PROJET	CONCEPTEUR
S. TURBIDE	S. TURBIDE	S. TURBIDE

DESSINÉ PAR: S.T. 04/07/18
APPROUVÉ PAR: S.L. 05/07/18

DESSIN DE REFERENCE	NO.	REVISION	ECN	DATE	PAR


NUMERO PROJET **3309-06-06**
NUMERO DESSIN **3309-INST-1**
PAGE **1 / 1**

TOUS DROITS RÉSERVÉS/COPYRIGHT SERVICE TECHNIQUE SOLUTION INC.

INSTALLATION TYPE FOR CLASS SHOWN:

- ☐ CLASS 0: NO CLASSIFICATION
- ☑ CATEGORY 1: WET LOCATION
- ☐ CLASS 1, ZONE2 AND CATEGORY 1

SUBMITTED FOR APPROVAL



1.10 WIRE TYPE

CODE	DESCRIPTION					APPLICATION
8220	FT4	600V	20GA	2WIRES	NON-SHLD	CONTROL EQUIPMENT
8221	FT4	600V	20GA	3WIRES	NON-SHLD	CONTROL EQUIPMENT
8241	FT4	600V	22GA	3WIRES	SHLD	MSTP COMMUNICATION
8242	FT4	600V	22GA	4WIRES	SHLD	CONTROL EQUIPMENT
8190	FT4	600V	16GA	2WIRES	NON-SHLD	CONTROL EQUIPMENT 24VAC

SEE DATA SHEET FOR MORE DETAILS

CLIENT
SOCIÉTÉ DE CONTRÔLE JOHNSON S.E.C.
765 avenue Godin, Ville de Québec
QC, Canada G1M 2W8

PROJET
WASTEWATER TREATMENT PLANT UPG.
City of Iqaluit
NU, Canada

TITRE
INSTALLATION TYPE CLASSIFICATION AREA REF. E002

STS service technique solution
Service Technique Solution Inc.
2112 ave. de la Rivière-Jaune
Québec, QC
G2N 1T5
Tel.: (418) 849-4004
Fax: (418) 841-7820
R.B.Q. 5605-0495-01

REPRESENTANT	GERANT DE PROJET	CONCEPTEUR
S. TURBIDE	S. TURBIDE	S. TURBIDE

DESSINÉ PAR: S.T. 04/07/18
APPROUVÉ PAR: S.L. 05/07/18

DESSIN DE REFERENCE	NO.	REVISION	ECN	DATE	PAR


NUMERO PROJET **3309-06-06**
NUMERO DESSIN **3309-INST-2**
PAGE **1 / 1**

TOUS DROITS RÉSERVÉS/COPYRIGHT SERVICE TECHNIQUE SOLUTION INC.

SUBMITTED FOR APPROVAL

INSTALLATION TYPE FOR CLASS SHOWN:

- ☐ CLASS 0: NO CLASSIFICATION
- ☐ CATEGORY 1: WET LOCATION
- ☑ CLASS 1, ZONE2 AND CATEGORY 1



3.6 WIRE TYPE

CODE	DESCRIPTION				APPLICATION
33H1801X	300V	18GA	2WIRES	NON-SHLD	CONTROL EQUIPMENT
33H1802X	300V	18GA	4WIRES	NON-SHLD	CONTROL EQUIPMENT
46A1602-40	600V	16GA	2WIRES	NON-SHLD	CONTROL EQUIPMENT
46A1603-40	600V	16GA	3WIRES	NON-SHLD	CONTROL EQUIPMENT
19A1402	600V	14GA	2WIRES	NON-SHLD	CONTROL EQUIPMENT

SEE DATA SHEET FOR MORE DETAILS

CLIENT
SOCIÉTÉ DE CONTRÔLE JOHNSON S.E.C.
765 avenue Godin, Ville de Québec
QC, Canada G1M 2W8

PROJET
WASTEWATER TREATMENT PLANT UPG.
City of Iqaluit
NU, Canada

TITRE
INSTALLATION TYPE CLASSIFICATION AREA REF. E002

STS service technique solution
Service Technique Solution Inc.
2112 ave. de la Rivière-Jaune
Québec, QC
G2N 1T5
Tel.: (418) 849-4004
Fax: (418) 841-7820
R.B.Q. 5605-0495-01

REPRESENTANT	GERANT DE PROJET	CONCEPTEUR
S. TURBIDE	S. TURBIDE	S. TURBIDE

DESSINÉ PAR:	APPROUVÉ PAR:
S.T. 04/07/18	S.L. 05/07/18

DESSIN DE REFERENCE	NO.	REVISION	ECN	DATE	PAR

NUMERO PROJET **3309-06-06**

NUMERO DESSIN **3309-INST-3**

PAGE **1 / 1**

TOUS DROITS RÉSERVÉS/COPYRIGHT SERVICE TECHNIQUE SOLUTION INC.

EMT

Set Screw Fittings

CI5404 (-IT) / CI5408 (-IT)



CI5410 (-IT) / CI5432 (-IT)



c UL us LISTED

Cat. No.		Trade Size (in.)
Regular	Insulated	
EMT Set Screw Fittings (Steel)		
CI5404	CI5404-IT	1/2
CI5406	CI5406-IT	3/4
CI5408	CI5408-IT	1
CI5410	CI5410-IT	1-1/4
CI5412	CI5412-IT	1-1/2
CI5416	CI5416-IT	2
CI5420	CI5420-IT	2-1/2
CI5424	CI5424-IT	3
CI5432	CI5432-IT	4

Concrete-tight

CI5004 (-IT) / CI5008 (-IT)



CI5010 (-IT) / CI5016 (-IT)



CI5020 (-IT) / CI5032 (-IT)



Cat. No.		Trade Size (in.)
Regular (Zinc)	Insulated (Steel)	
EMT Set Screw Fittings (Zinc)		
CI5004	CI5004-IT	1/2
CI5006	CI5006-IT	3/4
CI5008	CI5008-IT	1
CI5010	CI5010-IT	1-1/4
CI5012	CI5012-IT	1-1/2
CI5016	CI5016-IT	2
CI5020	CI5020-IT	2-1/2
CI5024	CI5024-IT	3
CI5032	CI5032-IT	4

Concrete-tight. Zinc Die Cast Locknut. IT: with insulated throat.

CI5054 / CI5058



Cat. No.	Trade Size (in.)	Offset (in.)
EMT Set Screw Offset Body Fittings (Zinc Alloy)		
CI5054	1/2	3/8
CI5056	3/4	3/4
CI5058	1	3/4

Concrete-tight.

TC121A-FA





Cat. No.		Trade Size (in.)	Std. Pkg. Qty
Regular	Insulated		
EMT / Fire Alarm Set Screw Fittings (Red Steel)			
TC121A-FA	TC721A-FA	1/2	50
TC122A-FA	TC722A-FA	3/4	50
TC123A-FA	TC723A-FA	1	25

EMT

Set Screw Couplings

CI5504 / CI5508



CI5120 / CI5132



CI5104 / CI5116



CI5510 / CI5532



1.1

Cat. No.		Trade Size (in.)
Steel	Zinc Alloy	
EMT Set Screw Couplings		
CI5504*	CI5104	1/2
CI5506*	CI5106	3/4
CI5508*	CI5108	1
CI5510*	CI5110	1-1/4
CI5512*	CI5112	1-1/2
CI5516*	CI5116	2
CI5520*	CI5120	2-1/2
CI5524*	CI5124	3
CI5532*	CI5132	4

* cULus Listed only
Concrete-tight

CI5164 / CI5168



Cat. No.	Trade Size (in.)	
	EMT	Rigid
EMT / Rigid Couplings (Zinc Alloy)		
CI5164	1/2	1/2
CI5166	3/4	3/4
CI5168	1	1

Concrete-tight

TK121A-FA





Cat. No.	Trade Size (in.)	Std. Pkg. Qty
EMT / Fire Alarm Set Screw Couplings (Red Steel)		
TK121A-FA	1/2	50
TK122A-FA	3/4	50
TK123A-FA	1	25

EMT

Compression Fittings and Couplings

- Models from 2-1/2 to 4 in. are also suitable for rigid and IMC conduit

TC111A



TC711A



Cat. No.		Trade Size (in.)
Regular	Insulated	
EMT Compression Fittings (Zinc-plated steel)		
TC111A	TC711A	1/2
TC112A	TC712A	3/4
TC113A	TC713A	1
TC114A*	TC714A	1-1/4
TC115A*	TC715A	1-1/2
TC116A*	TC716A	2
TC117A	TC717A	2-1/2
TC118A	TC718A	3
TC119A	TC719A	3-1/2
TC1110A	TC7110A	4

UL FILE NO. E-16592. * O-rings are supplied.
Concrete-tight.

TK111A



Cat. No.	Trade Size (in.)
EMT Compression Couplings (Zinc-plated steel)	
TK111A	1/2
TK112A	3/4
TK113A	1
TK114A	1-1/4
TK115A	1-1/2
TK116A	2
TK117A	2-1/2
TK118A	3
TK119A	3-1/2
TK1110A	4

UL FILE NO. E-16592.
Concrete-tight.

CI5804 (-IT) / CI5832 (-IT)



Zinc Die Cast Locknut
IT: with insulated throat

Cat. No.		Trade Size (in.)
Regular	Insulated	
EMT Compression Fittings (Zinc Alloy)		
CI5804	CI5804-IT	1/2
CI5806	CI5806-IT	3/4
CI5808	CI5808-IT	1
CI5810	CI5810-IT	1-1/4
CI5812	CI5812-IT	1-1/2
CI5816	CI5816-IT	2
CI5820	CI5820-IT	2-1/2
CI5824	CI5824-IT	3
CI5832	CI5832-IT	4

Concrete-tight.

CI5904 / CI5932



Cat. No.	Trade Size (in.)
EMT Compression Couplings (Zinc Alloy)	
CI5904	1/2
CI5906	3/4
CI5908	1
CI5910	1-1/4
CI5912	1-1/2
CI5916	2
CI5920	2-1/2
CI5924	3
CI5932	4

Concrete-tight.

EMT

Wet-location fittings



CI5612-IT-WL





CI5706-WL




CI5620-WL

Specifications

Material: Steel body and steel locknut
Finish: Electro zinc plated
Liner (insulated fittings only): Nylon
Threads: Hub threads (NPS)
Sealing Gasket: Neoprene
Sealing Ring: Nylon
Use: Wet locations, concrete-tight

UL Listed Raintight (File E-16592)
UL514B / CSAC22.2–N°18.3
NEMA FB-1
NEMA 3R



Wet-location EMT compression fittings

Cat. No.	Hub Size (in.)	Dimensions (in.)			Std. Ctn.
		A	B	C	
Non-insulated					
CI5604-WL	½	1.22	0.47	1.14	100
CI5606-WL	¾	1.21	0.48	1.38	50
CI5608-WL	1	1.30	0.50	1.67	25
CI5610-WL	1-¼	1.50	0.60	2.06	25
CI5612-WL	1-½	1.53	0.65	2.27	20
CI5616-WL	2	1.67	0.73	2.77	10
CI5620-WL	2-½	2.77	0.87	3.65	5
CI5624-WL	3	2.75	0.87	4.30	5
CI5632-WL	4	3.12	0.92	5.23	5
Insulated					
CI5604-IT-WL	½	1.22	0.54	1.14	100
CI5606-IT-WL	¾	1.21	0.55	1.38	50
CI5608-IT-WL	1	1.30	0.57	1.67	25
CI5610-IT-WL	1-¼	1.50	0.69	2.06	25
CI5612-IT-WL	1-½	1.53	0.74	2.27	20
CI5616-IT-WL	2	1.67	0.82	2.77	10
CI5620-IT-WL	2-½	2.77	0.99	3.65	5
CI5624-IT-WL	3	2.75	0.99	4.30	5
CI5632-IT-WL	4	3.12	1.04	5.23	5

Wet-location EMT compression couplings

Cat. No.	Hub Size (in.)	Dimensions (in.)			Std. Ctn.
		A	B	C	
CI5704-WL	½	1.94	1.14	–	100
CI5706-WL	¾	2.09	1.38	–	50
CI5708-WL	1	2.31	1.67	–	25
CI5710-WL	1-¼	2.58	2.06	–	25
CI5712-WL	1-½	2.74	2.27	–	20
CI5716-WL	2	2.83	2.77	–	10
CI5720-WL	2-½	4.47	3.65	–	5
CI5724-WL	3	4.70	4.30	–	5
CI5732-WL	4	5.75	5.23	–	5

EMT

Accessories

CI1304 / CI1316



CI1404 / CI1416



CI1520 / CI1532



Cat. No.	Trade Size (in.)	Max. EMT Dia. (in.)	Hole Size (in.)
One Hole EMT Straps (Galvanized Steel)			
CI1304	1/2	0.71	1/4
CI1306	3/4	0.92	1/4
CI1308	1	1.16	5/16
CI1310	1-1/4	1.51	7/16
CI1312	1-1/2	1.74	7/16
CI1316	2	2.20	9/16
Two Hole EMT Straps (Galvanized Steel)			
CI1404	1/2	0.71	3/16
CI1406	3/4	0.92	3/16
CI1408	1	1.16	3/16
CI1410	1-1/4	1.51	1/4
CI1412	1-1/2	1.74	1/4
CI1416	2	2.20	3/8
CI1520	2-1/2	2.88	3/8
CI1524	3	3.50	3/8
CI1528	3-1/2	4.00	1/2
CI1532	4	4.50	1/2

CI5153



CI5154



Cat. No.	Trade Size (in.)		Clamping Range (in.)	
	EMT	Flex.	Min.	Max.
EMT / Flex Couplings (Zinc Alloy)				
CI5153	1/2	3/8	0.17	0.63
CI5154	1/2	1/2	0.75	0.95

CI7538




Cat. No.	Max. Flex. Conduit Dia. (in.)	Hole Size (in.)
One Hole Double Sided Strap (Galvanized Steel)		
CI7538*	1.05	3/16

*Any combination of 3/8 in., 1/2 in. and 3/4 in. EMT, rigid conduit, flexible conduit or teck cables

EMT

Accessories

500-SC / 503-SC



Cat. No.	Trade Size (in.)	Jaw Opening (in.)	Tap Base and Back	Dimensions (in.)		
				A	B	C
Beam Clamps (Malleable Iron)						
500-SC	1/4NC	15/16	1/4-20	1	1-1/4	1-7/16
501	5/16NC	7/8	5/16-18	1-9/16	1-9/16	1-11/16
502	3/8NC	1	3/8-16	2	1-7/8	1-3/4
503-SC	1/2NC	1	1/2-13	2-1/2	2-3/8	2-3/8

CICH-0404 / CICH-3232



Cat. No.	Trade Size (in.)	
	EMT	Rigid
Conduit Hangers-Steel (with nuts & bolts)		
CICH-0404	1/2	1/2
CICH-0606	3/4	3/4
CICH-0808	1	1
CICH-0010	1-1/4	—
CICH-1012	1-1/2	1-1/4
CICH-1200	—	1-1/2
CICH-1616	2	2
CICH-2020	2-1/2	2-1/2
CICH-2424	3	3
CICH-2828	3-1/2	3-1/2
CICH-3232 *	4	4

* Not CSA certified

EMT

Pull Elbows and Conduit Fittings

CI5204 / CI5206



Zinc Die Cast Locknut


CI5304 / CI5306 / CI5308-G / CI5310-G



-G: with gasket.


CICA-1/2 / CICA-2





CILBA-1/2 / CILBA-2 / CILBSA-2-1/2 / CILBSA-4





Cat. No.	Trade Size (in.)	Dimensions (in.)		
		A	B	C
Pull Elbows, EMT to Box (Zinc Alloy)				
CI5204	1/2	1-5/16	1-1/8	—
CI5206	3/4	1-1/2	1-1/4	—
Pull Elbows, EMT to EMT (Zinc Alloy)				
CI5304	1/2	1-5/16	15/16	—
CI5306	3/4	1-5/8	1-1/4	—
CI5308-G	1	1-15/16	1-5/8	—
CI5310-G	1-1/4	2-1/4	2	—
EMT Conduit Fittings - "C" Type (Cast Aluminum)				
CICA-1/2	1/2	4-7/8	1-3/8	1-3/8
CICA-3/4	3/4	5-9/16	1-1/2	1-7/16
CICA-1	1	6-1/2	1-3/4	1-3/4
CICA-1-1/4	1-1/4	8-5/8	1-15/16	2-1/2
CICA-1-1/2	1-1/2	8-5/8	2-11/16	2-1/2
CICA-2	2	10-15/16	3	3-3/16
EMT Conduit Fittings - "LB" Type (Cast Aluminum)				
CILBA-1/2	1/2	4-5/16	1-1/2	1-3/8
CILBA-3/4	3/4	4-15/16	1-7/8	1-9/16
CILBA-1	1	6-1/16	2-1/16	1-13/16
CILBA-1-1/4	1-1/4	7-7/8	2-15/16	2-1/2
CILBA-1-1/2	1-1/2	7-7/8	3-1/16	2-1/2
CILBA-2	2	10	3-3/4	3-3/16
CILBSA-2-1/2 *	2-1/2	13	7-3/8	4-1/4
CILBSA-3 *	3	13	7-3/8	4-1/4
CILBSA-3-1/2 *	3-1/2	15-1/4	9	5-1/4
CILBSA-4 *	4	15-1/4	9	5-1/4

Covers and gaskets are included with all aluminum conduit fittings
Types CICA and CILBA are also suitable for use with rigid conduit (NPSM threads)
* For EMT only, not threaded

EMT

Conduit Fittings, Accessories and Entrance Heads


CILRL-1/2 / CILRL-2




Combined LL/LR
Left and right
application

CITA-1/2 / CITA-2







Cat. No.	Trade Size (in.)	Dimensions (in.)		
		A	B	C
EMT Conduit Fittings - "LRL" Type (Cast Aluminum)				
CILRL-1/2	1/2	4-7/16	1-11/16	2-1/8
CILRL-3/4	3/4	5-3/16	1-7/8	2-1/4
CILRL-1	1	6	2-3/16	2-1/2
CILRL-1-1/4	1-1/4	7-15/16	2-3/4	3-1/2
CILRL-1-1/2	1-1/2	7-15/16	3-1/4	3-1/2
CILRL-2	2	10-3/16	3-11/16	4-1/8
EMT Conduit Fittings - "T" Type (Cast Aluminum)				
CITA-1/2	1/2	4-7/8	1-3/8	2-1/16
CITA-3/4	3/4	5-9/16	1-3/4	2-1/8
CITA-1	1	6-1/2	2	2-1/2
CITA-1-1/4	1-1/4	8-11/16	2-5/8	3-1/2
CITA-1-1/2	1-1/2	8-11/16	3	3-9/16
CITA-2	2	10-7/8	3-1/4	4-3/16

Covers and gaskets are included with all aluminum conduit fittings
Types CILRL and CITA are also suitable for use with rigid conduit (NPSM Threads)

CIBC-1/2 / CIBC-2



Cat. No.	Gros. nom. (in.)
Blank Covers for Aluminum Conduit Fittings (Stamped Aluminum)	
CIBC-1/2	1/2
CIBC-3/4	3/4
CIBC-1	1
CIBC-1-1/4	1-1/4
CIBC-2	2

For 1-1/2, use CIBC-1-1/4
Screws not included

CIG-1/2 / CIG-2



Cat. No.	Trade Size (in.)
Gaskets for Aluminum Conduit Fittings (Neoprene)	
CIG-1/2	1/2
CIG-3/4	3/4
CIG-1	1
CIG-1-1/4	1-1/4
CIG-2	2

For 1-1/2, use CIG-1-1/4

CIEFSA-1/2 / CIEFSA-4



Cat. No.	Trade Size (in.)
Service Entrance Heads (Cast Aluminum)	
CIEFSA-1/2	1/2
CIEFSA-3/4	3/4
CIEFSA-1	1
CIEFSA-1 1/4	1-1/4
CIEFSA-1 1/2	1-1/2
CIEFSA-2	2
CIEFSA-2 1/2	2-1/2
CIEFSA-3	3
CIEFSA-3 1/2	3-1/2
CIEFSA-4	4

Consult page D10 for technical specifications

FT-10.1

8241 SPECIFICATIONS

Building Automation & Control

Non-Plenum (FT4)

APPLICATION

Building Automation - HVAC
Régulation

CONDUCTORS	
Material	Tinned copper
Size	22 AWG
Stranding	7 x 0.010"
Configuration	Triad
No. of triads	1
Color code	A (see chart)

INSULATION	
Material	Semi-Rigid PVC
Temperature	105 °C
Insulation thickness	0.01 mm
Voltage	600 Volts

SHIELD	
Type	Foil
Material	Aluminum/Mylar
Thickness	0.025 mm
Apply to	Triad

DRAIN WIRE	
Material	Tinned Copper
Size	24 awg
Construction	7 x 32 awg

OUTER JACKET	
Material	PVC
Jacket thickness	0.167 mm
Color	Orange
Rip cord	Apply
Diameter	4.24 mm

OPTIONS	
CSA/UL approbation	FT4
Quality insurance	ISO 9002
ROHS	Yes

CHARACTERISTICS	
Outer diameter	0.15 mm
Bending radius	50.8 mm
Weight	29.7 kgs/km
Capacitance A*	40.2 pF/ft
Capacitance B**	72.9 pF/ft
Impedance	60 Ohms
Conductor resistance at 20°C	16.6 Ohms/1000

The values shown are nominal.
* Capacitance between conductors
** Capacitance between one conductor and other conductors connected to shield
last revision: 2015-08-19 18:13:06.

FT-10.2

8242 SPECIFICATIONS

Building Automation & Control

Non-Plenum (FT4)

APPLICATION

Building Automation - HVAC
Régulation

CONDUCTORS	
Material	Tinned copper
Size	22 AWG
Stranding	7 x 0.010"
Cabling lay	9 T.P.F.
Configuration	Conductors
Conductor(s)	4
Color code	1 (see chart)

INSULATION	
Material	Semi-rigid PVC
Temperature	105 °C
Insulation thickness	0.25 mm
Voltage	600 Volts

SHIELD	
Type	Foil
Material	Aluminum/Mylar
Thickness	0.038 mm
Apply to	Conductors

DRAIN WIRE	
Material	Tinned Copper
Size	24 awg
Construction	7 x 32 awg

OUTER JACKET	
Material	PVC
Jacket thickness	0.38 mm
Color	Orange
Rip cord	Apply
Diameter	5.23 mm
Temperature	105 °C

OPTIONS	
CSA/UL approbation	FT4
Quality insurance	ISO 9002
ROHS	Yes

CHARACTERISTICS	
Outer diameter	4.14 mm
Bending radius	50.8 mm
Weight	26.47 kgs/km
Capacitance A*	36 pF/ft
Capacitance B**	65 pF/ft
Impedance	60 ohms
Conductor resistance at 20°C	15.7 ohms/1000 ft

The values shown are nominal.
* Capacitance between conductors
** Capacitance between one conductor and other conductors connected to shield
last revision: 2015-08-19 18:13:06.

FT-10.3

8220 SPECIFICATIONS

Building Automation & Control

Non-Plenum (FT4)

APPLICATION

Contrôle de bâtiment - (HVAC)
Régulation

CONDUCTORS	
Material	Bare Copper
Size	20 AWG
Stranding	7 x 0.0126"
Cabling lay	6.67 T.P.F.
Configuration	Pair
Pair(s)	1
Color code	A (see chart)

INSULATION	
Material	Semi-Rigid PVC
Temperature	105 °C
Insulation thickness	0.25 mm
Voltage	600 Volts
Attenuation	

OUTER JACKET	
Material	PVC
Jacket thickness	0.38 mm
Color	Orange
Rip cord	Apply
Diameter	3.94 mm
Temperature	105 °C

OPTIONS	
Quality insurance	ISO 9002
ROHS	Yes

CHARACTERISTICS	
Bending radius	50.8 mm
Weight	19 kgs/km
Capacitance A*	30 pF/pi
Impedance	64 Ohms
Conductor resistance at 20°C	9.33 Ohms/1000'

The values shown are nominal.
* Capacitance between conductors
** Capacitance between one conductor and other conductors connected to shield
last revision: 2016-03-19 17:50:35.

FT-10.4

8221 SPECIFICATIONS

Building Automation & Control

Non-Plenum (FT4)

APPLICATION

Building Automation - HVAC
Régulation

CONDUCTORS	
Material	Bare Copper
Size	20 AWG
Stranding	7 x 0.0126"
Cabling lay	6.67 T.P.F.
Configuration	Triad
No. of triads	1
Color code	A (see chart)

INSULATION	
Material	Semi-rigid PVC
Temperature	105 °C
Insulation thickness	0.25 mm
Voltage	600 Volts

OUTER JACKET	
Material	PVC
Jacket thickness	0.38 mm
Color	Orange
Rip cord	Apply
Diameter	4.04 mm
Temperature	105 °C

OPTIONS	
Quality insurance	ISO 9002
ROHS	Yes

CHARACTERISTICS	
Bending radius	50.8 mm
Weight	21 kgs/km
Capacitance A*	30 pF/ft
Impedance	64 Ohms
Conductor resistance at 20°C	9.33 Ohms/1000 ft

The values shown are nominal.
* Capacitance between conductors
** Capacitance between one conductor and other conductors connected to shield
last revision: 2015-08-19 18:13:06.

FT-10

8190 SPECIFICATIONS

Building Automation & Control

Non-Plenum (FT4)

APPLICATION

Building Automation - HVAC
Régulation

CONDUCTORS	
Material	Bare Copper
Size	16 AWG
Stranding	7 x 0.0192"
Cabling lay	3.71 TPF
Configuration	Pair
Pair(s)	1
Color code	A (see chart)

INSULATION	
Material	Semi-Rigid PVC
Temperature	105 °C
Insulation thickness	0.508 mm
Voltage	600 Volts

OUTER JACKET	
Material	PVC
Jacket thickness	0.58 mm
Color	Orange
Rip cord	Apply
Diameter	5.99 mm
Temperature	105 °C

OPTIONS	
CSA/UL approbation	FT4
Quality insurance	ISO 9002
ROHS	Yes

CHARACTERISTICS	
Bending radius	50.8 mm
Weight	54 kgs/km
Capacitance A*	30 pF/ft
Impedance	64 Ohms
Conductor resistance at 20°C	4.19 Ohms/1000 foot

The values shown are nominal.
* Capacitance between conductors
** Capacitance between one conductor and other conductors connected to shield
last revision: 2016-04-12 10:44:06.


Electrical Metallic Tubing (EMT) and True Color™ EMT

Columbia-MBF™
A PART OF atkore INTERNATIONAL

E-Z Pull™ EMT

- Hot galvanized steel using patented inline Flo-Coat® process for long lasting exterior protection
- E-Z Pull interior coating provides a smooth raceway for fast, easier wire-pulling
- Excellent mechanical protection for conductors
- Ductility for faster and easier bending
- Optimal EMI shielding characteristics
- Listed to Underwriters Laboratories Safety Standard UL 797
- Manufactured in accordance with ANSI C80.3
- Available in sizes 1/2 (16) - 4 (103)

Quality Electrical Metallic Tubing



True Color™ EMT

- All the benefits of E-Z Pull EMT
- Instant identification of multiple circuits
- Fire Alarm® Red EMT
- Healthcare Green EMT
- Data Com Blue EMT
- Available in 8 colors
- Available in sizes 1/2 (16) - 4 (103)

Identify Important Circuits Instantly!



True Color™ Applications

Black EMT
- Blends in dark colored areas

Fire Alarm® EMT
- Emergency circuits
- Fire alarm and Security systems

Orange EMT
- Construction/research areas
- Fiber optic systems
- Auto repair/maintenance

Yellow EMT
- High voltage wiring
- Caution areas
- Special equipment

Green EMT
- Hospital and healthcare areas
- Nurse call stations
- Critical circuits

Blue EMT
- Low voltage wiring
- Data com/video
- Network security

Purple EMT
- Specialty wiring systems
- Security systems

White EMT
- Blends in light colored areas

Silver EMT
- Standard Use
- Contemporary architecture







Project Information

Company Name: _____
Address: _____
City: _____
State & Zip: _____
Phone: _____
Project Name: _____
City: _____
State: _____

NOTE: Special orders are non-cancelable, non-returnable and non-refundable

Electrical Metallic Tubing (EMT) and True Color™ EMT

Columbia-MBF™
A PART OF atkore INTERNATIONAL

FEATURES & SPECIFICATIONS

Manufactured for Long Life

Columbia-MBF® EMT is precision manufactured from high grade mild strip steel for exceptional durability and long-lasting life. Columbia-MBF EMT is hot galvanized using a patented inline Flo-Coat™ process. This process combines zinc, a conversion coating, and a clear organic polymer topcoat to form a triple layer of protection against corrosion and abrasion.

E-Z Pull™ EMT combines strength with ductility, providing easy bending, cutting and joining while resisting flattening, kinking and splitting. Available in sizes 1/2 (16) - 4 (103).

Coatings

Columbia-MBF's EMT (Electrical Metallic Tubing) has a special low friction ID coating called E-Z Pull that greatly improves the slip properties between conduit and wire. With E-Z Pull EMT, wire pulls through the EMT smoothly and easily, making installation easier and faster.

EMI Shielding

Columbia-MBF EMT is very effective in reducing electromagnetic field levels for encased power distribution circuits, shielding computers and other sensitive electronic equipment from the effects of electromagnetic interference.

For more information on EMT shielding, visit www.columbia-mbf.ca to obtain the **GEMI** (**G**rounding and **E**lectro-**M**agnetic **I**nterference) software analysis program.

Codes & Standards Compliance

Columbia-MBF EMT is Certified to Canadian Standards Association C22.2 No.83.1. As a metal raceway, EMT functions as an equipment bonding conductor when installed in compliance with the Canadian Electrical Code (CEC), including Section 10 *Grounding and Bonding* and Section 12-1400 *Electrical Metallic Tubing*. Documentation is available in the GEMI (Grounding and Electro-Magnetic Interference) analysis software and related research studies found at the www.columbia-mbf.ca website.

Installation of EMT shall be in accordance with the Canadian Electrical Code and the CSA Certification information.

Specification Data

To specify Columbia-MBF EMT, include the following: Electrical Metallic Tubing shall be equal to that manufactured by Columbia-MBF Inc. EMT shall be hot galvanized steel O.D. with an organic corrosion resistant I.D. coating, and shall be CSA Certified to Standard C22.2 No. 83.1 and manufactured in accordance with ANSI C80.3.

Electrical Metallic Tubing (EMT) and True Color™ EMT

Certified to Canadian Standards Association Safety Standard CSA C22.2 No.83.1
Manufactured in accordance with ANSI C80.3

Trade Size	Metric Designator	Outside Diameter[1]		Nominal Wall Thickness[2]		Approximate Weight Per 100 Ft. (30.5M)		Standard Bundle Quantity		True Color** Bundle Qty.	
		in	mm	in	mm	lb	kg	ft	m	ft	m
1/2	16	0.706	17.93	0.042	1.07	30	13.6	2500	762.0	3500	1066.8
3/4	21	0.922	23.42	0.049	1.24	46	20.9	2000	609.6	2500	762.0
1	27	1.163	29.54	0.057	1.45	67	30.4	1000	304.8	1500*	457.2
1-1/4	35	1.510	38.35	0.065	1.65	101	45.8	500	152.4	2000	609.6
1-1/2	41	1.740	44.20	0.065	1.65	116	52.6	500	152.4	1500	457.2
2	53	2.197	55.80	0.065	1.65	148	67.1	510	155.4	1200	365.7
2-1/2	63	2.875	73.03	0.072	1.83	216	98.0	250	76.2	610	185.9
3	78	3.500	88.90	0.072	1.83	263	119.3	200	61.0	510	155.4
3-1/2	91	4.000	101.60	0.083	2.11	349	158.3	100	30.5	370	112.7
4	103	4.500	114.30	0.083	2.11	393	178.3	100	30.5	300	91.5

1.2

[1]Outside diameter tolerances: +/- .005 in. (.13mm) for size 1/2 (16mm) through 2 (53mm);
+/- .010 in. (.25mm) for size 2-1/2 (63);
+/- .015 in. (.38mm) for size 3 (78);
+/- .020 in. (.50mm) for size 3-1/2 (91) and 4 (103).
NOTE: Length = 10 ft. (3.05m) with a tolerance of +/- .25 in. (6mm)
[2]For information only. Not a requirement of the CSA standard.

*True Color Blue size 1 (27) bundle quantity: 3000 ft / (914.4m)
** True Color Size 2 (53)- 4 (103) are available through special order

NOTE: Special orders are non-cancelable, non-returnable and non-refundable


6560 Northwest Drive, Mississauga, Ontario L4V 1P2
Phone / 905.362.0180 • Toll-Free / 866.632.0180
www.columbia-mbf.ca

Electrical Metallic Tubing (EMT) Elbows

Columbia-MBF™
A PART OF atkore INTERNATIONAL

EMT 90° Elbows

Certified to Canadian Standards Association Safety Standard CSA C22.2 No.83.1
Manufactured in accordance with ANSI C80.3




Trade Size	Metric Designator	Radius (A)[1]		Offset (B)[2]		Straight (D)[1]		Approximate Weight Per 100 Pieces		Standard Package
		in	mm	in	mm	in	mm	lb	kg	
1/2	16	4	102	5 7/8	149	1 1/2	38	25	11.3	25
3/4	21	4 1/2	114	7	178	1 1/2	38	46	20.9	50
1	27	5 3/4	146	8 3/4	222	1 7/8	48	84	38.1	25
1 1/4	35	7 1/4	184	10 1/8	257	2	51	144	65.3	20
1 1/2	41	8 1/4	210	11 3/4	298	2	51	193	87.5	15
2	53	9 1/2	241	14	356	2	51	296	134.3	10
2 1/2	63	10 1/2	267	16 1/4	413	3	76	504	228.6	80
3	78	13	330	18 3/4	476	3 1/8	79	701	318.0	50
3 1/2	91	15	381	21 1/4	540	3 1/4	83	1047	474.9	50
4	103	16	406	23 3/8	594	3 3/8	86	1310	594.2	36

[1]Minimum requirement as per CSA Standard
[2]For information only, not a requirement as per CSA Standard
Sizes 2-1/2 (63) and larger shipped in palletized cartons or bulk.
Also available in the following Degrees (60°, 45°, 30°, 22-1/2°, 15° & 11-1/4°)

EMT 45° Elbows

Certified to Canadian Standards Association Safety Standard CSA C22.2 No.83.1
Manufactured in accordance with ANSI C80.3



Trade Size	Metric Designator	Radius (A)[1]		Offset (B)[2]		Offset (C)[2]		Straight (D)[1]		Approximate Weight Per 100 Pieces		Standard Package
		in	mm	in	mm	in	mm	in	mm	lb	kg	
1/2	16	4	102	6 1/8	156	2 1/2	64	1 1/2	38	18	8.2	25
3/4	21	4 1/2	114	7 3/8	187	3 1/8	79	1 1/2	38	33	15.0	50
1	27	5 3/4	146	8 3/4	222	3 5/8	92	1 7/8	48	56	25.4	25
1 1/4	35	7 1/4	184	10 1/8	257	4 1/8	105	2	51	97	44.0	20
1 1/2	41	8 1/4	210	13 1/8	333	5 3/8	137	2	51	145	65.8	15
2	53	9 1/2	241	13 1/8	333	5 1/2	140	2	51	185	83.9	10
2 1/2	63	10 1/2	267	17 1/2	445	7 1/4	184	3	76	360	163.3	80
3	78	13	330	17 1/2	445	7 1/4	184	3 1/8	79	438	198.7	50
3 1/2	91	15	381	26 1/8	664	10 7/8	276	3 1/4	83	873	396.0	50
4	103	16	406	26 1/4	667	10 7/8	276	3 3/8	86	983	445.9	36

[1]Minimum requirement as per CSA Standard
[2]For information only, not a requirement as per CSA Standard
Sizes 2-1/2 (63) and larger shipped in palletized cartons or bulk.
Also available in the following Degrees (90°, 60°, 30°, 22-1/2°, 15° & 11-1/4°)

NOTE: Special orders are non-cancelable, non-returnable and non-refundable


6560 Northwest Drive, Mississauga, Ontario L4V 1P2
Phone / 905.362.0180 • **Toll-Free /** 866.632.0180
www.columbia-mbf.ca

Electrical Metallic Tubing (EMT) Elbows

Columbia-MBF™
A PART OF atkore INTERNATIONAL

EMT Large Radius 90° Elbows

Certified to Canadian Standards Association Safety Standard CSA C22.2 No.83.1
Manufactured in accordance with ANSI C80.3



Trade Size	Metric Designator	Radius (A)		Offset (B)[2]		Straight (D)[2]		Approximate Weight Per 100 Pieces	
		in	mm	in	mm	in	mm	lb	kg
1	27	12	305	20 5/8	524	8 5/8	219	201	91.2
1	27	15	381	24 1/4	616	9 1/4	235	235	106.6
1	27	18	457	27 7/8	708	9 7/8	251	268	121.6
1	27	24	610	34 5/8	879	10 5/8	270	329	149.2
1	27	30	762	41	1041	11	279	385	174.6
1	27	36	914	46 3/4	1187	10 3/4	273	436	197.8
1	27	42	1067	54	1372	12	305	503	228.2
1	27	48	1219	60 1/4	1530	12 1/4	311	558	253.1
1 1/4	35	12	305	20 5/8	524	8 5/8	219	303	137.4
1 1/4	35	15	381	24 1/4	616	9 1/4	235	354	160.6
1 1/4	35	18	457	27 7/8	708	9 7/8	251	404	183.3
1 1/4	35	24	610	34 5/8	879	10 5/8	270	497	225.4
1 1/4	35	30	762	41	1041	11	279	581	263.5
1 1/4	35	36	914	46 3/4	1187	10 3/4	273	657	298.0
1 1/4	35	42	1067	54	1372	12	305	758	343.8
1 1/4	35	48	1219	60 1/4	1530	12 1/4	311	842	381.9
1 1/2	41	12	305	20 5/8	524	8 5/8	219	348	157.9
1 1/2	41	15	381	24 1/4	616	9 1/4	235	406	184.2
1 1/2	41	18	457	27 7/8	708	9 7/8	251	464	210.5
1 1/2	41	24	610	34 5/8	879	10 5/8	270	570	258.6
1 1/2	41	30	762	41	1041	11	279	667	302.6
1 1/2	41	36	914	46 3/4	1187	10 3/4	273	754	342.0
1 1/2	41	42	1067	54	1372	12	305	870	394.6
1 1/2	41	48	1219	60 1/4	1530	12 1/4	311	967	438.6
2	53	12	305	20 5/8	524	8 5/8	219	444	201.4
2	53	15	381	24 1/4	616	9 1/4	235	518	235.0
2	53	18	457	27 7/8	708	9 7/8	251	592	268.5
2	53	24	610	34 5/8	879	10 5/8	270	728	330.2
2	53	30	762	41	1041	11	279	851	386.0
2	53	36	914	46 3/4	1187	10 3/4	273	962	436.4
2	53	42	1067	54	1372	12	305	1110	503.5
2	53	48	1219	60 1/4	1530	12 1/4	311	1233	559.3
2 1/2	63	12	305	20 5/8	524	8 5/8	219	648	293.9
2 1/2	63	15	381	24 1/4	616	9 1/4	235	756	342.9
2 1/2	63	18	457	27 7/8	708	9 7/8	251	864	391.9
2 1/2	63	24	610	34 5/8	879	10 5/8	270	1062	481.7
2 1/2	63	30	762	41	1041	11	279	1242	563.4
2 1/2	63	36	914	46 3/4	1187	10 3/4	273	1404	636.9
2 1/2	63	42	1067	54	1372	12	305	1620	734.8
2 1/2	63	48	1219	60 1/4	1530	12 1/4	311	1800	816.5

[2]For information only, not a requirement as per CSA Standard

Chart continued on the next page

Sizes 2-1/2 (63) and larger shipped in palletized cartons or bulk.
Also available in the following Degrees (60°, 45°, 30°, 22-1/2°, 15° & 11-1/4°)

NOTE: Special orders are non-cancelable, non-returnable and non-refundable


6560 Northwest Drive, Mississauga, Ontario L4V 1P2
Phone / 905.362.0180 • Toll-Free / 866.632.0180
www.columbia-mbf.ca

Electrical Metallic Tubing (EMT) Elbows

Columbia-MBF™
A PART OF atkore INTERNATIONAL

EMT Large Radius 90° Elbows (continued)

Certified to Canadian Standards Association Safety Standard CSA C22.2 No.83.1
Manufactured in accordance with ANSI C80.3



Trade Size	Metric Designator	Radius (A)		Offset (B)[2]		Straight (D) [2]		Approximate Weight Per 100 Pieces	
		in	mm	in	mm	in	mm	lb	kg
3	78	15	381	24 1/4	616	9 1/4	235	921	417.8
3	78	18	457	27 7/8	708	9 7/8	251	1052	477.2
3	78	24	610	34 5/8	879	10 5/8	270	1293	586.5
3	78	30	762	41	1041	11	279	1512	685.8
3	78	36	914	46 3/4	1187	10 3/4	273	1710	775.7
3	78	42	1067	54	1372	12	305	1973	895.0
3	78	48	1219	60 1/4	1530	12 1/4	311	2192	994.3
3 1/2	91	18	457	27 7/8	708	9 7/8	251	1396	633.2
3 1/2	91	24	610	34 5/8	879	10 5/8	270	1716	778.4
3 1/2	91	30	762	41	1041	11	279	2007	910.4
3 1/2	91	36	914	46 3/4	1187	10 3/4	273	2269	1029.2
3 1/2	91	42	1067	54	1372	12	305	2618	1187.5
3 1/2	91	48	1219	60 1/4	1530	12 1/4	311	2908	1319.1
4	103	18	457	27 7/8	708	9 7/8	251	1572	713.1
4	103	24	610	34 5/8	879	10 5/8	270	1932	876.4
4	103	30	762	41	1041	11	279	2260	1025.1
4	103	36	914	46 3/4	1187	10 3/4	273	2555	1158.9
4	103	42	1067	54	1372	12	305	2948	1337.2
4	103	48	1219	60 1/4	1530	12 1/4	311	3275	1485.5

[2]For information only, not a requirement as per CSA Standard
Sizes 2-1/2 (63) and larger shipped in palletized cartons or bulk.
Also available in the following Degrees (60°, 45°, 30°, 22-1/2°, 15° & 11-1/4°)

NOTE: Special orders are non-cancelable, non-returnable and non-refundable

6560 Northwest Drive, Mississauga, Ontario L4V 1P2
Phone / 905.362.0180 • Toll-Free / 866.632.0180
www.columbia-mbf.ca

EMT

Set Screw Fittings

CI5404 (-IT) / CI5408 (-IT)



CI5410 (-IT) / CI5432 (-IT)



c UL us LISTED

Cat. No.		Trade Size (in.)
Regular	Insulated	
EMT Set Screw Fittings (Steel)		
CI5404	CI5404-IT	1/2
CI5406	CI5406-IT	3/4
CI5408	CI5408-IT	1
CI5410	CI5410-IT	1-1/4
CI5412	CI5412-IT	1-1/2
CI5416	CI5416-IT	2
CI5420	CI5420-IT	2-1/2
CI5424	CI5424-IT	3
CI5432	CI5432-IT	4

Concrete-tight

1.3

CI5004 (-IT) / CI5008 (-IT)



CI5010 (-IT) / CI5016 (-IT)



CI5020 (-IT) / CI5032 (-IT)



Cat. No.		Trade Size (in.)
Regular (Zinc)	Insulated (Steel)	
EMT Set Screw Fittings (Zinc)		
CI5004	CI5004-IT	1/2
CI5006	CI5006-IT	3/4
CI5008	CI5008-IT	1
CI5010	CI5010-IT	1-1/4
CI5012	CI5012-IT	1-1/2
CI5016	CI5016-IT	2
CI5020	CI5020-IT	2-1/2
CI5024	CI5024-IT	3
CI5032	CI5032-IT	4

Concrete-tight. Zinc Die Cast Locknut. IT: with insulated throat.

CI5054 / CI5058



Cat. No.	Trade Size (in.)	Offset (in.)
EMT Set Screw Offset Body Fittings (Zinc Alloy)		
CI5054	1/2	3/8
CI5056	3/4	3/4
CI5058	1	3/4

Concrete-tight.

TC121A-FA





Cat. No.		Trade Size (in.)	Std. Pkg. Qty
Regular	Insulated		
EMT / Fire Alarm Set Screw Fittings (Red Steel)			
TC121A-FA	TC721A-FA	1/2	50
TC122A-FA	TC722A-FA	3/4	50
TC123A-FA	TC723A-FA	1	25

EMT

Set Screw Couplings

CI5504 / CI5508



CI5120 / CI5132



CI5104 / CI5116



CI5510 / CI5532



Cat. No.		Trade Size (in.)
Steel	Zinc Alloy	
EMT Set Screw Couplings		
CI5504*	CI5104	1/2
CI5506*	CI5106	3/4
CI5508*	CI5108	1
CI5510*	CI5110	1-1/4
CI5512*	CI5112	1-1/2
CI5516*	CI5116	2
CI5520*	CI5120	2-1/2
CI5524*	CI5124	3
CI5532*	CI5132	4

* cULus Listed only
Concrete-tight

CI5164 / CI5168



Cat. No.	Trade Size (in.)	
	EMT	Rigid
EMT / Rigid Couplings (Zinc Alloy)		
CI5164	1/2	1/2
CI5166	3/4	3/4
CI5168	1	1

Concrete-tight

TK121A-FA





Cat. No.	Trade Size (in.)	Std. Pkg. Qty
EMT / Fire Alarm Set Screw Couplings (Red Steel)		
TK121A-FA	1/2	50
TK122A-FA	3/4	50
TK123A-FA	1	25

EMT

Compression Fittings and Couplings

- Models from 2-1/2 to 4 in. are also suitable for rigid and IMC conduit

TC111A



TC711A



Cat. No.		Trade Size (in.)
Regular	Insulated	
EMT Compression Fittings (Zinc-plated steel)		
TC111A	TC711A	1/2
TC112A	TC712A	3/4
TC113A	TC713A	1
TC114A*	TC714A	1-1/4
TC115A*	TC715A	1-1/2
TC116A*	TC716A	2
TC117A	TC717A	2-1/2
TC118A	TC718A	3
TC119A	TC719A	3-1/2
TC1110A	TC7110A	4

UL FILE NO. E-16592. * O-rings are supplied.
Concrete-tight.

TK111A



Cat. No.	Trade Size (in.)
EMT Compression Couplings (Zinc-plated steel)	
TK111A	1/2
TK112A	3/4
TK113A	1
TK114A	1-1/4
TK115A	1-1/2
TK116A	2
TK117A	2-1/2
TK118A	3
TK119A	3-1/2
TK1110A	4

UL FILE NO. E-16592.
Concrete-tight.

CI5804 (-IT) / CI5832 (-IT)



Zinc Die Cast Locknut
IT: with insulated throat

Cat. No.		Trade Size (in.)
Regular	Insulated	
EMT Compression Fittings (Zinc Alloy)		
CI5804	CI5804-IT	1/2
CI5806	CI5806-IT	3/4
CI5808	CI5808-IT	1
CI5810	CI5810-IT	1-1/4
CI5812	CI5812-IT	1-1/2
CI5816	CI5816-IT	2
CI5820	CI5820-IT	2-1/2
CI5824	CI5824-IT	3
CI5832	CI5832-IT	4

Concrete-tight.

CI5904 / CI5932



Cat. No.	Trade Size (in.)
EMT Compression Couplings (Zinc Alloy)	
CI5904	1/2
CI5906	3/4
CI5908	1
CI5910	1-1/4
CI5912	1-1/2
CI5916	2
CI5920	2-1/2
CI5924	3
CI5932	4

Concrete-tight.

EMT

Wet-location fittings



CI5612-IT-WL





CI5706-WL




CI5620-WL

Specifications

Material: Steel body and steel locknut
Finish: Electro zinc plated
Liner (insulated fittings only): Nylon
Threads: Hub threads (NPS)
Sealing Gasket: Neoprene
Sealing Ring: Nylon
Use: Wet locations, concrete-tight

UL Listed Raintight (File E-16592)
UL514B / CSAC22.2–N°18.3
NEMA FB-1
NEMA 3R



Wet-location EMT compression fittings

Cat. No.	Hub Size (in.)	Dimensions (in.)			Std. Ctn.
		A	B	C	
Non-insulated					
CI5604-WL	½	1.22	0.47	1.14	100
CI5606-WL	¾	1.21	0.48	1.38	50
CI5608-WL	1	1.30	0.50	1.67	25
CI5610-WL	1-¼	1.50	0.60	2.06	25
CI5612-WL	1-½	1.53	0.65	2.27	20
CI5616-WL	2	1.67	0.73	2.77	10
CI5620-WL	2-½	2.77	0.87	3.65	5
CI5624-WL	3	2.75	0.87	4.30	5
CI5632-WL	4	3.12	0.92	5.23	5
Insulated					
CI5604-IT-WL	½	1.22	0.54	1.14	100
CI5606-IT-WL	¾	1.21	0.55	1.38	50
CI5608-IT-WL	1	1.30	0.57	1.67	25
CI5610-IT-WL	1-¼	1.50	0.69	2.06	25
CI5612-IT-WL	1-½	1.53	0.74	2.27	20
CI5616-IT-WL	2	1.67	0.82	2.77	10
CI5620-IT-WL	2-½	2.77	0.99	3.65	5
CI5624-IT-WL	3	2.75	0.99	4.30	5
CI5632-IT-WL	4	3.12	1.04	5.23	5

Wet-location EMT compression couplings

Cat. No.	Hub Size (in.)	Dimensions (in.)			Std. Ctn.
		A	B	C	
CI5704-WL	½	1.94	1.14	–	100
CI5706-WL	¾	2.09	1.38	–	50
CI5708-WL	1	2.31	1.67	–	25
CI5710-WL	1-¼	2.58	2.06	–	25
CI5712-WL	1-½	2.74	2.27	–	20
CI5716-WL	2	2.83	2.77	–	10
CI5720-WL	2-½	4.47	3.65	–	5
CI5724-WL	3	4.70	4.30	–	5
CI5732-WL	4	5.75	5.23	–	5

EMT

Accessories

CI1304 / CI1316



CI1404 / CI1416



CI1520 / CI1532



Cat. No.	Trade Size (in.)	Max. EMT Dia. (in.)	Hole Size (in.)
One Hole EMT Straps (Galvanized Steel)			
CI1304	1/2	0.71	1/4
CI1306	3/4	0.92	1/4
CI1308	1	1.16	5/16
CI1310	1-1/4	1.51	7/16
CI1312	1-1/2	1.74	7/16
CI1316	2	2.20	9/16
Two Hole EMT Straps (Galvanized Steel)			
CI1404	1/2	0.71	3/16
CI1406	3/4	0.92	3/16
CI1408	1	1.16	3/16
CI1410	1-1/4	1.51	1/4
CI1412	1-1/2	1.74	1/4
CI1416	2	2.20	3/8
CI1520	2-1/2	2.88	3/8
CI1524	3	3.50	3/8
CI1528	3-1/2	4.00	1/2
CI1532	4	4.50	1/2

CI5153



CI5154



Cat. No.	Trade Size (in.)		Clamping Range (in.)	
	EMT	Flex.	Min.	Max.
EMT / Flex Couplings (Zinc Alloy)				
CI5153	1/2	3/8	0.17	0.63
CI5154	1/2	1/2	0.75	0.95

CI7538




Cat. No.	Max. Flex. Conduit Dia. (in.)	Hole Size (in.)
One Hole Double Sided Strap (Galvanized Steel)		
CI7538*	1.05	3/16

*Any combination of 3/8 in., 1/2 in. and 3/4 in. EMT, rigid conduit, flexible conduit or teck cables

EMT

Accessories

500-SC / 503-SC



Cat. No.	Trade Size (in.)	Jaw Opening (in.)	Tap Base and Back	Dimensions (in.)		
				A	B	C
Beam Clamps (Malleable Iron)						
500-SC	1/4NC	15/16	1/4-20	1	1-1/4	1-7/16
501	5/16NC	7/8	5/16-18	1-9/16	1-9/16	1-11/16
502	3/8NC	1	3/8-16	2	1-7/8	1-3/4
503-SC	1/2NC	1	1/2-13	2-1/2	2-3/8	2-3/8

CICH-0404 / CICH-3232



Cat. No.	Trade Size (in.)	
	EMT	Rigid
Conduit Hangers-Steel (with nuts & bolts)		
CICH-0404	1/2	1/2
CICH-0606	3/4	3/4
CICH-0808	1	1
CICH-0010	1-1/4	—
CICH-1012	1-1/2	1-1/4
CICH-1200	—	1-1/2
CICH-1616	2	2
CICH-2020	2-1/2	2-1/2
CICH-2424	3	3
CICH-2828	3-1/2	3-1/2
CICH-3232 *	4	4

* Not CSA certified

EMT

Pull Elbows and Conduit Fittings

CI5204 / CI5206



Zinc Die Cast Locknut


CI5304 / CI5306 / CI5308-G / CI5310-G



-G: with gasket.


CICA-1/2 / CICA-2





CILBA-1/2 / CILBA-2 / CILBSA-2-1/2 / CILBSA-4





Cat. No.	Trade Size (in.)	Dimensions (in.)		
		A	B	C
Pull Elbows, EMT to Box (Zinc Alloy)				
CI5204	1/2	1-5/16	1-1/8	—
CI5206	3/4	1-1/2	1-1/4	—
Pull Elbows, EMT to EMT (Zinc Alloy)				
CI5304	1/2	1-5/16	15/16	—
CI5306	3/4	1-5/8	1-1/4	—
CI5308-G	1	1-15/16	1-5/8	—
CI5310-G	1-1/4	2-1/4	2	—
EMT Conduit Fittings - "C" Type (Cast Aluminum)				
CICA-1/2	1/2	4-7/8	1-3/8	1-3/8
CICA-3/4	3/4	5-9/16	1-1/2	1-7/16
CICA-1	1	6-1/2	1-3/4	1-3/4
CICA-1-1/4	1-1/4	8-5/8	1-15/16	2-1/2
CICA-1-1/2	1-1/2	8-5/8	2-11/16	2-1/2
CICA-2	2	10-15/16	3	3-3/16
EMT Conduit Fittings - "LB" Type (Cast Aluminum)				
CILBA-1/2	1/2	4-5/16	1-1/2	1-3/8
CILBA-3/4	3/4	4-15/16	1-7/8	1-9/16
CILBA-1	1	6-1/16	2-1/16	1-13/16
CILBA-1-1/4	1-1/4	7-7/8	2-15/16	2-1/2
CILBA-1-1/2	1-1/2	7-7/8	3-1/16	2-1/2
CILBA-2	2	10	3-3/4	3-3/16
CILBSA-2-1/2 *	2-1/2	13	7-3/8	4-1/4
CILBSA-3 *	3	13	7-3/8	4-1/4
CILBSA-3-1/2 *	3-1/2	15-1/4	9	5-1/4
CILBSA-4 *	4	15-1/4	9	5-1/4

Covers and gaskets are included with all aluminum conduit fittings
Types CICA and CILBA are also suitable for use with rigid conduit (NPSM threads)
* For EMT only, not threaded

EMT

Conduit Fittings, Accessories and Entrance Heads


CILRL-1/2 / CILRL-2




Combined LL/LR
Left and right
application

CITA-1/2 / CITA-2







Cat. No.	Trade Size (in.)	Dimensions (in.)		
		A	B	C
EMT Conduit Fittings - "LRL" Type (Cast Aluminum)				
CILRL-1/2	1/2	4-7/16	1-11/16	2-1/8
CILRL-3/4	3/4	5-3/16	1-7/8	2-1/4
CILRL-1	1	6	2-3/16	2-1/2
CILRL-1-1/4	1-1/4	7-15/16	2-3/4	3-1/2
CILRL-1-1/2	1-1/2	7-15/16	3-1/4	3-1/2
CILRL-2	2	10-3/16	3-11/16	4-1/8
EMT Conduit Fittings - "T" Type (Cast Aluminum)				
CITA-1/2	1/2	4-7/8	1-3/8	2-1/16
CITA-3/4	3/4	5-9/16	1-3/4	2-1/8
CITA-1	1	6-1/2	2	2-1/2
CITA-1-1/4	1-1/4	8-11/16	2-5/8	3-1/2
CITA-1-1/2	1-1/2	8-11/16	3	3-9/16
CITA-2	2	10-7/8	3-1/4	4-3/16

Covers and gaskets are included with all aluminum conduit fittings
Types CILRL and CITA are also suitable for use with rigid conduit (NPSM Threads)

CIBC-1/2 / CIBC-2



Cat. No.	Gros. nom. (in.)
Blank Covers for Aluminum Conduit Fittings (Stamped Aluminum)	
CIBC-1/2	1/2
CIBC-3/4	3/4
CIBC-1	1
CIBC-1-1/4	1-1/4
CIBC-2	2

For 1-1/2, use CIBC-1-1/4
Screws not included

CIG-1/2 / CIG-2



Cat. No.	Trade Size (in.)
Gaskets for Aluminum Conduit Fittings (Neoprene)	
CIG-1/2	1/2
CIG-3/4	3/4
CIG-1	1
CIG-1-1/4	1-1/4
CIG-2	2

For 1-1/2, use CIG-1-1/4

CIEFSA-1/2 / CIEFSA-4



Cat. No.	Trade Size (in.)
Service Entrance Heads (Cast Aluminum)	
CIEFSA-1/2	1/2
CIEFSA-3/4	3/4
CIEFSA-1	1
CIEFSA-1 1/4	1-1/4
CIEFSA-1 1/2	1-1/2
CIEFSA-2	2
CIEFSA-2 1/2	2-1/2
CIEFSA-3	3
CIEFSA-3 1/2	3-1/2
CIEFSA-4	4

Consult page D10 for technical specifications

4 in. Square Boxes

Conduit Knockouts




BC52151-K

Concentric knockouts.



CI52151-KSB

Concentric knockouts.



BC52151-KSSX

Concentric knockouts. “Wraparound” bracket for 2-1/2 in. and 3-5/8 in. steel studs. With integral support bracket.



BC53151-K

Concentric knockouts.

Cat. No.	Volume (Cu. in.)	Features		Knockouts			
		Bracket	Raised Ground Screw	1/2 in. sides	1/2 in. bottom	3/4 in. sides	3/4 in. bottom
1-1/2 in. Deep							
BC52151-K	21.0	-	yes	10	4	6	2
CI52151-KSB	21.0	“SB”	yes	8	4	4	2
BC52151-KSSX	21.0	“SSX”	yes	7	4	3	2
BC53151-K	21.0	-	-	10	-	6	-

4 in. Square Boxes


Conduit Knockouts



BC52171-HV-KIT



BC52171-KSSXHVKIT



CI52171-1-SSX-1

"Wraparound" bracket for 2-1/2 in. and 3-5/8 in. steel studs.
With integral support bracket.
Present for 2 x 1/2 in. drywall thickness.



CI52171-1




BC52171-K

Concentric knockouts.




CI52171-KSB

Concentric knockouts.




BC52171-KSSX

Concentric knockouts. "Wraparound" bracket for 2-1/2 in. and 3-5/8 in. steel studs.
With integral support bracket.
Present for 1 x 1/2 in. drywall thickness.



CI52171-KSSX-1

Concentric knockouts. "Wraparound" bracket for 2-1/2 in. and 3-5/8 in. steel studs.
With integral support bracket.
Present for 2 x 1/2 in. drywall thickness.



BC53171-K

Concentric knockouts.

Cat. No.	Volume (Cu. in.)	Features		Knockouts				
		Bracket	Raised Ground Screw	1/2 in. sides	1/2 in. bottom	3/4 in. sides	3/4 in. bottom	1 in. sides
2-1/8 in. Deep								
BC52171-HV-KIT	33.6	-	yes	6	-	2	-	-
BC52171-KSSXHVKIT	33.6	"SSX"	yes	6	-	2	-	-
CI52171-1	30.0	-	yes	-	4	-	2	4
CI52171-1-SSX	21.0	"SSX"	yes	-	4	-	2	2
CI52171-1-SSX-1	21.0	"SSX"	yes	-	4	-	2	2
BC52171-K	30.0	-	yes	10	4	6	2	-
CI52171-KSB	30.0	"SB"	yes	8	4	4	2	-
BC52171-KSSX	30.0	"SSX"	yes	7	4	3	2	-
CI52171-KSSX-1	30.0	"SSX"	yes	7	4	3	2	-
BC53171-K	30.0	-	-	10	-	6	-	-

4 in. Square Boxes

Covers



BC52-C-1



BC52-C-6



CI52-C-3




BC52-C-0



CI52-C-10 to CI-52-C-62



BC52-C-0-B



BC52-C-00




BC52-C-17 to CI52-C-18-5/8

Cat. No.	Description
Flat Covers	
BC52-C-1	Blank
BC52-C-6	1/2 in. conduit knockout
Plaster Ring Cover	
CI52-C-3	Raised 1/2 in. (3.4 cu. in.) Tapped ears on 2-3/4 in. centers
Single Device Covers	
BC52-C-0	Flat
BC52-C-0-B	Flat blank cover
CI52-C-10	Raised 1/8 in. (1.0 cu. in.)
BC52-C-13	Raised 1/2 in. (3.6 cu. in.)
CI52-C-14	Raised 3/4 in. (5.7 cu. in.)
CI52-C-14-5/8	Raised 5/8 in. (4.3 cu. in.)
CI52-C-15	Raised 7/8 in. (6.8 cu. in.)
CI52-C-16	Raised 1-1/4 in. (9.5 cu. in.)
CI52-C-62	Raised 1/4 in. (1.8 cu. in.)
Two Device Covers	
BC52-C-00	Flat
BC52-C-17	Raised 1/2 in. (6.2 cu. in.)
CI52-C-18	Raised 3/4 in. (10.3 cu. in.)
CI52-C-18-5/8	Raised 5/8 in. (8.3 cu. in.)


1.4

4 in. Square Boxes


Covers



BC52C49-1/2 to CI52-C-51-2



52 C 52 1/2 to 52 C 54 2



52CADJ


Cat. No.	Description
One Device Square Cornered Tile Covers	
BC52C49-1/2	Raised 1/2 in. (3.4 cu. in.)
BC52C49-3/4	Raised 3/4 in. (5.3 cu. in.)
BC52-C-49-5/8	Raised 5/8 in. (4.3 cu. in.)
BC52-C-49-1	Raised 1 in. (6.8 cu. in.)
CI52-C-49-1 1/4	Raised 1-1/4 in. (8.6 cu. in.)
CI52-C-50-1 1/2	Raised 1-1/2 in. (10.0 cu. in.)
CI52-C-51-2	Raised 2 in. (14.0 cu. in.)
One Device Square Cornered Tile Covers - Adjustable	
52CADJ	Adjustable from 1/2 in. to 1-1/2 in. raise (from 3.4 to 10.0 cu. in.)
Two Device Square Cornered Tile Covers	
52 C 52 1/2	Raised 1/2 in. (6.0 cu. in.)
52 C 52 5/8	Raised 5/8 in. (8.3 cu. in.)
52 C 52 3/4	Raised 3/4 in. (9.0 cu. in.)
52 C 52 1	Raised 1 in. (12.5 cu. in.)
52 C 52 1 1/4	Raised 1-1/4 in. (15.5 cu. in.)
52 C 53 1 1/2	Raised 1-1/2 in. (19.0 cu. in.)
52 C 54 2	Raised 2 in. (25.5 cu. in.)

4 in. Square Boxes

Covers



BC8361 | BC8362 | BC8363



BC8364 | BC8365 | BC8366 | BC8367


Cat. No.	Description
3/8 in. Raised Surface Covers (4.6 cu. in.) **Device Mount**	
BC8361	One toggle switch
BC8362	For 2-5/8 in. diameter 30 / 50 A single receptacle
BC8363	For 1-13/32 in. diameter 15 A single receptacle
BC8364	For 1-19/32 in. diameter 20 / 30 A single locking receptacle
BC8365	One duplex receptacle
BC8366	For 2-9/64 in. diameter 30 A single receptacle
BC8367	Two toggle switches


Complete with device mounting screws

NEMA Configuration							
Cover	A	V	Pole	Wire	Phase	Rec. Dia	NEMA
BC8363	15	125	2	3	1	1.406	5-15R
BC8364	20	125	2	3	1	1.562	L5-20R
BC8364	20	250	2	3	1	1.562	L6-20-R
BC8364	20	347	2	3	1	1.562	L24-20R
BC8364	20	600	2	3	1	1.562	L9-20R
BC8364	20	125/250	3	3	1	1.562	L10-20R
BC8364	20	250	3	3	3	1.562	L11-20R
BC8364	20	125/250	3	4	3	1.562	L14-20R
BC8366	30	125	2	3	1	2.109	5-30R
BC8364	30	125	2	3	1	1.562	L5-30R
BC8366	30	250	2	3	1	2.109	6-30R
BC8364	30	250	2	3	1	1.562	L6-30R
BC8362	30	125/250	3	4	3	2.647	14-30R
BC8362	50	125/250	3	4	1	2.647	14-50R


4 in. Square Boxes

Covers



BC8368



BC8371


BC8375


BC8376


BC8377


BC8378


BC97002

Cat. No.	Description
3/8 in. Raised Surface Covers (4.6 cu. in.)	
BC8368	2 Decora/GFCI
BC8371	Two duplex receptacles
BC8375	One toggle switch, one duplex receptacle
BC8376	One Decora/GFCI
BC8377	One toggle switch, one Decora/GFCI
BC8378	One duplex receptacle, one Decora/GFCI
GFCI Conversion Kits (Stainless Steel / Steel)	
BC97002	To install GFCI on 4 in. square boxes. Complete with mounting screws

Complete with device mounting screws
When extra capacity is required, the 8300 Series of 4 in. square covers can be mounted on a 72 Series of 4-11/16 in. square boxes using a CI72-A-52 adaptor. (see page A41)

4 in. Square Boxes

Conduit Knockouts




BC52151-K

Concentric knockouts.



CI52151-KSB

Concentric knockouts.



BC52151-KSSX

Concentric knockouts. "Wraparound" bracket for 2-1/2 in. and 3-5/8 in. steel studs. With integral support bracket.



BC53151-K

Concentric knockouts.

Cat. No.	Volume (Cu. in.)	Features		Knockouts			
		Bracket	Raised Ground Screw	1/2 in. sides	1/2 in. bottom	3/4 in. sides	3/4 in. bottom
1-1/2 in. Deep							
1.5 BC52151-K	21.0	-	yes	10	4	6	2
CI52151-KSB	21.0	"SB"	yes	8	4	4	2
BC52151-KSSX	21.0	"SSX"	yes	7	4	3	2
BC53151-K	21.0	-	-	10	-	6	-

4 in. Square Boxes


Conduit Knockouts



BC52171-HV-KIT



BC52171-KSSXHVKIT



CI52171-1-SSX-1

"Wraparound" bracket for 2-1/2 in. and 3-5/8 in. steel studs.
With integral support bracket.
Present for 2 x 1/2 in. drywall thickness.



CI52171-1




BC52171-K

Concentric knockouts.




CI52171-KSB

Concentric knockouts.




BC52171-KSSX

Concentric knockouts. "Wraparound" bracket for 2-1/2 in. and 3-5/8 in. steel studs.
With integral support bracket.
Present for 1 x 1/2 in. drywall thickness.



CI52171-KSSX-1

Concentric knockouts. "Wraparound" bracket for 2-1/2 in. and 3-5/8 in. steel studs.
With integral support bracket.
Present for 2 x 1/2 in. drywall thickness.



BC53171-K

Concentric knockouts.

Cat. No.	Volume (Cu. in.)	Features		Knockouts				
		Bracket	Raised Ground Screw	1/2 in. sides	1/2 in. bottom	3/4 in. sides	3/4 in. bottom	1 in. sides
2-1/8 in. Deep								
BC52171-HV-KIT	33.6	-	yes	6	-	2	-	-
BC52171-KSSXHVKIT	33.6	"SSX"	yes	6	-	2	-	-
CI52171-1	30.0	-	yes	-	4	-	2	4
CI52171-1-SSX	21.0	"SSX"	yes	-	4	-	2	2
CI52171-1-SSX-1	21.0	"SSX"	yes	-	4	-	2	2
BC52171-K	30.0	-	yes	10	4	6	2	-
CI52171-KSB	30.0	"SB"	yes	8	4	4	2	-
BC52171-KSSX	30.0	"SSX"	yes	7	4	3	2	-
CI52171-KSSX-1	30.0	"SSX"	yes	7	4	3	2	-
BC53171-K	30.0	-	-	10	-	6	-	-

4 in. Square Boxes

Covers



BC52-C-1



BC52-C-6



CI52-C-3




BC52-C-0



CI52-C-10 to CI-52-C-62



BC52-C-0-B



BC52-C-00




BC52-C-17 to CI52-C-18-5/8


Cat. No.	Description
Flat Covers	
BC52-C-1	Blank
BC52-C-6	1/2 in. conduit knockout
Plaster Ring Cover	
CI52-C-3	Raised 1/2 in. (3.4 cu. in.) Tapped ears on 2-3/4 in. centers
Single Device Covers	
BC52-C-0	Flat
BC52-C-0-B	Flat blank cover
CI52-C-10	Raised 1/8 in. (1.0 cu. in.)
BC52-C-13	Raised 1/2 in. (3.6 cu. in.)
CI52-C-14	Raised 3/4 in. (5.7 cu. in.)
CI52-C-14-5/8	Raised 5/8 in. (4.3 cu. in.)
CI52-C-15	Raised 7/8 in. (6.8 cu. in.)
CI52-C-16	Raised 1-1/4 in. (9.5 cu. in.)
CI52-C-62	Raised 1/4 in. (1.8 cu. in.)
Two Device Covers	
BC52-C-00	Flat
BC52-C-17	Raised 1/2 in. (6.2 cu. in.)
CI52-C-18	Raised 3/4 in. (10.3 cu. in.)
CI52-C-18-5/8	Raised 5/8 in. (8.3 cu. in.)

4 in. Square Boxes


Covers



BC52C49-1/2 to CI52-C-51-2



52 C 52 1/2 to 52 C 54 2



52CADJ


Cat. No.	Description
One Device Square Cornered Tile Covers	
BC52C49-1/2	Raised 1/2 in. (3.4 cu. in.)
BC52C49-3/4	Raised 3/4 in. (5.3 cu. in.)
BC52-C-49-5/8	Raised 5/8 in. (4.3 cu. in.)
BC52-C-49-1	Raised 1 in. (6.8 cu. in.)
CI52-C-49-1 1/4	Raised 1-1/4 in. (8.6 cu. in.)
CI52-C-50-1 1/2	Raised 1-1/2 in. (10.0 cu. in.)
CI52-C-51-2	Raised 2 in. (14.0 cu. in.)
One Device Square Cornered Tile Covers - Adjustable	
52CADJ	Adjustable from 1/2 in. to 1-1/2 in. raise (from 3.4 to 10.0 cu. in.)
Two Device Square Cornered Tile Covers	
52 C 52 1/2	Raised 1/2 in. (6.0 cu. in.)
52 C 52 5/8	Raised 5/8 in. (8.3 cu. in.)
52 C 52 3/4	Raised 3/4 in. (9.0 cu. in.)
52 C 52 1	Raised 1 in. (12.5 cu. in.)
52 C 52 1 1/4	Raised 1-1/4 in. (15.5 cu. in.)
52 C 53 1 1/2	Raised 1-1/2 in. (19.0 cu. in.)
52 C 54 2	Raised 2 in. (25.5 cu. in.)

4 in. Square Boxes

Covers



BC8361 | BC8362 | BC8363



BC8364 | BC8365 | BC8366 | BC8367


Cat. No.	Description
3/8 in. Raised Surface Covers (4.6 cu. in.) **Device Mount**	
BC8361	One toggle switch
BC8362	For 2-5/8 in. diameter 30 / 50 A single receptacle
BC8363	For 1-13/32 in. diameter 15 A single receptacle
BC8364	For 1-19/32 in. diameter 20 / 30 A single locking receptacle
BC8365	One duplex receptacle
BC8366	For 2-9/64 in. diameter 30 A single receptacle
BC8367	Two toggle switches


Complete with device mounting screws

NEMA Configuration							
Cover	A	V	Pole	Wire	Phase	Rec. Dia	NEMA
BC8363	15	125	2	3	1	1.406	5-15R
BC8364	20	125	2	3	1	1.562	L5-20R
BC8364	20	250	2	3	1	1.562	L6-20-R
BC8364	20	347	2	3	1	1.562	L24-20R
BC8364	20	600	2	3	1	1.562	L9-20R
BC8364	20	125/250	3	3	1	1.562	L10-20R
BC8364	20	250	3	3	3	1.562	L11-20R
BC8364	20	125/250	3	4	3	1.562	L14-20R
BC8366	30	125	2	3	1	2.109	5-30R
BC8364	30	125	2	3	1	1.562	L5-30R
BC8366	30	250	2	3	1	2.109	6-30R
BC8364	30	250	2	3	1	1.562	L6-30R
BC8362	30	125/250	3	4	3	2.647	14-30R
BC8362	50	125/250	3	4	1	2.647	14-50R


4 in. Square Boxes

Covers



BC8368



BC8371


BC8375


BC8376


BC8377



BC8378


BC97002


Cat. No.	Description
3/8 in. Raised Surface Covers (4.6 cu. in.)	
BC8368	2 Decora/GFCI
BC8371	Two duplex receptacles
BC8375	One toggle switch, one duplex receptacle
BC8376	One Decora/GFCI
BC8377	One toggle switch, one Decora/GFCI
BC8378	One duplex receptacle, one Decora/GFCI
GFCI Conversion Kits (Stainless Steel / Steel)	
BC97002	To install GFCI on 4 in. square boxes. Complete with mounting screws

Complete with device mounting screws
When extra capacity is required, the 8300 Series of 4 in. square covers can be mounted on a 72 Series of 4-11/16 in. square boxes using a CI72-A-52 adaptor. (see page A41)

Utility Boxes and Covers



CI2018 | CI2018-SB | BC2020 | BC2020-R



BC20-C-1 | BC20-C-3 | BC20-C-4 | BC20-C-5

Cat. No.	Volume (Cu. in.)	Features		Knockouts		
		Bracket	Raised Ground Screw	1/2 in. ends	1/2 in. bottom	1/2 in. sides
1-1/2 in. Deep — 4 in. x 2-1/4 in.						
CI2018	13.0	-	no	2	2	6
CI2018-SB	13.0	"SB"	no	2	2	3
1-7/8 in. Deep — 4 in. x 2-1/8 in.						
BC2020	14.0	-	yes	2	2	6
BC2020-R	14.0	-	-	2	-	6

Cat. No.	Description
Covers — 20 Series	
BC20-C-1	For duplex receptacle
BC20-C-3	For 1-13/32 in. diameter 15 A single receptacle
BC20-C-4	Blank
BC20-C-5	For toggle switch

1.6

Note: BC2020-R can be installed on CI2018 / BC2020 Series Covers: Device mounting screws included

Utility Boxes and Covers



Cat. No.	Volume (Cu. in.)	Features		Knockouts		
		Bracket	Raised Ground Screw	1/2 in. ends	1/2 in. bottom	1/2 in. sides
1-1/2 in. Deep – 4 in. x 2-1/4 in.						
CI1141	13.0	mounting ears	no	2	2	6
1-7/8 in. Deep – 4 in. x 2-3/8 in.						
BC1110	16.5	-	yes	2	2	6
CI1110-SB	16.5	"SB"	yes	2	2	3
BC1110-R	16.5	-	-	2	-	6
2-1/8 in. Deep – 4 in. x 2-1/2 in.						
1151	18.5	-	yes	2	2	-
1198	18.5	-	yes	2	2	-
1199	18.5	-	yes	2	2	-
1-7/8 in. Deep – 4 in. x 2-3/8 in.						
BC1110-LSKO	16.5	-	yes	2	2	-
BC1110-SSX	16.5	"SSX"	yes	2	2	-

Cat. No.	Description	Cat. No.	Description
Covers – 11 Series			
BC11-C-1	For duplex receptacle	BC11-C-10	Decora/GFCI
BC11-C-2	For 1-19/32 in. diameter 20 A single locking receptacle	CI11-C-10-HV	Decora 347 V
BC11-C-3	For 1-13/32 in. diameter 15 A single receptacle	BC11-C-4-HV	Blank 347 V
BC11-C-4	Blank	BC11-C-5-HV	For toggle switch
BC11-C-5	For toggle switch		

Note: Covers: Device mounting screws included

Câbles armés et conduits flexibles

Connecteurs

CI70




Contre-écrou
en zinc moulé

L-16



Contre-écrou
en zinc moulé

CI71 / CI73



Contre-écrou
en zinc moulé

CI2175



Contre-écrou
en zinc moulé

CI2210 / CI2236



Contre-écrou
en zinc moulé

CI2238 / CI2240



Contre-écrou
en zinc moulé

CI4090



Contre-écrou
en aluminium

1.7

N° de cat.	Grosseur nom. (po)	Gamme de serrage (po)		Applications suggérées	Conduit flexible
		Min.	Max.	AC90 (BX)	
Connecteurs à une vis (alliage de zinc)					
L-16	3/8	0,12	0,63	14/2-10/2-14/3-10/3-14/4-10/4	5/16-3/8
CI70	3/8	0,13	0,70	14/2, 12/2, 10/2, 14/3, 12/3, 10/3, 14/4	3/8
CI71	1/2	0,33	0,95	14/2-10/2; 14/3-10/3; 14/4-8/4	5/16, 3/8, 1/2
CI72	3/4	0,60	1,15	6/2; 8/3-3/3; 8/4-3/4	1/2, 3/4
CI73	1	0,93	1,47	3/3-3/0/3; 2/4-1/4	3/4, 1
Connecteurs doubles (alliage de zinc)					
CI2175	3/8	0,15	0,65	14/2-10/2; 14/3-10/3; 14/4-12/4	3/8
Connecteurs coudés à 90° (alliage de zinc)					
CI2210	3/8	0,40	0,63	14/2-10/2; 14/3-10/3 14/4-12/4	3/8
CI2211	1/2	0,65	0,97	8/2; 8/3; 10/4	1/2
CI2214	3/4	0,77	1,12	1/0/1-4/0/1; 6/2-4/2; 8/3-3/3; 8/4-6/4	3/4
CI2216	1	1,06	1,40	4/0/1-350/1; 2/2; 4/3-2/3; 6/4-4/4	1
CI2218	1-1/4	1,34	1,65	500/1-750/1; 1/3-3/0/3; 1/4-1/0/4	1-1/4
CI2234	1-1/2	1,70	2,15	600/1-1000/1; 2/0/3; 1/4-3/0/4	1-1/2
CI2236	2	1,51	2,47	600/1-1000/1; 2/0/3-400/3; 1/4-4/0/4	1-1/2 - 2
Connecteurs coudés à 90° (aluminium)					
CI2238	2-1/2	2,50	3,08	600/3-750/3	2-1/2
CI2240	3	2,95	3,55	1000/3	3
CI4090	4	4,17	4,62	—	4

Utilisés en emplacements secs, ces connecteurs conviennent également aux câbles ACWU90 de diamètres équivalents. Un connecteur et un contre-écrou non ferreux doivent servir au raccord de câbles à monoconducteur lorsque le courant nominal est de plus de 200 ampères.

REMARQUE: Les connecteurs de grosseur nominale de 3/8 po se posent sur une débouchure de 1/2 po.

Dans l'industrie électrique, les améliorations techniques sont chose de tous les jours. Il en va donc de soi que les fabricants de câbles modifient leurs produits de temps à autre. Pour cette raison, il est fortement recommandé de vérifier la grosseur des câbles auprès du fabricant avant de faire le choix d'un connecteur.

Voir le guide technique pour les dimensions (D38-D39).

Utility Boxes and Covers



CI2018




CI2018-SB




BC2020



BC2020-R



BC20-C-1



BC20-C-3



BC20-C-4



BC20-C-5

Cat. No.	Volume (Cu. in.)	Features		Knockouts		
		Bracket	Raised Ground Screw	1/2 in. ends	1/2 in. bottom	1/2 in. sides
1-1/2 in. Deep — 4 in. x 2-1/4 in.						
CI2018	13.0	-	no	2	2	6
CI2018-SB	13.0	"SB"	no	2	2	3
1-7/8 in. Deep — 4 in. x 2-1/8 in.						
1.8 BC2020	14.0	-	yes	2	2	6
BC2020-R	14.0	-	-	2	-	6

Cat. No.	Description
Covers — 20 Series	
BC20-C-1	For duplex receptacle
BC20-C-3	For 1-13/32 in. diameter 15 A single receptacle
BC20-C-4	Blank
BC20-C-5	For toggle switch

Note: BC2020-R can be installed on CI2018 / BC2020 Series Covers: Device mounting screws included

Utility Boxes and Covers




Cat. No.	Volume (Cu. in.)	Features		Knockouts		
		Bracket	Raised Ground Screw	1/2 in. ends	1/2 in. bottom	1/2 in. sides
1-1/2 in. Deep – 4 in. x 2-1/4 in.						
CI1141	13.0	mounting ears	no	2	2	6
1-7/8 in. Deep – 4 in. x 2-3/8 in.						
BC1110	16.5	-	yes	2	2	6
CI1110-SB	16.5	"SB"	yes	2	2	3
BC1110-R	16.5	-	-	2	-	6
2-1/8 in. Deep – 4 in. x 2-1/2 in.						
1151	18.5	-	yes	2	2	-
1198	18.5	-	yes	2	2	-
1199	18.5	-	yes	2	2	-
1-7/8 in. Deep – 4 in. x 2-3/8 in.						
BC1110-LSKO	16.5	-	yes	2	2	-
BC1110-SSX	16.5	"SSX"	yes	2	2	-

Cat. No.	Description	Cat. No.	Description
Covers – 11 Series			
BC11-C-1	For duplex receptacle	BC11-C-10	Decora/GFCI
BC11-C-2	For 1-19/32 in. diameter 20 A single locking receptacle	CI11-C-10-HV	Decora 347 V
BC11-C-3	For 1-13/32 in. diameter 15 A single receptacle	BC11-C-4-HV	Blank 347 V
BC11-C-4	Blank	BC11-C-5-HV	For toggle switch
BC11-C-5	For toggle switch		

Note: Covers: Device mounting screws included

Type ABR



Trade Size (in.)	Cat. No.	Coil Length (m)	Cat. No.	Coil Length (m)	Cat. No.	Coil Length (m)	Cat. No.	Reel Content* (m)	Wt. kg/30m
-	-	-	-	-	**ABR716-30**	30	**ABR716-300**	300	-
3/8	**ABR038-8†**	8	**ABR038-15†**	15	**ABR038-30†**	30	**ABR038-300†**	300	7.0
1/2	**ABR050-8**	8	**ABR050-15**	15	**ABR050-30**	30	**ABR050-300**	300	9.5
3/4	**ABR075-8**	8	**ABR075-15**	15	**ABR075-30**	30	**ABR075-150**	150	13.5
1	-	-	**ABR100-15**	15	-	-	**ABR100-120**	120	24.0
1-1/4	-	-	**ABR125-15**	15	-	-	**ABR125-120**	120	31.0
1-1/2	-	-	**ABR150-8**	8	-	-	**ABR150-90**	90	47.0
2	-	-	**ABR200-8**	8	-	-	**ABR200-45**	45	67.0
2-1/2	-	-	**ABR250-8**	8	-	-		-	92.0
3	-	-	**ABR300-8**	8	-	-		-	107.0
3-1/2	-	-	**ABR350-8**	8	-	-		-	122.0
4	-	-	**ABR400-8**	8	-	-		-	142.0

1.9

See Chart on p.153 for dimensions and tolerances.
** See p.153 for label and packaging detail.*
Note: Dimensions and Bend Radii are identical to Type BR, p. 140.
† CSA Certified.


Type ABR
This non-jacketed flexible aluminum conduit has many universal wiring applications. It is often referred to as "Greenfield" or "Reduced Wall Flex".

Construction
Type ABR is formed using a high strength aluminum alloy strip. The result is a conduit with similar characteristics to those of type BR steel but at about 1/3 the weight.

Applications
General Use:
In accordance with CEC Rule 12-1002 (1) the flexible metal conduit is permitted in or on buildings of either combustible or non-combustible constructions.
Restriction and Exception:
CEC Rule 12-1004 (a) states:"12 (3/8) trade size flexible metal conduit shall be permitted to be used for runs of not more than 1.5 m (5 ft) for the connection of equipment." and CEC Rule 12-1004 (b) states:"12 (3/8) trade size liquidtight flexible conduit may be used as permitted by this code."
Securements with straps:
CEC Rule 12-1010 (3) states: "When flexible metal conduit is installed, it shall be secured at intervals not exceeding 1.5 m (5 ft) and within 300 mm (12 in.) on each side of every outlet box or fitting except where flexible metal conduit is fished and except for lengths of not over 900 mm (3 ft) at terminals where flexibility is necessary."
Conductor fill:
CEC Rule 12-1014 defines the maximum number of conductor, the CEC Tables 6 provides the maximum number of conductors of one size in trade sizes of conduit, CEC Table 8 provides the maximum allowable per cent conduit fill, and CEC Table 9 provides the cross-sectional areas of conduit.
Applications: refer to Type BR, p. 140.

Listing / Certification
Listed. (sizes 3/8 through 3 in.). Conforms to UL Standard ANSI/UL-1 for Flexible Metal Conduit.
Certified. (**3/8 inch size only**). Conforms to CSA 22.2 No. 56 for use per CEC C22.1 Section 12-1300.
Meets Federal Specification WW-C-566c Type II

Type ABRH



Trade Size	CSA Metric Desig.	T&B Type	Internal Diameter (in.) Min.	Internal Diameter (in.) Max.	Outer Diameter (in.) Min.	Outer Diameter (in.) Max.	Inside Bend Radius	WT. Lbs. per 100 Ft.	Coil Lenght Mtr.
3/8	12	**ABRH038**	0.375	0.393	0.560	0.610	2	7	30, 150, 300
7/16	14	**ABRH716**	0.437	0.457	-	0.675	2.25	8	30, 150, 300
1/2	16	**ABRH050**	0.625	0.645	0.860	0.920	3	16	30, 150, 300
3/4	21	**ABRH075**	0.812	0.835	1.045	1.105	4	18	30, 150, 300
1	27	**ABRH100**	1.000	1.040	1.300	1.380	5	35	15, 120
1-1/4	35	**ABRH125**	1.250	1.300	1.550	1.630	6.2	43	15, 120
1-1/2	41	**ABRH150**	1.500	1.575	1.850	1.950	7.5	55	8, 15, 30
2	53	**ABRH200**	2.000	2.080	2.350	2.454	10	73	8, 15
2-1/2	63	**ABRH250**	2.500	2.700	2.860	3.060	12.5	90	8, 15
3	78	**ABRH300**	3.000	3.200	3.360	3.560	15	107	8, 15
4	103	**ABRH400**	4.000	-	4.360	4.560	20	142	8, 15

TYPE - ABRH
This non-jacketed flexible aluminum conduit has many universal wiring applications.

Construction
Type ABRH is formed from a heavy gauge aluminum strip. Its profile and helical shape allow it to withstand substantial impact and crushing forces.

Applications
This conduit is intended as a metal raceway for wires and cable where CSA Certification is required. Suitable for use with connectors intended for "FMC (Flexible Metal Conduit).

Certified
File # LL 18858 Conforms to CSA 22.2 No. 56 for use per the Canadian Electrical Code C22.1 Section 12-1300.

Rigid PVC Conduit Pipe & Fittings

A system for residential, industrial, commercial and institutional applications.







ROYAL® Electrical Solutions

ROYAL Electrical Solutions

Table of Contents



Product Description - Features and Benefits	1
Installation Guidelines - Solvent Welding Joints	2
Solvent Welding Joints/Pipe Dimensions/Specs	3
Solvent Cementing	4
Expansion and Contraction	5
Setting the Piston Opening	6
Fittings - Bends (Bell End)	7-8
Fittings - Miscellaneous	9-18

Note: This brochure is not intended to assume the authority of the Design Engineer. Actual jobsite conditions will vary significantly. The sole responsibility for all design and installation decisions lies with the Design Engineer. All local health and safety regulations must be followed.

Rigid PVC Conduit Pipe & Fittings

A system for residential, industrial, commercial and institutional applications.

Product Description & Applications

Royal Building Products® Electrical Solutions manufactures a complete line of Rigid PVC Conduit pipe and fittings for electrical applications. Our products are designed to reduce labour and maintenance costs, while offering superior performance.

Products are certified by the Canadian Standards Association (CSA) and Underwriters Laboratories (UL) for use in above and below ground applications. Our Rigid PVC conduit pipe and fittings are available in 12 to 150mm (½- to 6-inch) diameters and 3- or 6-metre (10- or 20-foot) lengths.

Standards and Codes

Royal Electrical Solutions Rigid PVC Conduit pipe and fittings are certified to CSA Standards as noted below. Our Rigid PVC conduit pipe and fittings shall be installed according to the Canadian Electrical Code (CEC) Part I, Rules 12-1100 - 12-1122 and the National Electrical Code (NEC) Article 352.

Pipe	Fittings
C22.2 No. 211.2	C22.2 No. 18.2, 85 (Boxes) No. 40 (Electrical Encl.) No. 42.1 (Covers) No. 85 (Fittings)
UL 651	UL 514C (Boxes) UL 50 (Electrical Encl.) UL 514D (Covers) UL 651 (Fittings)
Conforms to NEMA TC2	





Features and Benefits

Saves Labour

Rigid PVC Conduit pipe and fittings are easy to install, cut and join.

Easy Wire Pulls

The conduit's smooth interior surface reduces friction and prevents damage to wires when pulling wire and conductors for long runs and even through 90° bends.

Lightweight Materials

Rigid PVC Conduit is easier to move and handle because it is approximately one-fifth the weight of steel and half the weight of aluminum.

Approximate Weight Comparison

Size mm (in)	PVC lb/100ft (kg/m)	Aluminum lb/100ft (kg/m)	Steel lb/100ft (kg/m)
12 (½)	16.1 (0.24)	27 (0.40)	79 (1.20)
19 (¾)	21.5 (0.32)	37 (0.55)	105 (1.55)
25 (1)	31.9 (0.47)	53 (0.80)	153 (2.30)
32 (1¼)	43.8 (0.65)	70 (1.05)	201 (3.00)
38 (1½)	52.3 (0.78)	86 (1.30)	249 (3.70)
50 (2)	70.3 (1.05)	116 (1.75)	334 (5.00)
63 (2½)	112.0 (1.61)	183 (2.75)	527 (7.85)
75 (3)	146.7 (2.18)	239 (3.55)	690 (10.25)
90 (3½)	176.4 (2.63)	288 (4.30)	831 (12.40)
100 (4)	208.9 (3.11)	340 (5.10)	982 (14.60)
125 (5)	283.4 (4.22)	465 (6.90)	1,344 (20.40)
150 (6)	368.0 (5.48)	613 (9.10)	1,771 (26.35)

Simplifies Direct Burial

Royal Electrical Solutions Rigid PVC Conduit does not require additional protection for direct burial installations according to the Canadian Electrical Code (CEC) and the National Electrical Code (NEC). Normal construction practices should be followed for trenching and backfill operations.

Non-Conductive

Rigid PVC Conduit is non-conductive.

Long Life

Royal Rigid PVC Conduit and fittings resist acids, alkalis, salt solutions and most other chemicals. (Refer to the Royal Chemical Resistance Guide for detailed information.) There is no risk of corrosion when exposed to naturally corrosive soil conditions, electrochemical or galvanic environments. Royal's Rigid PVC Conduit has achieved sunlight resistance as per the requirements of the Electrical Code.

FT-4 Rating

Rigid PVC Conduit pipe has an FT-4 Rating and can be used in non-combustible construction as per Part 3 of the National Building Code of Canada (NBC).

Installation Guidelines

Cutting

Royal Rigid PVC Conduit can easily be cut with a hacksaw, a fine-toothed handsaw or PVC conduit cutters. For conduit with more than a 50mm (2-inch) diameter, use a mitre box or saw guide to ensure a square cut. Deburr the end using a knife or file.

Bending

It may be necessary to create bends in the field by heating and deforming Rigid PVC Conduit. To accomplish this, the following guidelines should be followed:

• For heating the Rigid PVC Conduit, use a heat gun or some other flameless heat source. Do not use an open flame to heat the conduit. Rigid PVC Conduit must be heated to approximately 127°C (260°F) in order to bend without kinking.

• Heat a length of conduit equal to approximately 10 times the nominal diameter.

• Once the Rigid PVC Conduit has been adequately heated, bend it to the required angle plus 3 extra degrees. The additional angle will accommodate the "spring back" which will occur during cooling.

• After bending of the conduit is completed, immediately cool the bend using water or cold air.

• According to the Canadian Electrical Code (CEC) and the National Electrical Code (NEC), the minimum bending radius for rigid conduit is as shown in the table below.

Nominal Size mm (in)	Min. Radius to Centre of Conduit or Tubing mm (in)
16 (½)	102 (4.016)
21 (¾)	114 (4.489)
27 (1)	146 (5.748)
35 (1¼)	184 (7.244)
41 (1½)	210 (8.268)
53 (2)	241 (9.488)
63 (2½)	267 (10.512)
78 (3)	330 (12.992)
91 (3½)	381 (14.606)
103 (4)	406 (15.984)
129 (5)	610 (24.016)
155 (6)	762 (30.000)





Procedure for Solvent Welding Joints

• Use solvent cement and primer prior to expiration date marked on container.
• Above 0° C ambient temperature, joints may be assembled without the use of primer, provided adequate penetration and softening of the pipe/fitting surface can be achieved with solvent cement alone.


1. Assemble materials for the job, including correct solvent cement, primer and correctly sized applicator.

2. Cut pipe as square as possible using a hand saw and miter box or mechanical saw. Do not use a diagonal cut, as it reduces the bonding area in the joint.

3. If plastic tubing cutters are used, care must be taken to remove any raised bead at the end of the pipe, caused by cutting. A file or reamer may be used to remove the bead.

4. Use a knife, file or reamer to remove burrs from the inside and outside of the pipe end, as these will hinder the integrity of the joint. All sharp edges should be removed from the inside and outside edges of the pipe to prevent the pipe from pushing the solvent cement into the fitting socket, thereby causing a weak spot to form. The pipe end should be chamfered, as shown below.

Chamfered Pipe



Procedure for Solvent Welding Joints Continued

5. All dirt, grease and moisture should be removed from the pipe and socket by thoroughly wiping with a clean, dry cloth.

6. Dry fit pipe and fitting joints prior to cementing. For proper interference fit, the pipe should go easily into the socket approximately ⅓ to ⅔ of the socket depth. If this is not the case, other pipe or fittings should be used.

7. The applicator should be sized according to the size of pipe and fittings being joined. The brush width of the applicator should be equal to approximately ½ of the pipe diameter.

8. Primer is used to penetrate and soften the surfaces so that they will fuse together under a wide variety of conditions. The penetration or softening can be checked by dragging the edge of a knife or sharp object over the coated surface. If a few thousandths of an inch of the primed surface can be scratched or scraped away, proper penetration has occurred. Varying weather conditions affect priming and cementing action and may require more time or repeated applications to either or both surfaces.

9. If using primer, use the correct applicator size (see #7) and aggressively work the primer into the socket, keeping the surface and applicator wet until the surface has softened, re-dipping the applicator as required. When the surface is primed, remove any puddles of primer from the socket.

10. Aggressively work the primer on to the end of the pipe, to a point ½" beyond the depth of the socket.

11. Perform a second application of primer in the socket.

12. While the surfaces are still wet, the appropriate solvent cement should be applied.

13. Using the correct applicator size, aggressively work a full, even layer of cement onto the pipe end to a point equal to the depth of the socket. Do not brush out to a thin paint type layer, as this will dry within a few seconds.

14. Aggressively work a medium layer of cement into the fitting socket; avoid puddling cement in the socket. On the pipe end, do not coat beyond the socket depth or allow cement to run down into the pipe beyond the socket.

15. Apply a second full, even layer of cement on the pipe.

16. Immediately, while the cement is still wet, assemble the joint. Use enough force to ensure that the pipe is fully inserted into the socket. Twist the pipe a ¼ turn as it is being inserted.

17. Hold the joint together for approximately 30 seconds to avoid push out.

18. After assembly, inspect the joint to ensure that there is a ring or bead of cement completely around the juncture of the pipe and socket. If there are voids in this ring, sufficient cement was not applied and the joint may be defective.

19. Remove the excess cement from the pipe and socket (including the ring or bead) using a cloth. Avoid disturbing or moving the joint.

20. Handle newly cemented joints with care until initial set has taken place. Follow set and cure times before handling or testing the system.

Pipe Dimensions

Nominal Size mm (in)	Avg. Outside Diameter mm (in)	Avg. Inside Diameter mm (in)	Avg. Wall Thickness mm (in)	Approx. Weight lb/100ft (kg/m)
12 (½)	21 (0.840)	15 (0.608)	3 (0.116)	16.1 (0.24)
19 (¾)	27 (1.050)	21 (0.810)	3 (0.120)	21.5 (0.32)
25 (1)	33 (1.315)	26 (1.033)	4 (0.141)	31.9 (0.47)
32 (1¼)	42 (1.660)	35 (1.362)	4 (0.149)	43.8 (0.65)
38 (1½)	48 (1.900)	40 (1.592)	4 (0.154)	52.3 (0.78)
50 (2)	60 (2.375)	52 (2.049)	4 (0.163)	70.3 (1.05)
63 (2½)	73 (2.875)	62 (2.445)	5 (0.215)	112.0 (1.61)
75 (3)	89 (3.500)	77 (3.042)	6 (0.229)	146.7 (2.18)
90 (3½)	102 (4.000)	89 (3.520)	6 (0.240)	176.4 (2.63)
100 (4)	114 (4.500)	102 (3.998)	6 (0.251)	208.9 (3.11)
125 (5)	141 (5.565)	127 (5.017)	7 (0.274)	283.4 (4.22)
150 (6)	168 (6.625)	153 (6.031)	8 (0.297)	368.0 (5.48)

Specification

All wiring shall be installed in Royal Electrical Solutions Rigid PVC Conduit and secured with proper fittings. All conduit and fittings shall be manufactured by Royal Building Products, Pipe & Fittings Solutions. All outlets, pull boxes and junction points shall be Royal products.

Exposed conduit shall be securely attached and supported with straps that are installed at the recommended spacing specified in CEC Section 12-1114. The straps must allow for linear expansion and contraction of the conduit due to temperature change. If the variance in temperature exceeds 14°C (25°F), expansion joints shall be installed according to the manufacturer's recommendations.

If Rigid PVC Conduit is embedded in concrete or direct buried, support straps are not required.

Solvent Cementing

All connections should be made using and applying Royal Electrical Solutions solvent cement.

Set Times

Average Initial Set Times			
Temperature Range	Pipe Sizes ½" to 1¼"	Pipe Sizes 1½" to 2"	Pipe Sizes 2½" to 6"
15°C to 40°C	2 min.	5 min.	30 min.
5°C to 15°C	5 min.	10 min.	2 hrs.
-16°C to 5°C	10 min.	15 min.	12 hrs.

Joint Cure Schedule

Average Joint Cure Times			
Temperature Range During Assembly & Cure Periods	Pipe Sizes ½" to 1¼"	Pipe Sizes 1½" to 2"	Pipe Sizes 2½" to 6"
15°C to 40°C	2 min.	5 min.	30 min.
5°C to 15°C	5 min.	10 min.	2 hrs.
-16°C to 5°C	10 min.	15 min.	12 hrs.

In damp or humid weather allow 50% more cure time.

Estimated Solvent Cement Requirements

Average Number of Joints per Litre of Solvent Cement									
Pipe/Fitting Diameter	½"	¾"	1"	1½"	2"	2½"	3"	4"	6"
Number of Joints	300	200	125	90	60	40	40	30	10

Estimated Primer Requirements

Average Number of Joints per Litre of Primer									
Pipe/Fitting Diameter	½"	¾"	1"	1½"	2"	2½"	3"	4"	6"
Number of Joints	600	400	250	180	120	80	80	60	20

Solvent Cementing in Cold Weather:

- Store pipe and fittings in a heated area. Prefabricate as much of the system as possible in a heated area.
- When not in use, store sealed solvent cement and primer between 5°C and 21°C. Do not use open flame or electric heaters to warm cements and primers.
- Take care to remove moisture, ice and snow from the mating surfaces.

Solvent Cementing in Hot Weather:

- At the time of assembly, the surface temperature of the mating surfaces should not exceed 45°C. Shade or shelter the joint surfaces from direct sunlight for at least 1 hour prior to joining and during the joining process. If necessary, swab the mating surfaces with clean, wet rags to reduce the surface temperature (thoroughly dry surfaces before applying primer or cement).
- Make joints during the cooler early morning hours.
- Apply cement quickly and join pipe to fitting as quickly as possible after applying the cement.
- Keep solvent cement container closed or covered when not in use, to minimize solvent loss.

Solvent Cementing in Wet Conditions:

- Mating surfaces must be dry when the joint is made.
- Work under a cover or canopy to keep rain off pipe and fittings.
- Work quickly after drying the pipe and fitting to avoid condensation.
- Allow a longer cure time before the system is tested or used.

Storage and Handling of Solvent Cement and Primer:

- Solvent cement and primer contain highly flammable solvents. Follow all specific safety precautions provided on container label and Material Safety Data Sheet.
- Keep primer and solvent cement away from heat, sparks and open flame.
- Keep containers tightly closed except when in use.
- Ensure proper ventilation of work area and avoid inhaling solvent vapours.
- Where the possibility of splashing exists, wear proper eye protection or a face shield.
- Avoid contact with skin.

Support Straps

Rigid PVC conduit must be supported with straps when installed in above ground applications. These straps should be installed snugly, while allowing linear movement of the conduit. See the table below for recommended maximum spacing of support straps.

Maximum Recommended Spacing of Support Straps		
Nominal Size mm (in)	CEC Recommended Spacing ft (m)	NEC Recommended Spacing ft (m)
16 (½)	2½ (0.75)	3 (0.91)
21 (¾)	2½ (0.75)	3 (0.91)
27 (1)	2½ (0.75)	3 (0.91)
35 (1¼)	4 (1.20)	5 (1.50)
41 (1½)	4 (1.20)	5 (1.50)
53 (2)	6 (1.80)	5 (1.50)
63 (2½)	6 (1.80)	3 - 6 (1.80)
78 (3)-129 (5)	7 (2.10)	3½ - 5 (2.10)
155 (6)	8 (2.50)	8 (2.50)

Storing Conduit Pipe and Fittings

Store Rigid PVC conduit pipe and fittings at the same temperature. Otherwise they may expand and contract at different rates and become incompatible.

Maximum Operating Temperatures

According to the Canadian Electrical Code (CEC), Rigid PVC conduit is intended for use at a continuous operating temperature of 75°C (167°F). For US applications, our Rigid PVC conduit is rated for use with 90°C wiring, according to the requirements of the NEC.

Ambient Temperatures

Royal Electrical Solutions Rigid PVC Conduit and fittings can be installed in locations with an ambient temperature not exceeding 50°C (122°F).

Expansion Joints

According to the CEC, if the amount of expansion expected due to temperature variance during and after construction is more than 45mm, expansion joints must be used.

Expected Expansion

The coefficient of linear expansion for Rigid PVC conduit is as follows:

3×10^{-5} in (expansion/contraction) / in (pipe length) /°F (change in temperature),

5.4×10^{-5} mm (expansion/contraction)/mm (pipe length)/°C (change in temperature)





Note:

The following chart shows the amount of expansion expected with various pipe lengths/temperature changes. If the Rigid PVC Conduit is installed in an exposed location, 17°C (30°F) should be added to the amount of temperature change (ΔT) due to the effects of radiant heat.

Expansion/Contraction of PVC (mm)

Length of Pipe Run (m)

ΔT (°C)	2	4	6	8	10	12	14	16	18	20
5	0.54	1.08	1.62	2.16	2.70	3.24	3.78	4.32	4.86	5.40
10	1.08	2.16	3.24	4.32	5.40	6.48	7.56	8.64	9.72	10.80
15	1.62	3.24	4.86	6.48	8.10	9.72	11.34	12.96	14.58	16.20
20	2.16	4.32	6.48	8.64	10.80	12.96	15.12	17.28	19.44	21.60
25	2.70	5.40	8.10	10.80	13.50	16.20	18.90	21.60	24.30	27.00
30	3.24	6.48	9.72	12.96	16.20	19.44	22.68	25.92	29.16	32.40
35	3.78	7.56	11.34	15.12	18.90	22.68	26.46	30.24	34.02	37.80
40	4.32	8.64	12.96	17.28	21.60	25.92	30.24	34.56	38.88	43.20
45	4.86	9.72	14.58	19.44	24.30	29.16	34.02	38.88	43.74	48.60
50	5.40	10.80	16.20	21.60	27.00	32.40	37.80	43.20	48.60	54.00

Expansion/Contraction of PVC (in)

Length of Pipe Run (ft)

ΔT (°F)	5	10	15	20	25	30	35	40	45	50
5	0.01	0.02	0.03	0.04	0.05	0.05	0.06	0.07	0.08	0.09
10	0.02	0.04	0.05	0.07	0.09	0.11	0.13	0.14	0.16	0.18
15	0.03	0.05	0.08	0.11	0.14	0.16	0.19	0.22	0.24	0.27
20	0.04	0.07	0.11	0.14	0.18	0.22	0.25	0.29	0.32	0.36
25	0.05	0.09	0.14	0.18	0.23	0.27	0.32	0.36	0.41	0.45
30	0.05	0.11	0.16	0.22	0.27	0.32	0.38	0.43	0.49	0.54
35	0.06	0.13	0.19	0.25	0.32	0.38	0.44	0.50	0.57	0.63
40	0.07	0.14	0.22	0.29	0.36	0.43	0.50	0.58	0.65	0.72
45	0.08	0.16	0.24	0.32	0.41	0.49	0.57	0.65	0.73	0.81
50	0.09	0.18	0.27	0.36	0.45	0.54	0.63	0.72	0.81	0.90

Required Number of Expansion Joints

The following table shows the amount of travel that is available with each trade size of Royal Electrical Solutions Rigid PVC conduit expansion joints:

Part Number	Description in	Travel Allowance mm (in)
REJ10	½" Expansion Joint	102 (4)
REJ15	¾" Expansion Joint	102 (4)
REJ20	1" Expansion Joint	102 (4)
REJ25	1¼" Expansion Joint	102 (4)
REJ30	1½" Expansion Joint	102 (4)
REJ35	2" Expansion Joint	102 (4)
REJ40	2½" Expansion Joint	102 (4)
REJ45	3" Expansion Joint	204 (8)
REJ50	3½" Expansion Joint	204 (8)
REJ55	4" Expansion Joint	204 (8)
REJ60	5" Expansion Joint	204 (8)
REJ65	6" Expansion Joint	204 (8)

The required number of expansion joints can be calculated using the following formula:

$$\#\ \text{Expansion Joints Required} = \frac{\text{Total Expected Amount of Expansion (in)}}{\text{Expansion Joint Travel Allowance (in)}}$$

$$\#\ \text{Expansion Joints Required} = \frac{\text{Total Expected Amount of Expansion (mm)}}{\text{Expansion Joint Travel Allowance (mm)}}$$

The number of expansion joints calculated above should be rounded up to the nearest whole number.

Setting the Piston Opening

Expansion joints must be installed such that they allow for both expansion and contraction of the conduit. The piston of the expansion joint must be set at the correct position to allow for this linear movement. To determine the correct position for the piston at the time and temperature of installation, the following formula should be used:

$$\text{Piston Setting (in)} = \frac{\text{(Max. Temp. (°F) – Install. Temp. (°F))}}{\text{Total Expected Temperature Change (°F)}} \times \left[\text{Expansion Joint Expansion Allow. (in)}\right]$$

$$\text{Piston Setting (mm)} = \frac{\text{(Max. Temp. (°C) – Install. Temp. (°C))}}{\text{Total Expected Temperature Change (°C)}} \times \left[\text{Expansion Joint Expansion Allow. (mm)}\right]$$

Installation Guidelines

• Securely fasten the expansion joint barrel so that it does not shift. Loosely connect the conduit so that it is free to move.


• To function properly, expansion joints should be installed near a fixed point.

• It is better to use more expansion joints than not enough, since problems are difficult to correct after conductors and wires have been pulled through the conduit.

• Ensure that the barrel and piston are aligned and level.

• For vertical installations of expansion joints, install with the piston at the bottom to prevent dirt and water from getting inside the joint and causing it to malfunction.

Installation Example



If one expansion joint is required:
Securely fasten the barrel of the expansion joint close to one of the boxes. Support the conduit with straps, but allow free movement of the conduit for expansion and contraction. (See Drawing 1)

If two expansion joints are required:
There are two options available:


1. Firmly fasten one expansion joint near each end of the run and firmly fasten the conduit at the centre. Support the rest of the conduit with straps allowing for movement of the conduit. (See Drawing 2)

2. Firmly fasten the expansion joints back-to-back at the centre of the run. The conduit should be supported with straps to allow free movements as it expands and contracts. (See Drawing 3)


If three or more expansion joints are required:
Evenly space the expansion joints along the run of Rigid PVC conduit. Tightly fasten each expansion joint and support the conduit with straps. Do not restrict the movement of the conduit.


*For information on Maximum Recommended Spacing of Support Straps, see page 4.


Drawings 1 - 4




FITTINGS - Bends (Bell Ends)


90° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1090	46120	0.840	1.500	4.00
	¾	REE1590	46150	1.050	1.500	4.50
	1	REE2090	46180	1.315	1.875	5.75
	1¼	REE2590	46210	1.660	2.000	7.25
	1½	REE3090	46240	1.900	2.000	8.25
	2	REE3590	46270	2.375	2.000	9.50
	2½	REE4090	46330	2.875	3.000	10.50
	3	REE4590	46360	3.500	3.125	13.00
	3½	REE5090	46390	4.000	3.250	15.00
	4	REE5590	46420	4.500	3.375	16.00
	5	REE6090	46440	5.565	3.622	24.00
	6	REE6590	46460	6.625	3.740	30.00


45° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1045	46120	0.840	1.500	4.00
	¾	REE1545	46150	1.050	1.500	4.50
	1	REE2045	46180	1.315	1.875	5.75
	1¼	REE2545	46210	1.660	2.000	7.25
	1½	REE3045	46240	1.900	2.000	8.25
	2	REE3545	46270	2.375	2.000	9.50
	2½	REE4045	46330	2.875	3.000	10.50
	3	REE4545	46360	3.500	3.125	13.00
	3½	REE5045	46390	4.000	3.250	15.00
	4	REE5545	46420	4.500	3.375	16.00
	5	REE6045	46440	5.565	3.625	24.00
	6	REE6545	46460	6.625	3.750	30.00


30° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1030	46100	0.840	1.500	4.00
	¾	REE1530	46130	1.050	1.500	4.50
	1	REE2030	46160	1.315	1.875	5.75
	1¼	REE2530	46190	1.660	2.000	7.25
	1½	REE3030	46220	1.900	2.000	8.25
	2	REE3530	46274	2.375	2.000	9.50
	2½	REE4030	46310	2.875	3.000	10.50
	3	REE4530	46340	3.500	3.125	13.00
	3½	REE5030	46375	4.000	3.250	15.00
	4	REE5530	46400	4.500	3.375	16.00
	5	REE6030	46425	5.565	3.625	24.00
	6	REE6530	46442	6.625	3.750	30.00


Utilities 90° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	2	REE2-24	46501	2.375	41.20	24.00
	2	REE2-36	46502	2.375	31.70	36.00
	3	REE3-24	46503	3.500	41.20	24.00
	3	REE3-36	46504	3.500	31.70	36.00
	4	REE4-36	46465	4.500	31.70	36.00
	4	REE4-48	46505	4.500	31.70	48.00
	5	REE5-36	46506	5.565	31.70	36.00
	6	REE6-36	46507	6.625	31.70	36.00

Fittings - Bends (Plain Ends)


90° Elbows - Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1090PE	46120	0.840	1.500	4.00
	¾	REE1590PE	46150	1.050	1.500	4.50
	1	REE2090PE	46180	1.315	1.875	5.75
	1¼	REE2590PE	46210	1.660	2.000	7.25
	1½	REE3090PE	46240	1.900	2.000	8.25
	2	REE3590PE	46270	2.375	2.000	9.50
	2½	REE4090PE	46330	2.875	3.000	10.50
	3	REE4590PE	46360	3.500	3.125	13.00
	3½	REE5090PE	46390	4.000	3.250	15.00
	4	REE5590PE	46420	4.500	3.375	16.00
	5	REE6090PE	46440	5.565	3.622	24.00
	6	REE6590PE	46460	6.625	3.740	30.00


45° Elbows - Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1045PE	46110	0.840	1.500	4.00
	¾	REE1545PE	46140	1.050	1.500	4.50
	1	REE2045PE	46170	1.315	1.875	5.75
	1¼	REE2545PE	46200	1.660	2.000	7.25
	1½	REE3045PE	46230	1.900	2.000	8.25
	2	REE3545PE	46280	2.375	2.000	9.50
	2½	REE4045PE	46320	2.875	3.000	10.50
	3	REE4545PE	46350	3.500	3.125	13.00
	3½	REE5045PE	46380	4.000	3.250	15.00
	4	REE5545PE	46415	4.500	3.375	16.00
	5	REE6045PE	46430	5.565	3.622	24.00
	6	REE6545PE	46450	6.625	3.740	30.00


30° Elbows - Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1030PE	46100	0.840	1.500	4.00
	¾	REE1530PE	46130	1.050	1.500	4.50
	1	REE2030PE	46160	1.315	1.875	5.75
	1¼	REE2530PE	46190	1.660	2.000	7.25
	1½	REE3030PE	46220	1.900	2.000	8.25
	2	REE3530PE	46274	2.375	2.000	9.50
	2½	REE4030PE	46310	2.875	3.000	10.50
	3	REE4530PE	46340	3.500	3.125	13.00
	3½	REE5030PE	46375	4.000	3.250	15.00
	4	REE5530PE	46400	4.500	3.375	16.00
	5	REE6030PE	46425	5.565	3.622	24.00
	6	REE6530PE	46442	6.625	3.740	30.00


45° Elbows - Extended Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	1¼	REE2590E	46125	1.660	14.750	7.25
	1½	REE3090E	46260	1.900	14.750	8.25
	2	REE3590E	43290	2.375	14.750	9.50

Fittings - Couplings and Adapters

Couplings	Sizes (in)	Product Code	UPC Number	Outside Diameter (OD) (in)	Inside Diameter (ID) (in)	Length (L) (in)
 2.1	½	REC10	45950	1.080	0.840	1.437
	¾	REC15	45960	1.300	1.050	1.703
	1	REC20	45970	1.590	1.315	2.031
	1¼	REC25	45980	2.000	1.660	2.156
	1½	REC30	45990	2.230	1.900	2.281
	2	REC35	46000	2.720	2.375	2.406
	2½	REC40	46010	3.320	2.875	3.187
	3	REC45	46020	4.000	3.500	3.437
	3½	REC50	46030	4.500	4.000	3.625
	4	REC55	46060	5.000	4.500	3.750
	5	REC60	46080	6.120	5.565	4.187
	6	REC65	46090	7.370	6.625	4.562


5° Couplings *(*Fabricated)*	Sizes (in)	Product Code	UPC Number	Outside Diameter (OD) (in)	Inside Diameter (ID) (in)	Length (L) (in)
	2	R5EC35	46800	2.375	2.049	4.0
	2½	R5EC40	46805	3.500	2.445	5.5
	3	R5EC45	46810	3.500	3.042	6.0
	3½	R5EC50	46815	4.500	3.521	7.0
	4	R5EC55	46820	4.500	3.998	7.0
	5	R5EC60	46825	5.565	5.018	7.5
	6	R5EC65	46830	6.625	6.031	11.0

Terminal Adapters (½" - 1¼" Tapered Thread, 6" NPT)	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	Inside Diameter (ID) (in)	Thread (in)
	½	RTA10	45730	0.750	0.700	0.591	1.550
	¾	RTA15	45740	1.000	0.675	0.790	1.750
	1	RTA20	45750	1.115	0.625	1.000	1.860
	1¼	RTA25	45760	1.300	0.640	1.311	2.125
	1½	RTA30	45770	1.425	0.725	1.530	2.250
	2	RTA35	45780	1.150	0.800	1.970	2.100
	2½	RTA40	45790	1.900	0.800	2.346	2.930
	3	RTA45	45800	2.000	0.815	2.915	3.055
	3½	RTA50	45810	1.715	1.000	3.385	3.055
	4	RTA55	45820	1.990	0.815	3.850	3.215
	5	RTA60	45830	2.000	1.725	5.015	5.985
	6	RTA65	45840	2.130	1.875	6.025	6.500

Female Adapters (Npt Tapered Thread)	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	Inside Diameter (ID) (in)	Thread (in)
	½	RFA10	44990	0.800	0.825	0.620	1.725
	¾	RFA15	45000	0.800	1.000	0.820	1.900
	1	RFA20	45010	1.000	1.200	1.065	2.300
	1¼	RFA25	45020	1.015	1.300	1.395	2.425
	1½	RFA30	45030	1.050	1.290	1.575	2.440
	2	RFA35	45040	1.075	1.375	2.050	2.550
	2½	RFA40	45050	1.675	1.985	2.470	3.760
	3	RFA45	45060	1.630	2.150	3.090	4.100
	3½	RFA50	45070	1.800	2.000	3.540	3.985
	4	RFA55	45080	1.755	2.185	4.025	4.210
	5	RFA60	45090	2.065	3.000	5.035	5.240
	6	RFA65	45100	2.065	3.000	6.045	5.235

Fittings - Expansions Joints, Straps and Meter Accessories

Expansion Joints



Sizes (in)	Product Code	UPC Number	Expanded Length (E) (in)	Contracted Length (C) (in)	Travel (in)
½	REJ10	44870	12.00	8.00	4.00
¾	REJ15	44880	12.00	8.00	4.00
1	REJ20	44890	12.50	8.50	4.00
1¼	REJ25	44900	13.00	9.00	4.00
1½	REJ30	44910	13.00	9.00	4.00
2	REJ35	44920	13.25	9.25	4.00
2½	REJ40	44930	13.25	9.25	4.00
3	REJ45	44940	22.25	14.25	8.00
3½	REJ50	44950	22.25	14.25	8.00
4	REJ55	44960	22.25	14.25	8.00
5	REJ60	44963	22.25	14.25	8.00
6	REJ65	44966	22.25	14.25	8.00

Expansion Joints

PVC — 2 Hole



Sizes (in)	Product No.	UPC No.
½	RPS10	45540
¾	RPS15	45550
1	RPS20	45560
1¼	RPS25	45570
1½	RPS30	45580
2	RPS35	45590

PVC Coated Steel — 2 Hole



Sizes (in)	Product No.	UPC No.
2	RCS35	44783
2½	RCS40	44784
3	RCS45	44785
3½	RCS50	44786
4	RCS55	44787
5	RCS60	44788
6	RCS65	44789

PVC Coated Steel — 1 Hole



Sizes (in)	Product No.	UPC No.
½	RCS10-1	46850
¾	RCS15-1	46852
1	RCS20-1	46854
1¼	RCS25-1	46856
1½	RCS30-1	46858
2	RCS35-1	46860
2½	RCS40-1	46862
3	RCS10-1	46864
4	RCS10-1	46866

Meter Offsets



Sizes (in)	Product No.	UPC No.
1¼	RM025	45500
2	RM035	45510

Meter Hubs



Sizes (in)	Product No.	UPC No.
1¼	RMHU25	45480
1½	RMHU30	45485
2	RMHU35	45490

Long Meter Offsets *(Fabricated)*



Sizes (in)	Product No.	UPC No.
1¼	RLM025	45472
1½	RML030	45474
2	RML035	45476

Expansion & Deflection Fittings Assembly



Sizes (in)	Product No.	UPC No.
2	RSEJ35	46990
3	RSEJ45	46992
4	RSEJ55	46994

Service Entrance Fittings



Sizes (in)	Product No.	UPC No.
½	REF10	44795
¾	REF15	44800
1	REF20	44810
1¼	REF25	44820
1½	REF30	44830
2	REF35	44840
2½	REF40	44842
3	REF45	44844
3½	REF50	44852
4	REF55	44860

Ecovoc Solvent Cement *(*c/w Screw Cap & Dauber)*




Sizes (in)	Product No.	UPC No.	Carton Qty.
250ml	RVOC250*	54790	24
475ml	RVOC475*	54795	12
950ml	RVOC950*	54797	12
4L	RVOC4L	54799	4


Privoc Solvent Cement *(*c/w Screw Cap & Dauber)*





Sizes (in)	Product No.	UPC No.	Carton Qty.
250ml	RVOCPR250*	54800	24
475ml	RVOCPR475*	54802	12
950ml	RVOCPR950*	54804	12
4L	RVOCPR4L	54806	4

Fittings - Access Fittings


Type C	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)
	½	RSC10S	46600	5.606	0.639	1.268	1.100	0.840
	¾	RSC20S	46605	5.606	0.810	1.536	1.325	1.050
	1	RSC30S	46610	6.500	0.910	1.700	1.600	1.335
	1¼	RSC40S	46615	7.900	1.050	2.300	2.250	1.100
	1½	RSC50S	46620	8.500	1.125	2.675	2.250	1.900
	2	RSC60S	45605	10.875	1.160	3.188	2.820	2.375
	2½	RSC70S	45606	14.600	1.750	4.500	3.950	2.870
	3	RSC80S	45607	14.600	1.900	4.500	3.950	3.510
	3½	RSC90S	45609	17.040	2.125	5.536	5.000	4.000
	4	RSC100S	45608	17.040	2.125	5.536	5.000	4.530


Type LB	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)	H (in)
	½	RSLB10S	45620	4.337	0.639	1.268	0.840	1.297	4.095	2.487	1.005
	¾	RSLB20S	45630	5.395	0.810	1.536	1.050	1.297	4.095	2.487	1.005
	1	RSLB30S	45640	6.250	0.910	1.700	1.335	1.500	4.750	2.075	1.125
	1¼	RSLB40S	45650	7.625	1.050	2.300	1.100	1.750	5.750	3.575	1.562
	1½	RSLB50S	45660	8.250	1.125	2.675	1.900	1.750	6.500	3.938	1.656
	2	RSLB60S	45670	10.531	1.160	3.188	2.375	2.344	8.156	4.535	1.968
	2½	RSLB70S	45675	13.630	1.750	4.500	2.870	2.733	9.825	6.240	2.610
	3	RSLB80S	45680	13.630	1.900	4.500	3.510	3.805	10.897	6.240	2.610
	3½	RSLB90S	45610	16.000	2.125	5.536	4.000	4.535	11.465	7.500	2.975
	4	RSLB100S	45681	16.000	2.125	5.536	4.530	4.535	11.465	7.500	2.975


Type LL	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)
	½	RSLL10S	46650	4.337	0.639	1.268	2.487	0.840	4.095	1.297
	¾	RSLL20S	46655	5.395	0.810	1.536	2.487	1.050	4.095	1.297
	1	RSLL30S	46660	6.250	0.910	1.700	2.075	1.335	4.750	1.500
	1¼	RSLL40S	46665	7.625	1.050	2.300	3.575	1.100	5.750	1.750
	1½	RSLL50S	46670	8.250	1.125	2.675	3.938	1.900	6.500	1.750
	2	RSLL60S	45682	10.531	1.160	3.188	4.535	2.375	8.156	2.344
	2½	RSLL70S	45672	13.630	1.750	4.500	6.240	2.870	9.825	3.805
	3	RSLL80S	46674	13.630	1.900	4.500	6.240	3.510	10.897	2.733
	3½	RSLL90S	46678	16.000	2.125	5.536	7.500	4.000	11.465	4.535
	4	RSLL100S	46676	16.000	2.125	5.536	7.500	4.530	11.465	4.535

Type LR	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)
	½	RSLR10S	46700	4.337	0.639	1.268	2.487	0.840	4.095	1.297
	¾	RSLR20S	46705	5.395	0.810	1.536	2.487	1.050	4.095	1.297
	1	RSLR30S	46710	6.250	0.910	1.700	2.075	1.335	4.750	1.500
	1¼	RSLR40S	46715	7.625	1.050	2.300	3.575	1.100	5.750	1.750
	1½	RSLR50S	46720	8.250	1.125	2.675	3.938	1.900	6.500	1.750
	2	RSLR60S	45683	10.531	1.160	3.188	4.535	2.375	8.156	2.344
	2½	RSLR70S	46725	13.630	1.750	4.500	6.240	2.870	9.825	3.805
	3	RSLR80S	46728	13.630	1.900	4.500	6.240	3.510	10.897	2.733
	3½	RSLR90S	46738	16.000	2.125	5.536	7.500	4.000	11.465	4.535
	4	RSLR100S	46735	16.000	2.125	5.536	7.500	4.530	11.465	4.535

Fittings - Access Fittings

Type E	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)
	½	RSE10S	46630	4.337	0.639	1.268	0.840
	¾	RSE20S	46632	5.395	0.810	1.536	1.050
	1	RSE30S	46634	6.250	0.910	1.700	1.335
	1¼	RSE40S	46636	7.625	1.050	2.300	1.100
	1½	RSE50S	46638	8.250	1.125	2.675	1.900
	2	RSE60S	46640	10.351	1.160	3.188	2.375
	2½	RSE70S	46642	13.630	1.750	4.500	2.870
	3	RSE80S	46644	13.630	1.900	4.500	3.510
	3½	RSE90S	46648	16.000	2.125	5.536	4.000
	4	RSE100S	46646	16.000	2.125	5.536	4.530

Type T	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)
	½	RST10S	45690	2.280	0.639	1.100	0.840
	¾	RST20S	45700	2.803	0.810	1.325	1.050
	1	RST30S	45710	3.250	0.910	1.600	1.335
	1¼	RST40S	45720	3.950	1.050	2.250	1.100
	1½	RST50S	45723	4.250	1.125	2.250	1.900
	2	RST60S	45725	5.438	1.160	2.820	2.375
	2½	RST70S	46745	7.300	1.750	3.950	2.870
	3	RST80S	46748	7.300	1.900	3.950	3.510
	3½	RST90S	46752	8.535	2.125	5.000	4.000
	4	RST100S	46750	8.535	2.125	5.000	4.530

Type TB	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)	H (in)
	½	RSTB10S	45692	2.280	0.639	1.268	1.100	0.840	2.487	1.005	0.750
	¾	RSTB20S	45702	2.803	0.810	1.536	1.325	1.050	2.487	1.005	0.810
	1	RSTB30S	45712	3.250	0.910	1.700	1.600	1.335	2.075	1.125	1.115
	1¼	RSTB40S	45721	3.950	1.050	2.300	2.250	1.100	3.575	1.562	1.300
	1½	RSTB50S	45724	4.250	1.125	2.675	2.250	1.900	3.938	1.656	1.425
	2	RSTB60S	45727	5.438	1.160	3.188	2.820	2.375	4.535	1.968	1.160
	2½	RSTB70S	46760	7.300	1.750	4.500	3.950	2.870	6.240	2.610	-
	3	RSTB80S	46762	7.300	1.900	4.500	3.950	3.510	6.240	2.610	-
	3½	RSTB90S	46766	8.535	2.125	5.536	5.000	4.000	7.500	2.975	-
	4	RSTB100S	46764	8.535	2.125	5.536	5.000	4.530	7.500	2.975	-

Fittings - Cover Plates

Single Gang Cover Plates - F Series



Description	Product Code	UPC Number
Toggle Switch	RTSC15-10	45845
Duplex Receptacle	RDRC15-10R20	44685
Single Receptacle - 15 Amp	RC15-10R20-3	47035
Single Receptacle - 20 Amp	RC15-10R30-3	47036
Single Receptacle - 30 Amp	RC15-10	47037
Single Blank with Gasket	RBRC15-10	44680
Gasket	GASK15-10	44682

Double Gang Cover Plates - F Series



Description	Product Code	UPC Number
Double Switch	RTSC20-2	45846
Combo Switch/Receptacle	RTSDC20-2	45847
Double Duplex	RDRC20-2	44686
Double Blank with Gasket	RBRC20-2	44681
Gasket	GASK20-2	45949

Triple Gang Cover Plates - F Series



Description	Product Code	UPC Number
Triple Switch	RTSC20-3	45857
Double Switch Receptacle	RDSDR20-3	44689
Double Receptacle/Switch	RTSDC20-3	45858
Triple Receptacle	RDRC20-3	44688
Triple Blank with Gasket	RBRC20-3	44683
Gasket	GASK20-3	45859

Fittings - Weatherproof Cover Plates

Single Gang Weatherproof Cover Plates



RVSC15-10 RVSC15-10 RWTG15-10 RWGF15-10 RWTL RVSC15-10 GASK W

Description	Product Code	UPC Number
Toggle Switch Cover	RVSC15-10	45940
Plunger Switch Cover	RVPT15-10	45930
Toggle	RWTG15-10	45339
Duplex Receptacle	RWDR15-10	45093
Duplex Receptacle - White	RWDR15-10W	45094
Ground Fault Receptacle	RWGF15-10	45095
Ground Fault Receptacle - White	RWGF15-10W	45098
Single Receptacle - 15 Amp	RWTL15	45470
Single Receptacle - 20 Amp	RWTL20	45472
Single Receptacle - 30 Amp	RWTL30	45480
Single Receptacle - 50 Amp	RWTL50	45482
Gasket	GASK W	45484

Double Gang Weatherproof Cover Plates



RVSC20-2 RVSRC20-2 RVSDR20-2 RVSRR20-2 GASK20-2

Description	Product Code	UPC Number
Double Toggle	RVSC20-2	45941
Plunger/GFI	RVSRC20-2	45947
Plunger/Duplex Receptacle	RVSDR20-2	45945
Plunger/Single Receptacle	RVSRR20-2	45948
Gasket	GASK20-2	45949

Fittings - Slab Boxes

Single Gang Boxes - F Series



RFS



RFSS



RFSC



RFSCC

Description	Product Code	UPC Number	Volume (in3)
½" FS	RFS10	45200	17.0
¾" FS	RFS15	45210	17.0
½" FSS	RFSS10	45240	17.5
¾" FSS	RFSS15	45250	17.5
½" FSC	RFSC10	45220	16.3
¾" FSC	RFSC15	45230	16.3
½" FSCC	RFSCC10	45233	17.0
¾" FSCC	RFSCC15	45235	17.0

Single Gang Deep Boxes - FD Series



RFDS



RFDC



BLANK



347 VOLT

Outside Dimensions: Length = 4.5", Width = 6.6", Height = 2.5", except BLANK, L = 4.5", W = 6.6", H = 3.0"

Description	Product Code	UPC Number	Volume (in3)
½" FSC	RFSC3-10	45224	56.0
¾" FSC	RFSC3-15	45232	56.0
1" FSC	RFSC3-20	45228	56.0
½" FS	RFS3-10	45208	54.0
¾" FS	RFS3-15	45218	54.0
1" FS	RFS3-20	45219	54.0
BLANK	RFD-3	45155	73.8

Double Gang Boxes - F Series


FS


FSS


FSC


FSCC


BLANK

Outside Dimensions: Length = 4.5", Width = 4.75", Height = 2.5", except BLANK, L=4.75", W=4.75", H=3.0"

Description	Product Code	UPC Number	Volume (in3)
½" FS	RFS2-10	45205	39.5
¾" FS	RFS2-15	45215	39.5
1" FS	RFS2-20	45216	39.5
½" FSS	RFSS2-10	45242	37.0
¾" FSS	RFSS2-15	45244	37.0
1" FSS	RFSS2-20	45246	37.0
½" FSC	RFSC2-10	45222	37.0
¾" FSC	RFSC2-15	45231	37.0
1" FSC	RFSC2-20	45226	37.0
½" FSCC	RFSCC2-10	45234	36.0
¾" FSCC	RFSCC2-15	45238	36.0
1" FSCC	RFSCC2-20	45239	36.0
BLANK	RFD-D	45150	52.0

Triple Gang Boxes - F Series


FSC


FS


BLANK

Outside Dimensions: Length = 4.5", Width = 6.6", Height = 2.5", except BLANK, L = 4.5", W = 6.6", H = 3.0"

Description	Product Code	UPC Number	Volume (in3)
½" FSC	RFSC3-10	45224	56.0
¾" FSC	RFSC3-15	45232	56.0
1" FSC	RFSC3-20	45228	56.0
½" FS	RFS3-10	45208	54.0
¾" FS	RFS3-15	45218	54.0
1" FS	RFS3-20	45219	54.0
BLANK	RFD-3	45155	73.8

Octagonal Boxes



Size (in)	Product No.	UPC No.
4 x 1½	ROB15/10	45520
4 x 2	ROB20	45525
¾	RKO15	45450
1	RKO20	45455


Octagonal Box Extension Rings



Size (in)	Product No.	UPC No.
1	RXR20	46490
2	RXR35	46495

Junction Boxes With Gasket









Nominal Size (in)	Product Number	UPC Number	Inside Length & Width (A) (in)	Outside Length & Width (B) (in)	Length Screw to Screw (C) (in)	Outside Height (E) (in)	Inside Height (D) (in)	Screw Size (F)	Volume (in3)
4 x 4 x 2	RJB442	45300	3.675	4.000	3.450	2.125	2.000	8-32	25.4
4 x 4 x 4	RJB444	45310	3.675	4.000	3.450	4.188	3.750	8-32	47.5
4 x 4 x 6	RJB446	45315	3.675	4.000	3.450	6.225	6.000	8-32	76.1
5 x 5 x 2	RJB552	45320	4.680	5.000	4.485	2.000	1.845	8-32	38.7
6 x 6 x 4	RJB664	45330	6.000	6.375	5.813	4.188	4.000	10-32	139.5
6 x 6 x 6	RJB666	45335	6.000	6.375	5.813	6.188	6.000	10-32	209.3
8 x 8 x 4	RJB884	45340	8.075	8.625	7.996	4.230	4.005	¼-20	258.6
8 x 8 x 7	RJB887	45350	8.100	8.625	7.996	7.250	7.035	¼-20	455.6
12 x 12 x 4	RJB12124	45280	12.085	12.580	11.874	4.256	4.030	¼-20	578.3
12 x 12 x 6	RJB12126	45290	12.085	12.580	11.874	6.240	6.025	¼-20	864.6
12 x 12 x 8	RJB12128	45295	12.085	12.580	11.874	8.250	8.025	¼-20	1151.6

Highway Boxes









Nominal Size (in)	Product Number	UPC Number	Box Inside Length & Width (B) (in)	Box Inside Depth (H) (in)	Lid Length & Width (L) (in)	Thickness of Lid (T) (in)	Volume (in3)
6 x 6 x 4	H664	47040	6.0	4.25	9.0	0.60	139.5
6 x 6 x 6	H666	47041	6.0	6.25	9.0	0.60	209.3
8 x 8 x 4	H884	47042	8.0	4.25	11.5	0.75	258.6
8 x 8 x 6	H886	47043	8.0	6.25	11.5	0.75	400.0
8 x 8 x 7	H887	47044	8.0	7.25	11.5	0.75	455.6
8 x 8 x 7	H887-A	47045	8.0	7.25	11.5	0.75	418.4

Junction Box Adapters



Size (in)	Product No.	UPC No.
½	RJBA10	45360
¾	RJBA15	45370
1	RJBA20	45380
1¼	RJBA25	45390
1½	RJBA30	45400
2	RJBA35	45410
2½	RJBA40	45420
3	RJBA45	45430
3½	RJBA50	45435
4	RJBA55	45440

Duplex Floor Boxes & Cover (*Includes Leveling Ring)



Size (in)	Product No.	UPC No.
4 x ¾	RFDB4	46980
2 x ¾, 2 x 1	RFDB2	46982
Polycarbonate Bronze Cover	RFDBC	46984

Notes:

Our various pipe and fittings solutions have been manufactured to meet the needs of our customers and their applications. Contact one of the below Sales Centres for more information:

- Municipal Pipe & Fittings Solutions
- Plumbing Pipe & Fittings Solutions
- Electrical Pipe & Fittings Solutions
- Industrial Pipe & Fittings Solutions
- Irrigation Pipe & Fittings Solutions

Sales & Distribution Centres:

Langley, BC, Canada
T/F 1.800.663.0696
F 1.800.663.6564

Woodbridge, ON, Canada
T/F 1.866.769.7473
F 905.856.3986

Laval, QC, Canada
T/F 1.800.465.9754
F 450.688.6624

Distribution Centres:

Calgary, AB, Canada
T/F 1.800.663.0696
F 1.800.663.6564

Winnipeg, MB, Canada
T/F 1.800.663.0696
F 1.800.663.6564

royalelectricalca.com





MIX
Paper from responsible sources
FSC® C003472

E_RCPF_BRV4
Printed 02.2014

ROYAL® Building Products

Pipe & Fittings Solutions | Municipal Plumbing Electrical Industrial Irrigation

Rigid PVC Conduit Pipe & Fittings

A system for residential, industrial, commercial and institutional applications.







ROYAL® Electrical Solutions

ROYAL Electrical Solutions

Table of Contents



Product Description - Features and Benefits	1
Installation Guidelines - Solvent Welding Joints	2
Solvent Welding Joints/Pipe Dimensions/Specs	3
Solvent Cementing	4
Expansion and Contraction	5
Setting the Piston Opening	6
Fittings - Bends (Bell End)	7-8
Fittings - Miscellaneous	9-18

Note: This brochure is not intended to assume the authority of the Design Engineer. Actual jobsite conditions will vary significantly. The sole responsibility for all design and installation decisions lies with the Design Engineer. All local health and safety regulations must be followed.

Rigid PVC Conduit Pipe & Fittings

A system for residential, industrial, commercial and institutional applications.

Product Description & Applications

Royal Building Products® Electrical Solutions manufactures a complete line of Rigid PVC Conduit pipe and fittings for electrical applications. Our products are designed to reduce labour and maintenance costs, while offering superior performance.

Products are certified by the Canadian Standards Association (CSA) and Underwriters Laboratories (UL) for use in above and below ground applications. Our Rigid PVC conduit pipe and fittings are available in 12 to 150mm (½- to 6-inch) diameters and 3- or 6-metre (10- or 20-foot) lengths.

Standards and Codes

Royal Electrical Solutions Rigid PVC Conduit pipe and fittings are certified to CSA Standards as noted below. Our Rigid PVC conduit pipe and fittings shall be installed according to the Canadian Electrical Code (CEC) Part I, Rules 12-1100 - 12-1122 and the National Electrical Code (NEC) Article 352.

Pipe	Fittings
C22.2 No. 211.2	C22.2 No. 18.2, 85 (Boxes) No. 40 (Electrical Encl.) No. 42.1 (Covers) No. 85 (Fittings)
UL 651	UL 514C (Boxes) UL 50 (Electrical Encl.) UL 514D (Covers) UL 651 (Fittings)
Conforms to NEMA TC2	





Features and Benefits

Saves Labour

Rigid PVC Conduit pipe and fittings are easy to install, cut and join.

Easy Wire Pulls

The conduit's smooth interior surface reduces friction and prevents damage to wires when pulling wire and conductors for long runs and even through 90° bends.

Lightweight Materials

Rigid PVC Conduit is easier to move and handle because it is approximately one-fifth the weight of steel and half the weight of aluminum.

Approximate Weight Comparison

Size mm (in)	PVC lb/100ft (kg/m)	Aluminum lb/100ft (kg/m)	Steel lb/100ft (kg/m)
12 (½)	16.1 (0.24)	27 (0.40)	79 (1.20)
19 (¾)	21.5 (0.32)	37 (0.55)	105 (1.55)
25 (1)	31.9 (0.47)	53 (0.80)	153 (2.30)
32 (1¼)	43.8 (0.65)	70 (1.05)	201 (3.00)
38 (1½)	52.3 (0.78)	86 (1.30)	249 (3.70)
50 (2)	70.3 (1.05)	116 (1.75)	334 (5.00)
63 (2½)	112.0 (1.61)	183 (2.75)	527 (7.85)
75 (3)	146.7 (2.18)	239 (3.55)	690 (10.25)
90 (3½)	176.4 (2.63)	288 (4.30)	831 (12.40)
100 (4)	208.9 (3.11)	340 (5.10)	982 (14.60)
125 (5)	283.4 (4.22)	465 (6.90)	1,344 (20.40)
150 (6)	368.0 (5.48)	613 (9.10)	1,771 (26.35)

Simplifies Direct Burial

Royal Electrical Solutions Rigid PVC Conduit does not require additional protection for direct burial installations according to the Canadian Electrical Code (CEC) and the National Electrical Code (NEC). Normal construction practices should be followed for trenching and backfill operations.

Non-Conductive

Rigid PVC Conduit is non-conductive.

Long Life

Royal Rigid PVC Conduit and fittings resist acids, alkalis, salt solutions and most other chemicals. (Refer to the Royal Chemical Resistance Guide for detailed information.) There is no risk of corrosion when exposed to naturally corrosive soil conditions, electrochemical or galvanic environments. Royal's Rigid PVC Conduit has achieved sunlight resistance as per the requirements of the Electrical Code.

FT-4 Rating

Rigid PVC Conduit pipe has an FT-4 Rating and can be used in non-combustible construction as per Part 3 of the National Building Code of Canada (NBC).

Installation Guidelines

Cutting

Royal Rigid PVC Conduit can easily be cut with a hacksaw, a fine-toothed handsaw or PVC conduit cutters. For conduit with more than a 50mm (2-inch) diameter, use a mitre box or saw guide to ensure a square cut. Deburr the end using a knife or file.

Bending

It may be necessary to create bends in the field by heating and deforming Rigid PVC Conduit. To accomplish this, the following guidelines should be followed:

• For heating the Rigid PVC Conduit, use a heat gun or some other flameless heat source. Do not use an open flame to heat the conduit. Rigid PVC Conduit must be heated to approximately 127°C (260°F) in order to bend without kinking.

• Heat a length of conduit equal to approximately 10 times the nominal diameter.

• Once the Rigid PVC Conduit has been adequately heated, bend it to the required angle plus 3 extra degrees. The additional angle will accommodate the "spring back" which will occur during cooling.

• After bending of the conduit is completed, immediately cool the bend using water or cold air.

• According to the Canadian Electrical Code (CEC) and the National Electrical Code (NEC), the minimum bending radius for rigid conduit is as shown in the table below.

Nominal Size mm (in)	Min. Radius to Centre of Conduit or Tubing mm (in)
16 (½)	102 (4.016)
21 (¾)	114 (4.489)
27 (1)	146 (5.748)
35 (1¼)	184 (7.244)
41 (1½)	210 (8.268)
53 (2)	241 (9.488)
63 (2½)	267 (10.512)
78 (3)	330 (12.992)
91 (3½)	381 (14.606)
103 (4)	406 (15.984)
129 (5)	610 (24.016)
155 (6)	762 (30.000)





Procedure for Solvent Welding Joints

• Use solvent cement and primer prior to expiration date marked on container.
• Above 0° C ambient temperature, joints may be assembled without the use of primer, provided adequate penetration and softening of the pipe/fitting surface can be achieved with solvent cement alone.


1. Assemble materials for the job, including correct solvent cement, primer and correctly sized applicator.

2. Cut pipe as square as possible using a hand saw and miter box or mechanical saw. Do not use a diagonal cut, as it reduces the bonding area in the joint.

3. If plastic tubing cutters are used, care must be taken to remove any raised bead at the end of the pipe, caused by cutting. A file or reamer may be used to remove the bead.

4. Use a knife, file or reamer to remove burrs from the inside and outside of the pipe end, as these will hinder the integrity of the joint. All sharp edges should be removed from the inside and outside edges of the pipe to prevent the pipe from pushing the solvent cement into the fitting socket, thereby causing a weak spot to form. The pipe end should be chamfered, as shown below.

Chamfered Pipe



Procedure for Solvent Welding Joints Continued

5. All dirt, grease and moisture should be removed from the pipe and socket by thoroughly wiping with a clean, dry cloth.

6. Dry fit pipe and fitting joints prior to cementing. For proper interference fit, the pipe should go easily into the socket approximately ⅓ to ⅔ of the socket depth. If this is not the case, other pipe or fittings should be used.

7. The applicator should be sized according to the size of pipe and fittings being joined. The brush width of the applicator should be equal to approximately ½ of the pipe diameter.

8. Primer is used to penetrate and soften the surfaces so that they will fuse together under a wide variety of conditions. The penetration or softening can be checked by dragging the edge of a knife or sharp object over the coated surface. If a few thousandths of an inch of the primed surface can be scratched or scraped away, proper penetration has occurred. Varying weather conditions affect priming and cementing action and may require more time or repeated applications to either or both surfaces.

9. If using primer, use the correct applicator size (see #7) and aggressively work the primer into the socket, keeping the surface and applicator wet until the surface has softened, re-dipping the applicator as required. When the surface is primed, remove any puddles of primer from the socket.

10. Aggressively work the primer on to the end of the pipe, to a point ½" beyond the depth of the socket.

11. Perform a second application of primer in the socket.

12. While the surfaces are still wet, the appropriate solvent cement should be applied.

13. Using the correct applicator size, aggressively work a full, even layer of cement onto the pipe end to a point equal to the depth of the socket. Do not brush out to a thin paint type layer, as this will dry within a few seconds.

14. Aggressively work a medium layer of cement into the fitting socket; avoid puddling cement in the socket. On the pipe end, do not coat beyond the socket depth or allow cement to run down into the pipe beyond the socket.

15. Apply a second full, even layer of cement on the pipe.

16. Immediately, while the cement is still wet, assemble the joint. Use enough force to ensure that the pipe is fully inserted into the socket. Twist the pipe a ¼ turn as it is being inserted.

17. Hold the joint together for approximately 30 seconds to avoid push out.

18. After assembly, inspect the joint to ensure that there is a ring or bead of cement completely around the juncture of the pipe and socket. If there are voids in this ring, sufficient cement was not applied and the joint may be defective.

19. Remove the excess cement from the pipe and socket (including the ring or bead) using a cloth. Avoid disturbing or moving the joint.

20. Handle newly cemented joints with care until initial set has taken place. Follow set and cure times before handling or testing the system.

Pipe Dimensions

Nominal Size mm (in)	Avg. Outside Diameter mm (in)	Avg. Inside Diameter mm (in)	Avg. Wall Thickness mm (in)	Approx. Weight lb/100ft (kg/m)
12 (½)	21 (0.840)	15 (0.608)	3 (0.116)	16.1 (0.24)
19 (¾)	27 (1.050)	21 (0.810)	3 (0.120)	21.5 (0.32)
25 (1)	33 (1.315)	26 (1.033)	4 (0.141)	31.9 (0.47)
32 (1¼)	42 (1.660)	35 (1.362)	4 (0.149)	43.8 (0.65)
38 (1½)	48 (1.900)	40 (1.592)	4 (0.154)	52.3 (0.78)
50 (2)	60 (2.375)	52 (2.049)	4 (0.163)	70.3 (1.05)
63 (2½)	73 (2.875)	62 (2.445)	5 (0.215)	112.0 (1.61)
75 (3)	89 (3.500)	77 (3.042)	6 (0.229)	146.7 (2.18)
90 (3½)	102 (4.000)	89 (3.520)	6 (0.240)	176.4 (2.63)
100 (4)	114 (4.500)	102 (3.998)	6 (0.251)	208.9 (3.11)
125 (5)	141 (5.565)	127 (5.017)	7 (0.274)	283.4 (4.22)
150 (6)	168 (6.625)	153 (6.031)	8 (0.297)	368.0 (5.48)

Specification

All wiring shall be installed in Royal Electrical Solutions Rigid PVC Conduit and secured with proper fittings. All conduit and fittings shall be manufactured by Royal Building Products, Pipe & Fittings Solutions. All outlets, pull boxes and junction points shall be Royal products.

Exposed conduit shall be securely attached and supported with straps that are installed at the recommended spacing specified in CEC Section 12-1114. The straps must allow for linear expansion and contraction of the conduit due to temperature change. If the variance in temperature exceeds 14°C (25°F), expansion joints shall be installed according to the manufacturer's recommendations.

If Rigid PVC Conduit is embedded in concrete or direct buried, support straps are not required.

Solvent Cementing

All connections should be made using and applying Royal Electrical Solutions solvent cement.

Set Times

Average Initial Set Times			
Temperature Range	Pipe Sizes ½" to 1¼"	Pipe Sizes 1½" to 2"	Pipe Sizes 2½" to 6"
15°C to 40°C	2 min.	5 min.	30 min.
5°C to 15°C	5 min.	10 min.	2 hrs.
-16°C to 5°C	10 min.	15 min.	12 hrs.

Joint Cure Schedule

Average Joint Cure Times			
Temperature Range During Assembly & Cure Periods	Pipe Sizes ½" to 1¼"	Pipe Sizes 1½" to 2"	Pipe Sizes 2½" to 6"
15°C to 40°C	2 min.	5 min.	30 min.
5°C to 15°C	5 min.	10 min.	2 hrs.
-16°C to 5°C	10 min.	15 min.	12 hrs.

In damp or humid weather allow 50% more cure time.

Estimated Solvent Cement Requirements

Average Number of Joints per Litre of Solvent Cement									
Pipe/Fitting Diameter	½"	¾"	1"	1½"	2"	2½"	3"	4"	6"
Number of Joints	300	200	125	90	60	40	40	30	10

Estimated Primer Requirements

Average Number of Joints per Litre of Primer									
Pipe/Fitting Diameter	½"	¾"	1"	1½"	2"	2½"	3"	4"	6"
Number of Joints	600	400	250	180	120	80	80	60	20

Solvent Cementing in Cold Weather:

- Store pipe and fittings in a heated area. Prefabricate as much of the system as possible in a heated area.
- When not in use, store sealed solvent cement and primer between 5°C and 21°C. Do not use open flame or electric heaters to warm cements and primers.
- Take care to remove moisture, ice and snow from the mating surfaces.

Solvent Cementing in Hot Weather:

- At the time of assembly, the surface temperature of the mating surfaces should not exceed 45°C. Shade or shelter the joint surfaces from direct sunlight for at least 1 hour prior to joining and during the joining process. If necessary, swab the mating surfaces with clean, wet rags to reduce the surface temperature (thoroughly dry surfaces before applying primer or cement).
- Make joints during the cooler early morning hours.
- Apply cement quickly and join pipe to fitting as quickly as possible after applying the cement.
- Keep solvent cement container closed or covered when not in use, to minimize solvent loss.

Solvent Cementing in Wet Conditions:

- Mating surfaces must be dry when the joint is made.
- Work under a cover or canopy to keep rain off pipe and fittings.
- Work quickly after drying the pipe and fitting to avoid condensation.
- Allow a longer cure time before the system is tested or used.

Storage and Handling of Solvent Cement and Primer:

- Solvent cement and primer contain highly flammable solvents. Follow all specific safety precautions provided on container label and Material Safety Data Sheet.
- Keep primer and solvent cement away from heat, sparks and open flame.
- Keep containers tightly closed except when in use.
- Ensure proper ventilation of work area and avoid inhaling solvent vapours.
- Where the possibility of splashing exists, wear proper eye protection or a face shield.
- Avoid contact with skin.

Support Straps

Rigid PVC conduit must be supported with straps when installed in above ground applications. These straps should be installed snugly, while allowing linear movement of the conduit. See the table below for recommended maximum spacing of support straps.

Maximum Recommended Spacing of Support Straps		
Nominal Size mm (in)	CEC Recommended Spacing ft (m)	NEC Recommended Spacing ft (m)
16 (½)	2½ (0.75)	3 (0.91)
21 (¾)	2½ (0.75)	3 (0.91)
27 (1)	2½ (0.75)	3 (0.91)
35 (1¼)	4 (1.20)	5 (1.50)
41 (1½)	4 (1.20)	5 (1.50)
53 (2)	6 (1.80)	5 (1.50)
63 (2½)	6 (1.80)	3 - 6 (1.80)
78 (3)-129 (5)	7 (2.10)	3½ - 5 (2.10)
155 (6)	8 (2.50)	8 (2.50)

Storing Conduit Pipe and Fittings

Store Rigid PVC conduit pipe and fittings at the same temperature. Otherwise they may expand and contract at different rates and become incompatible.

Maximum Operating Temperatures

According to the Canadian Electrical Code (CEC), Rigid PVC conduit is intended for use at a continuous operating temperature of 75°C (167°F). For US applications, our Rigid PVC conduit is rated for use with 90°C wiring, according to the requirements of the NEC.

Ambient Temperatures

Royal Electrical Solutions Rigid PVC Conduit and fittings can be installed in locations with an ambient temperature not exceeding 50°C (122°F).

Expansion Joints

According to the CEC, if the amount of expansion expected due to temperature variance during and after construction is more than 45mm, expansion joints must be used.

Expected Expansion

The coefficient of linear expansion for Rigid PVC conduit is as follows:

3×10^{-5} in (expansion/contraction) / in (pipe length) /°F (change in temperature),

5.4×10^{-5} mm (expansion/contraction)/mm (pipe length)/°C (change in temperature)





Note:

The following chart shows the amount of expansion expected with various pipe lengths/temperature changes. If the Rigid PVC Conduit is installed in an exposed location, 17°C (30°F) should be added to the amount of temperature change (ΔT) due to the effects of radiant heat.

Expansion/Contraction of PVC (mm)

Length of Pipe Run (m)

ΔT (°C)	2	4	6	8	10	12	14	16	18	20
5	0.54	1.08	1.62	2.16	2.70	3.24	3.78	4.32	4.86	5.40
10	1.08	2.16	3.24	4.32	5.40	6.48	7.56	8.64	9.72	10.80
15	1.62	3.24	4.86	6.48	8.10	9.72	11.34	12.96	14.58	16.20
20	2.16	4.32	6.48	8.64	10.80	12.96	15.12	17.28	19.44	21.60
25	2.70	5.40	8.10	10.80	13.50	16.20	18.90	21.60	24.30	27.00
30	3.24	6.48	9.72	12.96	16.20	19.44	22.68	25.92	29.16	32.40
35	3.78	7.56	11.34	15.12	18.90	22.68	26.46	30.24	34.02	37.80
40	4.32	8.64	12.96	17.28	21.60	25.92	30.24	34.56	38.88	43.20
45	4.86	9.72	14.58	19.44	24.30	29.16	34.02	38.88	43.74	48.60
50	5.40	10.80	16.20	21.60	27.00	32.40	37.80	43.20	48.60	54.00

Expansion/Contraction of PVC (in)

Length of Pipe Run (ft)

ΔT (°F)	5	10	15	20	25	30	35	40	45	50
5	0.01	0.02	0.03	0.04	0.05	0.05	0.06	0.07	0.08	0.09
10	0.02	0.04	0.05	0.07	0.09	0.11	0.13	0.14	0.16	0.18
15	0.03	0.05	0.08	0.11	0.14	0.16	0.19	0.22	0.24	0.27
20	0.04	0.07	0.11	0.14	0.18	0.22	0.25	0.29	0.32	0.36
25	0.05	0.09	0.14	0.18	0.23	0.27	0.32	0.36	0.41	0.45
30	0.05	0.11	0.16	0.22	0.27	0.32	0.38	0.43	0.49	0.54
35	0.06	0.13	0.19	0.25	0.32	0.38	0.44	0.50	0.57	0.63
40	0.07	0.14	0.22	0.29	0.36	0.43	0.50	0.58	0.65	0.72
45	0.08	0.16	0.24	0.32	0.41	0.49	0.57	0.65	0.73	0.81
50	0.09	0.18	0.27	0.36	0.45	0.54	0.63	0.72	0.81	0.90

Required Number of Expansion Joints

The following table shows the amount of travel that is available with each trade size of Royal Electrical Solutions Rigid PVC conduit expansion joints:

Part Number	Description in	Travel Allowance mm (in)
REJ10	½" Expansion Joint	102 (4)
REJ15	¾" Expansion Joint	102 (4)
REJ20	1" Expansion Joint	102 (4)
REJ25	1¼" Expansion Joint	102 (4)
REJ30	1½" Expansion Joint	102 (4)
REJ35	2" Expansion Joint	102 (4)
REJ40	2½" Expansion Joint	102 (4)
REJ45	3" Expansion Joint	204 (8)
REJ50	3½" Expansion Joint	204 (8)
REJ55	4" Expansion Joint	204 (8)
REJ60	5" Expansion Joint	204 (8)
REJ65	6" Expansion Joint	204 (8)

The required number of expansion joints can be calculated using the following formula:

$$\#\ \text{Expansion Joints Required} = \frac{\text{Total Expected Amount of Expansion (in)}}{\text{Expansion Joint Travel Allowance (in)}}$$

$$\#\ \text{Expansion Joints Required} = \frac{\text{Total Expected Amount of Expansion (mm)}}{\text{Expansion Joint Travel Allowance (mm)}}$$

The number of expansion joints calculated above should be rounded up to the nearest whole number.

Setting the Piston Opening

Expansion joints must be installed such that they allow for both expansion and contraction of the conduit. The piston of the expansion joint must be set at the correct position to allow for this linear movement. To determine the correct position for the piston at the time and temperature of installation, the following formula should be used:

$$\text{Piston Setting (in)} = \frac{\text{(Max. Temp. (°F) – Install. Temp. (°F))}}{\text{Total Expected Temperature Change (°F)}} \times \left[\text{Expansion Joint Expansion Allow. (in)}\right]$$

$$\text{Piston Setting (mm)} = \frac{\text{(Max. Temp. (°C) – Install. Temp. (°C))}}{\text{Total Expected Temperature Change (°C)}} \times \left[\text{Expansion Joint Expansion Allow. (mm)}\right]$$

Installation Guidelines

• Securely fasten the expansion joint barrel so that it does not shift. Loosely connect the conduit so that it is free to move.


• To function properly, expansion joints should be installed near a fixed point.

• It is better to use more expansion joints than not enough, since problems are difficult to correct after conductors and wires have been pulled through the conduit.

• Ensure that the barrel and piston are aligned and level.

• For vertical installations of expansion joints, install with the piston at the bottom to prevent dirt and water from getting inside the joint and causing it to malfunction.

Installation Example



If one expansion joint is required:
Securely fasten the barrel of the expansion joint close to one of the boxes. Support the conduit with straps, but allow free movement of the conduit for expansion and contraction. (See Drawing 1)

If two expansion joints are required:
There are two options available:


1. Firmly fasten one expansion joint near each end of the run and firmly fasten the conduit at the centre. Support the rest of the conduit with straps allowing for movement of the conduit. (See Drawing 2)

2. Firmly fasten the expansion joints back-to-back at the centre of the run. The conduit should be supported with straps to allow free movements as it expands and contracts. (See Drawing 3)


If three or more expansion joints are required:
Evenly space the expansion joints along the run of Rigid PVC conduit. Tightly fasten each expansion joint and support the conduit with straps. Do not restrict the movement of the conduit.


*For information on Maximum Recommended Spacing of Support Straps, see page 4.


Drawings 1 - 4




FITTINGS - Bends (Bell Ends)


90° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1090	46120	0.840	1.500	4.00
	¾	REE1590	46150	1.050	1.500	4.50
	1	REE2090	46180	1.315	1.875	5.75
	1¼	REE2590	46210	1.660	2.000	7.25
	1½	REE3090	46240	1.900	2.000	8.25
	2	REE3590	46270	2.375	2.000	9.50
	2½	REE4090	46330	2.875	3.000	10.50
	3	REE4590	46360	3.500	3.125	13.00
	3½	REE5090	46390	4.000	3.250	15.00
	4	REE5590	46420	4.500	3.375	16.00
	5	REE6090	46440	5.565	3.622	24.00
	6	REE6590	46460	6.625	3.740	30.00


45° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1045	46120	0.840	1.500	4.00
	¾	REE1545	46150	1.050	1.500	4.50
	1	REE2045	46180	1.315	1.875	5.75
	1¼	REE2545	46210	1.660	2.000	7.25
	1½	REE3045	46240	1.900	2.000	8.25
	2	REE3545	46270	2.375	2.000	9.50
	2½	REE4045	46330	2.875	3.000	10.50
	3	REE4545	46360	3.500	3.125	13.00
	3½	REE5045	46390	4.000	3.250	15.00
	4	REE5545	46420	4.500	3.375	16.00
	5	REE6045	46440	5.565	3.625	24.00
	6	REE6545	46460	6.625	3.750	30.00


30° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1030	46100	0.840	1.500	4.00
	¾	REE1530	46130	1.050	1.500	4.50
	1	REE2030	46160	1.315	1.875	5.75
	1¼	REE2530	46190	1.660	2.000	7.25
	1½	REE3030	46220	1.900	2.000	8.25
	2	REE3530	46274	2.375	2.000	9.50
	2½	REE4030	46310	2.875	3.000	10.50
	3	REE4530	46340	3.500	3.125	13.00
	3½	REE5030	46375	4.000	3.250	15.00
	4	REE5530	46400	4.500	3.375	16.00
	5	REE6030	46425	5.565	3.625	24.00
	6	REE6530	46442	6.625	3.750	30.00


Utilities 90° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	2	REE2-24	46501	2.375	41.20	24.00
	2	REE2-36	46502	2.375	31.70	36.00
	3	REE3-24	46503	3.500	41.20	24.00
	3	REE3-36	46504	3.500	31.70	36.00
	4	REE4-36	46465	4.500	31.70	36.00
	4	REE4-48	46505	4.500	31.70	48.00
	5	REE5-36	46506	5.565	31.70	36.00
	6	REE6-36	46507	6.625	31.70	36.00

Fittings - Bends (Plain Ends)


90° Elbows - Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1090PE	46120	0.840	1.500	4.00
	¾	REE1590PE	46150	1.050	1.500	4.50
	1	REE2090PE	46180	1.315	1.875	5.75
	1¼	REE2590PE	46210	1.660	2.000	7.25
	1½	REE3090PE	46240	1.900	2.000	8.25
	2	REE3590PE	46270	2.375	2.000	9.50
	2½	REE4090PE	46330	2.875	3.000	10.50
	3	REE4590PE	46360	3.500	3.125	13.00
	3½	REE5090PE	46390	4.000	3.250	15.00
	4	REE5590PE	46420	4.500	3.375	16.00
	5	REE6090PE	46440	5.565	3.622	24.00
	6	REE6590PE	46460	6.625	3.740	30.00


45° Elbows - Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1045PE	46110	0.840	1.500	4.00
	¾	REE1545PE	46140	1.050	1.500	4.50
	1	REE2045PE	46170	1.315	1.875	5.75
	1¼	REE2545PE	46200	1.660	2.000	7.25
	1½	REE3045PE	46230	1.900	2.000	8.25
	2	REE3545PE	46280	2.375	2.000	9.50
	2½	REE4045PE	46320	2.875	3.000	10.50
	3	REE4545PE	46350	3.500	3.125	13.00
	3½	REE5045PE	46380	4.000	3.250	15.00
	4	REE5545PE	46415	4.500	3.375	16.00
	5	REE6045PE	46430	5.565	3.622	24.00
	6	REE6545PE	46450	6.625	3.740	30.00


30° Elbows - Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1030PE	46100	0.840	1.500	4.00
	¾	REE1530PE	46130	1.050	1.500	4.50
	1	REE2030PE	46160	1.315	1.875	5.75
	1¼	REE2530PE	46190	1.660	2.000	7.25
	1½	REE3030PE	46220	1.900	2.000	8.25
	2	REE3530PE	46274	2.375	2.000	9.50
	2½	REE4030PE	46310	2.875	3.000	10.50
	3	REE4530PE	46340	3.500	3.125	13.00
	3½	REE5030PE	46375	4.000	3.250	15.00
	4	REE5530PE	46400	4.500	3.375	16.00
	5	REE6030PE	46425	5.565	3.622	24.00
	6	REE6530PE	46442	6.625	3.740	30.00


45° Elbows - Extended Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	1¼	REE2590E	46125	1.660	14.750	7.25
	1½	REE3090E	46260	1.900	14.750	8.25
	2	REE3590E	43290	2.375	14.750	9.50

Fittings - Couplings and Adapters

Couplings	Sizes (in)	Product Code	UPC Number	Outside Diameter (OD) (in)	Inside Diameter (ID) (in)	Length (L) (in)
	½	REC10	45950	1.080	0.840	1.437
	¾	REC15	45960	1.300	1.050	1.703
	1	REC20	45970	1.590	1.315	2.031
	1¼	REC25	45980	2.000	1.660	2.156
	1½	REC30	45990	2.230	1.900	2.281
	2	REC35	46000	2.720	2.375	2.406
	2½	REC40	46010	3.320	2.875	3.187
	3	REC45	46020	4.000	3.500	3.437
	3½	REC50	46030	4.500	4.000	3.625
	4	REC55	46060	5.000	4.500	3.750
	5	REC60	46080	6.120	5.565	4.187
	6	REC65	46090	7.370	6.625	4.562


5° Couplings *(*Fabricated)*	Sizes (in)	Product Code	UPC Number	Outside Diameter (OD) (in)	Inside Diameter (ID) (in)	Length (L) (in)
	2	R5EC35	46800	2.375	2.049	4.0
	2½	R5EC40	46805	3.500	2.445	5.5
	3	R5EC45	46810	3.500	3.042	6.0
	3½	R5EC50	46815	4.500	3.521	7.0
	4	R5EC55	46820	4.500	3.998	7.0
	5	R5EC60	46825	5.565	5.018	7.5
	6	R5EC65	46830	6.625	6.031	11.0

Terminal Adapters (½" - 1¼" Tapered Thread, 6" NPT)	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	Inside Diameter (ID) (in)	Thread (in)
	½	RTA10	45730	0.750	0.700	0.591	1.550
	¾	RTA15	45740	1.000	0.675	0.790	1.750
	1	RTA20	45750	1.115	0.625	1.000	1.860
	1¼	RTA25	45760	1.300	0.640	1.311	2.125
	1½	RTA30	45770	1.425	0.725	1.530	2.250
	2	RTA35	45780	1.150	0.800	1.970	2.100
	2½	RTA40	45790	1.900	0.800	2.346	2.930
	3	RTA45	45800	2.000	0.815	2.915	3.055
	3½	RTA50	45810	1.715	1.000	3.385	3.055
	4	RTA55	45820	1.990	0.815	3.850	3.215
	5	RTA60	45830	2.000	1.725	5.015	5.985
	6	RTA65	45840	2.130	1.875	6.025	6.500

Female Adapters (Npt Tapered Thread)	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	Inside Diameter (ID) (in)	Thread (in)
	½	RFA10	44990	0.800	0.825	0.620	1.725
	¾	RFA15	45000	0.800	1.000	0.820	1.900
	1	RFA20	45010	1.000	1.200	1.065	2.300
	1¼	RFA25	45020	1.015	1.300	1.395	2.425
	1½	RFA30	45030	1.050	1.290	1.575	2.440
	2	RFA35	45040	1.075	1.375	2.050	2.550
	2½	RFA40	45050	1.675	1.985	2.470	3.760
	3	RFA45	45060	1.630	2.150	3.090	4.100
	3½	RFA50	45070	1.800	2.000	3.540	3.985
	4	RFA55	45080	1.755	2.185	4.025	4.210
	5	RFA60	45090	2.065	3.000	5.035	5.240
	6	RFA65	45100	2.065	3.000	6.045	5.235

Fittings - Expansions Joints, Straps and Meter Accessories

Expansion Joints



Sizes (in)	Product Code	UPC Number	Expanded Length (E) (in)	Contracted Length (C) (in)	Travel (in)
½	REJ10	44870	12.00	8.00	4.00
¾	REJ15	44880	12.00	8.00	4.00
1	REJ20	44890	12.50	8.50	4.00
1¼	REJ25	44900	13.00	9.00	4.00
1½	REJ30	44910	13.00	9.00	4.00
2	REJ35	44920	13.25	9.25	4.00
2½	REJ40	44930	13.25	9.25	4.00
3	REJ45	44940	22.25	14.25	8.00
3½	REJ50	44950	22.25	14.25	8.00
4	REJ55	44960	22.25	14.25	8.00
5	REJ60	44963	22.25	14.25	8.00
6	REJ65	44966	22.25	14.25	8.00

Expansion Joints

PVC — 2 Hole



Sizes (in)	Product No.	UPC No.
½	RPS10	45540
¾	RPS15	45550
1	RPS20	45560
1¼	RPS25	45570
1½	RPS30	45580
2	RPS35	45590

PVC Coated Steel — 2 Hole



Sizes (in)	Product No.	UPC No.
2	RCS35	44783
2½	RCS40	44784
3	RCS45	44785
3½	RCS50	44786
4	RCS55	44787
5	RCS60	44788
6	RCS65	44789

PVC Coated Steel — 1 Hole



Sizes (in)	Product No.	UPC No.
½	RCS10-1	46850
¾	RCS15-1	46852
1	RCS20-1	46854
1¼	RCS25-1	46856
1½	RCS30-1	46858
2	RCS35-1	46860
2½	RCS40-1	46862
3	RCS10-1	46864
4	RCS10-1	46866

Meter Offsets



Sizes (in)	Product No.	UPC No.
1¼	RM025	45500
2	RM035	45510

Meter Hubs



Sizes (in)	Product No.	UPC No.
1¼	RMHU25	45480
1½	RMHU30	45485
2	RMHU35	45490

Long Meter Offsets *(Fabricated)*



Sizes (in)	Product No.	UPC No.
1¼	RLM025	45472
1½	RML030	45474
2	RML035	45476

Expansion & Deflection Fittings Assembly



Sizes (in)	Product No.	UPC No.
2	RSEJ35	46990
3	RSEJ45	46992
4	RSEJ55	46994

Service Entrance Fittings




Sizes (in)	Product No.	UPC No.
½	REF10	44795
¾	REF15	44800
1	REF20	44810
1¼	REF25	44820
1½	REF30	44830
2	REF35	44840
2½	REF40	44842
3	REF45	44844
3½	REF50	44852
4	REF55	44860

Ecovoc Solvent Cement *(*c/w Screw Cap & Dauber)*




Sizes (in)	Product No.	UPC No.	Carton Qty.
250ml	RVOC250*	54790	24
475ml	RVOC475*	54795	12
950ml	RVOC950*	54797	12
4L	RVOC4L	54799	4


Privoc Solvent Cement *(*c/w Screw Cap & Dauber)*





Sizes (in)	Product No.	UPC No.	Carton Qty.
250ml	RVOCPR250*	54800	24
475ml	RVOCPR475*	54802	12
950ml	RVOCPR950*	54804	12
4L	RVOCPR4L	54806	4

Fittings - Access Fittings


Type C	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)
	½	RSC10S	46600	5.606	0.639	1.268	1.100	0.840
	¾	RSC20S	46605	5.606	0.810	1.536	1.325	1.050
	1	RSC30S	46610	6.500	0.910	1.700	1.600	1.335
	1¼	RSC40S	46615	7.900	1.050	2.300	2.250	1.100
	1½	RSC50S	46620	8.500	1.125	2.675	2.250	1.900
	2	RSC60S	45605	10.875	1.160	3.188	2.820	2.375
	2½	RSC70S	45606	14.600	1.750	4.500	3.950	2.870
	3	RSC80S	45607	14.600	1.900	4.500	3.950	3.510
	3½	RSC90S	45609	17.040	2.125	5.536	5.000	4.000
	4	RSC100S	45608	17.040	2.125	5.536	5.000	4.530


Type LB	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)	H (in)
	½	RSLB10S	45620	4.337	0.639	1.268	0.840	1.297	4.095	2.487	1.005
	¾	RSLB20S	45630	5.395	0.810	1.536	1.050	1.297	4.095	2.487	1.005
	1	RSLB30S	45640	6.250	0.910	1.700	1.335	1.500	4.750	2.075	1.125
	1¼	RSLB40S	45650	7.625	1.050	2.300	1.100	1.750	5.750	3.575	1.562
	1½	RSLB50S	45660	8.250	1.125	2.675	1.900	1.750	6.500	3.938	1.656
	2	RSLB60S	45670	10.531	1.160	3.188	2.375	2.344	8.156	4.535	1.968
	2½	RSLB70S	45675	13.630	1.750	4.500	2.870	2.733	9.825	6.240	2.610
	3	RSLB80S	45680	13.630	1.900	4.500	3.510	3.805	10.897	6.240	2.610
	3½	RSLB90S	45610	16.000	2.125	5.536	4.000	4.535	11.465	7.500	2.975
	4	RSLB100S	45681	16.000	2.125	5.536	4.530	4.535	11.465	7.500	2.975


Type LL	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)
	½	RSLL10S	46650	4.337	0.639	1.268	2.487	0.840	4.095	1.297
	¾	RSLL20S	46655	5.395	0.810	1.536	2.487	1.050	4.095	1.297
	1	RSLL30S	46660	6.250	0.910	1.700	2.075	1.335	4.750	1.500
	1¼	RSLL40S	46665	7.625	1.050	2.300	3.575	1.100	5.750	1.750
	1½	RSLL50S	46670	8.250	1.125	2.675	3.938	1.900	6.500	1.750
	2	RSLL60S	45682	10.531	1.160	3.188	4.535	2.375	8.156	2.344
	2½	RSLL70S	45672	13.630	1.750	4.500	6.240	2.870	9.825	3.805
	3	RSLL80S	46674	13.630	1.900	4.500	6.240	3.510	10.897	2.733
	3½	RSLL90S	46678	16.000	2.125	5.536	7.500	4.000	11.465	4.535
	4	RSLL100S	46676	16.000	2.125	5.536	7.500	4.530	11.465	4.535

Type LR	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)
	½	RSLR10S	46700	4.337	0.639	1.268	2.487	0.840	4.095	1.297
	¾	RSLR20S	46705	5.395	0.810	1.536	2.487	1.050	4.095	1.297
	1	RSLR30S	46710	6.250	0.910	1.700	2.075	1.335	4.750	1.500
	1¼	RSLR40S	46715	7.625	1.050	2.300	3.575	1.100	5.750	1.750
	1½	RSLR50S	46720	8.250	1.125	2.675	3.938	1.900	6.500	1.750
	2	RSLR60S	45683	10.531	1.160	3.188	4.535	2.375	8.156	2.344
	2½	RSLR70S	46725	13.630	1.750	4.500	6.240	2.870	9.825	3.805
	3	RSLR80S	46728	13.630	1.900	4.500	6.240	3.510	10.897	2.733
	3½	RSLR90S	46738	16.000	2.125	5.536	7.500	4.000	11.465	4.535
	4	RSLR100S	46735	16.000	2.125	5.536	7.500	4.530	11.465	4.535

Fittings - Access Fittings

Type E	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)
	½	RSE10S	46630	4.337	0.639	1.268	0.840
	¾	RSE20S	46632	5.395	0.810	1.536	1.050
	1	RSE30S	46634	6.250	0.910	1.700	1.335
	1¼	RSE40S	46636	7.625	1.050	2.300	1.100
	1½	RSE50S	46638	8.250	1.125	2.675	1.900
	2	RSE60S	46640	10.351	1.160	3.188	2.375
	2½	RSE70S	46642	13.630	1.750	4.500	2.870
	3	RSE80S	46644	13.630	1.900	4.500	3.510
	3½	RSE90S	46648	16.000	2.125	5.536	4.000
	4	RSE100S	46646	16.000	2.125	5.536	4.530

Type T	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)
	½	RST10S	45690	2.280	0.639	1.100	0.840
	¾	RST20S	45700	2.803	0.810	1.325	1.050
	1	RST30S	45710	3.250	0.910	1.600	1.335
	1¼	RST40S	45720	3.950	1.050	2.250	1.100
	1½	RST50S	45723	4.250	1.125	2.250	1.900
	2	RST60S	45725	5.438	1.160	2.820	2.375
	2½	RST70S	46745	7.300	1.750	3.950	2.870
	3	RST80S	46748	7.300	1.900	3.950	3.510
	3½	RST90S	46752	8.535	2.125	5.000	4.000
	4	RST100S	46750	8.535	2.125	5.000	4.530

Type TB	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)	H (in)
	½	RSTB10S	45692	2.280	0.639	1.268	1.100	0.840	2.487	1.005	0.750
	¾	RSTB20S	45702	2.803	0.810	1.536	1.325	1.050	2.487	1.005	0.810
	1	RSTB30S	45712	3.250	0.910	1.700	1.600	1.335	2.075	1.125	1.115
	1¼	RSTB40S	45721	3.950	1.050	2.300	2.250	1.100	3.575	1.562	1.300
	1½	RSTB50S	45724	4.250	1.125	2.675	2.250	1.900	3.938	1.656	1.425
	2	RSTB60S	45727	5.438	1.160	3.188	2.820	2.375	4.535	1.968	1.160
	2½	RSTB70S	46760	7.300	1.750	4.500	3.950	2.870	6.240	2.610	-
	3	RSTB80S	46762	7.300	1.900	4.500	3.950	3.510	6.240	2.610	-
	3½	RSTB90S	46766	8.535	2.125	5.536	5.000	4.000	7.500	2.975	-
	4	RSTB100S	46764	8.535	2.125	5.536	5.000	4.530	7.500	2.975	-

Fittings - Cover Plates

Single Gang Cover Plates - F Series



Description	Product Code	UPC Number
Toggle Switch	RTSC15-10	45845
Duplex Receptacle	RDRC15-10R20	44685
Single Receptacle - 15 Amp	RC15-10R20-3	47035
Single Receptacle - 20 Amp	RC15-10R30-3	47036
Single Receptacle - 30 Amp	RC15-10	47037
Single Blank with Gasket	RBRC15-10	44680
Gasket	GASK15-10	44682

Double Gang Cover Plates - F Series



Description	Product Code	UPC Number
Double Switch	RTSC20-2	45846
Combo Switch/Receptacle	RTSDC20-2	45847
Double Duplex	RDRC20-2	44686
Double Blank with Gasket	RBRC20-2	44681
Gasket	GASK20-2	45949

Triple Gang Cover Plates - F Series



Description	Product Code	UPC Number
Triple Switch	RTSC20-3	45857
Double Switch Receptacle	RDSDR20-3	44689
Double Receptacle/Switch	RTSDC20-3	45858
Triple Receptacle	RDRC20-3	44688
Triple Blank with Gasket	RBRC20-3	44683
Gasket	GASK20-3	45859

Fittings - Weatherproof Cover Plates

Single Gang Weatherproof Cover Plates



RVSC15-10 RVSC15-10 RWTG15-10 RWGF15-10 RWTL RVSC15-10 GASK W

Description	Product Code	UPC Number
Toggle Switch Cover	RVSC15-10	45940
Plunger Switch Cover	RVPT15-10	45930
Toggle	RWTG15-10	45339
Duplex Receptacle	RWDR15-10	45093
Duplex Receptacle - White	RWDR15-10W	45094
Ground Fault Receptacle	RWGF15-10	45095
Ground Fault Receptacle - White	RWGF15-10W	45098
Single Receptacle - 15 Amp	RWTL15	45470
Single Receptacle - 20 Amp	RWTL20	45472
Single Receptacle - 30 Amp	RWTL30	45480
Single Receptacle - 50 Amp	RWTL50	45482
Gasket	GASK W	45484

Double Gang Weatherproof Cover Plates



RVSC20-2 RVSRC20-2 RVSDR20-2 RVSRR20-2 GASK20-2

Description	Product Code	UPC Number
Double Toggle	RVSC20-2	45941
Plunger/GFI	RVSRC20-2	45947
Plunger/Duplex Receptacle	RVSDR20-2	45945
Plunger/Single Receptacle	RVSRR20-2	45948
Gasket	GASK20-2	45949

Fittings - Slab Boxes

Single Gang Boxes - F Series



RFS



RFSS



RFSC



RFSCC

Description	Product Code	UPC Number	Volume (in3)
½" FS	RFS10	45200	17.0
¾" FS	RFS15	45210	17.0
½" FSS	RFSS10	45240	17.5
¾" FSS	RFSS15	45250	17.5
½" FSC	RFSC10	45220	16.3
¾" FSC	RFSC15	45230	16.3
½" FSCC	RFSCC10	45233	17.0
¾" FSCC	RFSCC15	45235	17.0

Single Gang Deep Boxes - FD Series



RFDS



RFDC



BLANK



347 VOLT

Outside Dimensions: Length = 4.5", Width = 6.6", Height = 2.5", except BLANK, L = 4.5", W = 6.6", H = 3.0"

Description	Product Code	UPC Number	Volume (in3)
½" FSC	RFSC3-10	45224	56.0
¾" FSC	RFSC3-15	45232	56.0
1" FSC	RFSC3-20	45228	56.0
½" FS	RFS3-10	45208	54.0
¾" FS	RFS3-15	45218	54.0
1" FS	RFS3-20	45219	54.0
BLANK	RFD-3	45155	73.8

Double Gang Boxes - F Series


FS


FSS


FSC


FSCC


BLANK

Outside Dimensions: Length = 4.5", Width = 4.75", Height = 2.5", except BLANK, L=4.75", W=4.75", H=3.0"

Description	Product Code	UPC Number	Volume (in3)
½" FS	RFS2-10	45205	39.5
¾" FS	RFS2-15	45215	39.5
1" FS	RFS2-20	45216	39.5
½" FSS	RFSS2-10	45242	37.0
¾" FSS	RFSS2-15	45244	37.0
1" FSS	RFSS2-20	45246	37.0
½" FSC	RFSC2-10	45222	37.0
¾" FSC	RFSC2-15	45231	37.0
1" FSC	RFSC2-20	45226	37.0
½" FSCC	RFSCC2-10	45234	36.0
¾" FSCC	RFSCC2-15	45238	36.0
1" FSCC	RFSCC2-20	45239	36.0
BLANK	RFD-D	45150	52.0

Triple Gang Boxes - F Series


FSC


FS


BLANK

Outside Dimensions: Length = 4.5", Width = 6.6", Height = 2.5", except BLANK, L = 4.5", W = 6.6", H = 3.0"

Description	Product Code	UPC Number	Volume (in3)
½" FSC	RFSC3-10	45224	56.0
¾" FSC	RFSC3-15	45232	56.0
1" FSC	RFSC3-20	45228	56.0
½" FS	RFS3-10	45208	54.0
¾" FS	RFS3-15	45218	54.0
1" FS	RFS3-20	45219	54.0
BLANK	RFD-3	45155	73.8

Octagonal Boxes



Size (in)	Product No.	UPC No.
4 x 1½	ROB15/10	45520
4 x 2	ROB20	45525
¾	RKO15	45450
1	RKO20	45455


Octagonal Box Extension Rings



Size (in)	Product No.	UPC No.
1	RXR20	46490
2	RXR35	46495

Junction Boxes With Gasket









Nominal Size (in)	Product Number	UPC Number	Inside Length & Width (A) (in)	Outside Length & Width (B) (in)	Length Screw to Screw (C) (in)	Outside Height (E) (in)	Inside Height (D) (in)	Screw Size (F)	Volume (in3)
4 x 4 x 2	RJB442	45300	3.675	4.000	3.450	2.125	2.000	8-32	25.4
4 x 4 x 4	RJB444	45310	3.675	4.000	3.450	4.188	3.750	8-32	47.5
4 x 4 x 6	RJB446	45315	3.675	4.000	3.450	6.225	6.000	8-32	76.1
5 x 5 x 2	RJB552	45320	4.680	5.000	4.485	2.000	1.845	8-32	38.7
6 x 6 x 4	RJB664	45330	6.000	6.375	5.813	4.188	4.000	10-32	139.5
6 x 6 x 6	RJB666	45335	6.000	6.375	5.813	6.188	6.000	10-32	209.3
8 x 8 x 4	RJB884	45340	8.075	8.625	7.996	4.230	4.005	¼-20	258.6
8 x 8 x 7	RJB887	45350	8.100	8.625	7.996	7.250	7.035	¼-20	455.6
12 x 12 x 4	RJB12124	45280	12.085	12.580	11.874	4.256	4.030	¼-20	578.3
12 x 12 x 6	RJB12126	45290	12.085	12.580	11.874	6.240	6.025	¼-20	864.6
12 x 12 x 8	RJB12128	45295	12.085	12.580	11.874	8.250	8.025	¼-20	1151.6

Highway Boxes









Nominal Size (in)	Product Number	UPC Number	Box Inside Length & Width (B) (in)	Box Inside Depth (H) (in)	Lid Length & Width (L) (in)	Thickness of Lid (T) (in)	Volume (in3)
6 x 6 x 4	H664	47040	6.0	4.25	9.0	0.60	139.5
6 x 6 x 6	H666	47041	6.0	6.25	9.0	0.60	209.3
8 x 8 x 4	H884	47042	8.0	4.25	11.5	0.75	258.6
8 x 8 x 6	H886	47043	8.0	6.25	11.5	0.75	400.0
8 x 8 x 7	H887	47044	8.0	7.25	11.5	0.75	455.6
8 x 8 x 7	H887-A	47045	8.0	7.25	11.5	0.75	418.4

Junction Box Adapters



Size (in)	Product No.	UPC No.
½	RJBA10	45360
¾	RJBA15	45370
1	RJBA20	45380
1¼	RJBA25	45390
1½	RJBA30	45400
2	RJBA35	45410
2½	RJBA40	45420
3	RJBA45	45430
3½	RJBA50	45435
4	RJBA55	45440

Duplex Floor Boxes & Cover (*Includes Leveling Ring)



Size (in)	Product No.	UPC No.
4 x ¾	RFDB4	46980
2 x ¾, 2 x 1	RFDB2	46982
Polycarbonate Bronze Cover	RFDBC	46984

Notes:

Our various pipe and fittings solutions have been manufactured to meet the needs of our customers and their applications. Contact one of the below Sales Centres for more information:

- Municipal Pipe & Fittings Solutions
- Plumbing Pipe & Fittings Solutions
- Electrical Pipe & Fittings Solutions
- Industrial Pipe & Fittings Solutions
- Irrigation Pipe & Fittings Solutions

Sales & Distribution Centres:

Langley, BC, Canada
T/F 1.800.663.0696
F 1.800.663.6564

Woodbridge, ON, Canada
T/F 1.866.769.7473
F 905.856.3986

Laval, QC, Canada
T/F 1.800.465.9754
F 450.688.6624

Distribution Centres:

Calgary, AB, Canada
T/F 1.800.663.0696
F 1.800.663.6564

Winnipeg, MB, Canada
T/F 1.800.663.0696
F 1.800.663.6564

royalelectricalca.com





MIX
Paper from responsible sources
FSC® C003472

E_RCPF_BRV4
Printed 02.2014

ROYAL® Building Products

Pipe & Fittings Solutions | Municipal Plumbing Electrical Industrial Irrigation

Rigid PVC Conduit Pipe & Fittings

A system for residential, industrial, commercial and institutional applications.

Product Description & Applications

Royal Building Products® Electrical Solutions manufactures a complete line of Rigid PVC Conduit pipe and fittings for electrical applications. Our products are designed to reduce labour and maintenance costs, while offering superior performance.

Products are certified by the Canadian Standards Association (CSA) and Underwriters Laboratories (UL) for use in above and below ground applications. Our Rigid PVC conduit pipe and fittings are available in 12 to 150mm (½- to 6-inch) diameters and 3- or 6-metre (10- or 20-foot) lengths.

Standards and Codes

Royal Electrical Solutions Rigid PVC Conduit pipe and fittings are certified to CSA Standards as noted below. Our Rigid PVC conduit pipe and fittings shall be installed according to the Canadian Electrical Code (CEC) Part I, Rules 12-1100 - 12-1122 and the National Electrical Code (NEC) Article 352.

Pipe	Fittings
C22.2 No. 211.2	C22.2 No. 18.2, 85 (Boxes) No. 40 (Electrical Encl.) No. 42.1 (Covers) No. 85 (Fittings)
UL 651	UL 514C (Boxes) UL 50 (Electrical Encl.) UL 514D (Covers) UL 651 (Fittings)
Conforms to NEMA TC2	





Features and Benefits

Saves Labour

Rigid PVC Conduit pipe and fittings are easy to install, cut and join.

Easy Wire Pulls

The conduit's smooth interior surface reduces friction and prevents damage to wires when pulling wire and conductors for long runs and even through 90° bends.

Lightweight Materials

Rigid PVC Conduit is easier to move and handle because it is approximately one-fifth the weight of steel and half the weight of aluminum.

Approximate Weight Comparison

Size mm (in)	PVC lb/100ft (kg/m)	Aluminum lb/100ft (kg/m)	Steel lb/100ft (kg/m)
12 (½)	16.1 (0.24)	27 (0.40)	79 (1.20)
19 (¾)	21.5 (0.32)	37 (0.55)	105 (1.55)
25 (1)	31.9 (0.47)	53 (0.80)	153 (2.30)
32 (1¼)	43.8 (0.65)	70 (1.05)	201 (3.00)
38 (1½)	52.3 (0.78)	86 (1.30)	249 (3.70)
50 (2)	70.3 (1.05)	116 (1.75)	334 (5.00)
63 (2½)	112.0 (1.61)	183 (2.75)	527 (7.85)
75 (3)	146.7 (2.18)	239 (3.55)	690 (10.25)
90 (3½)	176.4 (2.63)	288 (4.30)	831 (12.40)
100 (4)	208.9 (3.11)	340 (5.10)	982 (14.60)
125 (5)	283.4 (4.22)	465 (6.90)	1,344 (20.40)
150 (6)	368.0 (5.48)	613 (9.10)	1,771 (26.35)

Simplifies Direct Burial

Royal Electrical Solutions Rigid PVC Conduit does not require additional protection for direct burial installations according to the Canadian Electrical Code (CEC) and the National Electrical Code (NEC). Normal construction practices should be followed for trenching and backfill operations.

Non-Conductive

Rigid PVC Conduit is non-conductive.

Long Life

Royal Rigid PVC Conduit and fittings resist acids, alkalis, salt solutions and most other chemicals. (Refer to the Royal Chemical Resistance Guide for detailed information.) There is no risk of corrosion when exposed to naturally corrosive soil conditions, electrochemical or galvanic environments. Royal's Rigid PVC Conduit has achieved sunlight resistance as per the requirements of the Electrical Code.

FT-4 Rating

Rigid PVC Conduit pipe has an FT-4 Rating and can be used in non-combustible construction as per Part 3 of the National Building Code of Canada (NBC).

Installation Guidelines

Cutting

Royal Rigid PVC Conduit can easily be cut with a hacksaw, a fine-toothed handsaw or PVC conduit cutters. For conduit with more than a 50mm (2-inch) diameter, use a mitre box or saw guide to ensure a square cut. Deburr the end using a knife or file.

Bending

It may be necessary to create bends in the field by heating and deforming Rigid PVC Conduit. To accomplish this, the following guidelines should be followed:

• For heating the Rigid PVC Conduit, use a heat gun or some other flameless heat source. Do not use an open flame to heat the conduit. Rigid PVC Conduit must be heated to approximately 127°C (260°F) in order to bend without kinking.

• Heat a length of conduit equal to approximately 10 times the nominal diameter.

• Once the Rigid PVC Conduit has been adequately heated, bend it to the required angle plus 3 extra degrees. The additional angle will accommodate the "spring back" which will occur during cooling.

• After bending of the conduit is completed, immediately cool the bend using water or cold air.

• According to the Canadian Electrical Code (CEC) and the National Electrical Code (NEC), the minimum bending radius for rigid conduit is as shown in the table below.

Nominal Size mm (in)	Min. Radius to Centre of Conduit or Tubing mm (in)
16 (½)	102 (4.016)
21 (¾)	114 (4.489)
27 (1)	146 (5.748)
35 (1¼)	184 (7.244)
41 (1½)	210 (8.268)
53 (2)	241 (9.488)
63 (2½)	267 (10.512)
78 (3)	330 (12.992)
91 (3½)	381 (14.606)
103 (4)	406 (15.984)
129 (5)	610 (24.016)
155 (6)	762 (30.000)





Procedure for Solvent Welding Joints

• Use solvent cement and primer prior to expiration date marked on container.

• Above 0° C ambient temperature, joints may be assembled without the use of primer, provided adequate penetration and softening of the pipe/fitting surface can be achieved with solvent cement alone.


1. Assemble materials for the job, including correct solvent cement, primer and correctly sized applicator.

2. Cut pipe as square as possible using a hand saw and miter box or mechanical saw. Do not use a diagonal cut, as it reduces the bonding area in the joint.

3. If plastic tubing cutters are used, care must be taken to remove any raised bead at the end of the pipe, caused by cutting. A file or reamer may be used to remove the bead.

4. Use a knife, file or reamer to remove burrs from the inside and outside of the pipe end, as these will hinder the integrity of the joint. All sharp edges should be removed from the inside and outside edges of the pipe to prevent the pipe from pushing the solvent cement into the fitting socket, thereby causing a weak spot to form. The pipe end should be chamfered, as shown below.

Chamfered Pipe



Procedure for Solvent Welding Joints Continued

5. All dirt, grease and moisture should be removed from the pipe and socket by thoroughly wiping with a clean, dry cloth.

6. Dry fit pipe and fitting joints prior to cementing. For proper interference fit, the pipe should go easily into the socket approximately ⅓ to ⅔ of the socket depth. If this is not the case, other pipe or fittings should be used.

7. The applicator should be sized according to the size of pipe and fittings being joined. The brush width of the applicator should be equal to approximately ½ of the pipe diameter.

8. Primer is used to penetrate and soften the surfaces so that they will fuse together under a wide variety of conditions. The penetration or softening can be checked by dragging the edge of a knife or sharp object over the coated surface. If a few thousandths of an inch of the primed surface can be scratched or scraped away, proper penetration has occurred. Varying weather conditions affect priming and cementing action and may require more time or repeated applications to either or both surfaces.

9. If using primer, use the correct applicator size (see #7) and aggressively work the primer into the socket, keeping the surface and applicator wet until the surface has softened, re-dipping the applicator as required. When the surface is primed, remove any puddles of primer from the socket.

10. Aggressively work the primer on to the end of the pipe, to a point ½" beyond the depth of the socket.

11. Perform a second application of primer in the socket.

12. While the surfaces are still wet, the appropriate solvent cement should be applied.

13. Using the correct applicator size, aggressively work a full, even layer of cement onto the pipe end to a point equal to the depth of the socket. Do not brush out to a thin paint type layer, as this will dry within a few seconds.

14. Aggressively work a medium layer of cement into the fitting socket; avoid puddling cement in the socket. On the pipe end, do not coat beyond the socket depth or allow cement to run down into the pipe beyond the socket.

15. Apply a second full, even layer of cement on the pipe.

16. Immediately, while the cement is still wet, assemble the joint. Use enough force to ensure that the pipe is fully inserted into the socket. Twist the pipe a ¼ turn as it is being inserted.

17. Hold the joint together for approximately 30 seconds to avoid push out.

18. After assembly, inspect the joint to ensure that there is a ring or bead of cement completely around the juncture of the pipe and socket. If there are voids in this ring, sufficient cement was not applied and the joint may be defective.

19. Remove the excess cement from the pipe and socket (including the ring or bead) using a cloth. Avoid disturbing or moving the joint.

20. Handle newly cemented joints with care until initial set has taken place. Follow set and cure times before handling or testing the system.

Pipe Dimensions

Nominal Size mm (in)	Avg. Outside Diameter mm (in)	Avg. Inside Diameter mm (in)	Avg. Wall Thickness mm (in)	Approx. Weight lb/100ft (kg/m)
12 (½)	21 (0.840)	15 (0.608)	3 (0.116)	16.1 (0.24)
19 (¾)	27 (1.050)	21 (0.810)	3 (0.120)	21.5 (0.32)
25 (1)	33 (1.315)	26 (1.033)	4 (0.141)	31.9 (0.47)
32 (1¼)	42 (1.660)	35 (1.362)	4 (0.149)	43.8 (0.65)
38 (1½)	48 (1.900)	40 (1.592)	4 (0.154)	52.3 (0.78)
50 (2)	60 (2.375)	52 (2.049)	4 (0.163)	70.3 (1.05)
63 (2½)	73 (2.875)	62 (2.445)	5 (0.215)	112.0 (1.61)
75 (3)	89 (3.500)	77 (3.042)	6 (0.229)	146.7 (2.18)
90 (3½)	102 (4.000)	89 (3.520)	6 (0.240)	176.4 (2.63)
100 (4)	114 (4.500)	102 (3.998)	6 (0.251)	208.9 (3.11)
125 (5)	141 (5.565)	127 (5.017)	7 (0.274)	283.4 (4.22)
150 (6)	168 (6.625)	153 (6.031)	8 (0.297)	368.0 (5.48)

Specification

All wiring shall be installed in Royal Electrical Solutions Rigid PVC Conduit and secured with proper fittings. All conduit and fittings shall be manufactured by Royal Building Products, Pipe & Fittings Solutions. All outlets, pull boxes and junction points shall be Royal products.

Exposed conduit shall be securely attached and supported with straps that are installed at the recommended spacing specified in CEC Section 12-1114. The straps must allow for linear expansion and contraction of the conduit due to temperature change. If the variance in temperature exceeds 14°C (25°F), expansion joints shall be installed according to the manufacturer's recommendations.

If Rigid PVC Conduit is embedded in concrete or direct buried, support straps are not required.

Solvent Cementing

All connections should be made using and applying Royal Electrical Solutions solvent cement.

Set Times

Average Initial Set Times			
Temperature Range	Pipe Sizes ½" to 1¼"	Pipe Sizes 1½" to 2"	Pipe Sizes 2½" to 6"
15°C to 40°C	2 min.	5 min.	30 min.
5°C to 15°C	5 min.	10 min.	2 hrs.
-16°C to 5°C	10 min.	15 min.	12 hrs.

Joint Cure Schedule

Average Joint Cure Times			
Temperature Range During Assembly & Cure Periods	Pipe Sizes ½" to 1¼"	Pipe Sizes 1½" to 2"	Pipe Sizes 2½" to 6"
15°C to 40°C	2 min.	5 min.	30 min.
5°C to 15°C	5 min.	10 min.	2 hrs.
-16°C to 5°C	10 min.	15 min.	12 hrs.

In damp or humid weather allow 50% more cure time.

Estimated Solvent Cement Requirements

Average Number of Joints per Litre of Solvent Cement									
Pipe/Fitting Diameter	½"	¾"	1"	1½"	2"	2½"	3"	4"	6"
Number of Joints	300	200	125	90	60	40	40	30	10

Estimated Primer Requirements

Average Number of Joints per Litre of Primer									
Pipe/Fitting Diameter	½"	¾"	1"	1½"	2"	2½"	3"	4"	6"
Number of Joints	600	400	250	180	120	80	80	60	20

Solvent Cementing in Cold Weather:

- Store pipe and fittings in a heated area. Prefabricate as much of the system as possible in a heated area.
- When not in use, store sealed solvent cement and primer between 5°C and 21°C. Do not use open flame or electric heaters to warm cements and primers.
- Take care to remove moisture, ice and snow from the mating surfaces.

Solvent Cementing in Hot Weather:

- At the time of assembly, the surface temperature of the mating surfaces should not exceed 45°C. Shade or shelter the joint surfaces from direct sunlight for at least 1 hour prior to joining and during the joining process. If necessary, swab the mating surfaces with clean, wet rags to reduce the surface temperature (thoroughly dry surfaces before applying primer or cement).
- Make joints during the cooler early morning hours.
- Apply cement quickly and join pipe to fitting as quickly as possible after applying the cement.
- Keep solvent cement container closed or covered when not in use, to minimize solvent loss.

Solvent Cementing in Wet Conditions:

- Mating surfaces must be dry when the joint is made.
- Work under a cover or canopy to keep rain off pipe and fittings.
- Work quickly after drying the pipe and fitting to avoid condensation.
- Allow a longer cure time before the system is tested or used.

Storage and Handling of Solvent Cement and Primer:

- Solvent cement and primer contain highly flammable solvents. Follow all specific safety precautions provided on container label and Material Safety Data Sheet.
- Keep primer and solvent cement away from heat, sparks and open flame.
- Keep containers tightly closed except when in use.
- Ensure proper ventilation of work area and avoid inhaling solvent vapours.
- Where the possibility of splashing exists, wear proper eye protection or a face shield.
- Avoid contact with skin.

Support Straps

Rigid PVC conduit must be supported with straps when installed in above ground applications. These straps should be installed snugly, while allowing linear movement of the conduit. See the table below for recommended maximum spacing of support straps.

Maximum Recommended Spacing of Support Straps		
Nominal Size mm (in)	CEC Recommended Spacing ft (m)	NEC Recommended Spacing ft (m)
16 (½)	2½ (0.75)	3 (0.91)
21 (¾)	2½ (0.75)	3 (0.91)
27 (1)	2½ (0.75)	3 (0.91)
35 (1¼)	4 (1.20)	5 (1.50)
41 (1½)	4 (1.20)	5 (1.50)
53 (2)	6 (1.80)	5 (1.50)
63 (2½)	6 (1.80)	3 - 6 (1.80)
78 (3)-129 (5)	7 (2.10)	3½ - 5 (2.10)
155 (6)	8 (2.50)	8 (2.50)

Rigid PVC Conduit Pipe & Fittings

A system for residential, industrial, commercial and institutional applications.







ROYAL® Electrical Solutions

ROYAL Electrical Solutions

Table of Contents



Product Description - Features and Benefits	1
Installation Guidelines - Solvent Welding Joints	2
Solvent Welding Joints/Pipe Dimensions/Specs	3
Solvent Cementing	4
Expansion and Contraction	5
Setting the Piston Opening	6
Fittings - Bends (Bell End)	7-8
Fittings - Miscellaneous	9-18

Note: This brochure is not intended to assume the authority of the Design Engineer. Actual jobsite conditions will vary significantly. The sole responsibility for all design and installation decisions lies with the Design Engineer. All local health and safety regulations must be followed.

Rigid PVC Conduit Pipe & Fittings

A system for residential, industrial, commercial and institutional applications.

Product Description & Applications

Royal Building Products® Electrical Solutions manufactures a complete line of Rigid PVC Conduit pipe and fittings for electrical applications. Our products are designed to reduce labour and maintenance costs, while offering superior performance.

Products are certified by the Canadian Standards Association (CSA) and Underwriters Laboratories (UL) for use in above and below ground applications. Our Rigid PVC conduit pipe and fittings are available in 12 to 150mm (½- to 6-inch) diameters and 3- or 6-metre (10- or 20-foot) lengths.

Standards and Codes

Royal Electrical Solutions Rigid PVC Conduit pipe and fittings are certified to CSA Standards as noted below. Our Rigid PVC conduit pipe and fittings shall be installed according to the Canadian Electrical Code (CEC) Part I, Rules 12-1100 - 12-1122 and the National Electrical Code (NEC) Article 352.

Pipe	Fittings
C22.2 No. 211.2	C22.2 No. 18.2, 85 (Boxes) No. 40 (Electrical Encl.) No. 42.1 (Covers) No. 85 (Fittings)
UL 651	UL 514C (Boxes) UL 50 (Electrical Encl.) UL 514D (Covers) UL 651 (Fittings)
Conforms to NEMA TC2	





Features and Benefits

Saves Labour

Rigid PVC Conduit pipe and fittings are easy to install, cut and join.

Easy Wire Pulls

The conduit's smooth interior surface reduces friction and prevents damage to wires when pulling wire and conductors for long runs and even through 90° bends.

Lightweight Materials

Rigid PVC Conduit is easier to move and handle because it is approximately one-fifth the weight of steel and half the weight of aluminum.

Approximate Weight Comparison

Size mm (in)	PVC lb/100ft (kg/m)	Aluminum lb/100ft (kg/m)	Steel lb/100ft (kg/m)
12 (½)	16.1 (0.24)	27 (0.40)	79 (1.20)
19 (¾)	21.5 (0.32)	37 (0.55)	105 (1.55)
25 (1)	31.9 (0.47)	53 (0.80)	153 (2.30)
32 (1¼)	43.8 (0.65)	70 (1.05)	201 (3.00)
38 (1½)	52.3 (0.78)	86 (1.30)	249 (3.70)
50 (2)	70.3 (1.05)	116 (1.75)	334 (5.00)
63 (2½)	112.0 (1.61)	183 (2.75)	527 (7.85)
75 (3)	146.7 (2.18)	239 (3.55)	690 (10.25)
90 (3½)	176.4 (2.63)	288 (4.30)	831 (12.40)
100 (4)	208.9 (3.11)	340 (5.10)	982 (14.60)
125 (5)	283.4 (4.22)	465 (6.90)	1,344 (20.40)
150 (6)	368.0 (5.48)	613 (9.10)	1,771 (26.35)

Simplifies Direct Burial

Royal Electrical Solutions Rigid PVC Conduit does not require additional protection for direct burial installations according to the Canadian Electrical Code (CEC) and the National Electrical Code (NEC). Normal construction practices should be followed for trenching and backfill operations.

Non-Conductive

Rigid PVC Conduit is non-conductive.

Long Life

Royal Rigid PVC Conduit and fittings resist acids, alkalis, salt solutions and most other chemicals. (Refer to the Royal Chemical Resistance Guide for detailed information.) There is no risk of corrosion when exposed to naturally corrosive soil conditions, electrochemical or galvanic environments. Royal's Rigid PVC Conduit has achieved sunlight resistance as per the requirements of the Electrical Code.

FT-4 Rating

Rigid PVC Conduit pipe has an FT-4 Rating and can be used in non-combustible construction as per Part 3 of the National Building Code of Canada (NBC).

Installation Guidelines

Cutting

Royal Rigid PVC Conduit can easily be cut with a hacksaw, a fine-toothed handsaw or PVC conduit cutters. For conduit with more than a 50mm (2-inch) diameter, use a mitre box or saw guide to ensure a square cut. Deburr the end using a knife or file.

Bending

It may be necessary to create bends in the field by heating and deforming Rigid PVC Conduit. To accomplish this, the following guidelines should be followed:

• For heating the Rigid PVC Conduit, use a heat gun or some other flameless heat source. Do not use an open flame to heat the conduit. Rigid PVC Conduit must be heated to approximately 127°C (260°F) in order to bend without kinking.

• Heat a length of conduit equal to approximately 10 times the nominal diameter.

• Once the Rigid PVC Conduit has been adequately heated, bend it to the required angle plus 3 extra degrees. The additional angle will accommodate the "spring back" which will occur during cooling.

• After bending of the conduit is completed, immediately cool the bend using water or cold air.

• According to the Canadian Electrical Code (CEC) and the National Electrical Code (NEC), the minimum bending radius for rigid conduit is as shown in the table below.

Nominal Size mm (in)	Min. Radius to Centre of Conduit or Tubing mm (in)
16 (½)	102 (4.016)
21 (¾)	114 (4.489)
27 (1)	146 (5.748)
35 (1¼)	184 (7.244)
41 (1½)	210 (8.268)
53 (2)	241 (9.488)
63 (2½)	267 (10.512)
78 (3)	330 (12.992)
91 (3½)	381 (14.606)
103 (4)	406 (15.984)
129 (5)	610 (24.016)
155 (6)	762 (30.000)





Procedure for Solvent Welding Joints

• Use solvent cement and primer prior to expiration date marked on container.

• Above 0° C ambient temperature, joints may be assembled without the use of primer, provided adequate penetration and softening of the pipe/fitting surface can be achieved with solvent cement alone.


1. Assemble materials for the job, including correct solvent cement, primer and correctly sized applicator.

2. Cut pipe as square as possible using a hand saw and miter box or mechanical saw. Do not use a diagonal cut, as it reduces the bonding area in the joint.

3. If plastic tubing cutters are used, care must be taken to remove any raised bead at the end of the pipe, caused by cutting. A file or reamer may be used to remove the bead.

4. Use a knife, file or reamer to remove burrs from the inside and outside of the pipe end, as these will hinder the integrity of the joint. All sharp edges should be removed from the inside and outside edges of the pipe to prevent the pipe from pushing the solvent cement into the fitting socket, thereby causing a weak spot to form. The pipe end should be chamfered, as shown below.

Chamfered Pipe



Procedure for Solvent Welding Joints Continued

5. All dirt, grease and moisture should be removed from the pipe and socket by thoroughly wiping with a clean, dry cloth.

6. Dry fit pipe and fitting joints prior to cementing. For proper interference fit, the pipe should go easily into the socket approximately ⅓ to ⅔ of the socket depth. If this is not the case, other pipe or fittings should be used.

7. The applicator should be sized according to the size of pipe and fittings being joined. The brush width of the applicator should be equal to approximately ½ of the pipe diameter.

8. Primer is used to penetrate and soften the surfaces so that they will fuse together under a wide variety of conditions. The penetration or softening can be checked by dragging the edge of a knife or sharp object over the coated surface. If a few thousandths of an inch of the primed surface can be scratched or scraped away, proper penetration has occurred. Varying weather conditions affect priming and cementing action and may require more time or repeated applications to either or both surfaces.

9. If using primer, use the correct applicator size (see #7) and aggressively work the primer into the socket, keeping the surface and applicator wet until the surface has softened, re-dipping the applicator as required. When the surface is primed, remove any puddles of primer from the socket.

10. Aggressively work the primer on to the end of the pipe, to a point ½" beyond the depth of the socket.

11. Perform a second application of primer in the socket.

12. While the surfaces are still wet, the appropriate solvent cement should be applied.

13. Using the correct applicator size, aggressively work a full, even layer of cement onto the pipe end to a point equal to the depth of the socket. Do not brush out to a thin paint type layer, as this will dry within a few seconds.

14. Aggressively work a medium layer of cement into the fitting socket; avoid puddling cement in the socket. On the pipe end, do not coat beyond the socket depth or allow cement to run down into the pipe beyond the socket.

15. Apply a second full, even layer of cement on the pipe.

16. Immediately, while the cement is still wet, assemble the joint. Use enough force to ensure that the pipe is fully inserted into the socket. Twist the pipe a ¼ turn as it is being inserted.

17. Hold the joint together for approximately 30 seconds to avoid push out.

18. After assembly, inspect the joint to ensure that there is a ring or bead of cement completely around the juncture of the pipe and socket. If there are voids in this ring, sufficient cement was not applied and the joint may be defective.

19. Remove the excess cement from the pipe and socket (including the ring or bead) using a cloth. Avoid disturbing or moving the joint.

20. Handle newly cemented joints with care until initial set has taken place. Follow set and cure times before handling or testing the system.

Pipe Dimensions

Nominal Size mm (in)	Avg. Outside Diameter mm (in)	Avg. Inside Diameter mm (in)	Avg. Wall Thickness mm (in)	Approx. Weight lb/100ft (kg/m)
12 (½)	21 (0.840)	15 (0.608)	3 (0.116)	16.1 (0.24)
19 (¾)	27 (1.050)	21 (0.810)	3 (0.120)	21.5 (0.32)
25 (1)	33 (1.315)	26 (1.033)	4 (0.141)	31.9 (0.47)
32 (1¼)	42 (1.660)	35 (1.362)	4 (0.149)	43.8 (0.65)
38 (1½)	48 (1.900)	40 (1.592)	4 (0.154)	52.3 (0.78)
50 (2)	60 (2.375)	52 (2.049)	4 (0.163)	70.3 (1.05)
63 (2½)	73 (2.875)	62 (2.445)	5 (0.215)	112.0 (1.61)
75 (3)	89 (3.500)	77 (3.042)	6 (0.229)	146.7 (2.18)
90 (3½)	102 (4.000)	89 (3.520)	6 (0.240)	176.4 (2.63)
100 (4)	114 (4.500)	102 (3.998)	6 (0.251)	208.9 (3.11)
125 (5)	141 (5.565)	127 (5.017)	7 (0.274)	283.4 (4.22)
150 (6)	168 (6.625)	153 (6.031)	8 (0.297)	368.0 (5.48)

Specification

All wiring shall be installed in Royal Electrical Solutions Rigid PVC Conduit and secured with proper fittings. All conduit and fittings shall be manufactured by Royal Building Products, Pipe & Fittings Solutions. All outlets, pull boxes and junction points shall be Royal products.

Exposed conduit shall be securely attached and supported with straps that are installed at the recommended spacing specified in CEC Section 12-1114. The straps must allow for linear expansion and contraction of the conduit due to temperature change. If the variance in temperature exceeds 14°C (25°F), expansion joints shall be installed according to the manufacturer's recommendations.

If Rigid PVC Conduit is embedded in concrete or direct buried, support straps are not required.

Solvent Cementing

All connections should be made using and applying Royal Electrical Solutions solvent cement.

Set Times

Average Initial Set Times			
Temperature Range	Pipe Sizes ½" to 1¼"	Pipe Sizes 1½" to 2"	Pipe Sizes 2½" to 6"
15°C to 40°C	2 min.	5 min.	30 min.
5°C to 15°C	5 min.	10 min.	2 hrs.
-16°C to 5°C	10 min.	15 min.	12 hrs.

Joint Cure Schedule

Average Joint Cure Times			
Temperature Range During Assembly & Cure Periods	Pipe Sizes ½" to 1¼"	Pipe Sizes 1½" to 2"	Pipe Sizes 2½" to 6"
15°C to 40°C	2 min.	5 min.	30 min.
5°C to 15°C	5 min.	10 min.	2 hrs.
-16°C to 5°C	10 min.	15 min.	12 hrs.

In damp or humid weather allow 50% more cure time.

Estimated Solvent Cement Requirements

Average Number of Joints per Litre of Solvent Cement									
Pipe/Fitting Diameter	½"	¾"	1"	1½"	2"	2½"	3"	4"	6"
Number of Joints	300	200	125	90	60	40	40	30	10

Estimated Primer Requirements

Average Number of Joints per Litre of Primer									
Pipe/Fitting Diameter	½"	¾"	1"	1½"	2"	2½"	3"	4"	6"
Number of Joints	600	400	250	180	120	80	80	60	20

Solvent Cementing in Cold Weather:

- Store pipe and fittings in a heated area. Prefabricate as much of the system as possible in a heated area.
- When not in use, store sealed solvent cement and primer between 5°C and 21°C. Do not use open flame or electric heaters to warm cements and primers.
- Take care to remove moisture, ice and snow from the mating surfaces.

Solvent Cementing in Hot Weather:

- At the time of assembly, the surface temperature of the mating surfaces should not exceed 45°C. Shade or shelter the joint surfaces from direct sunlight for at least 1 hour prior to joining and during the joining process. If necessary, swab the mating surfaces with clean, wet rags to reduce the surface temperature (thoroughly dry surfaces before applying primer or cement).
- Make joints during the cooler early morning hours.
- Apply cement quickly and join pipe to fitting as quickly as possible after applying the cement.
- Keep solvent cement container closed or covered when not in use, to minimize solvent loss.

Solvent Cementing in Wet Conditions:

- Mating surfaces must be dry when the joint is made.
- Work under a cover or canopy to keep rain off pipe and fittings.
- Work quickly after drying the pipe and fitting to avoid condensation.
- Allow a longer cure time before the system is tested or used.

Storage and Handling of Solvent Cement and Primer:

- Solvent cement and primer contain highly flammable solvents. Follow all specific safety precautions provided on container label and Material Safety Data Sheet.
- Keep primer and solvent cement away from heat, sparks and open flame.
- Keep containers tightly closed except when in use.
- Ensure proper ventilation of work area and avoid inhaling solvent vapours.
- Where the possibility of splashing exists, wear proper eye protection or a face shield.
- Avoid contact with skin.

Support Straps

Rigid PVC conduit must be supported with straps when installed in above ground applications. These straps should be installed snugly, while allowing linear movement of the conduit. See the table below for recommended maximum spacing of support straps.

Maximum Recommended Spacing of Support Straps		
Nominal Size mm (in)	CEC Recommended Spacing ft (m)	NEC Recommended Spacing ft (m)
16 (½)	2½ (0.75)	3 (0.91)
21 (¾)	2½ (0.75)	3 (0.91)
27 (1)	2½ (0.75)	3 (0.91)
35 (1¼)	4 (1.20)	5 (1.50)
41 (1½)	4 (1.20)	5 (1.50)
53 (2)	6 (1.80)	5 (1.50)
63 (2½)	6 (1.80)	3 - 6 (1.80)
78 (3)-129 (5)	7 (2.10)	3½ - 5 (2.10)
155 (6)	8 (2.50)	8 (2.50)

Storing Conduit Pipe and Fittings

Store Rigid PVC conduit pipe and fittings at the same temperature. Otherwise they may expand and contract at different rates and become incompatible.

Maximum Operating Temperatures

According to the Canadian Electrical Code (CEC), Rigid PVC conduit is intended for use at a continuous operating temperature of 75°C (167°F). For US applications, our Rigid PVC conduit is rated for use with 90°C wiring, according to the requirements of the NEC.

Ambient Temperatures

Royal Electrical Solutions Rigid PVC Conduit and fittings can be installed in locations with an ambient temperature not exceeding 50°C (122°F).

Expansion Joints

According to the CEC, if the amount of expansion expected due to temperature variance during and after construction is more than 45mm, expansion joints must be used.

Expected Expansion

The coefficient of linear expansion for Rigid PVC conduit is as follows:

3×10^{-5} in (expansion/contraction) / in (pipe length) /°F (change in temperature),

5.4×10^{-5} mm (expansion/contraction)/mm (pipe length)/°C (change in temperature)





Note:

The following chart shows the amount of expansion expected with various pipe lengths/temperature changes. If the Rigid PVC Conduit is installed in an exposed location, 17°C (30°F) should be added to the amount of temperature change (ΔT) due to the effects of radiant heat.

Expansion/Contraction of PVC (mm)

Length of Pipe Run (m)

ΔT (°C)	2	4	6	8	10	12	14	16	18	20
5	0.54	1.08	1.62	2.16	2.70	3.24	3.78	4.32	4.86	5.40
10	1.08	2.16	3.24	4.32	5.40	6.48	7.56	8.64	9.72	10.80
15	1.62	3.24	4.86	6.48	8.10	9.72	11.34	12.96	14.58	16.20
20	2.16	4.32	6.48	8.64	10.80	12.96	15.12	17.28	19.44	21.60
25	2.70	5.40	8.10	10.80	13.50	16.20	18.90	21.60	24.30	27.00
30	3.24	6.48	9.72	12.96	16.20	19.44	22.68	25.92	29.16	32.40
35	3.78	7.56	11.34	15.12	18.90	22.68	26.46	30.24	34.02	37.80
40	4.32	8.64	12.96	17.28	21.60	25.92	30.24	34.56	38.88	43.20
45	4.86	9.72	14.58	19.44	24.30	29.16	34.02	38.88	43.74	48.60
50	5.40	10.80	16.20	21.60	27.00	32.40	37.80	43.20	48.60	54.00

Expansion/Contraction of PVC (in)

Length of Pipe Run (ft)

ΔT (°F)	5	10	15	20	25	30	35	40	45	50
5	0.01	0.02	0.03	0.04	0.05	0.05	0.06	0.07	0.08	0.09
10	0.02	0.04	0.05	0.07	0.09	0.11	0.13	0.14	0.16	0.18
15	0.03	0.05	0.08	0.11	0.14	0.16	0.19	0.22	0.24	0.27
20	0.04	0.07	0.11	0.14	0.18	0.22	0.25	0.29	0.32	0.36
25	0.05	0.09	0.14	0.18	0.23	0.27	0.32	0.36	0.41	0.45
30	0.05	0.11	0.16	0.22	0.27	0.32	0.38	0.43	0.49	0.54
35	0.06	0.13	0.19	0.25	0.32	0.38	0.44	0.50	0.57	0.63
40	0.07	0.14	0.22	0.29	0.36	0.43	0.50	0.58	0.65	0.72
45	0.08	0.16	0.24	0.32	0.41	0.49	0.57	0.65	0.73	0.81
50	0.09	0.18	0.27	0.36	0.45	0.54	0.63	0.72	0.81	0.90

Required Number of Expansion Joints

The following table shows the amount of travel that is available with each trade size of Royal Electrical Solutions Rigid PVC conduit expansion joints:

Part Number	Description in	Travel Allowance mm (in)
REJ10	½" Expansion Joint	102 (4)
REJ15	¾" Expansion Joint	102 (4)
REJ20	1" Expansion Joint	102 (4)
REJ25	1¼" Expansion Joint	102 (4)
REJ30	1½" Expansion Joint	102 (4)
REJ35	2" Expansion Joint	102 (4)
REJ40	2½" Expansion Joint	102 (4)
REJ45	3" Expansion Joint	204 (8)
REJ50	3½" Expansion Joint	204 (8)
REJ55	4" Expansion Joint	204 (8)
REJ60	5" Expansion Joint	204 (8)
REJ65	6" Expansion Joint	204 (8)

The required number of expansion joints can be calculated using the following formula:

$$\#\ \text{Expansion Joints Required} = \frac{\text{Total Expected Amount of Expansion (in)}}{\text{Expansion Joint Travel Allowance (in)}}$$

$$\#\ \text{Expansion Joints Required} = \frac{\text{Total Expected Amount of Expansion (mm)}}{\text{Expansion Joint Travel Allowance (mm)}}$$

The number of expansion joints calculated above should be rounded up to the nearest whole number.

Setting the Piston Opening

Expansion joints must be installed such that they allow for both expansion and contraction of the conduit. The piston of the expansion joint must be set at the correct position to allow for this linear movement. To determine the correct position for the piston at the time and temperature of installation, the following formula should be used:

$$\text{Piston Setting (in)} = \frac{\text{(Max. Temp. (°F) – Install. Temp. (°F))}}{\text{Total Expected Temperature Change (°F)}} \times \left[\text{Expansion Joint Expansion Allow. (in)}\right]$$

$$\text{Piston Setting (mm)} = \frac{\text{(Max. Temp. (°C) – Install. Temp. (°C))}}{\text{Total Expected Temperature Change (°C)}} \times \left[\text{Expansion Joint Expansion Allow. (mm)}\right]$$

Installation Guidelines

• Securely fasten the expansion joint barrel so that it does not shift. Loosely connect the conduit so that it is free to move.


• To function properly, expansion joints should be installed near a fixed point.

• It is better to use more expansion joints than not enough, since problems are difficult to correct after conductors and wires have been pulled through the conduit.

• Ensure that the barrel and piston are aligned and level.

• For vertical installations of expansion joints, install with the piston at the bottom to prevent dirt and water from getting inside the joint and causing it to malfunction.

Installation Example



If one expansion joint is required:
Securely fasten the barrel of the expansion joint close to one of the boxes. Support the conduit with straps, but allow free movement of the conduit for expansion and contraction. (See Drawing 1)

If two expansion joints are required:
There are two options available:


1. Firmly fasten one expansion joint near each end of the run and firmly fasten the conduit at the centre. Support the rest of the conduit with straps allowing for movement of the conduit. (See Drawing 2)

2. Firmly fasten the expansion joints back-to-back at the centre of the run. The conduit should be supported with straps to allow free movements as it expands and contracts. (See Drawing 3)


If three or more expansion joints are required:
Evenly space the expansion joints along the run of Rigid PVC conduit. Tightly fasten each expansion joint and support the conduit with straps. Do not restrict the movement of the conduit.


*For information on Maximum Recommended Spacing of Support Straps, see page 4.


Drawings 1 - 4




FITTINGS - Bends (Bell Ends)


90° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1090	46120	0.840	1.500	4.00
	¾	REE1590	46150	1.050	1.500	4.50
	1	REE2090	46180	1.315	1.875	5.75
	1¼	REE2590	46210	1.660	2.000	7.25
	1½	REE3090	46240	1.900	2.000	8.25
	2	REE3590	46270	2.375	2.000	9.50
	2½	REE4090	46330	2.875	3.000	10.50
	3	REE4590	46360	3.500	3.125	13.00
	3½	REE5090	46390	4.000	3.250	15.00
	4	REE5590	46420	4.500	3.375	16.00
	5	REE6090	46440	5.565	3.622	24.00
	6	REE6590	46460	6.625	3.740	30.00


45° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1045	46120	0.840	1.500	4.00
	¾	REE1545	46150	1.050	1.500	4.50
	1	REE2045	46180	1.315	1.875	5.75
	1¼	REE2545	46210	1.660	2.000	7.25
	1½	REE3045	46240	1.900	2.000	8.25
	2	REE3545	46270	2.375	2.000	9.50
	2½	REE4045	46330	2.875	3.000	10.50
	3	REE4545	46360	3.500	3.125	13.00
	3½	REE5045	46390	4.000	3.250	15.00
	4	REE5545	46420	4.500	3.375	16.00
	5	REE6045	46440	5.565	3.625	24.00
	6	REE6545	46460	6.625	3.750	30.00


30° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1030	46100	0.840	1.500	4.00
	¾	REE1530	46130	1.050	1.500	4.50
	1	REE2030	46160	1.315	1.875	5.75
	1¼	REE2530	46190	1.660	2.000	7.25
	1½	REE3030	46220	1.900	2.000	8.25
	2	REE3530	46274	2.375	2.000	9.50
	2½	REE4030	46310	2.875	3.000	10.50
	3	REE4530	46340	3.500	3.125	13.00
	3½	REE5030	46375	4.000	3.250	15.00
	4	REE5530	46400	4.500	3.375	16.00
	5	REE6030	46425	5.565	3.625	24.00
	6	REE6530	46442	6.625	3.750	30.00


Utilities 90° Elbows - Bell End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	2	REE2-24	46501	2.375	41.20	24.00
	2	REE2-36	46502	2.375	31.70	36.00
	3	REE3-24	46503	3.500	41.20	24.00
	3	REE3-36	46504	3.500	31.70	36.00
	4	REE4-36	46465	4.500	31.70	36.00
	4	REE4-48	46505	4.500	31.70	48.00
	5	REE5-36	46506	5.565	31.70	36.00
	6	REE6-36	46507	6.625	31.70	36.00

Fittings - Bends (Plain Ends)


90° Elbows - Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1090PE	46120	0.840	1.500	4.00
	¾	REE1590PE	46150	1.050	1.500	4.50
	1	REE2090PE	46180	1.315	1.875	5.75
	1¼	REE2590PE	46210	1.660	2.000	7.25
	1½	REE3090PE	46240	1.900	2.000	8.25
	2	REE3590PE	46270	2.375	2.000	9.50
	2½	REE4090PE	46330	2.875	3.000	10.50
	3	REE4590PE	46360	3.500	3.125	13.00
	3½	REE5090PE	46390	4.000	3.250	15.00
	4	REE5590PE	46420	4.500	3.375	16.00
	5	REE6090PE	46440	5.565	3.622	24.00
	6	REE6590PE	46460	6.625	3.740	30.00


45° Elbows - Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1045PE	46110	0.840	1.500	4.00
	¾	REE1545PE	46140	1.050	1.500	4.50
	1	REE2045PE	46170	1.315	1.875	5.75
	1¼	REE2545PE	46200	1.660	2.000	7.25
	1½	REE3045PE	46230	1.900	2.000	8.25
	2	REE3545PE	46280	2.375	2.000	9.50
	2½	REE4045PE	46320	2.875	3.000	10.50
	3	REE4545PE	46350	3.500	3.125	13.00
	3½	REE5045PE	46380	4.000	3.250	15.00
	4	REE5545PE	46415	4.500	3.375	16.00
	5	REE6045PE	46430	5.565	3.622	24.00
	6	REE6545PE	46450	6.625	3.740	30.00


30° Elbows - Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	½	REE1030PE	46100	0.840	1.500	4.00
	¾	REE1530PE	46130	1.050	1.500	4.50
	1	REE2030PE	46160	1.315	1.875	5.75
	1¼	REE2530PE	46190	1.660	2.000	7.25
	1½	REE3030PE	46220	1.900	2.000	8.25
	2	REE3530PE	46274	2.375	2.000	9.50
	2½	REE4030PE	46310	2.875	3.000	10.50
	3	REE4530PE	46340	3.500	3.125	13.00
	3½	REE5030PE	46375	4.000	3.250	15.00
	4	REE5530PE	46400	4.500	3.375	16.00
	5	REE6030PE	46425	5.565	3.622	24.00
	6	REE6530PE	46442	6.625	3.740	30.00


45° Elbows - Extended Plain End	Sizes (in)	Product Code	UPC Number	Diameter (D) (in)	Length (L) (in)	Radius (R) (in)
	1¼	REE2590E	46125	1.660	14.750	7.25
	1½	REE3090E	46260	1.900	14.750	8.25
	2	REE3590E	43290	2.375	14.750	9.50

Fittings - Couplings and Adapters

Couplings	Sizes (in)	Product Code	UPC Number	Outside Diameter (OD) (in)	Inside Diameter (ID) (in)	Length (L) (in)
	½	REC10	45950	1.080	0.840	1.437
	¾	REC15	45960	1.300	1.050	1.703
	1	REC20	45970	1.590	1.315	2.031
	1¼	REC25	45980	2.000	1.660	2.156
	1½	REC30	45990	2.230	1.900	2.281
	2	REC35	46000	2.720	2.375	2.406
	2½	REC40	46010	3.320	2.875	3.187
	3	REC45	46020	4.000	3.500	3.437
	3½	REC50	46030	4.500	4.000	3.625
	4	REC55	46060	5.000	4.500	3.750
	5	REC60	46080	6.120	5.565	4.187
	6	REC65	46090	7.370	6.625	4.562


5° Couplings *(*Fabricated)*	Sizes (in)	Product Code	UPC Number	Outside Diameter (OD) (in)	Inside Diameter (ID) (in)	Length (L) (in)
	2	R5EC35	46800	2.375	2.049	4.0
	2½	R5EC40	46805	3.500	2.445	5.5
	3	R5EC45	46810	3.500	3.042	6.0
	3½	R5EC50	46815	4.500	3.521	7.0
	4	R5EC55	46820	4.500	3.998	7.0
	5	R5EC60	46825	5.565	5.018	7.5
	6	R5EC65	46830	6.625	6.031	11.0

Terminal Adapters (½" - 1¼" Tapered Thread, 6" NPT)	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	Inside Diameter (ID) (in)	Thread (in)
	½	RTA10	45730	0.750	0.700	0.591	1.550
	¾	RTA15	45740	1.000	0.675	0.790	1.750
	1	RTA20	45750	1.115	0.625	1.000	1.860
	1¼	RTA25	45760	1.300	0.640	1.311	2.125
	1½	RTA30	45770	1.425	0.725	1.530	2.250
	2	RTA35	45780	1.150	0.800	1.970	2.100
	2½	RTA40	45790	1.900	0.800	2.346	2.930
	3	RTA45	45800	2.000	0.815	2.915	3.055
	3½	RTA50	45810	1.715	1.000	3.385	3.055
	4	RTA55	45820	1.990	0.815	3.850	3.215
	5	RTA60	45830	2.000	1.725	5.015	5.985
	6	RTA65	45840	2.130	1.875	6.025	6.500

Female Adapters (Npt Tapered Thread)	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	Inside Diameter (ID) (in)	Thread (in)
	½	RFA10	44990	0.800	0.825	0.620	1.725
	¾	RFA15	45000	0.800	1.000	0.820	1.900
	1	RFA20	45010	1.000	1.200	1.065	2.300
	1¼	RFA25	45020	1.015	1.300	1.395	2.425
	1½	RFA30	45030	1.050	1.290	1.575	2.440
	2	RFA35	45040	1.075	1.375	2.050	2.550
	2½	RFA40	45050	1.675	1.985	2.470	3.760
	3	RFA45	45060	1.630	2.150	3.090	4.100
	3½	RFA50	45070	1.800	2.000	3.540	3.985
	4	RFA55	45080	1.755	2.185	4.025	4.210
	5	RFA60	45090	2.065	3.000	5.035	5.240
	6	RFA65	45100	2.065	3.000	6.045	5.235

Fittings - Expansions Joints, Straps and Meter Accessories

Expansion Joints



Sizes (in)	Product Code	UPC Number	Expanded Length (E) (in)	Contracted Length (C) (in)	Travel (in)
½	REJ10	44870	12.00	8.00	4.00
¾	REJ15	44880	12.00	8.00	4.00
1	REJ20	44890	12.50	8.50	4.00
1¼	REJ25	44900	13.00	9.00	4.00
1½	REJ30	44910	13.00	9.00	4.00
2	REJ35	44920	13.25	9.25	4.00
2½	REJ40	44930	13.25	9.25	4.00
3	REJ45	44940	22.25	14.25	8.00
3½	REJ50	44950	22.25	14.25	8.00
4	REJ55	44960	22.25	14.25	8.00
5	REJ60	44963	22.25	14.25	8.00
6	REJ65	44966	22.25	14.25	8.00

Expansion Joints

PVC	Sizes (in)	Product No.	UPC No.	PVC Coated Steel	Sizes (in)	Product No.	UPC No.	PVC Coated Steel	Sizes (in)	Product No.	UPC No.
2 Hole	½	RPS10	45540	2 Hole	2	RCS35	44783	1 Hole	½	RCS10-1	46850
	¾	RPS15	45550		2½	RCS40	44784		¾	RCS15-1	46852
	1	RPS20	45560		3	RCS45	44785		1	RCS20-1	46854
	1¼	RPS25	45570		3½	RCS50	44786		1¼	RCS25-1	46856
	1½	RPS30	45580		4	RCS55	44787		1½	RCS30-1	46858
	2	RPS35	45590		5	RCS60	44788		2	RCS35-1	46860
					6	RCS65	44789		2½	RCS40-1	46862
									3	RCS10-1	46864
									4	RCS10-1	46866

Meter Offsets



Sizes (in)	Product No.	UPC No.
1¼	RM025	45500
2	RM035	45510

Long Meter Offsets *(Fabricated)*



Sizes (in)	Product No.	UPC No.
1¼	RLM025	45472
1½	RML030	45474
2	RML035	45476

Service Entrance Fittings



Sizes (in)	Product No.	UPC No.
½	REF10	44795
¾	REF15	44800
1	REF20	44810
1¼	REF25	44820
1½	REF30	44830
2	REF35	44840
2½	REF40	44842
3	REF45	44844
3½	REF50	44852
4	REF55	44860

Meter Hubs



Sizes (in)	Product No.	UPC No.
1¼	RMHU25	45480
1½	RMHU30	45485
2	RMHU35	45490

Expansion & Deflection Fittings Assembly



Sizes (in)	Product No.	UPC No.
2	RSEJ35	46990
3	RSEJ45	46992
4	RSEJ55	46994

Ecovoc Solvent Cement *(*c/w Screw Cap & Dauber)*




Sizes (in)	Product No.	UPC No.	Carton Qty.
250ml	RVOC250*	54790	24
475ml	RVOC475*	54795	12
950ml	RVOC950*	54797	12
4L	RVOC4L	54799	4


Privoc Solvent Cement *(*c/w Screw Cap & Dauber)*





Sizes (in)	Product No.	UPC No.	Carton Qty.
250ml	RVOCPR250*	54800	24
475ml	RVOCPR475*	54802	12
950ml	RVOCPR950*	54804	12
4L	RVOCPR4L	54806	4

Fittings - Access Fittings


Type C	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)
	½	RSC10S	46600	5.606	0.639	1.268	1.100	0.840
	¾	RSC20S	46605	5.606	0.810	1.536	1.325	1.050
	1	RSC30S	46610	6.500	0.910	1.700	1.600	1.335
	1¼	RSC40S	46615	7.900	1.050	2.300	2.250	1.100
	1½	RSC50S	46620	8.500	1.125	2.675	2.250	1.900
	2	RSC60S	45605	10.875	1.160	3.188	2.820	2.375
	2½	RSC70S	45606	14.600	1.750	4.500	3.950	2.870
	3	RSC80S	45607	14.600	1.900	4.500	3.950	3.510
	3½	RSC90S	45609	17.040	2.125	5.536	5.000	4.000
	4	RSC100S	45608	17.040	2.125	5.536	5.000	4.530


Type LB	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)	H (in)
	½	RSLB10S	45620	4.337	0.639	1.268	0.840	1.297	4.095	2.487	1.005
	¾	RSLB20S	45630	5.395	0.810	1.536	1.050	1.297	4.095	2.487	1.005
	1	RSLB30S	45640	6.250	0.910	1.700	1.335	1.500	4.750	2.075	1.125
	1¼	RSLB40S	45650	7.625	1.050	2.300	1.100	1.750	5.750	3.575	1.562
	1½	RSLB50S	45660	8.250	1.125	2.675	1.900	1.750	6.500	3.938	1.656
	2	RSLB60S	45670	10.531	1.160	3.188	2.375	2.344	8.156	4.535	1.968
	2½	RSLB70S	45675	13.630	1.750	4.500	2.870	2.733	9.825	6.240	2.610
	3	RSLB80S	45680	13.630	1.900	4.500	3.510	3.805	10.897	6.240	2.610
	3½	RSLB90S	45610	16.000	2.125	5.536	4.000	4.535	11.465	7.500	2.975
	4	RSLB100S	45681	16.000	2.125	5.536	4.530	4.535	11.465	7.500	2.975


Type LL	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)
	½	RSLL10S	46650	4.337	0.639	1.268	2.487	0.840	4.095	1.297
	¾	RSLL20S	46655	5.395	0.810	1.536	2.487	1.050	4.095	1.297
	1	RSLL30S	46660	6.250	0.910	1.700	2.075	1.335	4.750	1.500
	1¼	RSLL40S	46665	7.625	1.050	2.300	3.575	1.100	5.750	1.750
	1½	RSLL50S	46670	8.250	1.125	2.675	3.938	1.900	6.500	1.750
	2	RSLL60S	45682	10.531	1.160	3.188	4.535	2.375	8.156	2.344
	2½	RSLL70S	45672	13.630	1.750	4.500	6.240	2.870	9.825	3.805
	3	RSLL80S	46674	13.630	1.900	4.500	6.240	3.510	10.897	2.733
	3½	RSLL90S	46678	16.000	2.125	5.536	7.500	4.000	11.465	4.535
	4	RSLL100S	46676	16.000	2.125	5.536	7.500	4.530	11.465	4.535

Type LR	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)
	½	RSLR10S	46700	4.337	0.639	1.268	2.487	0.840	4.095	1.297
	¾	RSLR20S	46705	5.395	0.810	1.536	2.487	1.050	4.095	1.297
	1	RSLR30S	46710	6.250	0.910	1.700	2.075	1.335	4.750	1.500
	1¼	RSLR40S	46715	7.625	1.050	2.300	3.575	1.100	5.750	1.750
	1½	RSLR50S	46720	8.250	1.125	2.675	3.938	1.900	6.500	1.750
	2	RSLR60S	45683	10.531	1.160	3.188	4.535	2.375	8.156	2.344
	2½	RSLR70S	46725	13.630	1.750	4.500	6.240	2.870	9.825	3.805
	3	RSLR80S	46728	13.630	1.900	4.500	6.240	3.510	10.897	2.733
	3½	RSLR90S	46738	16.000	2.125	5.536	7.500	4.000	11.465	4.535
	4	RSLR100S	46735	16.000	2.125	5.536	7.500	4.530	11.465	4.535

Fittings - Access Fittings

Type E	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)
	½	RSE10S	46630	4.337	0.639	1.268	0.840
	¾	RSE20S	46632	5.395	0.810	1.536	1.050
	1	RSE30S	46634	6.250	0.910	1.700	1.335
	1¼	RSE40S	46636	7.625	1.050	2.300	1.100
	1½	RSE50S	46638	8.250	1.125	2.675	1.900
	2	RSE60S	46640	10.351	1.160	3.188	2.375
	2½	RSE70S	46642	13.630	1.750	4.500	2.870
	3	RSE80S	46644	13.630	1.900	4.500	3.510
	3½	RSE90S	46648	16.000	2.125	5.536	4.000
	4	RSE100S	46646	16.000	2.125	5.536	4.530

Type T	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)
	½	RST10S	45690	2.280	0.639	1.100	0.840
	¾	RST20S	45700	2.803	0.810	1.325	1.050
	1	RST30S	45710	3.250	0.910	1.600	1.335
	1¼	RST40S	45720	3.950	1.050	2.250	1.100
	1½	RST50S	45723	4.250	1.125	2.250	1.900
	2	RST60S	45725	5.438	1.160	2.820	2.375
	2½	RST70S	46745	7.300	1.750	3.950	2.870
	3	RST80S	46748	7.300	1.900	3.950	3.510
	3½	RST90S	46752	8.535	2.125	5.000	4.000
	4	RST100S	46750	8.535	2.125	5.000	4.530

Type TB	Sizes (in)	Product Code	UPC Number	A (in)	B (in)	C (in)	D (in)	E (in)	F (in)	G (in)	H (in)
	½	RSTB10S	45692	2.280	0.639	1.268	1.100	0.840	2.487	1.005	0.750
	¾	RSTB20S	45702	2.803	0.810	1.536	1.325	1.050	2.487	1.005	0.810
	1	RSTB30S	45712	3.250	0.910	1.700	1.600	1.335	2.075	1.125	1.115
	1¼	RSTB40S	45721	3.950	1.050	2.300	2.250	1.100	3.575	1.562	1.300
	1½	RSTB50S	45724	4.250	1.125	2.675	2.250	1.900	3.938	1.656	1.425
	2	RSTB60S	45727	5.438	1.160	3.188	2.820	2.375	4.535	1.968	1.160
	2½	RSTB70S	46760	7.300	1.750	4.500	3.950	2.870	6.240	2.610	-
	3	RSTB80S	46762	7.300	1.900	4.500	3.950	3.510	6.240	2.610	-
	3½	RSTB90S	46766	8.535	2.125	5.536	5.000	4.000	7.500	2.975	-
	4	RSTB100S	46764	8.535	2.125	5.536	5.000	4.530	7.500	2.975	-

Fittings - Cover Plates

Single Gang Cover Plates - F Series



Description	Product Code	UPC Number
Toggle Switch	RTSC15-10	45845
Duplex Receptacle	RDRC15-10R20	44685
Single Receptacle - 15 Amp	RC15-10R20-3	47035
Single Receptacle - 20 Amp	RC15-10R30-3	47036
Single Receptacle - 30 Amp	RC15-10	47037
Single Blank with Gasket	RBRC15-10	44680
Gasket	GASK15-10	44682

Double Gang Cover Plates - F Series



Description	Product Code	UPC Number
Double Switch	RTSC20-2	45846
Combo Switch/Receptacle	RTSDC20-2	45847
Double Duplex	RDRC20-2	44686
Double Blank with Gasket	RBRC20-2	44681
Gasket	GASK20-2	45949

Triple Gang Cover Plates - F Series



Description	Product Code	UPC Number
Triple Switch	RTSC20-3	45857
Double Switch Receptacle	RDSDR20-3	44689
Double Receptacle/Switch	RTSDC20-3	45858
Triple Receptacle	RDRC20-3	44688
Triple Blank with Gasket	RBRC20-3	44683
Gasket	GASK20-3	45859

Fittings - Weatherproof Cover Plates

Single Gang Weatherproof Cover Plates



RVSC15-10 RVSC15-10 RWTG15-10 RWGF15-10 RWTL RVSC15-10 GASK W

Description	Product Code	UPC Number
Toggle Switch Cover	RVSC15-10	45940
Plunger Switch Cover	RVPT15-10	45930
Toggle	RWTG15-10	45339
Duplex Receptacle	RWDR15-10	45093
Duplex Receptacle - White	RWDR15-10W	45094
Ground Fault Receptacle	RWGF15-10	45095
Ground Fault Receptacle - White	RWGF15-10W	45098
Single Receptacle - 15 Amp	RWTL15	45470
Single Receptacle - 20 Amp	RWTL20	45472
Single Receptacle - 30 Amp	RWTL30	45480
Single Receptacle - 50 Amp	RWTL50	45482
Gasket	GASK W	45484

Double Gang Weatherproof Cover Plates



RVSC20-2 RVSRC20-2 RVSDR20-2 RVSRR20-2 GASK20-2

Description	Product Code	UPC Number
Double Toggle	RVSC20-2	45941
Plunger/GFI	RVSRC20-2	45947
Plunger/Duplex Receptacle	RVSDR20-2	45945
Plunger/Single Receptacle	RVSRR20-2	45948
Gasket	GASK20-2	45949

Fittings - Slab Boxes

Single Gang Boxes - F Series



RFS



RFSS



RFSC



RFSCC

Description	Product Code	UPC Number	Volume (in3)
½" FS	RFS10	45200	17.0
¾" FS	RFS15	45210	17.0
½" FSS	RFSS10	45240	17.5
¾" FSS	RFSS15	45250	17.5
½" FSC	RFSC10	45220	16.3
¾" FSC	RFSC15	45230	16.3
½" FSCC	RFSCC10	45233	17.0
¾" FSCC	RFSCC15	45235	17.0

Single Gang Deep Boxes - FD Series



RFDS



RFDC



BLANK



347 VOLT

Outside Dimensions: Length = 4.5", Width = 6.6", Height = 2.5", except BLANK, L = 4.5", W = 6.6", H = 3.0"

Description	Product Code	UPC Number	Volume (in3)
½" FSC	RFSC3-10	45224	56.0
¾" FSC	RFSC3-15	45232	56.0
1" FSC	RFSC3-20	45228	56.0
½" FS	RFS3-10	45208	54.0
¾" FS	RFS3-15	45218	54.0
1" FS	RFS3-20	45219	54.0
BLANK	RFD-3	45155	73.8

Double Gang Boxes - F Series


FS


FSS


FSC


FSCC


BLANK

Outside Dimensions: Length = 4.5", Width = 4.75", Height = 2.5", except BLANK, L=4.75", W=4.75", H=3.0"

Description	Product Code	UPC Number	Volume (in3)
½" FS	RFS2-10	45205	39.5
¾" FS	RFS2-15	45215	39.5
1" FS	RFS2-20	45216	39.5
½" FSS	RFSS2-10	45242	37.0
¾" FSS	RFSS2-15	45244	37.0
1" FSS	RFSS2-20	45246	37.0
½" FSC	RFSC2-10	45222	37.0
¾" FSC	RFSC2-15	45231	37.0
1" FSC	RFSC2-20	45226	37.0
½" FSCC	RFSCC2-10	45234	36.0
¾" FSCC	RFSCC2-15	45238	36.0
1" FSCC	RFSCC2-20	45239	36.0
BLANK	RFD-D	45150	52.0

Triple Gang Boxes - F Series


FSC


FS


BLANK

Outside Dimensions: Length = 4.5", Width = 6.6", Height = 2.5", except BLANK, L = 4.5", W = 6.6", H = 3.0"

Description	Product Code	UPC Number	Volume (in3)
½" FSC	RFSC3-10	45224	56.0
¾" FSC	RFSC3-15	45232	56.0
1" FSC	RFSC3-20	45228	56.0
½" FS	RFS3-10	45208	54.0
¾" FS	RFS3-15	45218	54.0
1" FS	RFS3-20	45219	54.0
BLANK	RFD-3	45155	73.8

Octagonal Boxes



Size (in)	Product No.	UPC No.
4 x 1½	ROB15/10	45520
4 x 2	ROB20	45525
¾	RKO15	45450
1	RKO20	45455


Octagonal Box Extension Rings



Size (in)	Product No.	UPC No.
1	RXR20	46490
2	RXR35	46495

Junction Boxes With Gasket









Nominal Size (in)	Product Number	UPC Number	Inside Length & Width (A) (in)	Outside Length & Width (B) (in)	Length Screw to Screw (C) (in)	Outside Height (E) (in)	Inside Height (D) (in)	Screw Size (F)	Volume (in3)
4 x 4 x 2	RJB442	45300	3.675	4.000	3.450	2.125	2.000	8-32	25.4
4 x 4 x 4	RJB444	45310	3.675	4.000	3.450	4.188	3.750	8-32	47.5
4 x 4 x 6	RJB446	45315	3.675	4.000	3.450	6.225	6.000	8-32	76.1
5 x 5 x 2	RJB552	45320	4.680	5.000	4.485	2.000	1.845	8-32	38.7
6 x 6 x 4	RJB664	45330	6.000	6.375	5.813	4.188	4.000	10-32	139.5
6 x 6 x 6	RJB666	45335	6.000	6.375	5.813	6.188	6.000	10-32	209.3
8 x 8 x 4	RJB884	45340	8.075	8.625	7.996	4.230	4.005	¼-20	258.6
8 x 8 x 7	RJB887	45350	8.100	8.625	7.996	7.250	7.035	¼-20	455.6
12 x 12 x 4	RJB12124	45280	12.085	12.580	11.874	4.256	4.030	¼-20	578.3
12 x 12 x 6	RJB12126	45290	12.085	12.580	11.874	6.240	6.025	¼-20	864.6
12 x 12 x 8	RJB12128	45295	12.085	12.580	11.874	8.250	8.025	¼-20	1151.6

Highway Boxes









Nominal Size (in)	Product Number	UPC Number	Box Inside Length & Width (B) (in)	Box Inside Depth (H) (in)	Lid Length & Width (L) (in)	Thickness of Lid (T) (in)	Volume (in3)
6 x 6 x 4	H664	47040	6.0	4.25	9.0	0.60	139.5
6 x 6 x 6	H666	47041	6.0	6.25	9.0	0.60	209.3
8 x 8 x 4	H884	47042	8.0	4.25	11.5	0.75	258.6
8 x 8 x 6	H886	47043	8.0	6.25	11.5	0.75	400.0
8 x 8 x 7	H887	47044	8.0	7.25	11.5	0.75	455.6
8 x 8 x 7	H887-A	47045	8.0	7.25	11.5	0.75	418.4

Junction Box Adapters



Size (in)	Product No.	UPC No.
½	RJBA10	45360
¾	RJBA15	45370
1	RJBA20	45380
1¼	RJBA25	45390
1½	RJBA30	45400
2	RJBA35	45410
2½	RJBA40	45420
3	RJBA45	45430
3½	RJBA50	45435
4	RJBA55	45440

Duplex Floor Boxes & Cover (*Includes Leveling Ring)



Size (in)	Product No.	UPC No.
4 x ¾	RFDB4	46980
2 x ¾, 2 x 1	RFDB2	46982
Polycarbonate Bronze Cover	RFDBC	46984

Notes:

Our various pipe and fittings solutions have been manufactured to meet the needs of our customers and their applications. Contact one of the below Sales Centres for more information:

- Municipal Pipe & Fittings Solutions
- Plumbing Pipe & Fittings Solutions
- Electrical Pipe & Fittings Solutions
- Industrial Pipe & Fittings Solutions
- Irrigation Pipe & Fittings Solutions

Sales & Distribution Centres:

Langley, BC, Canada
T/F 1.800.663.0696
F 1.800.663.6564

Woodbridge, ON, Canada
T/F 1.866.769.7473
F 905.856.3986

Laval, QC, Canada
T/F 1.800.465.9754
F 450.688.6624

Distribution Centres:

Calgary, AB, Canada
T/F 1.800.663.0696
F 1.800.663.6564

Winnipeg, MB, Canada
T/F 1.800.663.0696
F 1.800.663.6564

royalelectricalca.com





MIX
Paper from responsible sources
FSC® C003472

E_RCPF_BRV4
Printed 02.2014

ROYAL® Building Products

Pipe & Fittings Solutions | Municipal Plumbing Electrical Industrial Irrigation

Electrical Non-Metallic PVC Products

PVC Fittings
ENT Pipe and Fittings
Enclosures

Category E Product BRV1
October, 2012

E Series







ROYAL Electrical Solutions

Contents

Rigid PVC Conduit Fittings

Pages 4 - 25

Shown in Alphabetical Order

Access Fittings 6-8
- Type C 6
- Type E 7
- Type LB 6
- Type LL 7
- Type LR 7
- Type T 8
- Type TB 8

Bell End (Hub X Spigot) - Molded 9
Coupling 4
5° Coupling 4
Double Gang Box - F Series 12
Double Gang Weatherproof Cover Plate 11
Duct - Base Vertical Lock Spacer 15
Duct - Intermediate Vertical Lock Spacer 14
Duplex Floor Box Cover 13
Duplex Floor Box 13
ECOVOC Low VOC / Clear Cement 15

Elbows 16-25
Schedule 40
- Radius Elbow Belled - 45° 24" Radius 22
- Special Radius Elbow Belled - 45° 36" Radius 22
- Special Radius Elbow Belled - 45° 48" Radius 22
- Special Radius Elbow Belled - 90° 24" Radius 21
- Special Radius Elbow Belled - 90° 36" Radius 21
- Special Radius Elbow Belled - 90° 48" Radius 22
- Special Radius Elbow Plain End - 45° 24" Radius 20
- Special Radius Elbow Plain End - 45° 36" Radius 21
- Special Radius Elbow Plain End - 45° 48" Radius 21
- Special Radius Elbow Plain End - 90° 24" Radius 19
- Special Radius Elbow Plain End - 90° 36" Radius 20
- Special Radius Elbow Plain End - 90° 48" Radius 20
- Standard Elbows - 11 1/4° Elbow - Plain End 17
- Standard Elbows - 22 1/2° Elbow - Plain End 17
- Standard Elbows - 30° Elbow - Bell End 18
- Standard Elbows - 30° Elbow - Plain End 17
- Standard Elbows - 45° Elbow - Bell End 18
- Standard Elbows - 45° Elbow - Plain End 16
- Standard Elbows - 90° Elbow - Bell End 18
- Standard Elbows - 90° Elbow - Plain End 16

Schedule 80
- Special Radius Elbow Belled - 45° 24" Radius 25
- Special Radius Elbow Belled - 45° 36" Radius 25
- Special Radius Elbow Belled - 45° 48" Radius 25
- Special Radius Elbow Belled - 90° 24" Radius 24
- Special Radius Elbow Belled - 90° 36" Radius 24
- Special Radius Elbow Belled - 90° 48" Radius 24
- Special Radius Elbow Plain End 23
- Special Radius Elbow Plain End - 45° 48" Radius 24
- Special Radius Elbow Plain End - 90° 24" Radius 22
- Special Radius Elbow Plain End - 90° 36" Radius 23
- Special Radius Elbow Plain End - 90° 48" Radius 23
- Standard Elbows - 45° Elbow - Plain End 19
- Standard Elbows - 90° Elbow - Plain End 19

Expansions Joint 5
Junction Box Adapters 13
Junction Box with Gasket 13
KO Plug 12
Meter Offset 5
Meter Riser Kit 14
Octagonal Box 12
Octagonal Box Extension Ring 12
Pipe Strap PVC - 2 Hole 5
Pull Elbow 9
Reducer Bushing 10
Service Entrance Fitting 6
Single Gang Box - F Series 11
Single Gang Cover Plate - F Series 10
Single Gang Deep Box - FD Series 11
Single Gang Weatherproof Cover Plate 11
Slip Meter Riser 14
Solvent Weld End Cap 9
Strain Relief Connector 8
Threaded Strain Relief Connector 8
Terminal Adapter 4
- Female 5
- Male 4

Threaded Reducer Bushing 9
Universal Plug w/Pulling Eye 15
Vinyl Siding Electrical Mount 16

Contents

Rigid PVC Conduit Fittings with Brass Fasteners

Pages 26 - 29

Shown in Alphabetical Order

Access Fitting
- Type C 26
- Type E 27
- Type LL 26
- Type LR 27
- Type T 27
- Type TB 27
- Type LB 26

Double Gang Box - F Serie 28
Double Gang Weatherproof Cover Plate 29
Junction Box with Gasket 28
Single Gang Box - F Series 28
Single Gang Cover Plate - F Series 29
Single Gang Deep Box - FD Series 28
Single Gang Weatherproof Cover Plate 29

ENT - Tubing

Pages 30 - 31

Shown in Alphabetical Order

Coils
- Blue ENT Tubing 30
- Grey ENT Tubing 30

Reels
- Blue ENT Tubing 30
- Grey ENT Tubing 31

Straight Length
- Blue ENT Tubing 31
- Grey ENT Tubing 31

ENT - Fittings

Pages 32 - 35

Shown in Alphabetical Order

45 Degree Angled Form Stubby (Polyethylene) 33
Adapter with set screw 32
Clip Ring 32
Coupling 32
Deep Single Gang Concrete Wall Box 35
Isolator Module Slab Box 34
Quick-Snap Terminal Adapter 32
Shallow Single Gang Concrete Wall Box 35
Shallow Slab Box 34
Slab Box Extension Ring 33
Slab Box with Hub Extensions and Grey Lid 34
Slab Box with Knockouts and Grey Lid 34
Threaded Terminal Adapter with Lock Nut 32
Heavy Duty Lock Nut 33
Straight Stubby (Polyethylene) 33
Tapered Plug (Polyethylene) 33

PVC Enclosures

Pages 36 - 38

Shown in Alphabetical Order

Electrical Enclosures 38
Electrical Trough Box
- Latch Cover 36
- Screw Cover 36

Large Fabricated Junction Boxes 37

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
COUPLING						
	1/2″	E010050	REC10	6141623	E940D	200
	3/4″	E010075	REC15	6141624	E940E	125
	1″	E010100	REC20	6141625	E940F	70
	1 1/4″	E010125	REC25	6141626	E940G	40
	1 1/2″	E010150	REC30	6141627	E940H	30
	2″	E010200	REC35	6141628	E940J	40
	2 1/2″	E010250	REC40	6141629	E940K	20
	3″	E010300	REC45	6141630	E940L	40
	3 1/2″	E010350	REC50	6141631	E940M	30
	4″	E010400	REC55	6141632	E940N	20
	5″	E010500	REC60	6141633	E940P	10
	6″	E010600	REC65	6141634	E940R	8
	8″	E010800	-----	6141635D	-----	3
5° COUPLING						
	2″	E013200	R5EC35	6151457	E245J	20
	2 1/2″	E013250	R5EC40	-----	-----	12
	3″	E013300	R5EC45	6151458	-----	25
	3 1/2″	E013350	R5EC50	-----	-----	15
	4″	E013400	R5EC55	6151459	E245N	15
	5″	E013500	R5EC60	6151460	E245P	8
	6″	E013600	R5EC65	6151461	E245R	4
TERMINAL ADAPTER						
	1/2″	E011050	RTA10	5140103	E943D	200
	3/4″	E011075	RTA15	5140104	E943E	125
	1″	E011100	RTA20	5140105	E943F	70
	1 1/4″	E011125	RTA25	5140106	E943G	40
	1 1/2″	E011150	RTA30	5140107	E943H	30
	2″	E011200	RTA35	5140108	E943J	40
	2 1/2″	E011250	RTA40	5140109	E943K	20
	3″	E011300	RTA45	5140110	E943L	40
	3 1/2″	E011350	RTA50	5140111	E943M	30
	4″	E011400	RTA55	5140112	E943N	20
	5″	E011500	RTA60	5140113	E943P	10
	6″	E011600	RTA65	5140114	E943R	8




Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
FEMALE ADAPTER (NPT TAPERED THREAD)						
	1/2″	E012050	RFA10	5140043	E942D	200
	3/4″	E012075	RFA15	5140044	E942E	125
	1″	E012100	RFA20	5140045	E942F	70
	1 1/4″	E012125	RFA25	5140046	E942G	40
	1 1/2″	E012150	RFA30	5140047	E942H	30
	2″	E012200	RFA35	5140048	E942J	40
	2 1/2″	E012250	RFA40	5140049	E942K	20
	3″	E012300	RFA45	5140050	E942L	40
	3 1/2″	E012350	RFA50	5140051	E942M	30
	4″	E012400	RFA55	5140052	E942N	20
	5″	E012500	RFA60	5140053	E942P	10
	6″	E012600	RFA65	5140054	E942R	8
EXPANSIONS JOINT						
	1/2″	E016050	REJ10	5144031	E945D	25
	3/4″	E016075	REJ15	5144032	E945E	10
	1″	E016100	REJ20	5144033	E945F	10
	1 1/4″	E016125	REJ25	5144034	E945G	5
	1 1/2″	E016150	REJ30	5144035	E945H	5
	2″	E016200	REJ35	5144036	E945J	25
	2 1/2″	E016250	REJ40	5144037	E945K	12
	3″	E016300	REJ45	5144038	E945L	12
	3 1/2″	E016350	REJ50	5144039	E945M	6
	4″	E016400	REJ55	5144040	E945N	6
	5″	E016500	REJ60	5144041	E945P	1
	6″	E016600	REJ65	5144042	E945R	1
PIPE STRAP PVC - 2 HOLE						
	1/2″	E039050	RPS10	5133736	E977DC	300
	3/4″	E039075	RPS15	5133737	E977EC	200
	1″	E039100	RPS20	5133738	E977FC	200
	1 1/4″	E039125	RPS25	5133733	E977GC	200
	1 1/2″	E039150	RPS30	5133734	E977HC	200
	2″	E039200	RPS35	5133735	E977JC	200
METER OFFSET						
	1 1/4″	E024125	RMO25	5133183	E995G	15
	2″	E024200	RMO35	5133185	E995J	8


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SERVICE ENTRANCE FITTING						
	1/2″	E025050	REF10	5133590	-----	10
	3/4″	E025075	REF15	5133591	E998E CAR	10
	1″	E025100	REF20	5133741	E998F CAR	20
	1 1/4″	E025125	REF25	5133742	E998G CAR	20
	1 1/2″	E025150	REF30	5133695	E998H CAR	20
	2″	E025200	REF35	5133743	E998J	5
	2 1/2″	E025250	REF40	5133696	E998K UPC	5
	3″	E025300	REF45	5133697	E998L	5
	3 1/2″	E025350	REF50	5133698	-----	5
	4″	E025400	REF55	5133699	E998N	1
ACCESS FITTING - TYPE LB						
	1/2″	E033050	RSLB10S	5133663	E986D CAR	25
	3/4″	E033075	RSLB20S	5133664	E986E CAR	15
	1″	E033100	RSLB30S	5133665	E986F CAR	10
	1 1/4″	E033125	RSLB40S	5133666	E986G CAR	10
	1 1/2″	E033150	RSLB50S	5133667	E986H CAR	10
	2″	E033200	RSLB60S	5133668	E986J	5
	2 1/2″	E033250	RSLB70S	5133669	E986K	5
	3″	E033300	RSLB80S	5133670	E986L	5
	3 1/2″	E033350	RSLB90S	5133671	E986M	4
	4″	E033400	RSLB100S	5133672	E986N	4
ACCESS FITTING - TYPE C						
	1/2″	E032050	RSC10S	5133101	E987D CAR	25
	3/4″	E032075	RSC20S	5133102	E987E CAR	15
	1″	E032100	RSC30S	5133103	E987F CAR	10
	1 1/4″	E032125	RSC40S	5133104	E987G CAR	10
	1 1/2″	E032150	RSC50S	5133105	E987H CAR	10
	2″	E032200	RSC60S	5133106	E987J	5
	2 1/2″	E032250	RSC70S	5133108	-----	5
	3″	E032300	RSC80S	5133107	-----	5
	3 1/2″	E032350	RSC90S	5133110	-----	4
	4″	E032400	RSC100S	5133109	-----	4


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
ACCESS FITTING - TYPE LL						
	1/2″	E034050	RSLL10S	5133660	E984D CAR	25
	3/4″	E034075	RSLL20S	5133661	E984E CAR	15
	1″	E034100	RSLL30S	5133662	E984F CAR	10
	1 1/4″	E034125	RSLL40S	5133649	E984G CAR	10
	1 1/2″	E034150	RSLL50S	5133648	E984H CAR	10
	2″	E034200	RSLL60S	5133647	E984J	5
	2 1/2″	E034250	RSLL70S	5133644	------	5
	3″	E034300	RSLL80S	5133646	------	5
	3 1/2″	E034350	RSLL90S	5133640	------	4
	4″	E034400	RSLL100S	5133645	------	4
ACCESS FITTING - TYPE LR						
	1/2″	E035050	RSLR10S	5133650	E985D CAR	25
	3/4″	E035075	RSLR20S	5133651	E985E CAR	15
	1″	E035100	RSLR30S	5133652	E985F CAR	10
	1 1/4″	E035125	RSLR40S	5133653	E985G CAR	10
	1 1/2″	E035150	RSLR50S	5133654	E985H CAR	10
	2″	E035200	RSLR60S	5133655	E985J	5
	2 1/2″	E035250	RSLR70S	5133658	------	5
	3″	E035300	RSLR80S	5133656	------	5
	3 1/2″	E035350	RSLR90S	5133659	------	4
	4″	E035400	RSLR100S	5133657	------	4
ACCESS FITTING - TYPE E						
	1/2″	E036050	RSE10S	5133151	E998D CAR	25
	3/4″	E036075	RSE20S	5133152	E998E	15
	1″	E036100	RSE30S	5133153	E988F CAR	10
	1 1/4″	E036125	RSE40S	5133154	E988G CAR	10
	1 1/2″	E036150	RSE50S	5133155	E988H CAR	10
	2″	E036200	RSE60S	5133156	E988J	5
	2 1/2″	E036250	RSE70S	5133157	------	5
	3″	E036300	RSE80S	5133158	------	5
	3 1/2″	E036350	RSE90S	5133160	------	4
	4″	E036400	RSE100S	5133159	------	4


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
ACCESS FITTING - TYPE T						
	1/2″	E037050	RST10S	5133563	E983D CAR	25
	3/4″	E037075	RST20S	5133564	E983E CAR	15
	1″	E037100	RST30S	5133565	E983F	10
	1 1/4″	E037125	RST40S	5133566	E983G	10
	1 1/2″	E037150	RST50S	5133567	E983H CAR	10
	2″	E037200	RST60S	5133568	E983J	5
	2 1/2″	E037250	RST70S	5133569	-----	2
	3″	E037300	RST80S	5133570	-----	2
	3 1/2″	E037350	RST90S	5133572	-----	1
	4″	E037400	RST100S	5133571	-----	1
ACCESS FITTING - TYPE TB						
	1/2″	E069050	RSTB10S	-----	-----	30
	3/4″	E069075	RSTB20S	-----	-----	20
	1″	E069100	RSTB30S	-----	-----	10
	1 1/4″	E069125	RSTB40S	-----	-----	10
STRAIN RELIEF CONNECTOR						
	3/4″	E030075	RSRC15	-----	-----	25
THREADED STRAIN RELIEF CONNECTOR						
	1/2″	E031050	RTSRC10	5133430	-----	25
	3/4″	E031075	RTSRC15	5133431	-----	25





Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
PULL ELBOW						
	1/2″	E027050	RPE10	5240100	E990DR CAR	75
	3/4″	E027075	RPE15	5240101	E990ER CAR	50
SOLVENT WELD END CAP						
	1/2″	E026050	RCAP10	5140031	E958D	100
	3/4″	E026075	RCAP15	5140032	E958E	100
	1″	E026100	RCAP20	5140033	E958F	50
	1 1/4″	E026125	RCAP25	5140034	E958G	25
	1 1/2″	E026150	RCAP30	5140035	E958H	25
	2″	E026200	RCAP35	5140037	E958J	50
	2 1/2″	E026250	RCAP40	5140038	E958K	25
	3″	E026300	RCAP45	5140039	E958L	25
	4″	E026400	RCAP55	5140040	E958N	25
	5″	E026500	RCAP60	5140041	E958P	25
	6″	E026600	RCAP65	5140042	E958R	10
	8″	E026800	-----	-----	-----	6
THREADED REDUCER BUSHING						
	3/4″ X 1/2″	E0150705	R1825	-----	E9842D	200
	1″ X 1/2″	E0151005	R1826	-----	-----	200
	1″ X 3/4″	E0151007	R1827	-----	E9842E	200
BELL END (HUB X SPIGOT) - MOLDED						
	1/2″	E070050	REB10	5144003	-----	100
	3/4″	E070075	REB15	5144004	-----	100
	1″	E070100	REB20	5144005	E997F	50
	1 1/4″	E070125	REB25	5144006	E997G	50
	1 1/2″	E070150	REB30	5144007	E997H	50
	2″	E070200	REB35	5144008	E997J	40
	2 1/2″	E070250	REB40	5144009	E997K	30
	3″	E070300	REB45	5144010	E997L	50
	3 1/2″	E070350	REB50	5144011	E997M	50
	4″	E070400	REB55	5144012	E997N	50
	5″	E070500	REB60	5144013	E997P	25
	6″	E070600	REB65	5144014	E997R	15


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
REDUCER BUSHING						
	3/4" X 1/2"	E0140705	R1805	5142220	E950ED	100
	1" X 1/2"	E0141005	R1805 1	-----	E950FD CAR	3 BAGS X 100
	1" X 3/4"	E0141007	R1806	5142221	E950FE	100
	1 1/4" X 3/4"	E0141207	R1807 1	-----	E950GE CAR	2 BAGS X 25
	1 1/4" X 1"	E0141210	R1807	5142222	E950GF	50
	1 1/2" X 1"	E0141510	R1808 1	-----	E950HF CAR	50
	1 1/2" X 1 1/4"	E0141512	R1808	514223	E950HG CAR	50
	2" X 1"	E0142010	R1809 1	-----	-----	50
	2" X 1 1/4"	E0142012	R1809	-----	E950JG CAR	25
	2" X 1 1/2"	E0142015	R1810	5142224	E950JH CAR	25
	2 1/2" X 2"	E0142520	R1811	5142225	E950KJ CAR	25
	3" X 2"	E0143020	R1812 1	-----	E950LJ CAR	25
	3" X 2 1/2"	E0143025	R1812	5142226	E950LK	25
	4" X 2"	E0144020	R1813 1	-----	-----	15
	4" X 3"	E0144030	R1813	5142227	E950NL	20
	4" 3 1/2"	E0144035	R1814	5142229	-----	20
SINGLE GANG COVER PLATE - F SERIES						
	A. TOGGLE	E046002	RTSC15/10	-----	-----	100
	B. DUPLEX	E046001	RDRC15/10	-----	-----	100
	C. 15 AMP	E046004	R20RC15/10	-----	-----	100
	D. 20 AMP	E046003	R20 3RC15/10	-----	-----	100
	E. 30 AMP	E046005	R30 3RC15/10	-----	-----	100
	F. BLANK W/ GASKET	E046006	RBRC15/10	5133362	E980CN CAR	50



Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SINGLE GANG WEATHERPROOF COVER PLATE						
	A. TOGGLE S/ COVER	E047002	RVSC15/10	5133330	E98TSCN CAR	10
	B. PLUNGER S/ COVER	E047008	RVPT15/10	5133335	------	10
	C. TOGGLE	E047009	RWTG15/10	5133361	E98SSNCN CAR	10
	D. DUPLEX	E047001	RWDR15/10	5133352	E98GDRN CAR	10
	D. DUPLEX WHITE	E047010	RWDR15/10W	------	------	20
	E. GROUND FAULT	E047007	RWGF15/10	5133348	E98GFCN CAR	10
	E. GROUND FAULT WHITE	E047011	RWGF15/10W	------	------	20
	F. 15 AMP	E047003	RWTL15	5133350	E98SRCN CAR	10
	F. 20 AMP	E047004	RWTL20	5133320	E98G20N	10
	F. 30 AMP	E047005	RWTL30	5133321	E98G30N CAR	10
	F. 50 AMP	E047006	RWTL50	5133322	E98G5FN CAR	10
DOUBLE GANG WEATHERPROOF COVER PLATE						
	B. GFI & TOGGLE	E049005	------	5133345	E9G2GTN CAR	10
	C. DUPLEX & TOGGLE	E049006	------	5133337	E9GDSN CAR	10
	D. DOUBLE DU PLEX	E049007	------	5133347	E9GDDN CAR	10
	E. TOGGLE	E049008	------	5133331	E9G2SSN	10
	F. BLANK	E049009		5133410	E9802CN CAR	25
SINGLE GANG BOX - F SERIES						
	A. 1/2" FS	E042001	RFS10	5133363	E980DFN	10
	A. 3/4" FS	E042002	RFS15	5133364	E980EFN	10
	B. 1/2" FSS	E042003	RFSS10	5133540	E982DFN	10
	B. 3/4" FSS	E042004	RFSS15	5133542	E982EFN	10
	C. 1/2" FSC	E042005	RFSC10	5133463	E981DFN	10
	C. 3/4" FSC	E042006	RFSC15	5133464	E981EFN	10
	D. 1/2" FSCC	E042007	RFSCC10	5133544	E979DFN CAR	10
	D. 3/4" FSCC	E042008	RFSCC15	5133545	E979ERN CAR	10
SINGLE GANG DEEP BOX - FD SERIES						
	A. 1/2" FDS	E043001	RFDS10	5133300	E9801DN	10
	A. 3/4" FDS	E043002	RFDS15	5133301	E9801EN	10
	A. 1" FDS	E043003	RFDS20	5133302	E9801FN	10
	B. 1/2" FDC	E043004	RFDC10	5133310	E9811DN	10
	B. 3/4" FDC	E043005	RFDC15	5133311	E9811EN	10
	B. 1" FDC	E043006	RFDC20	5133312	E9811FN	10
	C. BLANK	E043007	RFD	5133420	E9801	10


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
DOUBLE GANG BOX - F SERIES						
	A. 1/2" FS	E041001	-----	5133380	E9802D	5
	A. 3/4" FS	E041002	-----	5133381	E9802E	5
	A. 1" FS	E041003	-----	5133382	E9802F	5
	B. 1/2" FSS	E041004	-----	5133390	-----	5
	B. 3/4" FSS	E041005	-----	5133391	-----	5
	B. 1" FSS	E041006	-----	5133392	-----	5
	C. 1/2" FSC	E041007	-----	5133370	E9812D	5
	C. 3/4" FSC	E041008	-----	5133371	E9812E	5
	C. 1" FSC	E041009	-----	5133372	E9812F	5
	D. 1/2" FSCC	E041011	-----	5133400	-----	5
	D. 3/4" FSCC	E041012	-----	5133401	-----	5
	D. 1" FSCC	E041013	-----	5133402	-----	5
	E. BLANK	E041010	-----	-----	E9802	5
OCTAGONAL BOX						
	4" X 1 1/2" (3/4" X1/2")	E028150	ROB15/10	-----	-----	20
	4" X 2" (1")	E028200	ROB20	-----	-----	12
KO PLUG						
	3/4"	E067075	RKO15	-----	-----	1
	1"	E067100	RTKO20	-----	-----	1
OCTAGONAL BOX EXTENSION RING						
	1"	E029100	RXR20	-----	-----	20
	2"	E029200	RXR35	-----	-----	20

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
DUPLEX FLOOR BOX/ LEVEL RING/ POUR COVER/ REDUCER BUSHING						
	4 - 3/4"	E068004	RFDB4	5133760	E971FB	9
	2 - 1", 2 - 3/4"	E068001	RFDB2	5133758	E971FB	9
DUPLEX FLOOR BOX COVER						
	POLY BRONZE COVER	E068003	RFDBC	5133678		10
JUNCTION BOX WITH GASKET						
	4" X 4" X 2"	E051442	RJB442	5133705	E989NNJ CAR	10
	4" X 4" X 4"	E051444	RJB444	5133709	E987N CAR	10
	4" X 4" X 6"	E051446	RJB446	5133707	E989NNR CAR	10
	5" X 5" X 2"	E051552	RJB552	5133706	E989PPJ CAR	10
	6" X 6" X 4"	E051664	RJB664	5133710	E987R CAR	10
	6" X 6" X 6"	E051666	RJB666	5133711	E989RRR UPC	5
	8" X 8" X 4"	E051884	RJB884	5133712	E989N CAR	5
	8" X 8" X 7"	E051887	RJB887	5133708	E989SSX UPC	4
	12" X 12" X 4"	E05112124	RJB12124	5133714	E989UUN	2
	12" X 12" X 6"	E05112126	RJB12126	5133713	E989R UPC	2
	12" X 12" X 8"	E05112128	RJB12128			3
JUNCTION BOX ADAPTERS						
	1/2"	E059050	RJBA10	5133715	E996D	100
	3/4"	E059075	RJBA15	5133716	E996E	100
	1"	E059100	RJBA20	5133717	E996F	100
	1 1/4"	E059125	RJBA25	5133718	E996G	50
	1 1/2"	E059150	RJBA30	5133719	E996H	50
	2"	E059200	RJBA35	5133720	E996J	25
	2 1/2"	E059250	RJBA40	5133721	E996K CAR	10
	3"	E059300	RJBA45	5133722	E996L	10
	3 1/2"	E059350	RJBA50	5133723		10
	4"	E059400	RJBA55	5133724	E996N	10

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
METER RISER KIT						
	1 1/4″	E092125	-----	-----	-----	1
	1 1/2″	E092150	-----	-----	-----	1
	2″	E092200	-----	-----	-----	1
	2 1/2″	E092250	-----	-----	-----	1
	3″	E092300	-----	-----	-----	1
SLIP METER RISER						
	2″	E093200	-----	5144028	E954JXX	20
	2 1/2″	E093250	-----	5144030	E954KXX	15
	3″	E093300	-----	5144043	E954LXX	10
	4″	E093400	-----	5144027	E954NXX	5
DUCT - INTERMEDIATE VERTICAL LOCK SPACER						
	2 X 1 1/2″	IS2015	IS2015	-----	-----	350
	2 X 2″	IS2020	IS2020	-----	-----	300
	2 X 3″	IS2030	IS2030	-----	-----	200
	3 X 1 1/2″	IS3015	IS3015	-----	-----	225
	3 X 2″	IS3020	IS3020	-----	-----	200
	3 X 3″	IS3030	IS3030	-----	-----	125
	4 X 1 ″	IS4010	IS4010	-----	-----	200
	4 X 1 1/2″	IS4015	IS4015	-----	-----	150
	4 X 2″	IS4020	IS4020	-----	-----	125
	4 X 3″	IS4030	IS4030	-----	-----	90
	5 X 1 1/2″	IS5015	IS5015	-----	-----	100
	5 X 2″	IS5020	IS5020	-----	-----	100
	5 X 3″	IS5030	IS5030	-----	-----	80
	6 X 1 1/2″	IS6015	IS6015	-----	-----	100
	6 X 2″	IS6020	IS6020	-----	-----	90
	6 X 3″	IS6030	IS6030	-----	-----	70
	8 X 1 1/2″	IS8015	-----	-----	-----	60
	8 X 2″	IS8020	-----	-----	-----	60

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
DUCT - BASE VERTICAL LOCK SPACER						
	2 X 1 1/2"	BS2015	BS2015	-----	-----	250
	2 X 2"	BS2020	BS2020	-----	-----	225
	2 X 3"	BS2030	BS2030	-----	-----	225
	3 X 1 1/2"	BS3015	BS3015	-----	-----	175
	3 X 2"	BS3020	BS3020	-----	-----	155
	3 X 3"	BS3030	BS3030	-----	-----	150
	4 X 1 "	BS4010	BS4010	-----	-----	175
	4 X 1 1/2"	BS4015	BS4015	-----	-----	140
	4 X 2"	BS4020	BS4020	-----	-----	140
	4 X 3"	BS4030	BS4030	-----	-----	120
	5 X 1 1/2"	BS5015	BS5015	-----	-----	120
	5 X 2"	BS5020	BS5020	-----	-----	120
	5 X 3"	BS5030	BS5030	-----	-----	100
	6 X 1 1/2"	BS6015	BS6015	-----	-----	100
	6 X 2"	BS6020	BS6020	-----	-----	100
	6 X 3"	BS6030	BS6030	-----	-----	95
	8 X 1 1/2"	BS8015	-----	-----	-----	50
	8 X 2"	BS8020	-----	-----	-----	50
UNIVERSAL PLUG W/PULLING EYE						
	2"	E091200	PLUG02	5315258	P258JT	70
	3"	E091300	PLUG03	5315260	P258LT	45
	4"	E091400	PLUG04	5315262	P258NT	80
	5"	E091500	PLUG05	5315263	P258PT	45
	6"	E091600	PLUG06	5315264	P258RT	35
ECOVOC LOW VOC / CLEAR CEMENT						
	PINT	RVOC475	RVOC475	7210612	VC9963	12
	QUART	RVOC950ML	RVOC950ML	7210613	VC9962	12

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
VINYL SIDING ELECTRICAL MOUNT						
	7 1/2" X 7 1/2"	10000	-----	-----	-----	10
	7 5/8" X 12"	41000	-----	-----	-----	10
	7 1/2" X 7 3/4"	13000	-----	-----	-----	10
	6" X 4 1/2"	43000	-----	-----	-----	10
	5 1/2" X 7 6/16"	44000	-----	-----	-----	10
	14 1/2" X 19"	42000	-----	-----	-----	1
	7" X 7"	17000	-----	-----	-----	10
SCH 40 STANDARD ELBOWS - 90° ELBOW - PLAIN END						
	1/2"	E018050	REE1090PE	5133823	UA9AD	50
	3/4"	E018075	REE1590PE	5133824	UA9AE	35
	1"	E018100	REE2090PE	5133825	UA9AF	20
	1 1/4"	E018125	REE2590PE	5133826	UA9AG	30
	1 1/2"	E018150	REE3090PE	5133827	UA9AH	30
	2"	E018200	REE3590PE	5133828	UA9AJ	15
	2 1/2"	E018250	REE4090PE	5133829	UA9AK CAR	18
	3"	E018300	REE4590PE	5133830	UA9AL	14
	3 1/2"	E018350	REE5090PE	5133831	UA9AM	12
	4"	E018400	REE5590PE	5133832	UA9AN	10
	5"	E018500	REE6090PE	5133835	UA9AP	1
	6"	E018600	REE6590PE	5133834	UA9AR	1
SCH 40 STANDARD ELBOWS - 45° ELBOW - PLAIN END						
	1/2"	E019050	REE1045PE	5133763	UA7AD	50
	3/4"	E019075	REE1545PE	5133764	UA7AE	25
	1"	E019100	REE2045PE	5133765	UA7AF	20
	1 1/4"	E019125	REE2545PE	5133766	UA7AG	25
	1 1/2"	E019150	REE3045PE	5133767	UA7AH	20
	2"	E019200	REE3545PE	5133768	UA7AJ	10
	2 1/2"	E019250	REE4045PE	5133769	UA7AK	20
	3"	E019300	REE4545PE	5133770	UA7AL CAR	8
	3 1/2"	E019350	REE5045PE	5133771	UA7AM	5
	4"	E019400	REE5545PE	5133772	UA7AN	20
	5"	E019500	REE6045PE	5133773	UA7AP	1
	6"	E019600	REE6545PE	5133774	UA7AR	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH 40 STANDARD ELBOWS - 30° ELBOW - PLAIN END						
	1/2″	E020050	REE1030PE	5133755	UA6AD	50
	3/4″	E020075	REE1530PE	5133744	UA6AE	25
	1″	E020100	REE2030PE	5133745	UA6AF	20
	1 1/4″	E020125	REE2530PE	5133746	UA6AG	25
	1 1/2″	E020150	REE3030PE	5133747	UA6AH	50
	2″	E020200	REE3530PE	5133748	UA6AJ	10
	2 1/2″	E020250	REE4030PE	5133749	UA6AK	20
	3″	E020300	REE4530PE	5133750	UA6AL	8
	3 1/2″	E020350	REE5030PE	5133751	UA6AM	5
	4″	E020400	REE5530PE	5133775	UA6AN	20
	5″	E020500	REE6030PE	5133753	UA6AP	1
	6″	E020600	REE6530PE	5133754	UA6AR	1
SCH 40 STANDARD ELBOWS - 22 1/2° ELBOW - PLAIN END						
	1 1/2″	E084150	-----	5134094	UA5AH	20
	2″	E084200	-----	5134067	UA5AJ	10
	2 1/2″	E084250	-----	5134096	UA5AK	20
	3″	E084300	-----	5134068	UA5AL	8
	3 1/2″	E084350	-----	5134095	UA5AM	5
	4″	E084400	-----	5133757	UA5AN	20
	5″	E084500	-----	5134037	UA5AP	1
	6″	E084600	-----	5133901	UA5AR	1
SCH 40 STANDARD ELBOWS - 11 1/4° ELBOW - PLAIN END						
	2″	E087200	-----	-----	UA3AJ	1
	3″	E087300	-----	-----	UA3AL	1
	4″	E087400	-----	-----	UA3AN	1
	5″	E087500	-----	-----	UA3AP	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH 40 STANDARD ELBOWS - 90° ELBOW - BELL END						
	1/2″	E021050	REE1090	5233823	UA9ADB	50
	3/4″	E021075	REE1590	5233824	UA9AEB	35
	1″	E021100	REE2090	5233825	UA9AFB	20
	1 1/4″	E021125	REE2590	5233826	UA9AGB	30
	1 1/2″	E021150	REE3090	5233827	UA9AHB	30
	2″	E021200	REE3590	5233828	UA9AJB	15
	2 1/2″	E021250	REE4090	5233829	UA9AKB CAR	18
	3″	E021300	REE4590	5233830	UA9ALB CAR	14
	3 1/2″	E021350	REE5090	5233831	UA9AMB	12
	4″	E021400	REE5590	5233832	UA9ANB	10
	5″	E021500	REE6090	5233835	UA9APB	1
	6″	E021600	REE6590	5233834	UA9ARB	1
SCH 40 STANDARD ELBOWS - 45° ELBOW - BELL EN						
	1/2″	E022050	REE1045	5233763	UA7ADB	50
	3/4″	E022075	REE1545	5233764	UA7AEB	25
	1″	E022100	REE2045	5233765	UA7AFB	20
	1 1/4″	E022125	REE2545	5233766	UA7AGB	25
	1 1/2″	E022150	REE3045	5233767	UA7AHB	20
	2″	E022200	REE3545	5233768	UA7AJB	10
	2 1/2″	E022250	REE4045	5233769	UA7AKB	20
	3″	E022300	REE4545	5233770	UA7ALB	8
	3 1/2″	E022350	REE5045	5233771	UA7AMB	5
	4″	E022400	REE5545	5233772	UA7ANB	20
	5″	E022500	REE6045	5233773	UA7APB	1
	6″	E022600	REE6545	5233774	UA7ARB	1
SCH 40 STANDARD ELBOWS - 30° ELBOW - BELL END						
	1/2″	E072050	REE1030		UA6ADB	50
	3/4″	E072075	REE1530		UA6AEB	35
	1″	E072100	REE2030		UA6AFB	50
	1 1/4″	E072125	REE2530		UA6AGB	30
	1 1/2″	E072150	REE3030		UA6AHB	50
	2″	E072200	REE3530	5233748	UA6AJB	10
	2 1/2″	E072250	REE4030		UA6AKB	10
	3″	E072300	REE4530	5233750	UA6ALB	8
	3 1/2″	E072350	REE5030	5233751	UA6AMB	5
	4″	E072400	REE5530	5233776	UA6ANB	20
	5″	E072500	REE6030	5233753	UA6APB	1
	6″	E072600	REE6530	5233754	UA6ARB	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH 80 STANDARD ELBOWS - SCH80 90° ELBOW - PLAIN END						
	1/2″	E085050	-----	5121053	UB9AD	50
	3/4″	E085075	-----	5121054	UB9AE	35
	1″	E085100	-----	5121055	UB9AF	20
	1 1/4″	E085125	-----	5121056	UB9AG	30
	1 1/2″	E085150	-----	5121057	UB9AH	30
	2″	E085200	-----	5121058	UB9AJ	15
	2 1/2″	E085250	-----	5121059	UB9AK CAR	18
	3″	E085300	-----	5121060	UB9AL CAR	14
	4″	E085400	-----	5121061	UB9AN	10
	5″	E085500	-----	5121062	UB9AP	1
	6″	E085600	-----	5121063	UB9AR	1
SCH 80 STANDARD ELBOWS - SCH80 45° ELBOW - PLAIN END						
	1/2″	E086050	-----	5121003	UB7AD	50
	3/4″	E086075	-----	5121004	UB7AE UPC	25
	1″	E086100	-----	5121005	UB7AF UPC	20
	1 1/4″	E086125	-----	5121006	UB7AG	25
	1 1/2″	E086150	-----	5121007	UB7AH	20
	2″	E086200	-----	5121008	UB7AJ UPC	10
	2 1/2″	E086250	-----	5121009	UB7AK	20
	3″	E086300	-----	5121010	UB7AL	8
	4″	E086400	-----	5121011	UB7AN	20
	5″	E086500	-----	5121012	UB7AP	1
	6″	E086600	-----	5121013	UB7AR	1
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 90° 24″ RADIUS						
	1″	E07510024	-----	5133859	UA9DF	1
	1 1/4″	E07512524	-----	5133883	UA9DG	1
	1 1/2″	E07515024	-----	5133873	UA9DH	1
	2″	E07520024	-----	5133836	UA9DJ	1
	2 1/2″	E07525024	-----	5133847	UA9DK	1
	3″	E07530024	-----	5133837	UA9DL	1
	3 1/2″	E07535024	-----	5133893	UA9DM	1
	4″	E07540024	-----	5133822	UA9DN	1
	5″	E07550024	-----	-----	-----	1
	6″	E07560024	-----	-----	-----	1


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 90° 36" RADIUS						
	1"	E07510036	-----	5133852	UA9FF	1
	1 1/4"	E07512536	-----	5133884	UA9FG	1
	1 1/2"	E07515036	-----	5133866	UA9FH	1
	2"	E07520036	-----	5133848	UA9FJ UPC	1
	2 1/2"	E07525036	-----	5133857	UA9FK UPC	1
	3"	E07530036	-----	5133820	UA9FL	1
	3 1/2"	E07535036	-----	5133818	UA9FM	1
	4"	E07540036	-----	5133821	UA9FN	1
	5"	E07550036	-----	5133841	UA9FP	1
	6"	E07560036	-----	5133877	UA9FR	1
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 90° 48" RADIUS						
	1"	E07510048	-----	5133864	UA9HF	1
	1 1/4"	E07512548	-----	5133871	UA9HG	1
	1 1/2"	E07515048	-----	5133865	UA9HH	1
	2"	E07520048	-----	5133876	UA9HJ	1
	2 1/2"	E07525048	-----	5133849	UA9HK	1
	3"	E07530048	-----	5133817	UA9HL	1
	3 1/2"	E07535048	-----	5133892	UA9HM	1
	4"	E07540048	-----	5133843	UA9HN	1
	5"	E07550048	-----	5133842	UA9HP	1
	6"	E07560048	-----	5133816	UA9HR	1
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 45° 24" RADIUS						
	1"	E07610024	-----	5133875	UA7DF	1
	1 1/4"	E07612524	-----	5133941	UA7DG	1
	1 1/2"	E07615024	-----	5133874	UA7DH	1
	2"	E07620024	-----	5133815	UA7DJ	1
	2 1/2"	E07625024	-----	5133935	UA7DK	1
	3"	E07630024	-----	5133800	UA7DL	1
	3 1/2"	E07635024	-----	5133802	UA7DM	1
	4"	E07640024	-----	5133812	UA7DN	1
	5"	E07650024	-----	-----	-----	1
	6"	E07660024	-----	-----	-----	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 45° 36" RADIUS						
	1"	E07610036	------	5133919	UA7FF	1
	1 1/4"	E07612536	------	5133956	UA7FG	1
	1 1/2"	E07615036	------	5133810	UA7FH	1
	2"	E07620036	------	5133778	UA7FJ	1
	2 1/2"	E07625036	------	5133801	UA7FK	1
	3"	E07630036	------	5133779	UA7FL	1
	3 1/2"	E07635036	------	5133939	UA7FM	1
	4"	E07640036	------	5133777	UA7FN	1
	5"	E07650036	------	5133780	UA7FP	1
	6"	E07660036	------	5133880	UA7FR	1
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 45° 48" RADIUS						
	1"	E07610048	------	5133940	UA7HF	1
	1 1/4"	E07612548	------	5133942	UA7HG	1
	1 1/2"	E07615048	------	5133811	UA7HH	1
	2"	E07620048	------	5133798	UA7HJ	1
	2 1/2"	E07625048	------	5134010	UA7HK	1
	3"	E07630048	------	5133781	------	1
	3 1/2"	E07635048	------	5133979	------	1
	4"	E07640048	------	5133776	UA7HN	1
	5"	E07650048	------	5133814	UA7HP	1
	6"	E07660048	------	5133813	UA7HR	1
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 90° 24" RADIUS						
	2"	E07920024	------	5133924	UA9DJB UPC	1
	2 1/2"	E07925024	------	5233847	UA9DKB UPC	1
	3"	E07930024	------	5233837	UA9DLB UPC	1
	3 1/2"	E07935024	------	5233893	UA9DMB	1
	4"	E07940024	------	5233822	UA9DNB	1
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 90° 36" RADIUS						
	2"	E07920036	------	5233848	UA9FJB	1
	2 1/2"	E07925036	------	5233857	UA9FKB	1
	3"	E07930036	------	5233930	UA9FLB	1
	3 1/2"	E07935036	------	5233818	UA9FMB	1
	4"	E07940036	------	5233842	UA9FNB	1
	5"	E07950036	------	5233841	UA9FPB	1
	6"	E07960036	------	5233877	UA9FRB	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 90° 48" RADIUS						
	2"	E07920048	-----	5233876	UA9HJB	1
	2 1/2"	E07925048	-----	5233849	UA9HKB	1
	3"	E07930048	-----	5233817	UA9HLB	1
	3 1/2"	E07935048	-----	5233892	-----	1
	4"	E07940048	-----	5233843	UA9HNB	1
	5"	E07950048	-----	5233868	UA9HPB	1
	6"	E07960048	-----	5233816	UA9HRB	1
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 45° 24" RADIUS						
	2"	E08020024	-----	5233815	UA7DJB	1
	2 1/2"	E08025024	-----	5233935	UA7DKB	1
	3"	E08030024	-----	5233800	UA7DLB	1
	3 1/2"	E08035024	-----	5233802	-----	1
	4"	E08040024	-----	5233812	UA7DNB	1
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 45° 36" RADIUS						
	2"	E08020036	-----	5233778	UA7FJB	1
	2 1/2"	E08025036	-----	5233801	UA7FKB	1
	3"	E08030036	-----	5233779	UA7FLB	1
	3 1/2"	E08035036	-----	5233939	-----	1
	4"	E08040036	-----	5233777	UA7FNB	1
	5"	E08050036	-----	5233780	UA7FPB	1
	6"	E08060036	-----	5133894	UA7FRB	1
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 45° 48" RADIUS						
	2"	E08020048	-----	5133759	UA7HJB	1
	2 1/2"	E08025048	-----	5233785	-----	1
	3"	E08030048	-----	5233782	UA7HLB	1
	3 1/2"	E08035048	-----	5233943	-----	1
	4"	E08040048	-----	5133761	UA7HNB	1
	5"	E08050048	-----	5233781	UA7HPB	1
	6"	E08060048	-----	5233813	UA7HRB	1
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END - 90° 24" RADIUS						
	1"	E07710024	-----	5121018	UB9DF	1
	1 1/4"	E07712524	-----	5119824	UB9DG	1
	1 1/2"	E07715024	-----	5121015	UB0DH UPC	1
	2"	E07720024	-----	5121019	UB9DJ UPC	1
	2 1/2"	E07725024	-----	5121028	UB9DK UPC	1
	3"	E07730024	-----	5121020	UB9DL	1
	4"	E07740024	-----	5121022	UB9DN	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END - 90° 36" RADIUS						
	1"	E07710036		5121080	UB9FF	1
	1 1/4"	E07712536		5121084	UB9FG	1
	1 1/2"	E07715036		5121100	UB9FH	1
	2"	E07720036		5121021	UB9FJ	1
	2 1/2"	E07725036		5121016	UB9FK	1
	3"	E07730036		5121081	UB9FL	1
	4"	E07740036		5121023	UB9FN	1
	5"	E07750036		5121083	UB9FP	1
	6"	E07760036		5121073	UB9FR	1
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END - 90° 48" RADIUS						
	1"	E07710048		5121065	UB9HF	1
	1 1/4"	E07712548		5136510	UB9HG	1
	1 1/2"	E07715048		5121076	UB9HH	1
	2"	E07720048		5121075	UB9HJ	1
	2 1/2"	E07725048		5121030	UB9HK	1
	3"	E07730048		5121082	UB9HL	1
	4"	E07740048		5121024	UB9HN	1
	5"	E07750048		5121025	UB9HP	1
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END						
	1"	E07810024		5136500	UB7DF	1
	1 1/4"	E07812524		5136512	UB7DG	1
	1 1/2"	E07815024		5163533	UB7DH	1
	2"	E07820024		5121101	UB7DJ	1
	2 1/2"	E07825024		5121943	UB7DK	1
	3"	E07830024		5121014	UB7DL	1
	4"	E07840024		5121089	UB7DN	1
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END						
	1"	E07810036		5136502		1
	1 1/4"	E07812536		5136514	UB7FG	1
	1 1/2"	E07815036		5136533	UB7FH	1
	2"	E07820036		5121098	UB7FJ	1
	2 1/2"	E07825036		5121150	UB7FK	1
	3"	E07830036		5121077	UB7FL	1
	4"	E07840036		5119821	UB7FN	1
	5"	E07850036		5119820	UB7FP	1
	6"	E07860036		5121072	UB7FR	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END - 45° 48" RADIUS						
	1"	E07810048	-----	5136503	UB7HF	1
	1 1/4"	E07812548	-----	5136515	UB7HG	1
	1 1/2"	E07815048	-----	5136534	-----	1
	2"	E07820048	-----	5121093	UB7HJ	1
	2 1/2"	E07825048	-----	5136563	-----	1
	3"	E07830048	-----	5121078	UB7HL	1
	4"	E07840048	-----	5121091	UB7HN	1
	5"	E07850048	-----	5121948	UB7HP	1
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 90° 24" RADIUS						
	1"	E08210024	-----	-----	-----	1
	1 1/4"	E08212524	-----	-----	-----	1
	1 1/2"	E08215024	-----	-----	-----	1
	2"	E08220024	-----	-----	UB9DJB	1
	2 1/2"	E08225024	-----	-----	UB9DKB	1
	3"	E08230024	-----	-----	UB9DLB	1
	4"	E08240024	-----	-----	-----	1
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 90° 36" RADIUS						
	1"	E08210036	-----	-----	-----	1
	1 1/4"	E08212536	-----	-----	-----	1
	1 1/2"	E08215036	-----	-----	-----	1
	2"	E08220036	-----	-----	-----	1
	2 1/2"	E08225036	-----	-----	UB9FKB	1
	3"	E08230036	-----	-----	UB9FLB	1
	4"	E08240036	-----	-----	UB9FNB	1
	5"	E08250036	-----	-----	-----	1
	6"	E08260036	-----	-----	-----	1
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 90° 48" RADIUS						
	1"	E08210048	-----	-----	-----	1
	1 1/4"	E08212548	-----	-----	-----	1
	1 1/2"	E08215048	-----	-----	-----	1
	2"	E08220048	-----	-----	-----	1
	2 1/2"	E08225048	-----	-----	-----	1
	3"	E08230048	-----	-----	-----	1
	4"	E08240048	-----	-----	UB9HNB	1
	5"	E08250048	-----	-----	-----	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 45° 24" RADIUS						
	1"	E08310024	-----	-----	-----	1
	1 1/4"	E08312524	-----	-----	-----	1
	1 1/2"	E08315024	-----	-----	-----	1
	2"	E08320024	-----	-----	-----	1
	2 1/2"	E08325024	-----	-----	-----	1
	3"	E08330024	-----	-----	-----	1
	4"	E08340024	-----	-----	-----	1
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 45° 36" RADIUS						
	1"	E08310036	-----	-----	-----	1
	1 1/4"	E08312536	-----	-----	-----	1
	1 1/2"	E08315036	-----	-----	-----	1
	2"	E08320036	-----	-----	-----	1
	2 1/2"	E08325036	-----	-----	-----	1
	3"	E08330036	-----	-----	-----	1
	4"	E08340036	-----	-----	-----	1
	5"	E08350036	-----	-----	-----	1
	6"	E08360036	-----	-----	-----	1
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 45° 48" RADIUS						
	1"	E08310048	-----	-----	-----	1
	1 1/4"	E08312548	-----	-----	-----	1
	1 1/2"	E08315048	-----	-----	-----	1
	2"	E08320048	-----	-----	-----	1
	2 1/2"	E08325048	-----	-----	-----	1
	3"	E08330048	-----	-----	-----	1
	4"	E08340048	-----	-----	-----	1
	5"	E08350048	-----	-----	-----	1

Rigid PVC Conduit Fittings

With Brass Fasteners

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE LB						
	1/2″	E533050	RSLB10S	-----	-----	25
	3/4″	E533075	RSLB20S	-----	-----	25
	1″	E533100	RSLB30S	-----	-----	15
	1 1/4″	E533125	RSLB40S	-----	-----	20
	1 1/2″	E533150	RSLB50S	-----	-----	10
	2″	E533200	RSLB60S	-----	-----	15
	2 1/2″	E533250	RSLB70S	-----	-----	5
	3″	E533300	RSLB80S	-----	-----	5
	3 1/2″	E533350	RSLB90S	-----	-----	5
	4″	E533400	RSLB100S	-----	-----	5
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE C						
	1/2″	E532050	RSC10S	-----	-----	30
	3/4″	E532075	RSC20S	-----	-----	20
	1″	E532100	RSC30S	-----	-----	15
	1 1/4″	E532125	RSC40S	-----	-----	15
	1 1/2″	E532150	RSC50S	-----	-----	10
	2″	E532200	RSC60S	-----	-----	15
	2 1/2″	E532250	RSC70S	-----	-----	4
	3″	E532300	RSC80S	-----	-----	4
	3 1/2″	E532350	RSC90S	-----	-----	4
	4″	E532400	RSC100S	-----	-----	4
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE LL						
	1/2″	E534050	RSLL10S	-----	-----	25
	3/4″	E534075	RSLL20S	-----	-----	20
	1″	E534100	RSLL30S	-----	-----	15
	1 1/4″	E534125	RSLL40S	-----	-----	10
	1 1/2″	E534150	RSLL50S	-----	-----	10
	2″	E534200	RSLL60S	-----	-----	10
	2 1/2″	E534250	RSLL70S	-----	-----	4
	3″	E534300	RSLL80S	-----	-----	4
	3 1/2″	E534350	RSLL90S	-----	-----	5
	4″	E534400	RSLL100S	-----	-----	5





Rigid PVC Conduit Fittings

With Brass Fasteners

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE LR						
	1/2″	E535050	RSLR10S	-----	-----	25
	3/4″	E535075	RSLR20S	-----	-----	20
	1″	E535100	RSLR30S	-----	-----	15
	1 1/4″	E535125	RSLR40S	-----	-----	10
	1 1/2″	E535150	RSLR50S	-----	-----	10
	2″	E535200	RSLR60S	-----	-----	10
	2 1/2″	E535250	RSLR70S	-----	-----	4
	3″	E535300	RSLR80S	-----	-----	4
	3 1/2″	E535350	RSLR90S	-----	-----	5
	4″	E535400	RSLR100S	-----	-----	5
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE E						
	1/2″	E536050	RSE10S	-----	-----	30
	3/4″	E536075	RSE20S	-----	-----	20
	1″	E536100	RSE30S	-----	-----	15
	1 1/4″	E536125	RSE40S	-----	-----	20
	1 1/2″	E536150	RSE50S	-----	-----	10
	2″	E536200	RSE60S	-----	-----	15
	2 1/2″	E536250	RSE70S	-----	-----	4
	3″	E536300	RSE80S	-----	-----	4
	3 1/2″	E536350	RSE90S	-----	-----	4
	4″	E536400	RSE100S	-----	-----	4
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE T						
	1/2″	E537050	RST10S	-----	-----	30
	3/4″	E537075	RST20S	-----	-----	20
	1″	E537100	RST30S	-----	-----	25
	1 1/4″	E537125	RST40S	-----	-----	15
	1 1/2″	E537150	RST50S	-----	-----	10
	2″	E537200	RST60S	-----	-----	10
	2 1/2″	E537250	RST70S	-----	-----	4
	3″	E537300	RST80S	-----	-----	4
	3 1/2″	E537350	RST90S	-----	-----	4
	4″	E537400	RST100S	-----	-----	4
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE TB						
	1/2″	E569050	RSTB10S	-----	-----	30
	3/4″	E569075	RSTB20S	-----	-----	20
	1″	E569100	RSTB30S	-----	-----	10
	1 1/4″	E569125	RSTB40S	-----	-----	10




Rigid PVC Conduit Fittings

With Brass Fasteners

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
BRASS FASTENER PRODUCTS - JUNCTION BOX WITH GASKET						
	4" X 4" X 2"	E551442	RJB442	------	------	15
	4" X 4" X 4"	E551444	RJB444	------	------	10
	4" X 4" X 6"	E551446	RJB446	------	------	8
	5" X 5" X 2"	E551552	RJB552	------	------	12
	6" X 6" X 4"	E551664	RJB664	------	------	15
	6" X 6" X 6"	E551666	RJB666	------	------	4
	8" X 8" X 4"	E551884	RJB884	------	------	4
	8" X 8" X 7"	E551887	RJB887	------	------	4
	12" X 12" X 4"	E55112124	RJB12124	------	------	2
	12" X 12" X 6"	E55112126	RJB12126	------	------	4
	12" X 12" X 8"	E55112128	RJB12128	------	------	3
BRASS FASTENER PRODUCTS - SINGLE GANG BOX - F SERIES						
	A. 1/2" FS	E542001	RFS10	------	------	10
	A. 3/4" FS	E542002	RFS15	------	------	10
	B. 1/2" FSS	E542003	RFSS10	------	------	10
	B. 3/4" FSS	E542004	RFSS15	------	------	10
	C. 1/2" FSC	E542005	RFSC10	------	------	10
	C. 3/4" FSC	E542006	RFSC15	------	------	10
	D. 1/2" FSCC	E542007	RFSCC10	------	------	10
	D. 3/4" FSCC	E542008	RFSCC15	------	------	10
BRASS FASTENER PRODUCTS - SINGLE GANG DEEP BOX - FD SERIES						
	A. 1/2" FDS	E543001	RFDS10	------	------	10
	A. 3/4" FDS	E543002	RFDS15	------	------	10
	A. 1" FDS	E543003	RFDS20	------	------	10
	B. 1/2" FDC	E543004	RFDC10	------	------	10
	B. 3/4" FDC	E543005	RFDC15	------	------	10
	B. 1" FDC	E543006	RFDC20	------	------	10
	C. BLANK	E543007	RFD	------	------	10
BRASS FASTENER PRODUCTS - DOUBLE GANG BOX - F SERIES						
	A. 1/2" FS	E541001	------	------	------	10
	A. 3/4" FS	E541002	------	------	------	10
	A. 1" FS	E541003	------	------	------	10
	B. 1/2" FSS	E541004	------	------	------	10
	B. 3/4" FSS	E541005	------	------	------	10
	B. 1" FSS	E541006	------	------	------	10
	C. 1/2" FSC	E541007	------	------	------	10
	C. 3/4" FSC	E541008	------	------	------	10
	C. 1" FSC	E541009	------	------	------	10
	D. 1/2" FSCC	E541011	------	------	------	10
	D. 3/4" FSCC	E541012	------	------	------	10
	D. 1" FSCC	E541013	------	------	------	10
	E. BLANK	E541010	------	------	------	10

Rigid PVC Conduit Fittings

With Brass Fasteners

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
BRASS FASTENER PRODUCTS - SINGLE GANG COVER PLATE - F SERIES						
	A. TOGGLE	E546002	RTSC15/10	------	------	100
	B. DUPLEX	E546001	RDRC15/10	------	------	100
	C. 15 AMP	E546004	R20RC15/10	------	------	100
	D. 20 AMP	E546003	R20 3RC15/10	------	------	100
	E. 30 AMP	E546005	R30 3RC15/10	------	------	100
	F. BLANK W/ GASKET	E546006	RBRC15/10	------	------	100
BRASS FASTENER PRODUCTS - DOUBLE GANG WEATHERPROOF COVER PLATE						
	B. GFI & TOGGLE	E549005	------	------	------	10
	C. DUPLEX & TOGGLE	E549006	------	------	------	10
	D. DOUBLE DU PLEX	E549007	------	------	------	10
	E. TOGGLE	E549008	------	------	------	10
	F. BLANK	E549009	------	------	------	25
BRASS FASTENER PRODUCTS - SINGLE GANG WEATHERPROOF COVER PLATE						
	A. TOGGLE S/ COVER	E547002	RVSC15/10	------	------	20
	B. PLUNGER S/ COVER	E547008	RVPT15/10	------	------	20
	C. TOGGLE	E547009	RWTG15/10	------	------	20
	D. DUPLEX	E547001	RWDR15/10	------	------	20
	D. DUPLEX WHITE	E547010	RWDR15/10W	------	------	20
	E. GROUND FAULT	E547007	RWGF15/10	------	------	20
	E. GROUND FAULT WHITE	E547011	RWGF15/10W	------	------	20
	F. 15 AMP	E547003	RWTL15	------	------	20
	F. 20 AMP	E547004	RWTL20	------	------	20
	F. 30 AMP	E547005	RWTL30	------	------	20
	F. 50 AMP	E547006	RWTL50	------	------	20

ENT - Tubing

Electrical Non-Metallic Tubing

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
COILS - BLUE ENT TUBING						
						FEET
	1/2	EC005200BL	-----	A51AEB1	12005 200	200
	3/4	EC007100BL	-----	A51AGA1	12007 100	100
	1	EC010100BL	-----	A51BAA1	12008 100	100
	1 1/4	EC012350BL	-----	-----	-----	350
	1 1/2	EC015300BL	-----	-----	-----	300
	2	EC020250BL	-----	-----	-----	250
COILS - GREY ENT TUBING						
						FEET
	1/2	EC005370	EC005370	-----	-----	370
	3/4	EC007240	EC007240	-----	-----	240
	1	EC010160	EC010160	-----	-----	160
	1 1/4	EC012500	EC012500	-----	-----	500
	1 1/2	EC015300	EC015300	-----	-----	300
	2	EC020225	EC020225	-----	-----	225
REELS - BLUE ENT TUBING						
						FEET
	1/2	ER 0051500BL	-----	A51AEQ1	12005AK 001	1,500
	3/4	ER 0071000BL	-----	A51AGJ1	12007AA 001	1,000
	1	ER 0101000BL	-----	A51BAJ1	-----	1,000
	1 1/4	ER 0121000BL	-----	-----	-----	1,000
	1 1/2	ER015750BL	-----	-----	12010 750	750
	2	ER020500BL	-----	-----	12011 500	500

ENT - Tubing

Electrical Non-Metallic Tubing

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
REELS - GREY ENT TUBING						
						FEET
	1/2	ER0052000	ER0052000	-----	-----	2,000
	3/4	ER0071500	ER0071500	-----	-----	1,500
	1	ER0101000	ER0101000	-----	-----	1,000
	1 1/4	ER0121000	ER0121000	-----	-----	1,000
	1 1/2	ER015750	ER015750	-----	-----	750
	2	ER020500	ER020500	-----	-----	500
STRAIGHT LENGTH - BLUE ENT TUBING						
						EACH
	1/2	ES00510BL	-----	-----	-----	100
	3/4	ES00710BL	-----	-----	-----	100
	1	ES01010BL	-----	-----	-----	100
STRAIGHT LENGTH - GREY ENT TUBING						
					SUPPLIED IN 10 FOOT LENGTHS	
						EACH
	1/2	ES00510	ES00510	-----	-----	100
	3/4	ES00710	ES00710	-----	-----	100
	1	ES01010	ES01010	-----	-----	100

ENT - Fittings

Electrical Non-Metallic Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
ENT COUPLING						
	1/2	RKC10	RKC10	5163380	A240D	150
	3/4	RKC15	RKC15	5163381	A240E	100
	1	RKC20	RKC20	5163382	A240F	50
	1 1/4	RKC25	RKC25	-----	-----	50
	1 1/2	RKC30	RKC30	-----	-----	40
	2	RKC35	RKC35	-----	-----	25
ENT THREADED TERMINAL ADAPTER WITH LOCK NUT						
	1/2	RKTA10	RKTA10	5163415	-----	150
	3/4	RKTA15	RKTA15	5163416	-----	100
	1	RKTA20	RKTA20	5163417	-----	50
	1 1/4	RKTA25	RKTA25	-----	-----	50
	1 1/2	RKTA30	RKTA30	-----	-----	50
	2	RKTA35	RKTA35	-----	-----	25
ENT ADAPTER WITH SET SCREW						
	1/2	RKTC10	RKTC10	-----	A245D	125
	3/4	RKTC15	RKTC15	-----	A245E	100
	1	RKTC20	RKTC20	-----	A245F	50
	1 1/4	RKTC25	RKTC25	-----	-----	50
	1 1/2	RKTC30	RKTC30	-----	-----	40
	2	RKTC35	RKTC35	-----	-----	15
ENT QUICK SNAP TERMINAL ADAPTER						
	1/2	RKTS10	RKTS10	5163405	A253D	150
	3/4	RKTS15	RKTS15	5163406	A253E	100
	1	RKTS20	RKTS20	5163407	A253F	50
ENT CLIP RING						
	1/2	RKR10	RKR10	-----	-----	200†
	3/4	RKR15	RKR15	-----	-----	200†
	1	RKR20	RKR20	-----	-----	200†
	1 1/4	RKR25	RKR25	-----	-----	100*
	1 1/2	RKR30	RKR30	-----	-----	100*
	2	RKR35	RKR35	-----	-----	50^

Rings are net priced per bag as follows: † = 20/bag * = 10/bag ^ = 5/bag

ENT - Fittings

Electrical Non-Metallic Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
HEAVY DUTY LOCK NUT						
	1/2	RLN10	RLN10	-----	-----	200
	3/4	RLN15	RLN15	-----	-----	200
	1	RLN20	RLN20	-----	-----	200
	1 1/4	RLN25	RLN25	-----	-----	200
	1 1/2	RLN30	RLN30	-----	-----	200
	2	RLN35	RLN35	-----	-----	200
STRAIGHT STUBBY (POLYETHYLENE)						
	1/2	RECM10	RECM10	EN050SBY	A210D	150
	3/4	RECM15	RECM15	EN075SBY	A210E	150
	1	RECM20	RECM20	EN100SBY	A210F	200
	1 1/4	RECM25	RECM25	-----	-----	200
45 DEGREE ANGLED FORM STUBBY (POLYETHYLENE)						
	1/2	RKASTB10	RKASTB10	-----	A220D	50
	3/4	RKASTB15	RKASTB15	-----	A220E	50
	1	RKASTB20	RKASTB20	-----	A220F	50
	1 1/4	RKASTB25	RKASTB25	-----	A220G	50
	1 1/2	RKASTB30	RKASTB30	-----	A220H	50
	2	RKASTB35	RKASTB35	-----	A220J	50
TAPERED PLUG (POLYETHYLENE)						
	1/2	RTP10	RTP10	-----	-----	250
	3/4	RTP15	RTP15	-----	-----	100
	1	RTP20	RTP20	-----	-----	100
SLAB BOX EXTENSION						
	1" EXTENSION	RSMBXTENSION	RSMBXTENSION	-----	-----	20

ENT - Fittings

Electrical Non-Metallic Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
ENT SLAB BOX WITH HUB EXTENSIONS AND GREY LID						
	1/2 (8)	RSMB H 10	RSMB H 10	ENS0500C	------	25
	1/2 (4) 3/4 (4)	RSMB H 10 15	RSMB H 10 15	ENS0507C	------	25
	1/2 (4) 3/4 (2)	RSMB H 10 15 20	RSMB H 10 15 20	------	------	25
	1 (2)			------	------	
	1/2 (4) 1 (4)	RSMB H 10 20	RSMB H 10 20	------	------	25
	3/4 (8)	RSMB H 15	RSMB H 15	------	------	25
	3/4 (4) 1 (4)	RSMB H 15 20	RSMB H 15 20	------	------	25
ENT SLAB BOX WITH KNOCKOUTS AND GREY LID						
	1/2 (8)	RSMB 10	RSMB 10	ENS0500K	------	25
	1/2 (4) 3/4 (4)	RSMB 10 15	RSMB 10 15	ENS0507K	------	25
	1/2 (4) 3/4 (2)	RSMB 10 15 20	RSMB 10 15 20	------	------	25
	1 (2)			------	------	
	1/2 (2) 3/4 (4)	RSMB 15 20 10	RSMB 15 20 10	------	------	25
	1 (2)			------	------	
	3/4 (8)	RSMB 15	RSMB 15	------	------	25
ENT SHALLOW SLAB BOX						
	1/2 (8)	RSMBS H 10	RSMBS H 10	------	------	25
	1/2 (4) 3/4 (4)	RSMBS H 10 15	RSMBS H 10 15	------	------	25
	1/2 (4) 3/4 (2)	RSMBS H 10 15 20	RSMBS H 10 15 20	------	------	25
	1 (2)			------	------	
	1/2 (4) 1 (4)	RSMBS H 10 20	RSMBS H 10 20	------	------	25
	3/4 (8)	RSMBS H 15	RSMBS H 15	------	------	25
	3/4 (4) 1 (4)	RSMBS H 15 20	RSMBS H 15 20	------	------	25
ENT ISOLATOR MODULE SLAB BOX						
	1/2 (8)	RSMB 10 IMB	RSMB 10 IMB	------	------	20
	1/2 (4) 3/4 (4)	RSMB 10 15 IMB	RSMB 10 15 IMB	------	------	20
	1/2 (4) 3/4 (2)	RSMB 10 15 20 IMB	RSMB 10 15 20 IMB	------	------	20
	1 (2)			------	------	
	1/2 (4) 1 (4)	RSMB 10 20 IMB	RSMB 10 20 IMB	------	------	20
	3/4 (8)	RSMB 15 IMB	RSMB 15 IMB	------	------	20
	3/4 (4) 1 (4)	RSMB 15 20 IMB	RSMB 15 20 IMB	------	------	20

ENT - Fittings

Electrical Non-Metallic Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
ENT SHALLOW SINGLE GANG CONCRETE WALL BOX						
	1/2	RSVSB H 10	RSVSB H 10	------	------	70
	3/4	RSVSB H 15	RSVSB H 15	------	------	70
	1	RSVSB H 20	RSVSB H 20	------	------	70
ENT DEEP SINGLE GANG CONCRETE WALL BOX						
	1/2 (8)	RSVDB H 10	RSVDB H 10	------	------	25
	1/2 (4) 3/4 (4)	RSVDB H 10 15	RSVDB H 10 15	------	------	25
	1/2 (4) 3/4 (2)	RSVDB H 10 15 20	RSVDB H 10 15 20	------	------	25
	1 (2)					
	1/2 (4) 1 (4)	RSVDB H 10 20	RSVDB H 10 20	------	------	25
	3/4 (8)	RSVDB H 15	RSVDB H 15	------	------	25

PVC Enclosures

Electrical Non-Metallic PVC Enclosures

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Weight Each Lbs.
ELECTRICAL TROUGH BOX (SCREW COVER)						
	4 X 4 X 12	ETR040412	ETR040412	-----	-----	3
	4 X 4 X 18	ETR040418	ETR040418	-----	-----	4
	4 X 4 X 24	ETR040424	ETR040424	-----	-----	5
	4 X 4 X 36	ETR040436	ETR040436	-----	-----	8
	4 X 4 X 48	ETR040448	ETR040448	-----	-----	10
	4 X 4 X 60	ETR040460	ETR040460	-----	-----	12
	6 X 6 X 12	ETR060612	ETR060612	-----	-----	5
	6 X 6 X 18	ETR060618	ETR060618	-----	-----	7
	6 X 6 X 24	ETR060624	ETR060624	-----	-----	8
	6 X 6 X 36	ETR060636	ETR060636	-----	-----	11
	6 X 6 X 48	ETR060648	ETR060648	-----	-----	14
	6 X 6 X 60	ETR060660	ETR060660	-----	-----	17
	8 X 8 X 12	ETR080812	ETR080812	-----	-----	7
	8 X 8 X 18	ETR080818	ETR080818	-----	-----	9
	8 X 8 X 24	ETR080824	ETR080824	-----	-----	11
	8 X 8 X 36	ETR080836	ETR080836	-----	-----	15
	8 X 8 X 48	ETR080848	ETR080848	-----	-----	19
	8 X 8 X 60	ETR080860	ETR080860	-----	-----	23
	12 X 12 X 24	ETR121224	ETR121224	-----	-----	27
	12 X 12 X 36	ETR121236	ETR121236	-----	-----	33
	12 X 12 X 48	ETR121248	ETR121248	-----	-----	39
	12 X 12 X 60	ETR121260	ETR121260	-----	-----	45
ELECTRICAL TROUGH BOX (LATCH COVER)						
	4 X 4 X 12	ELC040412	ELC040412	-----	-----	3
	4 X 4 X 18	ELC040418	ELC040418	-----	-----	4
	4 X 4 X 24	ELC040424	ELC040424	-----	-----	5
	4 X 4 X 36	ELC040436	ELC040436	-----	-----	8
	4 X 4 X 48	ELC040448	ELC040448	-----	-----	10
	4 X 4 X 60	ELC040460	ELC040460	-----	-----	12
	6 X 6 X 12	ELC060612	ELC060612	-----	-----	5
	6 X 6 X 18	ELC060618	ELC060618	-----	-----	7
	6 X 6 X 24	ELC060624	ELC060624	-----	-----	8
	6 X 6 X 36	ELC060636	ELC060636	-----	-----	11
	6 X 6 X 48	ELC060648	ELC060648	-----	-----	14
	6 X 6 X 60	ELC060660	ELC060660	-----	-----	17
	8 X 8 X 12	ELC080812	ELC080812	-----	-----	7
	8 X 8 X 18	ELC080818	ELC080818	-----	-----	9
	8 X 8 X 24	ELC080824	ELC080824	-----	-----	11
	8 X 8 X 36	ELC080836	ELC080836	-----	-----	15
	8 X 8 X 48	ELC080848	ELC080848	-----	-----	19
	8 X 8 X 60	ELC080860	ELC080860	-----	-----	23
	12 X 12 X 24	ELC121224	ELC121224	-----	-----	27
	12 X 12 X 36	ELC121236	ELC121236	-----	-----	33
	12 X 12 X 48	ELC121248	ELC121248	-----	-----	39

PVC Enclosures

Electrical Non-Metallic PVC Enclosures






Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Weight Each Lbs.
LARGE FABRICATED JUNCTION BOXES						
	12 X 10 X 6	E053121006	E053121006	-----	-----	8
	12 X 10 X 8	E053121008	E053121008	-----	-----	9
	12 X 12 X 4	E053121204	E053121204	-----	-----	7
	12 X 12 X 6	E053121206	E053121206	-----	-----	9
	12 X 12 X 8	E053121208	E053121208	-----	-----	10
	12 X 12 X 12	E053121212	E053121212	-----	-----	14
	14 X 12 X 4	E053141204	E053141204	-----	-----	9
	14 X 12 X 6	E053141206	E053141206	-----	-----	10
	14 X 12 X 8	E053141208	E053141208	-----	-----	12
	14 X 14 X 4	E053141404	E053141404	-----	-----	10
	14 X 14 X 6	E053141406	E053141406	-----	-----	12
	14 X 14 X 8	E053141408	E053141408	-----	-----	14
	14 X 14 X 10	E053141410	E053141410	-----	-----	16
	14 X 14 X 14	E053141414	E053141414	-----	-----	19
	16 X 16 X 10	E053161610	E053161610	-----	-----	21
	16 X 16 X 12	E053161612	E053161612	-----	-----	23
	16 X 16 X 16	E053161616	E053161616	-----	-----	22
	18 X 12 X 4	E053181204	E053181204	-----	-----	10
	18 X 12 X 6	E053181206	E053181206	-----	-----	12
	18 X 12 X 8	E053181208	E053181208	-----	-----	13
	18 X 16 X 4	E053181604	E053181604	-----	-----	12
	18 X 16 X 6	E053181606	E053181606	-----	-----	14
	18 X 16 X 8	E053181608	E053181608	-----	-----	16
	18 X 18 X 6	E053181806	E053181806	-----	-----	16
	18 X 18 X 8	E053181808	E053181808	-----	-----	18
	18 X 18 X 10	E053181810	E053181810	-----	-----	20
	18 X 18 X 12	E053181812	E053181812	-----	-----	22
	18 X 18 X 18	E053181818	E053181818	-----	-----	26
	20 X 18 X 8	E053201808	E053201808	-----	-----	20
	20 X 20 X 8	E053202008	E053202008	-----	-----	22
	24 X 18 X 6	E053241806	E053241806	-----	-----	20
	24 X 18 X 8	E053241808	E053241808	-----	-----	22
	24 X 18 X 12	E053241812	E053241812	-----	-----	25
	24 X 20 X 8	E053242008	E053242008	-----	-----	25
	24 X 24 X 6	E053242406	E053242406	-----	-----	25
	24 X 24 X 8	E053242408	E053242408	-----	-----	28
	24 X 24 X 10	E053242410	E053242410	-----	-----	33
	24 X 24 X 12	E053242412	E053242412	-----	-----	35
	24 X 24 X 24	E053242424	E053242424	-----	-----	40
	30 X 24 X 8	E053302408	E053302408	-----	-----	34
	30 X 30 X 10	E053303010	E053303010	-----	-----	39
	30 X 30 X 20	E053303020	E053303020	-----	-----	48
	30 X 30 X 30	E053303030	E053303030	-----	-----	60
	36 X 24 X 8	E053362408	E053362408	-----	-----	39
	36 X 36 X 12	E053363612	E053363612	-----	-----	61
	36 X 36 X 18	E053363618	E053363618	-----	-----	65
	36 X 36 X 20	E053363620	E053363620	-----	-----	67
	36 X 36 X 36	E053363636	E053363636	-----	-----	70
	40 X 40 X 12	E053404012	E053404012	-----	-----	78
	40 X 40 X 20	E053404020	E053404020	-----	-----	88

PVC Enclosures

Electrical Non-Metallic PVC Enclosures


Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Weight Each Lbs.
ELECTRICAL ENCLOSURES						
	20 X 12 X 8	EBH201208	EBH201208	-----	-----	14
	20 X 16 X 6	EBH201606	EBH201606	-----	-----	16
	20 X 16 X 8	EBH201608	EBH201608	-----	-----	17
	20 X 16 X 10	EBH201610	EBH201610	-----	-----	20
	20 X 16 X 12	EBH201612	EBH201612	-----	-----	22
	20 X 20 X 6	EBH202006	EBH202006	-----	-----	18
	20 X 20 X 8	EBH202008	EBH202008	-----	-----	21
	20 X 20 X 10	EBH2022010	EBH2022010	-----	-----	23
	20 X 24 X 6	EBH2022406	EBH2022406	-----	-----	21
	20 X 24 X 8	EBH202408	EBH202408	-----	-----	24
	24 X 12 X 6	EBH241206	EBH241206	-----	-----	15
	24 X 12 X 8	EBH241208	EBH241208	-----	-----	17
	24 X 12 X 10	EBH241210	EBH241210	-----	-----	19
	24 X 16 X 6	EBH241606	EBH241606	-----	-----	18
	24 X 16 X 8	EBH241608	EBH241608	-----	-----	20
	24 X 20 X 8	EBH242008	EBH242008	-----	-----	24
	24 X 20 X 10	EBH242010	EBH242010	-----	-----	26
	24 X 20 X 12	EBH242012	EBH242012	-----	-----	29
	24 X 20 X 16	EBH242016	EBH242016	-----	-----	34
	24 X 24 X 6	EBH242406	EBH242406	-----	-----	25
	24 X 24 X 8	EBH242408	EBH242408	-----	-----	28
	24 X 24 X 10	EBH242410	EBH242410	-----	-----	30
	24 X 24 X 12	EBH242412	EBH242412	-----	-----	33
	24 X 24 X 16	EBH242416	EBH242416	-----	-----	38
	24 X 30 X 8	EBH243008	EBH243008	-----	-----	33
	30 X 16 X 6	EBH301606	EBH301606	-----	-----	22
	30 X 20 X 6	EBH302006	EBH302006	-----	-----	26
	30 X 20 X 8	EBH302008	EBH302008	-----	-----	29
	30 X 20 X 10	EBH302010	EBH302010	-----	-----	32
	30 X 24 X 6	EBH302406	EBH302406	-----	-----	30
	30 X 24 X 8	EBH302408	EBH302408	-----	-----	33
	30 X 24 X 10	EBH302410	EBH302410	-----	-----	36
	30 X 24 X 12	EBH302412	EBH302412	-----	-----	39
	30 X 24 X 16	EBH302416	EBH302416	-----	-----	45
	30 X 24 X 20	EBH302420	EBH302420	-----	-----	51
	30 X 24 X 24	EBH302424	EBH302424	-----	-----	57
	30 X 30 X 8	EBH303008	EBH303008	-----	-----	39
	30 X 30 X 12	EBH303012	EBH303012	-----	-----	46
	30 X 36 X 8	EBH303608	EBH303608	-----	-----	46
	36 X 24 X 6	EBH362406	EBH362406	-----	-----	35
	36 X 24 X 8	EBH362408	EBH362408	-----	-----	29
	36 X 24 X 10	EBH362410	EBH362410	-----	-----	42



Our various pipe and fittings solutions have been manufactured to meet the needs of our customers and their applications. Contact the below Sales Center for more information:

- Plumbing Fittings Solutions
- Electrical Pipe & Fittings Solutions
- Municipal Pipe & Fittings Solutions





Sales & Distribution Center:

Royal Building Products
56400 Mound Road
Shelby Twp., MI 48316
T 1.800.232.5690
F 586.781.0888

royalbuildingproducts.com/plastic-trends

Printed 11.2012

ROYAL
Building Products

Pipe & Fittings Solutions | Municipal Plumbing Electrical

Electrical Non-Metallic PVC Products

PVC Fittings
ENT Pipe and Fittings
Enclosures

Category E Product BRV1
October, 2012

E Series







ROYAL Electrical Solutions

Contents

Rigid PVC Conduit Fittings

Pages 4 - 25

Shown in Alphabetical Order

Access Fittings 6-8
- Type C 6
- Type E 7
- Type LB 6
- Type LL 7
- Type LR 7
- Type T 8
- Type TB 8

Bell End (Hub X Spigot) - Molded 9
Coupling 4
5° Coupling 4
Double Gang Box - F Series 12
Double Gang Weatherproof Cover Plate 11
Duct - Base Vertical Lock Spacer 15
Duct - Intermediate Vertical Lock Spacer 14
Duplex Floor Box Cover 13
Duplex Floor Box 13
ECOVOC Low VOC / Clear Cement 15

Elbows 16-25
Schedule 40
- Radius Elbow Belled - 45° 24" Radius 22
- Special Radius Elbow Belled - 45° 36" Radius 22
- Special Radius Elbow Belled - 45° 48" Radius 22
- Special Radius Elbow Belled - 90° 24" Radius 21
- Special Radius Elbow Belled - 90° 36" Radius 21
- Special Radius Elbow Belled - 90° 48" Radius 22
- Special Radius Elbow Plain End - 45° 24" Radius 20
- Special Radius Elbow Plain End - 45° 36" Radius 21
- Special Radius Elbow Plain End - 45° 48" Radius 21
- Special Radius Elbow Plain End - 90° 24" Radius 19
- Special Radius Elbow Plain End - 90° 36" Radius 20
- Special Radius Elbow Plain End - 90° 48" Radius 20
- Standard Elbows - 11 1/4° Elbow - Plain End 17
- Standard Elbows - 22 1/2° Elbow - Plain End 17
- Standard Elbows - 30° Elbow - Bell End 18
- Standard Elbows - 30° Elbow - Plain End 17
- Standard Elbows - 45° Elbow - Bell End 18
- Standard Elbows - 45° Elbow - Plain End 16
- Standard Elbows - 90° Elbow - Bell End 18
- Standard Elbows - 90° Elbow - Plain End 16

Schedule 80
- Special Radius Elbow Belled - 45° 24" Radius 25
- Special Radius Elbow Belled - 45° 36" Radius 25
- Special Radius Elbow Belled - 45° 48" Radius 25
- Special Radius Elbow Belled - 90° 24" Radius 24
- Special Radius Elbow Belled - 90° 36" Radius 24
- Special Radius Elbow Belled - 90° 48" Radius 24
- Special Radius Elbow Plain End 23
- Special Radius Elbow Plain End - 45° 48" Radius 24
- Special Radius Elbow Plain End - 90° 24" Radius 22
- Special Radius Elbow Plain End - 90° 36" Radius 23
- Special Radius Elbow Plain End - 90° 48" Radius 23
- Standard Elbows - 45° Elbow - Plain End 19
- Standard Elbows - 90° Elbow - Plain End 19

Expansions Joint 5
Junction Box Adapters 13
Junction Box with Gasket 13
KO Plug 12
Meter Offset 5
Meter Riser Kit 14
Octagonal Box 12
Octagonal Box Extension Ring 12
Pipe Strap PVC - 2 Hole 5
Pull Elbow 9
Reducer Bushing 10
Service Entrance Fitting 6
Single Gang Box - F Series 11
Single Gang Cover Plate - F Series 10
Single Gang Deep Box - FD Series 11
Single Gang Weatherproof Cover Plate 11
Slip Meter Riser 14
Solvent Weld End Cap 9
Strain Relief Connector 8
Threaded Strain Relief Connector 8
Terminal Adapter 4
- Female 5
- Male 4

Threaded Reducer Bushing 9
Universal Plug w/Pulling Eye 15
Vinyl Siding Electrical Mount 16

Contents

Rigid PVC Conduit Fittings with Brass Fasteners

Pages 26 - 29

Shown in Alphabetical Order

Access Fitting
- Type C 26
- Type E 27
- Type LL 26
- Type LR 27
- Type T 27
- Type TB 27
- Type LB 26

Double Gang Box - F Serie 28
Double Gang Weatherproof Cover Plate 29
Junction Box with Gasket 28
Single Gang Box - F Series 28
Single Gang Cover Plate - F Series 29
Single Gang Deep Box - FD Series 28
Single Gang Weatherproof Cover Plate 29

ENT - Tubing

Pages 30 - 31

Shown in Alphabetical Order

Coils
- Blue ENT Tubing 30
- Grey ENT Tubing 30

Reels
- Blue ENT Tubing 30
- Grey ENT Tubing 31

Straight Length
- Blue ENT Tubing 31
- Grey ENT Tubing 31

ENT - Fittings

Pages 32 - 35

Shown in Alphabetical Order

45 Degree Angled Form Stubby (Polyethylene) 33
Adapter with set screw 32
Clip Ring 32
Coupling 32
Deep Single Gang Concrete Wall Box 35
Isolator Module Slab Box 34
Quick-Snap Terminal Adapter 32
Shallow Single Gang Concrete Wall Box 35
Shallow Slab Box 34
Slab Box Extension Ring 33
Slab Box with Hub Extensions and Grey Lid 34
Slab Box with Knockouts and Grey Lid 34
Threaded Terminal Adapter with Lock Nut 32
Heavy Duty Lock Nut 33
Straight Stubby (Polyethylene) 33
Tapered Plug (Polyethylene) 33

PVC Enclosures

Pages 36 - 38

Shown in Alphabetical Order

Electrical Enclosures 38
Electrical Trough Box
- Latch Cover 36
- Screw Cover 36

Large Fabricated Junction Boxes 37

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
COUPLING						
	1/2″	E010050	REC10	6141623	E940D	200
	3/4″	E010075	REC15	6141624	E940E	125
	1″	E010100	REC20	6141625	E940F	70
	1 1/4″	E010125	REC25	6141626	E940G	40
	1 1/2″	E010150	REC30	6141627	E940H	30
	2″	E010200	REC35	6141628	E940J	40
	2 1/2″	E010250	REC40	6141629	E940K	20
	3″	E010300	REC45	6141630	E940L	40
	3 1/2″	E010350	REC50	6141631	E940M	30
	4″	E010400	REC55	6141632	E940N	20
	5″	E010500	REC60	6141633	E940P	10
	6″	E010600	REC65	6141634	E940R	8
	8″	E010800	-----	6141635D	-----	3
5° COUPLING						
	2″	E013200	R5EC35	6151457	E245J	20
	2 1/2″	E013250	R5EC40	-----	-----	12
	3″	E013300	R5EC45	6151458	-----	25
	3 1/2″	E013350	R5EC50	-----	-----	15
	4″	E013400	R5EC55	6151459	E245N	15
	5″	E013500	R5EC60	6151460	E245P	8
	6″	E013600	R5EC65	6151461	E245R	4
TERMINAL ADAPTER						
	1/2″	E011050	RTA10	5140103	E943D	200
	3/4″	E011075	RTA15	5140104	E943E	125
	1″	E011100	RTA20	5140105	E943F	70
	1 1/4″	E011125	RTA25	5140106	E943G	40
	1 1/2″	E011150	RTA30	5140107	E943H	30
	2″	E011200	RTA35	5140108	E943J	40
	2 1/2″	E011250	RTA40	5140109	E943K	20
	3″	E011300	RTA45	5140110	E943L	40
	3 1/2″	E011350	RTA50	5140111	E943M	30
	4″	E011400	RTA55	5140112	E943N	20
	5″	E011500	RTA60	5140113	E943P	10
	6″	E011600	RTA65	5140114	E943R	8




Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
FEMALE ADAPTER (NPT TAPERED THREAD)						
	1/2″	E012050	RFA10	5140043	E942D	200
	3/4″	E012075	RFA15	5140044	E942E	125
	1″	E012100	RFA20	5140045	E942F	70
	1 1/4″	E012125	RFA25	5140046	E942G	40
	1 1/2″	E012150	RFA30	5140047	E942H	30
	2″	E012200	RFA35	5140048	E942J	40
	2 1/2″	E012250	RFA40	5140049	E942K	20
	3″	E012300	RFA45	5140050	E942L	40
	3 1/2″	E012350	RFA50	5140051	E942M	30
	4″	E012400	RFA55	5140052	E942N	20
	5″	E012500	RFA60	5140053	E942P	10
	6″	E012600	RFA65	5140054	E942R	8
EXPANSIONS JOINT						
	1/2″	E016050	REJ10	5144031	E945D	25
	3/4″	E016075	REJ15	5144032	E945E	10
	1″	E016100	REJ20	5144033	E945F	10
	1 1/4″	E016125	REJ25	5144034	E945G	5
	1 1/2″	E016150	REJ30	5144035	E945H	5
	2″	E016200	REJ35	5144036	E945J	25
	2 1/2″	E016250	REJ40	5144037	E945K	12
	3″	E016300	REJ45	5144038	E945L	12
	3 1/2″	E016350	REJ50	5144039	E945M	6
	4″	E016400	REJ55	5144040	E945N	6
	5″	E016500	REJ60	5144041	E945P	1
	6″	E016600	REJ65	5144042	E945R	1
PIPE STRAP PVC - 2 HOLE						
	1/2″	E039050	RPS10	5133736	E977DC	300
	3/4″	E039075	RPS15	5133737	E977EC	200
	1″	E039100	RPS20	5133738	E977FC	200
	1 1/4″	E039125	RPS25	5133733	E977GC	200
	1 1/2″	E039150	RPS30	5133734	E977HC	200
	2″	E039200	RPS35	5133735	E977JC	200
METER OFFSET						
	1 1/4″	E024125	RMO25	5133183	E995G	15
	2″	E024200	RMO35	5133185	E995J	8


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SERVICE ENTRANCE FITTING						
	1/2″	E025050	REF10	5133590	-----	10
	3/4″	E025075	REF15	5133591	E998E CAR	10
	1″	E025100	REF20	5133741	E998F CAR	20
	1 1/4″	E025125	REF25	5133742	E998G CAR	20
	1 1/2″	E025150	REF30	5133695	E998H CAR	20
	2″	E025200	REF35	5133743	E998J	5
	2 1/2″	E025250	REF40	5133696	E998K UPC	5
	3″	E025300	REF45	5133697	E998L	5
	3 1/2″	E025350	REF50	5133698	-----	5
	4″	E025400	REF55	5133699	E998N	1
ACCESS FITTING - TYPE LB						
	1/2″	E033050	RSLB10S	5133663	E986D CAR	25
	3/4″	E033075	RSLB20S	5133664	E986E CAR	15
	1″	E033100	RSLB30S	5133665	E986F CAR	10
	1 1/4″	E033125	RSLB40S	5133666	E986G CAR	10
	1 1/2″	E033150	RSLB50S	5133667	E986H CAR	10
	2″	E033200	RSLB60S	5133668	E986J	5
	2 1/2″	E033250	RSLB70S	5133669	E986K	5
	3″	E033300	RSLB80S	5133670	E986L	5
	3 1/2″	E033350	RSLB90S	5133671	E986M	4
	4″	E033400	RSLB100S	5133672	E986N	4
ACCESS FITTING - TYPE C						
	1/2″	E032050	RSC10S	5133101	E987D CAR	25
	3/4″	E032075	RSC20S	5133102	E987E CAR	15
	1″	E032100	RSC30S	5133103	E987F CAR	10
	1 1/4″	E032125	RSC40S	5133104	E987G CAR	10
	1 1/2″	E032150	RSC50S	5133105	E987H CAR	10
	2″	E032200	RSC60S	5133106	E987J	5
	2 1/2″	E032250	RSC70S	5133108	-----	5
	3″	E032300	RSC80S	5133107	-----	5
	3 1/2″	E032350	RSC90S	5133110	-----	4
	4″	E032400	RSC100S	5133109	-----	4


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
ACCESS FITTING - TYPE LL						
	1/2″	E034050	RSLL10S	5133660	E984D CAR	25
	3/4″	E034075	RSLL20S	5133661	E984E CAR	15
	1″	E034100	RSLL30S	5133662	E984F CAR	10
	1 1/4″	E034125	RSLL40S	5133649	E984G CAR	10
	1 1/2″	E034150	RSLL50S	5133648	E984H CAR	10
	2″	E034200	RSLL60S	5133647	E984J	5
	2 1/2″	E034250	RSLL70S	5133644	------	5
	3″	E034300	RSLL80S	5133646	------	5
	3 1/2″	E034350	RSLL90S	5133640	------	4
	4″	E034400	RSLL100S	5133645	------	4
ACCESS FITTING - TYPE LR						
	1/2″	E035050	RSLR10S	5133650	E985D CAR	25
	3/4″	E035075	RSLR20S	5133651	E985E CAR	15
	1″	E035100	RSLR30S	5133652	E985F CAR	10
	1 1/4″	E035125	RSLR40S	5133653	E985G CAR	10
	1 1/2″	E035150	RSLR50S	5133654	E985H CAR	10
	2″	E035200	RSLR60S	5133655	E985J	5
	2 1/2″	E035250	RSLR70S	5133658	------	5
	3″	E035300	RSLR80S	5133656	------	5
	3 1/2″	E035350	RSLR90S	5133659	------	4
	4″	E035400	RSLR100S	5133657	------	4
ACCESS FITTING - TYPE E						
	1/2″	E036050	RSE10S	5133151	E998D CAR	25
	3/4″	E036075	RSE20S	5133152	E998E	15
	1″	E036100	RSE30S	5133153	E988F CAR	10
	1 1/4″	E036125	RSE40S	5133154	E988G CAR	10
	1 1/2″	E036150	RSE50S	5133155	E988H CAR	10
	2″	E036200	RSE60S	5133156	E988J	5
	2 1/2″	E036250	RSE70S	5133157	------	5
	3″	E036300	RSE80S	5133158	------	5
	3 1/2″	E036350	RSE90S	5133160	------	4
	4″	E036400	RSE100S	5133159	------	4


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
ACCESS FITTING - TYPE T						
	1/2″	E037050	RST10S	5133563	E983D CAR	25
	3/4″	E037075	RST20S	5133564	E983E CAR	15
	1″	E037100	RST30S	5133565	E983F	10
	1 1/4″	E037125	RST40S	5133566	E983G	10
	1 1/2″	E037150	RST50S	5133567	E983H CAR	10
	2″	E037200	RST60S	5133568	E983J	5
	2 1/2″	E037250	RST70S	5133569	-----	2
	3″	E037300	RST80S	5133570	-----	2
	3 1/2″	E037350	RST90S	5133572	-----	1
	4″	E037400	RST100S	5133571	-----	1
ACCESS FITTING - TYPE TB						
	1/2″	E069050	RSTB10S	-----	-----	30
	3/4″	E069075	RSTB20S	-----	-----	20
	1″	E069100	RSTB30S	-----	-----	10
	1 1/4″	E069125	RSTB40S	-----	-----	10
STRAIN RELIEF CONNECTOR						
	3/4″	E030075	RSRC15	-----	-----	25
THREADED STRAIN RELIEF CONNECTOR						
	1/2″	E031050	RTSRC10	5133430	-----	25
	3/4″	E031075	RTSRC15	5133431	-----	25





Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
PULL ELBOW						
	1/2″	E027050	RPE10	5240100	E990DR CAR	75
	3/4″	E027075	RPE15	5240101	E990ER CAR	50
SOLVENT WELD END CAP						
	1/2″	E026050	RCAP10	5140031	E958D	100
	3/4″	E026075	RCAP15	5140032	E958E	100
	1″	E026100	RCAP20	5140033	E958F	50
	1 1/4″	E026125	RCAP25	5140034	E958G	25
	1 1/2″	E026150	RCAP30	5140035	E958H	25
	2″	E026200	RCAP35	5140037	E958J	50
	2 1/2″	E026250	RCAP40	5140038	E958K	25
	3″	E026300	RCAP45	5140039	E958L	25
	4″	E026400	RCAP55	5140040	E958N	25
	5″	E026500	RCAP60	5140041	E958P	25
	6″	E026600	RCAP65	5140042	E958R	10
	8″	E026800	-----	-----	-----	6
THREADED REDUCER BUSHING						
	3/4″ X 1/2″	E0150705	R1825	-----	E9842D	200
	1″ X 1/2″	E0151005	R1826	-----	-----	200
	1″ X 3/4″	E0151007	R1827	-----	E9842E	200
BELL END (HUB X SPIGOT) - MOLDED						
	1/2″	E070050	REB10	5144003	-----	100
	3/4″	E070075	REB15	5144004	-----	100
	1″	E070100	REB20	5144005	E997F	50
	1 1/4″	E070125	REB25	5144006	E997G	50
	1 1/2″	E070150	REB30	5144007	E997H	50
	2″	E070200	REB35	5144008	E997J	40
	2 1/2″	E070250	REB40	5144009	E997K	30
	3″	E070300	REB45	5144010	E997L	50
	3 1/2″	E070350	REB50	5144011	E997M	50
	4″	E070400	REB55	5144012	E997N	50
	5″	E070500	REB60	5144013	E997P	25
	6″	E070600	REB65	5144014	E997R	15


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
REDUCER BUSHING						
	3/4" X 1/2"	E0140705	R1805	5142220	E950ED	100
	1" X 1/2"	E0141005	R1805 1	-----	E950FD CAR	3 BAGS X 100
	1" X 3/4"	E0141007	R1806	5142221	E950FE	100
	1 1/4" X 3/4"	E0141207	R1807 1	-----	E950GE CAR	2 BAGS X 25
	1 1/4" X 1"	E0141210	R1807	5142222	E950GF	50
	1 1/2" X 1"	E0141510	R1808 1	-----	E950HF CAR	50
	1 1/2" X 1 1/4"	E0141512	R1808	514223	E950HG CAR	50
	2" X 1"	E0142010	R1809 1	-----	-----	50
	2" X 1 1/4"	E0142012	R1809	-----	E950JG CAR	25
	2" X 1 1/2"	E0142015	R1810	5142224	E950JH CAR	25
	2 1/2" X 2"	E0142520	R1811	5142225	E950KJ CAR	25
	3" X 2"	E0143020	R1812 1	-----	E950LJ CAR	25
	3" X 2 1/2"	E0143025	R1812	5142226	E950LK	25
	4" X 2"	E0144020	R1813 1	-----	-----	15
	4" X 3"	E0144030	R1813	5142227	E950NL	20
	4" 3 1/2"	E0144035	R1814	5142229	-----	20
SINGLE GANG COVER PLATE - F SERIES						
	A. TOGGLE	E046002	RTSC15/10	-----	-----	100
	B. DUPLEX	E046001	RDRC15/10	-----	-----	100
	C. 15 AMP	E046004	R20RC15/10	-----	-----	100
	D. 20 AMP	E046003	R20 3RC15/10	-----	-----	100
	E. 30 AMP	E046005	R30 3RC15/10	-----	-----	100
	F. BLANK W/ GASKET	E046006	RBRC15/10	5133362	E980CN CAR	50



Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SINGLE GANG WEATHERPROOF COVER PLATE						
	A. TOGGLE S/ COVER	E047002	RVSC15/10	5133330	E98TSCN CAR	10
	B. PLUNGER S/ COVER	E047008	RVPT15/10	5133335	------	10
	C. TOGGLE	E047009	RWTG15/10	5133361	E98SSNCN CAR	10
	D. DUPLEX	E047001	RWDR15/10	5133352	E98GDRN CAR	10
	D. DUPLEX WHITE	E047010	RWDR15/10W	------	------	20
	E. GROUND FAULT	E047007	RWGF15/10	5133348	E98GFCN CAR	10
	E. GROUND FAULT WHITE	E047011	RWGF15/10W	------	------	20
	F. 15 AMP	E047003	RWTL15	5133350	E98SRCN CAR	10
	F. 20 AMP	E047004	RWTL20	5133320	E98G20N	10
	F. 30 AMP	E047005	RWTL30	5133321	E98G30N CAR	10
	F. 50 AMP	E047006	RWTL50	5133322	E98G5FN CAR	10
DOUBLE GANG WEATHERPROOF COVER PLATE						
	B. GFI & TOGGLE	E049005	------	5133345	E9G2GTN CAR	10
	C. DUPLEX & TOGGLE	E049006	------	5133337	E9GDSN CAR	10
	D. DOUBLE DU PLEX	E049007	------	5133347	E9GDDN CAR	10
	E. TOGGLE	E049008	------	5133331	E9G2SSN	10
	F. BLANK	E049009		5133410	E9802CN CAR	25
SINGLE GANG BOX - F SERIES						
	A. 1/2" FS	E042001	RFS10	5133363	E980DFN	10
	A. 3/4" FS	E042002	RFS15	5133364	E980EFN	10
	B. 1/2" FSS	E042003	RFSS10	5133540	E982DFN	10
	B. 3/4" FSS	E042004	RFSS15	5133542	E982EFN	10
	C. 1/2" FSC	E042005	RFSC10	5133463	E981DFN	10
	C. 3/4" FSC	E042006	RFSC15	5133464	E981EFN	10
	D. 1/2" FSCC	E042007	RFSCC10	5133544	E979DFN CAR	10
	D. 3/4" FSCC	E042008	RFSCC15	5133545	E979ERN CAR	10
SINGLE GANG DEEP BOX - FD SERIES						
	A. 1/2" FDS	E043001	RFDS10	5133300	E9801DN	10
	A. 3/4" FDS	E043002	RFDS15	5133301	E9801EN	10
	A. 1" FDS	E043003	RFDS20	5133302	E9801FN	10
	B. 1/2" FDC	E043004	RFDC10	5133310	E9811DN	10
	B. 3/4" FDC	E043005	RFDC15	5133311	E9811EN	10
	B. 1" FDC	E043006	RFDC20	5133312	E9811FN	10
	C. BLANK	E043007	RFD	5133420	E9801	10


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
DOUBLE GANG BOX - F SERIES						
	A. 1/2" FS	E041001	-----	5133380	E9802D	5
	A. 3/4" FS	E041002	-----	5133381	E9802E	5
	A. 1" FS	E041003	-----	5133382	E9802F	5
	B. 1/2" FSS	E041004	-----	5133390	-----	5
	B. 3/4" FSS	E041005	-----	5133391	-----	5
	B. 1" FSS	E041006	-----	5133392	-----	5
	C. 1/2" FSC	E041007	-----	5133370	E9812D	5
	C. 3/4" FSC	E041008	-----	5133371	E9812E	5
	C. 1" FSC	E041009	-----	5133372	E9812F	5
	D. 1/2" FSCC	E041011	-----	5133400	-----	5
	D. 3/4" FSCC	E041012	-----	5133401	-----	5
	D. 1" FSCC	E041013	-----	5133402	-----	5
	E. BLANK	E041010	-----	-----	E9802	5
OCTAGONAL BOX						
	4" X 1 1/2" (3/4" X1/2")	E028150	ROB15/10	-----	-----	20
	4" X 2" (1")	E028200	ROB20	-----	-----	12
KO PLUG						
	3/4"	E067075	RKO15	-----	-----	1
	1"	E067100	RTKO20	-----	-----	1
OCTAGONAL BOX EXTENSION RING						
	1"	E029100	RXR20	-----	-----	20
	2"	E029200	RXR35	-----	-----	20

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
DUPLEX FLOOR BOX/ LEVEL RING/ POUR COVER/ REDUCER BUSHING						
	4 - 3/4"	E068004	RFDB4	5133760	E971FB	9
	2 - 1", 2 - 3/4"	E068001	RFDB2	5133758	E971FB	9
DUPLEX FLOOR BOX COVER						
	POLY BRONZE COVER	E068003	RFDBC	5133678		10
JUNCTION BOX WITH GASKET						
	4" X 4" X 2"	E051442	RJB442	5133705	E989NNJ CAR	10
	4" X 4" X 4"	E051444	RJB444	5133709	E987N CAR	10
	4" X 4" X 6"	E051446	RJB446	5133707	E989NNR CAR	10
	5" X 5" X 2"	E051552	RJB552	5133706	E989PPJ CAR	10
	6" X 6" X 4"	E051664	RJB664	5133710	E987R CAR	10
	6" X 6" X 6"	E051666	RJB666	5133711	E989RRR UPC	5
	8" X 8" X 4"	E051884	RJB884	5133712	E989N CAR	5
	8" X 8" X 7"	E051887	RJB887	5133708	E989SSX UPC	4
	12" X 12" X 4"	E05112124	RJB12124	5133714	E989UUN	2
	12" X 12" X 6"	E05112126	RJB12126	5133713	E989R UPC	2
	12" X 12" X 8"	E05112128	RJB12128			3
JUNCTION BOX ADAPTERS						
	1/2"	E059050	RJBA10	5133715	E996D	100
	3/4"	E059075	RJBA15	5133716	E996E	100
	1"	E059100	RJBA20	5133717	E996F	100
	1 1/4"	E059125	RJBA25	5133718	E996G	50
	1 1/2"	E059150	RJBA30	5133719	E996H	50
	2"	E059200	RJBA35	5133720	E996J	25
	2 1/2"	E059250	RJBA40	5133721	E996K CAR	10
	3"	E059300	RJBA45	5133722	E996L	10
	3 1/2"	E059350	RJBA50	5133723		10
	4"	E059400	RJBA55	5133724	E996N	10

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
METER RISER KIT						
	1 1/4″	E092125	-----	-----	-----	1
	1 1/2″	E092150	-----	-----	-----	1
	2″	E092200	-----	-----	-----	1
	2 1/2″	E092250	-----	-----	-----	1
	3″	E092300	-----	-----	-----	1
SLIP METER RISER						
	2″	E093200	-----	5144028	E954JXX	20
	2 1/2″	E093250	-----	5144030	E954KXX	15
	3″	E093300	-----	5144043	E954LXX	10
	4″	E093400	-----	5144027	E954NXX	5
DUCT - INTERMEDIATE VERTICAL LOCK SPACER						
	2 X 1 1/2″	IS2015	IS2015	-----	-----	350
	2 X 2″	IS2020	IS2020	-----	-----	300
	2 X 3″	IS2030	IS2030	-----	-----	200
	3 X 1 1/2″	IS3015	IS3015	-----	-----	225
	3 X 2″	IS3020	IS3020	-----	-----	200
	3 X 3″	IS3030	IS3030	-----	-----	125
	4 X 1 ″	IS4010	IS4010	-----	-----	200
	4 X 1 1/2″	IS4015	IS4015	-----	-----	150
	4 X 2″	IS4020	IS4020	-----	-----	125
	4 X 3″	IS4030	IS4030	-----	-----	90
	5 X 1 1/2″	IS5015	IS5015	-----	-----	100
	5 X 2″	IS5020	IS5020	-----	-----	100
	5 X 3″	IS5030	IS5030	-----	-----	80
	6 X 1 1/2″	IS6015	IS6015	-----	-----	100
	6 X 2″	IS6020	IS6020	-----	-----	90
	6 X 3″	IS6030	IS6030	-----	-----	70
	8 X 1 1/2″	IS8015	-----	-----	-----	60
	8 X 2″	IS8020	-----	-----	-----	60

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
DUCT - BASE VERTICAL LOCK SPACER						
	2 X 1 1/2"	BS2015	BS2015	-----	-----	250
	2 X 2"	BS2020	BS2020	-----	-----	225
	2 X 3"	BS2030	BS2030	-----	-----	225
	3 X 1 1/2"	BS3015	BS3015	-----	-----	175
	3 X 2"	BS3020	BS3020	-----	-----	155
	3 X 3"	BS3030	BS3030	-----	-----	150
	4 X 1 "	BS4010	BS4010	-----	-----	175
	4 X 1 1/2"	BS4015	BS4015	-----	-----	140
	4 X 2"	BS4020	BS4020	-----	-----	140
	4 X 3"	BS4030	BS4030	-----	-----	120
	5 X 1 1/2"	BS5015	BS5015	-----	-----	120
	5 X 2"	BS5020	BS5020	-----	-----	120
	5 X 3"	BS5030	BS5030	-----	-----	100
	6 X 1 1/2"	BS6015	BS6015	-----	-----	100
	6 X 2"	BS6020	BS6020	-----	-----	100
	6 X 3"	BS6030	BS6030	-----	-----	95
	8 X 1 1/2"	BS8015	-----	-----	-----	50
	8 X 2"	BS8020	-----	-----	-----	50
UNIVERSAL PLUG W/PULLING EYE						
	2"	E091200	PLUG02	5315258	P258JT	70
	3"	E091300	PLUG03	5315260	P258LT	45
	4"	E091400	PLUG04	5315262	P258NT	80
	5"	E091500	PLUG05	5315263	P258PT	45
	6"	E091600	PLUG06	5315264	P258RT	35
ECOVOC LOW VOC / CLEAR CEMENT						
	PINT	RVOC475	RVOC475	7210612	VC9963	12
	QUART	RVOC950ML	RVOC950ML	7210613	VC9962	12

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
VINYL SIDING ELECTRICAL MOUNT						
	7 1/2" X 7 1/2"	10000	-----	-----	-----	10
	7 5/8" X 12"	41000	-----	-----	-----	10
	7 1/2" X 7 3/4"	13000	-----	-----	-----	10
	6" X 4 1/2"	43000	-----	-----	-----	10
	5 1/2" X 7 6/16"	44000	-----	-----	-----	10
	14 1/2" X 19"	42000	-----	-----	-----	1
	7" X 7"	17000	-----	-----	-----	10
SCH 40 STANDARD ELBOWS - 90° ELBOW - PLAIN END						
	1/2"	E018050	REE1090PE	5133823	UA9AD	50
	3/4"	E018075	REE1590PE	5133824	UA9AE	35
	1"	E018100	REE2090PE	5133825	UA9AF	20
	1 1/4"	E018125	REE2590PE	5133826	UA9AG	30
	1 1/2"	E018150	REE3090PE	5133827	UA9AH	30
	2"	E018200	REE3590PE	5133828	UA9AJ	15
	2 1/2"	E018250	REE4090PE	5133829	UA9AK CAR	18
	3"	E018300	REE4590PE	5133830	UA9AL	14
	3 1/2"	E018350	REE5090PE	5133831	UA9AM	12
	4"	E018400	REE5590PE	5133832	UA9AN	10
	5"	E018500	REE6090PE	5133835	UA9AP	1
	6"	E018600	REE6590PE	5133834	UA9AR	1
SCH 40 STANDARD ELBOWS - 45° ELBOW - PLAIN END						
	1/2"	E019050	REE1045PE	5133763	UA7AD	50
	3/4"	E019075	REE1545PE	5133764	UA7AE	25
	1"	E019100	REE2045PE	5133765	UA7AF	20
	1 1/4"	E019125	REE2545PE	5133766	UA7AG	25
	1 1/2"	E019150	REE3045PE	5133767	UA7AH	20
	2"	E019200	REE3545PE	5133768	UA7AJ	10
	2 1/2"	E019250	REE4045PE	5133769	UA7AK	20
	3"	E019300	REE4545PE	5133770	UA7AL CAR	8
	3 1/2"	E019350	REE5045PE	5133771	UA7AM	5
	4"	E019400	REE5545PE	5133772	UA7AN	20
	5"	E019500	REE6045PE	5133773	UA7AP	1
	6"	E019600	REE6545PE	5133774	UA7AR	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH 40 STANDARD ELBOWS - 30° ELBOW - PLAIN END						
	1/2″	E020050	REE1030PE	5133755	UA6AD	50
	3/4″	E020075	REE1530PE	5133744	UA6AE	25
	1″	E020100	REE2030PE	5133745	UA6AF	20
	1 1/4″	E020125	REE2530PE	5133746	UA6AG	25
	1 1/2″	E020150	REE3030PE	5133747	UA6AH	50
	2″	E020200	REE3530PE	5133748	UA6AJ	10
	2 1/2″	E020250	REE4030PE	5133749	UA6AK	20
	3″	E020300	REE4530PE	5133750	UA6AL	8
	3 1/2″	E020350	REE5030PE	5133751	UA6AM	5
	4″	E020400	REE5530PE	5133775	UA6AN	20
	5″	E020500	REE6030PE	5133753	UA6AP	1
	6″	E020600	REE6530PE	5133754	UA6AR	1
SCH 40 STANDARD ELBOWS - 22 1/2° ELBOW - PLAIN END						
	1 1/2″	E084150	-----	5134094	UA5AH	20
	2″	E084200	-----	5134067	UA5AJ	10
	2 1/2″	E084250	-----	5134096	UA5AK	20
	3″	E084300	-----	5134068	UA5AL	8
	3 1/2″	E084350	-----	5134095	UA5AM	5
	4″	E084400	-----	5133757	UA5AN	20
	5″	E084500	-----	5134037	UA5AP	1
	6″	E084600	-----	5133901	UA5AR	1
SCH 40 STANDARD ELBOWS - 11 1/4° ELBOW - PLAIN END						
	2″	E087200	-----	-----	UA3AJ	1
	3″	E087300	-----	-----	UA3AL	1
	4″	E087400	-----	-----	UA3AN	1
	5″	E087500	-----	-----	UA3AP	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH 40 STANDARD ELBOWS - 90° ELBOW - BELL END						
	1/2″	E021050	REE1090	5233823	UA9ADB	50
	3/4″	E021075	REE1590	5233824	UA9AEB	35
	1″	E021100	REE2090	5233825	UA9AFB	20
	1 1/4″	E021125	REE2590	5233826	UA9AGB	30
	1 1/2″	E021150	REE3090	5233827	UA9AHB	30
	2″	E021200	REE3590	5233828	UA9AJB	15
	2 1/2″	E021250	REE4090	5233829	UA9AKB CAR	18
	3″	E021300	REE4590	5233830	UA9ALB CAR	14
	3 1/2″	E021350	REE5090	5233831	UA9AMB	12
	4″	E021400	REE5590	5233832	UA9ANB	10
	5″	E021500	REE6090	5233835	UA9APB	1
	6″	E021600	REE6590	5233834	UA9ARB	1
SCH 40 STANDARD ELBOWS - 45° ELBOW - BELL EN						
	1/2″	E022050	REE1045	5233763	UA7ADB	50
	3/4″	E022075	REE1545	5233764	UA7AEB	25
	1″	E022100	REE2045	5233765	UA7AFB	20
	1 1/4″	E022125	REE2545	5233766	UA7AGB	25
	1 1/2″	E022150	REE3045	5233767	UA7AHB	20
	2″	E022200	REE3545	5233768	UA7AJB	10
	2 1/2″	E022250	REE4045	5233769	UA7AKB	20
	3″	E022300	REE4545	5233770	UA7ALB	8
	3 1/2″	E022350	REE5045	5233771	UA7AMB	5
	4″	E022400	REE5545	5233772	UA7ANB	20
	5″	E022500	REE6045	5233773	UA7APB	1
	6″	E022600	REE6545	5233774	UA7ARB	1
SCH 40 STANDARD ELBOWS - 30° ELBOW - BELL END						
	1/2″	E072050	REE1030		UA6ADB	50
	3/4″	E072075	REE1530		UA6AEB	35
	1″	E072100	REE2030		UA6AFB	50
	1 1/4″	E072125	REE2530		UA6AGB	30
	1 1/2″	E072150	REE3030		UA6AHB	50
	2″	E072200	REE3530	5233748	UA6AJB	10
	2 1/2″	E072250	REE4030		UA6AKB	10
	3″	E072300	REE4530	5233750	UA6ALB	8
	3 1/2″	E072350	REE5030	5233751	UA6AMB	5
	4″	E072400	REE5530	5233776	UA6ANB	20
	5″	E072500	REE6030	5233753	UA6APB	1
	6″	E072600	REE6530	5233754	UA6ARB	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH 80 STANDARD ELBOWS - SCH80 90° ELBOW - PLAIN END						
	1/2″	E085050	-----	5121053	UB9AD	50
	3/4″	E085075	-----	5121054	UB9AE	35
	1″	E085100	-----	5121055	UB9AF	20
	1 1/4″	E085125	-----	5121056	UB9AG	30
	1 1/2″	E085150	-----	5121057	UB9AH	30
	2″	E085200	-----	5121058	UB9AJ	15
	2 1/2″	E085250	-----	5121059	UB9AK CAR	18
	3″	E085300	-----	5121060	UB9AL CAR	14
	4″	E085400	-----	5121061	UB9AN	10
	5″	E085500	-----	5121062	UB9AP	1
	6″	E085600	-----	5121063	UB9AR	1
SCH 80 STANDARD ELBOWS - SCH80 45° ELBOW - PLAIN END						
	1/2″	E086050	-----	5121003	UB7AD	50
	3/4″	E086075	-----	5121004	UB7AE UPC	25
	1″	E086100	-----	5121005	UB7AF UPC	20
	1 1/4″	E086125	-----	5121006	UB7AG	25
	1 1/2″	E086150	-----	5121007	UB7AH	20
	2″	E086200	-----	5121008	UB7AJ UPC	10
	2 1/2″	E086250	-----	5121009	UB7AK	20
	3″	E086300	-----	5121010	UB7AL	8
	4″	E086400	-----	5121011	UB7AN	20
	5″	E086500	-----	5121012	UB7AP	1
	6″	E086600	-----	5121013	UB7AR	1
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 90° 24″ RADIUS						
	1″	E07510024	-----	5133859	UA9DF	1
	1 1/4″	E07512524	-----	5133883	UA9DG	1
	1 1/2″	E07515024	-----	5133873	UA9DH	1
	2″	E07520024	-----	5133836	UA9DJ	1
	2 1/2″	E07525024	-----	5133847	UA9DK	1
	3″	E07530024	-----	5133837	UA9DL	1
	3 1/2″	E07535024	-----	5133893	UA9DM	1
	4″	E07540024	-----	5133822	UA9DN	1
	5″	E07550024	-----	-----	-----	1
	6″	E07560024	-----	-----	-----	1


Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 90° 36" RADIUS						
	1"	E07510036	-----	5133852	UA9FF	1
	1 1/4"	E07512536	-----	5133884	UA9FG	1
	1 1/2"	E07515036	-----	5133866	UA9FH	1
	2"	E07520036	-----	5133848	UA9FJ UPC	1
	2 1/2"	E07525036	-----	5133857	UA9FK UPC	1
	3"	E07530036	-----	5133820	UA9FL	1
	3 1/2"	E07535036	-----	5133818	UA9FM	1
	4"	E07540036	-----	5133821	UA9FN	1
	5"	E07550036	-----	5133841	UA9FP	1
	6"	E07560036	-----	5133877	UA9FR	1
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 90° 48" RADIUS						
	1"	E07510048	-----	5133864	UA9HF	1
	1 1/4"	E07512548	-----	5133871	UA9HG	1
	1 1/2"	E07515048	-----	5133865	UA9HH	1
	2"	E07520048	-----	5133876	UA9HJ	1
	2 1/2"	E07525048	-----	5133849	UA9HK	1
	3"	E07530048	-----	5133817	UA9HL	1
	3 1/2"	E07535048	-----	5133892	UA9HM	1
	4"	E07540048	-----	5133843	UA9HN	1
	5"	E07550048	-----	5133842	UA9HP	1
	6"	E07560048	-----	5133816	UA9HR	1
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 45° 24" RADIUS						
	1"	E07610024	-----	5133875	UA7DF	1
	1 1/4"	E07612524	-----	5133941	UA7DG	1
	1 1/2"	E07615024	-----	5133874	UA7DH	1
	2"	E07620024	-----	5133815	UA7DJ	1
	2 1/2"	E07625024	-----	5133935	UA7DK	1
	3"	E07630024	-----	5133800	UA7DL	1
	3 1/2"	E07635024	-----	5133802	UA7DM	1
	4"	E07640024	-----	5133812	UA7DN	1
	5"	E07650024	-----	-----	-----	1
	6"	E07660024	-----	-----	-----	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 45° 36" RADIUS						
	1"	E07610036	------	5133919	UA7FF	1
	1 1/4"	E07612536	------	5133956	UA7FG	1
	1 1/2"	E07615036	------	5133810	UA7FH	1
	2"	E07620036	------	5133778	UA7FJ	1
	2 1/2"	E07625036	------	5133801	UA7FK	1
	3"	E07630036	------	5133779	UA7FL	1
	3 1/2"	E07635036	------	5133939	UA7FM	1
	4"	E07640036	------	5133777	UA7FN	1
	5"	E07650036	------	5133780	UA7FP	1
	6"	E07660036	------	5133880	UA7FR	1
SCH. 40 SPECIAL RADIUS ELBOW PLAIN END - 45° 48" RADIUS						
	1"	E07610048	------	5133940	UA7HF	1
	1 1/4"	E07612548	------	5133942	UA7HG	1
	1 1/2"	E07615048	------	5133811	UA7HH	1
	2"	E07620048	------	5133798	UA7HJ	1
	2 1/2"	E07625048	------	5134010	UA7HK	1
	3"	E07630048	------	5133781	------	1
	3 1/2"	E07635048	------	5133979	------	1
	4"	E07640048	------	5133776	UA7HN	1
	5"	E07650048	------	5133814	UA7HP	1
	6"	E07660048	------	5133813	UA7HR	1
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 90° 24" RADIUS						
	2"	E07920024	------	5133924	UA9DJB UPC	1
	2 1/2"	E07925024	------	5233847	UA9DKB UPC	1
	3"	E07930024	------	5233837	UA9DLB UPC	1
	3 1/2"	E07935024	------	5233893	UA9DMB	1
	4"	E07940024	------	5233822	UA9DNB	1
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 90° 36" RADIUS						
	2"	E07920036	------	5233848	UA9FJB	1
	2 1/2"	E07925036	------	5233857	UA9FKB	1
	3"	E07930036	------	5233930	UA9FLB	1
	3 1/2"	E07935036	------	5233818	UA9FMB	1
	4"	E07940036	------	5233842	UA9FNB	1
	5"	E07950036	------	5233841	UA9FPB	1
	6"	E07960036	------	5233877	UA9FRB	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 90° 48" RADIUS						
	2"	E07920048	-----	5233876	UA9HJB	1
	2 1/2"	E07925048	-----	5233849	UA9HKB	1
	3"	E07930048	-----	5233817	UA9HLB	1
	3 1/2"	E07935048	-----	5233892	-----	1
	4"	E07940048	-----	5233843	UA9HNB	1
	5"	E07950048	-----	5233868	UA9HPB	1
	6"	E07960048	-----	5233816	UA9HRB	1
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 45° 24" RADIUS						
	2"	E08020024	-----	5233815	UA7DJB	1
	2 1/2"	E08025024	-----	5233935	UA7DKB	1
	3"	E08030024	-----	5233800	UA7DLB	1
	3 1/2"	E08035024	-----	5233802	-----	1
	4"	E08040024	-----	5233812	UA7DNB	1
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 45° 36" RADIUS						
	2"	E08020036	-----	5233778	UA7FJB	1
	2 1/2"	E08025036	-----	5233801	UA7FKB	1
	3"	E08030036	-----	5233779	UA7FLB	1
	3 1/2"	E08035036	-----	5233939	-----	1
	4"	E08040036	-----	5233777	UA7FNB	1
	5"	E08050036	-----	5233780	UA7FPB	1
	6"	E08060036	-----	5133894	UA7FRB	1
SCH. 40 SPECIAL RADIUS ELBOW BELLED - 45° 48" RADIUS						
	2"	E08020048	-----	5133759	UA7HJB	1
	2 1/2"	E08025048	-----	5233785	-----	1
	3"	E08030048	-----	5233782	UA7HLB	1
	3 1/2"	E08035048	-----	5233943	-----	1
	4"	E08040048	-----	5133761	UA7HNB	1
	5"	E08050048	-----	5233781	UA7HPB	1
	6"	E08060048	-----	5233813	UA7HRB	1
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END - 90° 24" RADIUS						
	1"	E07710024	-----	5121018	UB9DF	1
	1 1/4"	E07712524	-----	5119824	UB9DG	1
	1 1/2"	E07715024	-----	5121015	UB0DH UPC	1
	2"	E07720024	-----	5121019	UB9DJ UPC	1
	2 1/2"	E07725024	-----	5121028	UB9DK UPC	1
	3"	E07730024	-----	5121020	UB9DL	1
	4"	E07740024	-----	5121022	UB9DN	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END - 90° 36" RADIUS						
	1"	E07710036		5121080	UB9FF	1
	1 1/4"	E07712536		5121084	UB9FG	1
	1 1/2"	E07715036		5121100	UB9FH	1
	2"	E07720036		5121021	UB9FJ	1
	2 1/2"	E07725036		5121016	UB9FK	1
	3"	E07730036		5121081	UB9FL	1
	4"	E07740036		5121023	UB9FN	1
	5"	E07750036		5121083	UB9FP	1
	6"	E07760036		5121073	UB9FR	1
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END - 90° 48" RADIUS						
	1"	E07710048		5121065	UB9HF	1
	1 1/4"	E07712548		5136510	UB9HG	1
	1 1/2"	E07715048		5121076	UB9HH	1
	2"	E07720048		5121075	UB9HJ	1
	2 1/2"	E07725048		5121030	UB9HK	1
	3"	E07730048		5121082	UB9HL	1
	4"	E07740048		5121024	UB9HN	1
	5"	E07750048		5121025	UB9HP	1
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END						
	1"	E07810024		5136500	UB7DF	1
	1 1/4"	E07812524		5136512	UB7DG	1
	1 1/2"	E07815024		5163533	UB7DH	1
	2"	E07820024		5121101	UB7DJ	1
	2 1/2"	E07825024		5121943	UB7DK	1
	3"	E07830024		5121014	UB7DL	1
	4"	E07840024		5121089	UB7DN	1
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END						
	1"	E07810036		5136502		1
	1 1/4"	E07812536		5136514	UB7FG	1
	1 1/2"	E07815036		5136533	UB7FH	1
	2"	E07820036		5121098	UB7FJ	1
	2 1/2"	E07825036		5121150	UB7FK	1
	3"	E07830036		5121077	UB7FL	1
	4"	E07840036		5119821	UB7FN	1
	5"	E07850036		5119820	UB7FP	1
	6"	E07860036		5121072	UB7FR	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 80 SPECIAL RADIUS ELBOW PLAIN END - 45° 48" RADIUS						
	1"	E07810048	-----	5136503	UB7HF	1
	1 1/4"	E07812548	-----	5136515	UB7HG	1
	1 1/2"	E07815048	-----	5136534	-----	1
	2"	E07820048	-----	5121093	UB7HJ	1
	2 1/2"	E07825048	-----	5136563	-----	1
	3"	E07830048	-----	5121078	UB7HL	1
	4"	E07840048	-----	5121091	UB7HN	1
	5"	E07850048	-----	5121948	UB7HP	1
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 90° 24" RADIUS						
	1"	E08210024	-----	-----	-----	1
	1 1/4"	E08212524	-----	-----	-----	1
	1 1/2"	E08215024	-----	-----	-----	1
	2"	E08220024	-----	-----	UB9DJB	1
	2 1/2"	E08225024	-----	-----	UB9DKB	1
	3"	E08230024	-----	-----	UB9DLB	1
	4"	E08240024	-----	-----	-----	1
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 90° 36" RADIUS						
	1"	E08210036	-----	-----	-----	1
	1 1/4"	E08212536	-----	-----	-----	1
	1 1/2"	E08215036	-----	-----	-----	1
	2"	E08220036	-----	-----	-----	1
	2 1/2"	E08225036	-----	-----	UB9FKB	1
	3"	E08230036	-----	-----	UB9FLB	1
	4"	E08240036	-----	-----	UB9FNB	1
	5"	E08250036	-----	-----	-----	1
	6"	E08260036	-----	-----	-----	1
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 90° 48" RADIUS						
	1"	E08210048	-----	-----	-----	1
	1 1/4"	E08212548	-----	-----	-----	1
	1 1/2"	E08215048	-----	-----	-----	1
	2"	E08220048	-----	-----	-----	1
	2 1/2"	E08225048	-----	-----	-----	1
	3"	E08230048	-----	-----	-----	1
	4"	E08240048	-----	-----	UB9HNB	1
	5"	E08250048	-----	-----	-----	1

Rigid PVC Conduit Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 45° 24" RADIUS						
	1"	E08310024	-----	-----	-----	1
	1 1/4"	E08312524	-----	-----	-----	1
	1 1/2"	E08315024	-----	-----	-----	1
	2"	E08320024	-----	-----	-----	1
	2 1/2"	E08325024	-----	-----	-----	1
	3"	E08330024	-----	-----	-----	1
	4"	E08340024	-----	-----	-----	1
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 45° 36" RADIUS						
	1"	E08310036	-----	-----	-----	1
	1 1/4"	E08312536	-----	-----	-----	1
	1 1/2"	E08315036	-----	-----	-----	1
	2"	E08320036	-----	-----	-----	1
	2 1/2"	E08325036	-----	-----	-----	1
	3"	E08330036	-----	-----	-----	1
	4"	E08340036	-----	-----	-----	1
	5"	E08350036	-----	-----	-----	1
	6"	E08360036	-----	-----	-----	1
SCH. 80 SPECIAL RADIUS ELBOW BELLED - 45° 48" RADIUS						
	1"	E08310048	-----	-----	-----	1
	1 1/4"	E08312548	-----	-----	-----	1
	1 1/2"	E08315048	-----	-----	-----	1
	2"	E08320048	-----	-----	-----	1
	2 1/2"	E08325048	-----	-----	-----	1
	3"	E08330048	-----	-----	-----	1
	4"	E08340048	-----	-----	-----	1
	5"	E08350048	-----	-----	-----	1

Rigid PVC Conduit Fittings

With Brass Fasteners

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE LB						
	1/2″	E533050	RSLB10S	-----	-----	25
	3/4″	E533075	RSLB20S	-----	-----	25
	1″	E533100	RSLB30S	-----	-----	15
	1 1/4″	E533125	RSLB40S	-----	-----	20
	1 1/2″	E533150	RSLB50S	-----	-----	10
	2″	E533200	RSLB60S	-----	-----	15
	2 1/2″	E533250	RSLB70S	-----	-----	5
	3″	E533300	RSLB80S	-----	-----	5
	3 1/2″	E533350	RSLB90S	-----	-----	5
	4″	E533400	RSLB100S	-----	-----	5
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE C						
	1/2″	E532050	RSC10S	-----	-----	30
	3/4″	E532075	RSC20S	-----	-----	20
	1″	E532100	RSC30S	-----	-----	15
	1 1/4″	E532125	RSC40S	-----	-----	15
	1 1/2″	E532150	RSC50S	-----	-----	10
	2″	E532200	RSC60S	-----	-----	15
	2 1/2″	E532250	RSC70S	-----	-----	4
	3″	E532300	RSC80S	-----	-----	4
	3 1/2″	E532350	RSC90S	-----	-----	4
	4″	E532400	RSC100S	-----	-----	4
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE LL						
	1/2″	E534050	RSLL10S	-----	-----	25
	3/4″	E534075	RSLL20S	-----	-----	20
	1″	E534100	RSLL30S	-----	-----	15
	1 1/4″	E534125	RSLL40S	-----	-----	10
	1 1/2″	E534150	RSLL50S	-----	-----	10
	2″	E534200	RSLL60S	-----	-----	10
	2 1/2″	E534250	RSLL70S	-----	-----	4
	3″	E534300	RSLL80S	-----	-----	4
	3 1/2″	E534350	RSLL90S	-----	-----	5
	4″	E534400	RSLL100S	-----	-----	5





Rigid PVC Conduit Fittings

With Brass Fasteners

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE LR						
	1/2″	E535050	RSLR10S	-----	-----	25
	3/4″	E535075	RSLR20S	-----	-----	20
	1″	E535100	RSLR30S	-----	-----	15
	1 1/4″	E535125	RSLR40S	-----	-----	10
	1 1/2″	E535150	RSLR50S	-----	-----	10
	2″	E535200	RSLR60S	-----	-----	10
	2 1/2″	E535250	RSLR70S	-----	-----	4
	3″	E535300	RSLR80S	-----	-----	4
	3 1/2″	E535350	RSLR90S	-----	-----	5
	4″	E535400	RSLR100S	-----	-----	5
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE E						
	1/2″	E536050	RSE10S	-----	-----	30
	3/4″	E536075	RSE20S	-----	-----	20
	1″	E536100	RSE30S	-----	-----	15
	1 1/4″	E536125	RSE40S	-----	-----	20
	1 1/2″	E536150	RSE50S	-----	-----	10
	2″	E536200	RSE60S	-----	-----	15
	2 1/2″	E536250	RSE70S	-----	-----	4
	3″	E536300	RSE80S	-----	-----	4
	3 1/2″	E536350	RSE90S	-----	-----	4
	4″	E536400	RSE100S	-----	-----	4
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE T						
	1/2″	E537050	RST10S	-----	-----	30
	3/4″	E537075	RST20S	-----	-----	20
	1″	E537100	RST30S	-----	-----	25
	1 1/4″	E537125	RST40S	-----	-----	15
	1 1/2″	E537150	RST50S	-----	-----	10
	2″	E537200	RST60S	-----	-----	10
	2 1/2″	E537250	RST70S	-----	-----	4
	3″	E537300	RST80S	-----	-----	4
	3 1/2″	E537350	RST90S	-----	-----	4
	4″	E537400	RST100S	-----	-----	4
BRASS FASTENER PRODUCTS - ACCESS FITTING - TYPE TB						
	1/2″	E569050	RSTB10S	-----	-----	30
	3/4″	E569075	RSTB20S	-----	-----	20
	1″	E569100	RSTB30S	-----	-----	10
	1 1/4″	E569125	RSTB40S	-----	-----	10




Rigid PVC Conduit Fittings

With Brass Fasteners

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
BRASS FASTENER PRODUCTS - JUNCTION BOX WITH GASKET						
	4" X 4" X 2"	E551442	RJB442	------	------	15
	4" X 4" X 4"	E551444	RJB444	------	------	10
	4" X 4" X 6"	E551446	RJB446	------	------	8
	5" X 5" X 2"	E551552	RJB552	------	------	12
	6" X 6" X 4"	E551664	RJB664	------	------	15
	6" X 6" X 6"	E551666	RJB666	------	------	4
	8" X 8" X 4"	E551884	RJB884	------	------	4
	8" X 8" X 7"	E551887	RJB887	------	------	4
	12" X 12" X 4"	E55112124	RJB12124	------	------	2
	12" X 12" X 6"	E55112126	RJB12126	------	------	4
	12" X 12" X 8"	E55112128	RJB12128	------	------	3
BRASS FASTENER PRODUCTS - SINGLE GANG BOX - F SERIES						
	A. 1/2" FS	E542001	RFS10	------	------	10
	A. 3/4" FS	E542002	RFS15	------	------	10
	B. 1/2" FSS	E542003	RFSS10	------	------	10
	B. 3/4" FSS	E542004	RFSS15	------	------	10
	C. 1/2" FSC	E542005	RFSC10	------	------	10
	C. 3/4" FSC	E542006	RFSC15	------	------	10
	D. 1/2" FSCC	E542007	RFSCC10	------	------	10
	D. 3/4" FSCC	E542008	RFSCC15	------	------	10
BRASS FASTENER PRODUCTS - SINGLE GANG DEEP BOX - FD SERIES						
	A. 1/2" FDS	E543001	RFDS10	------	------	10
	A. 3/4" FDS	E543002	RFDS15	------	------	10
	A. 1" FDS	E543003	RFDS20	------	------	10
	B. 1/2" FDC	E543004	RFDC10	------	------	10
	B. 3/4" FDC	E543005	RFDC15	------	------	10
	B. 1" FDC	E543006	RFDC20	------	------	10
	C. BLANK	E543007	RFD	------	------	10
BRASS FASTENER PRODUCTS - DOUBLE GANG BOX - F SERIES						
	A. 1/2" FS	E541001	------	------	------	10
	A. 3/4" FS	E541002	------	------	------	10
	A. 1" FS	E541003	------	------	------	10
	B. 1/2" FSS	E541004	------	------	------	10
	B. 3/4" FSS	E541005	------	------	------	10
	B. 1" FSS	E541006	------	------	------	10
	C. 1/2" FSC	E541007	------	------	------	10
	C. 3/4" FSC	E541008	------	------	------	10
	C. 1" FSC	E541009	------	------	------	10
	D. 1/2" FSCC	E541011	------	------	------	10
	D. 3/4" FSCC	E541012	------	------	------	10
	D. 1" FSCC	E541013	------	------	------	10
	E. BLANK	E541010	------	------	------	10

Rigid PVC Conduit Fittings

With Brass Fasteners

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
BRASS FASTENER PRODUCTS - SINGLE GANG COVER PLATE - F SERIES						
	A. TOGGLE	E546002	RTSC15/10	------	------	100
	B. DUPLEX	E546001	RDRC15/10	------	------	100
	C. 15 AMP	E546004	R20RC15/10	------	------	100
	D. 20 AMP	E546003	R20 3RC15/10	------	------	100
	E. 30 AMP	E546005	R30 3RC15/10	------	------	100
	F. BLANK W/ GASKET	E546006	RBRC15/10	------	------	100
BRASS FASTENER PRODUCTS - DOUBLE GANG WEATHERPROOF COVER PLATE						
	B. GFI & TOGGLE	E549005	------	------	------	10
	C. DUPLEX & TOGGLE	E549006	------	------	------	10
	D. DOUBLE DU PLEX	E549007	------	------	------	10
	E. TOGGLE	E549008	------	------	------	10
	F. BLANK	E549009	------	------	------	25
BRASS FASTENER PRODUCTS - SINGLE GANG WEATHERPROOF COVER PLATE						
	A. TOGGLE S/ COVER	E547002	RVSC15/10	------	------	20
	B. PLUNGER S/ COVER	E547008	RVPT15/10	------	------	20
	C. TOGGLE	E547009	RWTG15/10	------	------	20
	D. DUPLEX	E547001	RWDR15/10	------	------	20
	D. DUPLEX WHITE	E547010	RWDR15/10W	------	------	20
	E. GROUND FAULT	E547007	RWGF15/10	------	------	20
	E. GROUND FAULT WHITE	E547011	RWGF15/10W	------	------	20
	F. 15 AMP	E547003	RWTL15	------	------	20
	F. 20 AMP	E547004	RWTL20	------	------	20
	F. 30 AMP	E547005	RWTL30	------	------	20
	F. 50 AMP	E547006	RWTL50	------	------	20

ENT - Tubing

Electrical Non-Metallic Tubing

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
COILS - BLUE ENT TUBING						
						FEET
	1/2	EC005200BL	-----	A51AEB1	12005 200	200
	3/4	EC007100BL	-----	A51AGA1	12007 100	100
	1	EC010100BL	-----	A51BAA1	12008 100	100
	1 1/4	EC012350BL	-----	-----	-----	350
	1 1/2	EC015300BL	-----	-----	-----	300
	2	EC020250BL	-----	-----	-----	250
COILS - GREY ENT TUBING						
						FEET
	1/2	EC005370	EC005370	-----	-----	370
	3/4	EC007240	EC007240	-----	-----	240
	1	EC010160	EC010160	-----	-----	160
	1 1/4	EC012500	EC012500	-----	-----	500
	1 1/2	EC015300	EC015300	-----	-----	300
	2	EC020225	EC020225	-----	-----	225
REELS - BLUE ENT TUBING						
						FEET
	1/2	ER 0051500BL	-----	A51AEQ1	12005AK 001	1,500
	3/4	ER 0071000BL	-----	A51AGJ1	12007AA 001	1,000
	1	ER 0101000BL	-----	A51BAJ1	-----	1,000
	1 1/4	ER 0121000BL	-----	-----	-----	1,000
	1 1/2	ER015750BL	-----	-----	12010 750	750
	2	ER020500BL	-----	-----	12011 500	500

ENT - Tubing

Electrical Non-Metallic Tubing

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
REELS - GREY ENT TUBING						
						FEET
	1/2	ER0052000	ER0052000	-----	-----	2,000
	3/4	ER0071500	ER0071500	-----	-----	1,500
	1	ER0101000	ER0101000	-----	-----	1,000
	1 1/4	ER0121000	ER0121000	-----	-----	1,000
	1 1/2	ER015750	ER015750	-----	-----	750
	2	ER020500	ER020500	-----	-----	500
STRAIGHT LENGTH - BLUE ENT TUBING						
						EACH
	1/2	ES00510BL	-----	-----	-----	100
	3/4	ES00710BL	-----	-----	-----	100
	1	ES01010BL	-----	-----	-----	100
STRAIGHT LENGTH - GREY ENT TUBING						
					SUPPLIED IN 10 FOOT LENGTHS	
						EACH
	1/2	ES00510	ES00510	-----	-----	100
	3/4	ES00710	ES00710	-----	-----	100
	1	ES01010	ES01010	-----	-----	100

ENT - Fittings

Electrical Non-Metallic Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
ENT COUPLING						
	1/2	RKC10	RKC10	5163380	A240D	150
	3/4	RKC15	RKC15	5163381	A240E	100
	1	RKC20	RKC20	5163382	A240F	50
	1 1/4	RKC25	RKC25	-----	-----	50
	1 1/2	RKC30	RKC30	-----	-----	40
	2	RKC35	RKC35	-----	-----	25
ENT THREADED TERMINAL ADAPTER WITH LOCK NUT						
	1/2	RKTA10	RKTA10	5163415	-----	150
	3/4	RKTA15	RKTA15	5163416	-----	100
	1	RKTA20	RKTA20	5163417	-----	50
	1 1/4	RKTA25	RKTA25	-----	-----	50
	1 1/2	RKTA30	RKTA30	-----	-----	50
	2	RKTA35	RKTA35	-----	-----	25
ENT ADAPTER WITH SET SCREW						
	1/2	RKTC10	RKTC10	-----	A245D	125
	3/4	RKTC15	RKTC15	-----	A245E	100
	1	RKTC20	RKTC20	-----	A245F	50
	1 1/4	RKTC25	RKTC25	-----	-----	50
	1 1/2	RKTC30	RKTC30	-----	-----	40
	2	RKTC35	RKTC35	-----	-----	15
ENT QUICK SNAP TERMINAL ADAPTER						
	1/2	RKTS10	RKTS10	5163405	A253D	150
	3/4	RKTS15	RKTS15	5163406	A253E	100
	1	RKTS20	RKTS20	5163407	A253F	50
ENT CLIP RING						
	1/2	RKR10	RKR10	-----	-----	200†
	3/4	RKR15	RKR15	-----	-----	200†
	1	RKR20	RKR20	-----	-----	200†
	1 1/4	RKR25	RKR25	-----	-----	100*
	1 1/2	RKR30	RKR30	-----	-----	100*
	2	RKR35	RKR35	-----	-----	50^

Rings are net priced per bag as follows: † = 20/bag * = 10/bag ^ = 5/bag

ENT - Fittings

Electrical Non-Metallic Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
HEAVY DUTY LOCK NUT						
	1/2	RLN10	RLN10	-----	-----	200
	3/4	RLN15	RLN15	-----	-----	200
	1	RLN20	RLN20	-----	-----	200
	1 1/4	RLN25	RLN25	-----	-----	200
	1 1/2	RLN30	RLN30	-----	-----	200
	2	RLN35	RLN35	-----	-----	200
STRAIGHT STUBBY (POLYETHYLENE)						
	1/2	RECM10	RECM10	EN050SBY	A210D	150
	3/4	RECM15	RECM15	EN075SBY	A210E	150
	1	RECM20	RECM20	EN100SBY	A210F	200
	1 1/4	RECM25	RECM25	-----	-----	200
45 DEGREE ANGLED FORM STUBBY (POLYETHYLENE)						
	1/2	RKASTB10	RKASTB10	-----	A220D	50
	3/4	RKASTB15	RKASTB15	-----	A220E	50
	1	RKASTB20	RKASTB20	-----	A220F	50
	1 1/4	RKASTB25	RKASTB25	-----	A220G	50
	1 1/2	RKASTB30	RKASTB30	-----	A220H	50
	2	RKASTB35	RKASTB35	-----	A220J	50
TAPERED PLUG (POLYETHYLENE)						
	1/2	RTP10	RTP10	-----	-----	250
	3/4	RTP15	RTP15	-----	-----	100
	1	RTP20	RTP20	-----	-----	100
SLAB BOX EXTENSION						
	1" EXTENSION	RSMBXTENSION	RSMBXTENSION	-----	-----	20

ENT - Fittings

Electrical Non-Metallic Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
ENT SLAB BOX WITH HUB EXTENSIONS AND GREY LID						
	1/2 (8)	RSMB H 10	RSMB H 10	ENS0500C	------	25
	1/2 (4) 3/4 (4)	RSMB H 10 15	RSMB H 10 15	ENS0507C	------	25
	1/2 (4) 3/4 (2)	RSMB H 10 15 20	RSMB H 10 15 20	------	------	25
	1 (2)			------	------	
	1/2 (4) 1 (4)	RSMB H 10 20	RSMB H 10 20	------	------	25
	3/4 (8)	RSMB H 15	RSMB H 15	------	------	25
	3/4 (4) 1 (4)	RSMB H 15 20	RSMB H 15 20	------	------	25
ENT SLAB BOX WITH KNOCKOUTS AND GREY LID						
	1/2 (8)	RSMB 10	RSMB 10	ENS0500K	------	25
	1/2 (4) 3/4 (4)	RSMB 10 15	RSMB 10 15	ENS0507K	------	25
	1/2 (4) 3/4 (2)	RSMB 10 15 20	RSMB 10 15 20	------	------	25
	1 (2)			------	------	
	1/2 (2) 3/4 (4)	RSMB 15 20 10	RSMB 15 20 10	------	------	25
	1 (2)			------	------	
	3/4 (8)	RSMB 15	RSMB 15	------	------	25
ENT SHALLOW SLAB BOX						
	1/2 (8)	RSMBS H 10	RSMBS H 10	------	------	25
	1/2 (4) 3/4 (4)	RSMBS H 10 15	RSMBS H 10 15	------	------	25
	1/2 (4) 3/4 (2)	RSMBS H 10 15 20	RSMBS H 10 15 20	------	------	25
	1 (2)			------	------	
	1/2 (4) 1 (4)	RSMBS H 10 20	RSMBS H 10 20	------	------	25
	3/4 (8)	RSMBS H 15	RSMBS H 15	------	------	25
	3/4 (4) 1 (4)	RSMBS H 15 20	RSMBS H 15 20	------	------	25
ENT ISOLATOR MODULE SLAB BOX						
	1/2 (8)	RSMB 10 IMB	RSMB 10 IMB	------	------	20
	1/2 (4) 3/4 (4)	RSMB 10 15 IMB	RSMB 10 15 IMB	------	------	20
	1/2 (4) 3/4 (2)	RSMB 10 15 20 IMB	RSMB 10 15 20 IMB	------	------	20
	1 (2)			------	------	
	1/2 (4) 1 (4)	RSMB 10 20 IMB	RSMB 10 20 IMB	------	------	20
	3/4 (8)	RSMB 15 IMB	RSMB 15 IMB	------	------	20
	3/4 (4) 1 (4)	RSMB 15 20 IMB	RSMB 15 20 IMB	------	------	20

ENT - Fittings

Electrical Non-Metallic Fittings

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Carton Qty
ENT SHALLOW SINGLE GANG CONCRETE WALL BOX						
	1/2	RSVSB H 10	RSVSB H 10	------	------	70
	3/4	RSVSB H 15	RSVSB H 15	------	------	70
	1	RSVSB H 20	RSVSB H 20	------	------	70
ENT DEEP SINGLE GANG CONCRETE WALL BOX						
	1/2 (8)	RSVDB H 10	RSVDB H 10	------	------	25
	1/2 (4) 3/4 (4)	RSVDB H 10 15	RSVDB H 10 15	------	------	25
	1/2 (4) 3/4 (2)	RSVDB H 10 15 20	RSVDB H 10 15 20	------	------	25
	1 (2)					
	1/2 (4) 1 (4)	RSVDB H 10 20	RSVDB H 10 20	------	------	25
	3/4 (8)	RSVDB H 15	RSVDB H 15	------	------	25

PVC Enclosures

Electrical Non-Metallic PVC Enclosures

Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Weight Each Lbs.
ELECTRICAL TROUGH BOX (SCREW COVER)						
	4 X 4 X 12	ETR040412	ETR040412	-----	-----	3
	4 X 4 X 18	ETR040418	ETR040418	-----	-----	4
	4 X 4 X 24	ETR040424	ETR040424	-----	-----	5
	4 X 4 X 36	ETR040436	ETR040436	-----	-----	8
	4 X 4 X 48	ETR040448	ETR040448	-----	-----	10
	4 X 4 X 60	ETR040460	ETR040460	-----	-----	12
	6 X 6 X 12	ETR060612	ETR060612	-----	-----	5
	6 X 6 X 18	ETR060618	ETR060618	-----	-----	7
	6 X 6 X 24	ETR060624	ETR060624	-----	-----	8
	6 X 6 X 36	ETR060636	ETR060636	-----	-----	11
	6 X 6 X 48	ETR060648	ETR060648	-----	-----	14
	6 X 6 X 60	ETR060660	ETR060660	-----	-----	17
	8 X 8 X 12	ETR080812	ETR080812	-----	-----	7
	8 X 8 X 18	ETR080818	ETR080818	-----	-----	9
	8 X 8 X 24	ETR080824	ETR080824	-----	-----	11
	8 X 8 X 36	ETR080836	ETR080836	-----	-----	15
	8 X 8 X 48	ETR080848	ETR080848	-----	-----	19
	8 X 8 X 60	ETR080860	ETR080860	-----	-----	23
	12 X 12 X 24	ETR121224	ETR121224	-----	-----	27
	12 X 12 X 36	ETR121236	ETR121236	-----	-----	33
	12 X 12 X 48	ETR121248	ETR121248	-----	-----	39
	12 X 12 X 60	ETR121260	ETR121260	-----	-----	45
ELECTRICAL TROUGH BOX (LATCH COVER)						
	4 X 4 X 12	ELC040412	ELC040412	-----	-----	3
	4 X 4 X 18	ELC040418	ELC040418	-----	-----	4
	4 X 4 X 24	ELC040424	ELC040424	-----	-----	5
	4 X 4 X 36	ELC040436	ELC040436	-----	-----	8
	4 X 4 X 48	ELC040448	ELC040448	-----	-----	10
	4 X 4 X 60	ELC040460	ELC040460	-----	-----	12
	6 X 6 X 12	ELC060612	ELC060612	-----	-----	5
	6 X 6 X 18	ELC060618	ELC060618	-----	-----	7
	6 X 6 X 24	ELC060624	ELC060624	-----	-----	8
	6 X 6 X 36	ELC060636	ELC060636	-----	-----	11
	6 X 6 X 48	ELC060648	ELC060648	-----	-----	14
	6 X 6 X 60	ELC060660	ELC060660	-----	-----	17
	8 X 8 X 12	ELC080812	ELC080812	-----	-----	7
	8 X 8 X 18	ELC080818	ELC080818	-----	-----	9
	8 X 8 X 24	ELC080824	ELC080824	-----	-----	11
	8 X 8 X 36	ELC080836	ELC080836	-----	-----	15
	8 X 8 X 48	ELC080848	ELC080848	-----	-----	19
	8 X 8 X 60	ELC080860	ELC080860	-----	-----	23
	12 X 12 X 24	ELC121224	ELC121224	-----	-----	27
	12 X 12 X 36	ELC121236	ELC121236	-----	-----	33
	12 X 12 X 48	ELC121248	ELC121248	-----	-----	39

PVC Enclosures

Electrical Non-Metallic PVC Enclosures






Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Weight Each Lbs.
LARGE FABRICATED JUNCTION BOXES						
	12 X 10 X 6	E053121006	E053121006	-----	-----	8
	12 X 10 X 8	E053121008	E053121008	-----	-----	9
	12 X 12 X 4	E053121204	E053121204	-----	-----	7
	12 X 12 X 6	E053121206	E053121206	-----	-----	9
	12 X 12 X 8	E053121208	E053121208	-----	-----	10
	12 X 12 X 12	E053121212	E053121212	-----	-----	14
	14 X 12 X 4	E053141204	E053141204	-----	-----	9
	14 X 12 X 6	E053141206	E053141206	-----	-----	10
	14 X 12 X 8	E053141208	E053141208	-----	-----	12
	14 X 14 X 4	E053141404	E053141404	-----	-----	10
	14 X 14 X 6	E053141406	E053141406	-----	-----	12
	14 X 14 X 8	E053141408	E053141408	-----	-----	14
	14 X 14 X 10	E053141410	E053141410	-----	-----	16
	14 X 14 X 14	E053141414	E053141414	-----	-----	19
	16 X 16 X 10	E053161610	E053161610	-----	-----	21
	16 X 16 X 12	E053161612	E053161612	-----	-----	23
	16 X 16 X 16	E053161616	E053161616	-----	-----	22
	18 X 12 X 4	E053181204	E053181204	-----	-----	10
	18 X 12 X 6	E053181206	E053181206	-----	-----	12
	18 X 12 X 8	E053181208	E053181208	-----	-----	13
	18 X 16 X 4	E053181604	E053181604	-----	-----	12
	18 X 16 X 6	E053181606	E053181606	-----	-----	14
	18 X 16 X 8	E053181608	E053181608	-----	-----	16
	18 X 18 X 6	E053181806	E053181806	-----	-----	16
	18 X 18 X 8	E053181808	E053181808	-----	-----	18
	18 X 18 X 10	E053181810	E053181810	-----	-----	20
	18 X 18 X 12	E053181812	E053181812	-----	-----	22
	18 X 18 X 18	E053181818	E053181818	-----	-----	26
	20 X 18 X 8	E053201808	E053201808	-----	-----	20
	20 X 20 X 8	E053202008	E053202008	-----	-----	22
	24 X 18 X 6	E053241806	E053241806	-----	-----	20
	24 X 18 X 8	E053241808	E053241808	-----	-----	22
	24 X 18 X 12	E053241812	E053241812	-----	-----	25
	24 X 20 X 8	E053242008	E053242008	-----	-----	25
	24 X 24 X 6	E053242406	E053242406	-----	-----	25
	24 X 24 X 8	E053242408	E053242408	-----	-----	28
	24 X 24 X 10	E053242410	E053242410	-----	-----	33
	24 X 24 X 12	E053242412	E053242412	-----	-----	35
	24 X 24 X 24	E053242424	E053242424	-----	-----	40
	30 X 24 X 8	E053302408	E053302408	-----	-----	34
	30 X 30 X 10	E053303010	E053303010	-----	-----	39
	30 X 30 X 20	E053303020	E053303020	-----	-----	48
	30 X 30 X 30	E053303030	E053303030	-----	-----	60
	36 X 24 X 8	E053362408	E053362408	-----	-----	39
	36 X 36 X 12	E053363612	E053363612	-----	-----	61
	36 X 36 X 18	E053363618	E053363618	-----	-----	65
	36 X 36 X 20	E053363620	E053363620	-----	-----	67
	36 X 36 X 36	E053363636	E053363636	-----	-----	70
	40 X 40 X 12	E053404012	E053404012	-----	-----	78
	40 X 40 X 20	E053404020	E053404020	-----	-----	88

PVC Enclosures

Electrical Non-Metallic PVC Enclosures


Item	Size in Inches	Part Number	Reference Royal	Reference CANTEX	Reference Thomas & Betts - Carlon	Weight Each Lbs.
ELECTRICAL ENCLOSURES						
	20 X 12 X 8	EBH201208	EBH201208	-----	-----	14
	20 X 16 X 6	EBH201606	EBH201606	-----	-----	16
	20 X 16 X 8	EBH201608	EBH201608	-----	-----	17
	20 X 16 X 10	EBH201610	EBH201610	-----	-----	20
	20 X 16 X 12	EBH201612	EBH201612	-----	-----	22
	20 X 20 X 6	EBH202006	EBH202006	-----	-----	18
	20 X 20 X 8	EBH202008	EBH202008	-----	-----	21
	20 X 20 X 10	EBH2022010	EBH2022010	-----	-----	23
	20 X 24 X 6	EBH2022406	EBH2022406	-----	-----	21
	20 X 24 X 8	EBH202408	EBH202408	-----	-----	24
	24 X 12 X 6	EBH241206	EBH241206	-----	-----	15
	24 X 12 X 8	EBH241208	EBH241208	-----	-----	17
	24 X 12 X 10	EBH241210	EBH241210	-----	-----	19
	24 X 16 X 6	EBH241606	EBH241606	-----	-----	18
	24 X 16 X 8	EBH241608	EBH241608	-----	-----	20
	24 X 20 X 8	EBH242008	EBH242008	-----	-----	24
	24 X 20 X 10	EBH242010	EBH242010	-----	-----	26
	24 X 20 X 12	EBH242012	EBH242012	-----	-----	29
	24 X 20 X 16	EBH242016	EBH242016	-----	-----	34
	24 X 24 X 6	EBH242406	EBH242406	-----	-----	25
	24 X 24 X 8	EBH242408	EBH242408	-----	-----	28
	24 X 24 X 10	EBH242410	EBH242410	-----	-----	30
	24 X 24 X 12	EBH242412	EBH242412	-----	-----	33
	24 X 24 X 16	EBH242416	EBH242416	-----	-----	38
	24 X 30 X 8	EBH243008	EBH243008	-----	-----	33
	30 X 16 X 6	EBH301606	EBH301606	-----	-----	22
	30 X 20 X 6	EBH302006	EBH302006	-----	-----	26
	30 X 20 X 8	EBH302008	EBH302008	-----	-----	29
	30 X 20 X 10	EBH302010	EBH302010	-----	-----	32
	30 X 24 X 6	EBH302406	EBH302406	-----	-----	30
	30 X 24 X 8	EBH302408	EBH302408	-----	-----	33
	30 X 24 X 10	EBH302410	EBH302410	-----	-----	36
	30 X 24 X 12	EBH302412	EBH302412	-----	-----	39
	30 X 24 X 16	EBH302416	EBH302416	-----	-----	45
	30 X 24 X 20	EBH302420	EBH302420	-----	-----	51
	30 X 24 X 24	EBH302424	EBH302424	-----	-----	57
	30 X 30 X 8	EBH303008	EBH303008	-----	-----	39
	30 X 30 X 12	EBH303012	EBH303012	-----	-----	46
	30 X 36 X 8	EBH303608	EBH303608	-----	-----	46
	36 X 24 X 6	EBH362406	EBH362406	-----	-----	35
	36 X 24 X 8	EBH362408	EBH362408	-----	-----	29
	36 X 24 X 10	EBH362410	EBH362410	-----	-----	42



Our various pipe and fittings solutions have been manufactured to meet the needs of our customers and their applications. Contact the below Sales Center for more information:

- Plumbing Fittings Solutions
- Electrical Pipe & Fittings Solutions
- Municipal Pipe & Fittings Solutions





Sales & Distribution Center:

Royal Building Products
56400 Mound Road
Shelby Twp., MI 48316
T 1.800.232.5690
F 586.781.0888

royalbuildingproducts.com/plastic-trends

Printed 11.2012

ROYAL
Building Products

Pipe & Fittings Solutions | Municipal Plumbing Electrical

Liquid-Tight Conduit
Malleable Iron Connectors


Technical Specifications

- Heavy duty malleable iron.
- Zinc electroplated for corrosion resistance.
- Tapered threaded hub complete with nitrile “O” ring and steel locknut.



CI6103 (-IT) / CI6116 (-IT)


IT: with insulated throat.





CI6303 (-IT) / CI6316 (-IT)

IT: with insulated throat.





LT-450 / LT-453

Cat. No.	Trade Size	KO Size	Dimensions A	B	C
Straight Liquid–Tight Connectors (Malleable Iron)					
CI6103	3/8	1/2	1-1/8	1/2	1-1/2
CI6104	1/2	1/2	1-1/4	1/2	1-1/2
CI6106	3/4	3/4	1-1/2	9/16	1-3/4
CI6108	1	1	1 3/4	5/8	1-7/8
CI6110	1-1/4	1-1/4	2-1/4	11/16	2-3/16
CI6112	1-1/2	1-1/2	2-9/16	13/16	2-3/8
CI6116	2	2	3-1/16	15/16	2-7/8
Straight Insulated Liquid–Tight Connectors (Malleable Iron)					
CI6103-IT	3/8	1/2	1-1/8	1/2	1-9/16
CI6104-IT	1/2	1/2	1-1/4	1/2	1-9/16
CI6106-IT	3/4	3/4	1-1/2	9/16	1-13/16
CI6108-IT	1	1	1-3/4	5/8	1-15/16
CI6110-IT	1-1/4	1-1/4	2-1/4	11/16	2-1/4
CI6112-IT	1-1/2	1-1/2	2-9/16	13/16	2-7/16
CI6116-IT	2	2	3-1/16	15/16	2-15/16
90° Liquid–Tight Connectors (Malleable Iron)					
CI6303	3/8	1/2	1-1/8	1/2	1-5/8
CI6304	1/2	1/2	1-1/4	1/2	1-3/4
CI6306	3/4	3/4	1-1/2	9/16	2-1/16
CI6308	1	1	1-3/4	5/8	2-1/4
CI6310	1-1/4	1-1/4	2-1/4	11/16	2-3/4
CI6312	1-1/2	1-1/2	2-9/16	13/16	3-1/8
CI6316	2	2	3-1/16	15/16	3-3/8
90° Insulated Liquid–Tight Connectors (Malleable Iron)					
CI6303-IT	3/8	1/2	1-1/8	1/2	1-5/8
CI6304-IT	1/2	1/2	1-1/4	1/2	1-3/4
CI6306-IT	3/4	3/4	1-1/2	9/16	2-1/16
CI6308-IT	1	1	1-3/4	5/8	2-1/4
CI6310-IT	1-1/4	1-1/4	2-1/4	11/16	2-3/4
CI6312-IT	1-1/2	1-1/2	2-9/16	13/16	3-1/8
CI6316-IT	2	2	3-1/16	15/16	3-3/8
45° Liquid–Tight Connectors (Malleable Iron)					
LT-450	3/8	1/2	1-1/16	1/2	1-9/16
LT-451	1/2	1/2	1-3/16	1/2	1-5/8
LT-452	3/4	3/4	1-7/16	9/16	7/8
LT-453	1	1	1-3/4	5/8	2-1/8
45° Connectors – Insulated Throat (Malleable Iron)					
LT-950	3/8	1/2	1-1/16	1/2	1-9/16
LT-951	1/2	1/2	1-3/16	1/2	1-5/8
LT-952	3/4	3/4	1-7/16	9/16	1-7/8
LT-953	1	1	1-3/4	5/8	2-1/8


Liquid-Tight Conduit

Zinc Alloy Connectors



CI6603 (-IT) / CI6632 (-IT)


IT: with insulated throat.





CI6703 (-IT) / CI6716 (-IT)

IT: with insulated throat.



Technical Specifications

Cat. No.	Trade Size	KO Size	Dimensions A	B	C
Straight Liquid-Tight Connectors (Zinc Alloy)					
CI6603	3/8	1/2	1.58	0.53	1.18
CI6604	1/2	1/2	1.52	0.53	1.29
CI6606	3/4	3/4	1.69	0.53	1.57
CI6608	1	1	2.06	0.58	1.81
CI6610	1-1/4	1-1/4	2.06	0.61	2.18
CI6612	1-1/2	1-1/2	2.09	0.63	2.51
CI6616	2	2	2.15	0.63	3.03
CI6620	2-1/2	2-1/2	3.54	1.02	3.68
CI6624	3	3	4.05	1.07	4.38
CI6632	4	4	4.99	1.15	5.54
Straight Insulated Liquid-Tight Connectors (Zinc Alloy)					
CI6603-IT	3/8	1/2	1.66	0.63	1.18
CI6604-IT	1/2	1/2	1.62	0.63	1.29
CI6606-IT	3/4	3/4	1.79	0.63	1.57
CI6608-IT	1	1	2.16	0.68	1.81
CI6610-IT	1-1/4	1-1/4	2.16	0.71	2.18
CI6612-IT	1-1/2	1-1/2	2.19	0.73	2.51
CI6616-IT	2	2	2.25	0.73	3.03
CI6620-IT	2-1/2	2-1/2	3.64	1.12	3.68
CI6624-IT	3	3	4.15	1.17	4.38
CI6632-IT	4	4	5.09	1.25	5.54
90° Liquid-Tight Connectors (Zinc Alloy)					
CI6703	3/8	1/2	2.11	0.53	2.53
CI6704	1/2	1/2	2.24	0.53	2.46
CI6706	3/4	3/4	2.47	0.55	2.79
CI6708	1	1	3.46	0.58	3.86
CI6710	1-1/4	1-1/4	3.37	0.67	3.99
CI6712	1-1/2	1-1/2	4.28	0.61	5.04
CI6716	2	2	4.21	0.71	5.06
LT-297	2-1/2	2-1/2	4.32	0.88	3.65
LT-298	3	3	4.81	0.88	4.32
LT-2910	4	4	5.32	0.88	5.32
90° Insulated Liquid-Tight Connectors (Zinc Alloy)					
CI6703-IT	3/8	1/2	2.27	0.63	2.53
CI6704-IT	1/2	1/2	2.24	0.63	2.46
CI6706-IT	3/4	3/4	2.54	0.65	2.79
CI6708-IT	1	1	3.25	0.68	3.86
CI6710-IT	1-1/4	1-1/4	3.50	0.77	3.99
CI6712-IT	1-1/2	1-1/2	4.30	0.71	5.04
CI6716-IT	2	2	5.16	0.81	5.06
LT-897	2-1/2	2-1/2	4.32	0.88	3.65
LT-898	3	3	4.81	0.88	4.32
LT-8910	4	4	5.32	0.88	5.32

Tapered threaded hub complete with zinc die cast locknut.

Steel Core


Type LT




JIC

Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Reel Content* (m)	Cat. No.	Reel Content* (m)	Inside Bend Radius		Weight kg/30m
							in.	(mm)	
1/4	LT025-75	75	-	-	-	-	1.0	(25.4)	8
5/16	LT032-75	75	-	-	-	-	1.0	(25.4)	8
3/8	LT038-30	30	LT038-150	150	LT038-300	300	1.5	(38.1)	9
1/2	LT050-30	30	LT050-150	150	LT050-300	300	2.0	(50.8)	11
3/4	LT075-30	30	LT075-150	150	LT075-300	300	2.5	(63.5)	15
1	LT100-30	30	LT100-120	120	-		3.0	(76.2)	24
1-1/4	LT125-15	15	LT125-75	75	-	-	3.5	(88.9)	31
1-1/2	LT150-15	15	LT150-45	45	-	-	4.5	(114.3)	40
2	LT200-15	15	LT200-30	30	-		5.5	(139.7)	53
5	LT500-8	8	-	-	-	-	17.5	(444.5)	212
6	LT600-8	8	-	-	-	-	22.5	(571.5)	259

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail



Squarelock with Filler
5/16 in. - 2 in.



Interlock
2-1/2 in. - 6 in.

Type LT

A general purpose, flexible liquidtight steel conduit designed for a variety of installations requiring motion, vibration and bending. It offers good mechanical and moisture protection to enclosed conductors.

Construction

The flexible inner core is made from a spiral wound strip of corrosion resistant plating steel. The 1/4 through 2 inch trade sizes are squarelock formed and, with the exception of the 1/4 inch size, contain a nylon cord packing within the convolutions.

The larger sizes are constructed with a fully interlocked strip to add strength and to prevent unraveling.

A flexible yet durable PVC jacket is extruded over this core creating a liquidtight conduit resistant to most oils, acids and vapors present in industrial environments.

Refer to the Conduit — Chemical Resistance Chart beginning on p. G30.

Applications

This conduit is used extensively in the machine tool and other industrial environments where flexibility is necessary for installation and maintenance or where vibration and movement must be absorbed. The inherent sunlight resistance of PVC enables this product to be used in outdoor applications. Compatible with standard liquidtight fittings. The construction of this conduit conforms to, and is suitable for use with Sections 16 & 17.7 of the Electrical Standard for Industrial Machinery (ANSI/NFPA-79).

Working Temperatures

-20°C to 80°C

Listing / Certification

JIC — manufactured in accordance with the dimensions and specifications as outlined by the Joint Industrial Council Standard for Mass Production Equipment and Machine Tools.

Standard Colours

Machine tool grey and black. Other colours available upon request. Part numbers listed designate grey jacket.

Steel Core

Type LOR



Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Carton Content* (m)	Cat. No.	Carton Content* (m)	Inside Bend Radius		Wt. kg/30m
							in.	(mm)	
3/8	LOR038-30	30	LOR038-150	150	LOR038-300	300	2.0	(50.8)	19
1/2	LOR050-50	30	LOR050-150	150	LOR050-300	300	2.5	(63.5)	11
3/4	LOR075-30	30	LOR075-150	150	LOR075-300	300	3.0	(76.2)	15
1	LOR100-30	30	LOR100-120	120	-	-	4.0	(101.6)	24
1-1/4	LOR125-15	15	LOR125-60	60	-	-	4.5	(114.3)	31
1-1/2	LOR150-15	15	-	-	-	-	5.5	(139.7)	40
2	LOR200-15	15	-	-	-	-	7.0	(177.8)	53
2-1/2	LOR250-8	8	-	-	-	-	9.5	(241.3)	76
3	LOR300-8	8	-	-	-	-	11.5	(292.1)	118
3-1/2	LOR350-8	8	-	-	-	-	13.0	(330.2)	132
4	LOR400-8	8	-	-	-	-	14.0	(356.6)	156
5	LOR500-8	8	-	-	-	-	20.0	(508.0)	221
6	LOR600-8	8	-	-	-	-	22.5	(571.5)	259

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail

Type LOR

JIC

This product is offered as a non-UL oil-resistant conduit that incorporates a high quality PVC jacket.

Applications

The LOR is ideally used in situations where a UL listing or CSA certification is not a factor but where a flexible conduit must withstand exposure to many harsh chemicals, oils, UV, etc. This conduit conforms to Section 17.7 of the Electrical Standard for Industrial Machinery. (ANSI/NFPA-79) Compatible with Standard Liquidtight Fittings.

Working Temperatures

-20°C to 60°C intermitting to 90°C

Standard Colours

Machine tool grey and black. Other colours available upon request. Part numbers listed designate grey jacket.

Note

For a UL listed version, consult your Regional Sales Office for Type LA/LOR.

Type EF



Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Carton Content* (m)	Cat. No.	Carton Content* (m)	Inside Bend Radius		Wt. kg/30m
							in.	(mm)	
3/8	EF038-30	30	EF038-150	150	EF038-300	300	1.5	(38.1)	9
1/2	EF050-30	30	EF050-150	150	EF050-300	300	2.0	(50.8)	11
3/4	EF075-30	30	EF075-150	150	EF075-300	300	3.0	(63.5)	14
1	EF100-30	30	EF100-120	120	-	-	3.0	(76.2)	20
1-1/4	EF125-15	15	EF125-75	75	-	-	3.5	(88.9)	25
1-1/2	EF150-15	15	EF150-45	45	-	-	4.5	(114.3)	41
2	EF200-15	15	EF200-30	30	-	-	5.5	(139.7)	5

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail

Type EF

JIC

This flexible liquidtight conduit is a competitive grade version of our Type LT. It conforms to both the JIC standards for dimensions and general construction, and to Section 17.7 of the Electrical Standard for Industrial Machinery (ANSI/NFPA-79).

Construction

The flexible inner core is constructed from a helically formed strip of corrosion resistant steel. A liquidtight PVC jacket is then extruded over the core.

Applications

General installations requiring some movement and protection for contained conductors. Forms a liquidtight system when installed with standard fittings for use indoors or out.

Working Temperatures


-20°C to 80°C

Standard Colour

Machine tool grey


Steel Core

Type LA




Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Reel Content* (m)	Cat. No.	Reel Content* (m)	Inside Bend Radius		Weight kg/30m
							in.	(mm)	
3/8	LA038-30	30	LA038-150	150	LA038-300	300	2.0	(50.8)	13
1/2	LA050-30	30	LA050-150	150	LA050-300	300	3.0	(76.2)	15
3/4	LA075-30	30	LA075-150	150	LA075-300	300	4.2	(106.7)	24
1	LA100-30	30	LA100-120	120	-	-	5.5	(139.7)	37
1-1/4	LA125-15	15	LA125-60	60	-	-	7.0	(177.8)	46
1-1/2	LA150-15	15	LA150-45	45	-	-	4.5	(114.3)	47
2	LA200-15	15	LA200-30	30	-	-	6.0	(152.4)	66
2-1/2	LA250-8	8	LA250-80	80	-	-	8.0	(203.2)	87
3	LA300-8	8	LA300-50	50	-	-	10.0	(254.0)	114
3-1/2	LA350-8	8	LA350-50	50	-	-	11.0	(279.4)	140
4	LA400-8	8	LA400-30	30	-	-	12.0	(304.8)	154

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail



Squarelock with filler
3/8 in. - 1-1/4 in.



Interlock
1-1/2 in. - 4 in.

Type LA

A flexible liquidtight steel conduit which is both listed UL and certified CSA. It offers outstanding protection against wet, oily conditions and is permitted for use in exposed or concealed locations.

Construction

The flexible inner core is made from a spiral wound strip of heavy gauge, corrosion resistant, hot-dipped galvanized steel. The 3/8 through 1-1/4 inch trade sizes are square lock formed and include an integral bonding strip of copper that is enclosed within the convolutions throughout its entire length. The 1-1/2 through 4 inch trade sizes are designed with a fully interlocked strip.

The liquidtight jacketing material is of a high quality, rugged, flame retardant flexible PVC compound which resists oils, mild acids and exposure to sunlight. For further information, refer to the Conduit — Chemical Resistance chart beginning on p. G30.

Applications

This conduit is intended for installation with Rule 12-1300 of Canadian Electrical Code (CEC) Part I 2009.

The use of a separate bonding conductor is mandatory in accordance with CEC Rule 12-1306 for Ordinary locations.

The use of Liquidtight Flexible Conduit with sign and Outline Lighting are in accordance with CEC Rule 34-400 (2):

- Listed and marked for direct burial and in poured concrete
- For containment of 600-volt and lower potential circuits
- Sunlight resistant

Working Temperatures

-30 ºC to 80 ºC (dry) / 60 ºC (wet) and 70 ºC (oil)

Listing / Certification

Certified. Conforms to CSA 22.2 No. 56 for use per CEC C22.1 Section 12-1300.


Listed. Conforms to UL Standard ANSI/UL-360 for Liquidtight Flexible Steel Conduit.

Standard Colours

Machine tool grey, and black. Other colours available upon request. Blue is commonly used for computer room installations.
See TYPE CBLA on p. G8.

Steel Core

Type CBLA — Computer Blue



Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Reel Content* (m)	Cat. No.	Reel Content* (m)	Inside Bend Radius		Weight kg/30m
							in.	(mm)	
3/8	CBLA038-30	30	CBLA038-150	150	CBLA038-300	300	2.0	(50.8)	13
1/2	CBLA050-30	30	CBLA050-150	150	CBLA050-300	300	3.0	(76.2)	15
3/4	CBLA075-30	30	CBLA075-150	150	CBLA075-300	300	4.2	(106.7)	24
1	CBLA100-30	30	CBLA100-120	120	-	-	5.5	(139.7)	37
1-1/4	CBLA125-15	15	CBLA125-60	60	-	-	7.0	(177.8)	46
1-1/2	CBLA150-15	15	CBLA150-45	45	-	-	4.5	(114.3)	47
2	CBLA200-15	15	CBLA200-30	30	-	-	6.0	(152.4)	66
2-1/2	CBLA250-8	8	CBLA250-80	80	-	-	8.0	(203.2)	87
3	CBLA300-8	8	CBLA300-50	50	-	-	10.0	(254.0)	114
3-1/2	CBLA350-8	8	CBLA350-50	50	-	-	11.0	(279.4)	140
4	CBLA400-8	8	CBLA400-30	30	-	-	12.0	(304.8)	154

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail

Type CBLA

Computer Blue LA is a liquidtight flexible steel conduit commonly used for computer room installations. The blue jacket colour easily identifies circuitry for computer power wiring.

Construction

CBLA has a flexible inner core made from a spiral wound strip of heavy gauge, hot-dipped galvanized steel. The 3/8 through 1-1/4 inch trade sizes contain an integral bonding strip of copper. The 1-1/2 and larger sizes are designed with a fully interlocked strip.

The jacketing material is a rugged flame retardant flexible blue PVC. For installations which do not allow the use of PVC, see TYPE ZHLA on p. G12.

Applications

Listed and marked for direct burial and in poured concrete.

Working Temperatures

-20°C to 60°C

Listing / Certification

Certified. Conforms to CSA 22.2 No. 56 for use per CEC C22.1 Section 12-1300

Listed. Conforms to UL Standard ANSI/UL-360 for Liquidtight Flexible Steel Conduit

Steel Core

Type CSA



Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Reel Content* (m)	Cat. No.	Reel Content* (m)	Inside Bend Radius		Weight kg/30m
							in.	(mm)	
3/8	CSA038-30	30	CSA038-150	150	CSA038-300	300	2.0	(50.8)	11
2.8 1/2	CSA050-30	30	CSA050-150	150	CSA050-300	300	3.0	(76.2)	16
3/4	CSA075-15	15	-	-		-	-		
3/4	CSA075-30	30	CSA075-150	150	CSA075-300	300	4.0	(101.6)	24
1	CSA100-30	30	CSA100-120	-	-	-	5.0	(127.0)	27
1-1/4	CSA125-15	15	CSA125-60	60	-	-	6.2	(157.5)	39
1-1/2	CSA150-15	15	CSA150-45	45	-	-	4.5	(114.3)	55
2	CSA200-15	15	CSA200-30	30	-	-	6.0	(152.4)	70
2-1/2	CSA250-8	8	-	-	-	-	8.0	(203.2)	93
3	CSA300-8	8	-	-	-	-	10.0	(254.0)	120
4	CSA400-8	8	-	-	-	-	12.0	(304.8)	181

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail

Type CSA

This flexible liquidtight steel conduit is certified CSA. Its design and function is similar to that of type LA except that it cannot be used as a ground return path per CEC. It also offers a wider operating temperature range.

Construction

The flexible inner core is made from a spiral wound strip of heavy gauge, corrosion resistant, hot-dipped galvanized steel. The 3/8 through 1-1/4 inch trade sizes are cord packed.

The durable PVC flame retardant jacket is designed for good flexibility and impact resistance at low temperatures.

Applications

This conduit is intended for use according to CEC as described in section 12-1300 for dry, damp or wet locations where flexibility is necessary.

This conduit is intended for installation with Rule 12-1300 of Canadian Electrical Code (CEC) Part I 2009.

The use of a separate bonding conductor is mandatory in accordance with CEC Rule 12-1306 for Ordinary Locations.

The use of Liquidtight Flexible Conduit with sign and Outline Lighting are in accordance with CEC Rule 34-400 (2)

Working Temperatures

-40°C to 75°C

Listing / Certification

Certified. Conforms to CSA Standard C22.2, No. 56. Flame Test Rating FT-4 per CSA Standard C22.2, No. 0.3.

Standard Colour

Black

Steel Core

Type ATLA — All Temperature



Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Reel Content* (m)	Cat. No.	Reel Content* (m)	Inside Bend Radius		Weight kg/30m
							in.	(mm)	
3/8	ATLA038-30	30	ATLA038-150	150	ATLA038-300	300	2.0	(50.8)	13
1/2	ATLA050-30	30	ATLA050-150	150	ATLA050-300	300	3.0	(76.2)	15
3/4	ATLA075-30	30	ATLA075-150	150	ATLA075-300	300	4.2	(106.7)	24
1	ATLA100-30	30	ATLA100-120	120	-	-	5.5	(139.7)	37
1-1/4	ATLA125-15	15	ATLA125-60	60	-	-	7.0	(177.8)	46
1-1/2	ATLA150-15	15	ATLA150-45	45	-	-	4.5	(114.3)	47
2	ATLA200-15	15	ATLA200-30	30	-	-	6.0	(152.4)	66
2-1/2	ATLA250-8**	8	-	-	-	-	8.0	(203.2)	87
3	ATLA300-8**	8	-	-	-	-	10.0	(254.0)	114
3-1/2	ATLA350-8**	8	-	-	-	-	11.0	(279.4)	140
4	ATLA400-8**	8	-	-	-	-	12.0	(304.8)	154

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail
** CSA not applicable

Type ATLA

A liquidtight flexible steel conduit designed specifically for extreme hot or cold environments. The flexible inner core is identical to that found in Type LA. The specially formulated PVC jacket remains flexible at low temperatures and resists ageing at elevated temperatures. It is listed UL and certified CSA.

Construction

ATLA has a flexible inner core made from a spiral wound strip of heavy gauge, hot-dipped galvanized steel. The 3/8 through 1-1/4 inch trade sizes contain an integral bonding strip of copper. The 1-1/2 and larger sizes are designed with a fully interlocked strip.

The jacketing material is a rugged flame retardant flexible PVC resistant to weathering, UV, oils and many chemicals. Refer to the Conduit — Chemical Resistance Guide beginning on p. G30.

Applications

Designed to be used with high temperature machine tool wiring. Ideal for outdoor installations in cold
climates. This conduit is intended for installation with Rule 12-1300 of Canadian Electrical Code (CEC) Part I 2002.

The use of a separate bonding conductor is mandatory in accordance with CEC Rule 12-1306 for Ordinary locations.

The use of Liquidtight Flexible Conduit with sign and Outline Lighting are in accordance with CEC Rule 34-400 (2).

- Listed and marked for direct burial and in poured concrete
- For containment of 600-volt and lower potential circuits

Working Temperatures

-55°C to 105°C Air / 60°C Wet / 70°C Oil

Listing / Certification

Certified. Conforms to CSA 22.2 No. 56 for use per the CEC C22.1 Section 12-1300

Listed. Conforms to UL Standard ANSI/UL-360 for Liquidtight Flexible Steel Conduit

Conforms to the requirements of Section 16 & 17.7 of the ANSI/NFPA-79 Electrical Standard for Industrial Machinery.

Standard Colour

Machine tool grey

Steel Core

Type AT — High and Low Temperatures



Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Reel Content* (m)	Cat. No.	Reel Content* (m)	Inside Bend Radius		Weight kg/30m
							in.	(mm)	
3/8	AT038-30	30	AT038-150	150	AT038-300	300	1.5	(38.1)	9
1/2	AT050-30	30	AT050-150	150	AT050-300	300	2.0	(50.8)	11
3/4	AT075-30	30	AT075-150	150	AT075-300	300	2.5	(63.5)	15
1	AT100-30	30	AT100-120	120	-	-	3.0	(76.2)	24
1-1/4	AT125-15	15	AT125-60	60	-	-	3.5	(88.9)	31
1-1/2	AT150-15	15	AT150-45	45	-	-	4.5	(114.3)	40
2	AT200-15	15	AT200-30	30	-	-	5.5	(139.7)	53
2-1/2	AT250-8	8	-	-	-	-	8.0	(203.2)	76
3	AT300-8	8	-	-	-	-	10.0	(254.0)	118
3-1/2	AT350-8	8	-	-	-	-	11.0	(279.4)	132
4	AT400-8	8	-	-	-	-	12.0	(304.8)	156
5	AT500-8	8	-	-	-	-	17.5	(444.5)	221
6	AT600-8	8	-	-	-	-	22.5	(571.5)	259

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail

Type AT

A flexible steel conduit which uses a jacketing material specifically designed for hot or cold environments.

Applications

Type AT is well suited for exposure to extreme climatic conditions. It is also widely used on industrial process equipment such as annealing ovens, lumber kilns, foundries and refrigeration, etc. The construction of this conduit conforms to, and is suitable for use with Sections 16 and 17.7 of the Electrical Standard for Industrial Machinery (ANSI/NFPA-79). Uses standard liquidtight fittings.

Working Temperatures

-55°C to 105°C intermitting to 120°C

Standard Colour

Machine tool grey

Note

For a UL listed and CSA certified version, see TYPE ATLA on p. G10.

Type ATX — Extreme Temperature



Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Reel Content* (m)	Cat. No.	Reel Content* (m)	Inside Bend Radius		Weight kg/30m
							in.	(mm)	
3/8	ATX038-30	30	ATX038-150	150	ATX038-300	300	1.5	(38.1)	10
1/2	ATX050-30	30	ATX050-150	150	ATX050-300	300	2.0	(50.8)	12
3/4	ATX075-30	30	ATX075-150	150	ATX075-300	300	2.5	(63.5)	18
1	ATX100-30	30	ATX100-120	120	-	-	3.0	(76.2)	25
1-1/4	ATX125-15	15	ATX125-60	60	-	-	3.5	(88.9)	33
1-1/2	ATX150-15	15	ATX150-45	45	-	-	4.5	(114.3)	47
2	ATX200-15	15	ATX200-30	30	-	-	5.5	(139.7)	62
2-1/2	ATX250-8	8	-	-	-	-	8.0	(203.2)	85
3	ATX300-8	8	-	-	-	-	10.0	(254.0)	111
4	ATX400-8	8	-	-	-	-	12.0	(304.8)	151

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail

Type ATX

A conduit designed to withstand an extreme temperature range.

Construction

Utilizes the flexibility of our standard LT core, coupled with the advantage of a thermoplastic rubber jacket that is virtually unaffected by temperature extremes and contains no halogens. The material has a UL 94-HB flammability rating.

Applications

Used in situations where there are concerns of resistance to temperature exposure. These include heavy outdoor equipment, boilers and furnaces, etc. Refer to the Conduit — Chemical Resistance Guide beginning on p. G30.

Working Temperatures

-60°C to 150°C intermitting to 165°C

Standard Colour

Black

Steel Core

Type ZHLA — Non-Halogen, Low Smoke, Flame Retardant



Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Reel Content* (m)	Cat. No.	Reel Content* (m)	Inside Bend Radius		Weight kg/30m
							in.	(mm)	
3/8	ZHLA038-30	30	ZHLA038-150	150	ZHLA038-300	300	2.0	(50.8)	13
1/2	ZHLA050-30	30	ZHLA050-150	150	ZHLA050-300	300	3.0	(76.2)	15
3/4	ZHLA075-30	30	ZHLA075-150	150	ZHLA075-300	300	4.2	(106.7)	24
1	ZHLA100-30	30	ZHLA100-120	120	-	-	5.5	(139.7)	37
1-1/4	ZHLA125-15	15	ZHLA125-60	60	-	-	7.0	(177.8)	46
1-1/2	ZHLA150-15	15	ZHLA150-45	45	-	-	4.5	(114.3)	47
2	ZHLA200-15	15	ZHLA200-30	30	-	-	6.0	(152.4)	66
2-1/2	ZHLA250-8	8	-	-	-	-	8.0	(203.2)	87
3	ZHLA300-8	8	-	-	-	-	10.0	(254.0)	114
3-1/2	ZHLA350-8	8	-	-	-	-	11.0	(279.4)	140
4	ZHLA400-8	8	-	-	-	-	12.0	(304.8)	154

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail

Type ZHLA Combustion & Flammability Properties

Combustion & Flammability Properties**	Test	Value
-Vertical Burn (Material)	UL94	V-0 Rating
		No Flaming Drips
-Vertical Burn (Conduit)	UL360	Pass
		No Flaming Drips
-Oxygen Index %	D2863	28.5
-Flame Spread Index	ASTM E162	20;
		No Flaming Drips
-Flame Propagation	ASTM C542	Pass
	(NFPA-130)	No Flaming Drips
-Smoke Generation (Flaming)	ASTM E662	Ds 50 @ 1.5 min
	(NFPA 258)	Ds 102 @ 4.0 min
-Smoke Generation (Non-Flaming)	ASTM E662	Ds 5 @ 1.5 min
	(NFPA 258)	Ds 26 @ 4.0 min
-Toxic Gas Generation	BOMBARDIER SMP 800-C	Pass
-Toxicity Index	NES 713	3.9

**Test data is based on controlled laboratory conditions and does not necessarily reflect performance in actual fire conditions
Additional product information available upon request

Type ZHLA

Non-halogen, low smoke and low flame spread are what makes Type ZHLA a proven choice for applications where limiting toxic combustion materials is an important issue. Since ZHLA is also UL Listed, it is ideal for field installation in confined, public areas such as subways, tunnels, etc.

Construction

ZHLA has a flexible inner core made from a spiral wound strip of heavy gauge, hot-dipped galvanized steel. The 3/8 in. through 1-1/4 in. trade sizes contain an integral bonding strip of copper. The 1-1/2 in. and larger sizes are designed with a fully interlocked strip. The specially formulated thermoplastic black polyurethane jacket has excellent flame resistance and low smoke and toxicity generation characteristics. It is also resistant to ozone, hydrocarbons, moderate chemicals, oils and fuels. Refer to the Conduit — Chemical Resistance Guide beginning on p. G30.

Applications

There are many situations and areas where PVC is not allowed for electrical construction. The jacketing material used for ZHLA virtually eliminates the release of acidic gases found in PVC products.

- Meets the requirements of Bombardier SMP 800-C for Toxic Gas Generation
- Meets the requirements of both ASTM E162 for Flame Spread and ASTM E662 for Smoke Generation.
- Listed and marked for direct burial and in poured concrete.
- For containment of 600 V and lower potential circuits.
- Sunlight resistant

Working Temperatures

-40°C to 80°C Air / 60°C Wet / 70°C Oil

Listing / Certification

Certified. Conforms to CSA 22.2 No. 56 for use per the CEC C22.1 Section 12-1300

Listed. Conforms to UL Standard ANSI/ UL-360 for Liquidtight Flexible Steel Conduit

Standard Colour

Black

Steel Core

Type CEA — Non-Halogen, Low Smoke, Flame Retardant



Trade Size (in.)	Cat. No.	Carton Content* (m)	Cat. No.	Reel Content* (m)	Minimum Jacket Thickness	Inside Bend Radius		Weight kg/30m
						in.	(mm)	
3/8	CEA038-30	30	CEA038-150	150	300	1.5	(38.1)	9
1/2	CEA050-30	30	CEA050-150	150	300	2.0	(50.8)	11
3/4	CEA075-30	30	CEA075-150	150	300	2.5	(63.5)	15
1	CEA100-30	30	CEA100-120	120	-	3.0	(76.2)	24
1-1/4	CEA125-15	15	CEA125-60	60	-	3.5	(88.9)	31
1-1/2	CEA150-15	15	CEA150-45	45	-	4.5	(114.3)	40
2	CEA200-15	15	CEA200-30	30	-	5.5	(139.7)	53
2-1/2	CEA250-8	8	-	-	-	8.0	(203.2)	76
3	CEA300-8	8	-	-	-	10.0	(254.0)	118
3-1/2	CEA350-8	8	-	-	-	11.0	(279.4)	132
4	CEA400-8	8	-	-	-	12.0	(304.8)	156
5	CEA500-8**	8	-	-	2.5	17.5	(444.5)	212
6	CEA600-8**	8	-	-	2.5	22.5	(635.0)	259

See Chart on p. G28 for dimensions and tolerances
* See p. G27 for label and packaging detail
**Available on request
Type ACEA also available (liquidtight flexible aluminum conduit)
Aluminum core weighs approximately one third less than steel core

Type CEA Combustion & Flammability Properties

Combustion & Flammability Properties**	Test	Value
-Vertical Burn (Material)	UL94	V-0 Rating
		No Flaming Drips
-Vertical Burn (Conduit)	UL360	Pass
		No Flaming Drips
-Oxygen Index %	D2863	28.5
-Flame Spread Index	ASTM E162	20;
		No Flaming Drips
-Flame Propagation	ASTM C542	Pass
	(NFPA-130)	No Flaming Drips
-Smoke Generation (Flaming)	ASTM E662	Ds 50 @ 1.5 min
	(NFPA 258)	Ds 102 @ 4.0 min
-Smoke Generation (Non-Flaming)	ASTM E662	Ds 5 @ 1.5 min
	(NFPA 258)	Ds 26 @ 4.0 min
-Toxic Gas Generation	BOMBARDIER SMP 800-C	Pass
-Toxicity Index	NES 713	3.9

**Test data is based on controlled laboratory conditions and does not necessarily reflect performance in actual fire conditions
Additional product information available upon request

Type CEA

This liquidtight flexible steel conduit is designed for applications where safety concerns exist regarding a material's reaction in a fire situation.

Construction

The flexible inner core of this product is made from a galvanized steel strip. As in type LT, this core contains string packing between the helical convolutions in trade sizes 3/8 in. through 2 in. The specially formulated thermoplastic polyurethane jacket has excellent flame retardant characteristics as well as low smoke and toxicity generation characteristics. Acidic gases such as hydrogen chloride, hydrogen fluoride and hydrogen bromide are virtually eliminated as products of combustion.

Applications

This product is ideally suited for installation in confined or enclosed areas where construction materials must generate very little smoke, and have a low flame spread as well as low toxic gas emissions in the event of fire. Such applications include mass transit vehicles where CEA is extensively used for wiring harnesses within and under passenger rail cars. Other applications include use in underground subway structures and tunnels.

Working Temperatures

-40°C to 80°C

Standard Colours

Grey and black. Other colours available upon request. Part numbers listed designate grey jacket.

Steel Core

Type BR



Type BR

This non-jacketed flexible steel conduit has many universal wiring applications. It is often referred to as "Greenfield" or "Reduced Wall Flex".

Construction

Type BR is formed from high corrosion resistant hot-dipped galvanized steel. Its profile and helical shape allow it to withstand impact and crushing forces.

Applications

General Use: In accordance with CEC Rule 12-1002 (1) the flexible metal conduit is permitted in or on buildings of either combustible or non-combustible constructions.

Restriction and Exception:

CEC Rule 12-1004 (a) states:"12 (3/8) trade size flexible metal conduit shall be permitted to be used for runs of not more than 1.5 m (5 ft.) for the connection of equipment." and CEC Rule 12-1004 (b) states:"12 (3/8) trade size liquidtight flexible conduit may be used as permitted by this code."

Securements with straps:

CEC Rule 12-1010 (3) states: "When flexible metal conduit is installed, it shall be secured at intervals not exceeding 1.5 m (5 ft.) and within 300 mm (12 in.) on each side of every outlet box or fitting except where flexible metal conduit is fished and except for lengths of not over 900 mm (3 ft) at terminals where flexibility is necessary."

Conductor fill:

CEC Rule 12-1014 defines the maximum number of conductor, the CEC Tables 6 provides the maximum number of conductors of one size in trade sizes of conduit, CEC Table 8 provides the maximum allowable per cent conduit fill, and CEC Table 9 provides the cross-sectional areas of conduit.

Specific Use and applications:

Elevators, Hoistways, in accordance with CEC Rules 38-021 (1) (a) (1) and 38-021 (1) (a) (iv) Elevators, Cars, in accordance with CEC Rules 38-021 (1) (b) (v) Elevators, Within Machine Rooms, Control Rooms and Machinery Spaces and Control Spaces, in accordance with CEC Rule 38-021 (1) (c) (i) Elevators, Conterweights, in accordance with CEC Rule 38-021 (1) (d) Escalators, in accordance with CEC Rule 38-021 (2) Lifts for persons with physical disabilities, in accordance with CEC Rule 38-021 (3) Theater installation, in accordance with CEC Rule 44-102 (1)

Listing / Certification


Certified. (3/8 inch size only). Conforms to CSA 22.2 No. 56 for use per CEC C22.1 Section 12-1000. Meets Federal Specification WW-C-566c Type II

Listed. (sizes 3/8 through 3 in.). Conforms to UL Standard ANSI/UL-1 for Flexible Metal Conduit.

Flexible metal conduit is also permitted for use on industrial machinery where temperatures exceed the limits of liquidtight flexible conduit. (ANSI/NFPA-79) Section 16.3.4 (exception) and Section 17.9.

Trade Size (in.)	Cat. No.	Inner Diameter				Outer Diameter			
		min.		max.		min.		max.	
		in.	(mm)	in.	(mm)	in.	(mm)	in.	(mm)
3/8	BR038*	0.375	(9.5)	0.393	(10.0)	0.560	(14.2)	0.610	(15.5)
1/2	BR050	0.625	(15.9)	0.645	(16.4)	0.860	(21.8)	0.920	(23.4)
3/4	BR075	0.812	(20.6)	0.835	(21.2)	1.045	(26.5)	1.105	(28.1)
1	BR100	1.000	(25.4)	1.040	(26.4)	1.300	(33.0)	1.380	(35.1)
1-1/4	BR125	1.250	(31.8)	1.300	(33.0)	1.550	(39.4)	1.630	(41.4)
1-1/2	BR150	1.500	(38.1)	1.575	(40.0)	1.850	(47.0)	1.950	(49.5)
2	BR200	2.000	(50.8)	2.080	(52.8)	2.350	(59.7)	2.454	(62.3)
2-1/2	BR250	2.500	(63.5)	2.700	(68.6)	2.860	(72.6)	3.060	(77.7)
3	BR300	3.000	(76.2)	3.200	(81.3)	3.360	(85.3)	3.560	(90.4)
3-1/2	BR350	3.500	(88.9)	-	-	3.860	(98.0)	4.060	(103.1)
4	BR400	4.000	(101.6)	-	-	4.360	(110.7)	4.560	(115.8)

* CSA Certified



Types BR and ABR Strip Profile

Trade Size (in.)	Cat. No.	Coil Content (m)	Cat. No.	Coil Content (m)	Cat. No.	Coil Content (m)	Cat. No.	Coil Content (m)	Cat. No.	Coil Content (m)	Inside Bend Radius		Weight kg/30m
											(in.)	(mm)	
3/8	BR038-8*	8	BR038-15*	15	BR038-30*	30	BR038-75*	75	BR038-300*	300	2.0	(50.8)	18
1/2	BR050-8	8	BR050-15	15	BR050-30	30	-	-	BR050-300	300	3.0	(76.2)	13
3/4	BR075-8	8	BR075-15	15	BR075-30	30	-	-	BR075-150	150	4.0	(101.6)	15
1	-	-	BR100-15	15	-	-	-	-	BR100-120	120	5.0	(127.0)	24
1-1/4	-	-	BR125-15	15	-	-	-	-	BR125-120	120	6.2	(157.5)	29
1-1/2	-	-	BR150-8	8	-	-	-	-	BR150-90	90	7.5	(190.5)	36
2	-	-	BR200-8	8	-	-	-	-	BR200-45	45	10.0	(254.0)	45
2-1/2	-	-	BR250-8	8	-	-	-	-	-	-	12.5	(317.5)	68
3	-	-	BR300-8	8	-	-	-	-	-	-	15.0	(381.0)	82
3-1/2	-	-	BR350-8	8	-	-	-	-	-	-	17.5	(444.5)	100
4	-	-	BR400-8	8	-	-	-	-	-	-	20.0	(508.0)	122

* CSA Certified

Steel

Type SL



Trade Size		Cat. No.	Coil Content (m)	Inner Diameter				Outer Diameter				Min. Inside Bend Radius		Weight kg/30m
				min.		max.		min.		max.				
in.	(mm)			in.	(mm)	in.	(mm)	in.	(mm)	in.	(mm)	in.	(mm)	
-	-	SL316-75	75	0.172	(4.35)	0.202	(5.13)	0.280	(7.11)	0.310	(7.87)	0.75	(19.5)	2
-	-	SL140-75	75	0.235	(5.97)	0.265	(6.73)	0.328	(8.33)	0.358	(9.09)	0.75	(19.5)	3
5/16	-	SL516-75	75	0.297	(7.54)	0.327	(8.31)	0.391	(9.93)	0.421	(10.69)	0.75	(19.5)	3
-	-	SL380-75	75	0.360	(9.14)	0.390	(9.91)	0.485	(12.32)	0.515	(13.08)	1.00	(25.4)	4
-	-	SL716-75	75	0.422	(10.72)	0.452	(11.48)	0.547	(13.89)	0.577	(14.66)	1.00	(25.4)	4
3/8	16	SL038-75	75	0.492	(12.50)	0.512	(13.00)	0.617	(15.67)	0.637	(16.18)	1.00	(25.4)	5
-	-	SL916-45	45	0.547	(13.89)	0.577	(14.66)	0.672	(17.07)	0.702	(17.83)	1.25	(31.8)	5
1/2	-	SL050-45	45	0.622	(15.80)	0.642	(16.31)	0.747	(18.97)	0.767	(19.48)	1.50	(38.1)	7
-	20	SL050M-45	45	0.650	(16.51)	0.670	(17.01)	0.775	(19.69)	0.795	(20.19)	1.50	(38.1)	7
-	-	SL340-45	45	0.735	(18.67)	0.765	(19.43)	0.865	(21.97)	0.895	(22.73)	1.50	(38.1)	8
3/4	25	SL075-30	30	0.827	(21.00)	0.847	(21.51)	0.957	(24.31)	0.977	(24.82)	2.00	(50.8)	8
1	-	SL100-15	15	1.041	(26.44)	1.066	(27.07)	1.181	(30.00)	1.206	(30.63)	2.00	(50.8)	9
-	32	SL100M-15	15	1.102	(27.99)	1.122	(28.50)	1.242	(31.55)	1.262	(32.05)	2.00	(50.8)	-

Type SL


This “extra-flexible” product, available in the smaller diameters, is designed for tightspot installation and where continuous flexing is required of a steel wound hose.

Construction

Type SL is helically wound from a formed strip of Electrogalvanized steel. It is sized to be used with a variety of set-screw and clamp type fittings.

Applications

Offers good mechanical protection to wiring in a variety of O.E.M. applications



Squarelock

Type UG



Cat. No.	Coil Content (m)	Inside Diameter		Outer Diameter Min. Inside		Bend Radius		Wt. kg/30m
		Min.	Max.	Min.	Max.			
		in. (mm)	in. (mm)	in. (mm)	in. (mm)	in.	(mm)	
UG380-15	15	0.443(11.25)	0.473(12.01)	0.563(14.30)	0.593(15.06)	2.5	(63.5)	7
UG120-15	15	0.755(19.18)	0.785(19.94)	0.875(22.23)	0.905(22.99)	3.0	(76.2)	10
UG340-15	15	0.943(23.95)	0.973(24.71)	1.063(28.70)	1.093(27.76)	3.5	(89.0)	14
UG100-15	15	1.208(30.68)	1.238(31.45)	1.328(33.73)	1.358(34.50)	4.5	(114.3)	16
UG125-15	15	1.485(37.72)	1.515(38.48)	1.578(40.08)	1.608(40.84)	5.5	(139.7)	23
UG150-15	15	1.735(44.07)	1.765(44.83)	1.843(46.81)	1.873(47.57)	6.5	(165.1)	27
UG200-15	15	2.235(56.77)	2.265(57.53)	2.390(60.71)	2.420(61.47)	8.5	(216.0)	36
UG280-15	15	2.735(69.47)	2.765(70.23)	2.937(74.60)	2.967(75.36)	10.5	(267.0)	39
UG300-15	15	3.360(85.34)	3.390(86.11)	3.438(87.33)	3.468(88.09)	13.0	(330.2)	48

Note: Trade sizes do not apply to Type UG

Type UG


A fully-interlocked flexible steel conduit designed for high strength in “tight-spot” installations.

Construction

This conduit is manufactured from a bright tin plated steel strip which is fully interlocked at the edges to produce a strong, yet flexible product. The interlock feature does not allow the conduit to unravel if twisted and permits the conduit to retain its shape when bent. This lightweight product is compatible with many set-screw and clamp type fittings.

Applications

The bright appearance of the finished product lends itself to installations where the conduit may be visible after final assembly.




Interlock

Steel Core

Type USL



Cat. No.	Inner Dia.		Outer Dia.		Cat. No.	Coil Content (m)	Min. Inside Bend Radius		Wt. kg/30m
	Min.	Max.	Min.	Max.					
	in. (mm)	in. (mm)	in. (mm)	in. (mm)			in.	(mm)	
USL516	0.297(7.54)	0.327(8.30)	0.457(11.60)	0.487(12.37)	USL516-75	75	1.25	(31.75)	5
USL380	0.360(9.14)	0.390(9.91)	0.520(13.20)	0.550(13.97)	USL380-75	75	1.25	(31.75)	6
USL716	0.422(10.7)	0.452(11.48)	0.582(14.78)	0.612(15.54)	USL716-75	75	1.50	(38.10)	7
USL120	0.485(12.3)	0.515(13.08)	0.645(15.86)	0.675(17.15)	USL120-75	75	1.50	(38.10)	8
USL916	0.557(14.1)	0.577(14.65)	0.707(17.96)	0.737(18.72)	USL916-75	75	1.50	(38.10)	9



Squarelock — Type USL

Type USL

This extra-flexible steel conduit is recognized UL and CSA for use within listed and certified assemblies.

Construction

Helically formed from hot-dipped galvanized steel, type USL offers good corrosion resistance and provides excellent mechanical protection to enclosed circuits.

Applications

This product is intended as a factory installed component of various assemblies. Typical uses include modular office partitions, showcase lighting, range tops and other appliances. For component applications within Canada, ask for CSA Report #LO 4000-4875.

Listing / Certification


UL Recognized File #E53253

Type VJC — with PVC Jacket



Trade Size (in.)	Cat. No.	Carton Content* (m)	Outside Dia. Over Jacket				Internal Bend radius				Wt. kg/30m
			Min.		Max.		Min.		Max		
			in.	(mm)	in.	(mm)	in.	(mm)	in.	(mm)	
3/8	VJC038-30	30	0.647	(16.43)	0.677	(17.20)	1.0	(25.4)	5	(127.0)	5
1/2	VJC050-30	30	0.777	(19.74)	0.807	(20.50)	1.5	(38.1)	6	(152.4)	7
-	VJC050M-30	30	0.805	(20.45)	0.835	(21.21)	1.5	(38.1)	6	(152.4)	7
3/4	VJC075-30	30	0.987	(25.07)	1.017	(25.83)	2.0	(51.0)	10	(254.0)	9
1	VJC100-30	30	0.221	(5.61)	1.246	(31.65)	3.0	(76.0)	10	(254.0)	11
-	VJC100M-30	30	1.272	(32.31)	1.302	(33.07)	3.0	(76.0)	10	(254.0)	-

* Reels available, consult your Regional Sales Office



Type VJC

Vacuum jacketed steel conduit for high-flex installations

Construction

A unique vacuum extrusion process allows this product to have a thin PVC jacket which does not restrict the great flexibility characteristics of the inner core. The core material is the same as type SL. VJC is designed with dimensions that will accept standard liquid-tight fittings.

Applications

VJC is suitable for use in both static applications where a tight bend diameter is needed and in dynamic use such as machining centers and robotics.

Working Temperatures

-20°C to 80°C

Standard Colour

Black. Other colours available upon request. Consult your Regional Sales Office for details.

3F Condulet® Conduit Outlet Boxes With Covers

GUA Series

Cl. I, Div. 1 & 2, Groups B*, C, D
Cl. II, Div. 1, Groups E, F, G
Cl. II, Div. 2, Groups F, G
Cl. III
NEMA 3, 4, 7CD, 9EFG

Explosionproof
Dust-Ignitionproof
Raintight
Wet Locations

Applications:

GUA series conduit outlet boxes are installed within hazardous area conduit systems to:

- Protect conductors in threaded rigid conduit
- Act as pull and splice boxes
- Connect lengths of conduit
- Change conduit direction
- Provide access to conductors for maintenance and future system changes
- Act as mounting outlets for fixtures (with appropriate covers)
- Act as sealing fittings (with appropriate covers)

Features:

GUA conduit boxes have:

- Neoprene "O" ring standard to meet NEMA 4 requirements
- Cast ears on cover to permit easy removal and tightening
- Internal green ground screw
- Four standard mounting pads except for boxes with bottom hubs
- Threaded cover openings
- Ten different hub arrangements
- Taper threaded hubs to provide grounding continuity
- Smooth integral hub bushing protects conductor insulation when pulling
- Surface covers furnished with boxes
- Sealing covers, dome covers, and fixture hanger covers are available
- Cover threads are 12 pitch standard, 16 pitch on select aluminum shapes and sizes

Certifications and Compliances:

- NEC/CEC:
  - Class I, Division 1 & 2, Groups B*, C, D
  - Class II, Division 1, Groups E, F, G
  - Class II, Division 2, Groups F, G
  - Class III
- UL Standard: 1203
- ANSI Standard: C33.27
- CSA Standard: C22.2 No. 30
- NEMA/EEMAC 3, 4

Standard Materials:

- Bodies – *Feraloy* iron alloy
- Covers – Copper-free aluminum

Standard Finishes:

- *Feraloy* iron alloy – electrogalvanized and aluminum acrylic paint
- Aluminum – natural

Size Ranges:

- Hub – ½" to 2"
- Cover opening – 2" to 5" dia.

Options:

Description	Suffix
• Bodies – copper-free aluminum	**SA†**
• Covers – *Feraloy* iron alloy – electrogalvanized and aluminum acrylic paint	**WOD**
• GUA Form 6 (with 3" cover opening) are available with optional cover with viewing window	**VW**
• *Corro-free*™ epoxy powder coat	**S752**
• To order box less cover, add "0" to end of catalog number (i.e. GUAT260)	
• Factory installed terminal blocks mounted to DIN Rail (see page 53 for ordering information)	**DIN12-112**
• Factory installed terminal blocks directly mounted to outlet box (see page 53 for ordering information	**TB14-112**

When assembled with sealing type cover, GUA series outlet boxes provide adequate sealing for 40% fill in hazardous areas – Class I, Groups C, D; Class II, Groups E, F, G; and Class III. Seals can be made in either horizontal or vertical positions. Use *Chico*® "A" sealing compound or *Chico*® SpeedSeal only. Conductor splices or connections must not be made in enclosures where sealing compound is to be used per NEC.

GUA



Hub Size	Cover Opening Dia.	Cat. #
½	2	**GUA14**
¾	2	**GUA24**
½	3	**GUA16**
¾	3	**GUA26†***
1	3	**GUA36**
1¼	3⅝	**GUA47**
1½	5	**GUA59**

GUAC



Hub Size	Cover Opening Dia.	Cat. #
½	2	**GUAC14†**
¾	2	**GUAC24†**
½	3	**GUAC16†***
¾	3	**GUAC26†***
1	3	**GUAC36†***
1¼	3⅝	**GUAC47†**
1¼	5	**GUAC49†***
1½	5	**GUAC59†***
2	5	**GUAC69†***

3.1


†Available in copper-free aluminum, add suffix -SA.
*When ordered with suffix -SA are listed for Class I, Division 1 & 2, Groups B, C and D, Class II, Division 1, Groups E, F, G and Class III. Covers have 16 pitch threads. Replacement cover is a GUA06-GB.

GUAB




Hub Size	Cover Opening Dia.	Cat. #
½	2	**GUAB14†**
¾	2	**GUAB24**
½	3	**GUAB16†***
¾	3	**GUAB26†***
1	3	**GUAB36†***
1¼	3⅝	**GUAB47†**
1½	5	**GUAB59†***
2	5	**GUAB69†***

GUAD



Hub Size	Cover Opening Dia.	Cat. #
½	2	**GUAD14**
¾	2	**GUAD24**
½	3	**GUAD16**
¾	3	**GUAD26†**
1	3	**GUAD36†**
1¼	5	**GUAD49**

Dimensions
In Inches:



GUAB Only **All others**

GUA, GUAD, GUAM, GUAW, GUAX

Cat. #	a	b	c	d
14	2½	1 13/16	1¾	⅝
24	2½	2	2	¾
16	3½	2	1⅞	⅝
26	3½	2	1⅞	¾
36	3½	2 5/16	2 3/16	⅞
37	4¼	2 5/16	2⅜	⅞
47	4¼	2 11/16	2¾	1 3/32
49	5¾	3 13/16	3¾	1 3/32
59	5¾	3 13/16	3¾	1 9/32
69	5¾	4 1/16	4	1 9/16

Length of Hub Hub Size	Dimension "e" Length
½ - ¾	⅞
1 – 1¼	1
1½ – 2	1 1/16

 Copyright© 2015 Eaton's Crouse-Hinds Business

Crouse-Hinds by EATON

Condulet® Conduit Outlet Boxes With Covers

GUA Series

Cl. I, Div. 1 & 2, Groups B*, C, D
Cl. II, Div. 1, Groups E, F, G
Cl. II, Div. 2, Groups F, G
Cl. III
NEMA 3, 4, 7CD, 9EFG

Explosionproof
Dust-Ignitionproof
Raintight
Wet Locations

GUAL



Hub Size	Cover Opening Dia.	Cat. #
1/2	2	**GUAL14†**
3/4	2	**GUAL24†**
1/2	3	**GUAL16†***
3/4	3	**GUAL26†***
1	3	**GUAL36†***
1 1/4	3 5/8	**GUAL47†**
1 1/4	5	**GUAL49†***
1 1/2	5	**GUAL59†***
2	5	**GUAL69†***

GUAN



Hub Size	Cover Opening Dia.	Cat. #
1/2	2	**GUAN14**
3/4	2	**GUAN24**
1/2	3	**GUAN16**
3/4	3	**GUAN26**
1	3	**GUAN36**
1 1/4	3 5/8	**GUAN47**
1 1/2	5	**GUAN59**
2	5	**GUAN69**

GUAT



Hub Size	Cover Opening Dia.	Cat. #
1/2	2	**GUAT14†**
3/4	2	**GUAT24†**
1/2	3	**GUAT16†***
3/4	3	**GUAT26†***
1	3	**GUAT36†***
1	3 5/8	**GUAT37**
1 1/4	3 5/8	**GUAT47†**
1 1/4	5	**GUAT49†***
1 1/2	5	**GUAT59†***
2	5	**GUAT69†***

GUAX



Hub Size	Cover Opening Dia.	Cat. #
1/2	2	**GUAX14**
3/4	2	**GUAX24**
1/2	3	**GUAX16†***
3/4	3	**GUAX26†***
1	3	**GUAX36†***
1	3 5/8	**GUAX37†**
1 1/4	3 5/8	**GUAX47†**
1 1/4	5	**GUAX49†***
1 1/2	5	**GUAX59†***
2	5	**GUAX69†***

GUAM



Hub Size	Cover Opening Dia.	Cat. #
1/2	2	**GUAM14**
3/4	2	**GUAM24**
1/2	3	**GUAM16**
3/4	3	**GUAM26**
1	3	**GUAM36**
1 1/4	3 5/8	**GUAM47**
2	5	**GUAM69**

GUAW



Hub Size	Cover Opening Dia.	Cat. #
1/2	2	**GUAW14**
3/4	2	**GUAW24†**
1/2	3	**GUAW16**
3/4	3	**GUAW26†***

Dimensions

GUAC, GUAT

Cat. #	a	b	c	d
14	2 1/2	2 1/4	2 3/16	5/8
24	2 1/2	2	2	3/4
16	3 1/2	2	1 7/8	5/8
26	3 1/2	2	1 7/8	3/4
36	3 1/2	2 5/16	2 3/16	7/8
37	4 1/4	2 5/16	2 3/8	7/8
47	4 1/4	2 11/16	2 3/4	1 3/32
49	5 3/4	3 13/16	3 3/4	1 5/32
59	5 3/4	3 13/16	3 3/4	1 9/32
69	5 3/4	4 1/16	4	1 9/16

GUAN

Cat. #	a	b	c	d
14	2 1/2	2 1/8	2 1/16	5/8
24	2 1/2	2 5/16	2 1/4	3/4
16	3 1/2	2	1 7/8	3/4
26	3 1/2	2	1 7/8	3/4
36	3 1/2	2 5/16	2 3/8	7/8
47	4 1/4	2 11/16	2 3/4	1 3/32
59	5 3/4	4 1/16	4	1 9/32
69	5 3/4	4 1/16	4	1 9/16

GUAB, GUAL

Cat. #	a	b	c	d
14	2 1/2	2 1/4	2 3/16	5/8
24	2 1/2	2 1/2	2 7/16	3/4
16	3 1/2	2	1 7/8	5/8
26	3 1/2	2	1 7/8	3/4
36	3 1/2	2 5/16	2 3/16	7/8
47	4 1/4	2 11/16	2 3/4	1 3/32
49	5 3/4	3 13/16	3 3/4	1 5/32
59	5 3/4	3 13/16	3 3/4	1 9/32
69	5 3/4	4 1/16	4	1 9/16

†Available in copper-free aluminum, add suffix -SA.
*When ordered with suffix -SA are listed for Class I, Division 1 & 2, Groups B, C and D, Class II, Division 1, Groups E, F, G and Class III. Covers have 16 pitch threads. Replacement cover is a GUA06-GB.

www.crouse-hinds.com US: 1-866-764-5454 CAN: 1-800-265-0502 Copyright© 2015 Eaton's Crouse-Hinds Business

For GUA Condulet® Conduit Outlet Boxes

Applications:

Threaded covers, canopies and extensions are used:

- To provide a seal in hazardous areas (sealing cover). See note below.
- To mount pendant lighting fixtures such as EVA listed in lighting section (fixture canopy)
- To mount EVA pendant lighting fixtures on cover which is then screwed into outlet box without twisting conductors (union hub cover)
- To mount pendant lighting fixtures on cover which is then screwed into outlet box as above, for wiring after fixture stem is installed (nipple cover)
- To provide means of increasing outlet box depth (threaded extension)

Features:

- Surface covers are supplied with GUA boxes
- Sealing cover has removable plug for filling enclosure with sealing compound after installation. Sealing cover meets 40% fill requirement of the NEC®. See note below.
- Fixture canopy has a threaded cover in its side to provide access for making splices or taps. Fixture with its conduit stem and canopy can be assembled and wired before installation and conductors can be spliced in canopy after it has been screwed into the body
- Cover threads are 12 pitch.

Standard Materials:

- Surface and dome covers, union hub covers, nipple covers – copper-free aluminum
- Sealing covers, fixture canopies, threaded extensions – *Feraloy*® iron alloy

Standard Finishes:

- Aluminum – natural
- *Feraloy* iron alloy – electrogalvanized and aluminum acrylic paint

Options:

Description	Suffix
Corro-free™ epoxy powder coat	**S752**
To order an iron surface cover	**WOD**

Size Ranges:

- Fixture stems – ¾"
- Body openings – 2" to 5"

Note: Depth of sealing compound in body must satisfy requirements of NEC section 501.15(C)(3). Splices and taps in sealing fittings are prohibited by NEC.

GUA Threaded Extension



Cover Opening Dia.	Ext. Depth	Cat. #
3	1¼	**GUA0631**

GUA Cover Opening	Replacement O-Ring Gasket Cat. #
2"	**GASK1713**
3"	**GASK1151**
3⅝"	**GASK1589**
5"	**GASK925**

Surface Cover



Cover Opening Dia.	Thread Pitch	Cat. #
2	12	**GUA04**
3	12	**GUA06**
3	16	**GUA06 GB***
3⅝	12	**GUA07**
5	12	**GUA09**
5	16	**GUA09 GB***

Dome Cover



Cover Opening Dia.	Ext. Depth	Thread Pitch	Cat. #
2	2	12	**GUA047**
3	2	12	**GUA067**
3⅝	2	12	**GUA077**
3⅝	4	12	**GUA0716**
5	4	12	**GUA514**
5	10	12	**GUA5110**

Sealing Cover



Cover Opening Dia.	Thread Pitch	Cat. #
2	12	**GUA041**
3	12	**GUA062**
3	16	**GUA062 GB***
3⅝	12	**GUA072**
5	12	**GUA092**

Nipple Cover



Cover Opening Dia.	Fixt. Stem Size	Thread Pitch	Cat. #
3	¾	12	**GUA0672**

Fixture Cover
Union Hub Type



Cover Opening Dia.	Fixt. Stem Size	Thread Pitch	Cat. #
3	¾	12	**GUA0687**

Fixture Canopy



Cover Opening Dia.	Fixt. Stem Size	Thread Pitch	Cat. #
3	¾	12	**GUA068**

†Also used with GUP bodies see page 753 or GU and GUE bodies see page 722.
GUA covers with suffix "GB" are used with Group B rated GUA aluminum bodies identified with symbols † on pages 50-51.

 Copyright© 2015 Eaton's Crouse-Hinds Business


Factory Installed Terminal Block Ordering Guide

For GUA Condulet® Conduit Outlet Boxes

DIN Rail Mounted Terminal Blocks:

Electrical Specifications:
30 Amp, 150V, AWG 26-10


Cat. #	Description
DIN12	DIN Rail Mounted, 2 Terminal Blocks GUA (Shapes C, L, N, T, X) Form 4 & 6 Cover Dia. Openings
DIN13	DIN Rail Mounted, 3 Terminal Blocks GUA (Shapes C, L, N, T, X) Form 4 & 6 Cover Dia. Openings
DIN14	DIN Rail Mounted, 4 Terminal Blocks GUA (Shapes C, L, N, T, X) Form 6, 7 & 9 Cover Dia. Openings
DIN16	DIN Rail Mounted, 6 Terminal Blocks GUA (Shapes C, L, N, T, X) Form 7 & 9 Cover Dia. Openings
DIN18	DIN Rail Mounted, 8 Terminal Blocks GUA (Shapes C, L, N, T, X) Form 7 & 9 Cover Dia. Opening
DIN 112	DIN Rail Mounted, 12 Terminal Blocks GUA (Shapes C, L, T, X) Form 9 Cover Dia. Opening



Direct Mounted Terminal Blocks:

Electrical Specifications:
30 Amp, 300V, AWG 26-10

Cat. #	Description
TB14	Direct Mounted Terminal Block, 4 Poles GUA (Shapes C, L, T, X) Form 6, 7 & 9 Cover Dia. Openings
TB16	Direct Mounted Terminal Block, 6 Poles GUA (Shapes C, L, T, X) Form 6, 7 & 9 Cover Dia. Openings
TB18	Direct Mounted Terminal Block, 4 Poles (8 Total) GUA (Shapes C, L, T, X) Form 7 & 9 Cover Dia. Opening
TB112	Direct Mounted Terminal Block, 12 Poles GUA (Shapes C, L, T, X) Form 9 Cover Dia. Opening



www.crouse-hinds.com US: 1-866-764-5454 CAN: 1-800-265-0502 Copyright© 2015 Eaton's Crouse-Hinds Business



Spec-Kon®

Overview M2
Catalog Numbering System M2
Terminals
Features and Benefits M3
Performance Requirements M4
Ring Terminals M5-M7
Multiple Stud Ring Terminals M8-M9
Large Ring Terminals M10-M12
Fork Terminals M13-M15
Locking Fork Terminals M16-M17
Flanged Fork Terminals M18-M19
Blade Terminals M20
Pin Terminals M21
Disconnects
Features and Benefits M22
Design Features M22
Performance Requirements M22
Female Disconnects 23-24
Male Disconnects M25
Piggy Back Disconnects M26
Fully Insulated Female Disconnects M27-M28
Fully Insulated Male Disconnects M28
Insulated Female Flag Disconnects M29
Insulated Barrel Flag Female Disconnects M29
Bullet Receptacles M30
Bullet Disconnects M31
Splices, Wire Joints and Quick Splices
Features and Benefits M32
Butt Splices M33-M34
Wire Joints M34
Quick Splices M34
Installation Tools
Hand Tools M35-M37
Automated Tools M38-M39
Power Operated Tools M40-M41
Application Information
Tool & Die Selection Chart M42
Strip Length Chart M42
Stud Size Chart M43
Common Conductor Size Chart M43

M

Thomas&Betts



Crimp Terminals, Disconnects, and Splices

Thomas & Betts is pleased to introduce Spec-Kon® crimp terminals, disconnects, and splices. Ideal for OEM applications, the Spec-Kon® line can be used anywhere a high number of terminations are required every day, such as the wiring harness, panelboard, telecommunications, and automotive industries.

The Spec-Kon® terminal offering includes:

- A broad selection of bulk-packaged loose piece terminals in non-insulated and insulated varieties, including male and female disconnects, rings, forks, pins, blades, butt splices, wire joints and bullet connectors.
- Terminals on mylar tape for automated applications, including the new KT-2500 power tool for frequent, repeated crimps.
- The ERG-2500 ergonomic hand tool, which crimps all sizes of insulated barrel-style Spec-Kon® wire termination products.

Catalog Numbering System

Example: KV18-6R-M


K	V	18	6	R	M
Product	**Terminal and Insulation**	**Wire Size Range**	**Feature Size**	**Terminal Type**	**Box Quantity**
Thomas & Betts Spec-Kon® Terminals	(Blank) Bare Non-Insulated (V) Vinyl Funnel Entry (N) Nylon Funnel Entry (VF) Vinyl Fully Insulated (NF) Nylon Fully Insulated	(18) 22-16 AWG (14) 16-14 AWG (10) 12-10 AWG (8) 8 AWG (6) 6 AWG (4) 4 AWG (2) 2 AWG	**Bolt Hole:** Ring and Fork Terminals **Tab Width:** (250 Series) Disconnects **Pin Length:** Pin Terminals **Blade Length:** Blade Terminals **Diameter:** Bullets	(R) Ring (MS) Multiple Stud Ring (F) Fork (LF) Locking Fork (FF) Flanged Fork (PT) Pin Terminal (BL) Blade Terminal (MD) Male Disconnect (FD) Female Disconnect (FFD) Female Flag Disconnect (PD) Piggy Back Disconnect (FB) Female Bullet (MB) Male Bullet (BS) Butt Splice (QS) Quick Splice (WJ) Wire Joint (Closed End) (BFD) Barrel Flag Disconnect	(C) = 100 (CC) = 200 (W) = 250 (D) = 500 (M) = 1,000 (T) = Mylar Tape* * Please contact Customer Service for pricing and availability.

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. www.tnb.com




Features and Benefits of Spec-Kon® Terminals

- *Internal barrel serrations*—During crimping, the wire will cold flow into serrations, giving lower resistance connections and improving tensile strength.
- *Size marking*—Wire range is stamped on the tongue (metric and English) for easy access to the terminal size without drawings/packaging.
- *Electro tin plating*—Provides excellent corrosion resistance, superior finish for better-looking installation.
- *Ergonomic hand tool*—Ergonomically designed ERG-2500 completes a UL listed crimp while requiring substantially lower handle forces.
- *One tool for all insulated products*—Thomas & Betts offers a single tool that crimps the entire range of standard insulated terminals, disconnects, and butt splices. Many competitors require 2 to 4 tools to cover the same range.
- *Color coding*—Insulators are color coded for specific wire size (red=22-16AWG, blue=16-14AWG, yellow=12-10AWG). Red=8AWG, blue=6AWG.




Nylon Insulated Terminals

- *Sleeved barrel*—Ensures barrel does not separate during crimping.
- *Molded insulators*—Molded insulators ensure consistent shape and quality, shaped entry speeds installation and reduces wire hang up.
- *Metal insulation sleeve*—Sleeve crimps wire insulation, providing high-vibration resistance and conductor strain relief.
- *Nylon material*—Ideal for harsh environments. Provides excellent chemical, impact and abrasion resistance.
- *Ratings*—UL Listed, cULus Listed, CSA, 600 V at 105ºC.



Vinyl Insulated Terminals

- *Brazed seam*—Ensures barrel does not separate during crimping.
- *Molded funnel entry insulators*—Funnel entry speeds installation and reduces wire hang up. Molded insulators ensure consistent shape and quality every time.
- *Insulation crimp*—The insulator mouth is flared to speed installation and accommodate thicker insulated wires. Also, provides insulation support strain relief in high-vibration applications.
- *Vinyl material*—Economical, moisture resistant and flame retardant (UL94V-0)
- *Ratings*—UL Listed, cULus Listed, CSA, 600 V at 105ºC.




Non-Insulated Terminals


- *Brazed seam*—Ensures barrel does not separate during crimping.
- *Chamfered barrel entry*—Smoothing the barrel entry edge facilitates wire insertion.
- *Ratings*—UL Listed, cULus Listed, CSA, 2000 V.

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.


Design Features of Spec-Kon® Terminals




Rings
Provides the most secure and reliable connection available




Multiple-Stud Rings
Special tongue style that accommodates 3 stud sizes with one terminal




Pins
Standard insulation-style terminals for use on DIN-style/metric terminal blocks




Blades
Standard insulation-style terminals for use on DIN-style/metric terminal blocks



Forks
Fast and easy to install without removing the terminal block screw



Locking Forks
Offers the secure connection of a ring terminal with the fast and easy installation of a fork terminal



Flanged Forks
Turned-up toes provide secure connections in high-vibration applications

Performance Requirements

Description	Wire Size (AWG)										
	#22	#20	#18	#16	#14	#12	#10	#8	#6	#4	#2
U.L. 486A (Terminals)											
Test Current for Max. 50˚C Rise (Amps)	9	12	17	18	30	35	50	70	95	125	70
Min. Tensile Strength* (Lbs.)	8	13	20	30	50	70	80	90	100	140	180

*** Pull-out force of the crimped terminal.**

Applicable Spec-Kon® products meet or exceed the following test specifications:

- UL486A (Terminals)
- CSA
- UL486C (Splices)

UL listed products are shown with the applicable logos in the product section.


UL file #E9809 (Terminals).

CSA file #LR4503

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**



- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry



Nylon Insulated Ring Terminals

Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
KN18-6R-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.260 6.6	.248 6.3	.803 20.4	.433 11.0	.177 4.5	.067 1.7	.030 0.75
KN18-8R-M		#8	.169 4.3	.260 6.6	.248 6.3	.803 20.4				
KN18-10R-M		#10	.209 5.3	.315 8.0	.276 7.0	.858 21.8				
KN18-14R-M		1/4	.252 6.4	.457 11.6	.433 11.0	1.094 27.8				
KN18-516R-M		5/16	.331 8.4	.457 11.6	.433 11.0	1.094 27.8				
KN14-6R-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.260 6.6	.248 6.3	.8.3 20.4	.433 11.0	.205 5.2	.091 2.3	.031 0.8
KN14-8R-M		#8	.169 4.3	.260 6.6	.248 6.3	.803 20.4				
KN14-10R-M		#10	.209 5.3	.335 8.5	.307 7.8	.898 22.8				
KN14-14R-M		1/4	.252 6.4	.472 12.0	.433 11.0	1.094 27.8				
KN14-516R-M		5/16	.331 8.4	.472 12.0	.433 11.0	1.094 27.8				
KN14-38R-M		3/8	.413 10.5	.535 13.6	.547 13.9	1.240 31.5				
KN10-6R-D	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.283 7.2	.240 6.1	.894 22.7	.512 13.0	.276 7.0	.134 3.4	.039 1.0
KN10-8R-D		#8	.169 4.3	.283 7.2	.240 6.1	.894 22.7				
KN10-10R-D		#10	.209 5.3	.374 9.5	.358 9.1	1.047 26.6				
KN10-14R-D		1/4	.252 6.4	.472 12.0	.413 10.5	1.164 29.5				
KN10-516R-D		5/16	.331 8.4	.591 15.0	.531 13.5	1.339 34.0				
KN10-38R-D		3/8	.413 10.5	.591 15.0	.531 13.5	1.339 34.0				
KN10-12R-D		1/2	.512 13.0	.756 19.2	.630 16.0	1.520 38.6				

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KN18-6R-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Tools used with Nylon Insulated Ring Terminals



ERG2500




KT-2500

For complete information regarding tools and the new Universal Applicator, see pages M35-M41.

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



- Molded Funnel Entry Insulator
- Brazed Seam
- Internal Barrel Serrations



Vinyl Insulated Ring Terminals

Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
KV18-6R-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.260 6.6	.248 6.3	.803 20.4	.433 11.0	.157 4.0	.067 1.7	.030 0.75
KV18-8R-M		#8	.169 4.3	.260 6.6	.248 6.3	.803 20.4				
KV18-10R-M		#10	.209 5.3	.315 8.0	.276 7.0	.858 21.8				
KV18-14R-M		1/4	.252 6.4	.457 11.6	.433 11.0	1.094 27.8				
KV18-516R-M		5/16	.331 8.4	.457 11.6	.433 11.0	1.094 27.8				
KV18-38R-M		3/8	.413 10.5	.835 13.6	.547 13.9	1.240 31.5				
KV14-6R-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.260 6.6	.248 6.3	.803 20.4	.433 11.0	.177 4.5	.091 2.3	.031 0.8
KV14-8R-M		#8	.169 4.3	.260 6.6	.248 6.3	.803 20.4				
KV14-10R-M		#10	.209 5.3	.335 8.5	.307 7.8	.898 22.8				
KV14-14R-M		1/4	.252 6.4	.472 12.0	.433 11.0	1.094 27.8				
KV14-516R-M		5/16	.331 8.4	.472 12.0	.433 11.0	1.094 27.8				
KV14-38R-M		3/8	.413 10.5	.535 13.6	.547 13.9	1.240 31.5				
KV10-6R-D	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.283 7.2	.240 6.1	.894 22.7	.512 13.0	.252 6.4	.134 3.4	.039 1.0
KV10-8R-D		#8	.169 4.3	.283 7.2	.240 6.1	.894 22.7				
KV10-10R-D		#10	.209 5.3	.374 9.5	.358 9.1	1.047 26.6				
KV10-14R-D		1/4	.252 6.4	.472 12.0	.413 10.5	1.161 29.5				
KV10-516R-D		5/16	.331 8.4	.591 15.0	.531 13.5	1.339 34.0				
KV10-38R-D		3/8	.413 10.5	.591 15.0	.531 13.5	1.339 34.0				
KV10-12R-D		1/2	.512 13.0	.756 19.2	.630 16.0	1.520 38.6				

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KV18-6R-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Tools used with Vinyl Insulated Ring Terminals



ERG2500



KT-2500


Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**

Non-Insulated Ring Terminals



- Chamfered Barrel
- Brazed Seam
- Internal Barrel Serrations



Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
K18-6R-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.260 6.6	.248 6.3	.567 14.4	.189 4.8	.134 3.4	.067 1.7	.030 0.75
K18-8R-M		#8	.169 4.3	.260 6.6	.248 6.3	.567 14.4				
K18-10R-M		#10	.209 5.3	.315 8.0	.276 7.0	.622 15.8				
K18-14R-M		1/4	.252 6.4	.457 11.6	.433 11.0	.858 21.8				
K18-516R-M		5/16	.331 8.4	.457 11.6	.433 11.0	.858 21.8				
K14-6R-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.260 6.6	.248 6.3	.567 14.4	.189 4.8	.161 4.1	.091 2.3	.031 0.8
K14-8R-M		#8	.169 4.3	.260 6.6	.248 6.3	.567 14.4				
K14-10R-M		#10	.209 5.3	.335 8.5	.307 7.8	.661 16.8				
K14-14R-M		1/4	.252 6.4	.472 12.0	.433 11.0	.858 21.8				
K14-516R-M		5/16	.331 8.4	.472 12.0	.433 11.0	.858 21.8				
K14-38R-M		3/8	.413 10.5	.535 13.6	.547 13.9	1.004 25.5				
K10-6R-M	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.283 7.2	.240 6.1	.618 15.7	.236 6.0	.220 5.6	.134 3.4	.039 1.0
K10-8R-M		#8	.169 4.3	.283 7.2	.240 6.1	.618 15.7				
K10-10R-M		#10	.209 5.3	.374 9.5	.358 9.1	.772 19.6				
K10-14R-M		1/4	.252 6.4	.472 12.0	.413 10.5	.886 22.5				
K10-516R-M		5/16	.331 8.4	.591 15.0	.531 13.5	1.063 27.0				
K10-38R-M		3/8	.413 10.5	.591 15.0	.531 13.5	1.063 27.0				
K10-12R-D		1/2	.512 13.0	.756 19.2	.630 16.0	1.244 31.6				

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: K18-6R-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Terminal Material: Copper

Tools used with Non-Insulated Ring Terminals



ERG2002



KT-2500

Thomas&Betts


© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**

Nylon Insulated Multiple Stud Ring Terminals



Catalog Number	Wire Range	Bolt Size	Dimension inch mm						
			W	F	L	E	D	d1	T
KN18-610MS-M	22-16 A.W.G. 0.5-1.5 mm²	#6 - #10	.339 8.6	.311 7.9	.996 25.3	.433 11.0	.177 4.5	.067 1.7	.030 0.75
KN14-610MS-M	16-14 A.W.G. 1.5-2.5 mm²	#6 - #10	.339 8.6	.311 7.9	.996 25.3	.433 11.0	.205 5.2	.091 2.3	.031 0.8
KN10-610MS-D	12-10 A.W.G. 4-6 mm²	#6 - #10	.390 9.9	.350 8.9	1.154 29.3	.512 13.0	.276 7.0	.134 3.4	.039 1.0

- Single terminal for 6, 8, and 10 stud sizes
- Molded Insulator
- Metal Insulation Sleeve
- Funnel Entry



Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KN18-610MS-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.


Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Vinyl Insulated Multiple Stud Ring Terminals



Catalog Number	Wire Range	Bolt Size	Dimension inch mm						
			W	F	L	E	D	d1	T
KV18-610MS-M	22-16 A.W.G. 0.5-1.5 mm²	#6 - #10	.339 8.6	.311 7.9	.996 25.3	.433 11.0	.157 4.0	.067 1.7	.030 0.75
KV14-610MS-M	16-14 A.W.G. 1.5-2.5 mm²	#6 - #10	.339 8.6	.311 7.9	.996 25.3	.433 11.0	.177 4.5	.091 2.3	.031 0.8
KV10-610MS-D	12-10 A.W.G. 4-6 mm²	#6 - #10	.390 9.9	.350 8.9	1.154 29.3	.512 13.0	.252 6.4	.134 3.4	.039 1.0

- Single terminal for 6, 8, and 10 stud sizes
- Molded Funnel Entry Insulator
- Brazed Seam



Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KV18-610MS-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Tools used with Nylon and Vinyl Insulated Multiple Stud Ring Terminals



ERG2500



KT-2500

Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. www.tnb.com



Non-Insulated Multiple Stud Ring Terminals


Catalog Number	Wire Range	Bolt Size	Dimension inch mm						
			W	F	L	E	D	d1	T
K18-610MS-M	22-16 A.W.G. 0.5-1.5 mm²	#6 - #10	.339 8.6	.311 7.9	.768 19.5	.189 4.8	.134 3.4	.067 1.7	.030 0.75
K14-610MS-M	16-14 A.W.G. 1.5-2.5 mm²	#6 - #10	.339 8.6	.311 7.9	.768 19.5	.189 4.8	.161 4.1	.091 2.3	.031 0.8
K10-610MS-M	12-10 A.W.G. 4-6 mm²	#6 - #10	.390 9.9	.350 8.9	.886 22.5	.236 6.0	.220 5.6	.134 3.4	.039 1.0

- Single terminal for 6, 8, and 10 stud sizes
- Brazed Seam
- Chamfered Barrel
- Internal Barrel Serrations

Box Quantity: (M)=1000
For Mylar Tape replace box quantity with (T). Example: K18-610MS-T
UL File #E9809
CSA File #LR4503

Terminal Material: Copper

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.



Tools used with Non-Insulated Multiple Stud Ring Terminals



ERG2002




KT-2500

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



- Brazed Seam
- Molded Funnel Entry Insulator
- Internal Barrel Serrations



Nylon Insulated Large Ring Terminals

Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
KN8-8R-D	8 A.W.G. 8 mm²	#8	.169 4.3	.315 8.0	.366 9.3	1.142 29.0	.630 16.0	.315 8.0	.177 4.5	.047 1.2
KN8-10R-D		#10	.209 5.3	.364 8.8	.429 10.9	1.232 31.3				
KN8-14R-D		1/4	.252 6.4	.472 12.0	.366 9.3	1.232 31.3				
KN8-516R-D		5/16	.331 8.4	.591 15.0	.543 13.8	1.469 37.3				
KN8-38R-D		3/8	.413 10.5	.591 15.0	.543 13.8	1.469 37.3				
KN8-12R-D		1/2	.512 13.0	.787 20.0	.591 15.0	1.614 41.0				
KN6-10R-W	6 A.W.G. 14 mm²	#10	.209 5.3	.472 12.0	.524 13.3	1.606 40.8	.846 21.5	.433 11.0	.228 5.8	.059 1.5
KN6-14R-W		1/4	.252 6.4							
KN6-516R-W		5/16	.331 8.4	.630 16.0	.559 14.2	1.713 43.5				
KN6-38R-W		3/8	.413 10.5							
KN6-12R-W		1/2	.512 13.0	.866 22.0	.780 19.8	2.047 52.0				

Box Quantity: (W)=250; (D)=500
For mylar tape, replace box quantity with (T). Example: KN8-8R-T.

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

#8 AWG on mylar tape is UL Listed.
#6 AWG on mylar tape is UL Listed.

UL File #E9809
CSA File #LR4503

M
Spec-Kon®

Tools used with Nylon Insulated Large Ring Terminals



TBM6S

For tooling information for nylon insulated large ring terminals, see page M37.



KT-2500


© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



- Brazed Seam
- Chamfered Barrel
- Internal Barrel Serrations

Non-Insulated Large Ring Terminals

Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
K8-8R-D	8 A.W.G. 8 mm²	#8	.169 4.3	.315 8.0	.366 9.3	.846 21.5	.337 8.5	.283 7.2	.177 4.5	.047 1.2
K8-10R-D		#10	.209 5.3	.346 8.8	.429 10.5	.937 23.8				
K8-14R-D		1/4	.252 6.4	.472 12.0	.366 9.3	.937 23.8				
K8-516R-D		5/16	.331 8.4	.591 15.0	.543 13.8	1.161 29.8				
K8-38R-D		3/8	.413 10.5	.591 15.0	.543 13.8	1.161 29.8				
K8-12R-D		1/2	.512 13.0	.787 20.0	.591 15.0	1.319 33.5				
K6-10R-D	6 A.W.G. 14 mm²	#10	.209 5.3	.472 12.0	.524 13.3	1.173 29.8	.413 10.5	.354 9.0	.228 5.85	.059 1.5
K6-14R-D		1/4	.252 6.4	.472 12.0	.524 13.3	1.173 29.8				
K6-516R-D		5/16	.331 8.4	.630 16.0	.559 14.2	1.280 32.5				
K6-38R-D		3/8	.413 10.5	.630 16.0	.559 14.2	1.280 32.5				
K6-12R-W		1/2	.512 13.0	.866 22.0	.780 19.8	1.614 41.0				
K4-8R-W*	4 A.W.G. 22 mm²	#8	.169 4.3	.481 12.2	.594 15.1	1.307 33.2	.472 12.0	.453 11.5	.303 7.7	.067 1.7
K4-10R-W*		#10	.209 5.3	.481 12.2	.594 15.1	.1.307 33.2				
K4-14R-W*		1/4	.252 6.4	.481 12.2	.594 15.1	1.299 33.0				
K4-516R-W*		5/16	.331 8.4	.650 16.5	.531 13.5	1.319 33.5				
K4-38R-W*		3/8	.413 10.5	.650 16.5	.531 13.5	1.319 33.5				
K4-12R-CC*		1/2	.512 13.0	.866 22.0	.776 19.7	1.661 42.5				
K2-10R-CC*	2 A.W.G. 38 mm²	#10	.209 5.3	.602 15.3	.685 17.4	1.535 39.0	.551 14.0	.524 13.3	.370 9.4	.071 1.8
K2-14R-CC*		1/4	.252 6.4	.602 15.3	.685 17.4	1.535 39.0				
K2-516R-CC*		5/16	.331 8.4	.602 15.3	.685 17.4	1.535 39.0				
K2-38R-CC*		3/8	.413 10.5	.602 15.3	.685 17.4	1.535 39.0				
K2-12R-CC*		1/2	.512 13.0	.866 22.0	.697 17.7	1.681 42.7				



Box Quantity: C=100; CC=200; (W)=250; (D)=500;

For mylar tape, replace box quantity with (T). Example: K6-10R-T.
See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Terminal Material: Copper

UL File #E9809
***Pending UL Listing**

Tools used with Non-Insulated Large Ring Terminals



TBM6S




KT-2500

For tooling information for nylon insulated large ring terminals, see page M37.

Thomas&Betts


© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



Vinyl Insulated Large Ring Terminals

Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm W	F	L	E	D	d1	T
KV8-8R-D	8 A.W.G. 8 mm²	#8	.169 4.3	.315 8.0	.366 9.3	1.16 29.5	.650 16.5	.335 8.5	.177 4.5	.047 1.2
KV8-10R-D		#10	.209 5.3	.346 8.8	.429 10.9	1.25 31.8				
KV8-14R-D		1/4	.252 6.4	.472 12.0	.366 9.3	1.25 31.8				
K8-516R-D		5/16	.331 8.4	.591 15.0	.543 13.8	1.49 37.8				
KV8-38R-D		3/8	.413 10.5	.591 15.0	.543 13.8	1.49 37.8				
KV8-12R-D		1/2	.512 13.0	.787 20.0	.591 15.0	1.63 41.5				
KV6-10R-W	6 A.W.G. 14 mm²	#10	.209 5.3	.472 12.0	.524 13.3	1.62 41.2	.886 22.5	.414 10.5	.222 5.65	.059 1.5
KV6-14R-W		1/4	.252 6.4	.472 12.0	.524 13.3	1.62 41.2				
KV6-516R-W		5/16	.331 8.4	.630 16.0	.571 14.5	1.75 44.5				
KV6-38R-W		3/8	.413 10.5	.630 16.0	.571 14.5	1.75 44.5				
KV6-12R-W		1/2	.512 13.0	.866 22.0	.780 19.8	2.09 53				

- Brazed Seam
- Internal Barrel Serrations



Box Quantity: (W)=250; (D)=500
For mylar tape, replace box quantity with (T). Example: KN8-8R-T.

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

#8 AWG on mylar tape is UL Listed.
#6 AWG on mylar tape is UL Listed.

UL File #E9809
CSA File #LR4503

M

Spec-Kon®

Tools used with Vinyl Insulated Large Ring Terminals



TBM6S

For tooling information for nylon insulated large ring terminals, see page M37.




KT-2500

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry



Nylon Insulated Fork Terminals

Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
KN18-6F-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.252 6.4	.256 6.5	.866 22.0	.433 11.0	.177 4.5	.067 1.7	.030 0.75
KN18-8F-M		#8	.169 4.3	.252 6.4	.256 6.5	.866 22.0				
KN18-10F-M		#10	.209 5.3	.319 8.1	.256 6.5	.866 22.0				
KN18-14F-M		1/4	.252 6.4	.374 9.5	.256 6.5	.866 22.0				
KN14-6F-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.236 6.0	.256 6.5	.866 22.0	.433 11.0	.205 5.2	.091 2.3	.031 0.8
KN14-8F-M		#8	.169 4.3	.252 6.4	.256 6.5	.866 22.0				
KN14-10F-M		#10	.209 5.3	.311 7.9	.256 6.5	.866 22.0				
KN14-14F-M		1/4	.252 6.4	.366 9.3	.256 6.5	.866 22.0				
KN10-6F-D	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.283 7.2	.295 7.5	.961 24.4	.512 13.0	.276 7.0	.134 3.4	.039 1.0
KN10-8F-D		#8	.169 4.3	.327 8.3	.276 7.0	1.004 25.5				
KN10-10F-D		#10	.209 5.3	.354 9.0	.276 7.0	1.004 25.5				
KN10-14F-D		1/4	.252 6.4	.354 9.0	.276 7.0	1.004 25.5				
KN10-516F-D		5/16	.315 8.4	.551 14.0	.413 10.5	1.201 30.5				

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KN18-6F-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105˚C 600 Volts Max.
Terminal Material: Copper

Tools used with Nylon Insulated Ring Terminals



ERG2500




KT-2500

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



Vinyl Insulated Fork Terminals

- Molded Funnel Entry Insulator
- Brazed Seam
- Internal Barrel Serrations



Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
KV18-6F-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.252 6.4	.256 6.5	.866 22.0	.433 11.0	.157 4.0	.067 1.7	.030 0.75
KV18-8F-M		#8	.169 4.3	.252 6.4	.256 6.5	.866 22.0				
KV18-10F-M		#10	.209 5.3	.319 8.1	.256 6.5	.866 22.0				
KV18-14F-M		1/4	.252 6.4	.374 9.5	.256 6.5	.866 22.0				
KV14-6F-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.236 6.0	.256 6.5	.866 22.0	.433 11.0	.177 4.5	.091 2.3	.031 0.8
KV14-8F-M		#8	.169 4.3	.252 6.4	.256 6.5	.866 22.0				
KV14-10F-M		#10	.209 5.3	.311 7.9	.256 6.5	.866 22.0				
KV14-14F-M		1/4	.252 6.4	.366 9.3	.256 6.5	.866 22.0				
KV10-6F-D	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.283 7.2	.295 7.5	.961 24.4	.512 13.0	.252 6.4	.134 3.4	.039 1.0
KV10-8F-D		#8	.169 4.3	.327 8.3	.276 7.0	1.004 25.5				
KV10-10F-D		#10	.209 5.3	.354 9.0	.276 7.0	1.004 25.5				
KV10-14F-D		1/4	.252 6.4	.354 9.0	.276 7.0	1.004 25.5				
KV10-516F-D		5/16	.315 8.4	.551 14.0	.413 10.5	1.201 30.5				

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KV18-6F-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Tools used with Vinyl Insulated Fork Terminals



ERG2500




KT-2500

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**



- Chamfered Barrel
- Brazed Seam
- Internal Barrel Serrations



Non-Insulated Fork Terminals

Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
K18-6F-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.252 6.4	.256 6.5	.630 16.0	.189 4.8	.134 3.4	.067 1.7	.030 0.75
K18-8F-M		#8	.169 4.3	.252 6.4						
K18-10F-M		#10	.209 5.3	.319 8.1						
K14-6F-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.236 6.0	.256 6.5	.630 16.0	.189 4.8	.161 4.1	.091 2.3	.031 0.8
K14-8F-M		#8	.169 4.3	.252 6.4						
K14-10F-M		#10	.209 5.3	.319 8.1						
K10-6F-M	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.283 7.2	.295 7.5	.685 17.4	.236 6.0	.220 5.6	.134 3.4	.039 1.0
K10-8F-M		#8	.169 4.3	.327 8.3	.276 7.0	.728 18.5				
K10-10F-M		#10	.209 5.3	.354 9.0						
K10-14F-M		1/4	.252 6.4	.354 9.0						

Box Quantity: (M)=1000
For Mylar Tape replace box quantity with (T). Example: K18-6F-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Terminal Material: Copper

Tools used with Non-Insulated Fork Terminals



ERG2002



KT-2500


Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.

Nylon Insulated Locking Fork Terminals



- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry



Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
KN18-6LF-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.252 6.4	.256 6.5	.866 22.0	.433 11.0	.177 4.5	.067 1.7	.030 0.75
KN18-8LF-M		#8	.169 4.3	.283 7.2						
KN18-10LF-M		#10	.209 5.3	.319 8.1						
KN14-6LF-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.236 6.0	.256 6.5	.866 22.0	.433 11.0	.205 5.2	.091 2.3	.031 0.8
KN14-8LF-M		#8	.169 4.3	.283 7.2						
KN14-10LF-M		#10	.209 5.3	.319 8.1						
KN10-6LF-D	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.327 8.3	.276 7.0	.992 25.2	.512 13.0	.276 7.0	.134 3.4	.039 1.0
KN10-8LF-D		#8	.169 4.3	.327 8.3						
KN10-10LF-D		#10	.209 5.3	.354 9.0						

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KN18-6LF-T
UL File #E9809, CSA File #LR4503


See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Vinyl Insulated Locking Fork Terminals



- Molded Funnel Entry Insulator
- Internal Barrel Serrations



Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
KV18-6LF-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.252 6.4	.256 6.5	.866 22.0	.433 11.0	.157 4.0	.067 1.7	.030 0.75
KV18-8LF-M		#8	.169 4.3	.283 7.2						
KV18-10LF-M		#10	.209 5.3	.319 8.1						
KV14-6LF-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.236 6.0	.256 6.5	.866 22.0	.433 11.0	.177 4.5	.091 2.3	.031 0.8
KV14-8LF-M		#8	.169 4.3	.283 7.2						
KV14-10LF-M		#10	.209 5.3	.319 8.1						
KV10-6LF-D	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.327 8.3	.276 7.0	.992 25.2	.512 13.0	.252 6.4	.134 3.4	.039 1.0
KV10-8LF-D		#8	.169 4.3	.327 8.3						
KV10-10LF-D		#10	.209 5.3	.354 9.0						

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T).
Example: KV18-6LF-T
UL File #E9809, CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Tools used with Nylon and Vinyl Insulated Locking Fork Terminals



ERG2500



KT-2500


Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. www.tnb.com

Non-Insulated Locking Fork Terminals



- Chamfered Barrel
- Brazed Seam
- Internal Barrel Serrations



Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm						
				W	F	L	E	D	d1	T
K18-6LF-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.252 6.4	.256 6.5	.630 16.0	.189 4.8	.134 3.4	.067 1.7	.030 0.75
K18-8LF-M		#8	.169 4.3	.283 7.2						
K18-10LF-M		#10	.209 5.3	.319 8.1						
K14-6LF-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.236 6.0	.256 6.5	.630 16.0	.189 4.8	.161 4.1	.091 2.3	.031 0.8
K14-8LF-M		#8	.169 4.3	.283 7.2						
K14-10LF-M		#10	.209 5.3	.319 8.1						
K10-6LF-M	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.327 8.3	.276 7.0	.717 18.2	.236 6.0	.220 5.6	.134 3.4	.039 1.0
K10-8LF-M		#8	.169 4.3	.327 8.3						
K10-10LF-M		#10	.209 5.3	.354 9.0						

Box Quantity: (M)=1000
For Mylar Tape replace box quantity with (T). Example: K18-6LF-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Terminal Material: Copper

Tools used with Non-Insulated Locking Fork Terminals



ERG2002




KT-2500

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.

Nylon Insulated Flanged Fork Terminals



- Reduces Slippage in High Vibration Applications
- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry



Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm							
				W	F	L	E	D	d1	A	T
KN18-6FF-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.335 8.5	.283 7.2	1.004 25.5	.433 11.0	.177 4.5	.067 1.7	.059 1.5	.030 0.75
KN18-8FF-M		#8	.169 4.3	.335 8.5	.283 7.2	1.004 25.5					
KN18-10FF-M		#10	.209 5.3	.335 8.5	.283 7.2	1.004 25.5					
KN14-6FF-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.335 8.5	.283 7.2	.945 24.0	.433 11.0	.205 5.2	.091 2.3	.059 1.5	.031 0.8
KN14-8FF-M		#8	.169 4.3	.335 8.5	.283 7.2	.945 24.0					
KN14-10FF-M		#10	.209 5.3	.335 8.5	.283 7.2	.945 24.0					
KN10-6FF-D	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.335 8.5	.295 7.5	1.063 27.0	.512 13.0	.276 7.0	.134 3.4	.059 1.5	.039 1.0
KN10-8FF-D		#8	.169 4.3	.335 8.5	.295 7.5	1.063 27.0					
KN10-10FF-D		#10	.209 5.3	.335 8.5	.295 7.5	1.063 27.0					

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KN18-6FF-T
UL File #E9809, CSA File #LR4503


See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Vinyl Insulated Flanged Fork Terminals



- Reduces Slippage in High Vibration Applications
- Molded Funnel Entry Insulator
- Brazed Seam
- Internal Barrel Serrations



Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm							
				W	F	L	E	D	d1	A	T
KV18-6FF-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.252 6.4	.201 5.1	.787 20.0	.433 11.0	.157 4.0	.067 1.7	.059 1.5	.030 0.75
KV18-8FF-M		#8	.169 4.3	.335 8.5	.283 7.2	1.004 25.5					
KV18-10FF-M		#10	.209 5.3	.335 8.5	.283 7.2	1.004 25.5					
KV14-6FF-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.335 8.5	.283 7.2	.945 24.0	.433 11.0	.177 4.5	.091 2.3	.059 1.5	.031 0.8
KV14-8FF-M		#8	.169 4.3	.335 8.5	.283 7.2	.945 24.0					
KV14-10FF-M		#10	.209 5.3	.335 8.5	.283 7.2	.945 24.0					
KV10-6FF-D	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.299 7.6	.244 6.2	1.004 25.5	.512 13.0	.252 6.4	.134 3.4	.059 1.5	.039 1.0
KV10-8FF-D		#8	.169 4.3	.299 7.6	.244 6.2	1.004 25.5					
KV10-10FF-D		#10	.209 5.3	.299 7.6	.244 6.2	1.004 25.5					

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T).
Example: KV18-6FF-T
UL File #E9809, CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Tools used with Nylon and Vinyl Insulated Flanged Fork Terminals



ERG2500




KT-2500

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**

Non-Insulated Flanged Fork Terminals



- Reduces Slippage in High Vibration Applications
- Chamfered Barrel
- Brazed Seam
- Internal Barrel Serrations



Catalog Number	Wire Range	Bolt Size (d2)		Dimension inch mm							
				W	F	L	E	D	d1	A	T
K18-6FF-M	22-16 A.W.G. 0.5-1.5 mm²	#6	.146 3.7	.335 8.5	.283 7.2	.768 19.5	.189 4.8	.134 3.4	.067 1.7	.059 1.5	.030 0.75
K18-8FF-M		#8	.169 4.3	.335 8.5	.283 7.2	.768 19.5					
K18-10FF-M		#10	.209 5.3	.335 8.5	.283 7.2	.768 19.5					
K14-6FF-M	16-14 A.W.G. 1.5-2.5 mm²	#6	.146 3.7	.335 8.5	.283 7.2	.709 18.0	.189 4.8	.161 4.1	.091 2.3	.059 1.5	.031 0.8
K14-8FF-M		#8	.169 4.3	.335 8.5	.283 7.2	.709 18.0					
K14-10FF-M		#10	.209 5.3	.335 8.5	.283 7.2	.709 18.0					
K10-6FF-M	12-10 A.W.G. 4-6 mm²	#6	.146 3.7	.335 8.5	.295 7.5	.787 20.0	.236 6.0	.220 5.6	.134 3.4	.059 1.5	.039 1.0
K10-8FF-M		#8	.169 4.3	.335 8.5	.295 7.5	.787 20.0					
K10-10FF-M		#10	.209 5.3	.335 8.5	.295 7.5	.787 20.0					

Box Quantity: (M)=1000
For Mylar Tape replace box quantity with (T). Example: K18-6FF-T
UL FIle #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Terminal Material: Copper

Tools used with Non-Insulated Flanged Fork Terminals



ERG2002




KT-2500

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



- For Use in DIN-Style Blade Terminal Blocks
- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry



Nylon Insulated Blade Terminals

Catalog Number	Wire Range	Dimension inch mm						
		W	F	L	E	D	d1	T
KN18-10BL-M	22-16 A.W.G. 0.5-1.5 mm²	.091 2.3	.394 10.0	.819 20.8	.433 11.0	.177 4.5	.067 1.7	.030 0.75
KN18-18BL-M		.087 2.2	.709 18.0	1.134 28.8				
KN14-10BL-M	16-14 A.W.G. 1.5-2.5 mm²	.094 2.4	.394 10.0	.819 20.8	.433 11.0	.205 5.2	.091 2.3	.031 0.8
KN14-18BL-M		.087 2.2	.709 18.0	1.134 28.8				
KN10-10BL-D	12-10 A.W.G. 4-6 mm²	.110 2.8	.394 10.0	.906 23.0	.512	.276	.134	.039


Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KN18-10BL-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper



- For Use in DIN-Style Blade Terminal Blocks
- Molded Funnel Entry Insulator
- Brazed Seam
- Internal Barrel Serrations



Vinyl Insulated Blade Terminals

Catalog Number	Wire Range	Dimension inch mm						
		W	F	L	E	D	d1	T
KV18-10BL-M	22-16 A.W.G. 0.5-1.5 mm²	.091 2.3	.394 10.0	.819 20.8	.433 11.0	.157 4.0	.067 1.7	.030 0.75
KV18-18BL-M		.087 2.2	.709 18.0	1.134 28.8				
KV14-10BL-M	16-14 A.W.G. 1.5-2.5 mm²	.094 2.4	.394 10.0	.819 20.8	.433 11.0	.177 4.5	.091 2.3	.031 0.8
KV14-18BL-M		.087 2.2	.709 18.0	1.134 28.8				
KV10-10BL-D	12-10 A.W.G. 4-6 mm²	.110 2.8	.394 10.0	.906 23.0	.512 13.0	.252 6.4	.134 3.4	.039 1.0

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KV18-10BL-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Tools used with Nylon and Vinyl Insulated Blade Terminals



ERG2500



KT-2500


Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**

Nylon Insulated Pin Terminals



- For Use in Pin-Style Terminal Blocks
- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry



Catalog Number	Wire Range	Dimension inch mm						
		W	F	L	E	D	d1	T
KN18-12PT-M	22-16 A.W.G. 0.5-1.5 mm²	.075 1.9	.472 12.0	.898 22.8	.433 11.0	.177 4.5	.067 1.7	.030 0.75
KN14-12PT-M	16-14 A.W.G. 1.5-2.5 mm²	.075 1.9	.472 12.0	.898 22.8	.433 11.0	.205 5.2	.091 2.3	.031 0.8
KN10-14PT-D	12-10 A.W.G. 4-6 mm²	.110 2.8	.551 14.0	1.063 27.0	.512 13.0	.276 7.0	.134 3.4	.039 1.0

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KN18-12PT-T
UL File #E9809
CSA File #LR4503


See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Vinyl Insulated Pin Terminals



- For Use in Pin-Style Terminal Blocks
- Molded Funnel Entry Insulator
- Brazed Seams
- Internal Barrel Serrations



Catalog Number	Wire Range	Dimension inch mm						
		W	F	L	E	D	d1	T
KV18-12PT-M	22-16 A.W.G. 0.5-2.5 mm²	.075 1.9	.472 12.0	.898 22.8	.433 11.0	.157 4.0	.067 1.7	.030 0.75
KV14-12PT-M	16-14 A.W.G. 1.5-2.5 mm²	.075 1.9	.472 12.0	.898 22.8	.433 11.0	.177 4.5	.091 2.3	.031 0.8
KV10-14PT-D	12-10 A.W.G. 4-6 mm²	.110 2.8	.551 14.0	1.063 27.0	.512 13.0	.252 6.4	.134 3.4	.039 1.0

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KV18-12PT-T
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Copper

Tools used with Nylon and Vinyl Insulated Pin Terminals



ERG2500




KT-2500

Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**


Spec-Kon®
Disconnects



Features and Benefits


Nylon and Vinyl Disconnects

- *Sleeved barrel*—Ensures barrel does not separate during crimping.
- *Funnel entry insulators*—Funnel entry speeds installation and reduces wire hang up.
- *Partial and fully insulated*—Offers a wide range of products to meet virtually any application




- *Metal insulation sleeve*—Sleeve crimps wire insulation, providing high-vibration resistance and conductor strain relief.
- *Ratings*—UL Listed, cULus Listed, CSA, 600 V at 105ºC for nylon and vinyl.


Design Features of Spec-Kon® Disconnects




Female Disconnect
Provides easy installation and removal from male tabs and auxiliary equipment




Male Disconnect
Tab-style male disconnects are fast and reliable




Female Piggy Back
Provides the option for multiple circuits using one termination point




Fully Insulated Female
Standard female tab with the safety and reliability of complete insulation



Fully Insulated Male
Standard male tab with the safety and reliability of complete insulation



Bullet Disconnect and Receptacle
Fast and reliable alternative to the tab style featuring a lower profile to reduce space requirements



M

Spec-Kon®

Performance Requirements

Description	Wire Size (AWG)						
	#22	#20	#18	#16	#14	#12	#10
U.L. 310 (Disconnects)							
Test Current for Max. 30˚C Rise (Amps)	3	4	7	10	15	20	24
Min. Tensile Strength* (Lbs.)	8	13	20	30	50	70	80

*** Pull-out force of the crimped terminal.**

Applicable Spec-Kon® products meet or exceed the following test specifications:

- UL310 (Disconnects)
- CSA

UL listed products are shown with the applicable logos in the product section.
UL file #E66716 (Disconnects).
CSA file #LR4503

Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.

Nylon Insulated Female Disconnects



110 Tab Size



187 Tab Size




250 Tab Size

Catalog Number	Wire Range	Tab Size inch	Dimension inch mm					
			W	F	L	B	D	T
KN18-110-20FD-M	22-16 A.W.G. 0.5-1.5 mm²	.110 x .020	.126 3.2	.256 6.5	.772 19.6	.433 11.0	.157 4.0	.012 0.3
KN18-110-32FD-M		.110 x .032	.126 3.2	.256 6.5	.772 19.6			
KN18-187-20FD-M		.187 x .020	.197 5.0	.252 6.4	.787 20.0			.016 0.4
KN18-187-32FD-M		.187 x .032	.197 5.0	.252 6.4	.787 20.0			
KN18-250FD-M		.250 x .032	.260 6.6	.287 7.3	.846 21.5			
KN14-110-20FD-M	16-14 A.W.G. 1.5-2.5 mm²	.110 x .020	.126 3.2	.252 6.4	.772 19.6	.433 11.0	.197 5.0	.012 0.3
KN14-110-32FD-M		.110 x .032	.126 3.2	.252 6.4	.772 19.6			
KN14-187-20FD-M		.187 x .020	.197 5.0	.256 6.5	.787 20.0			.016 0.4
KN14-187-32FD-M		.187 x .032	.197 5.0	.256 6.5	.787 20.0			
KN14-250FD-M		.250 x .032	.260 6.6	.287 7.3	.846 21.5			
KN10-110-20FD-D	12-10 A.W.G. 4-6 mm²	.110 x .020	.126 3.2	.343 8.7	.866 22.0	.512 13.0	.256 6.5	.016 0.4
KN10-110-32-FD-D		.110 x .032	.126 3.2	.343 8.7	.866 22.0			
KN10-187-20FD-D		.187 x .020	.197 5.0	.256 6.5	.866 22.0			
KN10-187-32FD-D		.187 x .032	.197 5.0	.256 6.5	.866 22.0			
KN10-250FD-D		.250 x .032	.260 6.6	.287 7.3	.925 23.5			

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KN18-110FD-T
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Brass with Copper Sleeve



- For Use in Temporary Connections to Male Disconnects & Terminal Blocks
- Multiple Sizes for Range of Applications
- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry

Tools used with Nylon Insulated Female Disconnects



ERG2500



KT-2500

Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.

Vinyl Insulated Female Disconnects



110 Tab Size



187 Tab Size




250 Tab Size

Catalog Number	Wire Range	Tab Size inch	Dimension inch mm					
			W	F	L	B	D	T
KV18-110-20FD-M	22-16 A.W.G. 0.5-1.5 mm²	.110 x .020	.126 3.2	.256 6.5	.728 19.0	.413 10.5	.150 3.8	.012 0.3
KV18-110-32-FD-M		.110 x .032	.126 3.2	.256 6.5	.728 19.0			
KV18-187-20FD-M		.187 x .020	.197 5.0	.252 6.4	.764 19.4			.016 0.4
KV18-187-32FD-M		.187 x .032	.197 5.0	.252 6.4	.764 19.4			
KV18-250FD-M		.250 x .032	.260 6.6	.287 7.3	.819 20.8			
KV14-110-20FD-M	16-14 A.W.G. 1.5-2.5 mm²	.110 x .020	.126 3.2	.256 6.5	.748 19.0	.413 10.5	.185 4.7	.012 0.3
KV14-110-32FD-M		.110 x .032	.126 3.2	.256 6.5	.748 19.0			
KV14-187-20-FD-M		.187 x .020	.197 5.0	.252 6.4	.764 19.4			.016 0.4
KV14-187-32-FD-M		.187 x .032	.197 5.0	.252 6.4	.764 19.4			
KV14-250FD-M		.250 x .032	.260 6.6	.287 7.3	.819 20.8			
KV10-110-20FD-D	12-10 A.W.G. 4-6 mm²	.110 x .020	.126 3.2	.343 8.7	.866 22.0	.512 13.0	.244 6.2	.016 0.4
KV10-110-32FD-D		.110 x .032	.126 3.2	.343 8.7	.866 22.0			
KV10-187-20FD-D		.187 x .020	.197 5.0	.256 6.5	.866 22.0			
KV10-187-32FD-D		.187 x .032	.197 5.0	.256 6.5	.866 22.0			
KV10-250FD-D		.250 x .032	.260 6.6	.287 7.3	.917 23.3			

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KV18-110FD-T
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 300 Volts Max.
Terminal Material: Brass with Copper Sleeve



M

Spec-Kon®

- For Use in Temporary Connections to Male Disconnects & Terminal Blocks
- Metal Insulation Sleeve
- Easy Entry Copper Sleeve

Tools used with Vinyl Insulated Female Disconnects



ERG2500




KT-2500

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. www.tnb.com

Nylon Insulated Male Disconnects



- For Use with Female Disconnects
- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry



Catalog Number	Wire Range	Tab Size inch	Dimension inch mm					
			W	F	L	B	D	T
KN18-250MD-M	22-16 A.W.G. 0.5-1.5 mm²	.250 x .032	.250 6.35	.303 7.7	.866 22.0	.413 11.0	.150 4.0	.016 0.4
KN14-250MD-M	16-14 A.W.G. 1.5-2.5 mm²	.250 x .032	.250 6.35	.303 7.7	.866 22.0	.433 11.0	.197 5.0	.016 0.4
KN10-250MD-D	12-10 A.W.G. 4-6 mm²	.250 x .032	.250 6.35	.303 7.7	.945 24.0	.512 13.0	.256 6.5	.016 0.4

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KN18-250MD-T
UL File #E66716
CSA File #LR4503


See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Brass with Copper Sleeve

Vinyl Insulated Male Disconnects



- For Use with Female Disconnects
- Metal Insulation Sleeve
- Easy Entry Copper Sleeve



Catalog Number	Wire Range	Tab Size inch	Dimension inch mm					
			W	F	L	B	D	T
KV18-250MD-M	22-16 A.W.G. 0.5-1.5 mm²	.250 x .032	.250 6.35	.303 7.7	.858 21.8	.413 10.5	.150 3.8	.016 0.4
KV14-250MD-M	16-14 A.W.G. 1.5-2.5 mm²	.250 x .032	.250 6.35	.303 7.7	.858 21.8	.413 10.5	.185 4.7	.016 0.4
KV10-250MD-D	12-10 A.W.G. 4-6 mm²	.250 x .032	.250 6.35	.303 7.7	.945 24.0	.512 13.0	.244 6.2	.016 0.4

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KV18-250MD-T
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 300 Volts Max.
Terminal Material: Brass with Copper Sleeve

Tools used with Nylon and Vinyl Insulated Male Disconnects



ERG2500



KT-2500

Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**

Nylon Insulated Piggy Back Disconnects




- Male and Female Tabs Combined
- Additional conductors may be added to existing installations without changing blocks
- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry

Catalog Number	Wire Range	Tab Size inch	Dimension inch mm							
			W	W1	F	F1	L	B	D	T
KN18-250PD-M	22-16 A.W.G. 0.5-1.5 mm²	.250 x .032	.260 6.6	.250 6.35	.315 8.0	.323 8.2	.906 23.0	.433 11.0	.157 4.0	.016 0.4
KN14-250PD-M	16-14A.W.G. 1.5-2.5 mm²	.250 x .032	.260 6.6	.250 6.35	.315 8.0	.323 8.2	.906 23.0	.433 11.0	.197 5.0	.016 0.4
KN10-250PD-D	12-10A.W.G. 4-6 mm²	.250 x .032	.260 6.6	.250 6.35	.315 8.0	.323 8.2	.945 24.0	.512 13.0	.256 6.5	.016 0.4

Box Quantity: (D)=500; (M)=1000
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Brass with Copper Sleeve



Vinyl Insulated Piggy Back Disconnects




- Male and Female Tabs Combined
- Additional conductors may be added to existing installations without changing blocks
- Brazed Seam
- Internal Barrel Serrations
- Funnel Entry

Catalog Number	Wire Range	Tab Size inch	Dimension inch mm							
			W	W1	F	F1	L	B	D	T
KV18-250PD-M	22-16 A.W.G. 0.5-1.5 mm²	.250 x .032	.260 6.6	.250 6.35	.315 8.0	.323 8.2	.886 22.5	.413 10.5	.150 3.8	.016 0.4
KV14-250PD-M	16-14 A.W.G. 1.5-2.5 mm²	.250 x .032	.260 6.6	.250 6.35	.315 8.0	.323 8.2	.886 22.5	.413 10.5	.185 4.7	.016 0.4
KV10-250PD-D	12-10 A.W.G. 4-6 mm²	.250 x .032	.260 6.6	.250 6.35	.315 8.0	.323 8.2	.945 24.0	.512 13.0	.244 6.2	.016 0.4

Box Quantity: (D)=500; (M)=1000
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 300 Volts Max.
Terminal Material: Brass with Copper Sleeve



Tools used with Nylon and Vinyl Insulated Piggy Back Disconnects



ERG2500



KT-2500

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**



110 Tab Size



187 Tab Size



250 Tab Size

Nylon Fully Insulated Female Disconnects


Catalog Number	Wire Range	Tab Size inch	Dimension inch / mm					
			W	F	L	B	D	T
KNF18-110-20FDM	22-16 A.W.G. 0.5-1.5 mm²	.110 x .020	.126 3.2	.252 6.4	.756 19.2	.433 11.0	.157 4.0	.012 0.3
KNF18-110-32FDM		.110 x .032	.126 3.2	.252 6.4	.756 19.2			
KNF18-187-20FDM		.187 x .020	.197 5.0	.256 6.5	.795 20.2			.016 0.4
KNF18-187-32FDM		.187 x .032	.197 5.0	.256 6.5	.795 20.2			
KNF18-250FD-D		.250 x .032	.260 6.6	.303 7.7	.846 21.5			
KNF14-187-20FDM	16-14 A.W.G. 1.5-2.5 mm²	.187 x .020	.197 5.0	.256 6.5	.795 20.2	.433 11.0	.256 6.0	.016 0.4
KNF14-187-32FDM		.187 x .032	.197 5.0	.256 6.5	.795 20.2			
KNF14-250FD-M		.250 x .032	.260 6.6	.287 7.3	.846 21.5			
KNF10-250FD-D	12-10 A.W.G. 4-6 mm²	.250 x .032	.260 6.6	.287 7.3	.953 24.2	.512 13.0	.256 6.5	.016 0.4

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KNF18-110-20FD-T
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Brass with Copper Sleeve

- Fully Insulated
- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry



Tools used with Nylon Fully Insulated Female Disconnects



ERG2500



KT-2500

Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



110 Tab Size



187 Tab Size



250 Tab Size

- Fully Insulated
- Brazed Seam
- Internal Barrel Serrations
- Funnel Entry


Vinyl Fully Insulated Female Disconnects

Catalog Number	Wire Range	Tab Size inch	Dimension inch mm					
			W	F	L	B	D	T
KVF18-110-20FDM	22-16 A.W.G. 0.5-1.5 mm²	.110 x .020	.126 3.2	.256 6.5	.748 19.0	.413 10.5	.150 3.8	.012 0.3
KVF18-110-32FDM		.110 x .032	.126 3.2	.256 6.5	.748 19.0			
KVF18-187-20FDM		.187 x .020	.197 5.0	.252 6.4	.807 20.5			.016 0.4
KVF18-187-32FDM		.187 x .032	.197 5.0	.252 6.4	.807 20.5			
KVF18-250FD-M		.250 x .032	.260 6.6	.287 7.3	.858 21.8			
KVF14-110-20FDM	16-14 A.W.G. 1.5-2.5 mm²	.110 x .020	.126 3.2	.256 6.5	.748 19.0	.413 10.5	.185 4.7	.012 0.3
KVF14-110-32FDM		.110 x .032	.126 3.2	.256 6.5	.748 19.0			
KVF14-187-20FDM		.187 x .020	.197 5.0	.252 6.4	.796 20.2			.016 0.4
KVF14-187-32FDM		.187 x .032	.197 5.0	.252 6.4	.796 20.2			
KVF14-250FD-M		.250 x .032	.260 6.6	.287 7.3	.874 22.2			
KVF10-250FD-D	12-10 A.W.G. 4-6 mm²	.250 x .032	.260 6.6	.287 7.3	.953 24.2	.492 12.5	.244 6.2	.016 0.4

Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KVF18-110-20FD-T
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 300 Volts Max.
Terminal Material: Brass with Copper Sleeve
Tools used with Vinyl Fully Insulated Female Disconnects: ERG2500 and KT2500.





- Fully Insulated
- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry

Nylon Fully Insulated Male Disconnects


Catalog Number	Wire Range	Tab Size inch	Dimension inch mm					
			W	F	L	B	D	T
KNF18-250MD-D	22-16 A.W.G. 0.5-1.5 mm²	.250 x .032	.250 6.35	.303 7.7	.976 24.0	.433 11.0	.157 4.0	.016 0.4
KNF14-250MD-D	16-14 A.W.G. 1.5-2.5 mm²	.250 x .032	.250 7.7	.303 24.0	.976	.433 11.0	.197 5.0	.016 0.4
KNF10-250MD-D	12-10 A.W.G. 4-6 mm²	.250 x .032	.250 6.35	.303 7.7	1.016 25.8	.512 13.0	.256 6.5	.016 0.4

Box Quantity: (D)=500
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Brass with Copper Sleeve

Yellow Male Disconnect Not Shown.
Tools used with Nylon Fully Insulated Male Disconnects: ERG2500 and KT2500.




Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. www.tnb.com



- Fully Insulated
- Molded Funnel Entry Insulator
- Internal Barrel Serrations



Nylon Fully Insulated Female Flag Disconnects

Catalog Number	Wire Range	Tab Size inch	Dimension inch / mm				
			W	F	L	d1	T
KNF18-187-20FFD-M	22-18 A.W.G. 0.5-1.5 mm²	.187 x .020	.197 5.0	.276 7.0	.591 15.0	.063 1.6	.016 0.4
KNF18-187-32FFD-M		.187 x .032	.197 5.0	.276 7.0	.591 15.0		
KNF18-250FFD-M		.250 x .032	.260 6.6	.299 7.6	.598 15.2		
KNF14-187-20FFD-M	16-14 A.W.G. 1.5-2.5 mm²	.187 x .020	.197 5.0	.276 7.0	.598 15.2	.083 2.1	.016 0.4
KNF14-187-32FFD-M		.187 x .032	.197 5.0	.276 7.0	.598 15.2		
KNF14-250FFD-M		.250 x .032	.260 6.6	.299 7.6	.598 15.2		


Box Quantity: (W)=250; (D)=500; (M)=1000

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105˚C 300 Volts Max.
Terminal Material: Brass



- Fully Insulated
- Molded Funnel Entry Insulator
- Internal Barrel Serrations



Nylon Fully Insulated Barrel Flag Female Disconnects

Catalog Number	Wire Range	Tab Size inch	Dimension inch / mm						
			W	F	L	L 1	B	D	T
KNF18-187-20BFD-D	22-18 A.W.G. 0.5-1.5 mm²	.187 x .020	.197 5.0	.244 6.2	.748 19.0	.555 14.1	.433 11.0	.137 3.5	.015 0.4
KNF18-187-32BFD-D		.187 x .032	.197 5.0	.244 6.2	.748 19.0	.555 14.1	.433 11.0	.137 3.5	.015 0.4
KNF18-250BFD-D		.250 x .032	.260 6.6	.307 7.8	.818 20.8	.653 16.6	.433 11.0	.157 4.0	.015 0.4
KNF14-250BFD-D	16-14 A.W.G.	.250 x .032	.260 6.6	.307 7.8	.818 20.8	.653 16.6	.433 11.0	.177 4.5	.015 0.4
KNF10-250BFD-D	12-10 A.W.G.	.250 x .032	.260 6.6	.307 7.8	.905 23.0	.697 17.7	.511 13.0	.248 6.3	.015 0.4

Box Quantity: (W)=250; (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T).
Example: KVF18-110-20FD-T

See pages in back of catalog for complete tool information.

Tool and Die Selection Chart on page M42.
Maximum Electrical Rating: 105˚C 600 Volts Max.
Terminal Material: Brass


Tools used with Nylon Fully Insulated Female Flag Disconnects and Nylon Fully Insulated Barrell Flag Female Disconnects: ERG2500F

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.

Nylon Fully Insulated Bullet Receptacles



- Fully Insulated
- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry



Catalog Number	Wire Range	Dimension inch mm					
		W	F	L	B	D	T
KNF18-4FB-M	22-16 A.W.G. 0.5-1.5 mm²	.153 3.9	.287 7.3	.992 25.2	.433 11.0	.157 4.0	.016 0.4
KNF14-4FB-M	16-14 A.W.G. 1.5-2.5 mm²	.153 3.9	.287 7.3	.992 25.2	.433 11.0	.197 5.0	.016 0.4

Box Quantity: (M)=1000
For Mylar Tape replace box quantity with (T). Example: KNF18-4FB-T
UL File #E66716
CSA File #LR4503


See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Brass with Copper Sleeve

Vinyl Fully Insulated Bullet Receptacles



- Brazed Seam
- Internal Barrel Serrations
- Funnel Entry



Catalog Number	Wire Range	Dimension inch mm					
		W	F	L	B	D	T
KVF18-4FB-M	22-16 A.W.G. 0.5-1.5 mm²	.153 3.9	.287 7.3	.917 23.3	.413 10.5	.150 3.8	.016 0.4
KVF14-4FB-M	16-14 A.W.G. 1.5-2.5 mm²	.153 3.9	.287 7.3	.917 23.3	.413 10.5	.185 4.7	.016 0.4
KVF10-5FB-D*	12-10 A.W.G. 4-6 mm²	.193 4.9	.276 7.0	.988 25.1	.492 12.5	.244 6.2	.018 0.45

***Not UL listed**
Box Quantity: (D)=500; (M)=1000
For Mylar Tape replace box quantity with (T). Example: KVF18-4FB-T
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 75°C 300 Volts Max.
Terminal Material: Brass with Copper Sleeve

Tools used with Nylon and Vinyl Insulated Bullet Receptacles



ERG2500



KT-2500


© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**

Nylon Fully Insulated Bullet Disconnects



Catalog Number	Wire Range	Dimension inch / mm					
		W	F	L	B	D	T
KNF18-4MB-D	22-16 A.W.G. 0.5-1.5 mm²	.157 4.0	.413 10.5	1.063 27.0	.394 10.0	.157 4.0	.016 0.4
KNF14-4MB-D	16-14 A.W.G. 1.5-2.5 mm²	.157 4.0	.413 10.5	1.063 27.0	.394 10.0	.177 4.5	.016 0.4

- Fully Insulated
- Metal Insulation Sleeve
- Molded Insulator
- Internal Barrel Serrations
- Funnel Entry



Box Quantity: (D)=500
For Mylar Tape replace box quantity with (T). Example: KNF18-4MB-T

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.


Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Brass with Copper Sleeve

Vinyl Insulated Bullet Disconnects



Catalog Number	Wire Range	Dimension inch / mm					
		W	F	L	B	D	T
KV18-4MB-M	22-16 A.W.G. 0.5-1.5 mm²	.157 4.0	.413 10.5	9.25 23.5	.413 10.5	.150 3.8	.016 0.4
KV14-4MB-M	16-14 A.W.G. 1.5-2.5 mm²	.157 4.0	.413 10.5	9.25 23.5	.413 10.5	.185 4.7	.016 0.4
KV10-5MB-D	12-10 A.W.G. 4-6 mm²	.197 5.0	.335 8.5	.945 24.0	.512 13.0	.244 6.2	.016 0.4

- Brazed Seam
- Internal Barrel Serrations
- Funnel Entry



Box Quantity: (D)=500
For Mylar Tape replace box quantity with (T). Example: KV18-4MB-T
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 75°C 300 Volts Max.
Terminal Material: Brass with Copper Sleeve

Tools used with Nylon and Vinyl Insulated Bullet Disconnects




ERG2500



KT-2500

Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



Features and Benefits


Splices / Wire Joints / Quick Splices

- Ideal for in-line splicing.
- Butt Splices available in Nylon, Vinyl, and non-insulated types.
- Vinyl Quick Splices are color-coded for wire ranges, and provide quick, easy in-line splicing and tapping.
- Nylon wire joint provides long-lasting, durable connection and can accommodate multiple leads. Rated 300 V at 105ºC.
- Available in 22-10 AWG.

Design Features of Splices, Wire Joints and Quick Splices



Butt Splice
Ideal for in-line splicing applications



Wire Joints
Provides terminating point for a group of wires running in one direction



Quick Splices
Great for quick in-line splicing and tapping without stripping the wire insulation

Performance Requirements

Description	Wire Size (AWG)										
	#22	#20	#18	#16	#14	#12	#10	#8	#6	#4	#2
U.L. 486A (Terminals)											
Test Current for Max. 50˚C Rise (Amps)	9	12	17	18	30	35	50	70	95	125	145
Min. Tensile Strength* (Lbs.)	8	13	20	30	50	70	80	90	100	140	160

*** Pull-out force of the crimped terminal.**

Applicable Spec-Kon® products meet or exceed the following test specifications:

- UL486A (Terminals)
- CSA
- UL486C (Splices)

UL listed products are shown with the applicable logos in the product section.
UL file #E9809 (Terminals).
CSA file #LR4503


© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



Nylon Insulated Butt Splice

Catalog Number	Wire Range	Dimension inch mm		
		L	D	d1
KN18-BS-M	22-16 A.W.G. 0.5-1.5 mm²	1.075 27.3	.126 3.2	.067 1.7
KN14-BS-M	16-14 A.W.G. 1.5-2.5 mm²	1.075 27.3	.150 3.8	.091 2.3
KN10-BS-D	12-10 A.W.G 4-6 mm²	1.110 28.2	.248 6.3	.134 3.4

- Internal Wire Stop
- Brazed Seams (Yellow -Tubular)
- Chamfered Funnel Entry



Box Quantity: (W)=250; (D)=500; (M)=1000

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.
UL File #9809
CSA File #LR4503

Maximum Electrical Rating: 105˚C 600 Volts Max.
Connector Material: Copper




Vinyl Insulated Butt Splice

Catalog Number	Wire Range	Dimension inch mm		
		L	D	d1
KV18-BS-M	22-16 A.W.G. 0.5-1.5 mm²	.986 24.6	.157 4.0	.067 1.7
KV14-BS-M	16-14 A.W.G. 1.5-2.5 mm²	.986 24.6	.177 4.5	.091 2.3
KV10-BS-D	12-10 A.W.G. 4-6 mm²	1.024 26.0	2.48 6.3	1.34 3.4

3.2

- Expanded Entry
- Brazed Seams (Yellow -Tubular)
- Internal Barrel Serrations



Box Quantity: (W)=250; (D)=500; (M)=1000
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 75˚C 600 Volts Max.
Terminal Material: Copper

Tool used with Nylon and Vinyl Insulated Butt Splice




ERG2500

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.

Non-Insulated Butt Splice



- Chamfered Barrel Entry
- Seamless Barrel Construction
- Wire Stop



Catalog Number	Wire Range	Dimension inch mm			
		L	D	d1	T
K18-BS-M	22-16 A.W.G. 0.5-1.5 mm²	.591 15.0	.130 3.3	.067 1.7	.031 0.8
K14-BS-M	16-14 A.W.G. 1.5-2.5 mm²	.591 15.0	.154 3.9	.091 2.3	.031 0.8
K10-BS-M	12-10 A.W.G. 4-6 mm²	.591 15.0	.213 5.4	.134 3.4	.039 1.0

Box Quantity: (M)=1000
UL File #E9809
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Terminal Material: Copper Tubular


Tool used with Non-Insulated Butt Splice



ERG2002

Nylon Insulated Wire Joint





Catalog Number	Wire Range	Dimension inch mm						
		W	F	L	D	E	T	C
KN18-WJ-M	22-16 A.W.G. 1.25 mm²	.209 5.3	.315 8.0	.827 21.0	.386 9.8	.276 7.0	.020 0.5	.091 2.3
KN14-WJ-M	16-14 A.W.G. 2 mm²	.236 6.0	.354 9.0	.827 21.0	.394 10.0	.276 7.0	.020 0.5	.122 3.1
KN10-WJ-D	12-10 A.W.G. 5.5 mm²	.299 7.6	.394 10.0	1.004 25.5	.492 12.5	.295 7.5	.028 0.7	.157 4.0

Box Quantity: (W)=250; (D)=500; (M)=1000
UL File #E66716
CSA File #LR4503

See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.


Maximum Electrical Rating: 105°C 300 Volts Max.
Terminal Material: Copper Tube


Tool used with Nylon Insulated Wire Joint



ERG2500WJ

Vinyl Insulated Quick Splice





Catalog Number	Wire Range	Dimension inch mm		
		W	L	Color
KV14-OOQS-D	22-18 A.W.G. 0.5-1.0 mm²	.787 20.0	1.063 27.0	red
KV18-OOQS-D	18-14 A.W.G. .75-2.5 mm²	.787 20.0	1.063 27.0	blue
KV10-OOQS*	12-10 A.W.G. 4-6 mm²	.807 20.5	1.358 34.5	yellow

Box Quantity: (W)=250; (D)=500; (M)=1000
*** 200 piece quantity only.**
See pages in back of catalog for complete tool information.
Tool and Die Selection Chart on page M42.

Maximum Electrical Rating: 105°C 600 Volts Max.
Terminal Material: Brass

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. www.tnb.com



ERG2500

Comfort Crimp® Terminal Tools
ERG-2500, ERG-2500F, ERG-2002, ERG-2500WJ

Ergonomic ratchet style hand tool used for installing insulated Spec-Kon® terminals. Specially designed ergonomic handles distributes the crimping force evenly across the user's hands. Helps reduce the risk of Carpal Tunnel Syndrome, the cause of almost one of every two industrial injuries. Ratchet design greatly reduces handle forces over conventional hand tools and incorporates the Shure-Stake® mechanism which ensures full compression every time. Color coded die nests (insulated only) facilitates getting the right terminal in the right nest.



ERG2002




ERG2500WJ

Catalog Number	Terminal Style	Wire Range
ERG-2500	All Insulated Terminals, Splices, & Disconnects (except Flags)	22 - 10 AWG
ERG-2002	All Non-Insulated Terminals, Splices, & Disconnects	22 - 10 AWG
ERG-2500F	Nylon Fully Insulated Female Flag Disconnects	22 - 14 AWG
ERG-2500WJ	Nylon Insulated Wire Joint	22 - 10 AWG


*** Contact Customer Service for availability of this product. Longer lead times may be required.**

Tool Gauging Requirements

Catalog Number	Wire Range	Gauging (inches)
ERG-2500	22 - 16 AWG 16 - 14 AWG 12 - 10 AWG	.080 - .088 .091 - .099 .119 - .127
ERG-2002	22 - 16 AWG 16 - 14 AWG 12 - 10 AWG	.067 - .062 .089 - .084 .115 - .110
ERG-2500F	22 - 14 AWG	–
ERG-2500WJ	22 - 10 AWG	–



- Installs Nylon and Vinyl Insulated Terminals, Disconnects, and Splices 22-10 AWG
- The force required to release the Shure-Stake® mechanism should be no less than 20 lbs.



- Installs Non-Insulated Terminals, Disconnects, and Splices 22-10 AWG
- The force required to release the Shure-Stake® mechanism should be no less than 15 lbs.

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.

Plier Type Tools
WT111M and WT112M



WT111M




WT112M


Economical plier type hand tool used for installing non-insulated and insulated Spec-Kon® terminals. Range of sizes include 22 AWG through 10 AWG. Nose of the tool is equipped with wire cutters for convenience.

Catalog Number	Description	Std. Pkg	Wt. each
WT111M	Non-Insulated Plier Tool with Cutter for 22-10 AWG	1	1
WT112M	Insulated and Non-Insulated Plier Tool with Cutter for 22-10 AWG	1	1

- These tools are designed with wire cutters for customer convenience.



- WT111M - Installs 22-10 AWG non-insulated Spec-Kon® Terminals
- Gauging for 22-14 AWG 0.027 - 0.053 in.
- Gauging for 12-10 AWG 0.072 - 0.098 in.



- WT112 M - Installs insulated and non-insulated Spec-Kon® terminals, splices, disconnects, and wire joints 22-10 AWG
- Gauging for insulated terminals .092 - .104
- Gauging for non-insulated terminals .044 - .056

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. www.tnb.com



TBM6



TBM6S


Toggle Type Tools TBM6 and TBM6S

Toggle type hand tool for installing large insulated and non-insulated Spec-Kon® terminals. Terminal size ranges from #8 AWG through #2 AWG MCM. Interchangeable dies are ordered separately. The TBM6S features the Shure-Stake® mechanism which ensures full compression every time.


Catalog Number	Terminal Size For use with Spec-Kon®	Std. Pkg	Wt. each
TBM6	8 - 2 AWG	1	9
TBM6S	8 - 2 AWG	1	9

Installing Dies

Nest Stationary Die	Indentor Movable Die	Terminal Size	Gauging (inches)
Installing dies for non-insulated Spec-Kon® terminals			
11805	**11802**	8 - 6 AWG	.157-.177
11806	**11802**	4 AWG	.196-.216
11807	**11802**	2 AWG	.224-.244
Installing dies for insulated Spec-Kon® terminals			
11822	–	8 AWG	.192 - .212
11823	–	6 AWG	.244-.264



- For use with non-insulated terminals Cat No. TBM6 and TBM6S



- For use with insulated terminals Cat No. TBM6 and TBM6S

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.

Spec-Kon®
Automated Tools

NEW



Universal Applicator


The Universal Applicator from Thomas & Betts offers a unique opportunity to use the range of quality Spec-Kon tape-mounted terminals on your own machine. If you have the press already, there's no need for additional costly investments on your plant floor to convert to another terminal. Our applicator will handle the entire range of Mylar-tape fed terminals offered in the Spec-Kon product line, and allows you more flexibility on your production line. Fast and simple. If you have the press, we've got the applicator.



The new Spec-Kon Universal Applicator is designed for quick terminal conversions in plant equipment such as the Applitek press.


Spec-Kon® Universal Applicator includes these prominent features:

- Allows industry-standard presses to use Spec-Kon® Terminal Products (AMP-compatible).
- Includes stand-alone presses.
- Also compatible with major brands of wire processing equipment.
- One single part – no additional accessories needed (excluding dies).
- Quick-change of tooling / dies in minutes – simply done with an Allen wrench.
- Convenient Crimp Height adjustment for range of crimping force fine-tuning.
- 22-10 AWG Range.
- Crimps Insulated and Uninsulated Spec-Kon® terminals.
- Crimps Nylon and Vinyl insulation terminals.
- All-metallic construction for years of use.
- Creates UL Listed Crimps.
- One year warranty, excluding dies.



M

Spec-Kon®



Catalog Number	Description	Std. Pkg	Wt. each
KT2500UA	Spec-Kon® Universal Applicator	1	17 lbs.

AMP is a registered trademark of Tyco Electronics Corporation

Die Chart

Catalog Number	Description	Wire Range
KT-18Z	Insulated Terminals, Disconnects, & Splices	22-16 AWG
KT-14Z	Insulated Terminals, Disconnects, & Splices	16-14 AWG
KT-10Z	Insulated Terminals, Disconnects, & Splices	12-10 AWG
KTU-18Z	Insulated Terminals, Disconnects, & Splices	22-16 AWG
KTU-14Z	Insulated Terminals, Disconnects, & Splices	16-14 AWG
KTU-10Z	Insulated Terminals, Disconnects, & Splices	12-10 AWG

Dimensions: 7.5" x 5.75" x 4.25"
Range: 22 AWG - 10 AWG Insulated and Noninsulated
See instruction manual for complete maintenance, installation and operating characteristics for this tool.

Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**

Spec-Kon®
Automated Tools

NEW



KT-2500 with reel and foot switch

Bench Mounted Tool for Mylar Tape – KT-2500


Compact, pneumatically operated bench mounted tool for crimping insulated and non-insulated Spec-Kon® terminals on mylar tape. Dies are color coded to match terminal insulation. Unit comes with fully guarded foot pedal and clear plastic safety guard over the die area for added safety. Unit incorporates the Shure-Stake® mechanism which ensures full compression every time.

Catalog Number	Description	Std. Pkg
KT-2500	Bench Mounted Crimping Tool for Mylar Tape	1


Space Requirement: 30"w x 20"h x 20"d
Weight: 55 lbs.
Wire Range: 22-10 AWG
Air Pressure: 90-125 psi input air supply

Installing Dies

Catalog Number	Terminal Style	Wire Range	Gauging (inches)
Installing dies for insulated Spec-Kon® terminals			
KT-18	Insulated Terminals & Disconnects	22-16 AWG	.105 - .109
KT-14	Insulated Terminals & Disconnects	16-14 AWG	.115 - .119
KT-10	Insulated Terminals & Disconnects	12-10 AWG	.134 - .138
Installing dies for non-insulated Spec-Kon® terminals			
KTU-18	Non-Insulated Terminals	22-16 AWG	.072 - .077
KTU-14	Non-Insulated Terminals	16-14 AWG	.096 - .101
KTU-10	Non-Insulated Terminals	12-10 AWG	.126 - .131



Insulated Terminals



Non-Insulated Terminals

M

Spec-Kon®

Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. **www.tnb.com**



ERG3000 Battery Powered Tool

Compact, portable, battery operated tool for crimping loose piece insulated and non-insulated Spec-Kon® terminals. Dies are color coded to match terminal insulation. Multi-nested die used for non-insulated which reduces setup time. Unit incorporates the Shure-Stake® mechanism which ensures full compression every time.

Catalog Number	Description	Wt. (lb.)
Standard Components	*Note: The part number ERG-3000 refers to a complete kit consisting of one ERG-3001,one ERG-3002, two ERG-3003, one ERG-3004, and one ERG-3005.*	
ERG-3001	Base Unit	11.0
ERG-3002	Hose & Tool Head Assembly	3.5
ERG-3003	NiCd Battery	1.3
ERG-3004	15 min. Battery Charge	3.0
ERG-3005	Carrying Case	6.3
ERG-3006	AC Adapter	7.0
ERG-3007	Benchmount	1.0
ERG-3008	Switch	2.5
ERG-3000	Complete Kit (see note below)	26.4

- Start button initiates crimping work cycle.
- Safety catch protects fingers when changing die sets.
- Compact tool head operates in tight spaces and weighs just 1.65 pounds to reduce fatigue.
- Swivel head improves access to small spaces.
- Control lever opens jaws for terminal installation and die change.
- Interchangeable dies accommodate Spec-Kon® terminals from 22-10 AWG.
- Easy-to-see indicator lamps show when ERG 3000 is ready to operate or in a work cycle.
- Portable base power unit houses the battery, hydraulic pump, fluid reservoir, and electronic control unit.
- Durable, flexible 8.2 foot hose connects the tool head to the base power unit for extra reach.

Installing Dies

Catalog Number	Terminal Style	Wire Range	Gauging (inches)
Installing dies for insulated Spec-Kon® terminals			
KT-18Y	Insulated Terminals & Disconnects	22-16 AWG	.105 - .109
KT-14Y	Insulated Terminals & Disconnects	16-14 AWG	.115 - .119
KT-10Y	Insulated Terminals & Disconnects	12-10 AWG	.134 - .138
Installing dies for non-insulated Spec-Kon® terminals			
KTU-2214Y	Non-Insulated Terminals (Two Nested Die Set)	22-16 AWG 16-14 AWG	.072 - .077 .096 - .101
KTU-10Y	Non-Insulated Terminals	12-10 AWG	.126 - .131

Technical Data

Base Unit

Working pressure	3625 psi
Power supply	NiCd Battery 12 V DC or AC/DC converter 110 V 60 Hz
Work cycle	1.5-3 seconds
Weight (with battery)	11 lb. (without tool/hose pack)
Dimensions	13.77"L x 7.28" W x 5.12" D
Temperature range	-4° to 122°F

Tool Head Assembly

Press force	3371 lbf
Weight (tool only)	1.65 lb.
Diameter of handle	1.61 in.
Length of handle	8.86 in.
Length of hose	7.22 ft.

Battery

Type	NiCd 12 V, rechargeable
Recharging time	15 min.
Number of recharges	1000

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.



13500 with foot switch

Bench Mounted Tool – 13500


Compact, pneumatically operated bench mounted tool for crimping loose piece insulated and non-insulated Spec-Kon® terminals. Dies are color coded to match terminal insulation. Multi-nested die used for non-insulated which reduces setup time. Unit incorporates the Shure-Stake® mechanism which ensures full compression every time.


Catalog Number	Description	Std. Pkg
13500	Bench Mounted Crimping Tool	1

Space Requirement: 8" X 12"
Weight: 10-12 lbs.
Wire Range: 8AWG - 2AWG Insulated & Uninsulated Terminals.
Air Pressure: 85-100 psi

Installing Dies

Catalog Number	Terminal Style	Wire Range	Gauging (inches)
Installing dies for insulated Spec-Kon® terminals			
KT-18X **KT-14X** **KT-10X**	Insulated Terminals & Disconnects	22-16 AWG 16-14 AWG 12-10 AWG	.105 - .109 .115 - .119 .134 - .138
Installing dies for non-insulated Spec-Kon® terminals			
KTU-2210X*	Non-Insulated Terminals (Three Nested Die Set)	22-16 AWG 16-14 AWG 12-10 AWG	.072 - .077 .096 - .101 .126 - .131





- For use with non-insulated terminals Cat No. TBM6 and TBM6S

- For use with insulated terminals Cat No. TBM6 and TBM6S

M
Spec-Kon®

Thomas&Betts

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.

Tool and Die Selection Chart

Spec-Kon® Terminals		Plier Tool	Ergonomic Hand Tool	KT-2500 Pneumatic Tool Die Part Numbers			13500 Pneumatic Tool Die Part Numbers			Erg-3000 Power Hand Tool Die Part Numbers		
Nylon Terminal (22-10 AWG)	KN or KNF	WT112M	ERG-2500	KT-18	KT-14	KT-10	KT-18X	KT-14X	KT-10X	KT-18Y	KT-14Y	KT-10Y
Nylon Butt Splice		WT112M	ERG-2500	N/A	N/A	N/A	KT-18X	KT-14X	KT-10X	KT-18Y	KT-14Y	KT-10Y
Nylon Disconnect		WT112M	ERG-2500	KT-18	KT-14	KT-10	KT-18X	KT-14X	KT-10X	KT-18Y	KT-14Y	KT-10Y
Nylon Terminal (8-6 AWG)		TBM6	N/A	KT-8	KT-6	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Vinyl Terminal (22-10 AWG)	KV or KVF	WT112M	ERG-2500	KT-18	KT-14	KT-10	KT-18X	KT-14X	KT-10X	KT-18Y	KT-14Y	KT-10Y
Vinyl Butt Splice		WT112M	ERG-2500	KT-18	KT-14	KT-10	KT-18X	KT-14X	KT-10X	KT-18Y	KT-14Y	KT-10Y
Vinyl Disconnect		WT112M	ERG-2500	KT-18	KT-14	KT-10	KT-18X	KT-14X	KT-10X	KT-18Y	KT-14Y	KT-10Y
Non Insulated Terminal (22-10 AWG)	K	WT111M	ERG-2002	KTU-18	KTU-14	KTU-10	KTU-2210X	KTU-2210X	KTU-2210X	KTU-2214Y KTU-10Y	KTU-2214Y KTU-10Y	KTU-2214Y KTU-10Y
Non Insulated Butt Splice		WT111M	ERG-2002	N/A	N/A	N/A	KTU-2210X	KTU-2210X	KTU-2210X	KTU-2214Y KTU-10Y	KTU-2214Y KTU-10Y	KTU-2214Y KTU-10Y
Non Insulated Terminal (8-6 AWG)		TBM6	N/A	N/A	N/A	N/A	KTU-8	KTU-6	N/A	N/A	N/A	N/A
Wire Joints	KN or KNF	WT112M	ERG-2500WJ	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Flag Terminals		N/A	ERG-2500F	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A

Strip Length Chart

Description	Terminal Series	Wire Strip Length
Non-Insulated Terminals	K18 K14 K10 K8 K6 K4 K2	1/4” 1/4” 5/16” 3/8” 7/16” 1/2" 9/16"
Vinyl Insulated Terminals	KV18 KV14 KV10 KV8 KV6	1/4” 1/4” 5/16” 3/8" 7/16"
Nylon Insulated Terminals	KN18 KN14 KN10 KN8 KN6	1/4” 1/4” 5/16” 3/8” 7/16”
Vinyl Insulated Disconnects	KV18 KV14 KV10	1/4” 1/4” 5/16”
Nylon Insulated Disconnects	KN18 KN14 KN10	1/4” 1/4” 5/16”
Vinyl Insulated Butt Splices	KV18 KV14 KV10	5/16” 5/16” 5/16”
Nylon Insulated Butt Splices	KN18 KN14 KN10	1/4” 1/4” 1/4”
Nylon Wire Joints	K18 K14 K10	9/32” 9/32” 11/32”

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice. www.tnb.com

Stud Size Chart

Standard Stud Size U.S		Stud Diameter Inches mm	Terminal Hole Dia. Inches mm	Spec-Kon Stud Size Part No. Designation
	#2 M2	.086 2.18	.090 2.29	2
	#4 M2,5	.112 2.84	.118 3.00	4
	#5 M3	.125 3.18	.127 3.23	5
	#6 M3,5	.138 3.51	.146 3.71	6
	#8 M4	.164 4.17	.173 4.39	8
	#10 M5	.190 4.83	.198 5.03	10
	1/4 M6	.250 6.35	.270 6.86	14
	5/16 M8	.312 7.92	.330 8.38	56
	3/8 M10	.375 9.53	.385 9.78	38
	1/2 M12	.500 12.7	.520 13.21	12
	5/8 M16	.625 15.88	.650 16.51	58
	3/4 M18	.750 19.05	.810 20.57	34

Common Conductor Size Chart

Size	No. of Strands	Individual Strand Size	Conductor Size	
		Inches mm	Inches mm	Circl. Mil Area mm
22AWG	7	.0096 0.24	.028 0.74	640 0.74
20AWG	10	.0100 0.25	.038 0.97	1020 0.519
18AWG	16	.0100 0.25	.048 1.22	1620 0.823
16AWG	26	.0100 0.25	.060 1.52	2580 1.310
14AWG	7	.0242 0.61	.073 1.85	4110 2.080
12AWG	7	.0305 0.77	.092 2.34	6530 3.310
10AWG	7	.0385 0.98	.116 2.95	10,380 5.261
8AWG	7	.0486 1.23	.146 3.71	16,510 8.367
6AWG	7	.0612 1.55	.184 4.67	26,240 13.30
4AWG	7	.0772 1.96	.232 5.89	41,740 21.15
2AWG	7	.0974 2.47	.292 7.42	66,360 33.62
1AWG	19	.0664 1.69	.332 8.43	83,690 42.41
1/10AWG	19	.0745 1.89	.373 9.47	105,600 53.49
2/0AWG	19	.0837 2.13	.418 10.62	133,100 67.43
3/0AWG	19	.0940 2.39	.470 11.94	167,800 85.01
4/0AWG	19	.1055 2.68	.528 13.41	211,600 107.2
250MCM	37	.0822 2.09	.575 14.61	250,000 127
300MCM	37	.0900 2.29	.630 16.00	300,000 152
350MCM	37	.0973 2.47	.681 17.29	350,000 177
400MCM	37	.1040 2.64	.728 18.49	400,000 203
500MCM	37	.1162 2.95	.813 20.65	500,000 253
600MCM	61	.0992 2.52	.893 22.68	600,000 304
750MCM	61	.1109 2.82	.998 25.35	750,000 380
800MCM	61	.1145 2.91	1.031 26.19	800,000 405
1000MCM	61	.1280 3.25	1.152 29.26	1,000,000 507

© 2002 Thomas & Betts Corporation. Specifications are subject to change without notice.

FS Boxes and Covers











Applications :

- FS boxes are CSA approved for wet locations
- FS device boxes are installed in applications that require a rugged unit to accept wiring devices, switches, electronic components and terminal blocks
- FS device boxes provide spacious accessible wiring chambers that are a convenient location to maintain or change a system; pull conductors; make splices or branch conduits
- FS device boxes, when used with an appropriate cover, provide a raintight installation
- Both weatherproof and dry location covers are available

Features/Benefits :

- FS device boxes are sand casted or die casted using copper free (less than 0.004 copper content) aluminum alloys.
- FS device boxes incorporate external hub design that provides maximum wiring capacity
- FS device boxes have precision molded NPT threaded hubs allowing trouble-free field installation of rigid conduit
- FS device boxes are available in 1-7/8 in. and 2-5/8 in. depth
- Carlon® nonmetallic weatherproof FS covers are UV resistant, flame retardant and non-corrosive

Standard Materials :

- CIFS and CIFD device boxes: sand cast, copper free aluminum (less than 0.004 copper content)
- CIFSU: die cast, copper free aluminum (less than 0.004 copper content)
- FS covers: die cast aluminum, sand cast aluminum or nonmetallic

Compliances :


Compliances as noted on each page of the catalogue include:


- CSA Certified
- UL Listed

FS Boxes and Covers



CIFDC-1/2






Cat. No.	Hub Size	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	Cu (in.)
FDC Boxes - 2-5/8 in. Deep (Cast Aluminum)												
CIFDC-1/2	2 x 1/2	1	2	4-5/16	2-13/16	15/16	2-5/8	1-3/8	2-7/8	2-3/8	2-5/32	22.5
CIFDC-3/4	2 x 3/4	1	2	4-5/16	2-13/16	15/16	2-5/8	1-3/8	2-7/8	2-3/8	2-13/32	22.5
CIFDC-1	2 x 1	1	2	4-5/16	2-13/16	1-3/8	2-5/8	1-5/8	2-7/8	2-3/8	2-13/32	22.5




CIFS-1G







CIFS-2G





CIFS-3G


Cat. No.	Hub Size	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	Cu (in.)
FS Boxes - 1-7/8 in. Deep (Cast Aluminum)												
CIFS-1G-1/2	1 x 1/2	1	3	4-5/16	2-13/16	13/16	1-7/8	1-1/4	2-7/8	2-5/16	1-9/16	14.0
CIFS-1G-3/4	1 x 3/4	1	3	4-5/16	2-13/16	13/16	1-7/8	1-1/2	2-7/8	2-5/16	1-9/16	14.0
CIFS-1G-1	1 x 1	1	3	4-5/16	2-13/16	13/16	1-7/8	1-3/4	2-7/8	2-5/16	1-9/16	14.0
CIFS-2G-1/2	1 x 1/2	2	3	4-3/8	4-11/16	7/8	1-7/8	1-1/4	2-7/8	4-1/4	1-5/8	26.0
CIFS-2G-3/4	1 x 3/4	2	3	4-3/8	4-11/16	7/8	1-7/8	1-9/16	2-7/8	4-1/4	1-5/8	26.0
CIFS-2G-1	1 x 1	2	3	4-3/8	4-11/16	7/8	1-7/8	1-3/4	2-7/8	4-1/4	1-5/8	26.0
CIFS-3G-1/2	1 x 1/2	3	3	4-3/8	6-1/2	7/8	1-7/8	1-1/4	2-7/8	6-1/16	1-5/8	41.0
CIFS-3G-3/4	1 x 3/4	3	3	4-3/8	6-1/2	7/8	1-7/8	1-9/16	2-7/8	6-1/16	1-5/8	41.0

FS Boxes and Covers




CIFSC-1G







CIFSC-3G-3/4




Cat. No.	Hub Size (in.)	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	Cu (in.)
FSC Boxes - 1-7/8 in. Deep (Cast Aluminum)												
CIFSC-1G-1/2	2 x 1/2	1	4	4-5/16	2-13/16	27/32	1-7/8	1-1/4	2-7/8	2-5/16	1-9/16	14.0
CIFSC-1G-3/4	2 x 3/4	1	4	4-5/16	2-13/16	27/32	1-7/8	1-1/2	2-7/8	2-5/16	1-9/16	14.0
CIFSC-1G-1	2 x 1	1	4	4-5/16	2-13/16	27/32	1-7/8	1-3/4	2-7/8	2-5/16	1-9/16	14.0
CIFSC-2G-1/2	2 x 1/2	2	4	4-3/8	4-11/16	31/32	1-7/8	1-1/4	2-7/8	4-1/4	1-5/8	26.0
CIFSC-2G-3/4	2 x 3/4	2	4	4-3/8	4-11/16	31/32	1-7/8	1-9/16	2-7/8	4-1/4	1-5/8	26.0
CIFSC-2G-1	2 x 1	2	4	4-3/8	4-11/16	31/32	1-7/8	1-3/4	2-7/8	4-1/4	1-5/8	26.0
CIFSC-3G-3/4	2 x 3/4	3	4	4-3/8	6-1/2	29/32	1-7/8	1-9/16	2-7/8	6-1/8	1-5/8	41.0



CIFSCC-1G






Cat. No.	Hub Size (in.)	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	J (in.)	Cu (in.)
FSCC Boxes - 1-7/8 in. Deep (Cast Aluminum)													
CIFSCC-1G-1/2	3 x 1/2	1	3	4-5/16	2-13/16	27/32	1-7/8	1-1/4	2-7/8	2-5/16	1-9/16	1-9/16	14.0
CIFSCC-1G-3/4	3 x 3/4	1	3	4-5/16	2-13/16	27/32	1-7/8	1-1/2	2-7/8	2-5/16	1-9/16	1-3/4	14.0



CIFS-1G-1/2-HV / CIFS-1G-3/4-HV





Cat. No.	Hub Size (in.)	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	J (in.)	Cu (in.)
347 Volt FS Box Kits - 1-7/8 in. Deep (Cast Aluminum)													
CIFS-1G-1/2-HV*	1 x 1/2	1	3	4-5/8	2-13/16	13/16	1-7/8	1-1/4	2-7/8	2-5/16	1-9/16	–	14.0
CIFS-1G-3/4-HV*	1 x 3/4	1	3	4-5/8	2-13/16	13/16	1-7/8	1-1/2	2-7/8	2-5/16	1-9/16	–	14.0

* For dry locations only
Includes stamped aluminum "CIFS-9HV" 347 V covers (not raintight)


FS Boxes and Covers



CIFSF (1 face)




CIFST (2 faces)



Cat. No.	Hub Size (in.)	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	J (in.)	Cu (in.)
FSF Box - 3 in. Deep (Cast Aluminum)													
CIFSF	2	–	–	4-5/16	2-3/4	31/32	2-7/8	2-7/8	2-13/16	2-13/32	1-15/32	–	30.5
FST Box - 3-5/8 in. Deep (Cast Aluminum)													
CIFST	2	–	–	4-5/16	2-3/4	1-3/8	3-3/8	3	2-7/8	2-5/16	2-13/16	–	38.7



CIFSU



Cat. No.	Hub Size (in.)		No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	K (in.)	Cu (in.)
Universal FSU Boxes - 2-3/8 in. Deep (Cast Aluminum)													
	End	Bottom											
CIFSU-1/2	2 x 1/2	1/2	2	4-5/16	2-3/4	13/16	2-3/8	1-1/8	2-13/16	2-1/2	1-29/32	7/16	18.5
CIFSU-3/4	2 x 3/4	3/4	2	4-5/16	2-3/4	13/16	2-3/8	1-1/8	2-13/16	2-1/2	2	7/16	18.5

Supplied with close up plugs




FG-09080

Cat. No.	Description
Mounting Lugs for CI-FSU	
FG-09080	Mounting lugs for a 3-Hole universal FSU box, 2-3/8 in. deep


FS Boxes and Covers

Single Gang



CCD-FS





CFSH-G




CWPDR





CWPDR-FS




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)	K (in.)	L (in.)
Single Gang Horizontal Covers (Cast Aluminum)							
CCD-FS	Silver – box mount (zinc)	2-13/16	4-9/16	1-7/8	3-1/4	–	–
CFSH-G	One GFCI receptacle – box mount	2-13/16	4-9/16	1-7/8	3-1/4	1-11/32	2-21/32
CWPDR	One duplex receptacle – device mount	2-13/16	4-9/16	–	–	–	–
CWPDR-FS	One duplex receptacle – box mount	2-13/16	4-9/16	1-7/8	3-1/4	–	–



CFSDR




CFSR-G





CWPV-G




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)	K (in.)	L (in.)
Single Gang Vertical Covers (Cast Aluminum)							
CFSDR	One duplex receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8	–	–
CFSR-G	One GFCI receptacle – box mount	4-9/16	2-13/16	3-1/4		2-21/32	1-11/32
CWPV-G	One GFCI receptacle – device mount	4-9/16	2-13/16	3-1/4	–	2-21/32	1-11/32


CFST




CFSTF




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang Switch Covers (Cast Aluminum)					
CFST	One plunger – box mount	4-9/16	2-13/16	3-1/4	1-7/8
CFSTF	One lever switch – box mount	4-9/16	2-13/16	3-1/4	1-7/8

FS Boxes and Covers


Single Gang


CCB





CCB-FS



CFSB




CIFS-100G


Nº de catalogue	Description	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang Blank Covers (Cast Aluminum)					
CCB	Silver – device mount (stamped aluminum)	4-9/16	2-13/16	3-9/32	–
CCB-FS	Silver – box mount (stamped aluminum)	4-9/16	2-13/16	3-1/4	1-7/8
CFSB	Blank – box mount	4-9/16	2-13/16	3-1/4	1-7/8
CIFS-100G	Blank – box mount (gasket glued on cover)	4-3/8	2-14/16	3-1/4	1-7/8


CFSR Series



Cat. No.	Description	Nominal Size (in.)	Max. Device Face Dia.	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang Vertical Covers (Cast Aluminum)							
CFSR-L	Single receptacle – box mount	1-9/16	1.600	4-9/16	2-13/16	3-1/4	1-7/8
CFSR-S	Single receptacle – box mount	1-3/8	1.395	4-9/16	2-13/16	3-1/4	1-7/8
CFSR-X	Single receptacle – box mount	1-27/32	1.865	4-9/16	2-13/16	3-1/4	1-7/8
CFSR-XL	Single receptacle – box mount	2-1/8	2.145	4-9/16	2-13/16	3-1/4	1-7/8
CFSR-Y	Single receptacle – box mount	1-3/4	1.750	4-9/16	2-13/16	3-1/4	1-7/8


FS-GKV




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang Gasket					
FS-GKV*	Single Gang – box mount – gasket	4-9/16	2-13/16	3-1/4	1-7/8

* CSA not applicable


FS Boxes and Covers

Two Gang



2CWPDR





2CWPR-M





2CFSR-M





2CFST




2CCB




2CFSB




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)	K (in.)
Two Gang (Cast Aluminum)						
2CWPDR	Two duplex receptacles – device mount	4-9/16	4-5/8	–	1-13/16	–
2CWPR-M	Single receptacle – hole – device mount	4-9/16	4-5/8	2-3/8	1-13/16	2-1/4
2CFSR-M	Single receptacle – hole – box mount	4-9/16	4-5/8	3-3/4	3-3/4	2-1/4
2CFST	Plunger style cover	4-9/16	4-5/8	3-3/4	3-3/4	–
2CCB	Silver – device mount (stamped aluminum)	4-9/16	4-5/8	3-9/32	1-13/16	–
2CFSB	Blank cover – box mount	4-9/16	4-5/8	3-3/4	3-3/4	–


FS Boxes and Covers

Dry-Tite® FS Covers Two Gang



CIFS-42





CIFS-62




CIFS-69





CIFS-92




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)
Two gang FS Covers* (Stamped Aluminum)					
CIFS-42*	Blank – two gang – box mount	4-5/8	4-9/16	3-1/4	3-11/16
CIFS-62*	Two duplex receptacles – box mount	4-5/8	4-9/16	3-1/4	3-11/16
CIFS-69*	One duplex receptacles, one toggle switch – box mount	4-5/8	4-9/16	3-1/4	3-11/16
CIFS-92*	Two toggle switches – box mount	4-5/8	4-9/16	3-1/4	3-11/16

* CIFS covers are CSA approved only



2CDR




2CTS




2CTDR




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)
Two Gang (Cast Aluminum)					
2CDR	Two duplex receptacles – device mount	4-9/16	4-5/8	–	1-13/16
2CTS	Two switch – device mount	4-9/16	4-5/8	2-3/8	1-13/16
2CTDR	One switch and one duplex receptacle – device mount	4-9/16	4-5/8	2-3/8	–

Dry-Tite® covers are approved for dry locations only


FS Boxes and Covers

Dry-Tite® FS Covers Single Gang


CDR





CTS




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang (Cast Aluminum)					
CDR	One duplex receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8
CTS	One switch receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8



CIFS-4




CIFS-7 / CIFS-5





CIFS-6





CIFS-9


CIFS-9-HV



Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)	K (in.)
Single Gang FS Covers (Stamped Aluminum)						
CIFS-4	Blank – single gang – box mount	4-9/16	2-13/16	3-1/4	1-7/8	–
CIFS-5	15 A single receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8	1-13/16
CIFS-6	One duplex receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8	–
CIFS-7	20 A single locking receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8	1-19/32
CIFS-9	One toggle switch – box mount	4-9/16	2-13/16	3-1/4	1-7/8	–
CIFS-9-HV	One toggle switch (347 V) – box mount	4-9/16	2-13/16	3-1/4	1-7/8	–


CRL




Cat. No.	Description	Nominal Size (in.)	Max. Device Face Dia.	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang (Cast Aluminum)							
CRL	Single receptacle – box mount	1-9/16	1.600	4-9/16	2-13/16	3-1/4	1-7/8
CRS	Single receptacle – box mount	1-3/8	1.395	4-9/16	2-13/16	3-1/4	1-7/8

Dry-Tite® covers are approved for dry locations only


FS Boxes and Covers

Single Gang


All sizes take standard covers and accessories or devices. Integral mounting feet provide easy mounting. Grounding lugs included.




Type FSE



Type FSS




Type FSC




Type FSCC






Type FD





Type FDC





Type FDE

Cat. No.	Description	Size (in.)	Volume Cu. In.	Std. Ctn. Qty.
Type FSE				
C980DFN-CTN	For dead-end terminations.	1/2	18	12
C980EFN-CTN		3/4	18	12
C980FFN-CTN		1	18	8
Type FSS				
C982DFN-CTN	For multiple dead-end circuit terminations or where additional support is required in stub-up applications.	1/2	18	12
C982EFN-CTN		3/4	18	12
C982FFN-CTN		1	18	8
Type FSC				
C981DFN-CTN	For through terminations.	1/2	18	12
C981EFN-CTN		3/4	18	12
C981FFN-CTN		1	18	8
Type FSCC				
C979DFN	For multiple through circuit termintions or where additional support is required in stub-up applications.	1/2	18	15
C979EFN		3/4	18	15
C979FFN		1	18	15

Cat. No.	Description	Size (in.)	Volume Cu. In.	Std. Ctn. Qty.
Type FD				
C981DFN-CTN	For terminations where hub requirements vary according to application – hubs easily made with flared wood bit or hole saw.	–	25	10
Type FDC				
C9811EN	For through terminations where large devices or additional wiring capacity is required.	3/4	25	10
C9811FN		1	25	10
Type FDE				
C9801DN	For dead-end terminations where large devices or additional wiring capacity is required.	1/2	25	10
C9801EN		3/4	25	10
C9801FN		1	25	10

FS Boxes and Covers


Single Gang


E98SRCN-CAR


E98G20N


E98G30N-CAR


E98G5FN-CAR




Cat. No.	Description	Colour	A (in.)	B (in.)	C (in.)	D (in.)	F (in.)	G (in.)
Single Gang Vertical Covers (Nonmetallic)								
E98SRCN-CAR	For 15 A or other single receptacles under 1.375 dia.	Grey	4-53/64	3-11/16	53/64	1-25/64 ± 1/16	3-1/4	1-57/64
E98G20N	For 20 A or other single receptacles under 1.625 dia.	Grey	4-53/64	3-11/16	53/64	1-41/64 ± 1-23/32	3-1/4	1-57/64
E98G30N-CAR	For 30 A or other single receptacles under 1.750 dia.	Grey	4-53/64	3-11/16	53/64	1-49/64 ± 1-23/32	3-1/4	1-57/64
E98G5FN-CAR	For 50 A or other single receptacles under 2.250 dia.	Grey	4-53/64	3-11/16	53/64	2-1/4 ± 1/16	3-1/4	1-57/64


E98GCBN


E98SSCN-CAR



E98GDRN-CAR


E98GFCN-CAR




Cat. No.	Description	Colour	A (in.)	B (in.)	C (in.)	F (in.)	G (in.)
Single Gang Vertical Covers (Nonmetallic)							
E98SSCN-CAR	Single switch	Grey	4-53/64	3-11/16	53/64	3-1/4	1-57/64
E98GDRN-CAR	Duplex receptacle	Grey	4-53/64	3-11/16	53/64	3-1/4	1-57/64
E98GFCN-CAR	GFCI receptacle – device opening dimensions: 2-5/8 H x 1-5/16 W	Grey	4-53/64	3-11/16	53/64	3-1/4	1-57/64


E98TSCN





E980CN-CAR



Cat. No.	Description	Colour	A (in.)	B (in.)	C (in.)	F (in.)	G (in.)
Single Gang Vertical Covers (Nonmetallic)							
E98TSCN	Toggle switch	Grey	4-3/4	3	31/32	3-9/32	1-57/64
E980CN-CAR	Supplied with stainless steel mounting screws and gasket	Grey	4-5/8	2-7/8	–	3-9/32	1-57/64
E980CM-CAR	Supplied with stainless steel mounting screws and gasket	White	4-5/8	2-7/8	–	3-9/32	1-57/64


E98DHGN-CAR


E98GHGN-CAR




Cat. No.	Description	Colour	A (in.)	B (in.)	C (in.)	F1 (in.)	F1/2 (in.)	G (in.)
Single Gang Horizontal Covers (Nonmetallic)								
E98DHGN-CAR	Duplex receptacle	Grey	3-1/8	4-7/8	13/16	1-57/64	61/64	3-9/32
E98GHGN-CAR	GFCI horizontal	Grey	3-1/8	4-7/8	13/16	1-57/64	61/64	3-9/32


FS Boxes and Covers

Two Gang


All sizes take standard covers and accessories or devices. Integral mounting feet provide easy mounting. Grounding screws are included.



Type 2FSC



Type 2FSE



Type FS


Cat. No.	Description	Size (in.)	Volume Cu. In.	Std. Ctn. Qty.
Type 2FSC				
CE9812DR	For through terminations where two devices or additional wiring capacity is required.	1/2	32	4
CE9812E-CTN		3/4	32	10
CE9812FR		1	32	10
Type 2FSE				
CE9802D-CTN	For dead-end terminations where two devices or additional wiring capacity is required.	1/2	18	10
CE9802E-CTN		3/4	18	10
CE9802FR		1	18	1
Type FS				
CE9802	For terminations where hub requirements vary according to application - hubs easily made with flared wood bit or hole saw.	N/A	32	10

FS Boxes and Covers

Two Gang




E9G2DDN-CAR





E9G2SSN







E9G2DSN-CAR




E9G2GTN-CAR







E9802CN-CAR



Cat. No.	Description	Colour	A (in.)	B (in.)	C (in.)	D (in.)	F (in.)	G (in.)
Two Gang Covers (Nonmetallic)								
E9G2DDN-CAR	Double duplex	Grey	4-27/34	4-27/34	–	–	3-17/64	3-9/16
E9G2SSN	Double toggle	Grey	4-55/64	3-17/64	–	–	3-17/64	3-9/16
E9802CN-CAR	Supplied with stainless steel mounting screws and gasket	Grey	4-55/64	4-55/64	–	–	3-17/64	3-9/16
E9G2GTN-CAR	Combination toggle / GFCI	Grey	4-55/64	3-17/64	1-53/64	55/64	3-17/64	3-9/16
E9G2DSN-CAR	Combination toggle / duplex receptacle	Grey	4-55/64	3-17/64	1-53/64	55/64	3-17/64	3-9/16

FS Boxes and Covers











Applications :

- FS boxes are CSA approved for wet locations
- FS device boxes are installed in applications that require a rugged unit to accept wiring devices, switches, electronic components and terminal blocks
- FS device boxes provide spacious accessible wiring chambers that are a convenient location to maintain or change a system; pull conductors; make splices or branch conduits
- FS device boxes, when used with an appropriate cover, provide a raintight installation
- Both weatherproof and dry location covers are available

Features/Benefits :

- FS device boxes are sand casted or die casted using copper free (less than 0.004 copper content) aluminum alloys.
- FS device boxes incorporate external hub design that provides maximum wiring capacity
- FS device boxes have precision molded NPT threaded hubs allowing trouble-free field installation of rigid conduit
- FS device boxes are available in 1-7/8 in. and 2-5/8 in. depth
- Carlon® nonmetallic weatherproof FS covers are UV resistant, flame retardant and non-corrosive

Standard Materials :

- CIFS and CIFD device boxes: sand cast, copper free aluminum (less than 0.004 copper content)
- CIFSU: die cast, copper free aluminum (less than 0.004 copper content)
- FS covers: die cast aluminum, sand cast aluminum or nonmetallic

Compliances :


Compliances as noted on each page of the catalogue include:


- CSA Certified
- UL Listed

FS Boxes and Covers



CIFDC-1/2






Cat. No.	Hub Size	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	Cu (in.)
FDC Boxes - 2-5/8 in. Deep (Cast Aluminum)												
CIFDC-1/2	2 x 1/2	1	2	4-5/16	2-13/16	15/16	2-5/8	1-3/8	2-7/8	2-3/8	2-5/32	22.5
CIFDC-3/4	2 x 3/4	1	2	4-5/16	2-13/16	15/16	2-5/8	1-3/8	2-7/8	2-3/8	2-13/32	22.5
CIFDC-1	2 x 1	1	2	4-5/16	2-13/16	1-3/8	2-5/8	1-5/8	2-7/8	2-3/8	2-13/32	22.5




CIFS-1G







CIFS-2G





CIFS-3G


Cat. No.	Hub Size	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	Cu (in.)
FS Boxes - 1-7/8 in. Deep (Cast Aluminum)												
CIFS-1G-1/2	1 x 1/2	1	3	4-5/16	2-13/16	13/16	1-7/8	1-1/4	2-7/8	2-5/16	1-9/16	14.0
CIFS-1G-3/4	1 x 3/4	1	3	4-5/16	2-13/16	13/16	1-7/8	1-1/2	2-7/8	2-5/16	1-9/16	14.0
CIFS-1G-1	1 x 1	1	3	4-5/16	2-13/16	13/16	1-7/8	1-3/4	2-7/8	2-5/16	1-9/16	14.0
CIFS-2G-1/2	1 x 1/2	2	3	4-3/8	4-11/16	7/8	1-7/8	1-1/4	2-7/8	4-1/4	1-5/8	26.0
CIFS-2G-3/4	1 x 3/4	2	3	4-3/8	4-11/16	7/8	1-7/8	1-9/16	2-7/8	4-1/4	1-5/8	26.0
CIFS-2G-1	1 x 1	2	3	4-3/8	4-11/16	7/8	1-7/8	1-3/4	2-7/8	4-1/4	1-5/8	26.0
CIFS-3G-1/2	1 x 1/2	3	3	4-3/8	6-1/2	7/8	1-7/8	1-1/4	2-7/8	6-1/16	1-5/8	41.0
CIFS-3G-3/4	1 x 3/4	3	3	4-3/8	6-1/2	7/8	1-7/8	1-9/16	2-7/8	6-1/16	1-5/8	41.0

FS Boxes and Covers




CIFSC-1G







CIFSC-3G-3/4




Cat. No.	Hub Size (in.)	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	Cu (in.)
FSC Boxes - 1-7/8 in. Deep (Cast Aluminum)												
CIFSC-1G-1/2	2 x 1/2	1	4	4-5/16	2-13/16	27/32	1-7/8	1-1/4	2-7/8	2-5/16	1-9/16	14.0
CIFSC-1G-3/4	2 x 3/4	1	4	4-5/16	2-13/16	27/32	1-7/8	1-1/2	2-7/8	2-5/16	1-9/16	14.0
CIFSC-1G-1	2 x 1	1	4	4-5/16	2-13/16	27/32	1-7/8	1-3/4	2-7/8	2-5/16	1-9/16	14.0
CIFSC-2G-1/2	2 x 1/2	2	4	4-3/8	4-11/16	31/32	1-7/8	1-1/4	2-7/8	4-1/4	1-5/8	26.0
CIFSC-2G-3/4	2 x 3/4	2	4	4-3/8	4-11/16	31/32	1-7/8	1-9/16	2-7/8	4-1/4	1-5/8	26.0
CIFSC-2G-1	2 x 1	2	4	4-3/8	4-11/16	31/32	1-7/8	1-3/4	2-7/8	4-1/4	1-5/8	26.0
CIFSC-3G-3/4	2 x 3/4	3	4	4-3/8	6-1/2	29/32	1-7/8	1-9/16	2-7/8	6-1/8	1-5/8	41.0



CIFSCC-1G






Cat. No.	Hub Size (in.)	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	J (in.)	Cu (in.)
FSCC Boxes - 1-7/8 in. Deep (Cast Aluminum)													
CIFSCC-1G-1/2	3 x 1/2	1	3	4-5/16	2-13/16	27/32	1-7/8	1-1/4	2-7/8	2-5/16	1-9/16	1-9/16	14.0
CIFSCC-1G-3/4	3 x 3/4	1	3	4-5/16	2-13/16	27/32	1-7/8	1-1/2	2-7/8	2-5/16	1-9/16	1-3/4	14.0



CIFS-1G-1/2-HV / CIFS-1G-3/4-HV





Cat. No.	Hub Size (in.)	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	J (in.)	Cu (in.)
347 Volt FS Box Kits - 1-7/8 in. Deep (Cast Aluminum)													
CIFS-1G-1/2-HV*	1 x 1/2	1	3	4-5/8	2-13/16	13/16	1-7/8	1-1/4	2-7/8	2-5/16	1-9/16	–	14.0
CIFS-1G-3/4-HV*	1 x 3/4	1	3	4-5/8	2-13/16	13/16	1-7/8	1-1/2	2-7/8	2-5/16	1-9/16	–	14.0

* For dry locations only
Includes stamped aluminum "CIFS-9HV" 347 V covers (not raintight)


FS Boxes and Covers



CIFSF (1 face)




CIFST (2 faces)



Cat. No.	Hub Size (in.)	No. of Gangs	No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	J (in.)	Cu (in.)
FSF Box - 3 in. Deep (Cast Aluminum)													
CIFSF	2	–	–	4-5/16	2-3/4	31/32	2-7/8	2-7/8	2-13/16	2-13/32	1-15/32	–	30.5
FST Box - 3-5/8 in. Deep (Cast Aluminum)													
CIFST	2	–	–	4-5/16	2-3/4	1-3/8	3-3/8	3	2-7/8	2-5/16	2-13/16	–	38.7



CIFSU



Cat. No.	Hub Size (in.)		No. of Lugs	A (in.)	B (in.)	C (in.)	D (in.)	E (in.)	F (in.)	G (in.)	H (in.)	K (in.)	Cu (in.)
Universal FSU Boxes - 2-3/8 in. Deep (Cast Aluminum)													
	End	Bottom											
CIFSU-1/2	2 x 1/2	1/2	2	4-5/16	2-3/4	13/16	2-3/8	1-1/8	2-13/16	2-1/2	1-29/32	7/16	18.5
CIFSU-3/4	2 x 3/4	3/4	2	4-5/16	2-3/4	13/16	2-3/8	1-1/8	2-13/16	2-1/2	2	7/16	18.5

Supplied with close up plugs




FG-09080

Cat. No.	Description
Mounting Lugs for CI-FSU	
FG-09080	Mounting lugs for a 3-Hole universal FSU box, 2-3/8 in. deep


FS Boxes and Covers

Single Gang



CCD-FS





CFSH-G




CWPDR





CWPDR-FS




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)	K (in.)	L (in.)
Single Gang Horizontal Covers (Cast Aluminum)							
CCD-FS	Silver – box mount (zinc)	2-13/16	4-9/16	1-7/8	3-1/4	–	–
CFSH-G	One GFCI receptacle – box mount	2-13/16	4-9/16	1-7/8	3-1/4	1-11/32	2-21/32
CWPDR	One duplex receptacle – device mount	2-13/16	4-9/16	–	–	–	–
CWPDR-FS	One duplex receptacle – box mount	2-13/16	4-9/16	1-7/8	3-1/4	–	–



CFSDR




CFSR-G





CWPV-G




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)	K (in.)	L (in.)
Single Gang Vertical Covers (Cast Aluminum)							
CFSDR	One duplex receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8	–	–
CFSR-G	One GFCI receptacle – box mount	4-9/16	2-13/16	3-1/4		2-21/32	1-11/32
CWPV-G	One GFCI receptacle – device mount	4-9/16	2-13/16	3-1/4	–	2-21/32	1-11/32


CFST




CFSTF




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang Switch Covers (Cast Aluminum)					
CFST	One plunger – box mount	4-9/16	2-13/16	3-1/4	1-7/8
CFSTF	One lever switch – box mount	4-9/16	2-13/16	3-1/4	1-7/8

FS Boxes and Covers


Single Gang


CCB




CCB-FS



CFSB





CIFS-100G

Nº de catalogue	Description	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang Blank Covers (Cast Aluminum)					
CCB	Silver – device mount (stamped aluminum)	4-9/16	2-13/16	3-9/32	–
CCB-FS	Silver – box mount (stamped aluminum)	4-9/16	2-13/16	3-1/4	1-7/8
CFSB	Blank – box mount	4-9/16	2-13/16	3-1/4	1-7/8
CIFS-100G	Blank – box mount (gasket glued on cover)	4-3/8	2-14/16	3-1/4	1-7/8


3.4


CFSR Series



Cat. No.	Description	Nominal Size (in.)	Max. Device Face Dia.	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang Vertical Covers (Cast Aluminum)							
CFSR-L	Single receptacle – box mount	1-9/16	1.600	4-9/16	2-13/16	3-1/4	1-7/8
CFSR-S	Single receptacle – box mount	1-3/8	1.395	4-9/16	2-13/16	3-1/4	1-7/8
CFSR-X	Single receptacle – box mount	1-27/32	1.865	4-9/16	2-13/16	3-1/4	1-7/8
CFSR-XL	Single receptacle – box mount	2-1/8	2.145	4-9/16	2-13/16	3-1/4	1-7/8
CFSR-Y	Single receptacle – box mount	1-3/4	1.750	4-9/16	2-13/16	3-1/4	1-7/8


FS-GKV




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang Gasket					
FS-GKV*	Single Gang – box mount – gasket	4-9/16	2-13/16	3-1/4	1-7/8

* CSA not applicable


FS Boxes and Covers

Two Gang



2CWPDR





2CWPR-M





2CFSR-M





2CFST




2CCB




2CFSB




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)	K (in.)
Two Gang (Cast Aluminum)						
2CWPDR	Two duplex receptacles – device mount	4-9/16	4-5/8	–	1-13/16	–
2CWPR-M	Single receptacle – hole – device mount	4-9/16	4-5/8	2-3/8	1-13/16	2-1/4
2CFSR-M	Single receptacle – hole – box mount	4-9/16	4-5/8	3-3/4	3-3/4	2-1/4
2CFST	Plunger style cover	4-9/16	4-5/8	3-3/4	3-3/4	–
2CCB	Silver – device mount (stamped aluminum)	4-9/16	4-5/8	3-9/32	1-13/16	–
2CFSB	Blank cover – box mount	4-9/16	4-5/8	3-3/4	3-3/4	–


FS Boxes and Covers

Dry-Tite® FS Covers Two Gang



CIFS-42





CIFS-62




CIFS-69





CIFS-92




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)
Two gang FS Covers* (Stamped Aluminum)					
CIFS-42*	Blank – two gang – box mount	4-5/8	4-9/16	3-1/4	3-11/16
CIFS-62*	Two duplex receptacles – box mount	4-5/8	4-9/16	3-1/4	3-11/16
CIFS-69*	One duplex receptacles, one toggle switch – box mount	4-5/8	4-9/16	3-1/4	3-11/16
CIFS-92*	Two toggle switches – box mount	4-5/8	4-9/16	3-1/4	3-11/16

* CIFS covers are CSA approved only



2CDR




2CTS




2CTDR




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)
Two Gang (Cast Aluminum)					
2CDR	Two duplex receptacles – device mount	4-9/16	4-5/8	–	1-13/16
2CTS	Two switch – device mount	4-9/16	4-5/8	2-3/8	1-13/16
2CTDR	One switch and one duplex receptacle – device mount	4-9/16	4-5/8	2-3/8	–

Dry-Tite® covers are approved for dry locations only


FS Boxes and Covers

Dry-Tite® FS Covers Single Gang


CDR





CTS




Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang (Cast Aluminum)					
CDR	One duplex receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8
CTS	One switch receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8



CIFS-4




CIFS-7 / CIFS-5





CIFS-6





CIFS-9


CIFS-9-HV



Cat. No.	Description	A (in.)	B (in.)	F (in.)	G (in.)	K (in.)
Single Gang FS Covers (Stamped Aluminum)						
CIFS-4	Blank – single gang – box mount	4-9/16	2-13/16	3-1/4	1-7/8	–
CIFS-5	15 A single receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8	1-13/16
CIFS-6	One duplex receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8	–
CIFS-7	20 A single locking receptacle – box mount	4-9/16	2-13/16	3-1/4	1-7/8	1-19/32
CIFS-9	One toggle switch – box mount	4-9/16	2-13/16	3-1/4	1-7/8	–
CIFS-9-HV	One toggle switch (347 V) – box mount	4-9/16	2-13/16	3-1/4	1-7/8	–


CRL




Cat. No.	Description	Nominal Size (in.)	Max. Device Face Dia.	A (in.)	B (in.)	F (in.)	G (in.)
Single Gang (Cast Aluminum)							
CRL	Single receptacle – box mount	1-9/16	1.600	4-9/16	2-13/16	3-1/4	1-7/8
CRS	Single receptacle – box mount	1-3/8	1.395	4-9/16	2-13/16	3-1/4	1-7/8

Dry-Tite® covers are approved for dry locations only


FS Boxes and Covers

Single Gang


All sizes take standard covers and accessories or devices. Integral mounting feet provide easy mounting. Grounding lugs included.




Type FSE



Type FSS




Type FSC




Type FSCC






Type FD





Type FDC





Type FDE

Cat. No.	Description	Size (in.)	Volume Cu. In.	Std. Ctn. Qty.
Type FSE				
C980DFN-CTN	For dead-end terminations.	1/2	18	12
C980EFN-CTN		3/4	18	12
C980FFN-CTN		1	18	8
Type FSS				
C982DFN-CTN	For multiple dead-end circuit terminations or where additional support is required in stub-up applications.	1/2	18	12
C982EFN-CTN		3/4	18	12
C982FFN-CTN		1	18	8
Type FSC				
C981DFN-CTN	For through terminations.	1/2	18	12
C981EFN-CTN		3/4	18	12
C981FFN-CTN		1	18	8
Type FSCC				
C979DFN	For multiple through circuit termintions or where additional support is required in stub-up applications.	1/2	18	15
C979EFN		3/4	18	15
C979FFN		1	18	15

Cat. No.	Description	Size (in.)	Volume Cu. In.	Std. Ctn. Qty.
Type FD				
C981DFN-CTN	For terminations where hub requirements vary according to application – hubs easily made with flared wood bit or hole saw.	–	25	10
Type FDC				
C9811EN	For through terminations where large devices or additional wiring capacity is required.	3/4	25	10
C9811FN		1	25	10
Type FDE				
C9801DN	For dead-end terminations where large devices or additional wiring capacity is required.	1/2	25	10
C9801EN		3/4	25	10
C9801FN		1	25	10

FS Boxes and Covers


Single Gang


E98SRCN-CAR


E98G20N


E98G30N-CAR


E98G5FN-CAR




Cat. No.	Description	Colour	A (in.)	B (in.)	C (in.)	D (in.)	F (in.)	G (in.)
Single Gang Vertical Covers (Nonmetallic)								
E98SRCN-CAR	For 15 A or other single receptacles under 1.375 dia.	Grey	4-53/64	3-11/16	53/64	1-25/64 ± 1/16	3-1/4	1-57/64
E98G20N	For 20 A or other single receptacles under 1.625 dia.	Grey	4-53/64	3-11/16	53/64	1-41/64 ± 1-23/32	3-1/4	1-57/64
E98G30N-CAR	For 30 A or other single receptacles under 1.750 dia.	Grey	4-53/64	3-11/16	53/64	1-49/64 ± 1-23/32	3-1/4	1-57/64
E98G5FN-CAR	For 50 A or other single receptacles under 2.250 dia.	Grey	4-53/64	3-11/16	53/64	2-1/4 ± 1/16	3-1/4	1-57/64


E98GCBN


E98SSCN-CAR



E98GDRN-CAR


E98GFCN-CAR




Cat. No.	Description	Colour	A (in.)	B (in.)	C (in.)	F (in.)	G (in.)
Single Gang Vertical Covers (Nonmetallic)							
E98SSCN-CAR	Single switch	Grey	4-53/64	3-11/16	53/64	3-1/4	1-57/64
E98GDRN-CAR	Duplex receptacle	Grey	4-53/64	3-11/16	53/64	3-1/4	1-57/64
E98GFCN-CAR	GFCI receptacle – device opening dimensions: 2-5/8 H x 1-5/16 W	Grey	4-53/64	3-11/16	53/64	3-1/4	1-57/64


E98TSCN





E980CN-CAR



Cat. No.	Description	Colour	A (in.)	B (in.)	C (in.)	F (in.)	G (in.)
Single Gang Vertical Covers (Nonmetallic)							
E98TSCN	Toggle switch	Grey	4-3/4	3	31/32	3-9/32	1-57/64
E980CN-CAR	Supplied with stainless steel mounting screws and gasket	Grey	4-5/8	2-7/8	–	3-9/32	1-57/64
E980CM-CAR	Supplied with stainless steel mounting screws and gasket	White	4-5/8	2-7/8	–	3-9/32	1-57/64


E98DHGN-CAR


E98GHGN-CAR




Cat. No.	Description	Colour	A (in.)	B (in.)	C (in.)	F1 (in.)	F1/2 (in.)	G (in.)
Single Gang Horizontal Covers (Nonmetallic)								
E98DHGN-CAR	Duplex receptacle	Grey	3-1/8	4-7/8	13/16	1-57/64	61/64	3-9/32
E98GHGN-CAR	GFCI horizontal	Grey	3-1/8	4-7/8	13/16	1-57/64	61/64	3-9/32


FS Boxes and Covers

Two Gang


All sizes take standard covers and accessories or devices. Integral mounting feet provide easy mounting. Grounding screws are included.



Type 2FSC



Type 2FSE



Type FS


Cat. No.	Description	Size (in.)	Volume Cu. In.	Std. Ctn. Qty.
Type 2FSC				
CE9812DR	For through terminations where two devices or additional wiring capacity is required.	1/2	32	4
CE9812E-CTN		3/4	32	10
CE9812FR		1	32	10
Type 2FSE				
CE9802D-CTN	For dead-end terminations where two devices or additional wiring capacity is required.	1/2	18	10
CE9802E-CTN		3/4	18	10
CE9802FR		1	18	1
Type FS				
CE9802	For terminations where hub requirements vary according to application - hubs easily made with flared wood bit or hole saw.	N/A	32	10

FS Boxes and Covers

Two Gang




E9G2DDN-CAR





E9G2SSN







E9G2DSN-CAR




E9G2GTN-CAR








E9802CN-CAR



Cat. No.	Description	Colour	A (in.)	B (in.)	C (in.)	D (in.)	F (in.)	G (in.)
Two Gang Covers (Nonmetallic)								
E9G2DDN-CAR	Double duplex	Grey	4-27/34	4-27/34	–	–	3-17/64	3-9/16
E9G2SSN	Double toggle	Grey	4-55/64	3-17/64	–	–	3-17/64	3-9/16
E9802CN-CAR	Supplied with stainless steel mounting screws and gasket	Grey	4-55/64	4-55/64	–	–	3-17/64	3-9/16
E9G2GTN-CAR	Combination toggle / GFCI	Grey	4-55/64	3-17/64	1-53/64	55/64	3-17/64	3-9/16
E9G2DSN-CAR	Combination toggle / duplex receptacle	Grey	4-55/64	3-17/64	1-53/64	55/64	3-17/64	3-9/16

Star Teck® (ST) – Series Fittings for Teck and ACWU Cable



Materials and Finishes
Available in a broad range of materials and finishes. Aluminum, steel, stainless steel, PVC coated.

Easy Installation and Dependable Grounding
Exclusive power-grip. Provides a grip that's high up on the cable—not on the first convolution—so precise cable preparation is not critical.

Dependable Grounding
Power-Grip grounding ring is non-magnetic stainless steel. Provides 360° long-term dependable grounding. It makes immediate contact with the cable.

Dependable Service
Stainless steel retaining ring. Withstands corrosive environments. Non-magnetic.

Built-in O-Ring
provides 360° seal even when enclosure surface is rough or uneven.

Sharp Biting Teeth
provide superior electrical bonding and allow corrosive liquids to drain away quickly.


Watertight
Tapered bushing. Cone shaped to provide a secure, tight fit while eliminating cupping or water in vertical installations.

Easy to Install in Tight Spaces
Low profile gland nut fits tight spaces. Has grooves for screwdriver installation, and flats for a wrench. Durable and reusable with funnel entry for easy cable insertion.

Easy Installation



1. Prepare cable



2. Insert cable



3. Tighten gland nut

Warning:

Always ensure that the system is de-energized before performing any installation.

Suggested specifications for metal-clad cable or teck cable fittings in hazardous locations:

1. All metal-clad cable fittings for jacketed and non-jacketed interlocked armour cable, continuous corrugated cable or teck cable shall be approved by a nationally recognized testing laboratory, inspection agency or product evaluation organization.
2. Where corrugated-jacketed, metal-clad cable exposed to intermittent or continuous moisture is terminated into a threaded opening, the fitting shall be watertight type furnished with:

a. an elastomeric beveled bushing.

b. a funnel entry, splined gland nut.

c. a non-magnetic, stainless steel grounding device with dual grounding action.

d. a taper threaded hub.

e. a hexagonal body and gland nut as manufactured by Thomas & Betts (aluminum Series ST050-464).

f. a built in sealing O-ring on hub side.

3. With single conductor cable and/or in corrosive environments, aluminum fittings such as Thomas & Betts Series ST050-464 shall be installed. Where explosion-proof or dust-ignition-proof boxes are required by the code, Star Teck® fittings must be used in conjunction with an approved sealing fitting.


Star Teck® (ST) – Series Fittings for Teck and ACWU Cable



3.5

Star Teck® (ST Series)

Star Teck® cable fittings are designed to accommodate a broad range of cables, thereby minimizing the possibility of mismatched cables and fittings in the field. They are available in hub sizes from 1/2 to 4 inches, and will handle outer jacket diameters from 0.525 to 4.340 inches.



Cat. No.	Hub Size (in.)	Range Over Jacket (in.)		Dimensions (in.)		
		min.	max.	A	B*	C
ST038-461S†	3/8	0.344	0.535	0.344	2.020	0.995
ST050-462	1/2	0.525	0.650	0.390	2.020	1.224
ST050-464	1/2	0.600	0.760	0.480	2.020	1.363
ST050-465	1/2	0.725	0.885	0.607	2.133	1.633
ST050-466	1/2	0.825	0.985	0.607	2.133	1.633
ST075-467	3/4	0.880	1.065	0.809	2.450	2.080
ST075-468	3/4	1.025	1.205	0.809	2.450	2.080
ST100-469	1	1.187	1.375	1.034	2.601	2.230
ST125-470	1-1/4	1.350	1.625	1.177	3.282	2.824
ST125-550	1-1/4	1.500	1.625	1.365	3.282	2.824
ST125-471	1-1/4	1.600	1.875	1.365	3.282	2.824
ST150-472	1-1/2	1.700	1.965	1.552	3.620	3.260
ST150-473	1-1/2	1.900	2.187	1.595	3.620	3.260
ST200-551	2	1.900	2.187	1.710	3.640	3.620
ST200-474	2	2.100	2.375	1.990	3.640	3.620
ST200-475	2	2.300	2.565	2.052	3.640	4.020
ST200-476	2	2.500	2.750	2.052	3.640	4.020
ST250-477	2-1/2	2.380	2.640	2.255	4.700	4.750
ST250-478	2-1/2	2.580	2.840	2.455	4.700	4.750
ST300-479	3	2.790	3.060	2.655	4.700	5.050
ST300-480	3	3.000	3.270	2.885	4.790	5.480
ST300-481	3	3.210	3.480	3.057	4.790	5.480
ST350-482	3-1/2	3.420	3.690	3.285	4.790	5.980
ST350-483	3-1/2	3.610	3.870	3.455	4.790	5.980
ST400-484	4	3.810	4.030	3.625	4.840	6.435
ST400-485	4	3.965	4.185	3.770	4.840	6.435
ST400-486	4	4.120	4.340	3.935	4.840	6.435

* Approximate dimension before installation
† Only available in steel

Materials

Aluminum: The above listed catalogue numbers relate to aluminum fittings. The body and gland nut on hub sizes 1/2 to 1 inch are machined from copper-free bar stock and 1-1/4 to 4 inches are made of cast copper-free aluminum

Steel: To order a steel or malleable iron fitting, add the suffix "S" to the catalogue number (example ST050-464S). The body and gland nut on hub sizes 1/2 to 1 inch are made of steel and 1-1/4 to 4 inches are made of malleable iron. Plating is electro-deposited zinc

Stainless Steel: To order a 316 stainless steel fitting, add the suffix "SS" to the catalogue number (example ST050-464SS). Only available for 1/2 thru 2 inch hub sizes

PVC-Coated Aluminum and Steel: To order, add the suffix "PVC" to the catalogue number (example ST050-464PVC or ST050-464SPVC)

Note - When using fittings on single conductor cable, aluminum fittings and aluminum locknuts must be used


Certifications

Type HLA. CSA Certified Class II, Divisions 1 and 2, Groups E, F, and G; Class III and Enclosure Type 4, Type 4X, Classes I, II and III. Suitable for Class I Division 1 locations when used in combination with a certified Class I sealing fitting. Also suitable for Class I Division 2 when installed in accordance with the applicable electrical code

Complies with IEC requirements for Class I, Zones 1 and 2, when used in combination with a certified Class I hazardous location sealing fitting

UL Listed Class I, Division 2; Class II, Division 2 and Class III. Meets sealing requirements for type 4 enclosures
PVC-coated fittings are only approved for ordinary location areas (OLA)


18 AWG 300V Instrumentation Cable



Product Code	AWG Size	# of Pairs or Triads	OD		Weight Aluminum		Weight Steel	
			In	mm	lb/mft	kg/km	lb/mft	kg/km
33H1801X	18	1 Pair	0.6	15.2	160	238	258	384
33H1802X	18	2 Pair	0.78	19.8	247	368	384	572
33H1804X	18	4 Pair	0.88	22.4	340	504	500	744
33H1806X	18	6 Pair	0.98	24.9	420	625	644	958
33H1808X	18	8 Pair	1.03	26.2	543	808	827	1230
33H1812X	18	12 Pair	1.28	32.5	725	1070	1045	1555
33H1816X	18	16 Pair	1.37	34.8	850	1265	1210	1801
33H1824X	18	24 Pair	1.63	41.4	1100	1637	1510	2247
33H1836X	18	36 Pair	1.8	45.7	1465	2180	1960	2917
33K1801X	18	1 Triad	0.61	15.5	175	260	275	409
33K1802X	18	2 Triad	0.81	20.6	275	409	417	621
33K1804X	18	4 Triad	0.93	23.6	385	573	555	826
33K1806X	18	6 Triad	1.115	28.2	535	796	780	1161
33K1808X	18	8 Triad	1.18	30	680	1012	995	1481
33K1812X	18	12 Triad	1.4	35.6	916	1363	1215	1808
33K1816X	18	16 Triad	1.5	38.1	10200	1518	1400	2083
33K1824X	18	24 Triad	1.8	45.7	1335	1987	1775	2642


3.6

18 AWG 600V Instrumentation Cable




Product Code	AWG Size	# of Pairs or Triads	OD		Weight Aluminum		Weight Steel	
			In	mm	lb/mft	kg/km	lb/mft	kg/km
33I1801X	18	1 Pair	0.61	15.5	154	229	257	382
33I1802X	18	2 Pair	0.82	20.83	238	354	387	575
33I1804X	18	4 Pair	0.96	24.5	355	499	504	750
33I1836X	18	36 Pair	1.85	47.1	1721	2561	2300	3423
33I1850X	18	50 Pair	2.29	58.1	2472	3679	3361	5001
33L1808X	18	8 Triad	1.29	32.8	673	1002	988	1470

14 AWG Multi-Conductor Teck 90 (XLPE) -40°C 600V



Product Code	No. of Cond.	Bonding AWG (Bare Copper)	Insulation Thickness		Inner Jacket Thickness		Inner Jacket Diameter		Armour Diameter		Outer Jacket Diameter		Weight Aluminum (Armoured)	
			Inches	mm	Inches	mm	Inches	mm	Inches	mm	Inches	mm	lbs/mft	kg/km
3.6.1 **19A1402**	2	14	.030	0.76	0.045	1.14	0.369	9.37	0.600	15.24	0.688	17.48	191	284
19A1403	3	14	.030	0.76	0.045	1.14	0.390	9.91	0.621	15.77	0.709	18.01	225	335
19A1404	4	14	.030	0.76	0.045	1.14	0.444	11.27	0.676	17.17	0.761	19.33	266	396
19A1405	5	14	.030	0.76	0.045	1.14	0.472	11.99	0.703	17.86	0.787	19.99	306	455
19A1406	6	14	.030	0.76	0.045	1.14	0.515	13.08	0.743	18.87	0.828	21.03	316	471
19A1407	7	14	.030	0.76	0.045	1.14	0.522	13.26	0.755	19.18	0.844	21.44	338	502
19A1408	8	14	.030	0.76	0.060	1.52	0.597	15.16	0.825	20.96	0.909	23.09	384	571
19A1410	10	14	.030	0.76	0.060	1.52	0.671	17.04	0.898	22.81	0.984	24.99	448	667
19A1412	12	14	.030	0.76	0.060	1.52	0.700	17.78	0.927	23.55	1.013	25.73	489	728
19A1415	15	14	.030	0.76	0.060	1.52	0.750	19.05	0.990	25.15	1.090	27.69	583	868
19A1420	20	14	.030	0.76	0.060	1.52	0.850	21.59	1.105	28.07	1.189	30.20	766	1140
19A1425	25	14	.030	0.76	0.080	2.03	0.983	24.99	1.239	31.47	1.326	33.68	852	1268
19A1430	30	14	.030	0.76	0.080	2.03	1.060	26.92	1.311	33.30	1.399	35.53	995	1481
19A1440	40	14	.030	0.76	0.080	2.03	1.179	29.95	1.431	36.35	1.519	38.86	124	1822
19A1450	50	14	.030	0.76	0.080	2.03	1.282	32.56	1.535	38.99	1.642	41.71	1468	2184

16 AWG 600V Armcon



Product Code	# of Cond.	Amp @ 30°C	Nominal OD inner jacket		Nominal OD Armour		Nominal OD Outer Jacket		Weight Aluminum (Armoured)	
			mm	In	mm	In	mm	In	lbs/mft	kg/km
46A1602-40	2	10	8.79	0.35	14.88	0.59	17.73	0.7	195	290.22
46A1603-40	3	10	9.49	0.37	15.6	0.61	18.43	0.73	216.12	321.62
46A1604-40	4	8	10.25	0.4	16.36	0.64	19.2	0.76	238.06	354.27
46A1605-40	5	8	10.92	0.43	17.02	0.67	19.87	0.78	259.84	386.68
46A1606-40	6	8	11.84	0.47	17.93	0.71	20.78	0.82	284.81	423.85
46A1607-40	7	7	12.75	0.5	18.85	0.74	21.69	0.85	310.22	461.66
46A1608-40	8	7	14.46	0.57	20.55	0.81	23.4	0.92	360.81	536.94
46A1610-40	10	7	15.65	0.62	21.74	0.86	24.59	0.97	397.91	592.15
46A1612-40	12	7	16.1	0.63	22.2	0.87	25.05	0.99	427.17	635.7
46A1615-40	15	7	17.32	0.68	23.42	0.92	26.26	1.03	478.14	711.55
46A1620-40	20	7	19.61	0.77	25.2	0.99	28.04	1.1	613.89	913.57
46A1625-40	25	6	22.76	0.9	28.85	1.14	31.7	1.25	759.63	1130.46
46A1630-40	30	6	24.01	0.95	30.1	1.19	32.9	1.3	834.31	1241.59
46A1640-40	40	6	26.72	1.05	32.82	1.29	35.66	1.4	1008.65	1501.04
46A1650-40	50	6	29.59	1.16	35.69	1.41	38.52	1.52	1174.61	1748

3.6.2

16 AWG 600V Armcon Connectors

No. of Cond.	Product Code	Connectors			
		OZG/Crouse Hinds	EGS/Iberville	Explosion Proof	Resin
2	46A1602-40	41TECK0502	41TMC2050075A	41TMC2X050075A	RAPIDEX30
3	46A1603-40	41TECK0503	41TMC2050099A	41TMC2X050099A	RAPIDEX30
4	46A1604-40	41TECK0503	41TMC2050099A	41TMC2X050099A	RAPIDEX30
5	46A1605-40	41TECK0503	41TMC2050099A	41TMC2X050099A	RAPIDEX30
6	46A1606-40	41TECK0503	41TMC2050099A	41TMC2X050099A	RAPIDEX30
7	46A1607-40	41TECK0755	41TMC2075118A	41TMC2X075118A	RAPIDEX30
8	46A1608-40	41TECK0755	41TMC2075118A	41TMC2X075118A	RAPIDEX30
10	46A1610-40	41TECK0755	41TMC2075118A	41TMC2X075118A	RAPIDEX30
12	46A1612-40	41TECK0755	41TMC2075118A	41TMC2X075118A	RAPIDEX30
15	46A1615-40	41TECK0756	41TMC2075118A	41TMC2X075118A	RAPIDEX30
20	46A1620-40	41TECK1007	41TMC2100137A	41TMC2X100137A	RAPIDEX30
25	46A1625-40	41TECK1007	41TMC2100137A	41TMC2X100137A	RAPIDEX30
30	46A1630-40	41TECK1258	41TMC2125162A	41TMC2X125162A	RAPIDEX30
40	46A1640-40	41TECK1258	41TMC2125162A	41TMC2X125162A	RAPIDEX30
50	46A1650-40	41TECK1259	41TMC2125162A	41TMC2X125162A	RAPIDEX30

REVIEWED BY GC CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: May 27, 2019

VEOLIA

SHOP DRAWINGS

Network Architecture

Date : 2019-05-24

General Information			
Project	WWTP UPGRADE - IQALUIT		
Client:	Kudlik Construction Ltd.	Project Number	2018-062
To:	Sandra Rousseau P.Eng., Project Manger	E-mail:	srousseau@kudlik.biz
Contractor	Veolia Water Technologies Canad Inc.	Project Number	5000218036
Address	4105 Sartelon, Ville St. Laurent PQ, H4S 2B3		
Project Manger:	Clément Bekaert	E-mail:	clement.bekaert@veolia.com
Phone:	514-334-7230 x 3243	Cell:	514-246-6232

Information on the Equipment			
Specialty:	Electrical / automation		
Equipment:	BFP Polymer Dosing system / DAF Polymer dosing system		
Drawing Reference:			
Specification reference:	46.36.11		
Article:			
Revision:	Rev02		
Titre:	Hydrapol Panel - Polymer dosing junction boxes- Electrical Drawings		
Numero client:	DA-Veolia-ED-02-Hydrapol		
Numero Veolia	5000218036-EPL-0006-AUT-VWT, EPL-0007-AUT-VWT, EPL-0004-AUT-VWT, EPL-0005-AUT-VWT		
Envoyer pour:	Approbation/Information:	Information	

Consultant Approval

SHOP DRAWINGS ARE REVIEWED UNLESS NOTED OTHERWISE

REVIEWED AS MODIFIED	X
REVISE & RESUBMIT	
SEAL & SIGNATURE REQUIRED	

Stantec

DATE June 3, 2019

SIGNATURE

REVIEW BY STANTEC IS FOR THE SOLE PURPOSE OF ASCERTAINING GENERAL CONFORMITY WITH DESIGN. CONTRACTOR IS RESPONSIBLE FOR DIMENSIONS, FABRICATION AND CONSTRUCTION METHODS, COORDINATION OF SUB-TRADES, DETAIL DESIGN OF COMPONENTS, AND ERRORS OR OMISSIONS ON SHOP DRAWINGS.

-Ensure that 'ESD triggered" is included in the "General Fault" output to CPL-901.
-Ensure that the aging tanks are complete with loop splitters for level indication duplicate output signal to CPL-901.
-Include CSA certifications in O&M manual submission.

4105 Sartelon
Ville St. Laurent, PQ
H4S-2B3

Phone: 514-334-7230
Fax: 514-334-5070
www.veoliawatertechnologies.ca

HYDRAPOL 250 CONTROL PANEL
PROJECT - 5000218036
LCP-04-700
DAF POLYMER DOSING SYSTEM

REV.	DESCRIPTION	DATE	REV.	VERIC/HK	APPR.	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-06	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND MAY CONTAIN CONFIDENTIAL AND PROPRIETARY OR OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO "I.D.C." AND ARE SUBMITTED TO YOU IN CONFIDENCE. THIS DOCUMENT MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED BY THE SUBMISSION OF THIS DOCUMENT. IT MUST NOT BE COPIED, CONFIDENTIAL AND PRI LEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, INSETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PERMISSION OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE ATTACHED PURPOSES OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE CONSTRUED AS GRANTING ANY LICENSE OR RIGHT OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET PEUT CONTENIR DES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES DESIGN CONCEPTS ET L'INFORMATION CONTENUE DANS CE DOCUMENT SONT CONFIDENTIELS ET PROPRIÉTAIRES À "I.D.C." ET SONT SOUMIS À VOUS EN CONFIANCE. CE DOCUMENT DOIT ÊTRE UTILISÉ UNIQUEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST ACCORDÉE DE PAR LA SOUMISSION DE CE DOCUMENT. IL NE DOIT PAS ÊTRE COPIÉ, INFORMATIONS PRIVILÉGIÉES ET CONFIDENTIELLES DE V.W.T. ET NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RÉINSÉRÉS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LA PERMISSION DE V.W.T. V.W.T. DÉCLINE TOUTE RESPONSABILITÉ OU OBLIGATION POUR L'UTILISATION DE CE DOCUMENT OU DES DESIGNS CONCEPTS ET L'INFORMATION CONTENUE DANS LES PRÉSENTES À DES FINS AUTRES QUE CELLES LIÉES AUX BUTS SPÉCIFIQUES DU PROJET CI-JOINT. EN AUCUN CAS CE DOCUMENT NE DOIT ÊTRE INTERPRÉTÉ COMME ACCORDANT UNE LICENCE OU UN DROIT DE V.W.T. TOUS DROITS D'AUTEUR, BREVET ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À CES MODALITÉS ET CONDITIONS.

DESSINÉ DESIGNER	M.JACQUES
DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET
DATE	2019-02-12
INGÉNIEUR ENGINEER	
DATE	
ECHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL
TITLE PAGE

CLIENT: IQALUIT WWTP

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT + DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-EPL-0006-AUT-VWT	JOME01	1 DE 5	4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE


04-07-2015 14:49:00 C:\Users\mjacques\Desktop\CARTOUCHE\VWT\RENOVE 2015.dwg mjacques

DRAWING INDEX


DESCRIPTION	DRAWING NUMBER
CONTROL PANEL	
TITLE PAGE	5000218036-EPL-0006-AUT-VWT-01
DRAWING LIST & LEGEND	5000218036-EPL-0006-AUT-VWT-02
OUTSIDE PANEL LAYOUT	5000218036-EPL-0006-AUT-VWT-03
INSIDE PANEL LAYOUT	5000218036-EPL-0006-AUT-VWT-04
PARTS LIST	5000218036-EPL-0006-AUT-VWT-05
SCHEMATIC DIAGRAM 600VAC	5000218036-ELD-0006-AUT-VWT-01
SCHEMATIC DIAGRAM 120VAC	5000218036-ELD-0006-AUT-VWT-02
SCHEMATIC DIAGRAM 120VAC	5000218036-ELD-0006-AUT-VWT-03
SCHEMATIC DIAGRAM 24VDC	5000218036-ELD-0006-AUT-VWT-04
SCHEMATIC DIAGRAM 24VDC	5000218036-ELD-0006-AUT-VWT-05
ETHERNET NETWORK AND PLC	5000218036-ELD-0006-AUT-VWT-06
RACK 00 SLOT 01 INPUTS, 1769-L16ER-BB1B	5000218036-ELD-0006-AUT-VWT-07
RACK 00 SLOT 01 OUTPUTS, 1769-L16ER-BB1B	5000218036-ELD-0006-AUT-VWT-08
RACK 0, SLOT 02, 1734-IEBC	5000218036-ELD-0006-AUT-VWT-09

COLORS AND WIRING GAGES		
120VAC POWER	BLACK	14AWG
120VAC CONTROL	RED	14AWG
NEUTRE	WHITE	14AWG
DRY CONTACT	YELLOW	14AWG
24VDC	BLUE(+), BLUE / WHITE(-)	16AWG (0 TO 9A) 14AWG (10A & +)
GROUND	GREEN	14AWG
ISOLATED GROUND	GREEN / YELLOW	14AWG
ANALOG I/O TWISTED PAIRS	BLACK(+), WHITE(-)	18AWG
DIGITAL I/O 120VA	RED	16AWG
DIGITAL I/O 24VDC	BLUE	16AWG
LOW VOLTAGE (12, 24, 48VDC)	BLUE	16AWG (0 À 9A) 14AWG (10A & +)
CONTROL CIRCUIT 5 TO 60VDC	BLUE(+), BLUE/WHITE(-), GREEN(GND)	16AWG (0 À 9A) 14AWG (10A & +)

SUPPLY WIRING IDENTIFICATION



LEGEND LIST



LR 60892

REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-06	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED BY THE SUBMISSION OF THIS DOCUMENT. THIS DOCUMENT CONTAINS CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WHETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PRIOR WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE OTHER OUR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY ANY PERSON FOR ANY PURPOSE OTHER THAN THE SPECIFIC PROJECT WITHOUT THE WRITTEN CONSENT OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS ET RENSEIGNEMENTS CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET SONT SOUMIS EN CONFIDENCE. CE DOCUMENT ET LES RENSEIGNEMENTS QU'IL CONTIENT DOIVENT ÊTRE UTILISÉS UNIQUEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST OCTROYÉE DE PAR LA SOUMISSION DE CE DOCUMENT. CE DOCUMENT CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET PRIVILÉGIÉS QUI SONT LA PROPRIÉTÉ DE V.W.T. ET NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, VENDUS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT ÉCRIT DE V.W.T. V.W.T. DÉCLINE TOUTE RESPONSABILITÉ ET TOUTE RESPONSABILITÉ QUANT À L'UTILISATION DE CE DOCUMENT OU DES IDÉES ET CONCEPTS QUI Y SONT CONTENUS À DES FINS AUTRES QUE CELLES SPÉCIFIQUES À CE PROJET. EN AUCUN CAS CE DOCUMENT OU LES IDÉES ET CONCEPTS QUI Y SONT CONTENUS NE DOIVENT ÊTRE UTILISÉS PAR QUICONQUE À QUELQUE FIN QUE CE SOIT AUTRE QUE CELLE POUR LAQUELLE CE DOCUMENT A ÉTÉ SOUMIS SANS LE CONSENTEMENT ÉCRIT DE V.W.T. TOUS DROITS D'AUTEUR, BREVET ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À CES CONDITIONS ET MODALITÉS.

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL
DRAWING LIST & LEGEND

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-EPL-0006-AUT-VWT	JOME01	2 DE 5		4

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE

Mardi 07 mai 2019, 14:49:00 C:\Users\mjacques\Desktop\CAM\TO-DO_WVTC\5000218036-EPL-0006-AUT-VWT-02.dwg



ENCLOSURE 42" x 36" x 12"



DOOR DETAILS

LR 60892

REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-06	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND MAY CONTAIN CONFIDENTIAL AND/OR PROPRIETARY OR OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND ITS CONTENTS MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED TO ANY INTELLECTUAL PROPERTY CONTAINED HEREIN. THIS IS A CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, INSERTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WHATSOEVER WITHOUT THE V.W.T. EXPRESSED RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN IS ASSUMED BY THE RECIPIENT OF THIS DOCUMENT OR ANY PERSON TO WHOM THE RECIPIENT RELEASES TO THE FITNESS FOR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE CONSTRUED AS RELATING TO THE FITNESS FOR THE PURPOSE OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL OUTSIDE PANEL LAYOUT


CLIENT: IQALUIT WWTP

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-EPL-0006-AUT-VWT	JOME01	3 DE 5		4

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE


L:1 X H:4
RACK 0, SLOT 01
ENET060540
L:1.5 X H:4
CB060355 2A
CB060416 5A
L:2 X H:4 (CUSTOMER)
L:1 X H:4
L:2 X H:4
ISOLATED GND
GND
FU060115
FU060115
FU060115A
TR060115
1500VA
FU060125
FU060125
FU060125A
TR060125
1500VA
DS060105
DB060110
BA060344
OL060145
OL060165
OL060155
CB060232
M060145
M060165
M060155
CR060375
MOTORS
DRY CONTACTS
CB060134
CB060135
CB060136
CB060137
CB060138
CB060139
CB060140
CB060141
CB060142
CB060143
CB060144
CB060145
CB060146
CB060147
CB060148
CB060149
CB060150
CB060151
CB060152
CB060153
CB060154
CB060155
CB060156
CB060157
CB060158
CB060159
CB060160
CB060161
CB060162
CB060163
CB060164
CB060165
CB060166
CB060167
CB060168
CB060169
CB060170
CB060171
CB060172
CB060173
CB060174
CB060175
CB060176
CB060177
CB060178
CB060179
CB060180
CB060181
CB060182
CB060183
CB060184
CB060185
CB060186
CB060187
CB060188
CB060189
CB060190
CB060191
CB060192
CB060193
CB060194
CB060195
CB060196
CB060197
CB060198
CB060199
CB060200
CB060201
CB060202
CB060203
CB060204
CB060205
CB060206
CB060207
CB060208
CB060209
CB060210
CB060211
CB060212
CB060213
CB060214
CB060215
CB060216
CB060217
CB060218
CB060219
CB060220
CB060221
CB060222
CB060223
CB060224
CB060225
CB060226
CB060227
CB060228
CB060229
CB060230
CB060231
CB060232
CB060233
CB060234
CB060235
CB060236
CB060237
CB060238
CB060239
CB060240
CB060241
CB060242
CB060243
CB060244
CB060245
CB060246
CB060247
CB060248
CB060249
CB060250
CB060251
CB060252
CB060253
CB060254
CB060255
CB060256
CB060257
CB060258
CB060259
CB060260
CB060261
CB060262
CB060263
CB060264
CB060265
CB060266
CB060267
CB060268
CB060269
CB060270
CB060271
CB060272
CB060273
CB060274
CB060275
CB060276
CB060277
CB060278
CB060279
CB060280
CB060281
CB060282
CB060283
CB060284
CB060285
CB060286
CB060287
CB060288
CB060289
CB060290
CB060291
CB060292
CB060293
CB060294
CB060295
CB060296
CB060297
CB060298
CB060299
CB060300
CB060301
CB060302
CB060303
CB060304
CB060305
CB060306
CB060307
CB060308
CB060309
CB060310
CB060311
CB060312
CB060313
CB060314
CB060315
CB060316
CB060317
CB060318
CB060319
CB060320
CB060321
CB060322
CB060323
CB060324
CB060325
CB060326
CB060327
CB060328
CB060329
CB060330
CB060331
CB060332
CB060333
CB060334
CB060335
CB060336
CB060337
CB060338
CB060339
CB060340
CB060341
CB060342
CB060343
CB060344
CB060345
CB060346
CB060347
CB060348
CB060349
CB060350
CB060351
CB060352
CB060353
CB060354
CB060355
CB060356
CB060357
CB060358
CB060359
CB060360
CB060361
CB060362
CB060363
CB060364
CB060365
CB060366
CB060367
CB060368
CB060369
CB060370
CB060371
CB060372
CB060373
CB060374
CB060375
CB060376
CB060377
CB060378
CB060379
CB060380
CB060381
CB060382
CB060383
CB060384
CB060385
CB060386
CB060387
CB060388
CB060389
CB060390
CB060391
CB060392
CB060393
CB060394
CB060395
CB060396
CB060397
CB060398
CB060399
CB060400
CB060401
CB060402
CB060403
CB060404
CB060405
CB060406
CB060407
CB060408
CB060409
CB060410
CB060411
CB060412
CB060413
CB060414
CB060415
CB060416
CB060417
CB060418
CB060419
CB060420
CB060421
CB060422
CB060423
CB060424
CB060425
CB060426
CB060427
CB060428
CB060429
CB060430
CB060431
CB060432
CB060433
CB060434
CB060435
CB060436
CB060437
CB060438
CB060439
CB060440
CB060441
CB060442
CB060443
CB060444
CB060445
CB060446
CB060447
CB060448
CB060449
CB060450
CB060451
CB060452
CB060453
CB060454
CB060455
CB060456
CB060457
CB060458
CB060459
CB060460
CB060461
CB060462
CB060463
CB060464
CB060465
CB060466
CB060467
CB060468
CB060469
CB060470
CB060471
CB060472
CB060473
CB060474
CB060475
CB060476
CB060477
CB060478
CB060479
CB060480
CB060481
CB060482
CB060483
CB060484
CB060485
CB060486
CB060487
CB060488
CB060489
CB060490
CB060491
CB060492
CB060493
CB060494
CB060495
CB060496
CB060497
CB060498
CB060499
CB060500
CB060501
CB060502
CB060503
CB060504
CB060505
CB060506
CB060507
CB060508
CB060509
CB060510
CB060511
CB060512
CB060513
CB060514
CB060515
CB060516
CB060517
CB060518
CB060519
CB060520
CB060521
CB060522
CB060523
CB060524
CB060525
CB060526
CB060527
CB060528
CB060529
CB060530
CB060531
CB060532
CB060533
CB060534
CB060535
CB060536
CB060537
CB060538
CB060539
CB060540
CB060541
CB060542
CB060543
CB060544
CB060545
CB060546
CB060547
CB060548
CB060549
CB060550
CB060551
CB060552
CB060553
CB060554
CB060555
CB060556
CB060557
CB060558
CB060559
CB060560
CB060561
CB060562
CB060563
CB060564
CB060565
CB060566
CB060567
CB060568
CB060569
CB060570
CB060571
CB060572
CB060573
CB060574
CB060575
CB060576
CB060577
CB060578
CB060579
CB060580
CB060581
CB060582
CB060583
CB060584
CB060585
CB060586
CB060587
CB060588
CB060589
CB060590
CB060591
CB060592
CB060593
CB060594
CB060595
CB060596
CB060597
CB060598
CB060599
CB060600
CB060601
CB060602
CB060603
CB060604
CB060605
CB060606
CB060607
CB060608
CB060609
CB060610
CB060611
CB060612
CB060613
CB060614
CB060615
CB060616
CB060617
CB060618
CB060619
CB060620
CB060621
CB060622
CB060623
CB060624
CB060625
CB060626
CB060627
CB060628
CB060629
CB060630
CB060631
CB060632
CB060633
CB060634
CB060635
CB060636
CB060637
CB060638
CB060639
CB060640
CB060641
CB060642
CB060643
CB060644
CB060645
CB060646
CB060647
CB060648
CB060649
CB060650
CB060651
CB060652
CB060653
CB060654
CB060655
CB060656
CB060657
CB060658
CB060659
CB060660
CB060661
CB060662
CB060663
CB060664
CB060665
CB060666
CB060667
CB060668
CB060669
CB060670
CB060671
CB060672
CB060673
CB060674
CB060675
CB060676
CB060677
CB060678
CB060679
CB060680
CB060681
CB060682
CB060683
CB060684
CB060685
CB060686
CB060687
CB060688
CB060689
CB060690
CB060691
CB060692
CB060693
CB060694
CB060695
CB060696
CB060697
CB060698
CB060699
CB060700
CB060701
CB060702
CB060703
CB060704
CB060705
CB060706
CB060707
CB060708
CB060709
CB060710
CB060711
CB060712
CB060713
CB060714
CB060715
CB060716
CB060717
CB060718
CB060719
CB060720
CB060721
CB060722
CB060723
CB060724
CB060725
CB060726
CB060727
CB060728
CB060729
CB060730
CB060731
CB060732
CB060733
CB060734
CB060735
CB060736
CB060737
CB060738
CB060739
CB060740
CB060741
CB060742
CB060743
CB060744
CB060745
CB060746
CB060747
CB060748
CB060749
CB060750
CB060751
CB060752
CB060753
CB060754
CB060755
CB060756
CB060757
CB060758
CB060759
CB060760
CB060761
CB060762
CB060763
CB060764
CB060765
CB060766
CB060767
CB060768
CB060769
CB060770
CB060771
CB060772
CB060773
CB060774
CB060775
CB060776
CB060777
CB060778
CB060779
CB060780
CB060781
CB060782
CB060783
CB060784
CB060785
CB060786
CB060787
CB060788
CB060789
CB060790
CB060791
CB060792
CB060793
CB060794
CB060795
CB060796
CB060797
CB060798
CB060799
CB060800
CB060801
CB060802
CB060803
CB060804
CB060805
CB060806
CB060807
CB060808
CB060809
CB060810
CB060811
CB060812
CB060813
CB060814
CB060815
CB060816
CB060817
CB060818
CB060819
CB060820
CB060821
CB060822
CB060823
CB060824
CB060825
CB060826
CB060827
CB060828
CB060829
CB060830
CB060831
CB060832
CB060833
CB060834
CB060835
CB060836
CB060837
CB060838
CB060839
CB060840
CB060841
CB060842
CB060843
CB060844
CB060845
CB060846
CB060847
CB060848
CB060849
CB060850
CB060851
CB060852
CB060853
CB060854
CB060855
CB060856
CB060857
CB060858
CB060859
CB060860
CB060861
CB060862
CB060863
CB060864
CB060865
CB060866
CB060867
CB060868
CB060869
CB060870
CB060871
CB060872
CB060873
CB060874
CB060875
CB060876
CB060877
CB060878
CB060879
CB060880
CB060881
CB060882
CB060883
CB060884
CB060885
CB060886
CB060887
CB060888
CB060889
CB060890
CB060891
CB060892
CB060893
CB060894
CB060895
CB060896
CB060897
CB060898
CB060899
CB060900
CB060901
CB060902
CB060903
CB060904
CB060905
CB060906
CB060907
CB060908
CB060909
CB060910
CB060911
CB060912
CB060913
CB060914
CB060915
CB060916
CB060917
CB060918
CB060919
CB060920
CB060921
CB060922
CB060923
CB060924
CB060925
CB060926
CB060927
CB060928
CB060929
CB060930
CB060931
CB060932
CB060933
CB060934
CB060935
CB060936
CB060937
CB060938
CB060939
CB060940
CB060941
CB060942
CB060943
CB060944
CB060945
CB060946
CB060947
CB060948
CB060949
CB060950
CB060951
CB060952
CB060953
CB060954
CB060955
CB060956
CB060957
CB060958
CB060959
CB060960
CB060961
CB060962
CB060963
CB060964
CB060965
CB060966
CB060967
CB060968
CB060969
CB060970
CB060971
CB060972
CB060973
CB060974
CB060975
CB060976
CB060977
CB060978
CB060979
CB060980
CB060981
CB060982
CB060983
CB060984
CB060985
CB060986
CB060987
CB060988
CB060989
CB060990
CB060991
CB060992
CB060993
CB060994
CB060995
CB060996
CB060997
CB060998
CB060999
CB061000
CB061001
CB061002
CB061003
CB061004
CB061005
CB061006
CB061007
CB061008
CB061009
CB061010
CB061011
CB061012
CB061013
CB061014
CB061015
CB061016
CB061017
CB061018
CB061019
CB061020
CB061021
CB061022
CB061023
CB061024
CB061025
CB061026
CB061027
CB061028
CB061029
CB061030
CB061031
CB061032
CB061033
CB061034
CB061035
CB061036
CB061037
CB061038
CB061039
CB061040
CB061041
CB061042
CB061043
CB061044
CB061045
CB061046
CB061047
CB061048
CB061049
CB061050
CB061051
CB061052
CB061053
CB061054
CB061055
CB061056
CB061057
CB061058
CB061059
CB061060
CB061061
CB061062
CB061063
CB061064
CB061065
CB061066
CB061067
CB061068
CB061069
CB061070
CB061071
CB061072
CB061073
CB061074
CB061075
CB061076
CB061077
CB061078
CB061079
CB061080
CB061081
CB061082
CB061083
CB061084
CB061085
CB061086
CB061087
CB061088
CB061089
CB061090
CB061091
CB061092
CB061093
CB061094
CB061095
CB061096
CB061097
CB061098
CB061099
CB061100
CB061101
CB061102
CB061103
CB061104
CB061105
CB061106
CB061107
CB061108
CB061109
CB061110
CB061111
CB061112
CB061113
CB061114
CB061115
CB061116
CB061117
CB061118
CB061119
CB061120
CB061121
CB061122
CB061123
CB061124
CB061125
CB061126
CB061127
CB061128
CB061129
CB061130
CB061131
CB061132
CB061133
CB061134
CB061135
CB061136
CB061137
CB061138
CB061139
CB061140
CB061141
CB061142
CB061143
CB061144
CB061145
CB061146
CB061147
CB061148
CB061149
CB061150
CB061151
CB061152
CB061153
CB061154
CB061155
CB061156
CB061157
CB061158
CB061159
CB061160
CB061161
CB061162
CB061163
CB061164
CB061165
CB061166
CB061167
CB061168
CB061169
CB061170
CB061171
CB061172
CB061173
CB061174
CB061175
CB061176
CB061177
CB061178
CB061179
CB061180
CB061181
CB061182
CB061183
CB061184
CB061185
CB061186
CB061187
CB061188
CB061189
CB061190
CB061191
CB061192
CB061193
CB061194
CB061195
CB061196
CB061197
CB061198
CB061199
CB061200
CB061201
CB061202
CB061203
CB061204
CB061205
CB061206
CB061207
CB061208
CB061209
CB061210
CB061211
CB061212
CB061213
CB061214
CB061215
CB061216
CB061217
CB061218
CB061219
CB061220
CB061221
CB061222
CB061223
CB061224
CB061225
CB061226
CB061227
CB061228
CB061229
CB061230
CB061231
CB061232
CB061233
CB061234
CB061235
CB061236
CB061237
CB061238
CB061239
CB061240
CB061241
CB061242
CB061243
CB061244
CB061245
CB061246
CB061247
CB061248
CB061249
CB061250
CB061251
CB061252
CB061253
CB061254
CB061255
CB061256
CB061257
CB061258
CB061259
CB061260
CB061261
CB061262
CB061263
CB061264
CB061265
CB061266
CB061267
CB061268
CB061269
CB061270
CB061271
CB061272
CB061273
CB061274
CB061275
CB061276
CB061277
CB061278
CB061279
CB061280
CB061281
CB061282
CB061283
CB061284
CB061285
CB061286
CB061287
CB061288
CB061289
CB061290
CB061291
CB061292
CB061293
CB061294
CB061295
CB061296
CB061297
CB061298
CB061299
CB061300
CB061301
CB061302
CB061303
CB061304
CB061305
CB061306
CB061307
CB061308
CB061309
CB061310
CB061311
CB061312
CB061313
CB061314
CB061315
CB061316
CB061317
CB061318
CB061319
CB061320
CB061321
CB061322
CB061323
CB061324
CB061325
CB061326
CB061327
CB061328
CB061329
CB061330
CB061331
CB061332
CB061333
CB061334
CB061335
CB061336
CB061337
CB061338
CB061339
CB061340
CB061341
CB061342
CB061343
CB061344
CB061345
CB061346
CB061347
CB061348
CB061349
CB061350
CB061351
CB061352
CB061353
CB061354
CB061355
CB061356
CB061357
CB061358
CB061359
CB061360
CB061361
CB061362
CB061363
CB061364
CB061365
CB061366
CB061367
CB061368
CB061369
CB061370
CB061371
CB061372
CB061373
CB061374
CB061375
CB061376
CB061377
CB061378
CB061379
CB061380
CB061381
CB061382
CB061383
CB061384
CB061385
CB061386
CB061387
CB061388
CB061389
CB061390
CB061391
CB061392
CB061393
CB061394
CB061395
CB061396
CB061397
CB061398
CB061399
CB061400
CB061401
CB061402
CB061403
CB061404
CB061405
CB061406
CB061407
CB061408
CB061409
CB061410
CB061411
CB061412
CB061413
CB061414
CB061415
CB061416
CB061417
CB061418
CB061419
CB061420
CB061421
CB061422
CB061423
CB061424
CB061425
CB061426
CB061427
CB061428
CB061429
CB061430
CB061431
CB061432
CB061433
CB061434
CB061435
CB061436
CB061437
CB061438
CB061439
CB061440
CB061441
CB061442
CB061443
CB061444
CB061445
CB061446
CB061447
CB061448
CB061449
CB061450
CB061451
CB061452
CB061453
CB061454
CB061455
CB061456
CB061457
CB061458
CB061459
CB061460
CB061461
CB061462
CB061463
CB061464
CB061465
CB061466
CB061467
CB061468
CB061469
CB061470
CB061471
CB061472
CB061473
CB061474
CB061475
CB061476
CB061477
CB061478
CB061479
CB061480
CB061481
CB061482
CB061483
CB061484
CB061485
CB061486
CB061487
CB061488
CB061489
CB061490
CB061491
CB061492
CB061493
CB061494
CB061495
CB061496
CB061497
CB061498
CB061499
CB061500
CB061501
CB061502
CB061503
CB061504
CB061505
CB061506
CB061507
CB061508
CB061509
CB061510
CB061511
CB061512
CB061513
CB061514
CB061515
CB061516
CB061517
CB061518
CB061519
CB061520
CB061521
CB061522
CB061523
CB061524
CB061525
CB061526
CB061527
CB061528
CB061529
CB061530
CB061531
CB061532
CB061533
CB061534
CB061535
CB061536
CB061537
CB061538
CB061539
CB061540
CB061541
CB061542
CB061543
CB061544
CB061545
CB061546
CB061547
CB061548
CB061549
CB061550
CB061551
CB061552
CB061553
CB061554
CB061555
CB061556
CB061557
CB061558
CB061559
CB061560
CB061561
CB061562
CB061563
CB061564
CB061565
CB061566
CB061567
CB061568
CB061569
CB061570
CB061571
CB061572
CB061573
CB061574
CB061575
CB061576
CB061577
CB061578
CB061579
CB061580
CB061581
CB061582
CB061583
CB061584
CB061585
CB061586
CB061587
CB061588
CB061589
CB061590
CB061591
CB061592
CB061593
CB061594
CB061595
CB061596
CB061597
CB061598
CB061599
CB061600
CB061601
CB061602
CB061603
CB061604
CB061605
CB061606
CB061607
CB061608
CB061609
CB061610
CB061611
CB061612
CB061613
CB061614
CB061615
CB061616
CB061617
CB061618
CB061619
CB061620
CB061621
CB061622
CB061623
CB061624
CB061625
CB061626
CB061627
CB061628
CB061629
CB061630
CB061631
CB061632
CB061633
CB061634
CB061635
CB061636
CB061637
CB061638
CB061639
CB061640
CB061641
CB061642
CB061643
CB061644
CB061645
CB061646
CB061647
CB061648
CB061649
CB061650
CB061651
CB061652
CB061653
CB061654
CB061655
CB061656
CB061657
CB061658
CB061659
CB061660
CB061661
CB061662
CB061663
CB061664
CB061665
CB061666
CB061667
CB061668
CB061669
CB061670
CB061671
CB061672
CB061673
CB061674
CB061675
CB061676
CB061677
CB061678
CB061679
CB061680
CB061681
CB061682
CB061683
CB061684
CB061685
CB061686
CB061687
CB061688
CB061689
CB061690
CB061691
CB061692
CB061693
CB061694
CB061695
CB061696
CB061697
CB061698
CB061699
CB061700
CB061701
CB061702
CB061703
CB061704
CB061705
CB061706
CB061707
CB061708
CB061709
CB061710
CB061711
CB061712
CB061713
CB061714
CB061715
CB061716
CB061717
CB061718
CB061719
CB061720
CB061721
CB061722
CB061723
CB061724
CB061725
CB061726
CB061727
CB061728
CB061729
CB061730
CB061731
CB061732
CB061733
CB061734
CB061735
CB061736
CB061737
CB061738
CB061739
CB061740
CB061741
CB061742
CB061743
CB061744
CB061745
CB061746
CB061747
CB061748
CB061749
CB061750
CB061751
CB061752
CB061753
CB061754
CB061755
CB061756
CB061757
CB061758
CB061759
CB061760
CB061761
CB061762
CB061763
CB061764
CB061765
CB061766
CB061767
CB061768
CB061769
CB061770
CB061771
CB061772
CB061773
CB061774
CB061775
CB061776
CB061777
CB061778
CB061779
CB061780
CB061781
CB061782
CB061783
CB061784
CB061785
CB061786
CB061787
CB061788
CB061789
CB061790
CB061791
CB061792
CB061793
CB061794
CB061795
CB061796
CB061797
CB061798
CB061799
CB061800
CB061801
CB061802
CB061803
CB061804
CB061805
CB061806
CB061807
CB061808
CB061809
CB061810
CB061811
CB061812
CB061813
CB061814
CB061815
CB061816
CB061817
CB061818
CB061819
CB061820
CB061821
CB061822
CB061823
CB061824
CB061825
CB061826
CB061827
CB061828
CB061829
CB061830
CB061831
CB061832
CB061833
CB061834
CB061835
CB061836
CB061837
CB061838
CB061839
CB061840
CB061841
CB061842
CB061843
CB061844
CB061845
CB061846
CB061847
CB061848
CB061849
CB061850
CB061851
CB061852
CB061853
CB061854
CB061855
CB061856
CB061857
CB061858
CB061859
CB061860
CB061861
CB061862
CB061863
CB061864
CB061865
CB061866
CB061867
CB061868
CB061869
CB061870
CB061871
CB061872
CB061873
CB061874
CB061875
CB061876
CB061877
CB061878
CB061879
CB061880
CB061881
CB061882
CB061883
CB061884
CB061885
CB061886
CB061887
CB061888
CB061889
CB061890
CB061891
CB061892
CB061893
CB061894
CB061895
CB061896
CB061897
CB061898
CB061899
CB061900
CB061901
CB061902
CB061903
CB061904
CB061905
CB061906
CB061907
CB061908
CB061909
CB061910
CB061911
CB061912
CB061913
CB061914
CB061915
CB061916
CB061917
CB061918
CB061919
CB061920
CB061921
CB061922
CB061923
CB061924
CB061925
CB061926
CB061927
CB061928
CB061929
CB061930
CB061931
CB061932
CB061933
CB061934
CB061935
CB061936
CB061937
CB061938
CB061939
CB061940
CB061941
CB061942
CB061943
CB061944
CB061945
CB061946
CB061947
CB061948
CB061949
CB061950
CB061951
CB061952
CB061953
CB061954
CB061955
CB061956
CB061957
CB061958
CB061959
CB061960
CB061961
CB061962
CB061963
CB061964
CB061965
CB061966
CB061967
CB061968
CB061969
CB061970
CB061971
CB061972
CB061973
CB061974
CB061975
CB061976
CB061977
CB061978
CB061979
CB061980
CB061981
CB061982
CB061983
CB061984
CB061985
CB061986
CB061987
CB061988
CB061989
CB061990
CB061991
CB061992
CB061993
CB061994
CB061995
CB061996
CB061997
CB061998
CB061999
CB062000
CB062001
CB062002
CB062003
CB062004
CB062005
CB062006
CB062007
CB062008
CB062009
CB062010
CB062011
CB062012
CB062013
CB062014
CB062015
CB062016
CB062017
CB062018
CB062019
CB062020
CB062021
CB062022
CB062023
CB062024
CB062025
CB062026
CB062027
CB062028
CB062029
CB062030
CB062031
CB062032
CB062033
CB062034
CB062035
CB062036
CB062037
CB062038
CB062039
CB062040
CB062041
CB062042
CB062043
CB062044
CB062045
CB062046
CB062047
CB062048
CB062049
CB062050
CB062051
CB062052
CB062053
CB062054
CB062055
CB062056
CB062057
CB062058
CB062059
CB062060
CB062061
CB062062
CB062063
CB062064
CB062065
CB062066
CB062067
CB062068
CB062069
CB062070
CB062071
CB062072
CB062073
CB062074
CB062075
CB062076
CB062077
CB062078
CB062079
CB062080
CB062081
CB062082
CB062083
CB062084
CB062085
CB062086
CB062087
CB062088
CB062089
CB062090
CB062091
CB062092
CB062093
CB062094
CB062095
CB062096
CB062097
CB062098
CB062099
CB062100
CB062101
CB062102
CB062103
CB062104
CB062105
CB062106
CB062107
CB062108
CB062109
CB062110
CB062111
CB062112
CB062113
CB062114
CB062115
CB062116
CB062117
CB062118
CB062119
CB062120
CB062121
CB062122
CB062123
CB062124
CB062125
CB062126
CB062127
CB062128
CB062129
CB062130
CB062131
CB062132
CB062133
CB062134
CB062135
CB062136
CB062137
CB062138
CB062139
CB062140
CB062141
CB062142
CB062143
CB062144
CB062145
CB062146
CB062147
CB062148
CB062149
CB062150
CB062151
CB062152
CB062153
CB062154
CB062155
CB062156
CB062157
CB062158
CB062159
CB062160
CB062161
CB062162
CB062163
CB062164
CB062165
CB062166
CB062167
CB062168
CB062169
CB062170
CB062171
CB062172
CB062173
CB062174
CB062175
CB062176
CB062177
CB062178
CB062179
CB062180
CB062181
CB062182
CB062183
CB062184
CB062185
CB062186
CB062187
CB062188
CB062189
CB062190
CB062191
CB062192
CB062193
CB062194
CB062195
CB062196
CB062197
CB062198
CB062199
CB062200
CB062201
CB062202
CB062203
CB062204
CB062205
CB062206
CB062207
CB062208
CB062209
CB062210
CB062211
CB062212
CB062213
CB062214
CB062215
CB062216
CB062217
CB062218
CB062219
CB062220
CB062221
CB062222
CB062223
CB062224
CB062225
CB062226
CB062227
CB062228
CB062229
CB062230
CB062231
CB062232
CB062233
CB062234
CB062235
CB062236
CB062237
CB062238
CB062239
CB062240
CB062241
CB062242
CB062243
CB062244
CB062245
CB062246
CB062247
CB062248
CB062249
CB062250
CB062251
CB062252
CB062253
CB062254
CB062255
CB062256
CB062257
CB062258
CB062259
CB062260
CB062261
CB062262
CB062263
CB062264
CB062265
CB062266
CB062267
CB062268
CB062269
CB062270
CB062271
CB062272
CB062273
CB062274
CB062275
CB062276
CB062277
CB062278
CB062279
CB062280
CB062281
CB062282
CB062283
CB062284
CB062285
CB062286
CB062287
CB062288
CB062289
CB062290
CB062291
CB062292
CB062293
CB062294
CB062295
CB062296
CB062297
CB062298
CB062299
CB062300
CB062301
CB062302
CB062303
CB062304
CB062305
CB062306
CB062307
CB062308
CB062309
CB062310
CB062311
CB062312
CB062313
CB062314
CB062315
CB062316
CB062317
CB062318
CB062319
CB062320
CB062321
CB062322
CB062323
CB062324
CB062325
CB062326
CB062327
CB062328
CB062329
CB062330
CB062331
CB062332
CB062333
CB062334
CB062335
CB062336
CB062337
CB062338
CB062339
CB062340
CB062341
CB062342
CB062343
CB062344
CB062345
CB062346
CB062347
CB062348
CB062349
CB062350
CB062351
CB062352
CB062353
CB062354
CB062355
CB062356
CB062357
CB062358
CB062359
CB062360
CB062361
CB062362
CB062363
CB062364
CB062365
CB062366
CB062367
CB062368
CB062369
CB062370
CB062371
CB062372
CB062373
CB062374
CB062375
CB062376
CB062377
CB062378
CB062379
CB062380
CB062381
CB062382
CB062383
CB062384
CB062385
CB062386
CB062387
CB062388
CB062389
CB062390
CB062391
CB062392
CB062393
CB062394
CB062395
CB062396
CB062397
CB062398
CB062399
CB062400
CB062401
CB062402
CB062403
CB062404
CB062405
CB062406
CB062407
CB062408
CB062409
CB062410
CB062411
CB062412
CB062413
CB062414
CB062415
CB062416
CB062417
CB062418
CB062419
CB062420
CB062421
CB062422
CB062423
CB062424
CB062425
CB062426
CB062427
CB062428
CB062429
CB062430
CB062431
CB062432
CB062433
CB062434
CB062435
CB062436
CB062437
CB062438
CB062439
CB062440
CB062441
CB062442
CB062443
CB062444
CB062445
CB062446
CB062447
CB062448
CB062449
CB062450
CB062451
CB062452
CB062453
CB062454
CB062455
CB062456
CB062457
CB062458
CB062459
CB062460
CB062461
CB062462
CB062463
CB062464
CB062465
CB062466
CB062467
CB062468
CB062469
CB062470
CB062471
CB062472
CB062473
CB062474
CB062475
CB062476
CB062477
CB062478
CB062479
CB062480
CB062481
CB062482
CB062483
CB062484
CB062485
CB062486
CB062487
CB062488
CB062489
CB062490
CB062491
CB062492
CB062493
CB062494
CB062495
CB062496
CB062497
CB062498
CB062499
CB062500
CB062501
CB062502
CB062503
CB062504
CB062505
CB062506
CB062507
CB062508
CB062509
CB062510
CB062511
CB062512
CB062513
CB062514
CB062515
CB062516
CB062517
CB062518
CB062519
CB062520
CB062521
CB062522
CB062523
CB062524
CB062525
CB062526
CB062527
CB062528
CB062529
CB062530
CB062531
CB062532
CB062533
CB062534
CB062535
CB062536
CB062537
CB062538
CB062539
CB062540
CB062541
CB062542
CB062543
CB062544
CB062545
CB062546
CB062547
CB062548
CB062549
CB062550
CB062551
CB062552
CB062553
CB062554
CB062555
CB062556
CB062557
CB062558
CB062559
CB062560
CB062561
CB062562
CB062563
CB062564
CB062565
CB062566
CB062567
CB062568
CB062569
CB062570
CB062571
CB062572
CB062573
CB062574
CB062575
CB062576
CB062577
CB062578
CB062579
CB062580
CB062581
CB062582
CB062583
CB062584
CB062585
CB062586
CB062587
CB062588
CB062589
CB062590
CB062591
CB062592
CB062593
CB062594
CB062595
CB062596
CB062597
CB062598
CB062599
CB062600
CB062601
CB062602
CB062603
CB062604
CB062605
CB062606
CB062607
CB062608
CB062609
CB062610
CB062611
CB062612
CB062613
CB062614
CB062615
CB062616
CB062617
CB062618
CB062619
CB062620
CB062621
CB062622
CB062623
CB062624
CB062625
CB062626
CB062627
CB062628
CB062629
CB062630
CB062631
CB062632
CB062633
CB062634
CB062635
CB062636
CB062637
CB062638
CB062639
CB062640
CB062641
CB062642
CB062643
CB062644
CB062645
CB062646
CB062647
CB062648
CB062649
CB062650
CB062651
CB062652
CB062653
CB062654
CB062655
CB062656
CB062657
CB062658
CB062659
CB062660
CB062661
CB062662
CB062663
CB062664
CB062665
CB062666
CB062667
CB062668
CB062669
CB062670
CB062671
CB062672
CB062673
CB062674
CB062675
CB062676
CB062677
CB062678
CB062679
CB062680
CB062681
CB062682
CB062683
CB062684
CB062685
CB062686
CB062687
CB062688
CB062689
CB062690
CB062691
CB062692
CB062693
CB062694
CB062695
CB062696
CB062697
CB062698
CB062699
CB062700
CB062701
CB062702
CB062703
CB062704
CB062705
CB062706
CB062707
CB062708
CB062709
CB062710
CB062711
CB062712
CB062713
CB062714
CB062715
CB062716
CB062717
CB062718
CB062719
CB062720
CB062721
CB062722
CB062723
CB062724
CB062725
CB062726
CB062727
CB062728
CB062729
CB062730
CB062731
CB062732
CB062733
CB062734
CB062735
CB062736
CB062737
CB062738
CB062739
CB062740
CB062741
CB062742
CB062743
CB062744
CB062745
CB062746
CB062747
CB062748
CB062749
CB062750
CB062751
CB062752
CB062753
CB062754
CB062755
CB062756
CB062757
CB062758
CB062759
CB062760
CB062761
CB062762
CB062763
CB062764
CB062765
CB062766
CB062767
CB062768
CB062769
CB062770
CB062771
CB062772
CB062773
CB062774
CB062775
CB062776
CB062777
CB062778
CB062779
CB062780
CB062781
CB062782
CB062783
CB062784
CB062785
CB062786
CB062787
CB062788
CB062789
CB062790
CB062791
CB062792
CB062793
CB062794
CB062795
CB062796
CB062797
CB062798
CB062799
CB062800
CB062801
CB062802
CB062803
CB062804
CB062805
CB062806
CB062807
CB062808
CB062809
CB062810
CB062811
CB062812
CB062813
CB062814
CB062815
CB062816
CB062817
CB062818
CB062819
CB062820
CB062821
CB062822
CB062823
CB062824
CB062825
CB062826
CB062827
CB062828
CB062829
CB062830
CB062831
CB062832
CB062833
CB062834
CB062835
CB062836
CB062837
CB062838
CB062839
CB062840
CB062841
CB062842
CB062843
CB062844
CB062845
CB062846
CB062847
CB062848
CB062849
CB062850
CB062851
CB062852
CB062853
CB062854
CB062855
CB062856
CB062857
CB062858
CB062859
CB062860
CB062861
CB062862
CB062863
CB062864
CB062865
CB062866
CB062867
CB062868
CB062869
CB062870
CB062871
CB062872
CB062873
CB062874
CB062875
CB062876
CB062877
CB062878
CB062879
CB062880
CB062881
CB062882
CB062883
CB062884
CB062885
CB062886
CB062887
CB062888
CB062889
CB062890
CB062891
CB062892
CB062893
CB062894
CB062895
CB062896
CB062897
CB062898
CB062899
CB062900
CB062901
CB062902
CB062903
CB062904
CB062905
CB062906
CB062907
CB062908
CB062909
CB062910
CB062911
CB062912
CB062913
CB062914
CB062915
CB062916
CB062917
CB062918
CB062919
CB062920
CB062921
CB062922
CB062923
CB062924
CB062925
CB062926
CB062927
CB062928
CB062929
CB062930
CB062931
CB062932
CB062933
CB062934
CB062935
CB062936
CB062937
CB062938
CB062939
CB062940
CB062941
CB062942
CB062943
CB062944
CB062945
CB062946
CB062947
CB062948
CB062949
CB062950
CB062951
CB062952
CB062953
CB062954
CB062955
CB062956
CB062957
CB062958
CB062959
CB062960
CB062961
CB062962
CB062963
CB062964
CB062965
CB062966
CB062967
CB062968
CB062969
CB062970
CB062971
CB062972
CB062973
CB062974
CB062975
CB062976
CB062977
CB062978
CB062979
CB062980
CB062981
CB062982
CB062983
CB062984
CB062985
CB062986
CB062987
CB062988
CB062989
CB062990
CB062991
CB062992
CB062993
CB062994
CB062995
CB062996
CB062997
CB062998
CB062999
CB063000
CB063001
CB063002
CB063003
CB063004
CB063005
CB063006
CB063007
CB063008
CB063009
CB063010
CB063011
CB063012
CB063013
CB063014
CB063015
CB063016
CB063017
CB063018
CB063019
CB063020
CB063021
CB063022
CB063023
CB063024
CB063025
CB063026
CB063027
CB063028
CB063029
CB063030
CB063031
CB063032
CB063033
CB063034
CB063035
CB063036
CB063037
CB063038
CB063039
CB063040
CB063041
CB063042
CB063043
CB063044
CB063045
CB063046
CB063047
CB063048
CB063049
CB063050
CB063051
CB063052
CB063053
CB063054
CB063055
CB063056
CB063057
CB063058
CB063059
CB063060
CB063061
CB063062
CB063063
CB063064
CB063065
CB063066
CB063067
CB063068
CB063069
CB063070
CB063071
CB063072
CB063073
CB063074
CB063075
CB063076
CB063077
CB063078
CB063079
CB063080
CB063081
CB063082
CB063083
CB063084
CB063085
CB063086
CB063087
CB063088
CB063089
CB063090
CB063091
CB063092
CB063093
CB063094
CB063095
CB063096
CB063097
CB063098
CB063099
CB063100
CB063101
CB063102
CB063103
CB063104
CB063105
CB063106
CB063107
CB063108
CB063109
CB063110
CB063111
CB063112
CB063113
CB063114
CB063115
CB063116
CB063117
CB063118
CB063119
CB063120
CB063121
CB063122
CB063123
CB063124
CB063125
CB063126
CB063127
CB063128
CB063129
CB063130
CB063131
CB063132
CB063133
CB063134
CB063135
CB063136
CB063137
CB063138
CB063139
CB063140
CB063141
CB063142
CB063143
CB063144
CB063145
CB063146
CB063147
CB063148
CB063149
CB063150
CB063151
CB063152
CB063153
CB063154
CB063155
CB063156
CB063157
CB063158
CB063159
CB063160
CB063161
CB063162
CB063163
CB063164
CB063165
CB063166
CB063167
CB063168
CB063169
CB063170
CB063171
CB063172
CB063173
CB063174
CB063175
CB063176
CB063177
CB063178
CB063179
CB063180
CB063181
CB063182
CB063183
CB063184
CB063185
CB063186
CB063187
CB063188
CB063189
CB063190
CB063191
CB063192
CB063193
CB063194
CB063195
CB063196
CB063197
CB063198
CB063199
CB063200
CB063201
CB063202
CB063203
CB063204
CB063205
CB063206
CB063207
CB063208
CB063209
CB063210
CB063211
CB063212
CB063213
CB063214
CB063215
CB063216
CB063217
CB063218
CB063219
CB063220
CB063221
CB063222
CB063223
CB063224
CB063225
CB063226
CB063227
CB063228
CB063229
CB063230
CB063231
CB063232
CB063233
CB063234
CB063235
CB063236
CB063237
CB063238
CB063239
CB063240
CB063241
CB063242
CB063243
CB063244
CB063245
CB063246
CB063247
CB063248
CB063249
CB063250
CB063251
CB063252
CB063253
CB063254
CB063255
CB063256
CB063257
CB063258
CB063259
CB063260
CB063261
CB063262
CB063263
CB063264
CB063265
CB063266
CB063267
CB063268
CB063269
CB063270
CB063271
CB063272
CB063273
CB063274
CB063275
CB063276
CB063277
C

Items	Qty	Part Number	Description	Manufacturer
ENCLOSURE	1	!SP1404283	Special Enclosure 42" x 36" x 12"	Hammond
ENCLOSURE	1	BOIHAMPKT99	Document Holder	Hammond
LTG060408	1	!RABUC-LED300-NW	LED Bar 300mm, 3 watts, 24 vdc (88861)	RAB
ZS060408	1	BOIHAMFDS1	Door Switch for Light	Hammond
DS060105	1	!TELGS1DU3	Fused Disconnect Switch 30A/600V (Fus. Type J	Schneider Electric
DS060105	1	!TELGS2AE8	Operating Shaft 30a 12.6"	Schneider Electric
DS060105	1	!TELGS2AH420	Operating Handle Red / Yellow NEMA 4-4X	Schneider
DS060105	3	FUSAJT15	Fuse 15 amp.Type J Time Delay	Mersen
DB060110	3	KCONMPDBC6263	Protective Cover for Distribution Block	Mersen
DB060110	1	KCONMPDB63133	Distribution Block	Mersen
OL060145	1	TELGV2ME05	Manual Starter 0,63-1A	Schneider Electric
OL060145	1	TELGVAN20	Aux Contact for GV2, GV3P, 2NO	Schneider Electric
M060145	1	TELLC1D09BD	Contactor 7,5HP/600V 1NO-1NC 24VDC	Schneider Electric
M060145	1	KTELLADN20	Aux Contact 2NO	Schneider Electric
OL060155	1	TELGV2ME05	Manual Starter 0,63-1A	Schneider Electric
OL060155	1	TELGVAN20	Aux Contact for GV2, GV3P, 2NO	Schneider Electric
M060155	1	TELLC1D09BD	Contactor 7,5HP/600V 1NO-1NF 24VDC	Schneider Electric
M060155	1	KTELLADN20	Aux Contact 2NO	Schneider Electric
OL060165	1	TELGV2ME06	Manual Starter 1-1,6A	Schneider Electric
OL060165	1	TELGVAN20	Aux Contact forGV2, GV3P, 2NO	Schneider Electric
M060165	1	TELLC1D09BD	Contactor 7,5HP/600V 1NO-1NF 24VDC	Schneider Electric
M060165	1	KTELLADN20	Aux Contact 2NO	Schneider Electric
CB060232	1	!SU202M-C15	Breaker 15A 2 poles	ABB
CR060375	1	TELLC1D09BD	Contactor 7,5HP/600V 1NO-1NF 24VDC	Schneider Electric
TR060115	1	!TRASQD9070FB3B	Fuse Holder for XFO (Primairy + Secondairy)	Schneider Electric
FU060115	2	FUSATQR5	Fuse 5 amp, CC, 600 v, Time Delay	Mersen
FU060115A	1	FUSATDR15	Fuse 15 amp, CC, 600 v, Time Delay	Mersen
TR060115	1	KSQD9070FSC2	Protective Cover for Transformer	Schneider Electric
TR060115	3	!SPL0001T	Protective Cover for Fuse Holder	Littelfuse
TR060115	1	TRASQD9070T1500D5	Transformer 1500 va 600/120 v.	Schneider Electric
TR060125	1	!TRASQD9070FB3B	Fuse Holder for XFO (Primairy + Secondairy)	Schneider Electric
FU060125	2	FUSATQR5	Fuse 5 amp, CC, 600 v, Time Delay	Mersen
TR060125	1	KSQD9070FSC2	Protective Cover for Transformer	Schneider Electric
TR060125	3	!SPL0001T	Protective Cover for Fuse Holder	Littelfuse
TR060125	1	!TRASQD9070T1500D37	Transformer 1500 va 600/120-240v v.	Schneider Electric
FU060125A	1	FUSATDR15	Fuse 15 amp, CC, 600 v, Time Delay	Mersen
BA060344	1	OMRS8VK-G48024	Power Supply 24 vcc 20 amp.	Omron
RELAYS	10	OMRG2RV-SL700 DC24	Control Relay 6 mm, 6 amp, 24 vdc	Omron
RELAYS	1	KOMRP2RVM-200B	Connecting Bar 20 poles for G2RV	Omron
CR060821	1	OMRG2R-1-SN-DC24 (S)	Relais 1 pôle 24 vca c/a témoin	Omron
CR060821	1	OMRP2RF-05-E	Base de relais type G2R-1	Omron
MCR060357	1	TELCAD50BD	Relay 10A 5NO 24VCC	Schneider Electric
HMI060546	1	2711P-T4W21D8S	PanelView Plus 7 4.3"	Allen-Bradley

PLC	1	1769-L16ER-BB1B	PLC	Allen-Bradley
PLC	1	1734-IE8C	Analog Input Card	Allen-Bradley
PLC	1	1734-TB	Point I/O terminal base	Allen-Bradley
DU060909	1	7920400000	Duplicateur signal 4-20mA	Weidmuller
ENET060544	1	TELTCSESU053FN0	Ethernet Switch 5 ports	Schneider Electric
HS060375	1	KTELZB4BD2	Selector 2 Position Maintained	Schneider Electric
HS060375	1	KTELZB4BZ101	Contact Block 1NO	Schneider Electric
HS060813	4	KTELZB4BD3	Selector 3 Position Maintained	Schneider Electric
HS060813	4	KTELZB4BZ103	Contact Block 2NO	Schneider Electric
HS060813	4	KTELZBE101	Contact Block 1NO	Schneider Electric
IL060805	1	KTELZB4BV043	Pilot Light Red (LED)	Schneider Electric
IL060805	1	TELZB4BVB4	Mounting Block with Light, LED 24V Red	Schneider Electric
ES060357	1	TELZB4BW643	Red Lit Mushroom Button	Schneider Electric
ES060357	1	TELZB4BVB4	Mounting Block with Light, LED 24V Red	Schneider Electric
ES060357	1	KTELZBE101	Contact Block 1NO	Schneider Electric
ES060357	1	KTELZBE102	Contact Block 1NC	Schneider Electric
ES060357	1	KTELZBY9320	Round EMERGENCY STOP Label	Schneider Electric
PB060709	1	KTELZB4BA2	Black Flush Button	Schneider Electric
PB060709	1	KTELZB4BZ101	Contact Block 1NO	Schneider Electric
GND	3	KN8020A108T	Grounding Bar 10 Holes	Ilsco
TERMINAL BLOCKS	37	ENT1SNK506010R0000	Terminal Block 30 amp. 6mm	ABB
TERMINAL BLOCKS	5	ENT1SNK505910R0000	End Cover	ABB
TERMINAL BLOCKS	32	ENT1SNK505210R0000	Terminal Block 2 Levels 5 mm	ABB
TERMINAL BLOCKS	2	ENT1SNK505960R0000	End Cover	ABB
TERMINAL BLOCKS	8	ENT1SNK505212R0000	Terminal Block 3 Levels	ABB
TERMINAL BLOCKS	1	ENT1SNK505961R0000	End Cover	ABB
FUSE	1	ENT1SNK508418R0000	Fuse Holder 1/4" x 1 1/4"	ABB
FUSE	23	ENT1SNK508425R0000	Fuse Terminal Block 2 Level	ABB
FUSE	1	ENT1SNK508911R0000	End Cover	ABB
FUSE	24	KFUSGMA2	Fuse 250 v. 2 amp. M5 x 20	Bussmann
FUSE	4	FUSGMA5	Fuse 125 v. 5 amp. M5 x 20	Bussmann
FUSE	5	KFUSGMA1	Fuse 250 v. 1 amp. M5 x 20	Bussmann
FUSE	4	FUSGMA3	Fuse 250 v. 3 amp. M5 x 20	Bussmann
FUSE	5	FUSABC20	Fuse 250 v. 20 amp. 1/4 x 1 1/4	Bussmann
TERMINAL BLOCKS	14	ENT1SNK900002R0000	End Stop	ABB
CB060304, CB060306	2	!SU201M-C1	Breaker 1A	ABB
CB060308, CB060355	2	!SU201M-C2	Breaker 2A	ABB
CB060416	1	!SU201M-C5	Breaker 5A	ABB
CB060344	1	!SU201M-C6	Breaker 6A	ABB
PATCH CORD	1	!CAT5ES-06GN	Ethernet Cable RJ45, 6 ft, Green	Infinite cables

LR 60892

REV.	DESCRIPTION	DATE	REV.	VERIÇHK	APPR	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-06	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND ITS CONTENTS MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED FOR ITS USE FOR ANY OTHER PURPOSE. THIS DOCUMENT IS STRICTLY CONFIDENTIAL AND PRI VILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WHETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PRIOR WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE ITEMS OR PURPOSES OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED FOR ANY PROJECT OTHER THAN THE ONE SPECIFIC TO THIS DOCUMENT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
LES RENSEIGNEMENTS CONTENUS DANS CE DOCUMENT SONT LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENNENT DES RENSEIGNEMENTS CONFIDENTIELS ET PROPRIÉTAIRES AINSI QUE D'AUTRES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS Y INTERVENANT CONSTITUENT LA PROPRIÉTÉ EXCLUSIVE DE V.V.T. ET SONT SOUMIS EN CONFIDENCE. LA DIVULGATION, LA REPRODUCTION, LE PRÊT OU L'UTILISATION DE TOUT OU PARTIE DU PRÉSENT DOCUMENT À QUELQUE FIN QUE CE SOIT, AUTRE QUE CELLE POUR LAQUELLE IL EST EXPRESSÉMENT SOUMIS ET POUR LAQUELLE AUCUNE LICENCE IMPLICITE N'EST ACCORDÉE, DOIT FAIRE L'OBJET D'UNE AUTORISATION PRÉALABLE ÉCRITE DE V.V.T. V.V.T. N'ASSUME AUCUNE RESPONSABILITÉ OU OBLIGATION POUR L'UTILISATION DU PRÉSENT DOCUMENT OU DES IDÉES ET CONCEPTS QU'IL CONTIENT POUR DES FINS AUTRES QUE CELLES SPÉCIFIQUES AU PROJET VISÉ PAR LE PRÉSENT DOCUMENT. EN AUCUN CAS LE PRÉSENT DOCUMENT NI LES IDÉES ET CONCEPTS QU'IL CONTIENT NE DOIVENT ÊTRE UTILISÉS POUR UN AUTRE PROJET QUE CELUI VISÉ PAR LE PRÉSENT DOCUMENT. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT IMPLIQUE L'ACCEPTATION DE CES CONDITIONS.

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL PARTS LIST


CLIENT: IQALUIT WWTP

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-EPL-0006-AUT-VWT	JOME01	5 DE 5		4

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



4	AS COMMISSIONNING	2019-05-17	SD				
3	AS BUILT	2019-05-06	SD				
2	FOR FAB	2019-04-02	RM				
1	FOR APPROVAL	2019-03-18	RM				
REV.	DESCRIPTION	DATE	REV.	VERIFIÉ/CHK	APPR.	ECN	

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO "I.D.C." AND ARE SUBMITTED IN CONFIDENCE. NEITHER THIS DOCUMENT NOR THE INFORMATION IT SUBMITTED SHALL BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED TO ANY OTHER USE OF THE INFORMATION. THIS DOCUMENT CONTAINS CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WHETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE EXCEPT WITH THE WRITTEN PERMIT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE OTHERWISE PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE CONSTRUED AS RELATING TO ANY MATTER OTHER THAN THE SPECIFIC PROJECT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE ET AUTRES LOIS. LES DESIGNS, CONCEPTS ET INFORMATIONS CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET SONT SOUMIS EN CONFIDENCE. CE DOCUMENT ET LES INFORMATIONS QUI Y SONT SOUMISES NE DOIVENT ÊTRE UTILISÉS UNIQUEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST OCTROYÉE DE TOUTE AUTRE UTILISATION DE L'INFORMATION. V.W.T. N'ASSUME AUCUNE RESPONSABILITÉ OU OBLIGATION POUR L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS ET INFORMATIONS QUI Y SONT CONTENUS POUR DES FINS AUTRES QUE CELLES SPÉCIFIQUES AU PROJET RELATIF À L'OBJET PRÉVU DE CE DOCUMENT. CE DOCUMENT OU LES CONCEPTS ET L'INFORMATION QUI Y SONT CONTENUS NE DOIVENT EN AUCUN CAS ÊTRE INTERPRÉTÉS COMME SE RAPPORTANT À UN AUTRE PROJET. TOUS LES DROITS D'AUTEUR, BREVET ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT IMPLIQUE L'ACCEPTATION DE CES TERMES ET CONDITIONS.

DESSINÉ/DESIGNER	M.JACQUES
DATE	2019-02-12
VÉRIFIÉ/CHECKER	S.DUQUET
DATE	2019-02-12
INGÉNIEUR/ENGINEER	
DATE	
ÉCHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL SCHEMATIC DIAGRAM 600VAC


CLIENT: IQALUIT WWTP

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0006-AUT-VWT	JOME01	1 DE 9		4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



MOTORS STATUS

MATURATION MIXER STATUS
FEEDER STATUS
HOPPER AGITATOR STATUS

INTERLOCKS

DOSING PUMPS PROTECTION
LOW LEVEL STORAGE TANK

ALARM DRY CONTACT

LOW POWDER LEVEL IN HOPPER
LOW WATER INLET PRESSURE
LOW LEVEL STORAGE TANK
HIGH LEVEL STORAGE TANK
RUN STATUS

MATURATION MIXER / POWDER FEEDER SCREW / HOPPER AGITATOR OL.

EMERGENCY STOP



GENERAL ALARM
DRY CONTACT

4	AS COMMISSIONNING	2019-05-17	SD				
3	AS BUILT	2019-05-06	SD				
2	FOR FAB	2019-04-02	RM				
1	FOR APPROVAL	2019-03-18	RM				
REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN	

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO "I.S.T." AND ARE CONFIDENTIAL AND PROTECTED BY COPYRIGHT LAWS. IT MUST NOT BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED TO THE USE OF THIS DOCUMENT OR THE INFORMATION IN IT. THIS IS A CONFIDENTIAL AND PRIVILEGED INFORMATION OF I.S.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, INSERTED OR USED IN ANY MANNER WHATSOEVER WITHOUT THE EXPRESS WRITTEN PERMIT OF I.S.T. I.S.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED OR EXPRESSED HEREIN IN CONNECTION WITH ANY USE WHICH RELATES TO THE OTHER OUR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED OR EXPRESSED HEREIN BE USED FOR ANY PURPOSE OTHER THAN THE INTENDED OF I.S.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS D'INFORMATION CONTENUS DANS CE DOCUMENT SONT EXPRIMÉES DE SOI-DISANT SECRÈTES ET SONT PROTÉGÉES PAR LES LOIS SUR LE DROIT D'AUTEUR. CE DOCUMENT NE DOIT ÊTRE UTILISÉ QUE DANS LE BUT POUR LEQUEL LE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST OCTROYÉE DE L'UTILISATION DE CE DOCUMENT OU DE L'INFORMATION QUI Y FIGURE. I.S.T. DÉCLINE TOUTE RESPONSABILITÉ OU RESPONSABILITÉ EN CAS D'UTILISATION DE CE DOCUMENT OU DES IDÉES ET CONCEPTS D'INFORMATION CONTENUS OU EXPRIMÉS ICI À DES FINS AUTRES QUE CELLES POUR LESQUELLES CE DOCUMENT A ÉTÉ PRÉPARÉ. EN AUCUN CAS CE DOCUMENT OU LES IDÉES ET CONCEPTS D'INFORMATION QUI Y SONT CONTENUS OU EXPRIMÉS ICI NE DOIVENT ÊTRE UTILISÉS À DES FINS AUTRES QUE CELLES POUR LESQUELLES IL A ÉTÉ PRÉPARÉ. LES DROITS D'AUTEUR, BREVET ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À CES CONDITIONS ET MODALITÉS.

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL SCHEMATIC DIAGRAM 120VAC

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0006-AUT-VWT	JOME01	2 DE 9		4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



4	AS COMMISSIONNING	2019-05-17	SD				
3	AS BUILT	2019-05-06	SD				
2	FOR FAB	2019-04-02	RM				
1	FOR APPROVAL	2019-03-18	RM				
REV.	DESCRIPTION	DATE	REV.	VERIC'HK	APPR.	ECN	

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE: ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED BY THE SUBMISSION OF THIS DOCUMENT. THIS DOCUMENT CONTAINS CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WHETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THIS DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE OTHER OUR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE CONSTRUED AS RELATING OR GIVING ANY RIGHT OF LICENT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE: L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS D'INFORMATION CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET APPARTIENNENT À V.W.T. ET SONT SOUMIS À CONDITION QU'ILS SOIENT UTILISÉS UNIQUEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST ACCORDÉE DE PAR LA SOUMISSION DE CE DOCUMENT. CE DOCUMENT CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET PRIVILÉGIÉS QUI SONT PROPRIÉTAIRES DE V.W.T. ET NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, VENDUS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT ÉCRIT DE V.W.T. V.W.T. N'ASSUME AUCUNE RESPONSABILITÉ OU RESPONSABILITÉ POUR L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS ET L'INFORMATION CONTENUS DANS LES PRÉSENTES À DES FINS AUTRES QUE LE PROJET SPÉCIFIQUE LIÉ À L'OBJET DE CE DOCUMENT. EN AUCUN CAS CE DOCUMENT NE DOIT ÊTRE INTERPRÉTÉ COMME ÉTANT LIÉ À UNE LICENCE OU À UN DROIT DE PROPRIÉTÉ. TOUS LES DROITS D'AUTEUR, BREVET ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À CES CONDITIONS ET MODALITÉS.

DESSINÉ DESIGNER	M.JACQUES
DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET
DATE	2019-02-12
INGÉNIEUR ENGINEER	
DATE	
ÉCHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL SCHEMATIC DIAGRAM 120VAC

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0006-AUT-VWT	JOME01	3 DE 9		4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



4	AS COMMISSIONNING	2019-05-17	SD				
3	AS BUILT	2019-05-06	SD				
2	FOR FAB	2019-04-02	RM				
1	FOR APPROVAL	2019-03-18	RM				
REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN	

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION IT SUBMITTED AND IN NO EVENT LICENCE IS GRANTED TO USE THE DESIGN CONCEPTS AND INFORMATION CONTAINED IN THIS CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, RIBBITTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PRIOR WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PURPOSE RELATED TO THE INTENDED FOR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE CONSTRUED AS GRANTING A LICENCE IN RESPECT OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE. LES DESIGN CONCEPTS ET INFORMATIONS CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET SOUMIS EN CONFIDENCE. CE DOCUMENT ET LES RENSEIGNEMENTS QU'IL CONTIENT DOIVENT ÊTRE UTILISÉS EXCLUSIVEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EN POSSESSION ET NE FAIRE L'OBJET D'AUCUNE LICENCE. LES CONCEPTS ET RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS CONTENUS DANS CE DOCUMENT NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RIBBITÉS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT ÉCRIT PRÉALABLE DE V.W.T. V.W.T. DÉCLINE TOUTE RESPONSABILITÉ ET DÉGAGE LA VEOLIA TOUT RECOURS EN RESPONSABILITÉ RELATIVEMENT À L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS ET RENSEIGNEMENTS QU'IL CONTIENT À DES FINS AUTRES QUE CELLES POUR LESQUELLES CE DOCUMENT EST EN POSSESSION ET NE FAIRE L'OBJET D'AUCUNE LICENCE. EN AUCUN CAS CE DOCUMENT NE DOIT ÊTRE INTERPRÉTÉ COMME UNE LICENCE À L'ÉGARD DE TOUT DROIT D'AUTEUR, BREVET OU AUTRE DROIT DE PROPRIÉTÉ INTELLECTUELLE DE V.W.T. TOUS DROITS D'AUTEUR, BREVET OU AUTRE DROIT DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UN ACCORD À L'ÉGARD DE CES CONDITIONS ET MODALITÉS.

DESSINÉ DESIGNER	M.JACQUES 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET 2019-02-12
INGÉNIEUR ENGINEER	
ÉCHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL SCHEMATIC DIAGRAM 24VDC

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0006-AUT-VWT	JOME01	4 DE 9		4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-06	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE: ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND MAY INCORPORATE CONFIDENTIAL AND PROPRIETARY INFORMATION, OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT, AND ARE SUBMITTED TO YOU ON THE CONDITION THAT THEY AND THIS DOCUMENT MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS BEXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED TO YOU OR ANY OTHER PERSON. THIS DOCUMENT MAY CONTAIN CONFIDENTIAL AND PRIVILEGED INFORMATION OF VWT AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REBITTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PRIOR WRITTEN CONSENT OF V.W.T. V.W.T ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT TO WHICH IT RELATES OR THE OTHER EXPRESS PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED FOR ANY PURPOSE DETRIMENTAL TO THE INTERESTS OF VWT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE : LES RENSEIGNEMENTS CONTENUS DANS CE DOCUMENT SONT LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET PEUVENT NOTAMMENT LES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES DESIGNS CONCEPTS ET INFORMATIONS CONTENUS DANS CE DOCUMENT SONT LA PROPRIÉTÉ DE VWT ET SONT SOUMIS AU FAIT QUE CE DOCUMENT DOIT ÊTRE UTILISÉ EXCLUSIVEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST OCTROYÉE DE VOUS OU DE TOUTE AUTRE PERSONNE. CE DOCUMENT PEUT CONTENIR DES INFORMATIONS CONFIDENTIELLES ET PRIVILÉGIÉES ET VWT ET AUCUNEMENT PEUVENT NE DOIVENT PAS ÊTRE DIVULGUÉES, REPRODUITES, PRÊTÉES, RENDUES OU UTILISÉES EN TOUTE OU EN PARTIE À DES FINS QUELCONQUES SANS LE CONSENTEMENT PRÉALABLE ÉCRIT DE V.W.T. V.W.T N'ASSUME AUCUNE RESPONSABILITÉ OU RESPONSABILITÉ POUR L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS DE CONCEPTION ET DES INFORMATIONS QUI Y SONT CONTENUES À DES FINS AUTRES QUE CELLES POUR LESQUELLES CE DOCUMENT EST SOUMIS ET EN PARTICULIER DE MANIÈRE PRÉJUDICIABLE AUX INTÉRÊTS DE VWT. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UN ACCORD À CES CONDITIONS ET MODALITÉS.

DESSINÉ DESIGNER	M.JACQUES
DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET
DATE	2019-02-12
INGÉNIEUR ENGINEER	
DATE	
ÉCHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL SCHEMATIC DIAGRAM 24VDC

CLIENT: IQALUIT WWTP

VEOLIA


VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036	ELD-0006-AUT-VWT	JOME01	5 DE 9	4

LR 60892


STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE

RACK 00, SLOT 01




RACK 00 SLOT 02

HMI060546



ENET060544



ENET060544/RACK 00 SLOT 01-ENET

ENET060544/HMI060546-ENET

RACK 0

SLOT 01, INPUTS, 1769-L16ER-BB1B, SEE CONNECTING DETAIL DRAWING 5000218036-ELD-0006-AUT-VWT-07

SLOT 01, OUTPUTS, 1769-L16ER-BB1B, SEE CONNECTING DETAIL DRAWING 5000218036-ELD-0006-AUT-VWT-08

SLOT 02, 1734-IE8C, SEE CONNECTING DETAIL DRAWING 5000218036-ELD-0006-AUT-VWT-09

REV.	DESCRIPTION	DATE	REV.	VERIFIÉ/CHK	APPR.	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-06	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. NO PART OF THIS DOCUMENT MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED BY THE SUBMISSION OF THIS DOCUMENT. THIS DOCUMENT IS STRICTLY CONFIDENTIAL AND PRI LEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, INSERTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WHATSOEVER WITHOUT THE PRIOR W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED OR EXPRESSED HEREIN IN CONNECTION WITH ANY USE THAT RELATES TO THE OTHER FOR PURPOSES OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED OR EXPRESSED HEREIN BE USED BY ANY PARTY FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS SPECIFICALLY FURNISHED. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL ETHERNET NETWORK AND PLC

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0006-AUT-VWT	JOME01	6 DE 9		4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



4	AS COMMISSIONNING	2019-05-17	SD				
3	AS BUILT	2019-05-06	SD				
2	FOR FAB	2019-04-02	RM				
1	FOR APPROVAL	2019-03-18	RM				
REV.	DESCRIPTION	DATE	REV.	VERIC/HK	APPR.	ECN	

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE: ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO "I.W.T." AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION IF SUBMITTED. AND IN NO EVENT LICENCE IS GRANTED TO USE THE DESIGN CONCEPTS AND INFORMATION CONTAINED IN THIS CONFIDENTIAL AND PRIVILEGED INFORMATION OF I.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, RIBBITTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE EXPRESS WRITTEN CONSENT OF I.W.T. I.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PURPOSE RELATED TO THE OTHERWISE PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY ANY PARTY FOR ANY PURPOSE IN VIOLATION OF I.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE : L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS ET L'INFORMATION CONTENUS DANS CE DOCUMENT SONT EXPRIMÉES EN CE QUI CONCERNE LA PROPRIÉTÉ DE "I.W.T." ET SONT SOUMIS EN CONFIDENCE. CE DOCUMENT ET L'INFORMATION DOIVENT ÊTRE UTILISÉS UNIQUEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EN POSSESSION SI SOUMIS ET AUCUNE LICENCE N'EST ACCORDÉE DE L'UTILISER POUR TOUTE AUTRE FIN QUE CELLE POUR LAQUELLE IL A ÉTÉ SOUMIS. LES RENSEIGNEMENTS CONFIDENTIELS ET PRIVILÉGIÉS SONT LA PROPRIÉTÉ DE I.W.T. ET NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RIBBITÉS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT ÉCRIT DE I.W.T. I.W.T. N'ASSUME AUCUNE RESPONSABILITÉ OU RESPONSABILITÉ POUR L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS DE CONCEPTION ET DE L'INFORMATION CONTENUE DANS LES PRÉSENTES À DES FINS AUTRES QUE LES FINS SPÉCIFIQUES LIÉES À L'OBJET DE CE DOCUMENT. EN AUCUN CAS CE DOCUMENT NE DOIT ÊTRE UTILISÉ PAR UNE PARTIE À QUELQUE FIN QUE CE SOIT EN VIOLATION DES CONCEPTS DE CONCEPTION ET DE L'INFORMATION CONTENUE DANS LES PRÉSENTES À DES FINS CONNEXES. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À L'ÉGARD DE CES CONDITIONS ET MODALITÉS.

DESSINÉ DESIGNER	M.JACQUES
DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET
DATE	2019-02-12
INGÉNIEUR ENGINEER	
DATE	
ÉCHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL
RACK 00 SLOT 01 INPUTS, 1769-L18ER-BB1B

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0006-AUT-VWT	JOME01	7 DE 9		4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



4	AS COMMISSIONNING	2019-05-17	SD				
3	AS BUILT	2019-05-06	SD				
2	FOR FAB	2019-04-02	RM				
1	FOR APPROVAL	2019-03-18	RM				

REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT OR ANY PART THEREOF MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION IT SUBMITTED AND IN DUPLICATE LICENCE IS GRANTED TO THE RECIPIENT. THIS DOCUMENT CONTAINS TRADE SECRETS AND CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WHETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PRIOR WRITTEN CONSENT OF V.W.T. ASSUMING NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE INTENDED PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED FOR ANY PURPOSE DETRIMENTAL TO THE INTERESTS OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET EST PROTÉGÉE PAR LES LOIS SUR LES DROITS D'AUTEUR, LES BREVETS ET LES AUTRES LOIS RELATIVES À LA PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET RENSEIGNEMENTS CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET APPARTIENNENT EXCLUSIVEMENT À V.W.T. CE DOCUMENT EST SOUMIS EN CONFIANCE. IL NE PEUT ÊTRE UTILISÉ QU'AUX FINS POUR LESQUELLES IL A ÉTÉ REMIS ET LA LICENCE EST ACCORDÉE UNIQUEMENT AU DESTINATAIRE. CE DOCUMENT CONTIENT DES SECRETS COMMERCIAUX ET DES RENSEIGNEMENTS CONFIDENTIELS ET PRIVILÉGIÉS QUI SONT LA PROPRIÉTÉ EXCLUSIVE DE V.W.T. CES RENSEIGNEMENTS NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, VENDUS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT PRÉALABLE ÉCRIT DE V.W.T. EN RECONNAISSANT QU'AUCUNE RESPONSABILITÉ OU OBLIGATION NE DÉCOULE DE L'UTILISATION DE CE DOCUMENT OU DES IDÉES ET RENSEIGNEMENTS QU'IL CONTIENT POUR DES FINS AUTRES QUE CELLES PRÉVUES DANS LE CADRE DU PROJET PRÉCIS LIÉ À L'OBJET PRÉVU DE CE DOCUMENT. EN AUCUN CAS CE DOCUMENT NI LES IDÉES OU RENSEIGNEMENTS QU'IL CONTIENT NE DOIVENT ÊTRE UTILISÉS À DES FINS QUI NUISENT AUX INTÉRÊTS DE V.W.T. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT NE CONSTITUE EN AUCUN CAS UNE CESSION DE CES DROITS.

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		


TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL
RACK 00 SLOT 01 OUTPUTS, 1769-L18ER-BB1B

CLIENT: IQALUIT WWTP

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036	ELD-0006-AUT-VWT	JOME01	8 DE 9	4



REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-06	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO "I.S.T." AND ARE SUBMITTED IN CONFIDENCE FOR THE SOLE USE OF "I.S.T." AND MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION IT SUBMITTED. AND IN NO IMPLICIT LICENCE IS GRANTED TO USE THE DESIGN CONCEPTS CONTAINED HEREIN. THIS DOCUMENT IS CONFIDENTIAL AND PRIVILEGED INFORMATION OF "I.S.T." AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, RIBBITTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PRIOR WRITTEN OF "I.S.T." "I.S.T." ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATE TO THE OTHER OUR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY ANY PERSON FOR ANY PURPOSE OTHER THAN THE SPECIFIC PROJECT WITHOUT THE WRITTEN CONSENT OF "I.S.T." ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES DESIGN CONCEPTS ET INFORMATION CONTENUS DANS CE DOCUMENT SONT LA PROPRIÉTÉ DE "I.S.T." ET SONT SOUMIS EN CONFIDENCE POUR L'USAGE EXCLUSIF DE "I.S.T." CE DOCUMENT NE DOIT ÊTRE UTILISÉ QUE POUR LE BUT POUR LEQUEL IL EST SOUMIS ET AUCUNE LICENCE N'EST IMPLICITEMENT ACCORDÉE QUANT À L'UTILISATION DE L'INFORMATION CONTENUE DANS LES PRÉSENTES. CE DOCUMENT CONFIDENTIEL ET PRIVILÉGIÉ APPARTIENT À "I.S.T." ET NE DOIT PAS ÊTRE DIVULGUÉ, REPRODUIT, PRÊTÉ, RIBBIS OU UTILISÉ EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT PRÉALABLE ÉCRIT DE "I.S.T." "I.S.T." N'ASSUME AUCUNE RESPONSABILITÉ OU RESPONSABILITÉ QUANT À L'UTILISATION DE CE DOCUMENT OU DES DESIGN CONCEPTS ET L'INFORMATION CONTENUE DANS LES PRÉSENTES POUR DES FINS AUTRES QUE CELLES QUI SE RAPPORTENT DIRECTEMENT AU PROJET SPÉCIFIQUE RELATIF À L'OBJET DE CE DOCUMENT. EN AUCUN CAS CE DOCUMENT NI LES DESIGN CONCEPTS OU L'INFORMATION QU'IL CONTIENT NE DOIVENT ÊTRE UTILISÉS PAR QUICONQUE À DES FINS AUTRES QUE CELLES QUI SE RAPPORTENT DIRECTEMENT AU PROJET SPÉCIFIQUE RELATIF À L'OBJET DE CE DOCUMENT SANS LE CONSENTEMENT PRÉALABLE ÉCRIT DE "I.S.T." TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À L'ÉGARD DE CES CONDITIONS.

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 250 CONTROL PANEL
RACK 0, SLOT 02, 1734-IE8C

CLIENT: IQALUIT WWTP

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036	ELD-0006-AUT-VWT	JOME01	9 DE 9	4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P01 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE

HYDRAPOL 500 CONTROL PANEL
PROJECT - 5000218036
LCP-04-900
BFP POLYMER DOSING SYSTEM

REV.	DESCRIPTION	DATE	REV.	VERIC/VÉR	APPR.	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-03	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE:
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND MAY CONTAIN CONFIDENTIAL AND PROPRIETARY INFORMATION OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED TO AND IN CONFIDENCE TO THE RECIPIENT. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION. IT SUBMITTED AND IN DUPLICATE LICENCE IS GRANTED TO THE RECIPIENT TO USE THE DESIGN CONCEPTS AND INFORMATION CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, INSETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PRIOR WRITTEN CONSENT OF V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE ATTACHED OR PURPOSES OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED FOR ANY PURPOSE OTHER THAN THE SPECIFIC OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET PEUT CONTENIR D'AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS ET INFORMATIONS CONTENUES DANS CE DOCUMENT SONT CONFIDENTIELS ET PROPRIÉTAIRES À V.W.T. ET SONT SOUMIS À LA CONFIDENTIALITÉ. CE DOCUMENT NE PEUT ÊTRE UTILISÉ QUE DANS LE BUT POUR LEQUEL IL EST EN POSSESSION. SI SOUMIS ET EN DOUBLE LA LICENCE EST ACCORDÉE AU DESTINATAIRE POUR UTILISER LES IDÉES, CONCEPTS ET INFORMATIONS CONFIDENTIELS ET PRIVILÉGIÉS APPARTENANT À V.W.T. ET NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RÉDIGÉS OU UTILISÉS EN TOUTE OU EN PARTIE À TOUTE AUTRE FIN SANS LE CONSENTEMENT ÉCRIT PRÉALABLE DE V.W.T. V.W.T. DÉCLINE TOUTE RESPONSABILITÉ OU RESPONSABILITÉ EN CAS D'UTILISATION DE CE DOCUMENT AINSI QUE DES IDÉES ET CONCEPTS ET INFORMATION CONTENUES DANS LES PRÉSENTES À DES FINS AUTRES QUE CELLES LIÉES AU PROJET SPÉCIFIQUE CI-JOINT OU AUX FINS DE CE DOCUMENT. EN AUCUN CAS, CE DOCUMENT OU LES IDÉES ET CONCEPTS ET INFORMATION CONTENUES DANS LES PRÉSENTES NE DOIVENT ÊTRE UTILISÉS À D'AUTRES FINS QUE CELLES SPÉCIFIQUES DU PROJET CI-JOINT. TOUS LES DROITS D'AUTEUR, BREVET ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UN ACCORD À CES CONDITIONS ET MODALITÉS.

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL
TITLE PAGE

CLIENT: IQALUIT WWTP

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT + DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-EPL-0007-AUT-VWT	JOME01	1 DE 5	4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE

M:\AUT\2015 11\5000 C \ Users \ mjacques \ Desktop \ CARTOUCHE \ VWTC RETAINER 2015.dwg - Model

DRAWING INDEX

DESCRIPTION	DRAWING NUMBER
CONTROL PANEL	
TITLE PAGE	5000218036-EPL-0007-AUT-VWT-01
DRAWING LIST & LEGEND	5000218036-EPL-0007-AUT-VWT-02
OUTSIDE PANEL LAYOUT	5000218036-EPL-0007-AUT-VWT-03
INSIDE PANEL LAYOUT	5000218036-EPL-0007-AUT-VWT-04
PARTS LIST	5000218036-EPL-0007-AUT-VWT-05
SCHEMATIC DIAGRAM 600VAC	5000218036-ELD-0007-AUT-VWT-01
SCHEMATIC DIAGRAM 120VAC	5000218036-ELD-0007-AUT-VWT-02
SCHEMATIC DIAGRAM 120VAC	5000218036-ELD-0007-AUT-VWT-03
SCHEMATIC DIAGRAM 24VDC	5000218036-ELD-0007-AUT-VWT-04
SCHEMATIC DIAGRAM 24VDC	5000218036-ELD-0007-AUT-VWT-05
ETHERNET NETWORK AND PLC	5000218036-ELD-0007-AUT-VWT-06
RACK 00 SLOT 01 INPUTS, 1769-L16ER-BB1B	5000218036-ELD-0007-AUT-VWT-07
RACK 00 SLOT 01 OUTPUTS, 1769-L16ER-BB1B	5000218036-ELD-0007-AUT-VWT-08
RACK 0, SLOT 02, 1734-IEBC	5000218036-ELD-0007-AUT-VWT-09

COLORS AND WIRING GAGES		
120VAC POWER	BLACK	14AWG
120VAC CONTROL	RED	14AWG
NEUTRE	WHITE	14AWG
DRY CONTACT	YELLOW	14AWG
24VDC	BLUE(+), BLUE / WHITE(-)	16AWG (0 TO 9A) 14AWG (10A & +)
GROUND	GREEN	14AWG
ISOLATED GROUND	GREEN / YELLOW	14AWG
ANALOG I/O TWISTED PAIRS	BLACK(+), WHITE(-)	18AWG
DIGITAL I/O 120VA	RED	16AWG
DIGITAL I/O 24VDC	BLUE	16AWG
LOW VOLTAGE (12, 24, 48VDC)	BLUE	16AWG (0 À 9A) 14AWG (10A & +)
CONTROL CIRCUIT 5 TO 60VDC	BLUE(+), BLUE/WHITE(-), GREEN(GND)	16AWG (0 À 9A) 14AWG (10A & +)

SUPPLY WIRING IDENTIFICATION

XX XX XX

- LINE NUMBER
- PAGE NUMBER
- PANEL NUMBER (IF MORE THAN ONE PANEL
  01 - PANEL No1
  02 - PANEL No2, ...

LEGEND LIST

- PSL — LOW PRESSURE SWITCH
- PSH — HIGH PRESSURE SWITCH
- LSL — LOW LEVEL SWITCH
- LSH — HIGH LEVEL SWITCH
- LSNO — LIMIT SWITCH NO
- LSNC — LIMIT SWITCH NC
- FSL — LOW FLOW SWITCH
- FSH — HIGH FLOW SWITCH
- TSL — LOW TEMPERATURE SWITCH
- TSH — HIGH TEMPERATURE SWITCH
- OFF DELAY TIMER [NO]
- OFF DELAY TIMER [NC]
- ON DELAY TIMER [NC]
- ON DELAY TIMER [NO]
- NO — CONTACT NO
- NC — CONTACT NC
- GND — GROUND
- GND — ISOLATED GROUND
- TERMINAL OF PANEL
- TERMINAL OF OTHER PANEL

- HS — MAINTAINED TWO POSITIONS SELECTOR
- HS — MAINTAINED THREE POSITIONS SELECTOR
- HS — THREE POSITIONS SELECTOR BOTH RETURN
- HS — THREE POSITIONS SELECTOR LEFT RETURN
- HS — THREE POSITIONS SELECTOR RIGHT RETURN
- PBNO — PUSH BUTTON NO
- PBNC — PUSH BUTTON NC
- ES — EMERGENCY STOP PUSH BUTTON
- POT — POTENTIOMETER
- FU — FUSE
- CB — CIRCUIT BREAKER
- IL — PUSH-TO-TEST LIGHT
- IL — LIGHT
- CMR — CURRENT MONITORING RELAY
- AC — A/C — AIR CONDITIONER UNIT

- M — CONTACTOR COIL
- TR — TIMER RELAY COIL
- CR — CONTROL RELAY COIL
- MCR — MASTER CONTROL RELAY COIL
- CR — CONTROL RELAY COIL WITH SURGE SURPRESSOR
- FV — SOLENOID
- R — RESISTANCE
- HN — HORN
- F — FAN / VENTILATOR / BLOWER
- CT — CURRENT TRANSFORMER
- PC — 120VAC DUPLEX OUTLET
- AM — AMPEREMETER
- VM — VOLMETER

- DISC — FUSED DISCONNECT SWITCH
- FU — 3PH FUSE HOLDER
- DISC — DISCONNECT SWITCH
- OL — MANUAL STARTER WITH THERMINAL & MAGNETIC PROTECTION
- OL — MANUAL STARTER WITH MAGNETIC PROTECTION
- M — CONTACTOR
- OL — OVERLOAD

- TR — H1, H2, X1, X2 — TRANSFORMER
- TR — H1, H2, X1, X2, X3, X4 — MULTI-TAPS TRANSFORMER

LR 60892

REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-03	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED BY THIS DOCUMENT OR BY THE DISCLOSURE OF ITS CONTENTS. THIS CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, INSERTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE OTHERWISE EXPRESS OR THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY ANY PERSON FOR ANY PURPOSE OTHER THAN THE SPECIFIC PROJECT WITHOUT THE WRITTEN CONSENT OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS ET RENSEIGNEMENTS CONTENUS DANS CE DOCUMENT SONT EXPRIMÉS EN CONFIDENCE. CE DOCUMENT ET LES RENSEIGNEMENTS QU'IL CONTIENT DOIVENT ÊTRE UTILISÉS EXCLUSIVEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST OCTROYÉE EN VERTU DU PRÉSENT DOCUMENT OU DE LA DIVULGATION DE SON CONTENU. CES RENSEIGNEMENTS CONFIDENTIELS ET PRIVILÉGIÉS SONT LA PROPRIÉTÉ DE V.W.T. ET NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, INSÉRÉS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT ÉCRIT DE V.W.T. V.W.T. DÉCLINE TOUTE RESPONSABILITÉ ET DÉGAGE LA VILLE DE SOREL-TRACY DE TOUTE RESPONSABILITÉ QUANT À L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS ET RENSEIGNEMENTS QU'IL CONTIENT À DES FINS AUTRES QUE CELLES SPÉCIFIQUES AU PROJET VISÉ PAR CE DOCUMENT OU AUTREMENT EXPRIMÉES DANS CE DOCUMENT. EN AUCUN CAS CE DOCUMENT OU LES CONCEPTS ET RENSEIGNEMENTS QU'IL CONTIENT NE DOIVENT ÊTRE UTILISÉS PAR QUICONQUE À DES FINS AUTRES QUE CELLES PRÉCISÉES DANS LE PRÉSENT DOCUMENT SANS LE CONSENTEMENT ÉCRIT DE V.W.T. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS À V.W.T. L'ACCEPTATION DE LA LIVRAISON DU PRÉSENT DOCUMENT CONSTITUE UNE ENTENTE À L'EFFET QUE LES CONDITIONS ÉNONCÉES CI-DESSUS S'APPLIQUENT.

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL
DRAWING LIST & LEGEND

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-EPL-0007-AUT-VWT	JOME01	2 DE 5		4

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE

30-APR-2019 14:49:00 C:\Users\rmassicotte\Desktop\CAM\TO-DO\VWT\5000218036-EPL-0007-AUT-VWT-02.DWG



ENCLOSURE 42" x 36" x 12"



DOOR DETAILS

LR 60892

REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-03	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE FOR A SPECIFIC PURPOSE AND MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED. ANDNO IMPLICIT LICENCE IS GRANTED TO USE THE DESIGN CONCEPTS OR INFORMATION. THIS DOCUMENT IS CONFIDENTIAL AND PRI VILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, INSERTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WHATSOEVER WITHOUT THE W.V.T. S ASSUMESNO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED OR EXPRESSED HEREIN IN CONNECTION WITH ANY USE WHICH RELATES TO THE OTHER OUR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED OR EXPRESSED HEREIN BE USED FOR THE BENEFIT OF A THIRD PARTY. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL OUTSIDE PANEL LAYOUT


CLIENT: IQALUIT WWTP

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-EPL-0007-AUT-VWT	JOME01	3 DE 5		4

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



4	AS COMMISSIONNING	2019-05-17	SD				
3	AS BUILT	2019-05-03	SD				
2	FOR FAB	2019-04-02	RM				
1	FOR APPROVAL	2019-03-18	RM				
REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN	

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND MAY CONTAIN CONFIDENTIAL, PROPRIETARY AND/OR OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED BY THE SUBMISSION OF THIS DOCUMENT. THIS DOCUMENT IS STRICTLY CONFIDENTIAL AND PRI VILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, INSETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE OTHER OUR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY ANY PERSON FOR ANY PURPOSE OTHER THAN THE SPECIFIC PROJECT FOR WHICH IT WAS PROVIDED. UNDER THE LAWS OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET PEUT CONTENIR DES LOIS DE NATURE CONFIDENTIELLE, PROPRIÉTAIRE ET AUTRE DE PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS D'INFORMATION CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET SOUMIS EN CONFIDENCE. CE DOCUMENT ET L'INFORMATION DOIVENT ÊTRE UTILISÉS EXCLUSIVEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST ACCORDÉE EN SOUMETTANT CE DOCUMENT. CE DOCUMENT EST STRICTEMENT CONFIDENTIEL ET CONTIENT DES RENSEIGNEMENTS PRIVILÉGIÉS DE V.W.T. ET CES DERNIERS NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RÉDIGÉS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT ÉCRIT DE V.W.T. V.W.T. N'ASSUME AUCUNE RESPONSABILITÉ OU RESPONSABILITÉ POUR L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS DE CONCEPTION ET DES INFORMATIONS CONTENUES DANS LES PRÉSENTES À DES FINS AUTRES QUE LE PROJET SPÉCIFIQUE LIÉ À L'AUTRE OBJET DE CE DOCUMENT. EN AUCUN CAS CE DOCUMENT OU LES CONCEPTS DE CONCEPTION ET L'INFORMATION QU'IL CONTIENT NE DOIVENT ÊTRE UTILISÉS PAR UNE PERSONNE À DES FINS AUTRES QUE CELLES POUR LESQUELLES IL A ÉTÉ FOURNI. TOUS LES DROITS D'AUTEUR, BREVET ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS EN VERTU DES LOIS DE V.W.T. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À CES CONDITIONS ET AVIS.

DESSINÉ DESIGNER	M.JACQUES	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	2019-02-12
INGÉNIEUR ENGINEER		

TITRE TITLE: HYDRAPOL 500 CONTROL PANEL INSIDE PANEL LAYOUT

CLIENT: IQALUIT WWTP

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-EPL-0007-AUT-VWT	JOME01	4 DE 5		4

ECHELLE/SCALE:

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE

Mai/07 2019, 11:49:00 C:\Users\mjacques\Desktop\CAM\CAD-CHE-QVTC-R&T\DWG\5000218036-EPL-0007-AUT-VWT-R04.dwg

Items	Qty	Part Number	Description	Manufacturer
ENCLOSURE	1	!SP1404283	Special Enclosure 42" x 36" x 12"	Hammond
ENCLOSURE	1	BOIHAMPKT99	Document Holder	Hammond
LTG070408	1	!RABUC-LED300-NW	LED Bar 300mm, 3 watts, 24 vdc (88861)	RAB
ZS070408	1	BOIHAMFDS1	Door Switch for Light	Hammond
DS070105	1	!TELGS1DU3	Fused Disconnect Switch 30A/600V (Fus. Type J	Schneider Electric
DS070105	1	!TELGS2AE8	Operating Shaft 30a 12.6"	Schneider Electric
DS070105	1	!TELGS2AH420	Operating Handle Red / Yellow NEMA 4-4X	Schneider
DS070105	3	FUSAJT15	Fuse 15 amp.Type J Time Delay	Mersen
DB070110	3	KCONMPDBC6263	Protective Cover for Distribution Block	Mersen
DB070110	1	KCONMPDB63133	Distribution Block	Mersen
OL070145	1	TELGV2ME05	Manual Starter 0,63-1A	Schneider Electric
OL070145	1	TELGVAN20	Aux Contact for GV2, GV3P, 2NO	Schneider Electric
M070145	1	TELLC1D09BD	Contactor 7,5HP/600V 1NO-1NF 24VDC	Schneider Electric
M070145	1	KTELLADN20	Aux Contact 2NO	Schneider Electric
OL070155	1	TELGV2ME05	Manual Starter 0,63-1A	Schneider Electric
OL070155	1	TELGVAN20	Aux Contact for GV2, GV3P, 2NO	Schneider Electric
M070155	1	TELLC1D09BD	Contactor 7,5HP/600V 1NO-1NF 24VDC	Schneider Electric
M070155	1	KTELLADN20	Aux Contact 2NO	Schneider Electric
OL070165	1	TELGV2ME06	Manual Starter 1-1,6A	Schneider Electric
OL070165	1	TELGVAN20	Aux Contact forGV2, GV3P, 2NO	Schneider Electric
M070165	1	TELLC1D09BD	Contactor 7,5HP/600V 1NO-1NF 24VDC	Schneider Electric
M070165	1	KTELLADN20	Aux Contact 2NO	Schneider Electric
CB070232	1	!SU202M-C15	Breaker 15A 2 poles	ABB
CR070375	1	TELLC1D09BD	Contactor 7,5HP/600V 1NO-1NF 24VDC	Schneider Electric
TR070115	1	!TRASQD9070FB3B	Fuse Holder for XFO (Primairy + Secondairy)	Schneider Electric
FU070115	2	FUSATQR5	Fuse 5 amp, CC, 600 v, Time Delay	Mersen
FU070115A	1	FUSATDR15	Fuse 15 amp, CC, 600 v, Time Delay	Mersen
TR070115	1	KSQD9070FSC2	Protective Cover for Transformer	Schneider Electric
TR070115	3	!SPL0001T	Protective Cover for Fuse Holder	Littelfuse
TR070115	1	TRASQD9070T1500D5	Transformer 1500 va 600/120 v.	Schneider Electric
TR070125	1	!TRASQD9070FB3B	Fuse Holder for XFO (Primairy + Secondairy)	Schneider Electric
FU070125	2	FUSATQR5	Fuse 5 amp, CC, 600 v, Time Delay	Mersen
TR070125	1	KSQD9070FSC2	Protective Cover for Transformer	Schneider Electric
TR070125	3	!SPL0001T	Protective Cover for Fuse Holder	Littelfuse
TR070125	1	!TRASQD9070T1500D37	Transformer 1500 va 600/120-240v v.	Schneider Electric
FU070125A	1	ABBE9230CC	Fuse Holder 30 amp, IP20, 2 poles, type CC	ABB
FU070125A	2	FUSATDR15	Fuse 15 amp, CC, 600 v, Time Delay	Mersen
BA070344	1	OMRS8VK-G48024	Power Supply 24 vcc 20 amp.	Omron
RELAYS	8	OMRG2RV-SL700 DC24	Control Relay 6 mm, 6 amp, 24 vdc	Omron
RELAYS	1	KOMRP2RVM-200B	Connecting Bar 20 poles for G2RV	Omron
CR070821	1	OMRG2R-1-SN-DC24 (S)	Relais 1 pôle 24 vca c/a témoin	Omron
CR070821	1	OMRP2RF-05-E	Base de relais type G2R-1	Omron
MCR070357	1	TELCAD50BD	Relay 10A 5NO 24VCC	Schneider Electric
HMI070546	1	2711P-T4W21D8S	PanelView Plus 7 4.3"	Allen-Bradley
PLC	1	1769-L16ER-BB1B	PLC	Allen-Bradley
PLC	1	1734-IE8C	Analog Input Card	Allen-Bradley
PLC	1	1734-TB	Point I/O terminal base	Allen-Bradley
DU070909	1	7920400000	Duplicateur signal 4-20mA	Weidmuller
ENET070544	1	TELTCSESU053FN0	Ethernet Switch 5 ports	Schneider Electric
HS070375	1	KTELZB4BD2	Selector 2 Position Maintained	Schneider Electric
HS070375	1	KTELZB4BZ101	Contact Block 1NO	Schneider Electric
HS070813	4	KTELZB4BD3	Selector 3 Position Maintained	Schneider Electric
HS070813	4	KTELZB4BZ103	Contact Block 2NO	Schneider Electric
HS070813	4	KTELZBE101	Contact Block 1NO	Schneider Electric
IL070805	1	KTELZB4BV043	Pilot Light Red (LED)	Schneider Electric
IL070805	1	TELZB4BVB4	Mounting Block with Light, LED 24V Red	Schneider Electric
ES070357	1	TELZB4BW643	Red Lit Mushroom Button	Schneider Electric
ES070357	1	TELZB4BVB4	Mounting Block with Light, LED 24V Red	Schneider Electric
ES070357	1	KTELZBE101	Contact Block 1NO	Schneider Electric
ES070357	1	KTELZBE102	Contact Block 1NC	Schneider Electric
ES070357	1	KTELZBY9320	Round EMERGENCY STOP Label	Schneider Electric
PB070709	1	KTELZB4BA2	Black Flush Button	Schneider Electric
PB070709	1	KTELZB4BZ101	Contact Block 1NO	Schneider Electric
GND	3	KN8020A108T	Grounding Bar 10 Holes	Ilsco
TERMINAL BLOCKS	37	ENT1SNK506010R0000	Terminal Block 30 amp. 6mm	ABB
TERMINAL BLOCKS	5	ENT1SNK505910R0000	End Cover	ABB
TERMINAL BLOCKS	32	ENT1SNK505210R0000	Terminal Block 2 Levels 5 mm	ABB
TERMINAL BLOCKS	2	ENT1SNK505960R0000	End Cover	ABB
TERMINAL BLOCKS	8	ENT1SNK505212R0000	Terminal Block 3 Levels	ABB
TERMINAL BLOCKS	1	ENT1SNK505961R0000	End Cover	ABB
FUSE	1	ENT1SNK508418R0000	Fuse Holder 1/4" x 1 1/4"	ABB
FUSE	23	ENT1SNK508425R0000	Fuse Terminal Block 2 Level	ABB
FUSE	1	ENT1SNK508911R0000	End Cover	ABB
FUSE	24	KFUSGMA2	Fuse 250 v. 2 amp. M5 x 20	Bussmann
FUSE	4	FUSGMA5	Fuse 125 v. 5 amp. M5 x 20	Bussmann
FUSE	5	KFUSGMA1	Fuse 250 v. 1 amp. M5 x 20	Bussmann
FUSE	4	FUSGMA3	Fuse 250 v. 3 amp. M5 x 20	Bussmann
FUSE	5	FUSABC20	Fuse 250 v. 20 amp. 1/4 x 1 1/4	Bussmann
TERMINAL BLOCKS	14	ENT1SNK900002R0000	End Stop	ABB
CB070304, CB070306	2	!SU201M-C1	Breaker 1A	ABB
CB070308, CB070355	2	!SU201M-C2	Breaker 2A	ABB
CB070416	1	!SU201M-C5	Breaker 5A	ABB
CB070344	1	!SU201M-C6	Breaker 6A	ABB
PATCH CORD	1	!CAT5ES-06GN	Ethernet Cable RJ45, 6 ft, Green	Infinite cables

LR 60892

REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR.	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-03	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE: ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO "I.S.T." AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION. IT SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED TO USE THE DESIGN CONCEPTS CONTAINED HEREIN. THIS DOCUMENT IS CONFIDENTIAL AND PRIVILEGED INFORMATION OF I.S.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WRITTEN OR USED IN WHOLE OR IN PART FOR THE BENEFIT OF ANYONE OTHER THAN I.S.T. I.S.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE PURPOSE WHICH RELATE TO THE OTHERWISE PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY ANY PERSON FOR ANY PURPOSE OTHER THAN THE PURPOSE OF I.S.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE : LES RENSEIGNEMENTS CONTENUS DANS CE DOCUMENT SONT LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENNENT DES RENSEIGNEMENTS CONFIDENTIELS ET DE PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS D'INGÉNIERIE CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET C'EST POURQUOI ILS SONT SOUMIS À LA CONDITION QU'ILS NE SERVENT QU'AUX FINS POUR LESQUELLES ILS SONT DESTINÉS. UNE LICENCE IMPLICITE N'EST ACCORDÉE À PERSONNE D'UTILISER LES IDÉES ET CONCEPTS D'INGÉNIERIE CONTENUS DANS CE DOCUMENT. CE DOCUMENT CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET PRIVILÉGIÉS D'I.S.T. ET NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RÉDIGÉS OU UTILISÉS EN TOUTE OU EN PARTIE AU PROFIT DE QUICONQUE D'AUTRE QUE I.S.T. I.S.T. N'ASSUME AUCUNE RESPONSABILITÉ OU OBLIGATION QUANT À L'UTILISATION DE CE DOCUMENT AINSI QUE DES IDÉES ET CONCEPTS D'INGÉNIERIE CONTENUS DANS LES PRÉSENTES À DES FINS AUTRES QUE CELLES QUI SONT LIÉES À L'OBJET DE CE DOCUMENT. EN AUCUN CAS CE DOCUMENT OU LES IDÉES ET CONCEPTS D'INGÉNIERIE QUI Y SONT CONTENUS NE DOIVENT ÊTRE UTILISÉS PAR QUICONQUE À DES FINS AUTRES QUE CELLES QUI SONT LIÉES À L'OBJET DE CE DOCUMENT. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ACCEPTATION DE CES CONDITIONS.


DESSINÉ DESIGNER	M.JACQUES	DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE	2019-02-12
INGÉNIEUR ENGINEER		DATE	
ÉCHELLE/SCALE:			

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL PARTS LIST

CLIENT: IQALUIT WWTP

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-EPL-0007-AUT-VWT	JOME01	5 DE 5		4



4	AS COMMISSIONNING	2019-05-17	SD				
3	AS BUILT	2019-05-03	SD				
2	FOR FAB	2019-04-02	RM				
1	FOR APPROVAL	2019-03-18	RM				
REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN	

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO "I.D.C" AND ARE SUBMITTED IN CONFIDENCE. NEITHER THIS DOCUMENT NOR ANY PART MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO DUPLICATE LICENCE IS GRANTED OR IMPLIED. THIS DOCUMENT MUST NOT BE COPIED AND THE CONTENTS, CONFIDENTIAL AND PRIVILEGED INFORMATION OF I.D.C.", AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WHETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PERMISSION OF I.D.C. I.D.C. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE ATTACHED OR PURPOSES OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY ANY PARTY FOR ANY PURPOSE IN VIOLATION OF I.D.C.'S ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES LOIS DE PROPRIÉTÉ INTELLECTUELLE ET AUTRES. LES IDÉES ET LES CONCEPTS DE CONCEPTION ET L'INFORMATION CONTENUE DANS CE DOCUMENT SONT LA PROPRIÉTÉ DE "I.D.C." ET SONT SOUMIS EN CONFIDENCE. NI CE DOCUMENT NI AUCUNE PARTIE NE DOIVENT ÊTRE UTILISÉS UNIQUEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE DUPLIQUÉE N'EST ACCORDÉE OU IMPLIQUÉE. CE DOCUMENT NE DOIT PAS ÊTRE COPIÉ ET LE CONTENU, L'INFORMATION CONFIDENTIELLE ET PRIVILÉGIÉE DOIVENT NE PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RÉDIGÉS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LA PERMISSION DE I.D.C. I.D.C. DÉCLINE TOUTE RESPONSABILITÉ OU RESPONSABILITÉ À L'ÉGARD DE L'UTILISATION DE CE DOCUMENT AINSI QUE DES IDÉES ET DES CONCEPTS DE CONCEPTION CONTENUS DANS LES PRÉSENTES À DES FINS AUTRES QUE CELLES LIÉES AU PROJET SPÉCIFIQUE CI-JOINT OU AUX FINS DE CE DOCUMENT. EN AUCUN CAS CE DOCUMENT NI LES IDÉES ET CONCEPTS DE CONCEPTION QUI Y SONT CONTENUS NE DOIVENT ÊTRE UTILISÉS PAR UNE PARTIE QUELCONQUE D'UNE MANIÈRE QUI ENFREINT LES DROITS D'AUTEUR, LES BREVETS ET LES AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE D'I.D.C. TOUS DROITS RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À CES CONDITIONS ET MODALITÉS.

DESSINÉ DESIGNER	M.JACQUES
DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET
DATE	2019-02-12
INGÉNIEUR ENGINEER	
DATE	
ECHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL SCHEMATIC DIAGRAM 600VAC

CLIENT: IQALUIT WWTP


VEOLIA


VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0007-AUT-VWT	JOME01	1 DE 9	4	

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE





REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-03	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO "I.D.C." AND ARE CONFIDENTIAL AND PROTECTED BY COPYRIGHT LAWS. THIS DOCUMENT MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED TO THE USE OF THE DESIGN CONCEPTS AND INFORMATION OF THIS CONFIDENTIAL AND PROPRIETARY INFORMATION OF I.D.C. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, INSERTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WHATSOEVER WITHOUT THE PRIOR WRITTEN CONSENT OF I.D.C. I.D.C. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE OTHERWISE PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE CONSTRUED AS RELATING TO ANY MANNER OF USE OF I.D.C. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES INFORMATIONS CONFIDENTIELLES ET PROPRIÉTAIRES ET D'AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE. LES DESIGN CONCEPTS ET INFORMATIONS CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET DE PROPRIÉTÉ EXCLUSIVE DE I.D.C. ET SONT PROTÉGÉS PAR DES LOIS SUR LES DROITS D'AUTEUR. CE DOCUMENT DOIT UNIQUEMENT ÊTRE UTILISÉ EXCLUSIVEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST OCTROYÉE DE L'UTILISATION DES CONCEPTS DE DESIGN ET DES INFORMATIONS CONTENUES DANS CE DOCUMENT CONFIDENTIEL ET DE PROPRIÉTÉ EXCLUSIVE DE I.D.C. ET CES DERNIERS NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, INSÉRÉS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT PRÉALABLE ÉCRIT DE I.D.C. I.D.C. N'ASSUME AUCUNE RESPONSABILITÉ OU RESPONSABILITÉ POUR L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS DE DESIGN ET DES INFORMATIONS QUI Y SONT CONTENUES À DES FINS AUTRES QUE CELLES SPÉCIFIQUES AU PROJET LIÉ À L'OBJET DE CE DOCUMENT. EN AUCUN CAS CE DOCUMENT NE DOIT ÊTRE INTERPRÉTÉ COMME SE RAPPORTANT À UNE QUELCONQUE MANIÈRE D'UTILISER LES CONCEPTS DE DESIGN ET LES INFORMATIONS CONTENUES DANS CE DOCUMENT. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UN ACCORD À CES CONDITIONS ET MODALITÉS.

DESSINÉ DESIGNER	M.JACQUES
DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET
DATE	2019-02-12
INGÉNIEUR ENGINEER	
DATE	
ÉCHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL SCHEMATIC DIAGRAM 120VAC

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036	ELD-0007-AUT-VWT	JOME01	2 DE 9	4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



4	AS COMMISSIONNING	2019-05-17	SD				
3	AS BUILT	2019-05-03	SD				
2	FOR FAB	2019-04-02	RM				
1	FOR APPROVAL	2019-03-18	RM				
REV.	DESCRIPTION	DATE	REV.	VERIC'HK	APPR.	ECN	

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE: ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND MAY CONTAIN CONFIDENTIAL, PROPRIETARY AND/OR OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION. IT SUBMITTED, AND IN NO EVENT LICENCE IS GRANTED OR IMPLIED TO USE THIS DOCUMENT OR THE INFORMATION IT CONTAINS. CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, RIGHTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THIS DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PURPOSE RELATE TO THE OTHER OUR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE CONSTRUED AS GRANTING ANY LICENCE OR RIGHT OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE : L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET PEUT RENFERMER LES LOIS DE PROPRIÉTÉ INTELLECTUELLE, CONFIDENTIELLES OU D'AUTRES NATURES. LES CONCEPTS ET L'INFORMATION CONTENUS DANS CE DOCUMENT SONT DÉPOSÉS EN CONFIANCE. CE DOCUMENT ET L'INFORMATION QU'IL CONTIENT DOIVENT ÊTRE UTILISÉS UNIQUEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EN POSSESSION, LE CAS ÉCHÉANT, ET AUCUNE LICENCE OU DROIT N'EST ACCORDÉ OU IMPLICITE EN CE QUI CONCERNE L'UTILISATION DE CE DOCUMENT OU DE L'INFORMATION QU'IL CONTIENT. LES RENSEIGNEMENTS CONFIDENTIELS ET PRIVILÉGIÉS SONT LA PROPRIÉTÉ DE V.W.T. ET NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RÉGIS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT ÉCRIT DE V.W.T. V.W.T. N'ASSUME AUCUNE RESPONSABILITÉ OU RESPONSABILITÉ POUR L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS ET L'INFORMATION QU'IL CONTIENT À DES FINS AUTRES QUE LES FINS PRÉCISES LIÉES À CE DOCUMENT. AUCUN DOCUMENT NI AUCUNE CONCEPTION NE DOIVENT ÊTRE INTERPRÉTÉS COMME ACCORDANT UNE LICENCE OU UN DROIT DE V.W.T. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À L'ÉGARD DE CES CONDITIONS.

DESSINÉ DESIGNER	M.JACQUES
DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET
DATE	2019-02-12
INGÉNIEUR ENGINEER	
DATE	
ÉCHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL SCHEMATIC DIAGRAM 120VAC

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0007-AUT-VWT	JOME01	3 DE 9		4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



LR 60892

REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-03	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED BY THE SUBMISSION OF THIS DOCUMENT. THIS DOCUMENT CONTAINS CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WHETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE EXCEPT WITH THE WRITTEN CONSENT OF V.W.T. ASSUMING NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THIS DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT THAT RELATES TO THE INTENDED PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED FOR ANY PURPOSE THAT MAY BE INJURIOUS TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS ET INFORMATIONS CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET APPARTIENNENT À V.W.T. CE DOCUMENT EST SOUMIS EN CONFIANCE. CE DOCUMENT ET LES RENSEIGNEMENTS QU'IL CONTIENT NE DOIVENT ÊTRE UTILISÉS UNIQUEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST OCTROYÉE DE PAR LA SOUMISSION DE CE DOCUMENT. CE DOCUMENT CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET PRIVILÉGIÉS DE V.W.T. ET ILS NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RÉDIGÉS OU UTILISÉS EN TOUTE OU EN PARTIE À QUELQUE FIN QUE CE SOIT SANS LE CONSENTEMENT ÉCRIT DE V.W.T. EN PRENANT EN CHARGE AUCUNE RESPONSABILITÉ OU RESPONSABILITÉ QUANT À L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS ET INFORMATIONS QU'IL CONTIENT À DES FINS AUTRES QUE CELLES QUI SE RAPPORTENT AU PROJET SPÉCIFIQUE QUI SE RAPPORTE À L'OBJET PRÉVU DE CE DOCUMENT. EN AUCUN CAS CE DOCUMENT NE DOIT ÊTRE UTILISÉ À DES FINS QUI PEUVENT NUIRE AUX INTÉRÊTS DE V.W.T. TOUS LES DROITS D'AUTEUR, BREVET ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT SIGNIFIE QUE LE DESTINATAIRE SE CONFORME AUX MODALITÉS CI-DESSUS.

DESSINÉ DESIGNER	M.JACQUES	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	2019-02-12
INGÉNIEUR ENGINEER		
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL SCHEMATIC DIAGRAM 24VDC


CLIENT: IQALUIT WWTP

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0007-AUT-VWT	JOME01	4 DE 9		4

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-03	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			
REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR.	ECN

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE: ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED TO ANY OTHER USE. THIS DOCUMENT MUST NOT BE COPIED IN WHOLE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WIBITTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PRIOR WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT TO WHICH IT RELATES TO THE OTHER EXPRESS PURPOSES OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED FOR ANY PURPOSE DETRIMENTAL TO THE INTERESTS OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE: L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET DE PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS ET L'INFORMATION CONTENUS DANS CE DOCUMENT SONT LA PROPRIÉTÉ DE V.W.T. ET SONT SOUMIS EN CONFIDENCE. CE DOCUMENT ET L'INFORMATION QU'IL CONTIENT NE DOIVENT ÊTRE UTILISÉS EXCLUSIVEMENT QUE POUR L'OBJET POUR LEQUEL LE DOCUMENT EST EXPRESSÉMENT SOUMIS ET AUCUNE LICENCE IMPLICITE N'EST OCTROYÉE DE TOUTE AUTRE UTILISATION. LA DIVULGATION, LA REPRODUCTION, LE PRÊT, LA TRANSMISSION OU L'UTILISATION, EN TOUT OU EN PARTIE, DE CES RENSEIGNEMENTS CONFIDENTIELS ET PRIVILÉGIÉS À TOUT AUTRE FIN QUE CELLE POUR LAQUELLE REPRÉSENTE LE PRÉSENT DOCUMENT SANS L'AUTORISATION ÉCRITE PRÉALABLE DE V.W.T. EST STRICTEMENT INTERDITE. V.W.T. DÉCLINE TOUTE RESPONSABILITÉ ET TOUTE RESPONSABILITÉ QUANT À L'UTILISATION DE CE DOCUMENT OU DES IDÉES ET CONCEPTS QU'IL CONTIENT À DES FINS AUTRES QUE CELLES POUR LESQUELLES IL A ÉTÉ SOUMIS. AUCUNE UTILISATION DE CE DOCUMENT NE DOIT ÊTRE FAITE DE MANIÈRE À PORTER PRÉJUDICE AUX INTÉRÊTS DE V.W.T. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À L'ÉGARD DE CES CONDITIONS.

DESSINÉ DESIGNER	M.JACQUES	DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE	2019-02-12
INGÉNIEUR ENGINEER		DATE	
ÉCHELLE/SCALE:			

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL SCHEMATIC DIAGRAM 24VDC

CLIENT: IQALUIT WWTP


VEOLIA


VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036	ELD-0007-AUT-VWT	JOME01	5 DE 9	4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE







RACK 0

SLOT 01, INPUTS, 1769-L16ER-BB1B, SEE CONNECTING DETAIL DRAWING 5000218036-ELD-0007-AUT-VWT-07

SLOT 01, OUTPUTS, 1769-L16ER-BB1B, SEE CONNECTING DETAIL DRAWING 5000218036-ELD-0007-AUT-VWT-08

SLOT 02, 1734-IE8C, SEE CONNECTING DETAIL DRAWING 5000218036-ELD-0007-AUT-VWT-09

REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR.	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-03	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE: ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO "I.S.T." AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION IS SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED TO USE THE DESIGN CONCEPTS OR INFORMATION. THIS DOCUMENT IS CONFIDENTIAL AND PRIVILEGED INFORMATION OF "I.S.T." AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, RIGHTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE WRITTEN CONSENT OF "I.S.T." "I.S.T." ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT TO WHICH IT RELATES TO THE OTHER FOR PURPOSES OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY ANY PARTY FOR ANY PURPOSE IN VIOLATION OF U.S.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE : L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES LOIS RELATIVES À LA PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET CONCEPTS ET RENSEIGNEMENTS CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET SONT SOUMIS À "I.S.T." À TITRE CONFIDENTIEL. CE DOCUMENT ET LES RENSEIGNEMENTS QU'IL CONTIENT NE DOIVENT ÊTRE UTILISÉS EXCLUSIVEMENT QUE POUR L'OBJET POUR LEQUEL LE DOCUMENT EST EN POSSESSION ET NE DOIVENT FAIRE L'OBJET D'AUCUNE DIVULGATION, REPRODUCTION, LOCATION, DROIT OU UTILISATION, EN TOUT OU EN PARTIE, SANS LE CONSENTEMENT ÉCRIT DE "I.S.T." "I.S.T." N'ASSUME AUCUNE RESPONSABILITÉ OU OBLIGATION POUR L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS ET RENSEIGNEMENTS QUI Y SONT CONTENUS POUR DES FINS AUTRES QUE CELLES QUI SE RAPPORTENT PRÉCISÉMENT AU PROJET AUQUEL IL SE RAPPORTE. TOUTE UTILISATION DE CE DOCUMENT OU DES CONCEPTS ET RENSEIGNEMENTS QUI Y SONT CONTENUS À DES FINS CONTRAIRES À LA LOI AMÉRICAINE EST STRICTEMENT INTERDITE. TOUS LES DROITS D'AUTEUR, BREVET, MARQUE DE COMMERCE ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À CES TERMES ET CONDITIONS.

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL ETHERNET NETWORK AND PLC

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0007-AUT-VWT	JOME01	6 DE 9		4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-03	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE: ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND MAY INCORPORATE CONFIDENTIAL AND PROPRIETARY INFORMATION OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT, AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION IS SUBMITTED. AND NO DUPLICATE LICENCE IS GRANTED OR IMPLIED. THIS DOCUMENT AND THE INFORMATION IT CONTAINS IS CONFIDENTIAL AND PRIVILEGED INFORMATION OF VWT, AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, RIBBITTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS SUBMITTED. VWT ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED OR EXPRESSED HEREIN FOR ANY PURPOSE OTHER THAN THAT WHICH RELATES TO THE INTENDED PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED OR EXPRESSED HEREIN BE USED FOR THE BENEFIT OF A THIRD PARTY. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE : L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET PEUT INCORPORER DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS ET D'AUTRES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES IDÉES ET DONNÉES CONTENUES DANS CE DOCUMENT SONT LA PROPRIÉTÉ DE VWT ET SONT SOUMISES EN CONFIDENCE. CE DOCUMENT ET LES RENSEIGNEMENTS QU'IL CONTIENT DOIVENT ÊTRE UTILISÉS EXCLUSIVEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST SOUMIS ET NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RIBBITÉS OU UTILISÉS EN TOUT OU EN PARTIE À D'AUTRES FINS SANS AUTORISATION ÉCRITE PRÉALABLE. AUCUNE LICENCE N'EST CONCÉDÉE OU IMPLIQUÉE. VWT N'ASSUME AUCUNE RESPONSABILITÉ OU RESPONSABILITÉ POUR L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS ET RENSEIGNEMENTS QU'IL CONTIENT OU EXPOSE À DES FINS AUTRES QUE CELLES QUI SE RAPPORTENT À L'OBJET PRÉVU DE CE DOCUMENT. CE DOCUMENT NE PEUT EN AUCUN CAS ÊTRE UTILISÉ AU PROFIT D'UNE TIERCE PARTIE. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE UNE ENTENTE À CES CONDITIONS ET MODALITÉS.

DESSINÉ DESIGNER	M.JACQUES	DATE 2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET	DATE 2019-02-12
INGÉNIEUR ENGINEER		DATE
ÉCHELLE/SCALE:		

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL
RACK 00 SLOT 01 INPUTS, 1769-L18ER-BB1B

CLIENT: IQALUIT WWTP


VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0007-AUT-VWT	JOME01	7 DE 9		4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



4	AS COMMISSIONNING	2019-05-17	SD				
3	AS BUILT	2019-05-03	SD				
2	FOR FAB	2019-04-02	RM				
1	FOR APPROVAL	2019-03-18	RM				
REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR.	ECN	

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT, AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION IT SUBMITTED. AND NO IMPLICIT LICENCE IS GRANTED TO USE THE DESIGN CONCEPTS AND INFORMATION. THIS DOCUMENT IS CONFIDENTIAL AND PRIVILEGED INFORMATION OF VWT, AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WHETTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE OTHER THAN THE PURPOSE FOR WHICH IT IS T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATE TO THE ATTACH OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY ANY PERSON FOR ANY PURPOSE OTHER THAN THE INTENDED OR PURPOSE OF THIS DOCUMENT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES DESSINS CONCEPTUELS ET RENSEIGNEMENTS CONTENUS DANS CE DOCUMENT SONT LA PROPRIÉTÉ DE VWT ET SONT SOUMIS EN CONFIDENCE. CE DOCUMENT ET LES RENSEIGNEMENTS QU'IL CONTIENT DOIVENT ÊTRE UTILISÉS UNIQUEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST PRÉSENTÉ. AUCUNE LICENCE IMPLICITE N'EST ACCORDÉE POUR UTILISER LES DESSINS CONCEPTUELS ET RENSEIGNEMENTS. CE DOCUMENT CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET PRIVILÉGIÉS QUI NE DOIVENT PAS ÊTRE DIVULGUÉS, REPRODUITS, PRÊTÉS, RÉDIGÉS OU UTILISÉS EN TOUTE OU EN PARTIE À DES FINS AUTRES QUE CELLES POUR LESQUELLES IL EST PRÉVU. V.W.T. DÉCLINE TOUTE RESPONSABILITÉ OU RESPONSABILITÉ QUANT À L'UTILISATION DE CE DOCUMENT AINSI QUE DES DESSINS CONCEPTUELS ET L'INFORMATION QUI Y SONT CONTENUS À DES FINS AUTRES QUE CELLES PRÉVUES DANS CE DOCUMENT. EN AUCUN CAS CE DOCUMENT NE DOIT ÊTRE UTILISÉ PAR QUICONQUE À DES FINS AUTRES QUE CELLES PRÉVUES DANS CE DOCUMENT. TOUS LES DROITS D'AUTEUR, BREVETS ET AUTRES DROITS DE PROPRIÉTÉ INTELLECTUELLE SONT RÉSERVÉS. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT IMPLIQUE L'ACCEPTATION DE CES CONDITIONS.

DESSINÉ DESIGNER	M.JACQUES
DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET
DATE	2019-02-12
INGÉNIEUR ENGINEER	
DATE	
ÉCHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL
RACK 00 SLOT 01 OUTPUTS, 1769-L18ER-BB1B


CLIENT: IQALUIT WWTP

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036-ELD-0007-AUT-VWT	JOME01	8 DE 9		4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE



REV.	DESCRIPTION	DATE	REV.	VERIF/CHK	APPR.	ECN
4	AS COMMISSIONNING	2019-05-17	SD			
3	AS BUILT	2019-05-03	SD			
2	FOR FAB	2019-04-02	RM			
1	FOR APPROVAL	2019-03-18	RM			

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS IN POSSESSION IT SUBMITTED. AND IN NO IMPLICIT LICENCE IS GRANTED TO USE THE DESIGN CONCEPTS OR INFORMATION. THIS DOCUMENT IS CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, WEBITTED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE PRIOR WRITTEN CONSENT OF V.W.T. V.W.T ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE INTENDED PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE CONSTRUED AS GRANTING ANY LICENSE OR RIGHT OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

AVIS DE CONFIDENTIALITÉ ET DE PROPRIÉTÉ INTELLECTUELLE
L'INFORMATION CONTENUE DANS CE DOCUMENT EST LA PROPRIÉTÉ EXCLUSIVE DE VEOLIA WATER TECHNOLOGIES CANADA INC. ET CONTIENT DES RENSEIGNEMENTS CONFIDENTIELS ET EXCLUSIFS AINSI QUE D'AUTRES LOIS SUR LA PROPRIÉTÉ INTELLECTUELLE. LES DESSINS, CONCEPTS ET INFORMATIONS CONTENUS DANS CE DOCUMENT SONT CONFIDENTIELS ET SOUMIS EN CONFIDENCE. CE DOCUMENT ET LES RENSEIGNEMENTS QU'IL CONTIENT DOIVENT ÊTRE UTILISÉS EXCLUSIVEMENT AUX FINS POUR LESQUELLES CE DOCUMENT EST SOUMIS. AUCUNE LICENCE OU DROIT N'EST ACCORDÉ EN CE QUI CONCERNE LES CONCEPTS OU RENSEIGNEMENTS DE CONCEPTION. V.W.T. N'ASSUME AUCUNE RESPONSABILITÉ OU RESPONSABILITÉ POUR L'UTILISATION DE CE DOCUMENT OU DES CONCEPTS DE CONCEPTION ET RENSEIGNEMENTS CONTENUS DANS LES PRÉSENTES À DES FINS AUTRES QUE LES FINS PRÉCISES RELATIVES AU PROJET DÉCRIT DANS CE DOCUMENT. EN AUCUN CAS CE DOCUMENT NE SAURAIT ÊTRE INTERPRÉTÉ COMME ACCORDANT UNE LICENCE OU UN DROIT DE V.W.T. QUELCONQUE EN MATIÈRE DE DROIT D'AUTEUR, DE BREVET OU D'AUTRE DROIT DE PROPRIÉTÉ INTELLECTUELLE. L'ACCEPTATION DE LA LIVRAISON DE CE DOCUMENT CONSTITUE L'ACCEPTATION DE CES CONDITIONS.

DESSINÉ DESIGNER	M.JACQUES
DATE	2019-02-12
VÉRIFIÉ CHECKER	S.DUQUET
DATE	2019-02-12
INGÉNIEUR ENGINEER	
DATE	
ÉCHELLE/SCALE:	

TITRE/TITLE: HYDRAPOL 500 CONTROL PANEL
RACK 0, SLOT 02, 1734-IE8C

CLIENT: IQALUIT WWTP

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJET/PROJECT	DESSIN/DRAWING No	INTERNE/INTERNAL	FEUILLET/SHEET	REV.
5000218036	ELD-0007-AUT-VWT	JOME01	9 DE 9	4

LR 60892

STD: "D" 22x34 | EBI ELECTRIC - 58011-P02 | BAR = 1" À L'ÉCHELLE D'IMPRESSION/BAR = 1" AT PLOT SCALE

WWTP UPGRADE
CITY OF IQALUIT
CONTROL JUNCTION BOX
JB-003 DAF polymer dosing skid
PROJECT: 5000218036

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-02-07	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT IN WHOLE OR IN PART IN CONTEXTS OR FOR PURPOSES NOT ENVISIONED BY V.W.T. AND ANY SUCH USE OR REUSE WILL BE AT THE USER'S OR REUSER'S SOLE RISK AND WITHOUT LIABILITY OR LEGAL EXPOSURE TO V.W.T. NO EXPRESS OR IMPLIED WARRANTIES ARE GIVEN WITH REGARD TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: JB-003 CONTROL JUNCTION BOX TITLE PAGE

CLIENT: WWTP UPGRADE CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc. Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0004-AU-VWT	–	01 OF 05	3


STD: "B" 11x17 | REF: A6798B | BAR = 1" AT PLOT SCALE

Mar 26, 2019 11:04:58 – G:\Projets A67XX\A6798A @ A6798B – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-003\REV 2 – Copy\5000218036-EPL-0004-AU-VWT-001.dwg – zhu

DRAWING LIST

DESCRIPTION	DRAWING NUMBER
CONTROL JUNCTION BOX JB-003	
TITLE PAGE	5000218036-EPL-0004-AU-VWT-001
LEGEND & DRAWING LIST	5000218036-EPL-0004-AU-VWT-002
EXTERNAL & INTERNAL LAYOUT	5000218036-EPL-0004-AU-VWT-003
BILL OF MATERIAL	5000218036-EPL-0004-AU-VWT-004
TERMINAL LAYOUT	5000218036-EPL-0004-AU-VWT-005
FIELD WIRING	5000218036-EID-0004-AU-VWT-001
FIELD WIRING	5000218036-EID-0004-AU-VWT-002

LEGEND



WIRE COLOR CODE	
MINIMAL 18AWG GAUGE	
POWER 120VAC	BLACK
CONTROL 120VAC	RED
NEUTRAL	WHITE
24VDC	BLUE
0VDC	BLUE/WHITE
DRY CONTRACT	YELLOW, 14AWG
NON-ISOLATED GROUND	GREEN
ISOLATED GROUND	GREEN/YELLOW
TWISTED PAIR	(+) BLACK & (-) WHITE

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-02-07	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERRED, NOR IS THE RECIPIENT GRANTED ANY LICENSE, EXPRESS OR IMPLIED, EXCEPT AS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR OF ANY PORTION THEREOF IN CONNECTION WITH ANY PROJECT NOTIFIED TO V.W.T. OTHER THAN THE PROJECT OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE: JB-003 CONTROL JUNCTION BOX LEGEND & DRAWING LIST

CLIENT: WWTP UPGRADE CITY OF IQALUIT


VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230


PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL	0004-AU-VWT	–	02 OF 05	3

Mar 26, 2019 11:05:00 - G:\Projets A67XX\A6798A @ A6798B - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESIN\000-DRAWINGS\JB-003\REV 2 - Copy\5000218036-EPL-0004-AU-VWT-002.dwg - zhu

BAR = 1" AT PLOT SCALE
REF: A6798B
STD: "B" 11x17

ENCLOSURE NEMA 4X–FIBERGLASS / 17,87H'' X 16W'' X 8D'' (PJ16148)
cUL APPROVAL





REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019–03–26	HZ	RA	–	–
2	FOR FABRICATION	2019–03–15	MR	RA	–	–
1	FOR APPROVAL	2019–02–07	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. IT THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T.. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT BY ANY OF ITS RECIPIENTS FOR PURPOSES OTHER THAN THOSE FOR WHICH IT WAS SUBMITTED OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE: JB–003
CONTROL JUNCTION BOX
EXTERNAL & INTERNAL LAYOUT

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230


PROJECT DRAWING	INTERNAL	SHEET	REV
500021803 6–EPL – 0004–AU–VWT	–	03 OF 05	3


STD: "B" 11x17 | REF: A6798B | BAR = 1" AT PLOT SCALE


Mar 26, 2019 11:05:01 – G:\Projets A67xx\A6798A @ A6798B – VEOLIA – 500021803 6 Iqaluit WWTP Upgrade\DOC\DESSIN\000–DRAWINGS\JB–003\REV 2 – Copy\500021803 6–EPL–0004–AU–VWT–003.dwg – zhu

Mar 26, 2019 11:05:03 - G:\Projets A67xx\A6798A @ A6798B - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-003\REV 2 - Copy\5000218036-EPL-0004-AU-VW1-004.dwg - zhu

BAR = 1" AT PLOT SCALE
REF: A6798B
STD: "B" 11x17







TERMINAL DESCRIPTION
A) ID(WAD8)
B) WDU6
C) WDU4
D) WDK2.5
E) DLD2.5
F) FUSE WSI 4/2
G) FUSE WSI 4
H) FUSE KDKS 1/EN4
J) WTR 2.5
K) WDU 2.5

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	-	-
2	FOR FABRICATION	2019-03-15	MR	RA	-	-
1	FOR APPROVAL	2019-02-07	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, OR OF THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN, IN A MANNER THAT DOES NOT RELATE DIRECTLY AND EXCLUSIVELY TO THE PURPOSE FOR WHICH IT WAS DELIVERED. IN PARTICULAR, AND WITHOUT RESTRICTING THE GENERALITY OF THE FOREGOING, IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
-	-
CHECKER	DATE
-	-
ENGINEER	DATE
-	-
SCALE:	N/A

TITLE: JB-003
CONTROL JUNCTION BOX
TERMINAL LAYOUT

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EPL - 0004-AU-VWT	-	04 OF 05	3

ITEM	DESCRIPTION	PART NUMBER	MANUF.	QTY	BY
1	NEMA 4X ENCLOSURE, DIM 17,87H'' X 16W'' X 8D'', FIBERGLASS REINFORCED POLYESTER, C/W PAN 14R1513	PJ16148	HAMMOND	1	ENV
2	TERMINAL 600VAC/DC, 20A WDU 2.5 C/W END PLATE 1050000000	1020000000	WEIDMULLER	A/R	ENV
3	TERMINAL 600VAC/DC, 30A WDU 4 C/W END PLATE 1050000000	1020100000	WEIDMULLER	A/R	ENV
4	TERMINAL 600VAC/DC, 50A WDU 6 C/W END PLATE 1050000000 OR SEPERATOR 1050100000	1020200000	WEIDMULLER	A/R	ENV
5	KNIFE TERMINAL 300VAC/DC, 10A, WTR 2.5 C/W END PLATE 1050000000	1855610000	WEIDMULLER	A/R	ENV
6	TERMINAL 2 LEVEL 300VAC/DC, 10A, WDK 2.5 C/W END PLATE 1059100000	1021500000	WEIDMULLER	A/R	ENV
7	TERMINAL 3 LEVEL 300VAC/DC, 10A, DLD 2.5 C/W END PLATE 1784210000	1784180000	WEIDMULLER	A/R	ENV
8	FUSE TERMINAL ¼ X 1¼, 300VAC/DC, 15A, WSI 4/2 C/W END PLATE 1880450000	1880430000	WEIDMULLER	A/R	ENV
9	FUSE TERMINAL 5 X 20mm, 300VAC/DC, 15A, WSI 4	1886580000	WEIDMULLER	A/R	ENV
10	FUSE TERMINAL 2 LEVEL 5 X 20mm, 300VAC/DC, 10A, KDKS 1/EN4 C/W END PLATE 9503330000	9503350000	WEIDMULLER	A/R	ENV
11	FUSE TERMINAL 2 LEVEL ¼ X 1¼, 300VAC/DC, 10A, KDKS 1/35DB C/W END PLATE 9532470000	9532440000	WEIDMULLER	A/R	ENV
12	END STOPPER WEW 35/2	1061200000	WEIDMULLER	A/R	ENV
13	COPPER GROUND BAR, #4-14	4C-190	NSI-INDUSTRIES	A/R	ENV
14	COPPER GROUND LUG, 600VAC, #6-14, STR	CB35-36-LY	PANDUIT	A/R	ENV

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-02-07	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, OR OF ANY PORTION THEREOF, EITHER AS REGARDS THE INFORMATION OR ANY OPINION OR RECOMMENDATION IN IT, MANNER THAT COSTS INCURRED RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE: JB-003
CONTROL JUNCTION BOX
BILL OF MATERIAL


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0004-AU-VWT	–	05 OF 05	3

STD: "B" 11x17 | REF: A6798B | BAR = 1" AT PLOT SCALE

Mar 26, 2019 11:05:03 – G:\Projets A67XX\A6798A @ A6798B – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-003\REV 2 – Copy\5000218036-EPL-0004-AU-VW1-003.dwg – zhu



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-02-07	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT IN WHOLE OR IN PART IN ANY OTHER CONTEXT OR FOR ANY PURPOSE OTHER THAN THE SPECIFIC PROJECT FOR WHICH IT WAS PREPARED BY V.W.T. IN A MANNER THAT COSTS INCURRED RELATIVE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: JB-003
CONTROL JUNCTION BOX
FIELD WIRING


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0004-AU-VWT	–	01 OF 02	3

STD: "B" 11x17 | REF: A6798B | BAR = 1" AT PLOT SCALE

Mar 26, 2019 11:05:06 – G:\Projets A67xx\A6798A @ A6798B – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-003\REV 2 – Copy\5000218036-EID-0004-AU-VWT-001.dwg – zhu



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-02-07	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT IN WHOLE OR IN PART IN ANY OTHER PROJECT OR FOR ANY PURPOSE OTHER THAN FOR WHICH IT IS SPECIFICALLY PREPARED OR ADAPTED BY V.W.T. IN A MANNER THAT DOES NOT RELATE DIRECTLY TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE: JB-003
CONTROL JUNCTION BOX
FIELD WIRING

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0004-AU-VWT	–	02 OF 02	3

STD: "B" 11x17 | REF: A6798B | BAR = 1" AT PLOT SCALE

Mar 26, 2019 11:05:07 – G:\Projets A67xX\A6798A @ A6798B – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-003\REV 2 – Copy\5000218036-EID-0004-AU-VWT-002.dwg – zhu

WWTP UPGRADE
CITY OF IQALUIT
CONTROL JUNCTION BOX
JB-004 BFP polymer dosing skid
PROJECT: 5000218036

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	-	-
2	FOR FABRICATION	2019-03-15	MR	RA	-	-
1	FOR APPROVAL	2019-02-07	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT IN WHOLE OR IN PART IN ANY OTHER PROJECT OR FOR ANY PURPOSE OTHER THAN THE PROJECT FOR WHICH IT IS SUBMITTED. IN A MANNER THAT GIVES RISE HEREBY TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	-	-
CHECKER	-	-
ENGINEER	-	-
SCALE:	N/A	

TITLE: JB-004 CONTROL JUNCTION BOX TITLE PAGE

CLIENT: WWTP UPGRADE CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL	- 0005-AU-VWT	-	01 OF 05	3

Mar 26, 2019 11:15:24 - G:\Projets A67XX\A6798A @ A6798B - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-004\REV 3 AS BUILT\5000218036-EPL-0005-AU-VWT-001.dwg - zhu

BAR = 1" AT PLOT SCALE


REF: A6798B

STD: "B" 11x17

DRAWING LIST

DESCRIPTION	DRAWING NUMBER
CONTROL JUNCTION BOX JB-004	
TITLE PAGE	5000218036-EPL-0005-AU-VWT-001
LEGEND & DRAWING LIST	5000218036-EPL-0005-AU-VWT-002
EXTERNAL & INTERNAL LAYOUT	5000218036-EPL-0005-AU-VWT-003
BILL OF MATERIAL	5000218036-EPL-0005-AU-VWT-004
TERMINAL LAYOUT	5000218036-EPL-0005-AU-VWT-005
FIELD WIRING	5000218036-EID-0005-AU-VWT-001
FIELD WIRING	5000218036-EID-0005-AU-VWT-002

LEGEND



WIRE COLOR CODE	
MINIMAL 18AWG GAUGE	
POWER 120VAC	BLACK
CONTROL 120VAC	RED
NEUTRAL	WHITE
24VDC	BLUE
0VDC	BLUE/WHITE
DRY CONTRACT	YELLOW, 14AWG
NON-ISOLATED GROUND	GREEN
ISOLATED GROUND	GREEN/YELLOW
TWISTED PAIR	(+) BLACK & (-) WHITE

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	-	-
2	FOR FABRICATION	2019-03-15	MR	RA	-	-
1	FOR APPROVAL	2019-02-07	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERRED, NOR IS THE RECEIVER GIVEN ANY RIGHT TO USE THEM, EXCEPT AS MAY BE EXPRESSLY AGREED IN WRITING. THEY ARE EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, OR PORTIONS THEREOF, BY ANY PARTY OTHER THAN THE PERSON TO WHOM IT IS DELIVERED OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE -
CHECKER	DATE -
ENGINEER	DATE -
SCALE:	N/A

TITLE: JB-004 CONTROL JUNCTION BOX LEGEND & DRAWING LIST

CLIENT: WWTP UPGRADE CITY OF IQALUIT


VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230


PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL	0005-AU-VWT	-	02 OF 05	3

Mar 26, 2019 11:15:26 - G:\Projets A67XX\A6798A @ A6798B - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-004\REV 3 AS BUILT\5000218036-EPL-0005-AU-VWT-002.dwg - zhu

BAR = 1" AT PLOT SCALE
REF: A6798B
STD: "B" 11x17

ENCLOSURE NEMA 4X–FIBERGLASS / 17,87H'' X 16W'' X 8D'' (PJ16148)
cUL APPROVAL





REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019–03–26	HZ	RA	–	–
2	FOR FABRICATION	2019–03–15	MR	RA	–	–
1	FOR APPROVAL	2019–02–07	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. IT THEY ARE NOT TRANSFERABLE. THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T.. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, OR OF THE DESIGN CONCEPTS OR INFORMATION CONTAINED HEREIN, FOR PURPOSES OTHER THAN THOSE SPECIFICALLY RELATED TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OF THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE: JB–004
CONTROL JUNCTION BOX
EXTERNAL & INTERNAL LAYOUT

CLIENT: WWTP UPGRADE
CITY OF IQALUIT


VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc. Canada. Tel: (514) 334-7230


PROJECT DRAWING	INTERNAL	SHEET	REV
500021803G–EPL – 0005–AU–VWT	–	03 OF 05	3


Mar 26, 2019 11:15:27 – G:\Projets A67xx\A6798A @ A6798B – VEOLIA – 500021803G Iqaluit WWTP Upgrade\DOC\DESSIN\000–DRAWINGS\JB–004\REV 3
AS BUILT\500021803G–EPL–0005–AU–VWT–003.dwg – zhu
BAR = 1" AT PLOT SCALE
REF: A6798B
STD: "B" 11x17

Mar 26, 2019 11:15:29 - G:\Projets A67XX\A6798A @ A6798B - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-004\REV 3
AS BUILT\5000218036-EPL-0005-AU-VWT-004.dwg - zhu

BAR = 1" AT PLOT SCALE
REF: A6798B
STD: "B" 11x17







TERMINAL DESCRIPTION
A) ID(WAD8)
B) WDU6
C) WDU4
D) WDK2.5
E) DLD2.5
F) FUSE WSI 4/2
G) FUSE WSI 4
H) FUSE KDKS 1/EN4
J) WTR 2.5
K) WDU 2.5

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	-	-
2	FOR FABRICATION	2019-03-15	MR	RA	-	-
1	FOR APPROVAL	2019-02-07	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. IT THEY ARE NOT TRANSFERABLE. THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. UNLESS OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT, THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, OR OF THE DESIGN CONCEPTS OR INFORMATION CONTAINED IN IT, FOR ANY PURPOSE OR IN A MANNER THAT IS NOT LIMITED HEREBY TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
-	-
CHECKER	DATE
-	-
ENGINEER	DATE
-	-
SCALE:	N/A

TITLE: JB-004
CONTROL JUNCTION BOX
TERMINAL LAYOUT

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0005-AU-VWT	-	04 OF 05	3

ITEM	DESCRIPTION	PART NUMBER	MANUF.	QTY	BY
1	NEMA 4X ENCLOSURE, DIM 17,87H'' X 16W'' X 8D'', FIBERGLASS REINFORCED POLYESTER, C/W PAN 14R1513	PJ16148	HAMMOND	1	ENV
2	TERMINAL 600VAC/DC, 20A WDU 2.5 C/W END PLATE 1050000000	1020000000	WEIDMULLER	A/R	ENV
3	TERMINAL 600VAC/DC, 30A WDU 4 C/W END PLATE 1050000000	1020100000	WEIDMULLER	A/R	ENV
4	TERMINAL 600VAC/DC, 50A WDU 6 C/W END PLATE 1050000000 OR SEPERATOR 1050100000	1020200000	WEIDMULLER	A/R	ENV
5	KNIFE TERMINAL 300VAC/DC, 10A, WTR 2.5 C/W END PLATE 1050000000	1855610000	WEIDMULLER	A/R	ENV
6	TERMINAL 2 LEVEL 300VAC/DC, 10A, WDK 2.5 C/W END PLATE 1059100000	1021500000	WEIDMULLER	A/R	ENV
7	TERMINAL 3 LEVEL 300VAC/DC, 10A, DLD 2.5 C/W END PLATE 1784210000	1784180000	WEIDMULLER	A/R	ENV
8	FUSE TERMINAL ¼ X 1¼, 300VAC/DC, 15A, WSI 4/2 C/W END PLATE 1880450000	1880430000	WEIDMULLER	A/R	ENV
9	FUSE TERMINAL 5 X 20mm, 300VAC/DC, 15A, WSI 4	1886580000	WEIDMULLER	A/R	ENV
10	FUSE TERMINAL 2 LEVEL 5 X 20mm, 300VAC/DC, 10A, KDKS 1/EN4 C/W END PLATE 9503330000	9503350000	WEIDMULLER	A/R	ENV
11	FUSE TERMINAL 2 LEVEL ¼ X 1¼, 300VAC/DC, 10A, KDKS 1/35DB C/W END PLATE 9532470000	9532440000	WEIDMULLER	A/R	ENV
12	END STOPPER WEW 35/2	1061200000	WEIDMULLER	A/R	ENV
13	COPPER GROUND BAR, #4-14	4C-190	NSI-INDUSTRIES	A/R	ENV
14	COPPER GROUND LUG, 600VAC, #6-14, STR	CB35-36-LY	PANDUIT	A/R	ENV

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-02-07	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED IN WHOLE OR IN PART FOR ANY PURPOSE EXCEPT AS IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, OR OF ANY INFORMATION, DESIGN OR CONCEPT CONTAINED THEREIN, FOR PURPOSES OTHER THAN THOSE EXPRESSLY SUBMITTED. WITH RESPECT TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: JB-004
CONTROL JUNCTION BOX
BILL OF MATERIAL


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
500021803G-EPL – 0005-AU-VWT	–	05 OF 05	3

BAR = 1" AT PLOT SCALE
REF: A6798B
STD: "B" 11x17

Mar 26, 2019 11:15:29 - G:\Projets A67xx\A6798A @ A6798B - VEOLIA - 500021803G Iqaluit WWTP Upgrade\DOC\DESIN\000-DRAWINGS\JB-004\REV 3
AS BUILT\500021803G-EPL-0005-AU-VWT-005.dwg - zhu



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-02-07	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, IN WHOLE OR IN PART, IN CONTRAVENTION OF THE CONDITIONS SET FORTH ABOVE. SHOULD SUCH USE OF, OR RELIANCE UPON, THIS DOCUMENT GIVE RISE TO ANY CLAIM, V.W.T. SHALL BE HELD HARMLESS FOR ANY AND ALL DAMAGES, INCLUDING BUT NOT LIMITED TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE: JB-004
CONTROL JUNCTION BOX
FIELD WIRING


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0005-AU-VWT	–	01 OF 02	3

STD: "B" 11x17
REF: A6798B
BAR = 1" AT PLOT SCALE

Mar 26, 2019 11:15:31 – G:\Projets A67XX\A6798A @ A6798B – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-004\REV 3 AS BUILT\5000218036-EID-0005-AU-VWT-001.dwg – zhu



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
3	AS BUILT	2019-03-26	HZ	RA	–	–
2	FOR FABRICATION	2019-03-15	MR	RA	–	–
1	FOR APPROVAL	2019-02-07	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.B.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.B.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.B.T. V.B.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT IN WHOLE OR IN PART IN CONTEXTS OR FOR PURPOSES NOT ORIGINALLY INTENDED BY V.B.T. V.B.T. DOES NOT GUARANTEE IN A MANNER THAT GOES BEYOND HEGARD TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.B.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE: JB-004 CONTROL JUNCTION BOX FIELD WIRING

CLIENT: WWTP UPGRADE CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EID – 0005-AU-VWT	–	02 OF 02	3

STD: "B" 11x17 | REF: A6798B | BAR = 1" AT PLOT SCALE

Mar 26, 2019 11:15:33 – G:\Projets A67XX\A6798A @ A6798B – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-004\REV 3 AS BUILT\5000218036-EID-0005-AU-VWT-002.dwg – zhu

Date: Dec 06, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Déc 06, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-12R1 - SU-ELE-012R1
PO-Nedco

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [x] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 24 17 Panelboards-Panel 4A CCN-014

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-012R1

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-12-06
BY Konrad Goluch

Bus to be copper. Min S.C Rating to be 14k A.I.C. Fully rated

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

Product data sheet
Characteristics

NF442L2
NF Pnlbrd Interior 250A, 3 PH, 4 Wire, 42 CCT, Mn Lug, Al

Product availability : Stock - Normally stocked in distribution facility

Price* : 2418.00 USD



Main

Load center type	Main lugs
Circuit breaker type	EDB/EDG/EDJ
Material	Aluminium

Complementary

Number of spaces	42
Enclosure nominal height	56 in 44 in
Enclosure nominal width	20 in
Enclosure nominal depth	5.75 inFor NEMA 1 enclosure 6.5 inFor NEMA 3R/5/12 enclosure
Line Rated Current	250 A
Wiring configuration	4-wire
Phase	3 phases
System Voltage	480Y/277 V AC

Environment

Standards	CSA C22.2 UL 67

Ordering and shipping details

Category	08350 - NF MLO INTERIOR RTA
Discount Schedule	PE1A
GTIN	00785901871569
Nbr. of units in pkg.	1
Package weight(Lbs)	43.300000000000004

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Returnability	Y
Country of origin	MX


Offer Sustainability

RoHS (date code: YYWW)	Compliant - since 1419 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity
Product environmental profile	Available
Product end of life instructions	Need no specific recycling operations
California proposition 65	WARNING: This product can expose you to chemicals including:
- - - - - - - Substance 1	Nickel compounds which is known to the State of California to cause cancer and
- - - - - - - Substance 2	Bisphenol A (BPA) which is known to the State of California to cause birth defects or other reproductive harm.
- - - - - - - More information	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months


REV	DESCRIPTION	BY	DATE	–	----	--	--/--/--
–	----	--	--/--/--	–	----	--	--/--/--



KNOCKOUTS				
SYMBOL	CONDUIT SIZE		KNOCKOUT DIA	
	IN	MM	IN	MM
A	.50	13	.88	22
B	.75	19	1.12	28
D	1.25	32	1.75	44
E	1.50	38	2.00	51
F	2.00	51	2.50	64
G	2.50	64	3.00	76
H	3.00	76	3.62	92
I	3.50	89	4.12	105

Enclosure

DUAL DIMENSIONS: INCHES
MILLIMETERS




REFERENCE CATALOG NO	L		S		M	
	IN	MM	IN	MM	IN	MM
MH26	26.00	660	21.00	533	20.00	508
MH32	32.00	813	27.00	686	26.00	660
MH38	38.00	965	33.00	838	32.00	813
MH44	44.00	1118	39.00	991	38.00	965
MH50	50.00	1270	45.00	1143	44.00	1118
MH56	56.00	1422	51.00	1295	50.00	1270
MH62	62.00	1575	57.00	1448	56.00	1422
MH68	68.00	1727	63.00	1600	62.00	1575
MH74	74.00	1880	69.00	1753	68.00	1727
MH80	80.00	2032	75.00	1905	74.00	1880
MH86	86.00	2184	81.00	2057	80.00	2032
MH92	92.00	2337	87.00	2210	86.00	2184

JOB NAME:	---	EQUIPMENT DESIGNATION:	---
JOB LOCATION:	---	EQUIPMENT TYPE:	NEMA 1 BOXES
DRAWN BY:	---	DRAWING TYPE:	---
ENGR:	---		
DATE:	JULY 2018		
DRAWING STATUS:	---	DWG# PBA600	PG 1 OF 1 REV –

CATALOG NUMBER	A		B		C	
	IN	MM	IN	MM	IN	MM
NC26S	26.12	663	17.70	436	6.16	156
NC32S	32.12	816	23.70	602	9.16	233
NC38S	38.12	968	29.70	754	12.16	309
NC44S	44.12	1121	35.70	907	15.16	385
NC50S	50.12	1273	41.70	1059	18.16	461
NC56S	56.12	1425	47.70	1212	21.16	537
NC62S	62.12	1578	53.70	1364	24.16	614
NC68S	68.12	1730	59.70	1516	27.16	690
NC74S	74.12	1883	65.70	1669	30.16	766
NC80S	80.12	2035	71.70	1821	33.16	842
NC26F	27.52	699	17.70	436	6.16	156
NC32F	33.52	851	23.70	602	9.16	233
NC38F	39.52	1004	29.70	754	12.16	309
NC44F	45.52	1156	35.70	907	15.16	385
NC50F	51.52	1309	41.70	1059	18.16	461
NC56F	57.52	1461	47.70	1212	21.16	537
NC62F	63.52	1613	53.70	1364	24.16	614
NC68F	69.52	1766	59.70	1516	27.16	690
NC74F	75.52	1918	65.70	1669	30.16	766
NC80F	81.52	2071	71.70	1821	33.16	842
NC86S	86.12	2187	77.70	1974	36.16	918
NC86F	87.52	2071	77.70	1974	36.16	918
NC35S	35.12	892	26.70	678	10.66	271
NC35F	36.52	928	26.70	678	10.66	271
NC41S	41.12	1044	32.70	831	13.66	347
NC41F	42.52	1080	32.70	831	13.66	347
NC92S	92.12	2340	83.70	2126	39.16	995

Surface Trim



DUAL DIMENSIONS: INCHES / MILLIMETERS

PANELBOARD COVER
TRIM TYPE 1
SURFACE/FLUSH

SQUARE D by Schneider Electric

DWG# NO. PWFDS-SYTI-0164

Product data sheet
Characteristics

EDB14015
E-Frame Brkr 15A, 1P, 277V, 18/25kA, Bolt-on Mnt



Main

Range of product	125 A Frame EDB-EGB-EJB
Product or component type	Miniature circuit-breaker
Device short name	EDB
Module type	E-Frame
Trip unit rating	875 A

Complementary

Line Rated Current	15 A
System Voltage	277 V AC
AWG gauge	AWG 14...AWG 6 copper AWG 12...AWG 6 aluminium
Breaking capacity	18 kA 277 V AC 18 kA 240 V AC 25 kA 120 V AC 18 kA 120/240 V AC
Circuit breaker application	HACR rated Switching Duty rated HID rated
Depth	4.05 in
Electrical connection	Lugs aluminium
Height	5.66 in
Holding current	270 A
Local signalling	Trip indicator
Mounting mode	Bolt-on
Number of poles	1
Number of spaces	1
Number of spaces required	1
Product destination	Panelboard NF
Product weight	2 lb(US)

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Protection type	Short-circuit Overload
Width	0.98 in
Trip unit technology	Thermal-magnetic
Breaking capacity code	D

Environment

Product certifications	CULus IEC
Ambient air temperature for operation	104 °F (40 °C)

Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 1423 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity
REACh	Reference not containing SVHC above the threshold Reference not containing SVHC above the threshold
Product environmental profile	Available
Product end of life instructions	Need no specific recycling operations

Product data sheet
Characteristics

EDB14010
E-5raF e Brmr 10k A1PA4, 027V88/ Al , 7Vnmk ABoM4 oRg Rt



g aiR

f aRpe oGJroduct	l Vn k 5raF e EDB-Ey B-EbB
Product or coF JoReRt tvJe	g iRiature circuit-Treamer
DeLice short RaF e	EDB
g oduM4 tvJe	E-5raF e
SriJ uRt ratiRp	, 8n k

CoF JM4F eRtarv

WiRe f ated CurreRt	10 k
. vsteF / oM4ape	4, 027V88 / kC
k6 y paupe	k6 y l 4HHHk6 y wcoJJer k6 y l VHHHk6 y waM4F iRuF
BreamiRp caJacitv	l , mk V88 / kC l , mk 4, 027V88 / kC Vn mk l V0 / kC Vn mk l V07V40 / kC Vn mk V40 / kC
Circuit Treamer aJJM4catioR	l kCf rated l ND rated
DeJth	4H0n iR
EM4ectricaMcoRRectioR	Wups aM4F iRuF
l eipht	nHwiR
l oM4iRp curreRt	V80 k
WocaMsipRaM4Rp	SriJ iRdicator
g ouRtiRp F ode	BoM4oR
quF Ter oGJoM4s	1
quF Ter oGsJaces	1
quF Ter oGsJaces re(uired	1
Product destiRatioR	PaReM4oard q5
Product Ueipht	4 M4)O. 9

DiscM4F er3Shis docuF eRtatioR is Rot iReRded as a suTstitute Gor aRi is Rot to Te used Gor deterF iRRp suitaTiM4v or reM4iaTiM4v oGthese Jroducts Gor sJeciGc user aJJM4catioRs

ProtectioR tvJe	. hort-circuit ° LerM ad
6 idth	VH-I4 iR
SriJ uRit techRoM pv	SherF aM F apRetic
BreamiRp caJacitv code	D

ERLiroRF eRt

Product certiGcatioRs	COWus
k F TieRt air teF Jerature Gor oJeratioR	I 04 Y5)40 YC9

° GGr . ustaiRaTiM v

. ustaiRaTM d oGGr status	y reeR PreF iuF Jroduct
f ol .)date code3226 6 9	CoF JM aRt - siRce I 4V1 - . chReider EM ctric decM ratioR oGcoRGrF itv . chReider EM ctric decM ratioR oGcoRGrF itv
f Ek Ch	f eGreRce Rot coRtaiRRp . / I C aToLe the threshoM d f eGreRce Rot coRtaiRRp . / I C aToLe the threshoM d
Product eRLiroRF eRtaMJroGM d	k LaiM aTM d
Product eRd oGM e iRstructioRs	q eed Ro sJeciGc recvcM Rp oJeratioRs

Date: July 11, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 11, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-01R2
PO-P18-123

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [x] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 28 16 05 Intrusion Detection

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-001-R2

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [x] REVIEWED
- [ ] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-16

BY Konrad Goluch

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the contractor.


Do not hesitate to contact me if you have any questions or concerns.

B208 Octo-input Module

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- Programmable input point functions
- Easy to read switch addressing
- 2 interconnect wiring connectors
- Provides eight points

The B208 Octo-input Module is an 8 point expansion device that connects to the control panel through the SDI2 bus. This module is fully supervised and communicates back to the control panel all point status changes. The module expansion points operate the same as the points on the control panel. Industrial, commercial, and institutional facilities are typical installations for the B208 module. The B208 connects to the SDI2 bus on the control panel using SDI2 terminals, or using the interconnect cable. You can connect multiple B208 modules to a single control panel. The B208 address switches allow for ease of use in device addressing.

System overview

The B208 Octo-input Module connects to a control panel through the SDI2 bus. This module is supervised and communicates back to the control panel all point status changes. The module's expansion points operate the same as the points on the control panel.

Functions

Loop inputs
The B208 uses up to eight inputs which may be Normally Open (NO), or Normally Closed (NC) with 1k Ω EOL resistor(s) for supervision.

Certifications and approvals

Region	Certification	
Australia	RCM	ACMA
Europe	CE	EMC, RoHS
USA	UL	
	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 609 - Standard for Local Burglar Alarm Units and Systems
	UL	UL 636 - Holdup Alarm Units and Systems
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems
	UL	UL 985 - Household Fire Warning System Units
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL	UL 1610 - Central Station Burglar Alarm Units
	FM	FM 3010 - Fire Alarm Signaling Systems
	CSFM	see our website

28 16 05

Region	Certification	
	FCC	Part 15 Class B
	FDNY-CoA	6174
	FDNY-CoA	6196
Canada	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units
	ULC	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems
	IC	ICES-003 - Information Technology Equipment (ITE)

Installation/configuration notes

Wiring considerations

The module to the control panel using the PWR, A, B, COM terminals on the control panel using the screw terminal strip or the interconnect wiring connector. Use 12 AWG to 22 AWG (1.5 mm to 0.6 mm) wires from the module to the control panel.

Compatibility

For UL 864 compliance, use a UL commercial fire approved control panel.

Control panels	B9512G/B9512G-E (Up to 59 modules) B8512G/B8512G-E (Up to 9 modules) B6512 (Up to 9 modules) B5512/B5512E (Up to 4 modules) B4512/B4512E (Up to 2 modules) D9412GV4 (Up to 24 modules) D7412GV4 (Up to 7 modules) D7212GV4 (Up to 3 modules)

Parts included

Quantity	Component
1	Module
1	Hardware pack
1	Interconnect cable
1	Installation manual

Technical specifications

Properties

Dimensions	2.5 in x 3.8 in x 0.60 in (6.37 cm x 9.6 cm x 1.5 cm)

Environmental considerations

Relative humidity	5% to 93% at +32°C (+90°F)
Temperature (operating)	0°C to +49°C (+32°F to +120°F)

Power requirements

Current	35 mA
Voltage	12 VDC nominal

Wiring

SDI2 wiring	Maximum distance – Wire size (unshielded wire only): 1000 ft (305 m) – 22 AWG (0.65 mm) 1000 ft (305 m) – 18 AWG (1.02 mm) Unshielded wire only

Loop inputs

Loop Inputs	Up to eight inputs. Input contacts may be Normally Open (NO) or Normally Closed (NC) with 1kΩ EOL resistor(s) for supervision. Note: Normally Closed (NC) is not permitted in Fire installations.

Ordering information

B208 Octo-input Module
Provides 8 programmable inputs.
Order number **B208**

28 16 05

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia


© Bosch Security Systems 2017 | Data subject to change without notice
2536957579 | en, V25, 17. Feb 2017

B430 Plug-in Telephone Communicator

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- Provides a single telephone line with RJ-45 connection for central station reporting and remote programming
- Easily configured for communications from Remote Programming Software (RPS) or a keypad, eliminating the need for separate configuration
- Easy two-step plug-in installation, troubleshooting, and maintenance

The B430 provides communication over the PSTN (Public Switched Telephone Network) by connecting the PSTN to the control panel. The module provides a single telephone jack, and easily installs into the control panel on-board plug-in module connector.

Functions

Central station reporting
The B430 supports reporting to a central station receiver through the telephone lines.
Remote programming of Bosch control panels
The B430 supports secure RPS programming of compatible Bosch control panels.

Certifications and approvals

Region	FCC Details
USA	FCC Registration Number: ESVAL00BB430 Ringer Eq: 0.0B

Region	Certification	
Australia	RCM	ACMA
Europe	CE	EMC, RoHS
USA	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 636 - Holdup Alarm Units and Systems
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems
	UL	UL 985 - Household Fire Warning System Units
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL	UL 1610 - Central Station Burglar Alarm Units
	CSFM	see our website
	FCC	Part 15 Class B
	FCC	Part 68
	FDNY-CoA	6174
Canada	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	CAN/ULC S545 - Residential Fire Warning System Control Units

28 16 05

Region	Certification	
	ULC	CAN/ULC S559 - Fire Signal Receiving Centres and Systems
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units
	ULC	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems
	IC	ICES-003 - Information Technology Equipment (ITE)
Brazil	ANATEL	1709-13-1855 [B430]

Installation/configuration notes

Mounting considerations

Connect the B430 Plug-in Telephone Communicator to any compatible control panel or interface module, which can then be mounted in a variety of enclosures for optimal situations.

Wiring considerations

The B430 connects to the control panel or interface modules without tools or physical wiring for power. It has an RJ-45 jack for plugging in the phone line (PSTN).

Communication speed

The module communicates at 2400 baud maximum.

Compatibility

Control panels	B9512G/B9512G-E B6512 B8512G/B8512G-E B5512/B5512E B4512/B4512E B3512/B3512E
Phone cords	D161 Dual Modular Telephone Cord D162 Modular Telephone Cord
Phone jack	D166 Telephone Jack

Parts included

Quantity	Component
1	B430 Plug-in Telephone Communicator
1	Literature pack

Technical specifications

Properties

Dimensions	2 in x 3.68 in x 0.60 in (50 mm x 93.5 mm x 15.25 mm)
Weight	1.3 pounds (0.6 KG)

Environmental considerations

Relative humidity	5% to 93% at +32°C (+90°F)
Temperature (operating)	0°C to +49°C (+32°F to +120°F)

Power requirements

Current (maximum)	Standby: 24 mA Alarm: 24 mA
Voltage (operating)	12 VDC nominal

Ordering information

B430 Plug-in Telephone Communicator
Plug-in PSTN communication module for control panel to central station receiver communication.
Order number **B430**

28 16 05

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2017 | Data subject to change without notice
18964708491 | en, V8, 17. Feb 2017

B920 Two-line Alphanumeric Keypad (SDI2)

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- 2-line LCD display with up to 32 character point, user, and area names
- Simple menu-style user interface with dedicated function buttons for common commands, including status indication
- Situation sensitive on-screen help makes system operation simple and easy
- Highly visible on (arm)/alarm, ready to turn on (arm), power and gas alarm indicators
- Simple installation with self-locking base and chassis design, plus built-in bubble level

The B920 Two-line Alphanumeric Keypad (SDI2) is a SDI2 bus compatible device. Each keypad has user adjustable options such as volume and display brightness. The B920 shows two-line system messages for all areas.

System overview

- For commercial use, install the keypad in building entrances and areas with unrestricted access. Mounting a keypad near exterior doors in hotel or business lobbies allows people to identify the type and location of the emergency.
- For residential use, install the keypad near the front and rear entrances to the home. Install additional keypads in a kitchen or in a bedroom.
- Use multiple keypads in a large building with many separate areas of security. Program multiple keypads to control multiple areas.
- Audible tones from the keypad sounder alert personnel to fire events and assist fire fighters in locating the keypad.

Functions

LCD display
The keypad uses words, numbers, and symbols to show the status of the security system. When several events occur, the keypad shows each event in order of priority.

Keys
Each keypad has 10 number keys, 7 function keys, and 6 navigation keys. When pressed, keys turn on keypad backlighting and emit the keypress tone (short beep). The function keys include programmable function keys and keys to initiate arming and bypassing with one keypress.

Audible tones
The keypad has a built-in speaker that produces several distinct warning tones. The tones are differentiated so that the user can recognize an event simply by hearing its associated tone. The keypad backlight illuminates when it emits an audible tone. Users can use a passcode to silence the tone.

28 16 05

Status indicators
The status indicators on the keypad provide a quick visual reference for system status.

✓	The indicator lights when the system is ready to turn on (arm).
	The indicator lights when the system is on (armed).
⚠	The indicator lights when there is a trouble condition.
GAS	The indicator lights when dangerous gases are present including carbon monoxide (NFPA 720).
	The indicator lights when the system has power.

Certifications and approvals

Region	Certification	
Australia	RCM	ACMA
Europe	CE	EMC, RoHS
USA	UL	
	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 609 - Standard for Local Burglar Alarm Units and Systems
	UL	UL 636 - Holdup Alarm Units and Systems
	UL	UL 985 - Household Fire Warning System Units
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL	UL 1610 - Central Station Burglar Alarm Units
	CSFM	see our website
	FCC	Part 15 Class B
Canada	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	CAN/ULC S545 - Residential Fire Warning System Control Units
	ULC	CAN/ULC S559 - Fire Signal Receiving Centres and Systems
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units
	ULC	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems
	IC	ICES-003 - Information Technology Equipment (ITE)

Installation/configuration notes

Mounting considerations
Mount in indoor, dry locations.

Power supply
A compatible control panel supplies the power and data requirements to the keypad through a four-wire connection.

Enclosure and wiring
The sliding self-locking enclosure has an integrated bubble level and custom gap-free, lift-gate style terminal blocks to make installation easier.

Compatible control panels
B9512G/B9512G-E
B8512G/B8512G-E
B6512
B5512/B5512E firmware v2.02 and higher
B4512/B4512E firmware v2.02 and higher
B3512/B3512E firmware v2.02 and higher
D9412GV4/D7412GV4 firmware v2.02 and higher

Parts included

Quantity	Component
1	Keypad
1	Hardware pack
1	Set of ABC key labels
1	Installation Guide
1	User's Quick Reference Guide

Technical specifications

Properties

Dimensions	6.2 in x 4.7 in x 1 in (158 mm x 120 mm x 26 mm)
Weight	11.3 oz (0.32 kg)
Material	Acrylonitrile butadiene styrene (ABS) Poly(methyl methacrylate) (PMMA)
Display window	2 line display 18 characters per line
Indicators	Illuminated keys Status indicators Warning and indicating tones

Environmental considerations

Relative humidity	5% to 93% at +32°C (+90°F) non-condensing
Temperature (operating)	0°C to +50°C (+32°F to +122°F)

28 16 05

Power requirements

Current	Standby:35 mA Alarm: 70 mA
Voltage (input)	12 VDC nominal

Wiring

Terminal wire size	12 AWG to 22 AWG (2.0 mm to 0.65 mm)
SDI2 wiring	Maximum distance – wire size (unshielded wire only): 1000 ft (305 m) – 22 AWG (0.65 mm)

Ordering information

B920 Two-line Alphanumeric Keypad (SDI2)
Two-line alphanumeric keypad
Order number **B920**

Accessories

B56 Keypad Surface Mount Box
Surface mount box for mounting a keypad to concrete or block.
Order number **B56**

B96 Keypad Trim Bezel
Cover the wall footprint of previous keypads when replacing them with the new, slim design of B Series keypads. The white trim bezel is 8.6 in x 6.3 in x 0.12 in (22 mm x 16 mm x 3 mm).
Order number **B96**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2017 | Data subject to change without notice
9973643275 | en, V16, 17. Feb 2017

B8103 Enclosure

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- Easy-to-install standoff location for mounting supported modules
- Made with cold-rolled steel with a white semi-gloss finish
- Easy access locations for battery placement
- Optional tamper switch mounting location

The enclosure houses many control panels and modules by Bosch. It is compatible with an enclosure tamper switch and can hold up to two batteries. Use the enclosure for residential fire and burglary installations and commercial burglary applications that do not require attack resistance.

Certifications and approvals

Region	Certification	
USA	UL	UL 294 - Standard for Access Control Units and Systems
	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 609 - Standard for Local Burglar Alarm Units and Systems
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems
	UL	UL 985 - Household Fire Warning System Units
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1610 - Central Station Burglar Alarm Units
	UL	UL 1635 - Standard for Digital Alarm Communicator System Units
	CSFM	see our website
	FDNY-CoA	6196
Canada	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units

Installation/configuration notes

Compatible locksets
D101 (Key #1358)
D101F (Key #203)

Compatible tamper switches
D110
ICP-EZTS

28 16 05

Parts included

Quantity	Component
1	Enclosure
1	Hardware pack
1	Literature pack

Technical specifications

Dimensions	41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.)
Weight	4.5 kg (10 lb)
Material	Cold-rolled steel
Color	White

Ordering information

B8103 Enclosure
White steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).
Order number **B8103**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia


© Bosch Security Systems 2017 | Data subject to change without notice
18395968139 | en, V11, 21. Mar 2017

B8512G Control Panels

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- Fully integrated intrusion, fire, and access control allows users to interface with one system instead of three
- Provides up to 99 points using a combination of hardwired or wireless devices for installation flexibility, and up to 8 areas and 8 doors for up to 500 users
- On-board Ethernet port for Conettix IP alarm communication and remote programming, compatible with modern IP networks including IPv6/IPv4, Auto-IP, and Universal Plug and Play
- Installer-friendly features for simple installation and communications, including on-board USB for easy on-site RPS programming, plus support for Remote Connect Service (not available in Europe, the Middle East, or Africa), and plug-in PSTN and cellular communication modules for simple installation and communications
- Remote Security Control (RSC) app which allows users to control their security systems – and view system cameras - remotely from mobile devices such as phones and tablets

The B9512G Control Panel and the B8512G Control Panel are the new premier commercial control panels from Bosch. B8512G control panels integrate intrusion, fire, and access control providing one simple user interface for all systems.
With the ability to adapt to large and small applications, the B8512G provides up to 99 individually identified points that can be split into 8 areas.
The control panel can communicate through its built-in Ethernet port (not applicable to “E” control panels), or through compatible plug-in modules that can send events over the public switched telephone network (PSTN) or over cellular network communications.

For users, programmable keypad shortcuts, situation sensitive on-screen help, and a bilingual user interface make system operation simple and easy.
With the B8512G, you can:

- Monitor alarm points for intruder, gas, or fire alarms.
- Program all system functions local or remote using Remote Programming Software (RPS) or by using basic programming through the keypad.
- Add up to 8 doors of access control using the optional B901 Access Control Module or D9210C Access Control Interface Module.

The B8512G is a direct replacement for previous control panel models D7412GV4, D7412GV3, D7412GV2, and D7412G.

28 16 05

Functions

Programmable outputs
- Four alarm-output patterns
- Programmable bell test

Point response
- Selectable point response time
- Selectable EOL values and configuration
- Cross point capability
- Fire alarm verification
- Dangerous gas indicator includes carbon monoxide (NFPA 720)
- Watch mode
- Selectable point response time

User interface
- Supervision of up to 32 keypads
- Custom keypad text is fully programmable through RPS
- Full function menu including customizable shortcuts
- Authority by area and 32 character name for each user
- 14 custom authority levels to restrict system features that each user can access
- Programmable primary and secondary language by user and keypad; select from English, Spanish, French, and Portuguese

Area configurations
Link multiple areas to a shared area such as a lobby or common entryway. The shared area then automatically turns On (arms) when all associate areas are armed and turns Off (disarms) when any one associate area is disarmed. For higher security applications, the Area Re-Arm feature guarantees that areas are always rearmed, and are disarmed for no longer than a specific, configurable, amount of time (for example, service time).

Custom functions
For added convenience, the installer can program custom functions that allow customers to complete complex tasks with one simple action. For example, a custom function can bypass a group of points and arm the system, allowing the user to perform these functions with one easy command. Users can activate custom functions with a keypad, keyfob, token, or card, or the control panel can activate a function in reaction to a faulted point, or automatically through a scheduled event (SKED).

Passcode security
- Two-man rule. Requires two people with two unique passcodes to be present at the time of opening.
- Early ambush. Allows users to verify that the facility is safe by requiring two passcodes. The control panel sends a duress event if the user does not enter the passcode a second time after inspecting the premises.
- Dual authentication. Requires two forms of identification before processing certain system commands, including turning off the system and opening doors. A standard system user must have a passcode, a credential (token or card), and appropriate command authority permissions.

Door control
Using the B901 Access Control Module or D9210C Access Control Interface Module, the control panel provides a fully supervised access control solution. The solution offers 14 programmable levels of access authority. Authority for door access is controlled by the user level, the group of the user, the time of day, the door state, and the area armed (On/Off) state.

Easy exit control
The control panel changes from one On (armed) state to another without turning off (disarming) the system. For example, if you change the state from Part On (Perimeter Arm) to All On (Master Arm), the control panel complies and reports the change. Easy Exit Control reduces the number of keystrokes, simplifying system operation.

Programmable passcode-controlled menu list
Passcode-controlled shortcuts provide users only with the options and information pertinent to them, simplifying system operation.

Flexible control
The system provides the flexibility to choose added convenience or high security. For example, you can restrict to a keypad's immediate local area turning on (arming) and turning off (disarming) the system with a passcode, even if the user has access to other areas. This is particularly useful for high security areas, where a user may have access to the area, but would prefer to only turn off (disarm) the area individually rather than with the rest of the system.

Monitor Delay/Delayed Response
Create a special point index that delays the reaction of a point for a specified time (up to 1 hour in minutes and seconds). This delay provides time for the specified condition to reset before activating any annunciation. The system can annunciate locally and send a report, if desired. When the system is armed, the point can respond like a normal point – providing dual functionality. Use this feature to ensure that perimeter doors have not been propped open, or to monitor critical areas such as computer rooms and safes, for example.

System users
The system supports up to 500 users. Each user can have a personalized passcode, a wireless keyfob, and a credential to control the system. You can assign passcodes to one of 14 customized authority levels in each area that can be restricted to operate only during certain times. You can program a primary and secondary language for each user and by keypad (select from English, Spanish, French, and Portuguese). The keypad changes to the user's programmed language when the user enters his passcode or holds the Help key.

28 16 05

Communication formats
The control panel prioritizes and sends reports to four route groups. Network and phone communications can use one of two communication formats: Modem4, Contact ID. Each group has a programmable primary and backup destination.
The control panel provides flexible communications for most central stations with reporting capabilities such as:
- Individual point numbers
- Opening or closing reports by user and area number
- Remote programming attempts
- Diagnostic reports

IP communication
The control panel can use IP to communicate with a Conettix D6600 or a Conettix D6100IPv6 Communications Receiver/Gateway. Use one of the following for IP:
- The on-board Ethernet connection (the on-board Ethernet port is excluded on “E” versions).
- A B426.
- A plug-in cellular communicator (B440/B440-C/B441/B441-C/B442/B443/B444).

Conettix IP communication provides a secure path that includes anti-replay/anti-substitution features, and enhanced security with up to AES 256-bit encryption (using Cipher Block Chaining (CBC)).
The control panel supports Domain Name System (DNS) for both remote programming and central station communication. DNS provides ease of use, eliminating the need to use static IP addresses as your reporting destination, and accommodates a simple solution for central station disaster recovery. The control panel supports both IPv6 and IPv4 networks.

Communication paths
The control panel accommodates up to four separate phone and four separate network paths to the central station receiver. When resetting alarms or turning a system on and off, the user is identified by name and number.

Personal notification
The control panel can send text messages and emails for personal notification over Ethernet or using a cellular communicator. You can configure up to 32 destinations using a combination of cellular phone numbers and email addresses. The control panel sends notifications in the user’s programmed primary language.

Bosch Remote Connect (Cloud)
Remote Connect simplifies connections from RPS, and the Remote Security Control app, using Bosch Cloud services. This service creates a secure connection to the control panel without specific router settings or the need for a static IP address or DNS.

Notice
The Bosch Remote Connect service is not available in Europe, the Middle East, or Africa.

Firmware updates
The system allows remote firmware updates:
- Control panel updates. Remotely update the control panel firmware for easy feature enhancements without replacing ROM chips.
- Module update support. Remotely update the firmware on connected SDI2 modules for easy feature enhancements without visiting each individual module.

Firmware updates occur through Remote Programming Software (RPS) and the RPS Firmware Update Wizard. The Firmware Update Wizard uses the on-board USB connection or the on-board Ethernet (IP) connection (the on-board Ethernet port is excluded on “E” versions) to transfer firmware updates.
The control panel can optionally receive firmware updates from RPS. Use one of the following communication methods:
- B426
- Plug-in cellular communicator: B440/B440-C/B441/B441-C/B442/B443/B444

Notice
Data rate apply
Cellular firmware updates require more time than Ethernet updates and carrier data rates apply.

A wide variety of input options
Each point:
- Single 1 kΩ, single 2 kΩ, dual 1 kΩ (1 kΩ + 1 kΩ), and No EOL (end-of-line) (EOL) resistor options (for on-board and B208 inputs)
- Programmable for Fire, Intrusion, Access, Gas, and Supervisory devices
- Supports hardwired and wireless devices
- Supports IP cameras by Bosch as point and output devices

IP camera support
The control panel can integrate directly with Bosch IP cameras, using them as fully supervised points and outputs.
Integration of cameras allows the camera’s video motion detection to activate points on the control panel. The control panel’s virtual outputs can be configured to trigger camera actions, including sending video snapshots via email.

Security and fire detection
The control panel provides eight on-board points, and up to 91 additional off-board points (depending on model and expansion interfaces). You can program individual points to monitor some types of burglar alarms, fire alarms, and supervision devices.

28 16 05

Event log
The event log stores up to 2048 local and reported events. The event log includes time, date, event, area, point, and user. View the event log from a keypad or use RPS to remotely retrieve event information. When the event log reaches a programmed threshold of stored events, it can send an optional report to a receiver.

Scheduled events (SKEDs)
The internal clock and calendar start individually scheduled events (SKEDs). SKEDs perform several functions such as turn on or off, relay control, or point bypassing.
The control panel offers:
- 40 scheduled events with up to 31 different functions
- 8 opening windows and 8 closing windows
- 8 user group windows
- Day-of-week, date-of-month, or holiday only schedules
- 4 holiday schedules of 366 days (leap year)

Dual bus and SDI keypad retrofits
The dual SDI2 device bus design provides greater installation flexibility, such as bus isolation for Intrusion and Fire. To use popular SDI keypads (for example D1255 and D1260), program one of the two SDI2 buses for SDI operation.

ZONEX and POPEX retrofits
To retrofit legacy Bosch control panels that use ZONEX and POPEX devices, the control panel is compatible with the B600 Retrofit (ZONEX) Module. The B600 adds two ZONEX buses to the control panel which can connect to existing legacy point bus (POPEX) devices (for example, the D8125).

Programming
Installers can perform limited programming on-site with a keypad (critical parameters; such as account IDs, central station and RPS IP addresses and phone numbers, reporting formats, and more). They can also do full programming on-site or remotely (attended or unattended) with RPS. A programmable system passcode prevents unauthorized remote programming.

Diagnostics
Keypads and RPS offer diagnostic help for monitoring and troubleshooting. The diagnostics features allow you to view the status of the wired and wireless devices. The features provide the status of the control panel and its connected devices, such as firmware version, power, and missing conditions. View the status of each area.

Remote Security Control app
The Remote Security Control (RSC) app allows users to control their security systems remotely from their devices. Users can:
- Turn their security system On or Off
- Turn specific areas On or Off
- Control outputs for applications such as lighting control
- View live video from Bosch IP cameras
- Grant access remotely by unlocking and locking doors

The app requires the installing dealer to create a Remote Access Profile for users, and to install the profile on their devices.

Bosch Video Management System integration
With Bosch Video Management System (Bosch VMS) and an intrusion system, the VMS operator has a single user interface to monitor and control the intrusion system combined with video surveillance. With Bosch VMS and a control panel, the operator can, for example:
- View videos triggered by intrusion events, including all relevant information such as areas, point, and user show in the display with the event.
- View areas, points, outputs, and doors – with their statuses – on the Bosch VMS map, providing the exact location in the system.
- Turn on (arm) and turn off (disarm) areas.
- Bypass and unbypass points.
- Lock and unlock doors (Bosch VMS 6.0 and higher).

Requirements to integrate Bosch VMS with a control panel:
- A licensed Bosch VMS system using Professional Editions v5.5 or higher or Bosch VMS Enterprise Edition v5.5 or higher.
- Expansion license to integrate the intrusion control panel. One license needed per control panel. Order number MBX-XINT-xx for the expansion license added to a Bosch VMS base license. Refer to the Bosch Video Management Software product page on the Bosch website, www.boschsecurity.com.
- Access to Remote Programming Software (RPS).

Certifications and approvals

Region	Regulatory compliance/quality marks	
USA	ANSI-SIA	CP-01-2010-Control Panel Standard - Features for False Alarm Reduction
Australia	RCM	[B9512G]
	RCM	[B8512G]
	RCM	ACMA
Europe	CE	EMC, LVD, RoHS [B9512G, B9512G-E, B8512G, B8512G-E]
USA	UL	[B9512G, B9512G-E, B8512G, B8512G-E, B299, B600, B901, B925F, B926F]
	UL	UL 294 - Standard for Access Control Units and Systems
	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 609 - Standard for Local Burglar Alarm Units and Systems
	UL	UL 636 - Holdup Alarm Units and Systems
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems
	UL	UL 985 - Household Fire Warning System Units

28 16 05

Region	Regulatory compliance/quality marks	
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL	UL 1610 - Central Station Burglar Alarm Units
	UL	UL 1635 - Standard for Digital Alarm Communicator System Units
	FM	Central Station
	FM	Local Protective Signaling
	FM	Remote Station
	CSFM	California State Fire Marshal (see our website)
	FCC	Part 15 Class B
	FDNY-CoA	Fire Department of New York City [B9512G, B9512G-E, B8512G, B8512G-E]
Canada	ULC	[B9512G, B9512G-E, B8512G, B8512G-E, B299, B600, B901, B925F, B926F]
	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	CAN/ULC S545 - Residential Fire Warning System Control Units
	ULC	CAN/ULC S559 - Fire Signal Receiving Centres and Systems
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units
	ULC	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems
	IC	ICES-003 - Information Technology Equipment (ITE)
Brazil	ANATEL	04450-16-01855 [B9512G, B8512G when used with B430 or B442]

Installation/configuration notes

Notice
Not all products and features are available in all regions. Consult your local Bosch representative for availability details.

Compatible products

Keypads

B942/B942W Touch Screen Keypad (SDI2)

B930 ATM Style Alphanumeric Keypad (SDI2)

B926F Fire Keypad (SDI2)

B925F Fire Keypad (SDI2)

B921C Two-line Capacitive Keypad (SDI2)

B920 Two-line Alphanumeric Keypad (SDI2)

B915/B915I Basic Keypad (SDI2)

D1255 Series Keypads

D1260 Series Keypads

D1256RB Fire Keypad

D1257RB Remote Fire Alarm Annunciator

Power

D1640 16.5 VAC 40 VA Transformer

DE-45-18 Transformer

D126 Standby Battery (12 V, 7 Ah)

D1218 Battery (12 V, 18 Ah)

D122 Dual Battery Harness

D122L Dual Battery Harness with Long Leads

Enclosures

B8103 Universal Enclosure (White)

D8103 Universal Enclosure (Gray)

D8108A Attack Resistant Enclosure

D8108A-CE Attack Resistant Enclosure with Built-in Transformer

D8109 Fire Enclosure

Accessories

B56 Keypad Surface Mount Box

B96 Keypad Trim Bezel

B99 USB Direct Connect Cable

B501-10 Interconnect wiring cables (pack of 10)

D161 Dual Modular Telephone Cord (7 f)

D162 Modular Telephone Cord (2 ft)

D166 Telephone Jack (RJ31X)

Detectors

D7050 Series Addressable Photoelectric Smoke and Smoke Heat Detector Heads

F220-B6PM/S 12/24 VDC Addressable Detector Bases with POPITs

F220-B6 12/24 VDC Two-wire Base

F220-B6R Standard 12/24 VDC Four-wire Base)

F220-P Photoelectric Smoke Detector

28 16 05

F220-PTH Photoelectric Smoke Detector with +135°F (+57°C) Heat Sensor

F220-PTH Photoelectric Smoke Detector with +135°F (+57°C) Heat Sensor and Carbon Monoxide Sensors

F220-B6C 12/24 VDC Four-wire Base with Auxiliary Form C Relay

FCC-380 Carbon Monoxide Detector

FCH-T320 Heat Detector

FCP-OT320 Multisensor Detector Optical/Thermal

FCP-O320 Optical Smoke Detector

MX775i Addressable PIR Detector

MX794i Long Range Multiplex PIR Detector

MX934i Addressable PIR Detector

MX938i Addressable PIR Detector

ZX776Z PIR Detector

ZX794Z Long Range PIR Detector

ZX835 TriTech Microwave/PIR Detector

ZX935Z PIR Detector

ZX938Z PIR Detector

ZX970 PIR/Microwave Detector

Bosch conventional detectors, including Professional Series, Blue Line Gen2, Blue Line, Classic Line, Commercial Line, and Ceiling Mount motion detectors, as well as glass break, seismic, request-to-exit, photoelectric, heat, and smoke detectors.

Modules

B208 Octo-input Module

B299 POPEX Module

B308 Octo-output Module

B426 Conettix Ethernet Communication Module

B430 Plug-in Telephone Communicator

B440 Conettix Plug-in Cellular Communicator (using 3G)

B441 Conettix Plug-in Cellular Communicator (using CDMA)

B442 Conettix Plug-in Cellular Communicator (using GPRS)

B443 Conettix Plug-in Cellular Communicator (using HSPA+)

B450 Conettix Plug-in Communicator Interface

B520 Auxiliary Power Supply Module

B600 Retrofit (ZONEX) Module

B810 wireless receiver (RADION)

B820 SDI2 Inovonics Interface Module

B901 Access Control Module

D113 Battery Lead Supervision Module

D125B Dual Class B Initiating Module

D126 Standby Battery (12 V, 7 Ah)

D129 Class A Initiating Module

D130 Auxiliary Relay Module

D132A Smoke Detector Reversing Relay Module

D133 Single Relay Module

D134 Dual Relay Module

D185 Reverse Polarity Signaling Module

D192G Class “B”, Style Y Bell Circuit Supervision

D1218 Battery (12 V, 18 Ah)

D8125 Addressable Expansion Module

D8125MUX Multiplex Bus Interface

D8128D OctoPOPIT Eight-point Expander

D8129 Octo-relay Module

D8130 Door Release Module

D9127U/T POPIT Module

DS7461i Single-zone Input Module

DS7465i Input-output Module

D9210C Access Control Interface Module

ICP-EZTS Cover and Wall Tamper Switch

ICP-SDI-9114 SDI Splitter

Applications

Remote Programming Software (RPS or RPS-LITE) v6.03 and higher

Bosch Video Management System v5.5 and higher

Remote Security Control (RSC)

Conettix receivers
(Managed and configured with Conettix D6200 Programming/ Administration Software v2.10)

Conettix D6600 Communications Receiver/Gateway (with only D6641 line cards installed) with CPU version 01.10.00

Conettix D6100IPv6 Communications Receiver/Gateway with CPU version 61.10.00

Conettix D6100i Communications Receiver/Gateway with CPU version 61.10.00

RADION wireless from Bosch

B810 wireless receiver (RADION)

RFBT-A/RFBT bill trap

RFDL-11-A/RFDL-11 TriTech motion detector

RFDW-RM-A/RFDW-RM recessed mount door/window contact

28 16 05

RFDW-SM-A/RFDW-SM surface mount door/window contact

RFGB-A/RFGB glass break detector

RFKF-A/RFKF two-button keyfob

RFKF-FBS-A/RFKF-FBS four-button keyfob

RFKF-TBS-A/RFKF-TBS two-button keyfob

RFPB-SB-A/ RFPB-SB single-button panic

RFPB-TB-A/RFPB-TB two-button panic

RFRP-A/RFRP repeater

RFSM-A/RFSM smoke detector

RFPR-12-A/RFPR-12 PIR motion detector

RFPR-C12-A/RFPR-C12 PIR curtain motion detector

RFUN-A/RFUN universal transmitter

Inovonics Wireless

B820 SDI2 Inovonics Interface Module

ENKIT-SDI2 SDI2 Inovonics Interface and Receiver Kit. Includes B820 and EN4200

EN1210 Universal Transmitter (Single-input)

EN1210EOL Universal Transmitter with EOL Resistor

EN1210W Door-Window Transmitter with Reed Switch

EN1215EOL Universal Transmitter with Wall Tamper, Reed Switch, and EOL Resistor

EN1223D Water-resistant Pendant Transmitter (Double-button)

EN1223S Water-resistant Pendant Transmitter (Single-button)

EN1224-ON Multiple-Condition Pendant Transmitter

EN1233D Necklace Pendant Transmitter (Double-button)

EN1233S Necklace Pendant Transmitter (Single-button)

EN1235D Beltclip Pendant Transmitter (Double-button)

EN1235DF Fixed-location Transmitter (Double-button)

EN1235S Beltclip Pendant Transmitter (Single-button)

EN1235SF Fixed-location Transmitter (Single-button)

EN1247 Glass-break Detector Transmitter

EN1249 Bill Trap Transmitter

EN1242 Smoke Detector Transmitter

EN1260 Wall Mount Motion Detector

EN1261HT High Traffic Motion Detector

EN1262 Motion Detector with Pet Immunity

EN1265 360° Ceiling Mount Motion Detector

EN4200 Serial Receiver

EN5040-T High Power Repeater with Transformer

Technical specifications

Properties

Dimensions	10.625 in x 7.75in x 1.875 in (26.99 x 19.69 x 4.76 cm)
Weight	1.95 lbs (0.88 kg)

Communications

Ethernet	10/100 full duplex (N/A for “E” control panels)

Environmental considerations

Relative humidity	5% to 93% at +32°C (+90°F)
Temperature (operating)	0°C to +49°C (+32°F to +120°F)

Power requirements

Current (maximum)	Standby: 180 mA Alarm: 260 mA
Output (alarm)	2 A at 12 VDC
Output (auxiliary, continuous power, and switched auxiliary combined)	1.4 A at 12 VDC nominal
Voltage (operating)	12 VDC nominal
Voltage (AC)	16.5 VAC 40 VA plug-in transformer (D1640/D1640-CA)

Wiring

Terminal wire size	12 AWG to 22 AWG (2.0 mm to 0.65 mm)
SDI2 wiring	Maximum distance – Wire size (unshielded wire only): 7,500 ft (2,286 m) – 22 AWG (0.65 mm)

Number of...

Areas	8
Custom functions	8
Events	Up to 2048
Passcode users	500, plus 1 Installer passcode
Points	99 (8 on-board, up to 91 off-board and virtual)
Programmable outputs	99 (3 on-board, up to 96 off-board and virtual)
RF points	91

28 16 05

IP cameras	8
SKEDs	40

Ordering information

B8512G IP control panel, 8 areas, 99 points
Supports up to 99 points, 3 on-board outputs, and 8 areas for intrusion, commercial fire. On-board Ethernet.
Order number **B8512G**

B8512G-E Control panel, 8 areas, 99 points, no IP
The B8512G-E is available only in kits.
Order number **B8512G-E**

B901 Door Controller
Fully supervised, addressable SDI2/SDI bus device that allows access control integration for Bosch G and B Series Control Panels.
Order number **B901**

Accessories

B520 Auxiliary power supply module, 2A 12V
Provides auxiliary power to 12 VDC devices or to SDI2 modules.
Order number **B520**

B208 SDI2 8-Input Expansion Module
Provides 8 programmable inputs.
Order number **B208**

B308 SDI2 8-Output Expansion Module
Provides 8 programmable relays.
Order number **B308**

B810 RECEIVER-SDI2
Receives RF signals from RADION transmitters, repeaters, and glassbreaks. Operates at 433.42 MHz. For use with compatible SDI2 bus control panels.
Order number **B810**

D122 Dual battery harness, 17" 18AWG
Harness with circuit breaker. Connects two batteries (in parallel) to a compatible control panel.
Order number **D122**

D122L Dual battery harness, 35", 12V
Harness with circuit breaker and leads measuring 35 in. (89 cm). Connects two batteries (in parallel) to a compatible control panel in a separate enclosure.
Order number **D122L**

D126 Battery, 12V 7Ah
A rechargeable sealed lead-acid power supply used as a secondary power supply or in auxiliary or ancillary functions.
Order number **D126**

D1218 Battery, 12V 18Ah
The D1218 is a 12 V 18 Ah sealed lead-acid battery with two bolt-fastened terminals. It is used for standby and auxiliary power. It connects to a compatible control panel using a D122 or D122L Dual battery harness.
Order number **D1218**

D137 Accessory mounting bracket for enclosure
Used to mount accessory modules in B8103, D8103, D8108A, and D8109 enclosures.
Order number **D137**

D1640 Transformer plug-in, 16V 40VA
System transformer rated at 16.5 VAC, 40 VA.
Order number **D1640**

D1640-CA 16VAC 40VA xfmr Canada
For use in Canada. System transformer rated at 16.5 VAC, 40 VA.
Order number **D1640-CA**

D9002-5 Mounting plate, 6 location 3-hole, 5 pcs
5 pack of mounting skirts for B8103, D8103, D8108A, and D8109 enclosures. Each skirt can hold up to six standard 3-hole mounting modules.
Order number **D9002-5**

D101 Enclosure lock and key set
Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.
Order number **D101**

D110 TAMPER SWITCH 2/PKG
Screw-on tamper switch that fits all enclosures. Shipped in packages of two.
Order number **D110**

ICP-EZTS TAMPER SWITCH-DUAL
Combination tamper switch with a wire loop for additional tamper outputs.
Order number **ICP-EZTS**

B8103 Universal enclosure, white
White steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).
Order number **B8103**

D8103 Steel enclosure, large, grey
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).
Order number **D8103**

D8108A Attack resistant enclosure, large, grey
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes a lock and key set.
Order number **D8108A**

28 16 05

D8109 Fire enclosure, 16x16x3.5", red
Red enclosure measuring 16 in. x 16 in. x 3.5 in. (41 cm x 41 cm x 9 cm). Made from 16 gauge (1.5 mm) cold-rolled steel with a full-length hinge. Includes a lock and key set. UL Listed for commercial fire/ burglary alarm applications.
Order number **D8109**

D8004 Transformer enclosure kit, grey
For applications that might require a remote transformer in an enclosure. Can be used with B Series control panels and D9412GV4/D7412GV4 control panels.
Order number **D8004**

BATB-40 Battery box/enclosure, 22x20.75x7.25"
Holds two dry or wet cell batteries. Optional BATB-SHELF battery shelf increases number of batteries. Suitable for residential/commercial fire or burglary applications.
Order number **BATB-40**

BATB-80 Battery box/enclosure, 14x20.75x7.25"
Battery box/enclosure with shelf holds up to four dry or wet cell batteries. Suitable for residential/ commercial fire or burglary applications.
Order number **BATB-80**

B99 USB direct connect cable
Male A to Male A USB cable for local programming of control panels with on-board USB ports.
Order number **B99**

B915 Basic Keypad
Two-line alphanumeric basic keypad with English function keys.
Order number **B915**

B915I LCD keypad, icon keys, SDI2
Two-line alphanumeric basic keypad with icon function keys.
Order number **B915I**

B920 2 Line Alpha Numeric Keypad (SDI2)
Two-line alphanumeric keypad
Order number **B920**

B921C Two-line Keypad w/Touch keys, Inputs
Two-line alphanumeric keypad with inputs and capacitive touch keys in black.
Order number **B921C**

B930 ATM Style-Alpha Numeric Keypad (SD12)
Five-line ATM style alphanumeric keypad
Order number **B930**

B942 Touch Screen KP Prox/Input/Output, black
Black SDI2 touch screen keypad with inputs and one output.
Order number **B942**

B942W Touch screen KP, prox/input/output,white
White SDI2 touch screen keypad with inputs and one output.
Order number **B942W**

B925F Fire and intrusion keypad, SDI2
Two-line alphanumeric fire and intrusion keypad.
Order number **B925F**

B926F Fire keypad, SDI2
Two-line alphanumeric fire keypad
Order number **B926F**

Software Options

D5500C-USB Kit with DVD and USB security dongle
Account management and control panel programming software with USB security key (dongle).
Order number **D5500C-USB**

28 16 05

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2017 | Data subject to change without notice
13825824395 | en, V23, 22. Aug 2017

D101 Lock and Key Set

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.

Ordering information

D101 Lock and Key Set
Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.
Order number **D101**

D122L Dual Battery Harness with Long Leads

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



Color-coded wire harness with circuit breaker to protect the charging circuit when connecting multiple 12 V batteries to a control panel. The leads accommodate the installation of extra 12 V batteries in an adjacent enclosure.

Certifications and approvals

Region	Certification	
USA	UL	AOTX: Local Alarm Units (UL464, UL609), APAW: Police Station Alarm Units (UL365, UL464)
	CSFM	see our website

Parts included

Quantity	Component
1	D122L Battery Harness
1	Lit – Installation Manual

Ordering information

D122L Dual Battery Harness with Long Leads
Color-coded harness with circuit breaker and leads measuring 89 cm (35 in.). Connects 12 V batteries to compatible control panels.
Order number **D122L**

D161 Dual Modular Telephone Cord

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- Connects an RJ31X Telco block to an RJ38X Telco jack
- 2.1 m (7 ft.) for longer distances

Certifications and approvals

Region	Certification	
USA	CSFM	see our website

Parts included

Quantity	Component
1	Telephone cord

Technical specifications

Length	2.1 m (7 ft.)
Color	Gray

Ordering information

D161 Dual Modular Telephone Cord
A 2.1 m (7 ft.), 8-conductor fully modular plug-in cord.
Order number **D161**

D1640-CA Transformer

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- System transformer rated at 16.5 VAC, 40 VA
- Suitable for use on approved ULC and cUL applications in Canada

For use in Canada. System transformer rated at 16.5 VAC, 40 VA.

Parts included

Quantity	Component
1	Transformer

Technical specifications

Rating	16.5 VAC, 40 VA
Dimensions	3.2 in x 2.8 in x 2.2 in (81 mm x 70 mm x 56 mm)
Color	White

Ordering information

D1640-CA Transformer
For use in Canada. System transformer rated at 16.5 VAC, 40 VA.
Order number **D1640-CA**

D126 Standby Battery (12 V, 7 Ah)

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- 12 VDC sealed lead-acid
- Fully rechargeable
- Maintenance-free
- For use as secondary power for accessory modules
- Long service life

A maintenance-free, sealed lead-acid, standby and auxiliary power supply that provides long service life and dependability.
The battery is for use only with charging circuits calibrated for lead-acid batteries. It is suitable for supplying backup power for fire, security, and access control systems during AC power failures.
The D126 fits in any of the currently offered enclosures and connects to the two color-coded battery leads supplied with the control panel or module. Use a D122 Dual Battery Harness to connect two D126 batteries in parallel and double the amp hour output.

Certifications and approvals

NYC/BSA	582-85-SA
DSI	CDFM

Region	Certification	
Europe	CE	Council Directive 89/336/EEC Electromagnetic Compatibility
USA	UL	ALVY: Access Control Systems Units (UL294), APOU: Proprietary Alarm Units (UL1076), UEHX7: Signaling Appliances, Miscellaneous Certified for Canada (cUL)

Region	Certification	
	FM	
	CSFM	7167-1615: 0100 CONTROL UNIT (HOUSEHOLD)
	CSFM	7165-1615: 0113 FIRE ALARM CONTROL UNIT (COMMERCIAL)
	CSFM	7167-1615:0124 7167 -- CONTROL UNIT (HOUSEHOLD)
	CSFM	7165-1615:0119 7165 -- FIRE ALARM CONTROL UNIT (COMMERCIAL)
	CSFM	7167-1615:0239 7167 -- CONTROL UNIT (HOUSEHOLD)

Installation/configuration notes

Standby Power Requirements
Refer to the appropriate control panel installation manual for information on calculating the standby battery requirements for the system. Total continuous and intermittent current requirements must not exceed the amp hour capacity of the battery.

Technical specifications

Capacity:	12 V, 7 Ah
Compatible Panels:	Compatible with all control panels

28 16 05

Dimensions:	15 cm x 8 cm (6 in. x 3 in.)
Height with Terminals:	10 cm (4 in.)
Weight:	2.5 kg (5.5 lb)

Ordering information

D126 Standby Battery (12 V, 7 Ah)
A rechargeable sealed lead-acid power supply used as a secondary power supply or in auxiliary or ancillary functions.
Order number **D126**

Represented by:

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com

© Bosch Security Systems 2013 | Data subject to change without notice
2548450571 | en, V4, 01. Oct 2013

D166 Telephone Jack

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



Ordering information

D166 Telephone Jack
Standard Telco RJ31X Telephone Jack measuring approximately 5 cm (2 in.) square by 2.5 cm (1 in.) high.
Order number **D166**

Professional Series TriTech Curtain Motion Detectors

www.boschsecurity.com

28 16 05

BOSCH
Invented for life

Curtain type motion detector



- 30 m (100 ft) x 2.6 m (8.5 ft) standard coverage
- 2.1 m to 3 m (7 ft to 10 ft) mounting height, no adjustments required, optional lookdown masking
- Sensor data fusion technology
- Range adaptive radar and active white light suppression
- Dynamic temperature compensation

The Professional Series TriTech Curtain Detectors are exceptionally suited for commercial indoor applications. Sensor data fusion technology ensures that the detector sends alarm conditions based on precise information. The powerful combination of unique features in the Professional Series delivers superior catch performance and virtually eliminates false alarms.
The self-locking two-piece enclosure, built-in bubble level, flexible mounting height, and three optional mounting brackets simplify installation and reduce service time.

Functions

Sensor Data Fusion Technology
Sensor data fusion technology is a unique feature that uses a sophisticated software algorithm to gather signals from five sensors: two pyroelectric sensors, a range adaptive radar sensor, a room temperature sensor, and a white light level sensor. The microcontroller analyzes and compares the sensor data to make the most intelligent alarm decisions in the security industry.

Range Adaptive Radar
The microwave transceiver automatically adjusts its detection thresholds based on input from the PIR sensors. Integrating the target distance information from the PIR significantly reduces false alarms from the microwave Doppler radar.

Active White Light Suppression
An internal light sensor measures the level of light intensity directed at the face of the detector. Sensor data fusion technology uses this information to eliminate false alarms from bright light sources.

Dynamic Temperature Compensation
The detector automatically adjusts PIR sensitivity to identify human intruders at critical temperatures. Dynamic temperature compensation detects human body heat accurately, avoids false alarms, and delivers consistent catch performance at all operating temperatures.

Cover and Wall Tamper Switch
When an intruder removes the cover or attempts to separate the detector from the wall, a normally-closed contact opens to alert the control panel.

28 16 05

Self-adjusting LEDs
The LED brightness adjusts automatically to the surrounding light level. A blue light-emitting diode (LED) indicates TriTech+ alarms and activates during a walk test. A yellow LED indicates microwave detection, and a red LED indicates PIR detection.

Remote Walk Test LED
Users can enter a command through a keypad, a control center, or programming software to remotely enable or disable the walk test LED.

Alarm Memory
Alarm memory flashes the alarm LED to indicate stored alarms for use in multiple unit applications. A switched voltage from the control panel controls the alarm memory.

Solid State Relays
Solid state relays send silent alarm output signals to provide a higher level of security and reliability. An external magnet does not activate the relay. The solid state relay uses less current than a mechanical relay, providing longer standby capacity during a power loss.

Draft, Insect, and Small Animal Immunity
The sealed optic chamber provides immunity to drafts and insects, reducing false alarms. Small animal immunity reduces false alarms caused by animals less than 4.5 kg (10 lb), such as rodents.

Remote Self Test
A remote self test initiates when the walk test input switches to its true state. The alarm relay and alarm LED activate for four seconds following a successful test. The trouble relay activates, and the alarm LED flashes following a failed test.

Input Power Supervision
When the power is lower than 8 V, a low input power trouble condition activates the trouble relay and causes the LED to flash. The trouble condition clears automatically when power reaches or exceeds 8 V.

Trouble Memory
When the walk test input switches to its true state for less than two seconds, the LED flashes to indicate the most recent trouble condition. If there is no trouble in memory, the LED does not flash. After twelve hours, or after the detector receives a second walk test pulse for two seconds or less, the LED stops flashing and the trouble memory clears.

Cloak and Camouflage Detection Technology
Cloak and Camouflage Detection Technology (C^2DT) maximizes catch performance against intruders attempting to cover their infrared signal.

DIP Switch Programming
The following functions are all programmed using DIP switch settings:
- Local Walk Test LED
- Remote Walk Test Input Polarity
- Alarm Memory Polarity
- MANTIS Anti-mask On and Off


Certifications and approvals

Europe	WEEE	Waste Electrical and Electronic Equipment Directive
The detectors are designed to also comply with requirements of:		
USA	FCC	Complies with Part 15

Region	Regulatory compliance/quality marks	
Australia	RCM	[ISC-PDL1-WC30G]
USA	UL	[ISC-PDL1-WC30G]
Brazil	ANATEL	[ISC-PDL1-WC30G]

Installation/configuration notes

Coverage Patterns



Standard Curtain Coverage 30 m x 2.6 m (100 ft x 8.6 ft)

Mounting
The recommended mounting height is 2 m to 3 m (7 ft to 10 ft) with no adjustments required.
Mount the motion detector level, both horizontally and vertically.
Mounting options:
- On a flat wall (surface, semi-flush), with the optional B335-3 Swiveling low-profile mount, or with the optional B328 Gimbal-mount Bracket
- In a corner (the junction of two perpendicular walls)
- On the ceiling with the optional B338 Universal Ceiling-mount Bracket

Wiring Considerations
Recommended wire size is 0.2 mm^2 to 1 mm^2 (26 AWG to 16 AWG).

Technical specifications

Electrical

Power Requirements	
Voltage (Operating):	9 VDC to 15 VDC
Current (Maximum):	< 26 mA with alarm, trouble, and LEDs active.
Current (Standby):	18 mA at 12 VDC
Outputs for both Models	

28 16 05

Tamper:	Normally-closed (NC) contacts (with cover on) rated at 25 VDC, 125 mA maximum. Connect tamper circuit to 24-hour protection circuit.
Trouble:	Solid state relay normally-closed (NC) contacts.
Alarm:	Solid state relay, normally-closed (NC) contacts, power supervised. 3 W, 125 mA, 25 DC, resistance < 10 Ω.

Mechanical

Enclosure Design

Color:	White
Dimensions:	127 mm x 69 mm x 58 mm (5 in. x 2.75 in. x 2.25 in.)
Material:	High-impact ABS plastic

Indicators

Alarm Indicator:	• Blue LED for TriTech+ alarms
	• Yellow LED for microwave detection
	• Red LED for PIR detection

Zones

Zones:	28

Environmental

Relative Humidity:	0 to 95%, non-condensing
Temperature (Operating and Storage):	-30°C to +55°C (-22°F to +130°F) *For UL Certificated installations, 0°C to +49°C (+32°F to +120°F)*
Protection Rating (EN 60529, EN 50102):	IP41, IK04

Ordering information

ISC-PDL1-WC30G Motion detector, 100ft (30m), curtain
Provides PIR and microwave, 30 m x 3 m (100 ft x 10 ft) coverage.
Order number **ISC-PDL1-WC30G**

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

ISC-PDL1-WC30H Motion detector 30m curtain, 10.588GHz
Provides PIR and microwave, 30 m x 3 m (100 ft x 10 ft) coverage. For use in France and the United Kingdom.
Order number **ISC-PDL1-WC30H**

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

Accessories

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

28 16 05

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2018 | Data subject to change without notice
2610618763 | en, V44, 11. Jan 2018

Professional Series TriTech Motion Detectors

www.boschsecurity.com

BOSCH
Invented for life



- 18 m x 25 m (60 ft x 80 ft) coverage, field selectable to 8 m x 10 m (25 ft x 33 ft)
- Sensor data fusion technology
- Tri-focus optics technology
- Range adaptive radar
- Microwave anti-mask

The ISC-PDL1-W18x Professional Series TriTech Detectors are exceptionally suited for commercial indoor applications. Sensor data fusion technology ensures that the detectors send alarm conditions based on precise information. Tri-focus optics eliminate coverage gaps and respond efficiently to intruders. The powerful combination of unique features in the Professional Series delivers superior catch performance and virtually eliminates false alarms.
The self-locking two-piece enclosure, built-in bubble level, flexible mounting height, and three optional mounting brackets simplify installation and reduce service time.

Functions

Sensor Data Fusion Technology
Sensor data fusion technology is a unique feature that uses a sophisticated software algorithm to gather signals from five sensors: two pyroelectric sensors, range adaptive radar, a room temperature sensor, and a white light level sensor. The microcontroller analyzes and compares the sensor data to make the most intelligent alarm decisions in the security industry.

Tri-focus Optics Technology
Tri-focus optics technology uses optics with three specific focal lengths: long-range coverage, middle-range coverage, and short-range coverage. The detector applies the three focal lengths to 86 detection zones, which combine to make 11 solid curtains of detection. Tri-focus optics technology also includes two pyroelectric sensors, which deliver twice the standard optical gain. The sensors process multiple signals to deliver precise performance virtually free of false alarms.

Range Adaptive Radar
The microwave transceiver automatically adjusts its detection thresholds based on input from the PIR sensors. Integrating the target audience distance information from the PIR significantly reduces false alarms from the microwave Doppler radar.

Microwave Anti-mask
The detector sends a supervision-trouble signal if microwave reflective material is placed within 30.5 cm (1 ft) of the detector.

Supervised Microwave and PIR
The detector provides single technology coverage if the microwave subsystem fails.

Active White Light Suppression
An internal light sensor measures the level of light intensity directed at the face of the detector. Sensor data fusion technology uses this information to eliminate false alarms from bright light sources.

Field Selectable Coverage (18 m x 25 m or 8 m x 10 m)
Installers can use a DIP switch to select 18 m x 25 m or 8 m x 10 m (60 ft x 80 ft or 25 ft x 33 ft) coverage.

Dynamic Temperature Compensation
The detector automatically adjusts PIR sensitivity to identify human intruders at critical temperatures. Dynamic temperature compensation detects human body heat accurately, avoids false alarms, and delivers consistent catch performance at all operating temperatures.

Cover and Wall Tamper Switch
When an intruder removes the cover or attempts to separate the detector from the wall, a normally-closed contact opens to alert the control panel.

Self-adjusting LED
The LED brightness adjusts automatically to the surrounding light level. A blue light-emitting diode (LED) indicates dual alarms and activates during a walk test. A yellow LED indicates microwave detection, and a red LED indicates PIR detection.

Remote Walk Test LED
Users can type a command through a keypad, a control center, or programming software to remotely enable or disable the walk test LED. Users can locally enable or disable the walk test LED through the DIP switch.

Alarm Memory
Alarm memory flashes the alarm LED to indicate stored alarms for use in multiple unit applications. A switched voltage from the control panel controls the alarm memory.

Solid State Relays
Solid state relays send silent alarm output signals to provide a higher level of security and reliability. An external magnet does not activate the relay. The solid state relay uses less current than a mechanical relay, providing longer standby capacity during a power loss.

Draft, Insect, and Small Animal Immunity
The sealed optic chamber provides immunity to drafts and insects, reducing false alarms. Small animal immunity reduces false alarms caused by animals less than 4.5 kg (10 lb), such as rodents.

Remote Self Test
A remote self test initiates when the walk test input switches to its true state. The alarm relay and alarm LED activate for four seconds following a successful test. The trouble relay activates, and the alarm LED flashes following a failed test.

Input Power Supervision
When the power is lower than 8 V, a low input power trouble condition activates the trouble relay and causes the LED to flash. The trouble condition clears automatically when power reaches or exceeds 8 V.

Trouble Memory
When the walk test input switches to its true state for less than two seconds, LED flashes to indicate the most recent trouble condition. If there is no trouble in memory, the LED does not flash. After twelve hours, or after the detector receives a second walk test pulse for two seconds or less, the LED stops flashing and the trouble memory clears.

Cloak and Camouflage Detection Technology
Cloak and Camouflage Detection Technology (C^2DT) maximizes catch performance against intruders attempting to cover their infrared signal.


Certifications and approvals

The detectors are designed to also comply with the requirements of:


Australia C-Tick

Region	Regulatory compliance/quality marks	
Australia	SCEC	[ISC-PDL1-W18G, ISC-PDL1-WA18G]
USA	UL	[ISC-PDL1-W18G]
	UL	UL 639 - Standard for Intrusion Detection Units
	FCC	[ISC-PDL1-W18G]
Canada	IC	[ISC-PDL1-W18G]
China	CCC	2009031901000559 [ISC-PDL1-W18G-CHI]
Brazil	ANATEL	[ISC-PDL1-W18G]

Installation/configuration notes



Long-range Coverage 18 m x 25 m (60 ft x 80 ft)



Selectable Short-range Coverage 8 m x 10 m (25 ft x 33 ft)

Mounting

The recommended mounting height is 2 m to 3 m (7 ft to 10 ft) with no adjustments required.
Mount the motion detector level, both horizontally and vertically.
Mounting options:

- On a flat wall (surface, semi-flush), with the optional B335-3 Swiveling low-profile mount, or with the optional B328 Gimbal-mount Bracket
- In a corner (the junction of two perpendicular walls)
- On the ceiling with the optional B338 Universal Ceiling-mount Bracket

Wiring Considerations

Recommended wire size is 0.2 mm^2 to 1 mm^2 (26 AWG to 16 AWG).

Technical specifications

Electrical

Power Requirements	
Voltage (Operating):	9 VDC to 15 VDC
Current (Maximum):	< 25 mA
Current (Standby):	13 mA
Outputs	
Relay:	Solid state relay, normally-closed (NC) contacts power supervised. 3 W, 125 mA, 25 VDC, resistance < 10 Ω.
Tamper:	Normally-closed (NC) contacts (with cover on) rated at 25 VDC, 125 mA maximum. Connect tamper circuit to 24-hour protection circuit.
Trouble:	Solid-state relay normally-closed (NC) contacts.

Mechanical

Enclosure Design	
Color:	White
Dimensions:	136 mm x 69 mm x 58 mm (5.25 in. x 2.75 in. x 2.25 in.)
Material:	High-impact ABS plastic
Indicators	
Alarm Indicator:	• Blue LED for TriTech alarms
	• Yellow LED for microwave detection
	• Red LED for PIR detection
Zones	
Zones:	86

Frequency Information	
Radio Frequency Interference (RFI) immunity:	No alarm or setup on critical frequencies in the range from 26 MHz to 1 GHz at 50 V/m.

Environmental

Relative Humidity:	0 to 95%, non-condensing
Temperature (Operating and Storage):	-29°C to +55°C (-20°F to +130°F) *For UL Certificated installations, 0°C to +49°C (+32°F to +120°F)*
Protection Rating:	IP41, IK04 (EN 60529, EN 50102)

Ordering information

ISC-PDL1-W18G Motion detector, 60ft (18m)
Provides PIR and microwave, 18 m x 25 m (60 ft x 80 ft) coverage. 10.525 GHz frequency.
Order number **ISC-PDL1-W18G**

ISC-PDL1-W18H Motion detector, 18m, 10.588GHz
Provides PIR and microwave, 18 m x 25 m (60 ft x 80 ft) coverage. 10.588 GHz frequency. For use in France and United Kingdom.
Order number **ISC-PDL1-W18H**

Accessories

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2018 | Data subject to change without notice
2607960459 | en, V40, 04. Jan 2018

ISN-CSD70 and ISN-CSD80 Compact Contacts

www.boschsecurity.com

BOSCH
Invented for life



- Closed loop
- Sensitive non-stick rhodium reed
- Bent long leads keep solder off the glass of the reed
- Two solder points on the wire
- Thick plastic shell resists crushing

The contacts are available in brown or white. All models have a rugged, one-piece construction that eliminates the need for extra donut adapters. The compact (stubby) design allows you to use the contact in smaller spaces, without paying for a miniature design. Use on steel doors in standard or tight-fitting applications.

Notice
The photograph shows model ISN-CSD80-W.

Certifications and approvals

UL and

Region	Certification	
Europe	CE	73/23/EEC and 93/68/EEC, EN50131: 1997, EN50131-6: 1997, EN60950: 2000, EN60335-1: 1994 +A1: 1996 Annex B
USA	UL	cULus: AMQV: Connectors and Switches (UL 634), AMQV7: Connectors and Switches Certified for Canada (ULC/ ORD-C634) [-CSD70 Series]
	UL	cULus: AMQV: Connectors and Switches (UL 634), AMQV7: Connectors and Switches Certified for Canada (ULC/ ORD-C634) [-CSD80 Series]

Installation/configuration notes

Compatibility Information
All contact models are compatible with control panel models that accept contact inputs.

Parts included

Quantity Per Package	Component
10	Contacts
10	Magnets

Technical specifications

Specifications for All Models

Gap Width:	38 mm (1.5 in.)
Wire Lead Type:	0.8 mm (0.029 in.) 22 AWG, 7 stranded
Wire Lead Length:	46 cm (18 in.) standard leads
Switch Configuration Type:	Single pole single throw (SPST)
Operating Temperature Range:	7.2°C to -95.56°C (-45°F to -140°F)

Specifications for ISN-CSD70-B/W Models

Contact Dimensions:	19 mm x 20.3 mm (0.75 in. x 0.80 in.)
Maximum Contact Resistance:	150 µΩ (micro-ohm)
Minimum Breakdown Voltage:	250 VDC
Insulation Resistance:	10^{10} Ω
Electrostatic Cap:	0.3 PF
Contact Capacity:	10 VAC
Maximum Conductive Current:	1.0 A
Maximum Voltage:	100 V

Specifications for ISN-CSD80-B/W Models

Contact Dimensions:	25 mm x 20 mm (1 in. x 0.80 in.)
Maximum Contact Resistance:	150 µΩ (micro-ohm)
Minimum Breakdown Voltage:	250 VDC
Insulation Resistance:	10^{10} Ω
Electrostatic Cap:	0.3 PF
Contact Capacity:	10 VAC
Maximum Conductive Current:	1.0 A
Maximum Voltage:	100 V

Package Information

ATTENTION! Each package contains ten contacts and ten magnets.

Ordering information

Brown Compact Contact with Standard Magnet (19 mm)
Brown recessed contact with 19 mm (0.75 in.) diameter. Includes a standard magnet. **Package contains ten contacts and ten magnets.**
Order number **ISN-CSD70-B**

White Compact Contact with Standard Magnet (19 mm)
White recessed contact with 19 mm (0.75 in.) diameter. Includes a standard magnet. **Package contains ten contacts and ten magnets.**
Order number **ISN-CSD70-W**

White Compact Contact with Standard Magnet (25 mm)
White recessed contact with 25 mm (1 in.) diameter. Includes standard magnet. **Package contains ten contacts and ten magnets.**
Order number **ISN-CSD80-W**

Represented by:

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn


America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com

© Bosch Security Systems 2013 | Data subject to change without notice
2646726155 | en, V1, 01. Oct 2013

B520 Auxiliary Power Supply Module

www.boschsecurity.com

BOSCH
Invented for life



- Provides up to 2A of 12V standby current for Fire or Burglar Applications (4A of Burglary alarm current)
- Supervises up to two 12v 7-18Ah batteries independently for up to 36AH of capacity
- Provides up to 80 hours of standby time
- Uses the Bosch standard TR1850 plug-in transformer
- Easy to read rotary switch addressing

The B520 Auxiliary Power Supply Module is a fully supervised, addressable SDI2 bus device that provides an integrated auxiliary power supply solution for Bosch control panels.

System overview

The B520 Auxiliary Power Supply Module is an auxiliary power supply expansion device that connects to compatible control panels through the SDI2 bus. This module is supervised and communicates back to the control panel all status changes.
Industrial, commercial, and institutional facilities are typical installations for the B520 module. The B520 rotary switches allow for ease of use in device addressing. The SDI2 Out terminals provide auxiliary power for SDI2 expansion devices such as keypads. The AUX PWR terminals provides added auxiliary power capabilities for additional devices such as PIR's.

Functions

Supervision Monitoring
The module monitors and communicates status information over the SDI2 bus for the following:

- Operation (Heartbeat)
- Battery 1 (BATT 1)
- Battery 2 (BATT 2)
- AC input power (AC)
- Battery OK
- Low Battery
- Missing Battery

Indicators

- Heartbeat [icon]: Blue LED flashing On and Off when system is operating normally. A steady On or Off LED indicates a system error. Triple flash indicates communication failure.
- BATT 1 LED: Green steady On LED indicates the battery status of BATT 1 is operating normally. Flashing indicates low battery. Triple flash indicates battery charger failure. Off LED indicates a missing battery.
- BATT 2 LED: Green steady On LED indicates the battery status of BATT 2 is operating normally. Flashing indicates low battery. Triple flash indicates battery charger failure. Off LED indicates a missing battery.
- AC LED: Green steady On LED indicates the AC power is operational. A pulsating LED (3 pulses per sec.) occurs when a battery test is being performed. Flashing indicates low or failed AC.

Battery Charging
Fully charged batteries, connected to the battery terminals, sustain power to the B520 in the event that the AC power fails.

If AC power fails (is absent, or low) on the B520, the B520 automatically switches from primary power (AC) to secondary power (battery). When AC power is present, the B520 performs periodic battery tests to ensure battery life and usability.

Certifications and approvals

Region	
US	UL 365 – Police Station Connected Burglar Alarm Units and Systems
	UL 609 – Local Burglar Alarm Units and Systems
	UL 636 – Holdup Alarm Units and Systems
	UL 864 – Control Units and Accessories for Fire Alarm Systems
	UL 985 – Household Fire Warning System Units
	UL 1023 – Household Burglar Alarm System Units
	UL 1076 – Proprietary Burglar Alarm Units and Systems
	UL 1610 – Central Station Burglar Alarm Units
	FCC Part 15 Class B
Canada	CAN/ULC S303 – Local Burglar Alarm Units and Systems
	CAN/ULC S304 – Signal Receiving Centre and Premise Alarm Control Units
	ULC-ORD C1023 – Household Burglar Alarm System Units
	ULC-ORD C1076 – Propriety Burglar Alarm Units and Systems
	ICES-003 – Digital Apparatus

Region	Certification	
USA	UL	20121010-S5579
	CSFM	see our website

Installation/configuration notes

Mounting Considerations

You can mount the B520 Auxiliary Power Supply Module in a variety of enclosures for optimal situations.

Mounting in the D8103 requires the addition on the B12 Mounting plate.

The D8103 enclosure supports up to two 12V, 18Ah batteries. The B10 supports either one 12V, 18Ah or up to two 12V, 7Ah batteries.

Wiring Considerations

The B520 connects to a control panel using the SDI2 IN connections (PWR, A, B, COM). Use 12 AWG to 22 AWG (1.5 mm to 0.6 mm) wires from the power supply to the control panel.

The B520 provides auxiliary power to expansion modules via the SDI2 OUT (PWR, A, B, COM), or AUX Power (AUX PWR) connections using the screw terminal strip, or by using the interconnect wiring connection. Use 12 AWG to 22 AWG (1.5 mm to 0.6 mm) wires from the module to the SDI2 expansion module(s).

Parts included

Quantity	Component
1	B520 Auxiliary Power Supply module
1	Hardware pack
1	Literature pack

B520 Kit, B10 Enclosure

Kit contents include:

- B520 Aux Power Supply
- TR1850 transformer
- B10 white enclosure

Order number: **B520-B**

B520 Kit, D8103 Enclosure

Kit contents include:

- B520 Aux Power Supply
- TR1850 transformer
- B12 mounting plate
- D8103 gray, steel enclosure

Order number: **B520-C**

Technical specifications

Properties

Board Dimensions	11.43 cm x 17.62 cm x 2.9 cm (4.5 in x 6.94 in x 1.15 in)
Maximum Distance – Wire Size	305 m (1000 ft) - 0.65 mm (22 AWG) 305 m (1000 ft) – 2 mm (18 AWG) Unshielded wire only
Compatibility	GV4 Series control panels (Up to 8 B520 Auxiliary Power Supply Modules per control panel) D8103 Enclosure B10 Large Control Panel Enclosure B12 Mounting Plate for the D8103 Enclosure D8108A Attack Enclosure D2203 Enclosure BATB-40 Enclosure AE1, AE2 Enclosures D8004 Transformer Enclosure*
B501-10	Interconnect cables (10 per pack)

*The D8004 Transformer Enclosure is required when the B520 and TR1850 (18 VAC, 50 VA) Transformer are used in UL 864 Fire, or Combination Burg and Fire applications.

Power Input

Transformer Power Supply	TR1850 (18 VAC, 50 VA) TR1850-CA (18 VAC, 50 VA) for Canada

Power Output

Current Available (Maximum)	2.0 A SDI2 Out and AUX Power (Combined) (up to 4.0 A of alarm current for Burglar Applications)
Current Reserved for Charging Batteries	150 mA
Current Drawn from the Panel	15 mA
Voltage (rated range)	11.5 to 12.2 VDC (special application)
Battery Configuration	Supports two*, separate 12 V sealed lead acid batteries (7-18 Ah) for up to 36 amp. *Battery 1 is required for normal operations. Battery 2 is optional.

Enclosure Battery Considerations

D8103	Holds up to two 18 Ah, or two 7 Ah batteries
B10	Holds up to one 18 Ah, or two 7 Ah batteries

Environmental Considerations

Operating Temperature	+32° to +120° F (0° to +49°C)
Storage Temperature	-4° to 140° F (-20° to +60° C)
Relative Humidity	5% to 93% at +32° (+90°F) non-condensing
Use	Intended for indoor use.

Ordering information

B520 Auxiliary Power Supply Module
Provides auxiliary power to 12VDC devices or to SDI2 modules.
Order number **B520**

Accessories

B10 Medium Control Panel Enclosure
White, steel enclosure. Accepts an optional lock and tamper switch. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in x 12.5 in x 3 in).
Order number **B10**

D2203 Enclosure
Gray steel enclosure. Accepts an optional lock and tamper switch. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in x 12.5 in x 3 in).
Order number **D2203**

D8103 Enclosure
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).
Order number **D8103**

D8108A Attack Resistant Enclosure
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes lock and key set. B520, B4512, and B5512 require the B12 mounting plate.
Order number **D8108A**

AE1 Standard Enclosure (Gray)
Standard gray enclosure with keyed lock. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in x 12.5 in x 3 in).
Order number **AE1**

AE2 Standard Enclosure (Red)
Standard red enclosure with keyed lock. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in. x 12.5 in. x 3 in.).
Order number **AE2**

D8004 Transformer Enclosure
For applications such as fire alarm that might require a transformer enclosure.
Order number **D8004**

B12 Mounting Plate for D8103 Enclosure
Required for mounting select control panels and other devices in D8103, D8108A, D8109, or BATB Battery Box enclosures.
Order number **B12**

TR1850 Transformer
For use in North America. Plug-in transformer with input: 120 VAC, 60 Hz, 0.50 A; output 18 VAC, 50 VA output.
Order number **TR1850**

D101 Lock and Key Set
Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.
Order number **D101**

ICP-EZTS Dual Tamper Switch
Combination tamper switch with a wire loop for additional tamper outputs.
Order number **ICP-EZTS**

BATB-40 Battery Box\Enclosure
The BATB-40 Battery Box holds two dry or wet cell batteries. The box can be used with fire alarm systems or intrusion systems.
Order number **BATB-40**

B520 Kit, B10 Enclosure
B520 Auxiliary Power Supply kit. Includes a TR1850 transformer and a B10 White, steel enclosure.
Order number **B520-B**

B520 Kit, D8103 Enclosure
B520 Auxiliary Power Supply kit. Includes a TR1850 transformer, a B12 mounting plate, and a D8103 Gray, steel enclosure.
Order number **B520-C**

Represented by:

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com

© Bosch Security Systems 2014 | Data subject to change without notice
2536892171 | en, V6, 04. Nov 2014

Date: Jun 12, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 12, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

SE-02
PO-P18-123

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 28 31 01 Fire Alarm System

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.



C3779

Job Name: IQALUIT WASTE WATER TREATMENT PLANT

Prop Number: **27-218-3016-000**

Customer: ARCTIC ELECTRICAL

PO Number: P18-123

Date: 2018/06/12

Section 28 31 01 Fire Alarm System

Chubb EDWARDS

28 31 01

LIFE SAFETY & INCIDENT MANAGEMENT

Intelligent Fire Alarm Systems

iO64, iO1000



FDNY
COA 6227

7165-1657:
0244

S3000

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 20, 2018
BY Chester Martinez, E.I.T.

Overview

EDWARDS brand intelligent life safety systems offer the power of high-end intelligent processing in configurations that deliver uncomplicated solutions for small to mid-sized applications. With intelligent detection, electronic addressing, automatic device mapping, optional Ethernet® connectivity, and a full line of easily-configured option cards and modules, these flexible systems offer versatility that benefits building owners and contractors alike.

The iO64 provides one Class A or Class B intelligent device loop that supports up to 64 device addresses, and two Class B Notification Appliance Circuits (NACs). Optional Class A device wiring is available with the use of a module.

The iO1000 provides one Class A or Class B intelligent device loop that supports up to 250 device addresses. Loop controller modules may be added in combination to expand total system capacity in 250-point increments to up to 1,000 device addresses. The iO1000 panel includes four NACs that may be wired for either Class A or Class B operation.

The RZI16-2 module adds even more capacity to iO installations by adding up to 16 conventional device circuits and two additional notification appliance circuits. This makes them an ideal retrofit solution that can accommodate new intelligent detectors, as well as existing conventional devices.

iO Series supports a wide range of high-end features, including:

- Signature Series intelligent modules, detectors, and bases
- R-Series remote annunciators
- SIGA-REL Releasing Modules
- Fully integrated CO detection using Signature Series detectors with or without audible signaling

Features

- Auto-programming speeds installation time
- Supports Signature Series intelligent modules and detectors
- Combines the Signature intelligent releasing module with Signature multisensor detectors for reliable fire suppression
- Form C contacts for alarm and trouble, Form A for supervisory
- Electronic addressing with automatic device mapping
- Optional Ethernet port for diagnostics, programming and a variety of system reports
- Two programmable switches with LEDs and custom labeling
- Supports Genesis horn silence over two wires, and UL 1971-compliant strobe synchronization
- Class B or Class A wiring
- Ground fault detection by module
- Supports up to eight serial annunciators, (LCD, LED-only, and graphic interface)
- Can use existing wiring for most retrofit applications
- Upload/download remotely or locally
- Two-level maintenance alert reporting
- Pre-alarm and alarm verification by point
- Adjustable detector sensitivity
- 4 x 20 character backlit LCD display
- Optional earthquake hardening: seismic Importance Factor 1.5
- Standalone operation
- Transmission test frequency by hour

Application

EDWARDS iO Series life safety systems are powerful intelligent solutions for small to mid-sized buildings. Advanced intelligent technology delivers the benefits of flexible system installation, while clean and easy-to-operate user interfaces make panel operation and system maintenance quick and intuitive.

The smart choice

Signature Series electronic addressing eliminates the tedium of setting dipswitches, and automatic device mapping ensures that each device resides on the system at its correct location. Meanwhile, innovative programming allows the designer to customize the system to precisely suit the needs of the building owner.

Reliability you can count on

The inherent fault-tolerant characteristics of Analog/Addressable Technology boosts the reliability of EDWARDS fire alarm systems. When combined with iO Series smoke and heat detectors, these systems deliver a level of dependability not previously available for small to mid-sized applications. All EDWARDS systems are built to exacting reliability benchmarks and meet international standards for quality, in addition to agency listings for dependability.

Clear-cut remote annunciation

Remote annunciation is a strong suit of the iO Series fire alarm systems. Up to eight annunciators can be installed on a single system. Compatible annunciators include a range of LED and LCD models that provide zone or point annunciation, as well as common control capabilities. iO control panels also supports graphic annunciation with optional RA Graphic Annunciator interface modules. Each interface provides common control and 32 LEDs.

28 31 01

Flexibility built right in

Two fully-programmable front panel switch/LED combinations provide an added measure of flexibility. Their slide-in labels take the mystery out of custom applications, and present a clean finished appearance.

Perfect for retrofits

EDWARDS iO Series control panels are particularly well-suited to retrofit applications. All connections are made over standard wiring – no shielded cable required. This means that in most situations existing wiring can be used to upgrade a legacy control panel to iO technology without the expense or disruption of rewiring the entire building. iO control panels also support the ingenious RZI16-2 Zone Module, which adds up to 16 conventional circuits and two NACs. This combination easily accommodates new intelligent detection alongside existing conventional circuits, making it an superior solution in the retrofit market.

Signals with a difference

iO system NACs are configurable to fully support the advanced signaling technology of EDWARDS Genesis and Enhanced Integrity notification appliances. These devices offer precision synchronization of strobes to UL 1971 standards. For Genesis devices, enabling this feature allows horns to be silenced while strobes on the same two-wire circuit continue to flash until the panel is reset.

A complete line of accessories

iO Series life safety systems are supported by a complete line of analog/addressable detectors, modules and related equipment. Consult the Ordering Information section for details.

Programming and remote diagnostics

EDWARDS iO Series life safety systems are simple to set up, yet offer advanced programming features that put these small building panels into a class of their own. The auto programming feature quickly gets the panel operational using factory default settings. Basic zone and point settings can be programmed through the front panel interface, so the system is up and running in no time.


For more advanced system configuration and correlation groups programming, iO Series systems interface to a PC running compatible iO-CU software. This option offers full system configuration in the familiar Windows® operating environment. Connection is made to a laptop through the panel's optional RS-232 communications port, which can also be used to connect a system printer.

Among the many innovative features of iO Series control panels is the optional network card. This module provides a standard 10/100 Base T Ethernet® network connection that permits access to the control panel from any remote location with the correct communications protocols. The connection can be used to download to the panel from the iO-CU, or upload and view system reports using the iO-CU.

Available system reports include:

- Correlation groups
- Device maintenance
- Internal status
- System status
- Dialer
- Device details
- History
- System configuration
- Walk test
- CO runtime

Dimensions



(1) Surface Mounting Holes
(2) Semi-flush mounting Holes
(3) Backbox with Door Attached
(4) Backbox with door and trim kit attached.

Panel dimensions, in (cm)


Model	D1*	D2	D3	D4	D5*	D6	D7	D8	D9
iO1000	28.0 (71.1)	3.85 (9.8)	9.0 (22.8)	22.0 (55.8)	15.75 (40.0)	10.25 (26.0)	4.4 (11.1)	28.2 (71.6)	2.7 (6.8)
iO64	21.5 (54.6)	3.85 (9.8)	7.5 (19.0)	15.5 (39.4)	14.25 (36.2)	10.25 (26.0)	4.5 (11.4)	21.7 (55.1)	2.7 (6.8)

** Add 1-1/2 in. (3.81 cm) to D1 and D5 dimensions for trim kit. The trim kit provides 0.75 inches (1.9 cm) of trim to the top, bottom, and sides of the backbox.*

System Layout


28 31 01

iO1000




Each iO1000 panel has room for up to two Signature loop controller modules in any combination of single or dual 250-device loops. iO1000 loops support 125 detectors and 125 modules.

iO64



Each iO64 panel ships with one Signature loop controller that supports 64 devices of any type. This panel's device capacity cannot be expanded.

Panel Layout




1 Transformer
2 Main AC wiring block & fuse holder
3 RS-232 card connector (J3)
4 Dialer card connection (J8)
5 Ethernet card connector (J1)
6 Main circuit board
7 Panel backbox enclosure
8 Operator interface
9 SLC card connector (J7)
10 Class A card connector (J2)
11 Tie wrap mounts
12 LED expander connector (J6)
13 Standby batteries

28 31 01

Signature device loop

The system provides one Signature device loop circuit with a total capacity of 125 detectors and 125 module addresses. The loop circuit is supervised for opens, shorts, and grounds.


Circuit specifications	iO1000	iO64
Device loops	One Class B or A loop, supporting 125 detectors and 125 modules. Expandable to four loops.	One Class B or A loop, supporting 64 devices of any kind.
Communication line voltage	Maximum 20 V peak-to-peak	
Circuit current	0.5 A max	
Circuit impedance	66Ω total, 0.5 µF, max	
Isolators	64 maximum	
Signal Synchronization	Supported on a system-wide basis (all device loops) when using a SIGA-CC1S or SIGA-MCC1S module and Genesis or Enhanced Integrity notification appliances.	



Notification appliance circuits (TB2)

iO1000 control panels come equipped with four notification appliance circuits. iO64 control panels come with two NACs. Each circuit can be individually configured for continuous, temporal, synchronized, and coded output.

Specifications	iO1000	iO64
Circuit Type	4 Class B or 2 Class A	2 Class B or 2 Class A with SA-CLA module
Voltage	24 VFWR	
Current	6.0 A total, 2.5 A max. per circuit at 120/230 VAC 60 Hz. 5.0 A total, 2.5 A max. per circuit at 230 VAC 50 Hz.	3.75 A total, 2.5 A max. per circuit at 120/230 VAC 60 Hz. 3.0 A total, 2.5 A max. per circuit at 230 VAC 50 Hz.
Impedance	26 Ω total, 0.35 µF max	
EOLR	15 K Ω, ½ W	
Synchronization	Supported system-wide	




Marking indicates output signal polarity when the circuit is active. Polarity reverses when the circuit is not active. Wire notification appliances accordingly. Notification appliance polarity shown in active state.

Auxiliary & smoke power outputs (TB3)

The control panel provides two auxiliary power outputs that can be used for powering ancillary equipment such as remote annunciators and two wire smoke detectors. Aux 2 can be software selected to operate continuously. The circuit is supervised for shorts and grounds.

Circuit specifications	
Circuit voltage range	21.9 to 28.3 V
Resettable circuit (Aux power 2)	24 VDC nominal at 500 mA
Continuous circuit (Aux power 1)	24 VDC nominal at 500 mA. Use this circuit for powering two-wire smoke detectors.

Note: Any current above 0.5 amp connected to both Aux 1 and 2 will reduce the total available NAC power by that amount.



(1) Trouble
(2) Supervisory
(3) Alarm
(4) Smoke/Aux

Alarm, trouble, and supervisory relay (TB3)

The trouble relay is normally-open, held closed, and opens on any trouble event or when the panel is de-energized. The supervisory relay is normally-open, and closes on any supervisory event. The alarm relay changes over on any alarm event.

Relay specifications

	Alarm	Trouble	Supervisory
Type	Form C		Form A
Voltage	24 VDC at 1 A resistive	24 VDC at 1 A resistive	

Relay circuits can only be connected to power-limited sources.


Annunciator loop (TB4)

The control panel provides a connection for up to eight serially driven and supervised remote annunciators.


Circuit specifications

Device loops	Class B (Style Y) or Class A (Style Z)
Circuit voltage	2.55 V
Circuit current	30 mA max
Circuit impedance	Up to 8 annunciators or 4000 feet

Class B



Class A



Option Cards

28 31 01

EDWARDS iO Series panels are supported by a complete line of modules and related equipment that enhance performance and extend system capabilities. Option cards plug directly into the control panel main circuit board or are connected to it with a ribbon cable. After installation, terminals remain accessible. The cabinet provides ample room for wire routing, keeping wiring neat at all times.


Single and Dual Loop Controller Cards

The iO-SDC1 is a single loop controller card that can be used with the iO64 as a replacement for the standard 64-point loop, or with the iO1000 as a 250-point expansion module.

The iO-SDC2 is a 500-point dual loop controller card for the iO1000 that provides two SLC circuits, each with 125 detector addresses and 125 module addresses.

Specifications	iO-SDC1	iO-SDC2
Device Addresses	iO1000: one loop, 250 device addresses iO64: 64 addresses	iO1000: two loops, 500 device addresses
Wiring	Class B or Class A	
Operating Voltage	24 VDC	
Operating Current (fully loaded loop)	Standby: 55 mA Alarm: 80 mA	Standby: 45 mA Alarm: 70 mA
Note: These ratings do not include the use of two-wire smoke modules.		
Communication Line Voltage	Max. 20.6 V peak-to-peak	
Terminal Rating	12 to 18 AWG (0.75 to 2.5 mm^2)	
Circuit Current	0.5 A max.	
Max total loop resistance	66 Ω	
Max total loop capacitance	0.5 µF	
Isolators	64 isolators maximum per loop (total both isolator bases and modules)	
Ground Fault Impedance	0 to 5 kΩ	
Operating Environment	32 to 120°F (0 to 49°C) 0 to 93% noncondensing at 90°F (32°C)	

SA-ETH Ethernet Interface Card




The SA-ETH card provides a standard 10/100 Base T Ethernet network connection for connecting to an intranet, a local network, or the Internet. The card can be used to download configuration programming from the iO-CU to the panel.

The Ethernet card is installed on the plastic assembly and connects to the main circuit board via a ribbon cable.

SA-ETH specifications	
Ethernet	10/100 Base T
Operating environment	
Temperature	32 to 120°F (0 to 49°C)
Humidity	0 to 93% RH, noncondensing at 90°F (32°C)

RZI16-2 Remote Zone Interface Module



The RZI16-2 Addressable Remote Zone Interface Module is an addressable device that provides connections for sixteen Class B Initiating Device Circuits and two Class B Supervised Output Circuits. The inputs and outputs can be configured individually for several device types.


It requires 18 consecutive addresses on the Signaling Line Circuit (SLC). Addresses are assigned electronically. There are no address switches to set.

The RZI16-2 incorporates two 8-segment DIP switches that are used to select the Alarm or Supervisory default device type for each of the 16 IDC circuits. The module also includes one 4-segment DIP switch used to select the default Relay or NAC output device type. Device types other than the default are accomplished through programming.

RZI16-2 Specifications	
Voltage	
24V/Aux nominal:	24 VDC
Supervisory current:	250 mA at 24 VDC nominal
Alarm Current	1000 mA
24V/Aux minimum:	18.4 VDC
24V/Aux maximum:	26.4 VDC
NAC1, NAC2 nominal:	24 VDC
Current	
Standby current for 4.7 k EOL (U.S.)	4.8 mA/ circuit
Standby current for 3.9 k EOL (Canada)	5.7 mA/ circuit
Alarm current at nominal voltage	31.1 mA/ circuit
Relay outputs	
Quantity	2
Type Rating (pilot duty)	Programmable 24 VDC at 2.5 A
Input circuit wiring resistance	25 Ω per wire
Initiating device circuits	
Quantity	16
EOL resistor	4.7 kΩ (U.S.); 3.9 kΩ Canada
Zone voltage	22.78 V for 4.7 kΩ (U.S.) 22.08 V for 3.9 kΩ (Canada)
Alarm current	31.1 mA/ channel at nominal voltage
Alarm impedance range	< 680 Ω
Trouble impedance range	> 5.55 kΩ
Supervised output circuits	
EOL resistor	15 kΩ
Quantity	2
Short circuit detection	< 2.6 kΩ
Open circuit detection	> 61.9 kΩ
Contact ratings	24 VDC at 2.5 A (5 A for two NACs)
Compatible cabinets	MFC(A), iO1000, APS

SA-DACT Dialer

The SA-DACT provides communications between the control panel and the central station over a telephone line system. It transmits system status changes (events) to a compatible digital alarm communicator receiver over the public switched telephone network. The dialer is capable of single, dual, or split reporting of events to two different account and telephone numbers. The modem feature of the SA-DACT can also be used for uploading and downloading panel configuration, history, and current status to a PC running the iO-CU.



The dialer phone lines connect to connectors on the dialer's main circuit board. Phone line 1 connects to connector J4 and phone line 2 connects to connector J1.

The SA-DACT queues messages and transmits them based on priority (alarm, supervisory, trouble, and monitor). Activations are transmitted before restorations.


The SA-DACT is installed on the plastic assembly and connects to the main circuit board via a ribbon cable.

SA-DACT specifications	
Phone line type	One or two loop-start lines on a public, switched network
Phone line connector	RJ-31/38X (C31/38X)
Communication formats	Contact ID (SIA DC-05)
Operating environment	
Temperature	32 to 120°F (0 to 49°C)
Humidity	0 to 93% RH, noncondensing at 90°F (32°C)

Compatible DACRs		
Receiver	**Models**	**Formats**
Ademco	685	Contact ID
FBII	CP220	Contact ID
Osborne-Hoffman	OH 2000	Contact ID
Bosch	D6600	Contact ID
Silent Knight	9800	Contact ID
Sur-Gard	SG-MLR1, MLR2	Contact ID

SA-232 RS-232 interface

The SA-232 card provides an RS-232 interface with iO panels. It can be used for connecting a printer to the control panel to print system events. The card also can be used for connecting a computer to download a configuration program from the iO-CU to the control panel.



The RS-232 card is installed on the plastic assembly and connects to the main circuit board via a ribbon cable.

SA-232 specifications	
Operating voltage	Standard EIA-232
Terminal rating	12 to18 AWG (0.75 to 2.5 sq mm)
Operating environment	
Temperature	32 to 120°F (0 to 49°C)
Humidity	0 to 93% RH, noncondensing at 90°F (32°C)


SA-CLA Class A Module (iO64 only)

The SA-CLA card provides Class A capability for NAC wiring. Its terminal block provides the wiring connection for NAC return wiring. The card is required for annunciator Class A wiring even though this wiring does not return to the SA-CLA card. The SA-CLA is compatible with iO64 control panels only. iO1000 panels are Class A Ready. The SA-CLA is installed directly to the control panel circuit board using its plastic standoffs and plug connection.

SA-CLA specifications	
Operating voltage	24 VFWR
Operating current	3.75 A FWR total at 120/230 VAC 60 Hz 3.0 A FWR total at 230 VAC 50 Hz 2.5 A max per circuit
Circuit impedance	26 ohms, 0.35uF
Terminal rating	12 to18 AWG (0.75 to 2.5 sq mm)
Operating environment	
Temperature	32 to 120°F (0 to 49°C)
Humidity	0 to 93% RH, noncondensing at 90°F (32°C)

D16L-iO LED Display Expander (iO1000 only)

The D16L-iO LED Display Expanders provide LED annunciation for up to 16 zones. It provides two LEDs for each zone. Two D16L-iO LED display expanders can be installed in each iO1000 panel.



(1) LED 1
(2) LED 2
(3) LED Expander 1
(4) LED Expander 2
(5) Alarm/non-alarm and trouble zone LEDs

Specifications

	iO64	iO1000
Device loops	1 loop Class B or Class A (Styles 4, 6, 7) supporting up to 64 device addresses (any combination of detectors and modules) Maximum T-taps: 63 (each device can be on its own branch)	1 loop, expandable to 4, Class A or B (Styles 4, 6, 7), each loop supporting up to 250 device addresses (125 detectors and 125 modules max.). Addresses 1 to 125 are for detectors and addresses 126 to 250 are for modules Maximum T-taps/loop: 124
Notification appliance circuits	2 Class B (Style Y), Class A (Style Z) optional 3.75 A FWR total at 120/230 VAC 60 Hz 3.0 A FWR total at 230 VAC 50 Hz 2.5 A FWR each max. per circuit	4 Class B (Style Y) or 2 Class A (Style Z) 6.0 A FWR total at 120/230 VAC 60 Hz 5.0 A FWR total at 230 VAC 50 Hz 2.5 A FWR each max. per circuit
Primary power	120 VAC, 60 Hz, 1.3 A max. 230 VAC, 50-60 Hz, 0.62 A max.	120 VAC, 60 Hz, 2.0 A max. 230 VAC, 50-60 Hz, 0.97 A max.
Base panel current standby	155 mA	172 mA
Base panel current alarm	204 mA	267 mA
Input zones	16 max.	32 max.
Remote annunciator	8 drops max., RS-485 Class B, Class A is optional Data line length: 4,000 ft. (1,219 m)	8 drops max., RS-485 Class A or B Data line length: 4,000 ft. (1,219 m)
Operating voltage	24 VDC panel	
Auxiliary power output circuit	Aux power 1: 500 mA, 24 VDC Aux power 2: 500 mA, 24 VDC (1 A possible if you reduce total available NAC power by 500 mA) Output: 28.3 to 21.9 VDC, special application *Note: For a list of compatible devices, see the iO64 and iO1000 Series Compatibility List (P/N 3102353-EN)*	
Loop circuit	Maximum loop resistance: 66 Ω Maximum loop capacitance: 0.5 µF Communication line voltage: Maximum 20.6 V peak-to-peak Operating current (fully loaded loop) Stand by: 55 mA/45 mA Alarm: 125 mA/115 mA (not including two-wire smoke modules) Circuit current: 0.5 A max. Style 4, 6, and 7 wiring Max. resistance between isolators: Limited only by overall wire run lengths 64 isolators maximum per loop (total both isolator bases and modules)	
Batteries	Type: Sealed lead acid Voltage: 24 VDC Charging current: 2.47 A max. Amp hour capacity: 26 Ah Standby operation: 24 hour or 60 hour Placement: Up to two 10 Ah batteries will fit in the iO64 control panel cabinet and two 18 Ah batteries will fit in the iO1000 control panel cabinet. If larger batteries are required, use an EDWARDS battery cabinet.	
SA-DACT dialer	Phone line type: One or two loop-start lines on a public, switched network Phone line connector: RJ-31/38X (C31/38X) Communication formats: Contact ID (SIA DC-05) Operating current Standby/Alarm: 41 mA Max.: 100 mA FCC registration number: GESAL01BSADACT Industry Canada Registration number: 3944A-SADACT Ringer equivalence number: 0.1B	
Ground fault impedance	0 to 5 kΩ	
Alarm contact	Form C N.O. 24 VDC at 1 A (resistive load)	
Trouble contact	Form C 24 VDC at 1 A (resistive load)	
Supervisory contact	Form A N.O. 24 VDC at 1 A (resistive load)	
Environmental	Temperature: 0 to 49°C (32 to 120°F) Relative humidity: 0 to 93% noncondensing	
Terminal rating	All terminals rated for 12 to 18 AWG (0.75 to 2.5 mm^2)	

EDWARDS
United Technologies
LIFE SAFETY & INCIDENT MANAGEMENT

Contact us...

Email: edwards.fire@fs.utc.com
Web: *Edwards-fire.com*

EDWARDS is a UTC brand.
1016 Corporate Park Drive
Mebane, NC 27302

© 2016 United Technologies Corporation.
All rights reserved.

Ordering Information

28 31 01

Part	Description
iO1000 Fire Alarm Systems	
IO1000G	Four loop system with one 250-point loop installed. 110v, gray door.
IO1000G-2	Four loop system with one 250-point loop installed. 230v, gray door.
IO1000G-2-PG	Four loop system with one 250-point loop installed. 230v, gray door, Portuguese.
IO1000G-2-SP	Four loop system with one 250-point loop installed. 230v, gray door, Spanish.
IO1000G-CA	Four loop system, one 250-point loop installed. 110v, gray door, LED strips, Canada.
IO1000GD	Four loop system, one 250-point loop installed. 110v, gray door, with dialer.
IO1000G-F	Four loop system, one 250-point loop. 110v, gray door, LED strips, French Canada.
IO1000G-PG	Four loop system with one 250-point loop installed. 110v, gray door, Portuguese.
IO1000G-SP	Four loop system with one 250-point loop installed. 110v, gray door, Spanish.
IO1000R	Four loop system with one 250-point loop installed. 110v, red door.
IO1000R-2	Four loop system with one 250-point loop installed. 230v, red door.
IO1000RD	Four loop system, one 250-point loop installed. 110v, red door, with dialer.
SA-TRIM2	iO1000 Flush mount trim, black.
iO64 Fire Alarm Systems	
IO64G	One loop system with one 64-point loop installed. 110v, gray door.
IO64G-2	One loop system with one 64-point loop installed. 230v, gray door.
IO64G-2-PG	One loop system with one 64-point loop installed. 230v, gray door, Portuguese.
IO64G-2-SP	One loop system with one 64-point loop installed. 230v, gray door, Spanish.
IO64GD	One loop system, one 64-point loop installed. 110v, gray door, with dialer.
IO64GL	One loop system, one 64-point loop installed. 110v, gray door, English Canada.
IO64GL-F	One loop system, one 64-point loop installed. 110v, gray door, French Canada.
IO64G-PG	One loop system with one 64-point loop installed. 110v, gray door, Portuguese.
IO64G-SP	One loop system with one 64-point loop installed. 110v, gray door, Spanish.
IO64R	One loop system with one 64-point loop installed. 110v, red door.
IO64R-2	One loop system with one 64-point loop installed. 230v, red door.
IO64RD	One loop system, one 64-point loop installed. 110v, red door, with dialer.
SA-TRIM1	iO64 Flush mount trim, black
Option Cards	
iO-SDC1	Expansion module, one 250-device loop.
iO-SDC2	Expansion module, two 250-device loops, 500 devices total. For iO1000 only.
RZI16-2	Remote Zone Interface Module. 16 Class B IDCs, 2 Class B Output. Includes bracket.
SA-DACT	Dual Line Dialer/Modem, supports Contact ID, mounts in cabinet on base plate.
SA-232	RS-232 Serial Port for connection to printers & computers, mounts in cabinet.
SA-ETH	Ethernet Port, Slave, mounts in cabinet on base plate.
SA-CLA	Class A adapter module. Provides Class A capacity on NACs. Mounts in cabinet on main board. iO64 systems only.
D16L-iO-2	LED Annunciator module, 16 X 2-LED zones (4 programmable for sup). Mounts in cabinet to right of LCD display for zones 17-32. For iO1000 only.
D16L-iO-1	LED Annunciator module, 16 X 2-LED zones (4 programmable for sup). Mounts in cabinet to left of LCD display for zones 1-16. For iO1000 only.
D8RY-iO-2	***Canada only:*** LED Annunciator module, two LEDs per zone, 16 zones (4 alarm only, 8 supervisory only, 4 alarm or supervisory). Mounts in cabinet. For iO1000 only.
D8RY-iO-1	***Canada only:*** LED Annunciator module, two LEDs per zone, 16 zones (4 alarm only, 8 supervisory only, 4 alarm or supervisory). Mounts in cabinet. For iO1000 only.
Accessories	
CTM	City Tie Module. 2-gang. Connection to a local energy fire alarm box.
MFC-A	Multifunction Fire Cabinet, 8" x 14" x 3.5" - red.
SIGA-REL	Releasing Module
PT-1S	System Printer
BC-1	Battery Cabinet. 14.0" x 18.25" x 7.25". Holds two 12V24A batteries.
BC-1R	Battery Cabinet - Red. 14.0" x 18.25" x 7.25". Holds two 12V24A batteries.
BC-1EQ	Seismic hardening Kit for iO series panels. Includes battery hardening for BC-1 enclosure and components to harden panel internal components.
Programming Tools	
iO-CU	IO Series configuration and diagnostics utility.
260097	RS232 cable, 4 conductor, DB9 PC interface

EDWARDS
United Technologies
LIFE SAFETY & INCIDENT MANAGEMENT

28 31 01

Intelligent Heat Detector

SIGA-HRD



S853

Overview

The SIGA-HRD is an intelligent fixed temperature/rate-of-rise fire detector. It monitors the temperature of the surrounding air and analyzes the data from the sensor to determine whether to initiate an alarm. The rate-of-rise heat function quickly detects a fast, flaming fire. The fixed-temperature heat function detects fire when the air temperature near the detector exceeds the alarm point.

The SIGA-HRD brings advanced sensing technology to a practical design that increases efficiency, saves installation time, cuts costs, and extends property protection capabilities. Continuous self-diagnostics ensures reliability over the long-haul, while the latest thermister technology makes these detectors ideal whereever dependable heat detection is required.

Standard Features

Note: *Some features described here may not be supported by all control systems. Check your control panel's Installation and Operation Guide for details.*

- Next Generation Heat Sensing Technology
- 15 °F (9 °C) per minute rate-of-rise alarm point
- 135 °F (57 °C) fixed temperature alarm point
- Uses existing wiring
- Automatic device mapping
- Sensor Markings Provide Easy Testing Identification
- Up To 250 Total Signature Devices Per Loop
- Non-volatile memory
- Electronic addressing
- Bicolor (green/red) status LED
- Standard, relay, fault isolator, and audible mounting bases
- 50 foot (15.2 meter) spacing

Provide detectors approved for the location in which they are installed as per the electrical drawings.

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Application


The SIGA-HRD combination fixed temperature/rate-of-rise heat detector provides a 15 °F (9 °C) per minute rate-of-rise heat sensor for the detection of fast-developing fires, as well as a 135°F (57°C) fixed temperature sensor for slow building-fires. The heat sensor monitors the temperature of the air and determines whether an alarm should be initiated.

Compatibility

The SIGA-HRD detector is compatible only with the Signature Loop Controller.

Installation

Signature Series detectors mount to North American 1-gang boxes, 3-1/2 inch or 4 inch octagon boxes, and to 4 inch square electrical boxes 1-1/2 inches (38 mm) deep. They mount to European BESA and 1-gang boxes with 60.3 mm fixing centers. See mounting base installation and wiring for more information.



Sensing and reporting technology

The microprocessor in each detector provides additional benefits - Self-diagnostics and History Log, Automatic Device Mapping, and Fast, Stable Communication.

Self-diagnostics and History Log - Each Signature Series detector constantly runs self-checks to provide important maintenance information. The results of the self-check are automatically updated and permanently stored in the detector's non-volatile memory.

Automatic Device Mapping - The loop controller learns where each device's serial number address is installed relative to other devices on the circuit. The mapping feature provides supervision of each device's installed location to prevent a detector from being reinstalled (after cleaning etc.) in a different location from where it was originally.

Fast Stable Communication - On-board intelligence means less information needs to be sent between the detector and the loop controller. Other than regular supervisory polling response, the detector only needs to communicate with the loop controller when it has something new to report.

Accessories 28 31 01

Detector mounting bases have wiring terminals that are accessible from the "room-side" after mounting the base to the electrical box. The bases mount to North American 1-gang boxes and to 3½ inch or 4 inch octagon boxes, 1½ inches (38 mm) deep. They also mount to European BESA and 1-gang boxes with 60.3 mm fixing centers. The SIGA-SB4, SIGA-RB4, and SIGA-IB4 mount to North American 4 inch sq. electrical boxes in addition to the above boxes. They include the SIGA-TS4 Trim Skirt, which is used to cover the "mounting ears" on the base. The SIGA-AB4G mounts to a 4 inch square box only.


SIGA-AB4G/T/LF
Audible Base


SIGA-SB
Standard Base


SIGA-IB
Isolator Base


SIGA-RB
Relay Base


SIGA-LED
Remote LED

Remote LED SIGA-LED - The remote LED connects to the SIGA-SB or SIGA-SB4 Standard Base only. It features a North American size 1-gang plastic faceplate with a white finish and red alarm LED.

SIGA-TS4 Trim Skirt - Supplied with 4 inch bases, it can also be ordered separately to use with the other bases to help hide surface imperfections not covered by the smaller bases.

Sounder Bases - Signature Series sounder bases are designed for use where localized or group alarm signaling is required.

- **SIGA-AB4G** bases provide sounder capability to Signature Series to heat and smoke detectors. They are not intended for use with combination carbon monoxide detectors in Fire-plus-CO mode.
- **SIGA-AB4GT** bases provide sounder capability to Signature Series smoke and heat detectors, as well as carbon monoxide detectors when used with a SIGA-TCDR Temporal Pattern Generator.
- **SIGA-AB4G-LF** bases provide 520 Hz low frequency sounder capability to Signature Series smoke and heat detectors, as well as carbon monoxide detectors when used with a SIGA-TCDR Temporal Pattern Generator. The SIGA-AB4G-LF is suitable for applications requiring low frequency audible tones.

Warnings & Cautions

- This detector does not operate without electrical power. As fires frequently cause power interruption, discuss further safeguards with the local fire protection specialist.
- This detector does not sense fires in areas where heat cannot reach the detector. Heat from fires in walls, roofs, or on the opposite side of closed doors may not reach the detector.
- This heat detector by itself does not provide life safety protection Use this detector with ionization and/or photoelectric smoke detectors.
- This detector does not detect oxygen levels, smoke, toxic gases, or flames. Use this device as part of a broad-based life safety program which includes a variety of information sources pertaining to heat and smoke levels, extinguishment systems, visual and audible devices, and other safety measures.
- Independent studies indicate that heat detectors should only be used when property protection alone is involved. Never rely on heat detectors as the sole means of fire protection.


Typical Wiring

The detector mounting bases accept #18 AWG (0.75mm^2), #16 (1.0mm^2), #14 AWG (1.5mm^2), and #12 AWG (2.5mm^2) wire sizes. Sizes #16 AWG (1.0mm^2) and #18 AWG (0.75mm^2) are preferred for ease of installation.

Standard Detector Base, SIGA-SB, SIGA-SB4

This is the basic mounting base for EDWARDS Signature Series detectors. The SIGA-LED Remote LED is supported by this Base.

Term	Description
1	Not Used
2	DATA IN/OUT (+)
3	Not Used
4	DATA IN (-)
4	Remote LED (-)
5	Remote LED (+)
6	Not Used
7	DATA OUT (-)




Isolator Detector Base, SIGA-IB, SIGA-IB4

This base includes a built-in line fault isolator for use on Class A circuits. A detector must be installed for it to operate. The isolator base does not support the SIGA-LED Remote LED.

The isolator operates as follows:

- a short on the line causes all isolators to open within 23 msec
- at 10 msec intervals, beginning on one side of the Class A circuit nearest the loop controller, the isolators close to provide the next isolator down the line with power
- when the isolator next to the short closes, it reopens within 10 msec.

The process repeats beginning on the other side of the loop controller.




Term	Description
1	Not Used
2	DATA IN/OUT (+)
3	DATA IN (-)
4	Not Used
5	Not Used
6	DATA OUT (-)
7	Not Used

28 31 01

Relay Detector Base, SIGA-RB, SIGA-RB4

This base includes a relay. Normally Open or Normally Closed operation is selected during installation. The dry contact is rated for 1 amp (pilot duty) @ 30 Vdc. The relay's position is supervised to avoid accidentally jarring it out of position. The SIGA-RB can be operated as a control relay if programmed to do so at the control panel. The relay base does not support the SIGA-LED Remote LED.




CONTACT RATING
1.0 Amp @ 30 VDC
(Pilot Duty)

Term	Description
1	Normally Open
2	DATA IN/OUT (+)
3	Common
4	DATA IN (-)
5	Not Used
6	Normally-Closed
7	DATA OUT (-)

Audible Sounder Bases, Fire Mode

AB4GT, AB4G, AB4G-LF sounder bases



LIFE SAFETY & INCIDENT MANAGEMENT

Contact us...


Email: edwards.fire@fs.utc.com
Web: *Edwards-fire.com*

EDWARDS is a UTC brand.
1016 Corporate Park Drive
Mebane, NC 27302

© 2016 United Technologies Corporation.
All rights reserved.

28 31 01

Dimensions



Specifications

Operating voltage	15.20 to 19.95 VDC
Normal operating current	32 µA
Alarm current	32 µA
Vibration level	10 to 35 Hz, with an amplitude of 0.01 in.
Rate-of-rise rating	15°F/min (8°C/min)
Fixed temperature rating	135°F (57.2°C). Actual alarm point 129 to 141°F (53.9 to 60.6°C).
Maximum spacing	50 ft. (15.2 m) centers
Compatible bases	See Ordering Information
Compatible detector testers	Testifire 1000, Testifire 2000
Operating environment	32 to 100°F (0 to 38°C), 0 to 93% RH, noncondensing
Construction	High Impact Engineering Polymer, White
Storage temperature	-4 to 140°F (-20 to 60°C)
Agency Listings	CAN/ULC-S530, UL 521

Ordering Information

	Catalog Number	Description	Ship Wt. lbs (kg)
★	SIGA-HRD	Intelligent fixed temperature/Rate-of-rise heat detector	0.4 (0.16)
	Compatible Bases		
★	SIGA-SB	Detector Mounting Base - Standard	
	SIGA-SB4	4-inch Detector Mounting Base c/w Trim Skirt	
	SIGA-RB	Detector Mounting Base w/Relay	
	SIGA-RB4	4-inch Detector Mounting Base w/Relay, c/w Trim Skirt	0.2 (.09)
	SIGA-IB	Detector Mounting Base w/Fault Isolator	
	SIGA-IB4	4-inch Detector Mounting Base w/ Fault Isolator, c/w Trim Skirt	
	SIGA-LED	Remote Alarm LED (not for EN54 applications)	
	SIGA-AB4G	Audible (Sounder) Base for Fire Detectors	0.3 (0.15)
	SIGA-AB4G-LF	Low Frequency Audible (Sounder) Base for CO and Fire Detectors	0.3 (0.15)
	SIGA-AB4GT	Audible (Sounder) Base for CO and Fire Detectors	0.3 (0.15)
	SIGA-TS4	Trim Skirt (supplied with 4-inch bases)	0.1 (0.04)
	SIGA-TS	Trim Skirt - (optional for non 4-inch bases)	0.1 (0.04)
	SIGA-DMP	Detector Mounting Plate	3.0 (1.4)
	SIGA-RTA	Detector Removal Tool	

28 31 01

LIFE SAFETY & INCIDENT MANAGEMENT

Intelligent Smoke Detector

SIGA-PD



S853

Overview

The Signature Series SIGA-PD optical smoke detector brings advanced sensing technology to a practical design that increases efficiency, saves installation time, cuts costs, and extends life safety and property protection capabilities. Continuous self-diagnostics ensure reliability over the long-haul, while environmental compensation helps reduce maintenance costs.

Like all Signature Series detectors, the SIGA-PD is an intelligent device that gathers analog information from its optical sensor, converting this data into digital signals. To make an alarm decision, the detector's on-board microprocessor measures and analyzes sensor readings and compares this information to historical data. Digital filters remove signal patterns that are not typical of fires, thus virtually eliminating unwanted alarms.

Standard Features

Note: *Some features described here may not be supported by all control systems. Check your control panel's Installation and Operation Guide for details.*

- Next Generation Optical Smoke Sensing Technology
- Wide 0.53 to 3.94 %/ft. (1.7 to 12.35 %/m) smoke obscuration
- Uses Existing Wiring
- Automatic Device Mapping
- Up To 250 Total Signature Addresses Per Loop
- Two Levels of Environmental Compensation
- Two Levels of Dirty Detector Warning
- Twenty Pre-Alarm Settings
- Five Sensitivity Settings
- Non-Volatile Memory
- Electronic Addressing
- Identification of Dirty or Defective Detectors
- Automatic Day/Night Sensitivity Adjustment
- Bicolor (Green/Red) Status Led
- Standard, Relay, Fault Isolator, and Audible Mounting Bases
- Sensor Markings Provide Easy Testing Identification

Provide detectors approved for the location in which they are installed as per the electrical drawings.

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

Stantec

☐ REVIEWED

☑ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Application


The SIGA-PD detects extremely small particles of combustion and triggers an alarm at the first sign of smoke. Thanks to its high-performance forward-scattering reflective response technology, the photoelectric smoke sensor responds quickly and reliably to a wide range of fire types, especially slow burning fires fuelled by combustibles typically found in modern multi-use buildings.

Compatibility

The SIGA-PD detector is compatible only with the Signature Loop Controller.

Installation

Signature Series detectors mount to North American 1-gang boxes, 3-1/2 inch or 4 inch octagon boxes, and to 4 inch square electrical boxes 1-1/2 inches (38 mm) deep. They mount to European BESA and 1-gang boxes with 60.3 mm fixing centers. See mounting base installation and wiring for more information.



Sensing and reporting technology

The microprocessor in each detector provides additional benefits - Self-diagnostics and History Log, Automatic Device Mapping, and Fast, Stable Communication.

Self-diagnostics and History Log - Each Signature Series detector constantly runs self-checks to provide important maintenance information. The results of the self-check are automatically updated and permanently stored in the detector's non-volatile memory

Automatic Device Mapping - The loop controller learns where each device's serial number address is installed relative to other devices on the circuit. The mapping feature provides supervision of each device's installed location to prevent a detector from being reinstalled (after cleaning etc.) in a different location from where it was originally.

Fast Stable Communication - On-board intelligence means less information needs to be sent between the detector and the loop controller. Other than regular supervisory polling response, the detector only needs to communicate with the loop controller when it has something new to report.

Testing & Maintenance 28 31 01

Each detector automatically identifies when it is dirty or defective and causes a "dirty detector" message. The detector's sensitivity measurement can also be transmitted to the loop controller. A sensitivity report may be printed to satisfy NFPA sensitivity measurements, which must be conducted at the end of the first year and every two years thereafter.

The user-friendly maintenance program shows the current state of each detector and other pertinent messages. Single detectors may be turned off temporarily from the control panel. Availability of maintenance features is dependent on the fire alarm system used.

Accessories

Detector mounting bases have wiring terminals that are accessible from the "room-side" after mounting the base to the electrical box. The bases mount to North American 1-gang boxes and to 3½ inch or 4 inch octagon boxes, 1½ inches (38 mm) deep. They also mount to European BESA and 1-gang boxes with 60.3 mm fixing centers. The SIGA-SB4, SIGA-RB4, and SIGA-IB4 mount to North American 4 inch sq. electrical boxes in addition to the above boxes. They include the SIGA-TS4 Trim Skirt, which is used to cover the "mounting ears" on the base. The SIGA-AB4G mounts to a 4 inch square box only.


SIGA-AB4G/T/LF
Audible Base


SIGA-SB
Standard Base


SIGA-IB
Isolator Base


SIGA-RB
Relay Base


SIGA-LED
Remote LED

Remote LED SIGA-LED - The remote LED connects to the SIGA-SB or SIGA-SB4 Standard Base only. It features a North American size 1-gang plastic faceplate with a white finish and red alarm LED.

SIGA-TS4 Trim Skirt - Supplied with 4 inch bases, it can also be ordered separately to use with the other bases to help hide surface imperfections not covered by the smaller bases.

Sounder Bases - Signature Series sounder bases are designed for use where localized or group alarm signaling is required.

- **SIGA-AB4G** bases provide sounder capability to Signature Series to heat and smoke detectors. They are not intended for use with combination carbon monoxide detectors in Fireplus-CO mode.
- **SIGA-AB4GT** bases provide sounder capability to Signature Series smoke and heat detectors, as well as carbon monoxide detectors when used with a SIGA-TCDR Temporal Pattern Generator.
- **SIGA-AB4G-LF** bases provide 520 Hz low frequency sounder capability to Signature Series smoke and heat detectors, as well as carbon monoxide detectors when used with a SIGA-TCDR Temporal Pattern Generator. The SIGA-AB4G-LF is suitable for applications requiring low frequency audible tones.


Typical Wiring

The detector mounting bases accept #18 AWG (0.75mm^2), #16 (1.0mm^2), #14 AWG (1.5mm^2), and #12 AWG (2.5mm^2) wire sizes. Sizes #16 AWG (1.0mm^2) and #18 AWG (0.75mm^2) are preferred for ease of installation.

Standard Detector Base, SIGA-SB, SIGA-SB4

This is the basic mounting base for EDWARDS Signature Series detectors. The SIGA-LED Remote LED is supported by this Base.

Term	Description
1	Not Used
2	DATA IN/OUT (+)
3	Not Used
4	DATA IN (-)
4	Remote LED (-)
5	Remote LED (+)
6	Not Used
7	DATA OUT (-)




Isolator Detector Base, SIGA-IB, SIGA-IB4

This base includes a built-in line fault isolator for use on Class A circuits. A detector must be installed for it to operate. The isolator base does not support the SIGA-LED Remote LED.

The isolator operates as follows:

- a short on the line causes all isolators to open within 23 msec
- at 10 msec intervals, beginning on one side of the Class A circuit nearest the loop controller, the isolators close to provide the next isolator down the line with power
- when the isolator next to the short closes, it reopens within 10 msec.


The process repeats beginning on the other side of the loop controller.



Term	Description
1	Not Used
2	DATA IN/OUT (+)
3	DATA IN (-)
4	Not Used
5	Not Used
6	DATA OUT (-)
7	Not Used

Relay Detector Base, SIGA-RB, SIGA-RB4

This base includes a relay. Normally Open or Normally Closed operation is selected during installation. The dry contact is rated for 1 amp (pilot duty) @ 30 Vdc. The relay's position is supervised to avoid accidentally jarring it out of position. The SIGA-RB can be operated as a control relay if programmed to do so at the control panel. The relay base does not support the SIGA-LED Remote LED.




CONTACT RATING
1.0 Amp @ 30 VDC
(Pilot Duty)

Term	Description
1	Normally Open
2	DATA IN/OUT (+)
3	Common
4	DATA IN (-)
5	Not Used
6	Normally-Closed
7	DATA OUT (-)

Audible Sounder Bases, Fire Mode

AB4GT, AB4G, AB4G-LF sounder bases



Warnings & Cautions

- This detector does not operate without electrical power. As fires frequently cause power interruption, discuss further safeguards with the local fire protection specialist.
- This detector does not sense fires in areas where smoke cannot reach the detector. Smoke from fires in walls, roofs, or on the opposite side of closed doors may not reach the detector.
- Photoelectric detectors have a wide range of fire-sensing capabilities and are best suited for detecting slow, smoldering fires.
- In Canada, install according to CAN/ULC-S524 Standard for the Installation of Fire Alarm Systems, CSA C22.1 Canadian Electrical Code, and the local authority having jurisdiction.

LIFE SAFETY & INCIDENT MANAGEMENT


Contact us...

Email: edwards.fire@fs.utc.com
Web: *Edwards-fire.com*

EDWARDS is a UTC brand.
1016 Corporate Park Drive
Mebane, NC 27302

© 2016 United Technologies Corporation.
All rights reserved.

Dimensions



Specifications

Operating voltage	15.20 to 19.95 VDC
Normal operating current	32 µA
Alarm current	32 µA
Smoke Sensitivity Range	UL/ULC: 0.53 to 3.94 %/ft. (1.7 to 12.35 %/m) obscuration
Vibration level	10 to 35 Hz, with an amplitude of 0.01 in.
Air velocity	0 to 4,000 ft./min (0 to 20 m/s)
Wall mounting	12 in. (305 mm) max. from ceiling
Compatible bases	See Ordering Information
Compatible detector testers	Testifire 1000, Testifire 2000
Operating environment	32 to 120°F (0 to 49°C), 0 to 93% RH, noncondensing
Construction	High Impact Engineering Polymer, White
Storage temperature	-4 to 140°F (-20 to 60°C)
Environmental compensation	Automatic
Agency Listings	CAN/ULC-S529, UL 268, UL 268A

Ordering Information

	Catalog Number	Description	Ship Wt. lbs (kg)
★	SIGA-PD	Intelligent Optical Smoke Detector	0.4 (0.16)
	Accessories		
★	SIGA-SB	Detector Mounting Base - Standard	
	SIGA-SB4	4-inch Detector Mounting Base c/w Trim Skirt	
	SIGA-RB	Detector Mounting Base w/Relay	
	SIGA-RB4	4-inch Detector Mounting Base w/Relay, c/w Trim Skirt	0.2 (.09)
	SIGA-IB	Detector Mounting Base w/Fault Isolator	
	SIGA-IB4	4-inch Detector Mounting Base w/ Fault Isolator, c/w Trim Skirt	
	SIGA-LED	Remote Alarm LED (not for EN54 applications)	
	SIGA-AB4G	Audible (Sounder) Base for Fire Detectors	0.3 (0.15)
	SIGA-AB4G-LF	Low Frequency Audible (Sounder) Base for CO and Fire Detectors	0.3 (0.15)
	SIGA-AB4GT	Audible (Sounder) Base for CO and Fire Detectors	0.3 (0.15)
	SIGA-TS4	Trim Skirt (supplied with 4-inch bases)	0.1 (0.04)
	SIGA-TS	Trim Skirt - (optional for non 4-inch bases)	0.1 (0.04)
	SIGA-DMP	Detector Mounting Plate	3.0 (1.4)
	SIGA-RTA	Detector Removal Tool	
	SIGA-VA	Detector Cleaning Tool	

EST™
Life Safety & Communications

28 31 01

Input Modules

SIGA-CT1, SIGA-CT1HT, SIGA-CT2, SIGA-MCT2

STANTEC PROJECT #: 110126045 SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.



SIGA-MCT2



SIGA-CT1/2

MEA

Application Notes Available

Overview

The SIGA-CT1 Single Input Module, SIGA-CT1HT High Temperature Single Input Module and SIGA-CT2/SIGA-MCT2 Dual Input Modules are intelligent analog addressable devices used to connect one or two Class B normally-open Alarm, Supervisory, or Monitor type dry contact Initiating Device Circuits (IDC).

The actual function of these modules is determined by the "personality code" selected by the installer. This code is downloaded to the module from the Signature loop controller during system configuration.

The input modules gather analog information from the initiating devices connected to them and convert it into digital signals. The module's on-board microprocessor analyzes the signal and decides whether or not to input an alarm.

The SIGA-CT1, SIGA-CT1HT and SIGA-CT2 mount to standard North American 1-gang electrical boxes, making them ideal for locations where only one module is required. Separate I/O and data loop connections are made to each module.

The SIGA-CT1HT module operates at an expanded temperature range of 32 ºF to 158 ºF (0 ºC to 70 ºC) for those applications requiring more extreme environmental temperature variation.

The SIGA-MCT2 is part of the UIO family of plug-in Signature Series modules. It functions identically to the SIGA-CT2, but takes advantage of the modular flexibility and easy installation that characterizes all UIO modules. Two- and six-module UIO motherboards are available. All wiring connections are made to terminal blocks on the motherboard. UIO assemblies may be mounted in Edwards enclosures.

Standard Features

- **Multiple applications**
  Including Alarm, Alarm with delayed latching (retard) for waterflow applications, Supervisory, and Monitor. The installer selects one of four "personality codes" to be downloaded to the module through the loop controller.
- **SIGA-CT1HT rated for high temperature environments**
  Suitable for attic installation and monitoring high temperature heat detectors.
- **Plug-in (UIO) or standard 1-gang mount**
  UIO versions allow quick installation where multiple modules are required. The 1-gang mount version is ideal for remote locations that require a single module.
- **Automatic device mapping**
  Signature modules transmit information to the loop controller regarding their circuit locations with respect to other Signature devices on the wire loop.
- **Electronic addressing**
  Programmable addresses are downloaded from the loop controller, a PC, or the SIGA-PRO Signature Program/Service Tool. There are no switches or dials to set.
- **Stand-alone operation**
  The module makes decisions and inputs an alarm from initiating devices connected to it even if the loop controller's polling interrogation stops. (Function availability dependent upon control panel.)
- **Ground fault detection by address**
  Detects ground faults right down to the device level.

Signature Series Overview


The Signature Series intelligent analog-addressable system from Edwards Security is an entire family of multi-sensor detectors and mounting bases, multiple-function input and output modules, network and non-network control panels, and user-friendly maintenance and service tools. Analog information from equipment connected to Signature devices is gathered and converted into digital signals. An onboard microprocessor in each Signature device measures and analyzes the signal and decides whether or not to input an alarm. The microprocessor in each Signature device provides four additional benefits – Self-diagnostics and History Log, Automatic Device Mapping, Stand-alone Operation and Fast, Stable Communication.

Self-diagnostics and History Log – Each Signature Series device constantly runs self-checks to provide important maintenance information. The results of the self-check are automatically updated and permanently stored in its non-volatile memory. This information is accessible for review any time at the control panel, PC, or using the SIGA-PRO Signature Program/Service Tool.


Automatic Device Mapping –The Signature Data Controller (SDC) learns where each device's serial number address is installed relative to other devices on the circuit. The SDC keeps a map of all Signature Series devices connected to it. The Signature Series Data Entry Program also uses the mapping feature. With interactive menus and graphic support, the wired circuits between each device can be examined. Layout or "as-built" drawing information showing branch wiring (T-taps), device types and their address are stored on disk for printing hard copy.

Installation

SIGA-CT1, SIGA-CT1HT and SIGA-CT2: modules mount to North American 2½ inch(64 mm) deep 1-gang boxes and 1½ inch (38 mm) deep 4 inch square boxes with 1-gang covers and SIGA-MP mounting plates. The terminals are suited for #12 to #18 AWG (2.5 mm^2 to 0.75 mm^2) wire size.



SIGA-MCT2: mount the UIO motherboard inside a suitable Edwards enclosure with screws and washers provided. Plug the SIGA-MCT2 into any available position on the motherboard and secure the module to the motherboard with the captive screws. Wiring connections are made to the terminals on the motherboard (see wiring diagram). UIO motherboard terminals are suited for #12 to #18 AWG (2.5 mm^2 to 0.75 mm^2) wire size.



Electronic Addressing - The loop controller electronically addresses each module, saving valuable time during system commissioning. Setting complicated switches or dials is not required. Each module has its own unique serial number stored in its on-board memory. The loop controller identifies each device on the loop and assigns a "soft" address to each serial number. If desired, the modules can be addressed using the SIGA-PRO Signature Program/Service Tool.

Edwards recommends that this module be installed according to latest recognized edition of national and local fire alarm codes.

Application

The duty performed by the SIGA-CT1 and SIGA-CT2/MCT2 is determined by their sub-type code or "Personality Code". The code is selected by the installer depending upon the desired application and is downloaded from the loop controller.

One personality code can be assigned to the SIGA-CT1. Two personality codes can be assigned to the SIGA-CT2/MCT2. Codes 1, 2, 3 and 4 can be mixed on SIGA-CT2/MCT2 modules only. For example, personality code 1 can be assigned to the first address (circuit A) and code 4 can be assigned to the second address (circuit B).

NORMALLY-OPEN ALARM - LATCHING (Personality Code 1) - Assign to one or both circuits. Configures either circuit A or B or both for Class B normally open dry contact initiating devices such as Pull Stations, Heat Detectors, etc. An ALARM signal is sent to the loop controller when the input contact is closed. The alarm condition is latched at the module.

NORMALLY-OPEN ALARM - DELAYED LATCHING (Personality Code 2) - Assign to one or both circuits. Configures either circuit A or B or both for Class B normally-open dry contact initiating devices such as Waterflow Alarm Switches. An ALARM signal is sent to the loop controller when the input contact is closed for approximately 16 seconds. The alarm condition is latched at the module.

NORMALLY-OPEN ACTIVE - NON-LATCHING (Personality Code 3) - Assign to one or both circuits. Configures either circuit A or B or both for Class B normally-open dry contact monitoring input such as from Fans, Dampers, Doors, etc. An ACTIVE signal is sent to the loop controller when the input contact is closed. The active condition is not latched at the module.

NORMALLY-OPEN ACTIVE - LATCHING (Personality Code 4) - Assign to one or both circuits. Configures either circuit A or B or both for Class B normally open dry contact monitoring input such as from Supervisory and Tamper Switches. An ACTIVE signal is sent to the loop controller when the input contact is closed. The active condition is latched at the module.


Typical Wiring

28 31 01


Modules will accept #18 AWG (0.75mm²), #16 (1.0mm²), and #14AWG (1.50mm²), and #12 AWG (2.50mm²) wire sizes.

Note: Sizes #16 AWG (1.0mm²) and #18 AWG (0.75mm²) are preferred for ease of installation. See Signature Loop Controller catalog sheet for detailed wiring requirement specifications.

Initiating (Slave) Device Circuit Wire Specifications		
Maximum Allowable Wire Resistance	50 ohms (25 ohms per wire) per Circuit	
Maximum Allowable Wire Capacitance	0.1µF per Circuit	
For Design Reference:	**Wire Size**	**Maximum Distance to EOLR**
	#18 AWG (0.75 mm²)	4,000 ft (1,219 m)
	#16 AWG (1.00 mm²)	
	#14 AWG (1.50 mm²)	
	#12 AWG (1.50 mm²)	




SIGA-CT1, SIGA-CT1HT



SIGA-CT2

NOTES

1. Maximum 25 Ohm resistance per wire.
2. Maximum #12 AWG (2.5 mm²) wire; Minimum #18 AWG (0.75 mm2).
3. Refer to Signature controller installation sheet for wiring specifications.
4. Maximum 10 Vdc @ 350 µA
5. The SIGA-UIO6R and the SIGA-UIO2R do not come with TB14.
6. All wiring is supervised and power-limited.
7. These modules will not support 2-wire smoke detectors.



SIGA-MCT2

Warnings & Cautions

This module will not operate without electrical power. As fires frequently cause power interruption, we suggest you discuss further safeguards with your local fire protection specialist.

Compatibility

The Signature Series modules are compatible only with EST's Signature Loop Controller.

EDWARDS
A UTC Fire & Security Company

Detection & alarm since 1872

U.S.
T 888-378-2329
F 866-503-3996

Canada
Chubb Edwards
T 519 376 2430
F 519 376 7258

Southeast Asia
T : +65 6391 9300
F : +65 6391 9306

India
T : +91 80 4344 2000
F : +91 80 4344 2050

Australia
T +61 3 9239 1200
F +61 3 9239 1299

Europe
T +32 2 725 11 20
F +32 2 721 86 13

Latin America
T 305 593 4301
F 305 593 4300

utcfireandsecurity.com

© 2010 UTC Fire & Security.
All rights reserved.

28 31 01

Specifications

Catalog Number	SIGA-CT1HT	SIGA-CT1	SIGA-CT2	SIGA-MCT2
Description	Single Input Module		Dual Input Module	
Type Code	48 (factory set) Four sub-types (personality codes) are available		49 (factory set) Four sub-types (personality codes) are available	
Address Requirements	Uses One Module Address		Uses Two Module Addresses	
Operating Current	Standby = 250µA; Activated = 400µA		Standby = 396µA; Activated = 680µA	
Operating Voltage	15.2 to 19.95 Vdc (19 Vdc nominal)			
Construction	High Impact Engineering Polymer			
Mounting	North American 2½ inch (64 mm) deep one-gang boxes and 1½ inch (38 mm) deep 4 inch square boxes with one-gang covers and SIGA-MP mounting plates			UIO2R/6R/6 Motherboard
Operating Environment	32°F to 158°F (0°C to 70°C)	32°F to 120°F (0°C to 49°C)		
Storage Environment	-4°F to 140°F (-20°C to 60°C); Humidity: 0 to 93% RH			
LED Operation	On-board Green LED - Flashes when polled; On-board Red LED - Flashes when in alarm/active. Both LEDs - Glow steady when in alarm (stand-alone)			
Compatibility	Use with Signature Loop Controller			
Agency Listings	UL, ULC, MEA, CSFM			

Ordering Information

Catalog Number	Description	Ship Wt. lbs (kg)
SIGA-CT1	Single Input Module — UL/ULC Listed	0.4 (0.15)
SIGA-CT1HT	Single Input Module High Teperature Operation UL/ULC Listed	0.4 (0.15)
★ SIGA-CT2	Dual Input Module — UL/ULC Listed	0.4 (0.15)
SIGA-MCT2	Dual Input Plug-in (UIO) Module — UL, ULC Listed	0.1 (0.05)

Related Equipment		
27193-11	Surface Mount Box - Red, 1-gang	1.0 (0.6)
27193-16	Surface Mount Box - White, 1-gang	1.0 (0.6)
SIGA-UIO2R	Universal Input-Output Module Board w/Riser Inputs — Two Module Positions	0.32 (0.15)
SIGA-UIO6R	Universal Input-Output Module Board w/Riser Inputs — Six Module Positions	0.62 (0.28)
SIGA-UIO6	Universal Input-Output Module Board — Six Module Positions	0.56 (0.25)
MFC-A	Multifunction Fire Cabinet — Red, supports Signature Module Mounting Plates	7.0 (3.1)
SIGA-MB4	Transponder Mounting Bracket (allows for mounting two 1-gang modules in a 2-gang box)	0.4 (0.15)
SIGA-MP1	Signature Module Mounting Plate, 1 footprint	1.5 (0.70)
SIGA-MP2	Signature Module Mounting Plate, 1/2 footprint	0.5 (0.23)
SIGA-MP2L	Signature Module Mounting Plate, 1/2 extended footprint	1.02 (0.46)

EST™
Life Safety & Communications

28 31 01

Control Relay Modules

SIGA-CR, SIGA-MCR, SIGA-CRR, SIGA-MCRR



MEA

Overview

The Control Relay Module and the Polarity Reversal Relay Module are part of the Signature Series system. They are intelligent analog addressable devices available in either plug-in (UIO) versions, or standard 1-gang mount versions.

The SIGA-CR/MCR Control Relay Module provides a Form "C" dry relay contact to control external appliances such as door closers, fans, dampers etc. This device does not provide supervision of the state of the relay contact. Instead, the on-board microprocessor ensures that the relay is in the proper ON/OFF state. Upon command from the loop controller, the SIGA-CR/MCR relay activates the normally open or normally-closed contact.

The SIGA-CRR/MCRR Polarity Reversal Relay Module provides a Form "C" dry relay contact to power and activate a series of SIGA-AB4G Audible Sounder Bases. Upon command from the Signature loop controller, the SIGA-CRR reverses the polarity of its 24 Vdc output, thus activating all Sounder Bases on the data loop.

Standard-mount versions (SIGA-CR and SIGA-CRR) are installed to standard North American 1-gang electrical boxes, making them ideal for locations where only one module is required. Separate I/O and data loop connections are made to each module.


Plug-in UIO versions (SIGA-MCR and SIGA-MCRR) are part of the UIO family of plug-in Signature Series modules. They function identically to the standard mount versions, but take advantage of the modular flexibility and easy installation that characterizes all UIO modules. Two- and six-module UIO motherboards are available. All wiring connections are made to terminal blocks on the motherboard. UIO assemblies may be mounted in Edwards enclosures.

Standard Features


- **Provides one no/nc contact (SIGA-CR/MCR)**
  Form "C" dry relay contact can be used to control external appliances such as door closers, fans, dampers etc.
- **Allows group operation of sounder bases**
  The SIGA-CRR/MCRR reverses the polarity of its 24 Vdc output, thus activating all Sounder Bases on the data loop.
- **Plug-in (UIO) or standard 1-gang mount**
  UIO versions allow quick installation where multiple modules are required. The 1-gang mount version is ideal for remote locations that require a single module.
- **Automatic device mapping**
  Signature modules transmit information to the loop controller regarding their circuit locations with respect to other Signature devices on the wire loop.
- **Electronic addressing**
  Programmable addresses are downloaded from the loop controller, a PC, or the SIGA-PRO Signature Program/Service Tool; there are no switches or dials to set.
- **Intelligent device with microprocessor**
  All decisions are made at the module to allow lower communication speed with substantially improved control panel response time and less sensitivity to line noise and loop wiring properties; twisted or shielded wire is not required.
- **Ground fault detection by address**
  Detects ground faults right down to the device level.

Installation

SIGA-CR and SIGA-CRR: modules mount to North American 2½ inch (64 mm) deep 1-gang boxes and 1½ inch (38 mm) deep 4 inch square boxes with 1-gang covers and SIGA-MP mounting plates. The terminals are suited for #12 to #18 AWG (2.5 mm^2 to 0.75 mm^2) wire size.



SIGA-MCR and SIGA-MCRR: mount the UIO motherboard inside a suitable Edwards enclosure with screws and washers provided. Plug the module into any available position on the motherboard and secure the module to the motherboard with the captive screws. Wiring connections are made to the terminals on the motherboard (see wiring diagram). UIO motherboard terminals are suited for #12 to #18 AWG (2.5 mm^2 to 0.75 mm^2) wire size.



Electronic Addressing - The loop controller electronically addresses each module, saving valuable time during system commissioning. Setting complicated switches or dials is not required. Each module has its own unique serial number stored in its onboard memory. The loop controller identifies each device on the loop and assigns a "soft" address to each serial number. If desired, the modules can be addressed using the SIGA-PRO Signature Program/Service Tool.

Edwards recommends that this module be installed according to latest recognized edition of national and local fire alarm codes.

Application

The operation of Signature Series control relays is determined by their sub-type code or "Personality Code."

Personality Code 8: CONTROL RELAY (SIGA-CR/MCR) - Dry Contact Output. This setting configures the module to provide one Form "C" DRY RELAY CONTACT to control Door Closers, Fans, Dampers, etc. Contact rating is 2.0 amp @ 24 Vdc; 0.5 amp @ 120 Vac (or 220 Vac for non-UL applications). Personality Code 8 is assigned at the factory. No user configuration is required.

Personality Code 8: POLARITY REVERSAL RELAY MODULE (SIGA-CRR/MCRR). This setting configures the module to reverse the polarity of its 24 Vdc output. Contact rating is 2.0 amp @ 24 Vdc (pilot duty). Personality Code 8 is assigned at the factory. No user configuration is required.

Compatibility

The Signature Series modules are compatible only with EST's Signature Loop Controller.

Warnings & Cautions

This module will not operate without electrical power. As fires frequently cause power interruption, we suggest you discuss further safeguards with your local fire protection specialist.


Testing & Maintenance

The module's automatic self-diagnosis identifies when it is defective and causes a trouble message. The user-friendly maintenance program shows the current state of each module and other pertinent messages. Single modules may be turned off (deactivated) temporarily, from the control panel. Availability of maintenance features is dependent on the fire alarm system used. Scheduled maintenance (Regular or Selected) for proper system operation should be planned to meet the requirements of the Authority Having Jurisdiction (AHJ). Refer to current NFPA 72 and ULC CAN/ULC 536 standards.


Typical Wiring

Modules will accept #18 AWG (0.75mm²), #16 (1.0mm²), #14 AWG (1.50mm²) and #12 AWG (2.5mm²) wire sizes.

Note: Sizes #16 AWG (1.0mm²) and #18 AWG (0.75mm²) are preferred for ease of installation. See Signature Loop Controller catalog sheet for detailed wiring requirement specifications.



SIGA-CR Control Relay



SIGA-MCR Control Relay


Notes

1. Refer to Signature Loop Controller Installation Sheet for wiring specifications.
2. NFPA 72 requires that the SIGA-CR/SIGA-MCR be installed in the same room as the device it is controlling. This requirement may not apply in all markets. Check with your local AHJ for details.
3. The SIGA-UIO6R and the SIGA-UIO2R do not come with TB14.
4. The SIGA-UIO6 does not come with TB8 through TB13.
5. Supervised and power-limited.
6. If the source is nonpower-limited, maintain a space of 1/4 inch from power-limited wiring or use FPL, FPLP, FPLR, or an equivalent in accordance with the National Electrical Code.
7. Maximum #12 AWG (2.5mm²) wire. Min. #18 (0.75mm²).


Typical Wiring


Modules will accept #18 AWG (0.75mm²), #16 (1.0mm²), #14 AWG (1.50mm²) and #12 AWG (2.50mm²) wire sizes.


Note: Sizes #16 AWG (1.0mm²) and #18 AWG (0.75mm²) are preferred for ease of installation. See Signature Loop Controller catalog sheet for detailed wiring requirement specifications.



SIGA-MCRR







Notes

1. Refer to the Signature controller installation sheet for wiring.
2. One Pair of Wires (24 Vdc power).
3. One Pair of Wires (Signature Data).
4. Single Wire (24 Vdc power).
5. The SIGA-UIO6R and the SIGA-UIO2R do not come with TB14.
6. The SIGA-UIO6 does not come with TB8 through TB13.
7. Supervised and power-limited.
8. If the source is nonpower-limited, maintain a space of 1/4 inch from power-limited wiring or use FPL, FPLP, FPLR, or an equivalent in accordance with the National Electrical Code.
9. Maximum #12 AWG (2.5 mm²) wire; Minimum #18 AWG (0.75 mm²).
10. End-of-Line Relay must monitor and report power supply trouble to control panel.
11. Class B Data wiring may be “T-tapped.”

Specifications

28 31 01

Catalog Number	SIGA-CR	SIGA-MCR	SIGA-CRR	SIGA-MCRR
Description	Control Relay		Polarity Reversal Relay	
Type Code	Personality Code 8 (Factory Set)		Personality Code 8 (Factory Set)	
Address Requirements	Uses 1 Module Address			
Operating Current	Standby = 100µA Activated = 100µA			
Operating Voltage	15.2 to 19.95 Vdc (19 Vdc nominal)			
Relay Type and Rating	Form "C" 24 VDC = 2 amps (pilot duty) 120 Vac = 0.5 amps 220 Vac (non-UL) = 0.5 amps			
Mounting	North American 2½ inch (64 mm) deep 1-gang boxes and 1½ inch (38 mm) deep 4 inch square boxes with 1-gang covers and SIGA-MP mounting plates	Plugs into UIO2R, UIO6R or UIO6 Motherboards	North American 2½ inch (64 mm) deep 1-gang boxes and 1½ inch (38 mm) deep 4 inch square boxes with 1-gang covers and SIGA-MP mounting plates	Plugs into UIO2R, UIO6R or UIO6 Motherboards
Construction & Finish	High Impact Engineering Polymer			
Storage and Operating Environment	Operating Temperature: 32°F to 120°F (0°C to 49°C) Storage Temperature: -4°F to 140°F (-20°C to 60°C) Humidity: 0 to 93% RH			
LED Operation	On-board Green LED - Flashes when polled On-board Red LED - Flashes when in alarm/active			
Compatibility	Use With: Signature Loop Controller			
Agency Listings	UL, ULC, CSFM, MEA			

Ordering Information

Catalog Number	Description	Ship Weight - lbs (kg)
★ SIGA-CR	Control Relay Module (Standard Mount)	0.4 (0.15)
SIGA-MCR	Control Relay Module (UIO Mount)	0.18 (0.08)
SIGA-CRR	Polarity Reversal Relay Module (Standard Mount)	0.4 (0.15)
SIGA-MCRR	Polarity Reversal Relay Module (UIO Mount)	0.18 (0.08)
Related Equipment		
27193-11	Surface Mount Box - Red, 1-gang	1 (0.6)
27193-16	Surface Mount Box - White, 1-gang	1 (0.6)
SIGA-UIO2R	Universal Input-Output Module Board w/Riser Inputs - Two Module Positions	0.32 (0.15)
SIGA-UIO6R	Universal Input-Output Module Board w/Riser Inputs - Six Module Positions	0.62 (0.28)
SIGA-UIO6	Universal Input-Output Module Board - Six Module Positions	0.56 (0.25)
SIGA-AB4G	Audible (Sounder) Detector Base	0.3 (0.15)
Accessories		
MFC-A	Multifunction Fire Cabinet - Red, supports Signature Module Mounting Plates	7.0 (3.1)
SIGA-MB4	Transponder Mounting Bracket (allows for mounting two 1-gang modules in a 2-gang box)	0.4 (0.15)
SIGA-MP1	Signature Module Mounting Plate, 1 footprint	1.5 (0.70)
SIGA-MP2	Signature Module Mounting Plate, 1/2 footprint	0.5 (0.23)
SIGA-MP2L	Signature Module Mounting Plate, 1/2 extended footprint	1.02 (0.46)

EDWARDS
A UTC Fire & Security Company

Detection & alarm since 1872

U.S.
T 888-378-2329
F 866-503-3996

Canada
Chubb-Edwards
T 519 376 2430
F 519 376 7258

Southeast Asia
T : +65 6391 9300
F : +65 6391 9306

India
T : +91 80 4344 2000
F : +91 80 4344 2050

Australia
T +61 3 9239 1200
F +61 3 9239 1299

Europe
T +32 2 725 11 20
F +32 2 721 86 13

Latin America
T 305 593 4301
F 305 593 4300

utcfireandsecurity.com

© 2010 UTC Fire & Security.
All rights reserved.

Signature Series Overview

28 31 01

The Signature Series intelligent analog-addressable system from Edwards is an entire family of multi-sensor detectors and mounting bases, multiple-function input and output modules, network and non-network control panels, and user-friendly maintenance and service tools. Analog information from equipment connected to Signature devices is gathered and converted into digital signals. An onboard microprocessor in each Signature device measures and analyzes the signal and decides whether or not to input an alarm. The microprocessor in each Signature device provides four additional benefits – Self-diagnostics and History Log, Automatic Device Mapping, Stand-alone Operation and Fast, Stable Communication.

Self-diagnostics and History Log – Each Signature Series device constantly runs self-checks to provide important maintenance information. The results of the self-check are automatically updated and permanently stored in its non-volatile memory. This information is accessible for review any time at the control panel, PC, or using the SIGA-PRO Signature Program/Service Tool. The information stored in device memory includes:

- Device serial number, address, and type
- Time and date of last alarm
- Most recent trouble code logged by the detector — 32 possible trouble codes may be used to diagnose faults.

Automatic Device Mapping –The Signature Data Controller (SDC) learns where each device's serial number address is installed relative to other devices on the circuit. The SDC keeps a map of all Signature Series devices connected to it. The Signature Series Data Entry Program also uses the mapping feature. With interactive menus and graphic support, the wired circuits between each device can be examined. Layout or "as-built" drawing information showing branch wiring (T-taps), device types and their address are stored on disk for printing hard copy. This takes the mystery out of the installation. The preparation of as-built drawings is fast and efficient.

Device mapping allows the Signature Data Controller to discover:

- Unexpected additional device addresses
- Missing device addresses
- Changes to the wiring in the circuit.

Most Signature modules use a personality code selected by the installer to determine their actual function. Personality codes are downloaded from the SDC during system configuration and are indicated during device mapping.

Standalone Operation – A decentralized alarm decision by the device is guaranteed. Onboard intelligence permits the device to operate in standalone (degrade) mode. If Signature loop controller CPU communications fail for more than four seconds, all devices on that circuit go into standalone mode. The circuit acts like a conventional alarm receiving circuit. Each Signature device on the circuit continues to collect and analyze information from its slave devices. When connected to a panel utilizing standalone operation, modules with their "personality" set as alarm devices (IDC) will alarm should their slave alarm-initiating device activate.

EST
Life Safety & Communications

28 31 01

Isolator Module

SIGA-IM

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☑ Electrical
☐ Structural ☐ Other
☐ Mechanical

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.



Patented

S3424

7300-1657: 0121

FM APPROVED

MEA

Application Notes Available

Provide isolators approved for the location in which they are installed as per the electrical drawings.

Overview

The SIGA-IM Isolator Module is part of EST's Signature Series system. This intelligent device enables part of the Signature data loop to continue operating should a short circuit occur. The module can be wired into a Class A data loop at any point.

If a fault occurs, the isolator cuts power to all devices beyond the isolator on the loop as follows:

- a short on the line causes all isolators to open within 23 msec.
- at 10 msec intervals, beginning on one side of the Class A circuit nearest the loop controller, the isolators close to provide the next isolator down the line with power.
- when the isolator next to the short closes, it reopens within 10 msec.

Once activated, the line fault isolator continuously checks the faulted side of the loop to determine if the short still exists. When the fault is corrected and system reset, the module automatically restores the entire data loop to the normal condition.

The microprocessor in every Signature module provides at least three important benefits — Self-diagnostics and History Log, Automatic Device Mapping, and Fast, Stable Communication.

Self-diagnostics and History Log - Each Signature Series module constantly runs self-checks to provide important maintenance information. This information is automatically updated and permanently stored in the module's non-volatile memory and is accessible for review any time using the SIGA-PRO Signature Program / Service Tool.

Automatic Device Mapping - The Signature loop controller learns keeps a map where each device's serial number address is installed relative to other devices on the data circuit.

Fast Stable Communication - Built-in intelligence means less information needs to be sent between the module and the loop controller. Other than regular supervisory polling response, the module only needs to communicate with the loop controller when it has something new to report.

Standard Features

- **Automatic device mapping**
  Each module transmits wiring information to the loop controller regarding its location with respect to other devices on the circuit.
- **Electronic addressing**
  Addresses are downloaded and permanently stored from a PC, or the SIGA-PRO Signature Program / Service Tool. There are no switches or dials to set.
- **Ground fault detection by address**
  Detects ground faults right down to the device level.
- **2-gang mounting**
- **Designed to ISO 9001 standards**

Testing & Maintenance

The module's automatic self-diagnosis identifies when it is defective and causes a trouble message. The user-friendly maintenance program shows the current state of each module and other pertinent messages. Single modules may be turned off (deactivated) temporarily, from the control panel. Availability of maintenance features is dependent on the fire alarm system used. Scheduled maintenance (Regular or Selected) for proper system operation should be planned to meet the requirements of the Authority Having Jurisdiction (AHJ). Refer to current NFPA 72 and ULC CAN/ ULC 536 standards.

Warnings & Cautions
This module will not operate without electrical power. As fires frequently cause power interruption, we suggest you discuss further safeguardwith your fire protection specialist.

Typical Wiring and Installation

The SIGA-IM module mounts to North American 2-1/2 inch (64 mm) deep 2-gang boxes and 1-1/2 inch (38 mm) deep 4 inch square boxes with 2 gang covers and SIGA-MP mounting plates. The module will accept #18 AWG (0.75mm^2), #16 (1.0mm^2), #14 AWG (1.50mm^2), and #12 AWG (2.50mm^2) wire sizes. *Note: Sizes #16 AWG (1.0mm^2) and #18 AWG (0.75mm^2) are preferred for ease of installation. See Signature Loop Controller catalog sheet for detailed wiring requirement specifications.*

Edwards recommends that this module be installed according to latest recognized edition of national and local fire alarm codes.


Application

This module should only be used on Class A circuits. The operation of the SIGA-IM is determined by its hardware type code and is assigned at the factory. No user configuration is required.

Compatibility

These modules are part of EST's Signature Series intelligent processing and control platform. They are compatible with EST3, EST3X and iO Series control panels.

Typical Wiring



1. For maximum wire resistance, refer to the appropriate manufacturer's documentation.
2. Max. #12 AWG (2.5mm²)wire.
3. Refer to Signature Loop Controller Installation Sheet for wiring specifications.
4. This module should be used only with Class A wiring.
5. Maximum circuit resistance between isolators is 6 ohms.
6. All wiring is power-limited and supervised.

Specifications

Description	Isolator Module - factory set hardware type code
Address Requirements	Uses One Detector Address
Circuit Resistance	Six ohms maximum between isolators
Operating Current	Standby = 45µA; Activated = 45µA
Operating Voltage	15.2 to 19.95 Vdc (19 Vdc nominal)
Construction & Finish	High Impact Engineering Polymer 2-gang front plate - White Finish
Storage Environment	Temperature: -4°F to 140°F (-20°C to 60°C)
Operating Environment	Temperature: 32°F to 120°F (0°C to 49°C); Humidity: 0 to 93% RH
LED Operation	On-board Green LED - Flashes when polled (normal)
Compatibility	Use with: Signature Loop Controller
Agency Listings	UL, ULC, CSFM, MEA, FM

Ordering Information 28 31 01

Catalog Number	Description	Ship Wt. lb (kg)
★ SIGA-IM	Fault Isolator Module - UL/ULC Listed	.5 (.23)
Accessories		
27193-21	Surface Mount Box - 2-gang RED	1 (.4)
27193-26	Surface Mount Box - 2-gang WHITE	
MFC-A	Multifunction Fire Cabinet - Red, supports Signature Module Mounting Plates	7.0 (3.1)
SIGA-MP1	Signature Module Mounting Plate, 1 footprint	1.5 (0.70)
SIGA-MP2	Signature Module Mounting Plate, 1/2 footprint	0.5 (0.23)
SIGA-MP2L	Signature Module Mounting Plate, 1/2 extended footprint	1.02 (0.46)

Contact us...

Email: edwards.fire@fs.utc.com
Web: *www.est-fire.com*

EST is an **EDWARDS** brand.

1016 Corporate Park Drive
Mebane, NC 27302

In Canada, contact Chubb Edwards...
Email: inquiries@chubbedwards.com
Web: *www.chubbedwards.com*

© 2013 UTC Fire & Security Americas Corporation, Inc. All rights reserved. Specifications subject to change without notice. Edwards is part of UTC Climate, Controls & Security, a unit of United Technologies Corporation.

28 31 01

Manual Pull Stations

SIGA-270, SIGA-270P, SIGA-278



SIGA-270 SERIES

MEA

Patented

STANTEC PROJECT #: 110126045 SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Provide pull stations approved for the location in which they are installed as per the electrical drawings.

Overview

The SIGA-270 and SIGA-278 series Manual Pull Stations are part of EST's Signature Series system. The SIGA-270 Fire Alarm Manual Pull Stations feature our very familiar teardrop shape. They are made from die-cast zinc and finished with red epoxy powder-coat paint complemented by aluminum colored stripes and markings. With positive pull-lever operation, one pull on the station handle breaks the glass rod and turns in a positive alarm, ensuring protection plus fool-proof operation. Presignal models (SIGA-270P) are equipped with a general alarm (GA) keyswitch for applications where two stage operation is required. The up-front highly visible glass rod discourages tampering, but is not required for proper operation.

EST's double action single stage SIGA-278 station is a contemporary style manual station made from durable red colored lexan. To initiate an alarm, first lift the upper door marked "LIFT THEN PULL HANDLE", then pull the alarm handle.

Standard Features

Note: *Some features described here may not be supported by all control systems. Check your control panel's Installation and Operation Guide for details.*

- **Traditional familiar appearance**
  SIGA-270 models feature our familiar teardrop design with simple positive pull action and sturdy die-cast metal body.
- **One stage (GA), two stage (pre-signal), and double action models**
  SIGA-270 models are available for one or two stage alarm systems. The single stage double action SIGA-278 features a rugged Lexan housing with keyed reset mechanism.
- **Break glass operation**
  An up-front visible glass rod on the SIGA-270 discourages tampering.
- **Intelligent device with integral microprocessor**
  All decisions are made at the station allowing lower communication speed while substantially improving control panel response time. Less sensitive to line noise and loop wiring properties; twisted or shielded wire is not required.
- **ADA Compliant**
  Meets ADA requirements for manual pull stations.
- **Electronic Addressing with Non-volatile memory**
  Permanently stores programmable address, serial number, type of device, and job number. Automatically updates historic information including hours of operation, last maintenance date, number of alarms and troubles, and time and date of last alarm.
- **Automatic device mapping**
  Each station transmits wiring information to the loop controller regarding its location with respect to other devices on the circuit.
- **Stand-alone operation**
  The station inputs an alarm even if the loop controller's polling interrogation stops.
- **Diagnostic LEDs**
  Status LEDs; flashing GREEN shows normal polling; flashing RED shows alarm state.
- **Designed for high ambient temperature operation**
  Install in ambient temperatures up to 120 °F (49 °C).

Application

The operating characteristics of the fire alarm stations are determined by their sub-type code or "Personality Code". NORMALLY-OPEN ALARM - LATCHING (Pesonality Code 1**)** is assigned by the factory; no user configuration is required. The device is configured for Class B IDC operation. An ALARM signal is sent to the loop controller when the station's pull lever is operated. The alarm condition is latched at the station.

Compatibility

Signature Series manual stations are compatible only with EST's Signature Loop Controller.

Warnings & Cautions

This device will not operate without electrical power. As fires frequently cause power interruption, we suggest you discuss further safeguards with your local fire protection specialist.

Testing & Maintenance

To test (or reset) the station simply open the station and operate the exposed switch. The SIGA-270 series are opened with a tool; the SIGA-278 requires the key which is supplied with that station.

The station's automatic self-diagnosis identifies when it is defective and causes a trouble message. The user-friendly maintenance program shows the current state of each Signature series device and other pertinent messages. Single devices may be deactivated temporarily, from the control panel. Availability of maintenance features is dependent on the fire alarm system used.

Scheduled maintenance (Regular or Selected) for proper system operation should be planned to meet the requirements of the Authority Having Jurisdiction (AHJ). Refer to current NFPA 72 and ULC CAN/ULC 536 standards.

Typical Wiring

28 31 01

The fire alarm station's terminal block accepts #18 AWG (0.75mm^2) to #12 AWG (2.5mm^2) wire sizes. See Signature Loop Controller catalog sheet for detailed wiring requirement specifications.

Wiring Notes

1. Refer to Signature Loop Controller manual for maximum wire distance.
2. All wiring is power limited and supervised.




Figure 4. Single Stage Systems




Figure 5. Two Stage Systems

Single-stage Signature Series fire alarm manual pull stations mount to North American 2½ inch (64 mm) deep 1-gang boxes.

Two stage presignal (270P) models require 1½ inch (38 mm) deep 4-inch square boxes with 1-gang, ½-inch raised covers. Openings must be angular. *Rounded openings are not acceptable.* Recommended box: Steel City Model 52-C-13; in Canada, use Iberville Model CI-52-C-49-1/2.

All models include terminals are suited for #12 to #18 AWG (2.5 mm^2 to 0.75 mm^2) wire size. Edwards recommends that these fire alarm stations be installed according to latest recognized edition of national and local fire alarm codes.

Electronic Addressing: The loop controller electronically addresses each manual station, saving valuable time during system commissioning. Setting complicated switches or dials is not required. Each station has its own unique serial number stored in its on-board memory. The loop controller identifies each device on the loop and assigns a "soft" address to each serial number. If desired, the stations can be addressed using the SIGA-PRO Signature Program/Service Tool.




Figure 1. SIGA-278 installation




Figure 2. SIGA-270, SIGC-270F, SIGC-270B installation




Figure 3. SIGA-270P, SIGC-270PB installation

EDWARDS
A UTC Fire & Security Company

Detection & alarm since 1872

U.S.
T 888-378-2329
F 866-503-3996

Canada
Chubb-Edwards
T 519 376 2430
F 519 376 7258

Southeast Asia
T : +65 6391 9300
F : +65 6391 9306

India
T : +91 80 4344 2000
F : +91 80 4344 2050

Australia
T +61 3 9239 1200
F +61 3 9239 1299

Europe
T +32 2 725 11 20
F +32 2 721 86 13

Latin America
T 305 593 4301
F 305 593 4300

utcfireandsecurity.com

© 2010 UTC Fire & Security.
All rights reserved.

Specifications

Catalog Number	SIGA-270, SIGC-270F, SIGC-270B	SIGA-270P, SIGC-270PB	SIGA-278
Description	Single Action - One Stage	Single Action -Two Stage (Presignal)	Double Action - One Stage
Addressing Requirements	Uses 1 Module Address	Uses 2 Module Addresses	Uses 1 Module Address
Operating Current	Standby = 250µA Activated = 400µA	Standby = 396µA Activated = 680µA	Standby = 250µA Activated = 400µA
Construction & Finish	Diecast Zinc - Red Epoxy with aluminum markings		Lexan - Red with white markings
Type Code	Factory Set		
Operating Voltage	15.2 to 19.95 Vdc (19 Vdc nominal)		
Storage and Operating Environment	Operating Temperature: 32ºF to 120ºF (0ºC to 49ºC) Storage Temperature: -4ºF to 140ºF (-20ºC to 60ºC) Humidity: 0 to 93% RH		
LED Operation	On-board Green LED - Flashes when polled On-board Red LED - Flashes w hen in alarm Both LEDs - Glow steady when in alarm (stand-alone)		
Compatibility	Use With: Signature Loop Controller		
Agency Listings	UL, ULC (note 1), MEA, CSFM		

Note: *SIGC-270F, SIGC-270B and SIGC-270PB are ULC listed only. Suffix "F" indicates French markings. Suffix "B" indicates English/French biling ual markings.*

Ordering Information

	Catalog Number	Description	Ship Wt. lbs (kg)
★	SIGA-270	One Stage Fire Alarm Station, English Markings - UL/ULC Listed	1 (0.5)
	SIGC-270F	One Stage Fire Alarm Station, French Markings - ULC Listed	
	SIGC-270B	One Stage Fire Alarm Station, French/English Markings - ULC Listed	
	SIGA-270P	Two Stage (Presignal) Fire Alarm Station, English Markings - UL/ULC Listed	
	SIGC-270PB	Two Stage (Presignal) Fire Alarm Station, French/English Markings - ULC Listed	
	SIGA-278	Double Action (One Stage) Fire Alarm Station, English Markings - UL/ULC Listed	

Accessories		
32997	GA Key w/Tag - for pre-signal station (CANADA ONLY)	0.1 (.05)
276-K2	GA Key - for pre-signal station (USA ONLY)	
276-K1	Station Reset Key, Supplied with all Key Reset Stations	
27165	12 Glass Rods - for SIGA-270 series (CANADA ONLY)	
270-GLR	20 Glass Rods - for SIGA-270 series (USA ONLY)	
276-GLR	20 Glass Rods - for SIGA-278 series	
276B-RSB	Surface Mount Box, Red - for SIGA pull stations	1 (0.6)

EST™
Life Safety & Communications

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other


component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
28 31 01
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED
DATE June 20, 2018
BY Chester Martinez, E.I.T.

Field Configurable Horns and Strobes

Genesis Series



ECS/MNS appliances available with clear or amber lenses.



Overview

The Genesis line of fire alarm and mass notification/emergency communications (ECS/MNS) signals are among the smallest, most compact audible-visible life safety signaling devices in the world. About the size of a deck of playing cards, these devices are designed to blend with any decor.

Thanks to patented breakthrough technology, Edwards Genesis strobes do not require bulky specular reflectors and lenses. Instead, an exclusive cavity design conditions light to produce a highly controlled distribution pattern. Significant development efforts employing this new technology have given rise to a new benchmark in strobe performance – FullLight technology.

FullLight strobe technology produces a smooth light distribution pattern without the spikes and voids characteristic of specular reflectors. This ensures the entire coverage area receives consistent illumination from the strobe flash. As a result, Genesis strobes with FullLight technology go well beyond the UL-1971 and ULC-S526 light distribution requirements.

Genesis strobes and horn-strobes offer selectable candela output by means of a conveniently-located switch on the side of the device. Models are also available that offer fixed 15/75 cd output. The candela output setting remains clearly visible even after final installation, yet it stays locked in place to prevent unauthorized tampering.

Genesis ECS/MNS appliances offer emergency signaling with clear or amber lenses and with optional ALERT housing labels. They are ideal for applications that require differentiation between fire alarm and mass notification alerts.

Standard Features

- **Unique low-profile design**
  - The most compact UL-1971/ULC-S526 listed strobe available
  - Ultra-slim – protrudes less than one inch
  - Attractive appearance
  - No visible mounting screws
- **Four field-configurable options in one device**
  - Select 15, 30, 75, or 110 cd strobe output
  - Select high (default) or low dB horn output
  - Select temporal (default) or steady horn output
  - Select public mode flash rate (default) or private mode temporal flash
- **Fixed 15/75 cd model available**
- **ECS/MNS models available**
- **Easy to install**
  - Fits standard 1-gang electrical boxes – no trim plate needed
  - Optional trim plate accommodates oversized openings
  - Pre-assembled with captive hardware
  - #12 AWG terminals – ideal for long runs or existing wiring
- **Unparalleled performance**
  - Industry's most even light distribution
  - Meets tough synchronizing standards for strobes
  - Single microprocessor controls both horn and strobe
  - Independent horn control over a single pair of wires
  - Highly regulated in-rush current
  - Multiple frequency tone improves sound penetration
  - Field-programmable temporal strobe output option

Application

Genesis strobes are UL 1971-listed for use indoors as wall-mounted public-mode notification appliances for the hearing impaired. Prevailing codes require strobes to be used where ambient noise conditions exceed 105 dBA (87dBA in Canada), where occupants use hearing protection, and in areas of public accommodation as defined in the *Americans with Disabilities Act (see application notes – USA)*.

Combination horn-strobe signals must be installed in accordance with guidelines established for strobe devices. Consult with your Authority Having Jurisdiction for details.

All Genesis strobes exceed UL synchronization requirements (within 10 milliseconds over a two-hour period) when used with a synchronization source. Synchronization is important in order to avoid epileptic sensitivity.

WARNING: These devices will not operate without electrical power. As fires frequently cause power interruptions, further safeguards such as backup power supplies may be required.

Horns

Genesis horn output reaches as high as 99 dB and features a unique multiple frequency tone that results in excellent sound penetration and an unmistakable warning of danger. Horns may be configured for either coded or non-coded signal circuits. They can also be set for low dB output with a jumper cut that reduces horn output by about 5 dB. Horn-only models may be ceiling-mounted or wall-mounted.

The suggested sound pressure level for each signaling zone used with alarm signals is at least 15 dB above the average ambient sound level, or 5 dB above the maximum sound level having a duration of at least 60 seconds, whichever is greater, measured 5 feet (1.5 m) above the floor. The average ambient sound level is, A-weighted sound pressure measured over a 24-hour period.

Doubling the distance from the signal to the ear will theoretically result in a 6 dB reduction of the received sound pressure level. The actual effect depends on the acoustic properties of materials in the space. A 3 dBA difference represents a barely noticeable change in volume.

ECS/MNS Applications

Genesis ECS/MNS strobe appliances bring the same high-performance fire alarm features and unobtrusive design to mass notification applications. Available with amber lenses and optional ALERT housing labels, they are ideal for applications that require differentiation between fire alarm and mass notification alerts.

Installation

Genesis horns and strobes mount to any standard one-gang surface or flush electrical box. Matching optional trim plates are used to cover oversized openings and can accommodate one-gang, two-gang, four-inch square, or octagonal boxes, and European 100 mm square.



Genesis Horn/Strobe with optional trim plate

All Genesis signals come pre-assembled with captive mounting screws for easy installation. Two tabs at the top of the signal unlock the cover to reveal the mounting hardware. The shallow depth of Genesis devices leaves ample room behind the signal for extra wiring. Once installed with the cover in place, no mounting screws are visible.

Field Configuration

Temporal horn and horn-strobe models are factory set to sound in a **three-pulse temporal pattern**. Units may be configured for use with coded systems by cutting a jumper on the circuit board. This results in a **steady output** that can be turned on and off (coded) as the system applies and removes power to the signal circuit. A Genesis Signal Master is required when horn-strobe models are configured for coded systems. Non-temporal, horn-only models sound a steady tone.


Genesis clear strobes and horn-strobes are shipped from the factory ready for use as **UL 1971 compliant** signals for public mode operation. These signals may be configured for **temporal flash** by cutting a jumper on the circuit board. This battery-saving feature is intended for private mode signaling only.

Genesis clear strobes and horn-strobes may be set for **15, 30, 75, or 110 candela output**. The output setting is changed by simply opening the device and sliding the switch to the desired setting. The device does not have to be removed to change the output setting. The setting remains visible through a small window on the side of the device after the cover is closed.

Horns and horn-strobes are factory set for **high dB output**. **Low dB output** may be selected by cutting a jumper on the circuit board. This reduces the output by about 5 dB.

Wiring

Field wiring terminals accommodate #18 to #12 AWG (0.75 mm² to 2.5 mm²) wiring. Horns, strobes, and combination horn-strobes are interconnected with a single pair of wires as shown below.



Note: Strobes must have continuous voltage.

Current Draw

28 31 01

Strobes, Horn-Strobes

Multi-cd Wall Strobes (G1-VM)

UL Rating	15 cd* RMS	30 cd* RMS	15/75 cd** RMS	75 cd* RMS	110 cd* RMS
16 Vdc	103	141	152	255	311
16 Vfwr	125	179	224	346	392

*G1-VM multi-cd; **G1F-V1575 fixed 15/75 cd

Typical Current	15 cd RMS	30 cd RMS	15/75 RMS	75 cd RMS	110 cd RMS
16 Vdc	85	127	150	245	285
20 Vdc	71	98	123	188	240
24 Vdc	59	82	104	152	191
33 Vdc	46	64	84	112	137
16 Vfwr	119	169	223	332	376
20 Vfwr	103	143	189	253	331
24 Vfwr	94	129	169	218	262
33 Vfwr	87	112	148	179	205

Wall Temporal Horn-strobes – High dB Setting

UL Rating	15 cd* RMS	30 cd* RMS	15/75 cd** RMS	75 cd* RMS	110 cd* RMS
16 Vdc	129	167	172	281	337
16 Vfwr	176	230	269	397	443

*G1-HDVM multi-cd
**G1F-HDV1575 fixed 15/75 cd

Typical Current	15 cd RMS	30 cd RMS	15/75 RMS	75 cd RMS	110 cd RMS
16 Vdc	102	135	160	246	309
20 Vdc	88	109	137	193	248
24 Vdc	81	94	122	161	203
33 Vdc	74	72	106	124	154
16 Vfwr	144	182	247	352	393
20 Vfwr	141	162	220	274	362
24 Vfwr	136	152	203	235	282
33 Vfwr	125	144	196	201	232

Wall Temporal Horn-strobes – Low dB Setting

UL Rating	15 cd* RMS	30 cd* RMS	15/75 cd** RMS	75 cd* RMS	110 cd* RMS
16 Vdc	122	160	146	274	330
16 Vfwr	162	216	231	383	429

*G1-HDVM multi-cd
**G1F-HDV1575 fixed 15/75 cd

Typical Current	15 cd RMS	30 cd RMS	15/75 RMS	75 cd RMS	110 cd RMS
16 Vdc	96	130	158	243	302
20 Vdc	79	104	133	189	241
24 Vdc	68	88	119	156	197
33 Vdc	56	71	100	118	146
16 Vfwr	128	180	241	344	389
20 Vfwr	118	157	213	266	343
24 Vfwr	113	144	195	230	279
33 Vfwr	112	137	182	197	226

Horns

Wall or Ceiling Mounted Temporal Horns (G1-HD)

UL Rating	High dB (RMS)	Low dB (RMS)
16 Vdc	26	19
24 Vdc	36	27
33 Vdc	41	33
16 Vfwr	51	37
24 Vfwr	69	52
33 Vfwr	76	70

Typical Current	High dB RMS	Low dB RMS
16 Vdc	22	17
20 Vdc	24	19
24 Vdc	27	22
33 Vdc	32	26
16 Vfwr	34	30
20 Vfwr	40	34
24 Vfwr	45	38
33 Vfwr	52	47

Wall or Ceiling Mounted Horns (G1-P)

UL Designation	Voltage Range	Max. Current, RMS
Regulated 24 Vdc	16 - 33 Vdc	13 mA
24 fwr	16 - 33 Vfwr	11 mA

Typical Current	RMS
24 Vdc	10
24 Vdc	11
31 Vdc	12
20 Vfwr	9
24 Vfwr	10

Current values are shown in mA.

dBA output

Temporal Horns, Horn-strobes (G1-HD, G1-HDVM series)

High dB Setting	UL464		Average	Peak
	Temporal	Steady	Temporal/ Steady	Temporal/ Steady
16 Vdc	81.4	85.5	91.4	94.2
24 Vdc	84.4	88.6	94.5	97.6
33 Vdc	86.3	90.4	96.9	99.5

Low dB Setting	UL464		Average	Peak
	Temporal	Steady	Temporal/ Steady	Temporal/ Steady
16 Vdc	76.0	80.1	86.3	89.2
24 Vdc	79.4	83.5	89.8	92.5
33 Vdc	82.1	86.5	92.5	95.3

Steady Tone Horns (G1-P series)


	UL464	Average	Peak
16 Vdc	77 dBA, min	85 dBA	91 dBA
16 Vfwr	77 dBA, min	85 dBA	91 dBA

Notes

1. All values shown are dBA measured at 10 feet (3.01m).
2. UL464 values measured in reverberant room.
3. Average and Peak values are measured in anechoic chamber.


Average Sound Output (dBA)

(High dB setting, anechoic, 24V, measured at 10ft)



Light output - (effective cd)

Percent of UL rating versus angle



Specifications

Housing	Red or white textured UV stabilized, color impregnated engineered plastic. Exceeds 94V-0 UL flammability rating.
Lens	Optical grade polycarbonate (clear)
Mounting (indoor only)	Strobes and horn-strobes are for wall-mount installation only. Horn-only models may be ceiling- or wall-mounted. Flush mount: 2½ inch (64 mm) deep one-gang box Surface mount: Model 27193 surface mount box, wiremold box, or equivalent surface-mount box With optional trim plate: One-gang, two-gang, four-inch square, octagonal, or European single-gang box
Wire connections	Screw terminals: single input for both horn and strobe. #18 to #12 AWG (0.75 mm^2 to 2.5 mm^2) wire size
Operating environment	Indoor only: 32-120°F (0-49°C) ambient temperature. 93% relative humidity
Agency listings/approvals	UL 1971, UL 1638, UL 464, ULC S525, ULC S526, CSFM, CE, FCC, MEA. (All models comply with ADA Code of Federal Regulation Chapter 28 Part 36 Final Rule.)
Dimensions (HxWxD)	Signal: 4-1/2" x 2-3/4" x 13/16" (113 mm x 68 mm x 21 mm) Trimplate: 5" (127 mm); Height – 5-7/8" (149 mm); Depth – ½" (13 mm)
Operating voltage	G1-HD series temporal-tone horns: non-coded, filtered 16-33 Vdc or unfiltered 16-33 Vdc FWR (or coded when horn set to steady tone) G1-HDVM series temporal-tone horn-strobes: non-coded, filtered 16-33 Vdc or unfiltered 16-33 Vdc FWR (or coded (audible NAC only) when used with optional G1M Genesis Signal Master) G1-VM series strobes: non-coded, filtered 16 - 33 Vdc or unfiltered 16-33 Vdc FWR G1-P series steady-tone horns: coded or non-coded, filtered 20-31 Vdc or unfiltered 20-27 Vfwr
Strobe output rating	UL 1971, UL 1638, ULC S526: selectable 15 cd, 30 cd, 75 cd, or 110 cd output UL 1971: 15 cd (fixed 15/75 cd models) UL 1638, ULCS526: 75 cd (fixed 15/75 cd models)
Strobe flash rate	G1-VM strobes and G1-HDVM series temporal-tone horn-strobes: one flash per second synchronized with optional G1M Genesis Signal Master indefinitely within 10 milliseconds. Temporal setting (private mode only): synchronized to temporal output of horns on same circuit
Synchronization Sources	SIGA-CC1S, SIGA-MCC1S, SIGA-CC2A, SIGA-MCC2A, G1M-RM BPS6A, BPS10A, APS6A, APS10A, iO64, iO500, Fireshield Plus 3, 5 and 10 zone. Add G1M for G1-CVM &G1-HDVM devices only.
Horn pulse rate	G1-HD temporal-tone horns and G1-HDVM series temporal-tone horn-strobes: temporal rate synchronized with optional G1M Genesis Signal Master indefinitely within 10 milliseconds. G1-P steady-tone horns: continuous, steady tone only
Temporal audible pattern	½ sec ON, ½ sec OFF, ½ sec ON, ½ sec OFF, ½ sec ON, 1½ sec OFF, then repeat cycle

Candela Output

Lens Color	Rating	Switch Position A	Switch Position B	Switch Position C	Switch Position D
Amber	UL 1638	110 cd	75 cd	30 cd	15 cd
Amber	UL 1971*	88 cd	60 cd	24 cd	12 cd
Clear	UL 1971	110 cd	75 cd	30 cd	15 cd

** Equivalent Rating*

28 31 01

Fire appliances available with white or red housings.



ECS/MNS appliances available with clear or amber lenses.



Ordering Information

Model	Housing	Marking	Lens	Strobe	Horn	Ship Wt. lbs (kg)
Fire Alarm Appliances (c/w running man icon screen printed on housing)						
G1-VM	White	None	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
G1F-HD	White	FIRE	Clear	Horn only	Selectable high/low dB	0.25 (0.11)
G1F-HDV1575	White	FIRE	Clear	15/75 cd[1]	Temporal hi/lo dB-24V	0.25 (0.11)
G1F-HDVM	White	FIRE	Clear	Selectable 15, 30, 75, or 110 cd	Selectable high/low dB	0.25 (0.11)
G1F-P	White	FIRE	Clear	Steady Horn (not compatible with Genesis Signal Master)		0.25 (0.11)
G1F-V1575	White	FIRE	Clear	15/75 cd[1]	Strobe only	0.25 (0.11)
G1F-VM	White	FIRE	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
G1-HD	White	None	Clear	Horn only	Selectable high/low dB	0.25 (0.11)
G1-HDVM	White	None	Clear	Selectable 15, 30, 75, or 110 cd	Selectable high/low dB	0.25 (0.11)
G1-P	White	None	Clear	Steady Horn (not compatible with Genesis Signal Master)		0.25 (0.11)
G1RF-HD	Red	FIRE	Clear	Horn only	Selectable high/low dB	0.25 (0.11)
G1RF-HDV1575	Red	FIRE	Clear	15/75 cd[1]	Temporal hi/lo dB-24V	0.25 (0.11)
★ G1RF-HDVM	Red	FIRE	Clear	Selectable 15, 30, 75, or 110 cd	Selectable high/low dB	0.25 (0.11)
G1RF-P	Red	FIRE	Clear	Steady Horn (not compatible with Genesis Signal Master)		0.25 (0.11)
G1RF-V1575	Red	FIRE	Clear	15/75 cd[1]	Strobe only	0.25 (0.11)
G1RF-VM	Red	FIRE	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
G1R-HD	Red	None	Clear	Horn only	Selectable high/low dB	0.25 (0.11)
G1R-HDVM	Red	None	Clear	Selectable 15, 30, 75, or 110 cd	Selectable high/low dB	0.25 (0.11)
G1R-P	Red	None	Clear	Steady Horn (not compatible with Genesis Signal Master)		0.25 (0.11)
G1R-VM	Red	None	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
ECS/MNS Appliances (no running man icon on housing)						
G1WA-VMA	White	ALERT	Amber	Selectable A, B, C or D	Strobe only	0.25 (0.11)
G1WA-VMC	White	ALERT	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
G1WN-VMA	White	None	Amber	Selectable A, B, C or D	Strobe only	0.25 (0.11)
G1WN-VMC	White	None	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
Trim Plates						
G1T	White	None	Genesis Trim Plate (for two-gang or 4" square boxes)			0.15 (0.7)
G1RT	Red	None	Genesis Trim Plate (for two-gang or 4" square boxes)			0.15 (0.7)
G1T-FIRE	White	FIRE	Genesis Trim Plate (for two-gang or 4" square boxes)			0.15 (0.7)
G1RT-FIRE	Red	FIRE	Genesis Trim Plate (for two-gang or 4" square boxes)			0.15 (0.7)
G1WT-ALERT	White	ALERT	Genesis Trim Plate (for two-gang or 4" square boxes)			0.15 (0.7)
Surface Boxes						
27193-16	White	N/A	One-gang surface mount box			1 (0.4)
27193-11	Red	N/A	One-gang surface mount box			1 (0.4)

[1] These 15/75 cd models provide fixed output and are not multi-candela devices. The 15 cd output component complies with UL1971, while the 75 cd output component complies with UL 1638.

28 31 01

EDWARDS
A UTC Fire & Security Company

Detection & alarm since 1872

U.S.
T 888 378 2329
F 866 503 3996

Canada
Chubb Edwards
T 519 376 2430
F 519 376 7258

Southeast Asia
T : +65 6391 9300
F : +65 6391 9306

India
T : +91 80 4344 2000
F : +91 80 4344 2050

Australia
T +61 3 9239 1200
F +61 3 9239 1299

Europe
T +32 2 725 11 20
F +32 2 721 86 13

Latin America
T 305 593 4301
F 305 593 4300

utcfireandsecurity.com

© 2010 UTC Fire & Security.
All rights reserved.

Life Safety & Communications

28 31 01

Sealed Lead-Acid Batteries



Overview

Rechargeable sealed lead-acid batteries are ideal for use as a secondary (standby) power source as defined by ULC requirements for ULC listed fire alarm control panels. Their low maintenance and high energy density make them ideal for fire alarm signaling applications.

Standard Features

- Rechargeable
- Non-spillable
- Non-hazardous
- Low maintenance
- High energy density

Application

When multiple power supplies are provided, each power supply's battery requirements should be calculated individually. Consult the specific system manual to determine battery capacity requirements.

Safety Information

Due to a battery's low internal resistance and high power density, high levels of short circuit current can develop across battery terminals. Put on protective eye covering and remove all jewelry before working on batteries. Do not rest tools or cables on the battery, and only use insulated tools. Follow all manufacturers installation instructions and diagrams when installing or maintaining batteries.

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☑ Electrical
☐ Structural ☐ Other
☐ Mechanical

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Contact us...
Email: edwards.fire@fs.utc.com
Web: *www.est-fire.com*

EST is an **EDWARDS** brand.

1016 Corporate Park Drive
Mebane, NC 27302

In Canada, contact Chubb Edwards...
Email: inquiries@chubbedwards.com
Web: *www.chubbedwards.com*

© 2015 UTC Fire & Security Americas Corporation, Inc. All rights reserved. Specifications subject to change without notice. Edwards is part of UTC Climate, Controls & Security, a unit of United Technologies Corporation.

28 31 01

Specifications

Case material	ABS thermoplastic
Regulatory information	DOT Class 60, batteries, non-hazardous, non-spillable
Operating environment	32° F to 120° F (0° C to 49° C) 0 to 93% RH, non-condensing

Ordering Information

Catalogue Number	Description	Dimensions (mm)	Shipping weight (kg)
12V4A5	4.5 AH sealed lead acid battery - 12Vdc	4.21" h x 2.76" w x 3.54" L (107 x 70 x 90)	3.26lbs (1.48kg)
12V7A2	7.2 AH sealed lead acid battery - 12Vdc	4" h x 2.6" w x 6.0" L (102 x 66 x 152)	4.85lbs (2.2kg)
★ 12V10A5	10.5 AH sealed lead acid battery - 12Vdc	4.8" h x 2.6" w x 6" L (122 x 66 x 152)	7.05lbs (3.2kg)
12V13A	13 AH sealed lead acid battery - 12Vdc	6.5" h x 3.15" w x 5.28" L (166 x 80 x 135)	10.2lbs (4.62kg)
12V18A	18 AH sealed lead acid battery - 12Vdc	6.6" h x 3.0" w x 7.1" L (168 x 76 x 180)	11.73lbs (5.32kg)
12V26A	26 AH sealed lead acid battery - 12Vdc	7.17" h x 4.92" w x 6.5" L (182 x 125 x 165)	19.8lbs (9.0kg)
12V35A	35 AH sealed lead acid battery - 12Vdc	6.26" h x 5.16" w x 7.76" L (159 x 131 x 197)	24.3lbs (10.9kg)
12V40A	40 AH sealed lead acid battery - 12Vdc	6.69" h x 6.5" w x 7.76" L (170 x 165 x 197)	29.1lbs (13.2kg)
12V50A	50 AH sealed lead acid battery - 12Vdc	7.87" h x 5.19" w x 10.11" L (200 x 132 x 257)	35.3lbs (16kg)
12V65A	65 AH sealed lead acid battery - 12Vdc	7.01" h x 6.57" w x 13.70" L (178 x 167 x 348)	42.3lbs (19.2kg)

Date: Jun 18, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 18, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-03
PO-P18-120

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Drawing E-601-Automatic Transfer Switch

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

THOMSON™
POWER SYSTEMS

APPROVAL DRAWINGS

ATTACHED DOCUMENTS ARE DRAFT FOR REVIEW ONLY AND ARE SUBJECT TO CHANGE WITHOUT NOTICE.

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE STANDARD TERMS & CONDITIONS.

THE INFORMATION CONTAINED IN THESE DRAWINGS IS THE PROPERTY OF THOMSON POWER SYSTEMS, IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

NOTE:
ANY PROGRAM SETTINGS SHOWN REFLECT FACTORY DEFAULT SETTINGS ONLY. FINAL SETTINGS WILL BE REQUIRED TO BE SET BY THE COMMISSIONING AUTHORITY. FAILURE TO DO SO MAY RESULT IN EQUIPMENT FAILURE.

PROJECT NAME / REFERENCE : IQALUIT WTP

CUSTOMER : FRONTIER POWER PRODUCTS

THOMSON CUSTOMER ORDER : C-058937 REV# : 0

WORKORDER / SERIAL NUMBER : W-102489

MODEL NUMBER : TS873A0400A1CN5BKKAA

ATTACHED DRAWINGS :

PHYSICAL LAYOUT & INSTALLATION DETAILS	W-102489-10A	REV#	0
MCS AC SCHEMATIC	W-102489-20A	REV#	0
ATS AC CONTROL SCHEMATIC	W-102489-20B	REV#	0
ATS DC CONTROL SCHEMATIC	W-102489-20C	REV#	0
STANDARD OPTION SCHEMATIC - CTKIT0400A	W-102489-30A	REV#	0
STANDARD OPTION SCHEMATIC - PPR-10	W-102489-30B	REV#	0

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-003 Automatic Transfer Switch

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED

☑ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Provide 4-position switch as per specifcations- Test, Auto, Manual, Engine Start.

FEATURES / RATINGS:

AMPERAGE :	400A
VOLTAGE :	347 / 600V (3PH, 4W, GROUNDED NEUTRAL)
POLES :	3-POLE
FREQUENCY :	60HZ
CONFIGURATION :	STANDARD ATS
APPLICATION :	STANDARD
OPERATION :	OPEN TRANSITION
ENCLOSURE :	NEMA 2, ASA # 61 GREY
ATS CONTROLLER :	TSC900 C/W GHC DISPLAY

UTILITY (OR SOURCE 1) SWITCHING DEVICE :	MOLDED CASE SWITCH
GENERATOR (OR SOURCE 2) SWITCHING DEVICE :	MOLDED CASE SWITCH
APPROVAL STANDARD :	UL1008 / CSA C22.2.NO 178

SYSTEM OPTIONS:

LPM :	TRANSFER SWITCH LOAD POWER METERING (0400A CT KIT)
PPR-10 :	PROGRAMMABLE POWER RELAY INCLUDES 10A FORM "C" CONTACT WIRED TO TERMINAL (EXTERNAL 24VDC REQ)
CUSTOM OPTION 1 :	NEMA 2 ENCLOSURE C/W DRIP SHIELD

SHOP DRAWING / SUBMITTAL REVIEW

☐ APPROVED ☐ APPROVED WITH CHANGES NOTED

☐ REVISE AND RESUBMIT ☐ REJECTED _____

SUBMITTAL WAS RECEIVED FOR DESIGN CONFORMITY AND GENERAL CONFORMANCE TO CONTRACT DOCUMENTS ONLY. THE CONTRACTOR FOR CONFIRMING AND CORRELATING DIMENSIONS AT JOB SITES FOR TOLERANCES, CLEARANCES, QUANTITIES, FABRICATION PROCESSES AND TECHNIQUES OF CONSTRUCTION, COORDINATION OF HIS WORK WITH OTHER TRADES AND FULL COMPLIANCE WITH CONTRACT


BY_____ DATE_____

COMPANY NAME_____


CITY_____STATE / PROV _____

9087A - 198TH STREET, LANGLEY, BC CANADA V1M 3B1
EMAIL : info@thomsonps.com, www.thomsonps.com


REGAL®




FRONT VIEW




LHS VIEW
(SIDE COVER REMOVED)



INTERIOR FRONT VIEW
(DOOR NOT SHOWN)



VIEWED FROM REAR
(INSIDE) OF DOOR



BASIC MODEL TS87xA	STANDARD ATS				
	CLOSING AND WITHSTAND RATING AVAILABLE AMPS (RMS) CLOSING & WITHSTAND RATINGS SHOWN ARE ONLY FOR ATS UTILITY AND/OR GENERATOR POWER SOURCE WHEN PROTECTED BY CIRCUIT BREAKER SUPPLIED WITH ADEQUATE OVERCURRENT PROTECTION. PLEASE REFER TO PRODUCT INSTRUCTION MANUAL FOR FURTHER INFORMATION ON UPSTREAM PROTECTION REQUIREMENT.				
	MAX. VOLTAGE	RATED CURRENT (A)	@240V	@480V	@600V
TS 873A--400	600	400	65,000	50,000	35,000

CONNECTION DATA		
400A ATS	UTILITY (SRC1)	1-2C, 2/0-500MCM Cu/Al PER PHASE
	GENERATOR (SRC2)	1-2C, 2/0-500MCM Cu/Al PER PHASE
	LOAD	1-2C, 2/0-500MCM Cu/Al PER PHASE
	NEUTRAL	1-2C, 2/0-500MCM Cu/Al PER SOURCE
	GROUND	6C, #6-250MCM Cu/Al

GENERAL NOTES	
1	POWER SWITCHING DEVICES ARE MECHANICALLY INTERLOCKED SO THAT ONLY ONE DEVICE IS CLOSED AT A TIME
2	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

2.5" x 5"

W1

DANGER
PELIGRO

Arc Flash and Shock Hazard
Will cause severe injury or death. Most likely arc-fault energy is at the load side of the ATS. Do not open door unless all sources of supply have been disconnected. Only qualified electrical personnel utilizing safe work practices and appropriate Personal Protective Equipment (PPE) should perform work on this equipment. Failure to follow NFPA 70E for instructions on PPE, may cause injury or death.

Risque d'Arc Electrique et d'Electrocution
Peut causer des blessures graves ou la mort. Peut être causé par un arc-flash d'énergie. Débranchez toutes les sources d'alimentation avant d'ouvrir la porte. Seul le personnel qualifié doit être habilité et entretenu uniquement par un électricien qualifié. Ce dernier doit connaître les pratiques de travail sécuritaires et porter l'équipement de protection individuelle approprié. Le non respect peut entraîner des blessures graves ou la mort. Consultez la norme NFPA 70E pour le manuel des exigences électriques PPE.

Riesgo de Arco y Choque Eléctrico
Va causando serious graves o muerte. Sitio de un circuito energizado - ver diagrama. Desconectar todas las fuentes de alimentación antes de abrir la puerta. Sólo el personal calificado debe estar instalado y mantener por personal calificado, usando medidas de seguridad y equipo de protección personal (PPE) adecuado. El incumplimiento puede resultar en lesiones graves o muerte.Consulte la NFPA 70E para los requisitos mínimos del equipo de protección personal (PPE).

QTY = 1

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5.0C - C-1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS	No.	REVISIONS	BY	AUTH	DATE

THOMSON POWER SYSTEMS


AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
PHYSICAL LAYOUT & INSTALLATION DETAILS
IQALUIT WTP

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER	FRONTIER POWER PRODUCTS		
CUSTOMER ORDER No.	C-058937	WORK ORDER No.	W-102489
DRAWN BY	NS	AUTH BY	OG
DATE	18-06-12	REV	0
DRAWING/FILE No.	W-102489-10A	SHEET	10A

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS



COLOR KEY	
BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

GENERAL NOTES

1. COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
2. REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5.0C-C-1
GRID COORDINATE
SHEET No.


DRAWING No.	REFERENCE DRAWINGS	No.	REVISIONS	BY	AUTH	DATE

THOMSON POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
MCS AC SCHEMATIC
IQALUIT WTP

CUSTOMER	FRONTIER POWER PRODUCTS
CUSTOMER ORDER No.	C-058937
WORK ORDER No.	W-102489
DRAWN BY	NS
AUTH. BY	OG
DATE	18-06-12
REV	0
DRAWING/FILE No.	W-102489-20A
SHEET	20A

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS



GENERAL NOTES	
1	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
2	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

VOLTAGE (X DENOTES HIGH POLARITY MARKER)							
PT TAP	208	240	380	400	416	480	600
H1	X	X			X	X	X
H2	X		X	X			
H3		X					
H4					X	X	X
H5	X	X	X	X			

COLOR KEY	
BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5.0C-C-1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS	No.	REVISIONS	BY	AUTH	DATE

THOMSON POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
ATS AC CONTROL SCHEMATIC

IQALUIT WTP


CUSTOMER FRONTIER POWER PRODUCTS

CUSTOMER ORDER No.	WORK ORDER No.
C-058937	W-102489

DRAWN BY	AUTH BY	DATE	REV
NS	OG	18-06-12	0

DRAWING/FILE No. W-102489-20B | SHEET 20B

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS



PARAMETER	MODBUS RTU SETTINGS
SLAVE ID	1
PORT NAME	COM 4
BAUD RATE	57600
PARITY	NONE
STOP BUS	ONE

TSC900 FACTORY DEFAULT SETTINGS

NOTE : REFER TO OPTION DRAWINGS FOR APPLICABLE CHANGES TO FACTORY DEFAULT SETTINGS

PARAMETER	DEFAULT	RANGE
GENERATOR (SOURCE 2) START DELAY	3 SEC	0–60 SEC
GENERATOR (SOURCE 2) WARM UP DELAY	2 SEC	0–3600 SEC
GENERATOR (SOURCE 2) COOL DOWN DELAY	300 SEC	0–3600 SEC
UTILITY (SOURCE 1) RETURN DELAY	300 SEC	0–3600 SEC
TRANSFER NEUTRAL DELAY	3 SEC	0–120 SEC
TRANSFER FAIL DELAY	30 SEC	0–120 SEC
EXERCISE TIMER	PROG.	PROG.
GENERATOR (SOURCE 2) UNDER VOLTAGE DELAY	3 SEC	0–10 SEC
GENERATOR (SOURCE 2) UNDER FREQUENCY DELAY	5 SEC	0–10 SEC
GENERATOR (SOURCE 2) UNDER VOLTAGE PICK UP	90%	75–100%
GENERATOR (SOURCE 2) UNDER VOLTAGE DROP OUT	85%	70–95%
UTILITY (SOURCE 1) UNDER VOLTAGE DELAY	1 SEC	0–10 SEC
UTILITY (SOURCE 1) UNDER VOLTAGE PICK UP	90%	75–100%
UTILITY (SOURCE 1) UNDER VOLTAGE DROP OUT	85%	70–95%

ALL SETTINGS ARE FIELD ADJUSTABLE UNLESS NOTED. REFER TO THE TSC900 MANUAL FOR A COMPLETE LISTING OF ALL TSC900 SETTINGS.

GENERAL NOTES

1	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
2	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

COLOR KEY

BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

FOR REVIEW ONLY

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5.0C – C – 1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS	No.	REVISIONS	BY	AUTH	DATE

THOMSON POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
ATS DC CONTROL SCHEMATIC


IQALUIT WTP


DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER	FRONTIER POWER PRODUCTS		
CUSTOMER ORDER No.	C-058937	WORK ORDER No.	W-102489
DRAWN BY	NS	AUTH BY	OG
DATE	18-06-12	REV.	0
DRAWING/FILE No.	W-102489-20C	SHEET	20C


© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS

☒ CTK0400A OPTION





ATS CONTROL PLATE



PART ID	OPTION KITS
CTK0100	100 AMPS
CTK0150	150 AMPS
CTK0250	200–250 AMPS
CTK0400	400 AMPS
CTK0600	600 AMPS
CTK0800	800 AMPS
CTK1200	1000–1200 AMPS
CTK1600	1600 AMPS
CTK2000	2000 AMPS

GENERAL NOTES	
1	CT'S TO BE MOUNTED ON THE LOAD SIDE OF THE ATS. CUSTOMER TO VERIFY POLARITY BEFORE CONNECTING THE CT SECONDARIES TO THE TRANSFER SWITCH CONTROLLER.
2	ATS CONTROL PLATE MOUNTED ON THE BACK SIDE OF DOOR FOR MCS / MOS AND FOR ICS MOUNTED ON THE BACKPAN.
3	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

BILL OF MATERIALS FOR CABLE HARNESS

PART DESCRIPTION	PART ID	QTY
WIRE, 18AWG, GREY, TINNED, TEW, 600V,	002027	600 INCHES
TERM. BLK, RAIL MNT, 40A, 600V, WK4/U,	001861	6
TERM. BLK, ENDPLATE, WK 2.5–4/U,	001872	1
SCREW, SHT–MTL, RDH, ROB #6 X 5/8"	002070	2
MTG–RAIL, TYPE–35, SLOTTED(7.5X2–METERS)	002795	6
TERM. BLK, PARTITION PLATE, WK2.5–4/U,	004189	2
CONN, MINI–FIT, J, 94V–2, 2X1–WAY,FEMALE (J5/J6/J7)	012654	3
CONN, FEMALE CRIMP, MINI–FIT, JR, SERIES	010954	6
WIRE SLEEVE, 0.5", EXPANDO PT PLUS,	000456	175 INCHES
TERM BLK CROSS CONN.W SCRW WK4/U SR7	009677	3
TERM. BLK, EARTH TERMINAL, 10–24 AWG	005211	2

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5.0C – C – 1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS | No. | REVISIONS | BY | AUTH | DATE


THOMSON™ POWER SYSTEMS


AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
STANDARD OPTION SCHEMATIC – CTKIT0400A
IQALUIT WTP

CUSTOMER: FRONTIER POWER PRODUCTS
CUSTOMER ORDER No.: C–058937
WORK ORDER No.: W–102489
DRAWN BY: NS | AUTH BY: OG | DATE: 18–06–12 | REV: 0
DRAWING/FILE No.: W–102489–30A
SHEET: 30A

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS

☒ PPR–10 OPTION





PR1				
T1	TYPE	T2	REF	
4	4h	7	A–5	
1	4W			
5	4h	8	A–6	
2	4W			
6	4h	9	A–7	
3	4W			


PR2			
T1	TYPE	T2	REF
4	4h	7	B–5
1	4W		
5	4h	8	B–6
2	4W		
6	4h	9	B–7
3	4W		

PPR–10 OPTION NOTES	
1	FOR POWER RELAY FUNCTIONAL DESCRIPTION REFER TO FACTORY DEFAULT DIGITAL OUTPUT FUNCTION TABLE ON ATS DC CONTROL SCHEMATIC
2	THE NUMBER OF RELAYS SUPPLIED WILL BE PER ORDERED QUANTITY
3	CUSTOMER TO WIRE DIRECTLY TO RELAY TERMINALS
4	SPECIFIED QUANTITY OF PROGRAMMABLE POWER RELAYS ARE WIRED FOR CUSTOMER AS PER OPTION LIST
5	DC SUPPLY FOR THE RELAYS, BY DEFAULT IS 24VDC. PLEASE SPECIFY THE VOLTAGE RATING OTHER THAN 24VDC ON OPTION LIST

BILL OF MATERIALS		
PART DESCRIPTION	PART ID	QTY
RELAY, 24VDC COIL, 11 PIN SQ., /W LED	004095	2
RELAY SOCKET, 11 PIN, SQ., RAIL MOUNT	000399	2
FUSE HOLDER, 1P, 30A, 600V, 200KA, CC	002374	1
FUSE, 3A, 600VAC, CLASS CC	003633	1
TERM. BLK, RAIL MNT, 40A, 600V, MK4/U,	001861	10

GENERAL NOTES	
1	FOR MCS/MDS/PCS TYPE ATS, MOUNT THE RELAYS ON SIDE COVER WHERE SPACE PERMITS
2	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

PPR RELAY
[TYPICAL]



FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5.0C–C–1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS	No.	REVISIONS	BY	AUTH	DATE

THOMSON™ POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
STANDARD OPTION SCHEMATIC – PPR–10
IQALUIT WTP

CUSTOMER FRONTIER POWER PRODUCTS
CUSTOMER ORDER No. C–058937
WORK ORDER No. W–102489
DRAWN BY NS | AUTH BY OG | DATE 18–06–12 | REV 0
DRAWING/FILE No. W–102489–30B
SHEET 30B

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS

Date: Jun 25, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 26, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-04
PO-P18-124

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 26 50 00 Lighting

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

Date: Jun 25, 2018

BDA Lighting Group
77 Auriga Drive, Unit 6
Ottawa On K2E7Z7
Phone: (613) 727-6223
Toll Free: (855) 606-6223
Website: WWW.BDALG.CA

Project Name:
Iqaluit Water Treatment Plant
BDA18-23511

Bid Date:
May 31, 2018

Submittal Date:
Jun 21, 2018

BDA LIGHTING GROUP

Jun 25, 2018

Guillevin Ottawa
175 Richmond Road
Ottawa ON K1Z 6W3

RE: Iqaluit Water Treatment Plant

Qty	Type	MFG	Part
8	401	HUBBELL LIGHTING	QSP2-24L-50-5K7-4-UNV-BL
7	404	Peerless Electric	NSL-RA-4-60-50K-W-WG-347
18	405	Peerless Electric	NSL-RA-4-60-50K-W-WG-347
	402		FMV11LCY/UNV34 76
	403		VMV5L2A/UNV34
	406		EGW/4/S/LED/HO/CW/UE

Contractor to review quantity prior to ordering

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- ☐ Architectural
- ☐ Structural
- ☐ Mechanical
- ☑ Electrical
- ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- ☐ REVIEWED
- ☑ REVIEWED, AS NOTED
- ☐ REVISE AND RESUBMIT
- ☐ NOT REVIEWED

DATE June 26, 2018

BY Chester Martinez, E.I.T.

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** QSP2-24L-50-5K7-4-UNV-BL Notes:	**Type:** 401 BDA18-23511

GEOPAK SERIES SIZE 2 LED

Architectural Wallpack

TRP2/RDI2/QSP2 NEW

Cat.#

Job

Type

HUBBELL Outdoor Lighting

Approvals

SPECIFICATIONS

Applications:
Medium sized architectural wallpacks in three stylish shapes accentuate building architecture and provide excellent illumination and uniformity

Construction:
- Die-cast aluminum housing and door
- Seven powder coat standard finishes, plus custom color options

LED:
- 24 or 32 high power LEDs deliver up to 10,800 lumens
- Up to 146 Lumens per watt
- Different lenses offer a variety of distribution patterns - Type I, II, III and IV (Forward throw)
- 3000K - 70 CRI, 4000K - 70 CRI, and 5000K - 70 CRI, CCT nominal

Electrical:
- Optional Dual Drivers & Dual Power Feeds for 50, 70 and 90 watt versions
- 120-277, 347 and 480 voltage, 50/60Hz
- Power factor ≥ 90%
- THD (Total Harmonic Distortion) <20%
- Ambient operating temperature -40°C to 40°C
- 20kA surge protection (series); Automatically takes fixture off-line when device is consumed

Installation/Mounting:
- Quick-mount adapter with gasket seal provides easy installation to wall or to recessed junction box (4" square junction box). Fixture attaches by two Allen-head hidden fasteners for tamper resistance.
- Black box accessory available for surface conduit application
- Optional inverted/up mounting (must specify when ordering)


Options/Controls:
- Drivers are 0-10V dimming standard
- Universal button photocontrol for dusk to dawn energy savings
- Photocell and occupancy sensor options available for complete on/off and dimming control
- Occupancy sensor options available for complete on/off and dimming control
- In addition, GeoPak Size 2 can be specified with SiteSync™ wireless control system for reduction in energy and maintenance cost while optimizing light quality 24/7. See ordering information or visit www. hubbell-lighting.com/sitesync for more details

Listings:
- IP65 rated housing
- DesignLights Consortium® (DLC) qualified. Please refer to the DLC website for specific product qualifications at www.designlights.org
- Zero uplight (U0), dark sky, neighbor friendly
- Drivers IP66 and RoHS compliant


Battery Backup:
- Intergral Battery Backup provides emergency lighting for the required 90 minute path of egress.
- Includes a long-life Lithium Iron Phosphate battery with optional battery heater for cold temperature application.
- Utilizes 4 LEDs in emergency mode with 657 lumens. Each of the 4 LEDs in emergency are designed to function independently in the unlikely event of a single LED malfunction
- Spectron® self-testing/self-diagnostic electronics are included standard
- Independent dedicated driver and LED array for battery/emergency mode operation.

Warranty:
For more information visit:
http://www.hubbelloutdoor.com/resources warranty/

PRODUCT IMAGE(S)



DIMENSIONS



SHIPPING INFORMATION

Catalog Number	G.W(kg)/ CTN	Carton Dimensions		
		Length Inch (cm)	Width Inch (cm)	Height Inch (cm)
QSP2	17 (7.7)	20.5 (52)	10.5 (26)	11 (28)
RDI2	18 (8.2)	20.5 (52)	9.5 (24)	12 (30)
TRP2	16 (7.3)	18.5 (47)	9.5 (24)	11.5 (29)

CERTIFICATIONS/LISTINGS

*3000K and warmer CCTs only

ORDERING INFORMATION

ORDERING EXAMPLE: TRP2-24L30-3K7-2-UNV-DB

FAMILY	LEDS - WATTAGE	CCT	DISTRIBUTION	VOLTAGE	FINISH	CONTROL OPTIONS	OPTIONS
TRP2 Trapezoid	**24L-30** 24 LEDs, 30 watts	**3K7** 3000K, 70CRI	**1** Type I	**UNV** 120-277V	**BL** Black Textured	**PC** Button Photocontrol	**SF**[3] Single Fuse & Fuse Holder
RDI2 Radius	**24L-50** 24 LEDs, 50 watts	**4K7** 4000K, 70CRI	**2** Type II	**120** 120V	**DB** Dark Bronze Textured	**SCP**[4,5] Programmable occupancy sensor, factory default is 10% light output	**DF**[3] Double Fuse & Fuse Holder
QSP2 Qtr-sphere	**24L-70** 24 LEDs, 70 watts	**5K7** 5000K, 70CRI	**3** Type III	**208** 208V	**GT** Graphite Textured	**SCO**[4] Sensor Control, On/Off	**E**[3] Battery Pack (0ºC)
	24L-90 24 LEDs, 90 watts		**4** Type IV	**240** 240V	**GYS** Light Gray Smooth	**SWP**[3,7] SiteSync Pre-Commission	**EH**[3] Battery Pack (-30oC) with heater
	32L-70 32 LEDs, 70 watts			**277** 277V	**PS** Platinum Silver Smooth	**SWPM**[3,4,7,8] SiteSync Pre-commission w/Occupancy Sensor	**2DR**[6] Dual Drivers
	32L-90 32 LEDs, 90 watts			**UHV**[1] 347/480V	**WH** White Textured	**SPEC SCP/SCO & SWPM MOUNT HEIGHT**	**2PF**[6] Dual Power Feeds
				347[1] 347V	**CC** Custom Color	**-8F** Up to 8ft mount height	**CS** Comfort Shield
				480[1] 480V		**-20F** Up to 20ft mount height	

SECONDARY MOUNTING
BLANK Downlight Only
NV[2] Inverted/Up Mounting

[1] 70 & 90 watt versions only
[2] Not available with SCP, SCO or SWPM sensor options
[3] Must specify voltage (120, 277 or 347V only for SWP & SWP, 120 or 277V only for E & EH)
[4] PCU option not applicable, included in sensor
[5] Must order minimum of one remote control to program dimming settings, 0-10V fully adjustable dimming with automatic daylight calibration and different time delay settings
[6] Not available with 30w version
[7] Must specify group and zone information at time or order. See www.HubbellLighting.com/products/sitesync for future details
[8] Specify time delay; dimming level and mounting height


© 2017 HUBBELL OUTDOOR LIGHTING, All Rights Reserved • For more information visit our website: **www.hubbelloutdoor.com** • Printed in USA

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** QSP2-24L-50-5K7-4-UNV-BL Notes:	**Type:** 401 BDA18-23511


ACCESSORIES (ORDER SEPARATELY)

Catalog Number	Description
SCP-REMOTE*	Remote control for SCP option. Order at least one per project to program and control dimming settings
BB-GEO-XX	Black box with 4 - 1/2" threaded conduit holes, specify finish by replacing "XX" with finish selection, eg. Dark Bronze "DB"
SWUSB**	SiteSync loaded on USB flash drive (Windows based only)
SWTAB**	SiteSync Windows Tablet
SWBRG+	SiteSync Wireless Bridge Node

* Must order minimum of one remote control to program dimming settings, 0-10V fully adjustable dimming with automatic daylight calibration and different time delay settings.
** When ordering with SiteSync, one of the following interface options must be chosen an ordered separately. Each option contains the SiteSync License, GUI and Bridge Node.
\+ If needed, an additional Bridge Node can be ordered.



BB-GEO-XX – Mounted to luminaire



INPUT POWER CONSUMPTION

# OF LEDS	DRIVE CURRENT (mA)	INPUT VOLTAGE (V)	CURRENT (Amps)	SYSTEM POWER (w)
24	350mA	120	0.23	28
		277	0.10	28
	625mA	120	0.41	49
		277	0.18	49
	900mA	120	0.59	71
		277	0.25	71
		347	0.20	71
		480	0.15	71
	1100mA	120	0.72	87
		277	0.31	87
		347	0.25	87
		480	0.18	87
32	650mA	120	0.56	67
		277	0.24	67
		347	0.19	67
		480	0.14	67
	850mA	120	0.69	83
		277	0.30	83
		347	0.24	83
		480	0.17	83

STANTEC PROJECT # 110126045
SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec
☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED
DATE June 26, 2018
BY Chester Martinez, E.I.T.


PERFORMANCE DATA

				5K (5000K nominal, 70 CRI)					4K (4000K nominal, 70 CRI)					3K (3000K nominal, 70 CRI)				
# OF LEDS	DRIVE CURRENT	SYSTEM WATTS	DIST. TYPE	LUMENS	LPW[1]	B	U	G	LUMENS	LPW[1]	B	U	G	LUMENS	LPW[1]	B	U	G
24	350mA	28	1	4,075	146	1	0	0	4,065	146	1	0	0	3,660	131	0	0	0
			2	3,747	134	1	0	1	3,738	134	1	0	1	3,366	121	1	0	1
			3	3,756	135	1	0	1	3,747	134	1	0	1	3,374	121	1	0	1
			4	3,656	131	0	0	1	3,647	131	0	0	1	3,284	118	0	0	1
	625mA	49	1	6,329	130	1	0	0	6,313	130	1	0	0	5,685	117	1	0	0
			2	5,820	120	1	0	1	5,806	119	1	0	1	5,228	108	1	0	1
			3	5,833	120	1	0	2	5,819	120	1	0	2	5,240	108	1	0	2
			4	5,678	117	1	0	2	5,664	117	1	0	2	5,100	105	1	0	2
	900mA	71	1	8,613	122	1	0	1	8,592	122	1	0	1	7,737	110	1	0	1
			2	7,921	112	1	0	2	7,902	112	1	0	2	7,115	101	1	0	2
			3	7,939	112	1	0	2	7,920	112	1	0	2	7,131	101	1	0	2
			4	7,728	109	1	0	2	7,709	109	1	0	2	6,942	98	1	0	2
	1100mA	87	1	10,791	124	1	0	1	10,765	124	1	0	1	9,694	112	1	0	1
			2	9,924	114	2	0	2	9,900	114	1	0	2	8,915	103	1	0	2
			3	9,946	115	1	0	2	9,922	114	1	0	2	8,935	103	1	0	2
			4	9,682	112	1	0	2	9,659	111	1	0	2	8,696	100	1	0	2
32	650mA	67	1	8,621	129	1	0	1	8,600	128	1	0	1	7,744	116	1	0	1
			2	7,928	118	1	0	2	7,909	118	1	0	2	7,122	106	1	0	2
			3	7,946	119	1	0	2	7,927	118	1	0	2	7,137	107	1	0	2
			4	7,735	115	1	0	2	7,716	115	1	0	2	6,948	104	1	0	2
	850mA	83	1	10,806	130	1	0	1	10,780	130	1	0	1	9,705	117	1	0	1
			2	9,938	120	2	0	2	9,914	119	1	0	2	8,927	108	1	0	2
			3	9,960	120	1	0	2	9,936	120	1	0	2	8,947	108	1	0	2
			4	9,695	117	1	0	2	9,672	117	1	0	2	8,709	105	1	0	2


© 2016 HUBBELL OUTDOOR LIGHTING, All Rights Reserved • For more information visit our website: **www.hubbelloutdoor.com** • Printed in USA

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** QSP2-24L-50-5K7-4-UNV-BL Notes:	**Type:** 401 BDA18-23511


PHOTOMETRIC REPORTS




TRP2-24L-50-4K7-1
15" MOUNTING HEIGHT



TRP2-24L-50-4K7-2
15" MOUNTING HEIGHT




TRP2-24L-50-4K7-3
15" MOUNTING HEIGHT



TRP2-24L-50-4K7-4
15" MOUNTING HEIGHT

PHOTOMETRICS - BATTERY BACK UP



11' Mounting Height

Provides Life Safety Code average illuminance of 1.0 fc. Assumes open space with no obstructions and mounting height of 11'.


Diagrams for illustration purposes only, please consult factory for application layout.

E & EH EMERGENCY BATTERY BACKUP



24 or 32 high power LEDs generate up to 11,000 lumens in normal mode and use 4 LEDs for up to 700 lumens in emergency mode.

INVERTED MOUNTING



Inverted mounting capabilities for uplighting applications. Specially designed frosted acrylic diffuser softens output, improves uniformity and prevents water from collecting.

COMFORT SHIELD



Comfort shield option utilizes a frosted acrylic lens that softens output and improves uniformity. Available from the factory or as an accessory for field installation.

CONTROL OPTIONS



Programmable occupancy sensor offers greater control and energy savings with adjustable delay and dimming levels (Factory default is 10%)

© 2017 HUBBELL OUTDOOR LIGHTING, All Rights Reserved • For more information visit our website: **www.hubbelloutdoor.com** • Printed in USA

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** NSL-RA-4-60-50K-W-WG-347 Notes:	**Type:** **404** BDA18-23511

PEERLESS electric·électrique

PROJECT:	DATE:
CAT. NO:	TYPE:
NOTES:	VOLTS:

NSL-RA

LED Narrow Strip Luminaire – Rounded Lens

LED

GENERAL DESCRIPTION

LED luminaire for surface or suspended installation, featuring a rounded extruded ribbed frosted acrylic lens. Available in 2ft, 4ft and 8ft models that provide uniform illumination with the narrow design. Available individually or for continuous-row mounting for uniform continuous lighting. Ideal for general utility applications, including commercial, residential, retail and also works well in cove applications.



SHIELDING

A rounded extruded ribbed frosted acrylic lens is standard.

ELECTRICAL

L80 performance at 60,000 hours minimum.
120-270V or 347V
80 CRI Standard**
3000K 3500K 4000K 5000K

FINISH

Standard finish is high gloss white polyester baked powder coat enamel.

GLOSSY / MATTE

*other colours available. Contact factory

LENGTHS

NOMINAL (ft)	ACTUAL(in)
2 ft	22.459"
4 ft	44.584"
8 ft	88.928"

CONSTRUCTION

Rigid one-piece body constructed from code gauge steel.

CERTIFICATION

Approved to UL1598 and
CSA C22.2 No. 250 standards*
Rated for damp locations.

Check the DLC Qualified Products List at *designlights.org* to confirm which versions are qualified.

MOUNTING

SURFACE MOUNTED

SUSPENDED

SENSOR

OC= On/Off Occupancy control
O5= 100%-50% Hi/Low Occupancy control
Consult factory

*Normal temperature: -20 degrees Celsius to +25 degrees Celsius.
**Other dimming options, lumen options, 90CRI and lengths available. Consult Factory.

V1-2018/01/09

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other


component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 26, 2018

BY Chester Martinez, E.I.T.



ORDERING INFORMATION

NSL – RA – – – – – – NO OPTION – NO OPTION –

OPTICAL DESIGN	LENGTH	LUMENS	CCT	FINISH	*OPTIONAL*	MOUNTING *OPTIONAL*	POWER CORD *OPTIONAL*	DRIVER
RA = Rounded Acrylic	**2** = 2'	**15** = 1500lm **23** = 2300lm **30** = 3000lm	**30K** = 3000K **35K** = 3500K **40K** = 4000K **50K** = 5000K	**GLOSSY** **W** = White Housing **B** = Black Housing **G** = Metallic Grey Housing **MATTE** **WM** = White Matte Housing **BM** = Black Matte Housing **GM** = Grey Matte Housing	**WG** = Wireguard	**A4** = Aircraft 48in **A5** = Aircraft 60in **A8** = Aircraft 96in **A12** = Aircraft 144in *for row mounting option, Consult factory	**C1** = Cord 5ft **C2** = Cord 6ft **C4** = Cord 9ft **C7** = Cord 13ft	**MV** = Standard 120V-277V Dimming (0-10v) **347** = Standard 347V Dimming (0-10v)
	4 = 4'	**29** = 2900lm **30** = 3000lm **40** = 4000lm **46** = 4600lm **60** = 6000lm						
	8 = 8'	**60** = 6000lm **80** = 8000lm **96** = 9600lm **120** = 12000lm						

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** NSL-RA-4-60-50K-W-WG-347 Notes:	**Type:** **404** BDA18-23511


PEERLESS electric·électrique


NSL-RA

LED Narrow Strip Luminaire – Rounded Lens


MODELS

NSL-RA-2






NSL-RA-4




NSL-RA-4-XX-XXK-X-WG-XX-XX
Optional: WG = Wireguard

NSL-RA-4



NSL-RA-8



Head Office - Montreal, Québec
Tel.: (514) 595-1671
Email: info@peerless-electric.com

Toronto, Ontario
Tel.: (416) 751-5644
Email: info@peerless-electric.com

Western Canada
Tel.: (403) 479-5943 / (514) 595-1671
Email: tkolody@peerless-electric.com

Specifications are subject to change. Please confirm latest specifications prior to placing order.

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** NSL-RA-4-60-50K-W-WG-347 Notes:	**Type:** 405 BDA18-23511

PEERLESS electric·électrique

PROJECT:	DATE:
CAT. NO:	TYPE:
NOTES:	VOLTS:

STANTEC PROJECT #: 110126045 SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.


Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 26, 2018

BY Chester Martinez, E.I.T.





NSL-RA

LED Narrow Strip Luminaire – Rounded Lens

LED

GENERAL DESCRIPTION

LED luminaire for surface or suspended installation, featuring a rounded extruded ribbed frosted acrylic lens. Available in 2ft, 4ft and 8ft models that provide uniform illumination with the narrow design. Available individually or for continuous-row mounting for uniform continuous lighting. Ideal for general utility applications, including commercial, residential, retail and also works well in cove applications.

SHIELDING

A rounded extruded ribbed frosted acrylic lens is standard.

ELECTRICAL

L80 performance at 60,000 hours minimum.
120-270V or 347V
80 CRI Standard**
3000K 3500K 4000K 5000K

FINISH

Standard finish is high gloss white polyester baked powder coat enamel.

GLOSSY / MATTE

*other colours available. Contact factory

LENGTHS

NOMINAL (ft)	ACTUAL(in)
2 ft	22.459"
4 ft	44.584"
8 ft	88.928"

CONSTRUCTION

Rigid one-piece body constructed from code gauge steel.

CERTIFICATION

Approved to UL1598 and
CSA C22.2 No. 250 standards*
Rated for damp locations.

Check the DLC Qualified Products List at *designlights.org* to confirm which versions are qualified.

MOUNTING

SURFACE MOUNTED

SUSPENDED

SENSOR

OC= On/Off Occupancy control
O5= 100%-50% Hi/Low Occupancy control
Consult factory

*Normal temperature: -20 degrees Celsius to +25 degrees Celsius.
**Other dimming options, lumen options, 90CRI and lengths available. Consult Factory.

V1-2018/01/09

SUSPENSION NOT INCLUDED SUPPLIED BY OTHERS

ORDERING INFORMATION

NSL – RA – – – – – – NO OPTION – NO OPTION –

OPTICAL DESIGN	LENGTH	LUMENS	CCT	FINISH	*OPTIONAL*	MOUNTING *OPTIONAL*	POWER CORD *OPTIONAL*	DRIVER
RA = Rounded Acrylic	**2** = 2'	**15** = 1500lm **23** = 2300lm **30** = 3000lm	**30K** = 3000K **35K** = 3500K **40K** = 4000K **50K** = 5000K	**GLOSSY** **W** = White Housing **B** = Black Housing **G** = Metallic Grey Housing **MATTE** **WM** = White Matte Housing **BM** = Black Matte Housing **GM** = Grey Matte Housing	**WG** = Wireguard	**A4** = Aircraft 48in **A5** = Aircraft 60in **A8** = Aircraft 96in **A12** = Aircraft 144in *for row mounting option, Consult factory	**C1** = Cord 5ft **C2** = Cord 6ft **C4** = Cord 9ft **C7** = Cord 13ft	**MV** = Standard 120V-277V Dimming (0-10v) **347** = Standard 347V Dimming (0-10v)
	4 = 4'	**29** = 2900lm **30** = 3000lm **40** = 4000lm **46** = 4600lm **60** = 6000lm						
	8 = 8'	**60** = 6000lm **80** = 8000lm **96** = 9600lm **120** = 12000lm						

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** NSL-RA-4-60-50K-W-WG-347 Notes:	**Type:** **405** BDA18-23511


PEERLESS electric·électrique


NSL-RA

LED Narrow Strip Luminaire – Rounded Lens


MODELS

NSL-RA-2






NSL-RA-4




NSL-RA-4-XX-XXK-X-WG-XX-XX
Optional: WG = Wireguard

NSL-RA-4



NSL-RA-8



Head Office - Montreal, Québec
Tel.: (514) 595-1671
Email: info@peerless-electric.com

Toronto, Ontario
Tel.: (416) 751-5644
Email: info@peerless-electric.com

Western Canada
Tel.: (403) 479-5943 / (514) 595-1671
Email: tkolody@peerless-electric.com

Specifications are subject to change. Please confirm latest specifications prior to placing order.

Hazardous Area LED Lighting
Champ® FMV LED Luminaires

GUILLEVIN OTTAWA
PO# 2010-RON971364D
drawings issued 2018-06-22

FMV11LCY/UNV34 76 page 6

CROUSE-HINDS SERIES

Champ® FMV

LED floodlights for harsh and hazardous areas









Type 402

EATON
Powering Business Worldwide



Type 402

Safe. Reliable. Efficient.

Featuring the industry's broadest range of LED luminaires for harsh, hazardous and industrial environments, Eaton's Crouse-Hinds can deliver a lighting solution that performs reliably in even the worst operating conditions. All the while reducing your energy, maintenance and manpower costs.

Why LED?

Energy efficiency
LED average energy consumption is significantly less than traditional fluorescent and HID fixtures

Start/restart time
Instant illumination vs. 10 minute restrike time for HID

Light quality
Higher color rendering compared to fluorescent and HID

Environmental benefits
Mercury-free LED eliminates disposal costs and lower energy consumption for a smaller carbon footprint

Why Crouse-Hinds?

Industry-best reliability
Built to withstand a wide array of applications

Thermal management
Effective heat sinking ensures longer life

Quality of light
Custom optics designed to maximize light distribution and intensity

Globally certified
Designed to global specifications for IEC and NEC applications

Serviceable drivers
Easy access to drivers for service or replacement

Why FMV LED?

Type 402

Reliable floodlights. FMV LED luminaires are engineered to deliver high lumen output and maintenance-free long life in the toughest conditions.

Versatile design

- Can be used for outdoor or indoor applications, and for a wide range of mounting heights depending on model and light level requirement

Smaller and lighter

- 25% smaller footprint than previous model
- 10 lbs. (4.5 kg) less weight than previous model

Full frame yoke

- Designed to utilize the SFA6 slipfitter and SWB6 wall mount bracket, making it ideal for retrofit or new installations



High lumen output:

- Up to 117 lumens per watt
- Up to 72% energy savings over traditional HID fixtures (compared to 400W MH)



Multiple lens options:

- Tempered clear glass lens standard
- Polycarbonate and diffused glass lens options available

Rugged heat sink


- Heat sink designed to perform and provide maximum light levels in high ambient temperatures up to +65°C and as low as -40°C
- Thick walled castings make for a tough, rugged housing that keeps the internal driver and LED temperature down

LED vs. HID savings at a glance


Why are so many facilities making the switch from HID to LED?

The numbers say it all.

FMV13L/UNV1 vs. 400 watt HID



72% REDUCTION IN ENERGY COSTS



75% LOWER TOTAL COST OF OWNERSHIP



100% MAINTENANCE REDUCTION

Assumptions: Calculations based on overall life of the LED system. Energy cost of $.09 per kilowatt; 24 hour per day operation; labor rate of $75 each for 2 workers; average time for fixture maintenance of 1 hour.

Features & specifications

Champ FMV LED floodlights

Champ FMV LED floodlights are designed to provide full-spectrum, crisp, white light. Seven versions of the Champ FMV are available, from 3,000 to 15,000 lumens, providing ideal solutions for a wide range of harsh and hazardous applications.

Up to 75% reduction in energy costs and 150,000 hours of continuous operation.

Model number	Nominal lumens*	Wattage	Lumens per watt	Equivalent HID luminaire
FMV3L	3,189	28	114	70W-100W
FMV5L	5,183	45	115	100W-150W
FMV7L	7,095	62	114	150W-175W
FMV9L	9,132	79	116	175W-250W
FMV11L	11,107	99	112	250W-400W
FMV13L	13,100	112	117	400W
FMV15L	15,181	131	116	450W

*Tolerance +/- 10%; @120 VAC, 25°C ambient, 7x6 optics.

Applications:

- Oil and gas refineries, drilling rigs, petrochemical facilities, food and beverage facilities, platforms, loading docks, tunnels, outdoor wall and stanchion mounted general area lighting, and where flammable vapors, gases, ignitable dusts, fibers or flyings are present
- Locations requiring continuous and consistent light levels in extreme ambient temperatures
- Where extremely corrosive, wet, dusty, hot and/or cold conditions exist
- IP66, Type 4X, marine, wet locations and hose-down environments
- Classified and hazardous locations

LED system:

- Cool white (5000K, 70 CRI) and warm white (3000K, 80 CRI)
- Custom designed optics – 7x6 standard, 3x3 optional (3L-11L)


Champ FMV LED benefits:

- Instant illumination and restrike
- Better visibility with crisp, white light
- Cold temperature operation / no warm-up required
- Minimum T3C temperature rating – safely operate in the most hazardous environments and any non-hazardous location
- Serviceable drivers
- Easy installation – yoke design to mount to SFA6
- Energy-efficient technology – up to 72% energy savings over HID fixtures
- 60,000 hours of rated life at 55°C – eliminates need for frequent lamp replacement
- Contains no mercury or other hazardous substances
- Shock- and vibration-resistant solid-state luminaires have no filaments or glass components that could break – greatly reduces the risk of premature failure
- Operating ambient -40°C to 65°C (NEC only; IEC -40°C to 55°C)
- 5 year fixture warranty‡

‡Extension of standard terms and conditions to five years. Refer to page 2 of the D-0914 authorized distributor price book for Crouse-Hinds standard Terms and Conditions.

LED system lifetime rated versus economic life:

Type 402



Economic life can range anywhere between 50,000 to 150,000 hours, or 5 to 20 years of maintenance-free operation.

Fixture life and years of maintenance-free operation

Ambient temperature	Fixture life (hours)	No. of years at 24 hours usage	No. of years at 12 hours usage
25°C	150,000	17	34
40°C	90,000	10	20
55°C	60,000	7	14

*50,000 hours of life at 65°C ambient.

Fixture life:

- Rated life of 60,000 hours @ 55°C operating ambient and 24/7 continuous operation for 365 days
- Economic life of 150,000 hours @ 25°C ambient
- L70 LED life >300,000 hours @ 55°C

Electrical ratings:

Model number	Input power (watts)	Input amps at 120-277 VAC
FMV3L	28.0 - 29.1	0.24 - 0.11
FMV5L	45.4 - 45.8	0.38 - 0.18
FMV7L	61.8 - 62.5	0.52 - 0.24
FMV9L	78.8 - 80.3	0.66 - 0.31
FMV11L	98.8 - 99.9	0.83 - 0.37
FMV13L	111.8 - 112.4	0.94 - 0.42
FMV15L	131.4 - 131.5	1.10 - 0.48

FMV3L - FMV15L	
Voltage range, VAC*	100-277V @ 50/60 Hz, 347-480V @ 50/60 Hz
Voltage range, VDC*	108-250V
Power factor	>0.9

*NEC voltage; see drivers below for IEC voltage.

Standard materials:

- Lamp housing and adapter – die cast aluminum with Corro-free™ epoxy powder coat
- Lens – heat- and impact-resistant glass (standard)
- Gaskets – silicone and neoprene
- External hardware – stainless steel

Qualifications and compliances:

- DesignLights Consortium® Qualified (some models are not DLC qualified)*

* Approved models include: FMV3L/UNV1; FMV5L/UNV1; FMV7L/UNV1; FMV9L/UNV1; FMV11L/UNV1; FMV13L/UNV1; FMV3L/UNV34; FMV5L/UNV34; FMV7L/UNV34; FMV9L/UNV34; FMV11L/UNV34; FMV13L/UNV34

7x6 optics on all approved models; 3x3 optics not DLC approved.

Refer to www.designlights.org Qualified Products List under family models for full listing details. Not all models are approved for all application categories.

Certifications and compliances:

Type 402

NEC and CEC:

- Class I, Division 2, Groups A, B, C, D; Class I, Zone 2; Class II, Groups E, F, G; Simultaneous Presence; Class III
- Type 4X, IP66

UL Standards:

- UL844; UL1598; UL1598A; UL8750

CSA Standard:

- CSA C22.2 No. 137

IEC Standards:

- IECEx UL 15.0029
- Ex nA IIC T5 Gc Tamb -40°C to +40°C
- Ex nA IIC T4 Gc Tamb -40°C to +55°C
- Ex tb IIIC T65 Db Tamb -40°C to +40°C
- Ex tb IIIC T80 Db Tamb -40°C to +55°C

ATEX/CE:

- CE0359 DEMKO 15 ATEX 1377
- CE0359 DEMKO 15 ATEX 1383
- Ⓔx II 3 G Ex nA IIC T5 Gc Tamb -40°C to +40°C
- Ⓔx II 3 G Ex nA IIC T4 Gc Tamb -40°C to +55°C
- Ⓔx II 2 D Ex tb IIIC T65 Db Tamb -40°C to +40°C
- Ⓔx II 2 D Ex tb IIIC T80 Db Tamb -40°C to +55°C



Temperature codes:


Model	Ambient temperature	Class I, Div. 2	Class II, Div. 1	Simultaneous rating Class I, Div. 2, Div. 1	Class I, Zone 2	ATEX 3G	ATEX 2D	Minimum wire temperature
FMV3L-FMV15L	40°C	T5	T4	T4	T5	T5	T65	90°C
	55°C	T4A	T3C	T3C	T4	T4	T80	90°C
	65°C	T4A	T3C	T3C	T4	–	–	90°C

Weights and dimensions:

Model number	Lbs.	Kg.	Width in.	Width mm.	Height in.	Height mm.	Depth in.	Depth mm.
FMV3L-FMV7L	30.7	13.9	15.5	393.7	12.0	304.8	7.0	177.8
FMV9L-FMV15L	31.8	14.4	15.5	393.7	12.0	304.8	7.0	177.8

Drivers:

Option	FMV3L - FMV15L
/UNV1	NEC: 100-277 VAC, 50/60 Hz; 108-250 VDC IEC: 100-252 VAC, 50/60 Hz; 111-227 VDC
/UNV34	NEC: 347-480 VAC, 50/60 Hz IEC: 385-436 VAC, 50/60 Hz



Ordering information

Part number example

~~FMV5LCY/UNV1D 76 S903~~

GUILLEVIN OTTAWA
PO# 2010-RON971364D
drawings issued 2018-06-22

FMV11LCY/UNV34 76

~~FMV 5L C Y /UNV1 D 76 S903~~

Model

FMV	NEC & IEC model

Light source/intensity

3L	3,189 nominal lumens*
5L	5,183 nominal lumens*
7L	7,095 nominal lumens*
9L	9,132 nominal lumens*
11L	11,107 nominal lumens*
13L	13,100 nominal lumens*
15L	15,181 nominal lumens*

*7x6 model.

Color temperature

C	5000K, 70 CRI (cool white)
W	3000K, 80 CRI (warm white)

Voltage

/UNV1	100-277 VAC, 50/60 Hz; 108-250 VDC
/UNV34	347-480 VAC 50/60 Hz

Mount

Y	Yoke

Options

S886	Two TMCX cable glands of like thread installed
S891	Diffused glass lens
S903	Polycarbonate lens

Entries

BLANK	¾" NPT
M20	20mm entry
M25	25mm entry

Optical distribution

76	7x6 floodlight pattern optics
33*	3x3 floodlight pattern optics

*3L - 11L only.

Dimming

D*	Dimmable driver
BLANK	Non-dimmable driver

*Dimmable driver option only available for NEC rated models.

Accessories (ordered separately)

DSV2	Bolt-on visor
P62	Bolt-on wire guard
SC831	Safety cable
SFA6	Floodlight slipfitter
SWB6	Slipfitter wall mount adapter

Type 402

STANTEC PROJECT #: 110126045

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

SUBMITTAL # ELE-004 Lighting

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 26, 2018


BY Chester Martinez, E.I.T.

Photometric data

Type 402

7x6 optics

FMV13L Height: 40 ft.; Tilt angle: 45°



Effective projected area (ft.-sq.):

Position	FMV3L - FMV15L
@ 0° Tilt	1.5
@ 45° Backwards tilt	1.1
@ 60° Forward tilt	0.8

Lumen output for glass lens models

Optic	FMV3L	FMV5L	FMV7L	FMV9L	FMV11L	FMV13L	FMV15L
7x6	3,189	5,183	7,095	9,132	11,107	13,100	15,181
3x3	3,064	5,038	7,000	8,962	10,917	–	–

Lumen output for diffused glass lens (S891) models


Optic	FMV3L	FMV5L	FMV7L	FMV9L	FMV11L	FMV13L	FMV15L
7x6	2,637	4,287	5,878	7,459	8,994	10,613	12,445
3x3	2,546	4,179	5,806	7,433	9,055	–	–

Lumen output for polycarbonate lens (S903) models

Optic	FMV3L	FMV5L	FMV7L	FMV9L	FMV11L	FMV13L	FMV15L
7x6	3,017	4,903	6,712	8,639	10,507	12,393	14,361
3x3	2,924	4,808	6,680	8,552	10,418	–	–

3x3 optics

FMV11L Height: 30 ft.; Tilt angle: 45°





Higher average footcandles/lux, uniformity and distribution coverage with 72% less energy consumption compared to 400W metal halide.

Type 402

U.S. (global headquarters): Eaton's Crouse-Hinds business

1201 Wolf Street
Syracuse, NY 13208

(866) 764-5454
FAX: (315) 477-5179
FAX Orders Only:
(866) 653-0640

crousecustomerctr@eaton.com

Canada

Toll Free: 800-265-0502
FAX: (800) 263-9504
FAX Orders only: (866) 653-0645

Eaton Middle East

9714-8066100
FAX: 9714-8894813

chmesales@eaton.com

Korea

82-2-3484-6783
82-2-3484-6778

CCHK-sales@
cooperindustries.com

Mexico/Latin America/Caribbean

52-555-804-4000
FAX: 52-555-804-4020

ventascentromex@eaton.com

Singapore

65-6645-9888
FAX: 65-6297-4819

chsi-sales@
cooperindustries.com

Australia

61-2-8787-2777
FAX: 61-2-9609-2342

CEASales@
cooperindustries.com

Europe (Germany)

49 (0) 6271 806-500
49 (0) 6271 806-476

sales.CCH.de@
cooperindustries.com

China

86-21-2899-3600
FAX: 86-21-2899-4055

cchsales@
cooperindustries.com

India

91-124-4683888
FAX: 91-124-4683899

cchindia@eaton.com

For more information:

If further assistance is required, please contact an authorized Eaton Distributor, Sales Office, or Customer Service Department.

Eaton's Crouse-Hinds
1201 Wolf Street
Syracuse, NY 13208
Crouse-Hinds.com

Eaton
1000 Eaton Boulevard
Cleveland, OH 44122
United States
Eaton.com

© 2015 Eaton
All Rights Reserved

Printed in USA
Publication No. 5242-1215
December 2015

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Powering Business Worldwide

GUILLEVIN OTTAWA
PO# 2010-RON971364D
drawings issued 2018-06-22

VMV5L2A/UNV34 page 8

Champ® VMV

LED luminaires for hazardous areas



3,000 to 25,000 lumen LED high bay luminaires



Type 403

EATON
Powering Business Worldwide



Champ® VMV LED

Safe. Reliable. Efficient.

Type 403

Featuring the industry's broadest range of LED luminaires for harsh, hazardous and industrial environments, Eaton's Crouse-Hinds can deliver a lighting solution that performs reliably in even the worst operating conditions. All the while reducing your energy, maintenance and manpower costs.

Why LED?

Useful life
Rated life is up to 60,000 hours of maintenance-free and safe operation

Energy efficiency
LED average energy consumption is significantly less than traditional fluorescent and HID fixtures

Start/restart time
Instant illumination versus 10 minute restrike time for HID

Light quality
Higher color rendering compared to fluorescent and HID

Environmental benefits
Mercury-free LED eliminates disposal costs and lower energy consumption for a smaller carbon footprint

Why Crouse-Hinds?

Rugged design
Built to withstand extreme temperatures, vibration, water and dust

High efficacy
Up to 124 lumens per watt (model dependent)

Thermal management
Effective heat sinking ensures longer life

Quality of light
Custom optics designed to maximize light distribution and intensity

Versatile mounting
LED fixtures are compatible with Crouse-Hinds' HID installed base

Why Champ VMV LED? Type 403

Rugged mid to high bay solutions. Champ VMV LED luminaires are engineered to provide maintenance-free operation while delivering long life and high lumen performance.



Built to last:

- Type 4X rated
- Impact-resistant lens sealed from the outside environment provides ingress protection against water and dust
- Die cast aluminum LED housing provides efficient thermal path to heat sink assembly
- Vertical fin design facilitates air flow and dust shedding

Simple installation and replacement:

- Contractor-friendly design is ideal for both retrofit and new construction
- Easy to retrofit using existing HID Champ mounting module
- Compact modular design for easy component replacement and future upgrades
- Available with lever lock connectors and standard three-pole terminal block



Custom optics:

- Type I, III and V optics designed to maximize light distribution and intensity*

* Type V optics standard.

Increased efficiency and durability:

- Up to 124 lumens per watt
- Economic life: 7-20 years



VMV3L-VMV11L

optimized for 8-30 foot mounting heights



VMV13L & VMV17L



VMV21L & VMV25L


optimized for 30-60 foot mounting heights

LED vs. HID savings at a glance


Why are so many facilities making the switch from HID to LED?

The numbers say it all.

VMV7L vs. 175 Watt MH



64% REDUCTION IN ENERGY COSTS



75% LOWER TOTAL COST OF OWNERSHIP



100% MAINTENANCE REDUCTION

Assumptions: Calculations based on overall life of the LED system. Energy cost of $.09 per kilowatt; 24 hour per day operation; labor rate of $75 each for 2 workers; average time for fixture maintenance of 1 hour.

Custom optics

Eaton's Crouse-Hinds continuously focuses on engineering product solutions tailored to our customers' unique needs and applications.

Champ VMV LED luminaires feature custom optics designed to maximize light distribution and intensity, providing flexibility for retrofits or new installations throughout the site.



Type III optics minimize light spillover onto the walls and direct light to the ground.

Three optical options to maximize light distribution and intensity



VMV3L - VMV11L



Type I



Type III



Type V



TYPE I

Long and rectangular for hallways, walkways, loading docks, catwalks.

Ideal for:

- Mining conveyor belts
- Aisleways and hallways
- Catwalks and walkways
- Ramps and loading docks
- Tunnels with overhead mounts

TYPE III

Wall mount light distribution, minimizing spillover on the wall.

Ideal for:

- Narrow crosswalks or passages with wall mounted fixtures
- Tunnels with wall mount
- Wall or stanchion mount requiring 180° forward throw beam patterns

TYPE V

Regular circular distribution pattern for high/low bay indoor and outdoor ceiling or pendant mount lighting.

Ideal for:

- Pendant, ceiling or stanchion mount overhead building mounts
- Processing mills, industrial plants, large buildings, warehouses, etc.

Colored LED options:

- Available in green and amber*
- Reduction in light pollution for night space observation and sky glow due to isolating blue wavelength in red and amber colors
- Wildlife-friendly
- Improves visibility for telescopes in observatories during night sky space exploration

* Custom optics not available with colored LEDs. One model per color, see assignment sheet.

Type 403

Case study: Type I optics

Catwalk/conveyor lighting

Utilizing Eaton's Crouse-Hinds lighting layout services, Champ VMV luminaires with Type I optics and HID luminaires are shown installed on a catwalk to compare photometrics.

Comparison

Champ Type I LEDs have a wider linear pattern than equivalent HID luminaires and provide more efficient light dispersion, which fully illuminates the catwalk.

Results


Champ VMV LED with Type I optics provides superior illumination along the conveyor and walkway safely. With no gaps in illumination, the optical pattern allows for increased spacing of fixtures and a safer conveyor system.

Savings realized


- **Champ Type I pattern allows for greater fixture spacing** along the catwalk or conveyor system
- Increased visibility with no dark spots results in safer conditions for workers
- LED system provides between 7 to 20 years of maintenance-free operation
- Up to 64% energy savings over the life of the fixture

Type 403

Champ® Gen III w/ Type I Optics




175W Metal Halide w/ Type I Optics



Luminaire	Calc. Type	Units	Avg.	Max.	Min.	Avg./Min.	Max./Min.
Champ VMV	Illuminance	Fc	26.91	36.9	17.4	1.55	2.12
175W MH	Illuminance	Fc	14.32	18.0	7.9	1.81	2.28

Champ VMV has broader coverage area, higher delivered footcandles and uniformity for a typical catwalk or conveyor application.



Lighting layout & design services:

Let us help you design your next big project!

Contact Crouse-Hinds Customer Service
crousecustomerctr@eaton.com
(866) 764-5454

Champ VMV Series LED Luminaires

Champ VMV Series LEDs are designed to provide full-spectrum, crisp, white light with custom IES Type I, III and V distribution.

Model	Typical lumens (Type V)*	Wattage	Lumens per watt	Equivalent HID luminaire	Typical energy savings / lifetime
VMV3L	3,531	29	122	70W-100W	Up to 77%
VMV5L	5,335	43	124	100W-150W	Up to 67%
VMV7L	7,195	62	116	150W-175W	Up to 67%
VMV9L	9,266	85	109	250W-320W	Up to 74%
VMV11L	11,440	113	101	320W-400W	Up to 74%
VMV13L	13,226	130	102	400W	Up to 68%
VMV17L	18,793	168	112	400W-600W	Up to 72%
VMV21L	22,110	196	113	600W-750W	Up to 74%
VMV25L	26,531	232	114	750W-1000W	Up to 77%

* Tolerance +/- 10%.

Applications:

- For areas with mounting heights of 8-60 feet
- Oil and gas refineries, drilling rigs, petrochemical facilities, food and beverage facilities, platforms, loading docks, tunnels, indoor/outdoor spotlighting, outdoor wall and stanchion mounted general area lighting, and where flammable vapors, gases, ignitable dusts, fibers or flyings are present
- Locations requiring continuous and consistent light levels in extreme ambient temperatures
- Where extremely corrosive, wet, dusty, hot and/or cold conditions exist
- Classified and hazardous locations

Champ VMV benefits:


- Instant illumination and restrike
- Cold temperature operation / no warm-up required
- Option for redundancy in drivers with multiple series circuits connected to each driver to avoid complete loss of illumination
- Easy installation - compact modular fixture attaches onto existing Champ mounting module
- Energy-efficient technology - up to 64% energy savings over HID fixtures
- Contains no mercury or other hazardous substances
- Shock- and vibration-resistant solid-state luminaires have no filaments or glass components that could break - greatly reduces the risk of premature failure
- Operating ambient: -40°C to 65°C (VMV3L-VMV11L models); -40°C to 55°C (VMV13L-VMV25L models)
- 5 year fixture warranty†

† Refer to page 2 of the D-0914 authorized distributor price book for Crouse-Hinds standard Terms and Conditions.

LED system:

- High intensity discrete power emitters
- Standard: cool white (5000K, 70 CRI)
  Optional: warm white, (3000K, 80 CRI)
- Custom Type I, III and V optics available
- Optics clocking in field to align Type I and Type III light patterns to illumination path for VMV13L-VMV25L

LED system lifetime rated versus economic life:



Economic life can range anywhere between 64,000 to 200,000 hours, or 7 to 20 years of maintenance-free operation.

Fixture life and years of maintenance-free operation

Ambient temperature	Fixture life (hours)	No. of years at 24 hours usage	No. of years at 12 hours usage
25°C	201,008	23	46
30°C	153,445	17	35
40°C	94,949	11	22
55°C	64,286	7	15

* 50,000 hrs of life at 65°C ambient for VMV3L-VMV11L/UNV1 models.

Fixture life:

- Rated life of 60,000 hours @ 55°C operating ambient and 24/7 continuous operation for 365 days
- Economic life of 200,000 hours @ 25°C ambient
- L70 >300,000 hours @ 55°C

Drivers

Option	Voltage: VMV3L-VMV25L
/UNV1	120-277 VAC, 50/60 Hz; 108-250 VDC, 50/60 Hz
/UNV34	347-480 VAC, 50/60 Hz

Standard materials:

- Lamp housing and adapter - die cast aluminum with Corro-free™ epoxy powder coat
- Lens - heat- and impact-resistant glass
- Gaskets - silicone
- External hardware - stainless steel
- Factory-sealed, no external seals required

Qualifications and compliances:

- DesignLights Consortium® Qualified (some models are not DLC qualified)*

Type 403

* Approved models include: VMV3L/UNV1; VMV5L/UNV1; VMV7L/UNV1; VMV9L/UNV1; VMV11L/UNV1; VMV13L/UNV1; VMV17L/UNV1; VMV21L/UNV1; VMV25L/UNV1; VMV3L/UNV34; VMV5L/UNV34; VMV7L/UNV34; VMV9L/UNV34; VMV11L/UNV34.

Refer to www.designlights.org Qualified Products List under family models for full listing details. Not all models are approved for all application categories.

Certifications and compliances:

Type 403

NEC and CEC

- Class I, Division 2, Groups A, B, C, D; Class I, Zone 2, nA nR; Class II, Groups E, F, G; Class III
- Zone 21 tb
- Simultaneous Presence
- Wet Locations, NEMA 4X, IP66

UL Standards

- UL844; UL1598 Luminaires; UL1598A Marine; UL8750; UL50; UL50E

CSA Standard

- cUL Listed to CSA Standard CSA C22.2 No. 137

IEC**

- IEC 60079-0:2011; IEC 60079-15:2010; IEC 60079-31:2008; IEC 60598-2-1:1979; IEC 60529:2001
- Ex nA nR IIC T* Gc -40 to +40
- Ex nA nR IIC T* Gc -40 to +55
- Ex nA nR IIC T* Gc -40 to +65
- Ex tb IIIC T*°C Db -40 to +40
- Ex tb IIIC T*°C Db -40 to +55
- Ex tb IIIC T*°C Db -40 to +65

VMV3L-VMV11L only

- IECEx UL 13.0052X

VMV13L-VMV25L only

- IECEx UL 14.0031X

ATEX/CE**

- EN 60079-0:2012; EN 60079-15:2010; EN 60079-31:2009; EN 60598-2-1:1989; EN 60929:1991 +A1:2001
- Ⓔx II 3 G Ex nA nR IIC T* Gc -40 to +40
- Ⓔx II 3 G Ex nA nR IIC T* Gc -40 to +55
- Ⓔx II 3 G Ex nA nR IIC T* Gc -40 to +65
- Ⓔx II 2 D Ex tb IIIC T*°C Db IP66 -40 to +40
- Ⓔx II 2 D Ex tb IIIC T*°C Db IP66 -40 to +55
- Ⓔx II 2 D Ex tb IIIC T*°C Db IP66 -40 to +65

VMV3L-VMV11L only

- DEMKO 13 ATEX 1475031X; DEMKO 13 ATEX 1305741X

VMV13L-VMV25L only

- DEMKO 14 ATEX 1324722X; DEMKO 14 ATEX 2274231X

* See temperature code table below.

** VMV3L-VMV11L rated to +65°C, VMV13L-VMV25L rated to +55°C.

Electrical ratings:

	VMV3L	VMV5L	VMV7L	VMV9L	VMV11L
Voltage range, VAC	120-277	120-277	120-277	120-277	120-277
Frequency	50/60 Hz	50/60 Hz	50/60 Hz	50/60 Hz	50/60 Hz
Input power (watts)	29	43	62	85	113
Input amps at 120-277 VAC	0.24-0.11	0.35-0.16	0.52-0.23	0.71-0.31	0.95-0.41
Voltage range, VDC	108-250	108-250	108-250	108-250	108-250
Power factor	>0.90	>0.90	>0.90	>0.90	>0.90
Total harmonic distortion (THD)	<20%	<20%	<20%	<20%	<20%
Nominal lumens† (Type V)	3,531	5,335	7,195	9,266	11,440

	VMV13L	VMV17L	VMV21L	VMV25L
Voltage range, VAC	120-277	120-277	120-277	120-277
Frequency	50/60 Hz	50/60 Hz	50/60 Hz	50/60 Hz
Input power (watts)	131	168	196	232
Input amps at 120-277 VAC	1.08-0.48	1.40-0.62	1.64-0.73	1.94-0.87
Voltage range, VDC	108-250	108-250	108-250	108-250
Power factor	>0.90	>0.90	>0.90	>0.90
Total harmonic distortion (THD)	<20%	<20%	<20%	<20%
Nominal lumens† (Type V)	13,226	18,793	22,110	26,531

† Tolerance +/- 10%.

Weights:

Luminaire	lbs.	kg.
VMV3L-VMV11L	21.8	8.07
VMV13L & VMV17L	36.0	16.32
VMV21L & VMV25L	44.0	19.95

Mounting module	lbs.	kg.
Pendant	1.25	0.57
Cone pendant	4.00	1.81
Flexible pendant	1.50	0.68
Ceiling	2.75	1.25
Wall	4.50	2.04
Angled stanchion*	3.50	1.59
Straight stanchion	4.50	2.04

* Angled stanchion for VMV3L-VMV11L models only.

Temperature codes:

Lamp/lumen output	Driver type	Ambient temperature	Class I, Div. 2	Class II, Div. I	Simultaneous rating Class I, Div. 2, Div. 1	Class I, Zone 2 AEx nA nR; Ex nA nR	Class III, Div. 1 Class II, Div. 1, Groups E, F, G Zone 21 AEx tb IIIC
3L, 5L, 7L, 9L, 11L	/UNV1	40°C	T5	T5	T3C	T6	T66°C
3L, 5L, 7L, 9L, 11L	/UNV1	55°C	T5	T4A	T3A	T5	T83°C
3L, 5L, 7L, 9L, 11L	/UNV1	65°C	T4A	T4A	T3A	T4	T92°C
3L, 5L, 7L, 9L, 11L	/UNV34	40°C	T3C	T5	T3C	T4	T70°C
3L, 5L, 7L, 9L, 11L	/UNV34	55°C	T3A	T4A	T3A	T4	T85°C
3L, 5L, 7L, 9L, 11L	/UNV34	65°C	T3A	T4A	T3A	T4	T92°C
13L, 17L	/UNV1; UNV34	40°C	T4A	T5	T4A	T6	T66°C
13L, 17L	/UNV1; UNV34	55°C	T4	T4A	T4	T5	T81°C
21L, 25L	/UNV1; UNV34	40°C	T4A	T5	T4A	T6	T71°C
21L, 25L	/UNV1; UNV34	55°C	T4	T4A	T4	T5	T86°C

Ordering information

GUILLEVIN OTTAWA
PO# 2010-RON971364D
drawings issued 2018-06-22

VMV5L2A/UNV34 page 8

Part number example
~~VMV17LW2AR1G/UNV1 S890~~

VMV 17L W 2A R1 G /UNV1 S890

Lamp/function

3L	3,531 lumen LED
5L	5,335 lumen LED
7L	7,195 lumen LED
9L	9,226 lumen LED
11L	11,440 lumen LED
13L	13,226 lumen LED
17L	18,793 lumen LED
21L	22,110 lumen LED
25L	26,531 lumen LED
GL*	Green (4,300 lumen LED)
AL*	Amber (5,000 lumen LED)

* Custom optics not available with colored LEDs.

Color temperature

BLANK	Cool (5000K), colored
W	Warm (3000K)

Mounting style

BLANK	No Cover
J*	1-½" stanchion, 25° angled
P	1-½" stanchion, straight
2A	¾" pendant
3A	1" pendant
20A	20mm pendant
25A	25mm pendant
2B	¾" cone pendant
3B	1" cone pendant
2C	¾" ceiling
3C	1" ceiling
20C	20mm ceiling
25C	25mm ceiling
2HA	¾" flexible pendant
2TW	¾" wall
3TW	1" wall
20TW	20mm wall
25TW	25mm wall

* For VMV3L-VMV11L only.

Suffixes

S812*	Trunnion mount kit with pin
S831**	Safety cable
S890	Quick clip
S891**	Diffused lens
S892***	Redundant driver
S896**	Teflon coated lens
S903	Polycarbonate lens
TB6	Six-pole terminal block

* Order with ceiling mount only.
** Not available for IEC.
*** Available for 5L & 7L only. Redundant driver standard on 9L - 25L models.
7L = 6,616 lumens with S892 suffix.

Voltage

/UNV1	120-277 VAC, 50/60 Hz; 108-250 VDC, 50/60 Hz
/UNV34	347-480 VAC, 50/60 Hz

Guard

BLANK	No guard
G	P3001 wire guard

Optics

BLANK	Type V optic standard *(all mounts)*
R1	Type I optic *(all mounts minus ceiling for 3L-11L, available with mounts for 13L-25L models)*
R1A*	Type I optic *(ceiling with conduit 45° counterclockwise or 135° clockwise from hinge)*
R1B*	Type I optic *(ceiling with conduit 45° clockwise or 135° counterclockwise from hinge)*
R3	Type III optic *(all mounts minus ceiling)*
R3AP*	Type III optic *(select when using Appleton® top hat adapter with Champ fixture)*
R3A1*	Type III optic *(ceiling with conduit 45° counterclockwise from top hat hinge)*
R3A2*	Type III optic *(ceiling with conduit 135° clockwise from top hat hinge)*
R3B1*	Type III optic *(ceiling with conduit 45° clockwise from top hat hinge)*
R3B2*	Type III optic *(ceiling with conduit 135° counterclockwise from top hat hinge)*

*For VMV3L-VMV11L only.

Type 403

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 26, 2018

BY Chester Martinez, E.I.T.


Accessories (ordered separately)

D2S20	Photocell, 120V, 50/60 Hz
D2S208 277	Photocell, 208-277V
VMVL S812 K1*	Trunnion mount kit with pin


* Order with ceiling mount only.

Mounting options and dimensions


Stanchion - 25° Angled




Stanchion - Straight




Pendant




Ceiling




Wall



Cone Pendant



Trunnion




Type 403


Photometric comparison at 15 ft. mounting height

Type 403

175W PSMH - Type I



VMV7L - Type I




Type I optical pattern




Calculation summary

Label	Calc. type (in Fc)	Avg.	Max.	Min.
VMV 175W MH Grid	Illuminance	0.45	2.8	0.0
VMV LED Grid	Illuminance	0.62	8.0	0.0

175W PSMH - Type III



VMV7L - Type III




Type III optical pattern




Calculation summary

Label	Calc. type (in Fc)	Avg.	Max.	Min.
VMV 175W MH Grid	Illuminance	0.53	3.2	0.1
VMV LED Grid	Illuminance	0.61	7.5	0.0

175W PSMH - Type V



VMV7L - Type V



Type V optical pattern



Calculation summary

Label	Calc. type (in Fc)	Avg.	Max.	Min.
VMV 175W MH Grid	Illuminance	0.51	2.8	0.1
VMV LED Grid	Illuminance	0.69	10.1	0.0

Higher average footcandles, uniformity and distribution coverage with less than half the lumens and energy consumption compared to 175W metal halide

Actual lumens (nominal†)	VMV3L	VMV5L	VMV7L	VMV9L	VMV11L
Type I	3,360	5,045	6,844	8,823	10,730
Type III	3,309	4,468	6,741	8,618	10,660
Type V	3,531	5,335	7,195	9,266	11,440

Actual lumens (nominal†)	VMV13L	VMV17L	VMV21L	VMV25L
Type I	12,842	18,194	21,404	25,685
Type III	12,493	17,699	20,822	24,987
Type V	13,266	18,793	22,110	26,531

† Tolerance +/- 10%.

Type 403

U.S. (global headquarters): Eaton's Crouse-Hinds business

1201 Wolf Street
Syracuse, NY 13208

(866) 764-5454
FAX: (315) 477-5179
FAX Orders Only:
(866) 653-0640

crousecustomerctr@eaton.com

Canada

Toll Free: 800-265-0502
FAX: (800) 263-9504
FAX Orders only: (866) 653-0645

Middle East (Dubai)

971 4 8066100
FAX: 971 4 8894813

chmesales@eaton.com

Korea

82-2-3484-6783
82-2-3484-6778

CCHK-sales@
cooperindustries.com

Mexico/Latin America/Caribbean

52-555-804-4000
FAX: 52-555-804-4020

ventascentromex@eaton.com

Singapore

65-6645-9888
FAX: 65-6297-4819

chsi-sales@
cooperindustries.com

Australia

61-2-8787-2777
FAX: 61-2-9609-2342

CEASales@
cooperindustries.com

Europe (Germany)

49 (0) 6271 806-500
49 (0) 6271 806-476

sales.CCH.de@
cooperindustries.com

China

86-21-2899-3600
FAX: 86-21-2899-4055

cchsales@
cooperindustries.com

India

91-124-4683888
FAX: 91-124-4683899

cchindia@
cooperindustries.com

For more information:

If further assistance is required, please contact an authorized Eaton Distributor, Sales Office, or Customer Service Department.

Eaton
1000 Eaton Boulevard
Cleveland, OH 44122
United States
Eaton.com

© 2018 Eaton
All Rights Reserved

Printed in USA
Publication No. 5123-0318
March 2018

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Powering Business Worldwide

LED WIDE ENCLOSED & GASKETED - EGW

Type 406



PRODUCT HIGHLIGHTS

- Vaportight design
- IP66, IP67 Certified (comparable to NEMA 6)
- NEMA 4X rated / NEMA 250-2003
- High pressure hose down (1500psi)
- NSF / ANSI Standard 2
- UL50E: standards for safety enclosures of electrical equipment
- 12 Point stainless steel latching and stainless hardware
- Sloped housing design promotes water displacement
- Optional stainless steel "V" bracket or "SB" surface bracket accessory
- RoHS Compliant

EXPECTED LIFE - Projected life of at least 60,000 hours. Contact factory for TM-21 detail.

LEDs - Use of closely-spaced medium-power, high-brightness chips minimizes pixelation and provides uniform lens luminance. Available in Cool White (5000K), Neutral White (4000K) and Warm White (3500K) color temperatures. CRI >= 80 (CW > 70). LM-80 reports available.

LENS - Frosted, injection molded, high impact acrylic is standard. An optional clear lens is also available.

HOUSING - The inner gear tray is constructed of code gauge steel. The outer housing is constructed of fiberglass reinforced polyester. Gasketing in the housing is constructed of closed cell polyurethane. Conduit entrance is provided at one end. All external hardware and hanging components are constructed of stainless steel.

ELECTRICAL - Universal voltage (120-277 Vac) input, 50/60Hz. Power factor > 0.9, THD < 20%, in-rush current < 15 Amps.

DRIVER - High-performance isolated driver features over-voltage, over-current and short-circuit (with auto-recovery) protection. Driver module is sealed to IP66 protection levels, with a Class A sound rating. 0-10 volt dimming standard.


OPERATING TEMPERATURE - -30°C to 45°C (-22°F to 113°F).

FINISH - All metal parts are painted after fabrication following treatment with phosphate rust inhibitor. Finish coating of housing reflecting surfaces is with high-reflectance (minimum 92%) polyester powder.

WARRANTY - Limited 5-year warranty

PHOTOMETRICS - Please visit our website at www.lsi-industries.com for detailed photometric data.

LISTING - Listed to UL 1598 and UL 8750



LIGHT OUTPUT - LED EGW

	Lumens (Nominal)			
	WW	NW	CW	Watts
HO	5930	5840	6540	57
VHO	9425	9590	11455	88
XHO	18972	20765	22005	164

LED Chips are frequently updated therefore values may increase.

This product, or selected versions of this product, meet the standards listed below. Please consult factory for your specific requirements.

MANUFACTURED IN USA

ARRA Funding Compliant

c UL us LISTED wet location

STANTEC PROJECT #: 110126045 SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all coordination of construction work of all trades, including those affected by shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 26, 2018

BY Chester Martinez, E.I.T.

ORDERING INFORMATION

TYPICAL ORDER EXAMPLE: **EGW 4 S LED HO CW UE**

Prefix	Length	Distribution	Light Source	Drive Current	Color Temperature	Line Voltage	Options
EGW - LED Wide Enclosed & Gasketed	4	S - Symmetric	LED	HO - High Output VHO - Very High Output XHO - Extreme High Output	CW - Cool White (5000K) NW - Neutral White (4000K) WW - Warm White (3500K)	UE - Universal Voltage (120-277V) 347 - 347V	CL - Clear Lens W6C163[1] - 6-foot, 16 gauge, 3 conductor cord with Wet Location fitting W6C164[1] - 6-foot, 16 gauge, 4 conductor cord with Wet Location fitting W6C165[1] - 6-foot, 16 gauge, 5 conductor cord with Wet Location fitting HUB - 3/4" N.P.T. HUB IN BACK / TOP (Damp Location Rated Only) LT - Lens Safety Teather EM - 1100 Lumen Emergency Battery Pack SD50 - Step Dimming to 50%

ACCESSORY ORDERING INFORMATION

Description	Order Number
Stainless Suspension Hangers ("V" Hook) (Pair)	EGWVB
Cable Hanging Set with Loop 10 ft. (pair)	LCH10
Cable Hanging Set with Loop 20 ft. (pair)	LCH20
Stainless Steel Surface Bracket	EGWSB

1- Specific voltage must be specified. Cord feed entrance available on housing end only.

Project Name Water treatment plant **Fixture Type** 406

Catalog # EGW 4 S LED HO CW 347V

© 2016
LSI INDUSTRIES INC.

Date: Jul 3, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 03, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-05
PO-AEN Stock

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [X] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 07 84 00 Firestopping

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-05
This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other
component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec
☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED
DATE 2018-07-04
BY Konrad Goluch

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-45
This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☑ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☐ Other
component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec
☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED
DATE 2018-07-04
BY Jason King

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

High performance intumescent firestop sealant FS-ONE MAX

Product description


- Intumescent (expands when exposed to fire) firestop sealant that helps protect combustible and non-combustible penetrations for up to 4 hours fire rating

Applications

- Effectively seals most common through penetrations in a variety of base materials
- For use on concrete, masonry and drywall
- Mixed and multiple penetrations
- Metal pipe penetrations
- Insulated metal pipe penetrations
- Plastic pipe penetrations
- Cable bundles and trays
- HVAC penetrations

Advantages

- One product for a variety of common through penetrations
- Cost-effective and easy-to-use solution
- Water-based and paintable
- W-rated systems available
- Ethylene glycol-free
- Industry leading VOC results
- Convenient multi application firestop solution for penetrations



Technical Data*	
Chemical basis	Water-based acrylic dispersion
Color	Red
Application temperature	41°F to 104°F
Storage and transportation range	41°F to 77°F
Approx. cure time *	4 mm / 3 days
Shelf life	12 months **
Temperature resistance range	-4°F to 212°F
Mold and mildew performance	Class 0 (ASTM G21-13)
Mold and mildew resistant	Yes
Surface burning characteristics (ASTM E 84-14)	Flame Spread: 0 Smoke Development: 10
Approvals	California State Fire Marshal - in progress
Tested in accordance with	ASTM G21 ASTM E 90 CAN/ULC-S115 UL 1479 ASTM E 814 ASTM E84

* At 75°F (24°C) and 50% relative humidity
** from date of manufacture

CLASSIFIED C UL US
FILL, VOID OR CAVITY MATERIAL
FOR USE IN THROUGH-PENETRATION
FIRESTOP SYSTEMS
SEE UL FIRE RESISTANCE DIRECTORY
66Y7

FM APPROVED

FBC SYSTEM COMPATIBLE
Visit fbcsystemcompatible.com.
FBC™ is a trademark of the Lubrizol Corporation.



W rated

01/15 DBS

Material Safety Data Sheet
acc. to ISO 11014

Printing date 09/18/2014 Version number 1 Reviewed on 09/18/2014

*
1 Identification

· **Product identifier**

· **Trade name: FS-ONE MAX**
· **Relevant identified uses of the substance or mixture and uses advised against** No further relevant information available.
· **Application of the substance / the mixture** Construction chemicals

· **Details of the supplier of the safety data sheet**
· **Manufacturer/Supplier:**
Hilti (Canada) Corp.
2360 Meadowpine Boulevard
Mississauga, Ontario L5N 6S2
Phone: (800) 363-4458
Fax: (800) 363-4459

· **Information department:**
chemicals.hse@hilti.com
see section 16
· **Emergency telephone number:**
Chem-Trec
Tel.: 1 800 424 9300
Hilti (Canada) Corp.
Phone: (800) 363-4458
Fax: (800) 363-4459

*
2 Hazard(s) identification

· **Classification of the substance or mixture** The product is not classified according to the Globally Harmonized System (GHS).

· **Label elements**
· **GHS label elements** Void
· **Hazard pictograms** Void
· **Signal word** Void
· **Hazard statements** Void
· **Hazard description:**
· **WHMIS classification** -
· **Other hazards**
· **Results of PBT and vPvB assessment**
· **PBT:** Not applicable.
· **vPvB:** Not applicable.

*
3 Composition/information on ingredients

· **Chemical characterization: Mixtures**
· **Description:** .

· **Dangerous components:** Void
· **Additional information** For the wording of the listed risk phrases refer to section 16.

4 First-aid measures

· **Description of first aid measures**
· **General information** No special measures required.
· **After inhalation** Take affected persons into fresh air and keep quiet.
· **After skin contact** Immediately wash with water and soap and rinse thoroughly.
· **After eye contact** Rinse opened eye for several minutes under running water. Then consult a doctor.
· **After swallowing** Seek immediate medical advice.
· **Most important symptoms and effects, both acute and delayed** No further relevant information available.
· **Indication of any immediate medical attention and special treatment needed** No further relevant information available.

5 Fire-fighting measures

· **Extinguishing media**
· **Suitable extinguishing agents** CO2, extinguishing powder or water spray. Fight larger fires with water spray or alcohol resistant foam.
· **Special hazards arising from the substance or mixture**
In case of fire, the following can be released:
Carbon monoxide (CO)
Carbondioxide (CO2)
· **Advice for firefighters**
· **Protective equipment:** Ensure adequate ventilation

6 Accidental release measures

· **Personal precautions, protective equipment and emergency procedures**
Ensure adequate ventilation
Wear protective clothing.

(Contd. on page 2)

Material Safety Data Sheet
acc. to ISO 11014

Printing date 09/18/2014 | Version number 1 | Reviewed on 09/18/2014

Trade name: FS-ONE MAX

(Contd. of page 1)

Particular danger of slipping on leaked/spilled product.
· **Environmental precautions:** Do not allow product to reach sewage system or any water course.
· **Methods and material for containment and cleaning up:**
Pick up mechanically.
Dispose contaminated material as waste according to item 13.
· **Reference to other sections**
See Section 7 for information on safe handling
See Section 8 for information on personal protection equipment.
See Section 13 for disposal information.

*
7 Handling and storage

· **Precautions for safe handling** No special measures required.
· **Information about protection against explosions and fires:** No special measures required.

· **Conditions for safe storage, including any incompatibilities**
· **Storage**
· **Requirements to be met by storerooms and receptacles:** keep containers securely closed and dry, store at 5 - 25 °C / 41 - 77 °F
· **Information about storage in one common storage facility:** Not required.
· **Further information about storage conditions:** None.

· **Storage class** 10
· **Specific end use(s)** No further relevant information available.

*
8 Exposure controls/personal protection

· **Control parameters**
· **Components with limit values that require monitoring at the workplace:**
The product does not contain any relevant quantities of materials with critical values that have to be monitored at the workplace.
· **Additional information:** The lists that were valid during the creation were used as basis.

· **Exposure controls**
· **Personal protective equipment**
· **General protective and hygienic measures**
The usual precautionary measures for handling chemicals should be followed.
Avoid contact with the eyes and skin.
Keep away from foodstuffs, beverages and feed.
Wash hands before breaks and at the end of work.
· **Breathing equipment:** Not necessary if room is well-ventilated.
· **Protection of hands:**



Protective gloves.

The glove material has to be impermeable and resistant to the product/ the substance/ the preparation.
Selection of the glove material on consideration of the penetration times, rates of diffusion and the degradation
EN 374
· **Material of gloves**
Synthetic gloves
The selection of the suitable gloves does not only depend on the material, but also on further marks of quality and varies from manufacturer to manufacturer. As the product is a preparation of several substances, the resistance of the glove material can not be calculated in advance and has therefore to be checked prior to the application.
· **Penetration time of glove material**
The exact break through time has to be found out by the manufacturer of the protective gloves and has to be observed.
· **For the permanent contact gloves made of the following materials are suitable:** Nitrile rubber, NBR
· **Eye protection:**



Tightly sealed goggles.

EN 166 + EN 170
· **Body protection:**



Protective work clothing.

(Contd. on page 3)

HILTI

Material Safety Data Sheet
acc. to ISO 11014

Printing date 09/18/2014 | Version number 1 | Reviewed on 09/18/2014

Trade name: FS-ONE MAX

(Contd. of page 2)

*
9 Physical and chemical properties

· **Information on basic physical and chemical properties**	
· **General Information**	
· **Appearance:**	
Form:	Pasty
Color:	Red
· **Odor:**	Characteristic
· **Odour threshold:**	Not determined.
· **pH-value:**	Not determined.
· **Change in condition**	
Melting point/Melting range:	Not determined.
Boiling point/Boiling range:	100 °C (212 °F)
· **Flash point:**	Not applicable
· **Flammability (solid, gaseous)**	Not applicable.
· **Ignition temperature:**	
Decomposition temperature:	Not determined.
· **Auto igniting:**	Product is not selfigniting.
· **Danger of explosion:**	Product does not present an explosion hazard.
· **Explosion limits:**	
Lower:	Not determined.
Upper:	Not determined.
· **Vapor pressure at 20 °C (68 °F):**	23 hPa (17 mm Hg)
· **Density:**	Not determined
· **Relative density**	Not determined.
· **Vapour density**	Not determined.
	Not applicable.
· **Evaporation rate**	Not determined.
· **Solubility in / Miscibility with**	
Water:	Not miscible or difficult to mix
· **Partition coefficient (n-octanol/water):**	Not determined.
· **Viscosity:**	
dynamic:	Not determined.
kinematic:	Not determined.
· **Solvent content:**	
Organic solvents:	1.0 %
Water:	18.5 %
· **Other information**	No further relevant information available.

10 Stability and reactivity

· **Reactivity**
· **Chemical stability**
· **Thermal decomposition / conditions to be avoided:** No decomposition if used according to specifications.
· **Possibility of hazardous reactions** No dangerous reactions known
· **Conditions to avoid** No further relevant information available.
· **Incompatible materials:** No further relevant information available.
· **Hazardous decomposition products:** No dangerous decomposition products known

*
11 Toxicological information

· **Information on toxicological effects**
· **Acute toxicity:**
· **Primary irritant effect:**
· **on the skin:** No irritant effect.
· **on the eye:** No irritating effect.
· **Sensitization:** No sensitizing effects known.
· **Additional toxicological information:**
When used and handled according to specifications, the product does not have any harmful effects according to our experience and the information provided to us.

· **Carcinogenic categories**

· **IARC (International Agency for Research on Cancer)**
None of the ingredients is listed.

· **NTP (National Toxicology Program)**
None of the ingredients is listed.

(Contd. on page 4)

Material Safety Data Sheet
acc. to ISO 11014

Printing date 09/18/2014 | Version number 1 | Reviewed on 09/18/2014

Trade name: FS-ONE MAX

(Contd. of page 3)

· **OSHA-Ca (Occupational Safety & Health Administration)**
None of the ingredients is listed.

12 Ecological information

· **Toxicity**
· **Aquatic toxicity:** No further relevant information available.
· **Persistence and degradability** No further relevant information available.
· **Bioaccumulative potential** No further relevant information available.
· **Mobility in soil** No further relevant information available.
· **Results of PBT and vPvB assessment**
· **PBT:** Not applicable.
· **vPvB:** Not applicable.
· **Other adverse effects** No further relevant information available.

13 Disposal considerations

· **Waste treatment methods**
· **Recommendation** Must not be disposed of together with household garbage. Do not allow product to reach sewage system.
· **European waste catalogue:**
08 00 00
08 04 00
08 04 10

· **Uncleaned packagings:**
· **Recommendation:** Dispose of packaging according to regulations on the disposal of packagings.

14 Transport information

· **UN-Number** · **DOT, TDG, ADN, IMDG, IATA**	Void
· **UN proper shipping name** · **DOT, TDG, ADN, IMDG, IATA**	Void
· **Transport hazard class(es)** · **DOT, TDG, ADN, IMDG, IATA** · **Class**	Void
· **Packing group** · **DOT, TDG, IMDG, IATA**	Void
· **Environmental hazards:** · **Marine pollutant:**	No
· **Special precautions for user**	Not applicable.
· **Transport in bulk according to Annex II of MARPOL73/78 and the IBC Code**	Not applicable.
· **UN "Model Regulation":**	-

*

15 Regulatory information

· **Safety, health and environmental regulations/legislation specific for the substance or mixture**
· **Sara**

· **Section 313 (Specific toxic chemical listings):**
None of the ingredients are listed.

· **TSCA (Toxic Substances Control Act):**
All ingredients are listed.

· **Proposition 65:**

· **Chemicals known to cause cancer:**
None of the ingredients are listed.

· **Cancerogenity categories**

· **EPA (Environmental Protection Agency)**
None of the ingredients is listed.

· **TLV (Threshold Limit Value established by ACGIH)**
None of the ingredients is listed.

· **MAK (German Maximum Workplace Concentration)**
None of the ingredients is listed.

(Contd. on page 5)

Material Safety Data Sheet
acc. to ISO 11014

Trade name: FS-ONE MAX

(Contd. of page 4)

· **NIOSH-Ca (National Institute for Occupational Safety and Health)**
None of the ingredients is listed.

· **National regulations**

· **Information about limitation of use:** Employment restrictions concerning young persons must be observed.
· **Chemical safety assessment:** not required.

16 Other information

This information is based on our present knowledge. However, this shall not constitute a guarantee for any specific product features and shall not establish a legally valid contractual relationship.

· **Department issuing MSDS:**
Hilti Corporation
Business Unit Chemicals
Quality/Safety/Environment
FL-9494 Schaan / Liechtenstein

chemicals.hse@hilti.com
Tel.: +423 234 3004
FAX.: +423 234 3462
· **Date of preparation / last revision** 09/18/2014 / -
· **Abbreviations and acronyms:**
IMDG: International Maritime Code for Dangerous Goods
DOT: US Department of Transportation
IATA: International Air Transport Association
ACGIH: American Conference of Governmental Industrial Hygienists
EINECS: European Inventory of Existing Commercial Chemical Substances
ELINCS: European List of Notified Chemical Substances
CAS: Chemical Abstracts Service (division of the American Chemical Society)
WHMIS: Workplace Hazardous Materials Information System (Canada)
· *** Data compared to the previous version altered.**

CERTIFICATE OF COMPLIANCE

Certificate Number	20150108-R13240
Report Reference	R13240
Issue Date	2015-January-08

Issued to: Hilti Construction Chemicals, Div of Hilti Inc.
5400 S 122nd East Ave
Tulsa, OK 74146

This is to certify that representative samples of Fill, Void or Cavity Materials
Fill, Void or Cavity Materials Certified for Canada
FS-ONE MAX Intumescent Sealant for use in Through-Penetration Firestop and Joint Systems in the UL Fire Resistance Directory and in the Products Certified for Canada Directory.

Have been investigated by UL in accordance with the Standard(s) indicated on this Certificate.

Standard(s) for Safety: ANSI/UL 1479, "Fire Tests of Through-Penetration Firestops," – Edition 4
ANSI/UL 2079, "Tests for Fire Resistance of Building Joint Systems," – Edition 4 – Revision Date 2014/12/17
CAN/ULC-S115, "Standard Method of Fire Tests of Firestop Systems." – Edition 4 – Issue Date 2011/06/01

Additional Information: See the UL Online Certifications Directory at www.ul.com/database for additional information

Only those products bearing the UL Classification Mark should be considered as being covered by UL's Classification and Follow-Up Service.

The UL Classification Mark includes: UL in a circle: with the word "CLASSIFIED" (as shown); a control number (may be alphanumeric) assigned by UL; a statement to indicate the extent of UL's evaluation of the product; and the product category name (product identity) as indicated in the appropriate UL Directory.

Look for the UL Classification Mark on the product.

William R. Carney, Director, North American Certification Programs

UL LLC

Any information and documentation involving UL Mark services are provided on behalf of UL LLC (UL) or any authorized licensee of UL. For questions, please contact a local UL Customer Service Representative at www.ul.com/contactus

January 30, 2015

To Whom It May Concern:

Re: Hilti FS-ONE MAX Firestop – LEED Info

The Hilti FS-ONE MAX Firestop is manufactured in Germany.

There is no post-consumer or post-industrial content in FS-ONE MAX and it cannot be recycled. The VOC content for FS-ONE MAX is 9 grams/liter.

FS-ONE MAX is not regulated as a hazardous waste by the Canadian EPA Standards. The regulations for the disposal of non-regulated industrial waste can vary from province to province and even city to city. For this reason, you should consult your local and provincial regulatory agencies for direction on disposal.

Please feel free to contact me at (918) 872-3704 if you have questions.

Sincerely,



Jerry Metcalf MPH, CHMM
Safety/Environmental Manager
Hilti Inc
(918) 872 3704
jerry.metcalf@hilti.com

Rev. Date: 12/19/2014

Hilti, Inc.
5400 South 122nd East Avenue
Tulsa, OK 74146

1-800-879-8000
www.hilti.com

February 2015

To Whom It May Concern:

Hilti FS-ONE Intumescent Firestop Sealant is being discontinued and replaced by FS-ONE MAX Intumescent Firestop Sealant. The listed UL/cUL systems on the next page have been updated to include FS-ONE MAX.

Testing is ongoing. Please check online for the most up to date listings.

As compared to FS-ONE, the new FS-ONE MAX offers W-rated systems, superior handling properties, extended shelf life, and is now ethylene glycol free.

The new FS-ONE MAX will be offered in the same package types as the FS-ONE Intumescent Firestop Sealant (cartridge, foil and bucket). Item numbers have changed.

Item Number	Product Type	Product Name
2101534	Firestop Intumescent Sealant 10 oz. cartridge	FS-ONE MAX
2101535	Firestop Intumescent Sealant 20 oz. foil	FS-ONE MAX
2101536	Firestop Intumescent Sealant 5 gallon pail	FS-ONE MAX

Sincerely,



Kevin Brandon
Fire Protection Product Manager
Hilti, Inc.

United States www.us.hilti.com/firestop
Canada www.hilti.ca/firestop

Testing is ongoing. Please check online for the most up to date listings.

FS-ONE MAX Intumescent Firestop Sealant for use in Joint System

BW-S-0001, BW-S-0002, CJ-D-0008, CJ-D-0009, CJ-D-0010, HW-D-0060, HW-D-0061, HW-D-0118, HW-D-0119, HW-D-0120, HW-D-0528, HW-D-0529, HW-D-0530, HW-D-1011, HW-D-1012, HW-D-1020, HW-S-0036, HW-S-0037, HW-S-0038, HW-S-0039, HW-S-0090.

FS-ONE MAX Intumescent Firestop Sealant for use in Through-Penetration Firestop System

C-AJ-0070, C-AJ-0090, C-AJ-0138, C-AJ-1149, C-AJ-1150, C-AJ-1151, C-AJ-1152, C-AJ-1153, C-AJ-1154, C-AJ-1155, C-AJ-1156, C-AJ-1158, C-AJ-1172, C-AJ-1173, C-AJ-1174, C-AJ-1177, C-AJ-1184, C-AJ-1226, C-AJ-1278, C-AJ-1291, C-AJ-1326, C-AJ-1342, C-AJ-1346, C-AJ-1380, C-AJ-1421, C-AJ-1454, C-AJ-1513, C-AJ-1534, C-AJ-1575, C-AJ-1597, C-AJ-1609, C-AJ-1610, C-AJ-2062, C-AJ-2066, C-AJ-2091, C-AJ-2094, C-AJ-2095, C-AJ-2098, C-AJ-2109, C-AJ-2110, C-AJ-2118, C-AJ-2141, C-AJ-2164, C-AJ-2167, C-AJ-2168, C-AJ-2169, C-AJ-2170, C-AJ-2217, C-AJ-2218, C-AJ-2220, C-AJ-2283, C-AJ-2284, C-AJ-2285, C-AJ-2294, C-AJ-2304, C-AJ-2305, C-AJ-2335, C-AJ-2336, C-AJ-2337, C-AJ-2342, C-AJ-2343, C-AJ-2371, C-AJ-2372, C-AJ-2393, C-AJ-2402, C-AJ-2407, C-AJ-2419, C-AJ-2420, C-AJ-2434, C-AJ-2435, C-AJ-2451, C-AJ-2468, C-AJ-2469, C-AJ-2488, C-AJ-2567, C-AJ-2569, C-AJ-2570, C-AJ-2599, C-AJ-2600, C-AJ-2613, C-AJ-2631, C-AJ-2632, C-AJ-2639, C-AJ-2647, C-AJ-2667, C-AJ-2674, C-AJ-2677, C-AJ-2700, C-AJ-3069, C-AJ-3070, C-AJ-3078, C-AJ-3079, C-AJ-3084, C-AJ-3095, C-AJ-3096, C-AJ-3152, C-AJ-3180, C-AJ-3198, C-AJ-3209, C-AJ-3232, C-AJ-3236, C-AJ-3239, C-AJ-3281, C-AJ-3283, C-AJ-3284, C-AJ-3285, C-AJ-3298, C-AJ-3318, C-AJ-3319, C-AJ-3320, C-AJ-4034, C-AJ-4035, C-AJ-4071, C-AJ-4083, C-AJ-4093, C-AJ-4094, C-AJ-5044, C-AJ-5045, C-AJ-5046, C-AJ-5047, C-AJ-5048, C-AJ-5057, C-AJ-5061, C-AJ-5069, C-AJ-5090, C-AJ-5091, C-AJ-5096, C-AJ-5184, C-AJ-5185, C-AJ-5198, C-AJ-5277, C-AJ-5289, C-AJ-5301, C-AJ-5320, C-AJ-5341, C-AJ-5342, C-AJ-5343, C-AJ-6017, C-AJ-6042, C-AJ-7006, C-AJ-7051, C-AJ-7084, C-AJ-7095, C-AJ-7098, C-AJ-7103, C-AJ-7104, C-AJ-7111, C-AJ-7122, C-AJ-7123, C-AJ-7140, C-AJ-7145, C-AJ-8038, C-AJ-8041, C-AJ-8044, C-AJ-8056, C-AJ-8058, C-AJ-8081, C-AJ-8099, C-AJ-8100, C-AJ-8107, C-AJ-8110, C-AJ-8143, C-AJ-8166, C-AJ-8178, C-AJ-8207, C-AJ-8208, C-AJ-8209, C-AJ-8210, C-AJ-8211, C-BJ-1034, C-BJ-1037, C-BJ-1045, C-BJ-1046, C-BJ-1055, C-BJ-1059, C-BJ-2011, C-BJ-2012, C-BJ-2013, C-BJ-2014, C-BJ-2016, C-BJ-2017, C-BJ-2021, C-BJ-2028, C-BJ-2040, C-BJ-2041, C-BJ-3024, C-BJ-3031, C-BJ-4025, C-BJ-4026, C-BJ-5006, C-BJ-5007, C-BJ-5013, C-BJ-5015, C-BJ-5018, C-BJ-7005, C-BJ-8010, C-BJ-8013, C-BJ-8024, C-BJ-8027, F-A-1014, F-A-1018, F-A-1028, F-A-1029, F-A-1105, F-A-1108, F-A-1127, F-A-1134, F-A-1135, F-A-1137, F-A-2009, F-A-2025, F-A-2046, F-A-2058, F-A-2067, F-A-2068, F-A-2074, F-A-2075, F-A-2089, F-A-2143, F-A-2154, F-A-2209, F-A-3012, F-A-3022, F-A-5019, F-A-5021, F-A-8004, F-B-2029, F-B-5003, F-C-0002, F-C-1009, F-C-1059, F-C-1106, F-C-1134, F-C-1135, F-C-1142, F-C-1147, F-C-2029, F-C-2030, F-C-2071, F-C-2081, F-C-2128, F-C-2142, F-C-2160, F-C-2189, F-C-2203, F-C-2204, F-C-2230, F-C-2231, F-C-2232, F-C-2262, F-C-2263, F-C-2270, F-C-2310, F-C-2334, F-C-2335, F-C-2382, F-C-2389, F-C-2401, F-C-2403, F-C-2404, F-C-3012, F-C-3044, F-C-3094, F-C-5004, F-C-5036, F-C-5037, F-C-5086, F-C-7013, F-C-7036, F-C-7037, F-C-7042, F-C-7043, F-C-7055, F-C-7057, F-C-7058, F-C-7059, F-C-8009, F-C-8014, F-C-8026, F-C-8038, F-E-1004, F-E-1018, F-E-2005, F-E-2026, F-E-2027, F-E-2028, F-E-2029, F-E-2033, F-E-3005, F-E-3012, F-E-5004, F-E-5013, F-E-7008, F-E-8008, W-J-0007, W-J-0015, W-J-0022, W-J-1020, W-J-1021, W-J-1022, W-J-1028, W-J-1041, W-J-1042, W-J-1058, W-J-1067, W-J-1068, W-J-1088, W-J-1089, W-J-1095, W-J-1174, W-J-1175, W-J-1191, W-J-1193, W-J-1202, W-J-1210, W-J-1214, W-J-1215, W-J-1221, W-J-1222, W-J-1226, W-J-1245, W-J-2019, W-J-2057, W-J-2072, W-J-2091, W-J-2107 W-J-2108, W-J-2115, W-J-2120, W-J-2121, W-J-2191, W-J-2205, W-J-2206, W-J-2207, W-J-2218, W-J-2229, W-J-2230, W-J-2236, W-J-2237, W-J-2242, W-J-2255, W-J-3050, W-J-3060, W-J-3061, W-J-3074, W-J-3121, W-J-3167, W-J-3168, W-J-3188, W-J-3189, W-J-3190, W-J-3196, W-J-3197, W-J-3199, W-J-4016, W-J-4027, W-J-4029, W-J-4048, W-J-4059, W-J-4060, W-J-4072, W-J-5003, W-J-5028, W-J-5041, W-J-5066, W-J-5067, W-J-5122, W-J-5134, W-J-5136, W-J-5145, W-J-5150, W-J-5151, W-J-5152, W-J-6003, W-J-7021, W-J-7022, W-J-7029, W-J-7038, W-J-7091, W-J-7109, W-J-7110, W-J-7112, W-J-7123, W-J-7124, W-J-8004, W-J-8007, W-J-8008, W-J-8009, W-J-8016, W-J-8022, W-J-8034, W-J-8035, W-J-8039, W-J-8043, W-J-8044, W-J-8045, W-J-8047, W-J-8048, W-J-8049, W-J-8050, W-J-8051, W-K-3002, W-L-0013, W-L-0014, W-L-0018, W-L-0019, W-L-0023, W-L-0030, W-L-0040, W-L-0042, W-L-0043, W-L-1054, W-L-1055, W-L-1056, W-L-1057, W-L-1058, W-L-1085, W-L-1092, W-L-1095, W-L-1110, W-L-1111, W-L-1148, W-L-1164, W-L-1165, W-L-1176, W-L-1205, W-L-1206, W-L-1214, W-L-1243, W-L-1252, W-L-1304, W-L-1359, W-L-1367, W-L-1380, W-L-1389, W-L-1392, W-L-1406, W-L-1408, W-L-1410, W-L-1412, W-L-1440, W-L-1441, W-L-1464, W-L-1465, W-L-1496, W-L-1497, W-L-2043, W-L-2044, W-L-2045, W-L-2051, W-L-2052, W-L-2053, W-L-2055, W-L-2075, W-L-2078, W-L-2098, W-L-2124, W-L-2127, W-L-2128, W-L-2165, W-L-2184, W-L-2186, W-L-2196, W-L-2197, W-L-2217, W-L-2236, W-L-2244, W-L-2245, W-L-2251, W-L-2292, W-L-2295, W-L-2315, W-L-2330, W-L-2335, W-L-2340, W-L-2341, W-L-2345, W-L-2377, W-L-2406, W-L-2411, W-L-2444, W-L-2445, W-L-2447, W-L-2453, W-L-2466, W-L-2467, W-L-2471, W-L-2472, W-L-2473, W-L-2474, W-L-2480, W-L-2482, W-L-2509, W-L-2510, W-L-2537, W-L-2538, W-L-2541, W-L-2546, W-L-2557, W-L-2558, W-L-2568, W-L-2583, W-L-2584, W-L-2593, W-L-2602, W-L-2603, W-L-3045, W-L-3046, W-L-3047, W-L-3048, W-L-3049, W-L-3058, W-L-3059, W-L-3065, W-L-3071, W-L-3079, W-L-3112, W-L-3139, W-L-3161, W-L-3185, W-L-3213, W-L-3220, W-L-3224, W-L-3226, W-L-3272, W-L-3278, W-L-3307, W-L-3310, W-L-3320, W-L-3334, W-L-3335, W-L-3382, W-L-3384, W-L-3385, W-L-3391, W-L-3392, W-L-3394, W-L-3396, W-L-4006, W-L-4011, W-L-4019, W-L-4038, W-L-4048, W-L-4060, W-L-4081, W-L-5016, W-L-5021, W-L-5022, W-L-5024, W-L-5025, W-L-5026, W-L-5027, W-L-5028, W-L-5046, W-L-5047, W-L-5073, W-L-5143, W-L-5144, W-L-5223, W-L-5224, W-L-5225, W-L-5240, W-L-5244, W-L-5257, W-L-5259, W-L-5260, W-L-5261, W-L-5263, W-L-5274, W-L-5292, W-L-5293, W-L-5294, W-L-6017, W-L-6019, W-L-7017, W-L-7018, W-L-7040, W-L-7042, W-L-7059, W-L-7068, W-L-7069, W-L-7096, W-L-7121, W-L-7124, W-L-7130, W-L-7151, W-L-7153, W-L-7154, W-L-7155, W-L-7156, W-L-7157, W-L-7158, W-L-7159, W-L-7188, W-L-7198, W-L-8004, W-L-8013, W-L-8014, W-L-8015, W-L-8023, W-L-8035, W-L-8047, W-L-8052, W-L-8059, W-L-8065, W-L-8071, W-L-8079, W-L-8081, W-L-8082, W-L-8085, W-L-8086, W-L-8087, W-L-8093, W-L-8094, W-L-8095, W-L-8098

FS-ONE MAX Intumescent Firestop Sealant for Canadian-Specific Systems

C-AJ-0004, C-AJ-1010, C-AJ-1011, C-AJ-1016, C-AJ-1023, C-AJ-1612, C-AJ-2021, C-AJ-2022, C-AJ-2023, C-AJ-2024, C-AJ-2035, C-AJ-2042, C-AJ-2049, C-AJ-2054+, C-AJ-2055+, C-AJ-2056+, C-AJ-2057+, C-AJ-2061, C-AJ-2070, C-AJ-2071, C-AJ-2072, C-AJ-2078, C-AJ-2079, C-AJ-2080, C-AJ-2678, C-AJ-3007, C-AJ-8014, F-A-2009, F-B-2008, F-A-2026+, F-C-2005, F-C-2006, F-C-2007, F-C-2009, F-C-2010, F-C-2035, F-C-2045, F-C-2378+, F-C-2416, F-C-7042, F-E-2005, F-E-2006, W-J-2019, W-J-2027, W-J-2028, W-L-2028, W-L-2050, W-J-2029+, W-J-2030, W-J-2031, W-J-2032, W-J-2245, W-J-2246, W-J-2247, W-J-5136, W-J-7001, W-J-8005, W-L-8005, W-L-0005, W-L-1406, W-L-2018, W-L-2027, W-L-2031, W-L-2032, W-L-2038, W-L-2043, W-L-2044, W-L-2047, W-L-2048, W-L-2052, W-L-2056, W-L-2057, W-L-2060, W-L-2061, W-L-2062, W-L-2406, W-L-2447, W-L-2471, W-L-2472, W-L-2565, W-L-2578, W-L-3307, W-L-5010, W-L-5011, W-L-5259, W-L-5260, W-L-5263, W-J-7007, W-L-8001, W-L-8010.

FS-ONE MAX Intumescent Firestop Sealant for Intertek Systems

HI/PHV 120-01 (now HI/PF 120-01) (now HI/PF 120-02), HI/PHV 120-03 (now HI/PF 120-03), HI/PHV 120-04 (now HI/PF 120-04), HI/PHV 120-05 (now HI/PF 120-05), HI/PV 60-01 (now HI/PF 60-01)

Hilti FS-ONE MAX product substitution letter

Firestop Putty Pad CFS-P PA

Product description
- A moldable firestop putty designed to help protect electrical outlet boxes


Product features
- Applied by hand, no tools required
- Fast, simple installation
- No electrical conductivity
- Paper backing may be left on one side

Areas of application
- Protection of electrical outlet boxes
- Commercial and residential applications
- Acoustically rated drywall

For use with
- Gypsum wall assemblies with wood or metal studs

Examples
- Where two outlets are within a single stud/cavity or within 24" measured horizontally (not back to back unless specified by the specific UL approval)

Installation instructions for CFS-P PA
Notice
- Before handling, read Material Safety Data Sheet and product label for safe usage and health information.
- Refer to the applicable listing (CLIV) in the UL Fire Resistance Directory or Hilti Firestop Systems Guide for complete installation information



Technical Data*	CFS-P PA
Dimensions (LxW)	CFS-P PA: 6" x 7" CFS-P PA: 7.25" x 7.25" CFS-P PA: 9.25" x 9.25"
Consistency	Moldable putty
Color	Dark red
Application temperature range	32°F to 104°F
Curing time	Non-curing
Density	1.45 g/cm³
Mold and mildew performance (ASTM G-21)	Class 0, no growth
Surface burning characteristics (ASTM E 84)	Flame spread: 0 Smoke development: 10
Sound transmission classification (ASTM E 90-97)	59 (Relates to specific construction)
LEED VOC	0.18 lb/gal (US)
Tested in accordance with	UL 263 ASTM E 84 ASTM G 21 ASTM E 90 CAN/ULC-S101

*At 73°F (23°C) and 50% relative humidity

CLASSIFIED c UL us

WALL OPENING PROTECTIVE MATERIAL
FIRE RESISTANCE CLASSIFICATION
SEE PRODUCT CATEGORY IN
UL FIRE RESISTANCE DIRECTORY
5BP5

Hilti Firestop
Saving lives through innovation and education

Hilti. Outperform. Outlast.

MATERIAL SAFETY DATA SHEET

Product identifier: **CFS-P PA Putty Pads**

Product use: Firestopping putty

Supplier: Hilti (Canada) Corporation, 2360 Meadowpine Blvd., Mississauga, Ontario L5N 6S2

Originator Hilti, Inc., P. O. Box 21148, Tulsa, Oklahoma, USA 74121

Emergency number: **Chem-Trec: 1 800 424 9300**

INGREDIENTS INFORMATION

Ingredient	CAS Number	% (wt.)	LC_{50}, (rat)	LD_{50} (rat)	TLV	STEL
Calicum carbonate	1317-65-3	15-40	N/Av	N/Av	NE	NE
Clay	1332-58-7	10-30	N/Av	N/Av	2 mg/m^3(R)	NE
1,3 Propanediol,2,2, bis(hydroxymethyl)	115-77-5	1-5	N/Av	19,500 mg/kg	10 mg/m^3	NE
Silica	14808-60-7	0.1-1	N/Av	N/Av	0.025 mg/m^3(R)	NE
Petroleum distillates	64742-47-8	0.1-1	N/Av	N/Av	NE	NE

PHYSICAL PROPERTIES

Appearance / Physical state:	Red coloured putty.	**Odour:**	Negligible odour.
Specific gravity (at 20ºC):	1.39	**VOC content:**	21 g/l
Vapour pressure (at 20ºC):	Not applicable.	**Vapour density:**	Not applicable.
Evaporation rate:	Not applicable.	**Boiling point:**	Not applicable.
Freezing point:	Not applicable.	**pH:**	Not determined.
Coefficient of H_20 / oil distrib:	Not applicable.	**Solubility in water:**	Not soluble.

FIRE AND EXPLOSION DATA

Flash point / Method	Not applicable	**Flammable limits:**	Not applicable
Conditions of flammability:	Not applicable	**Auto-ignition temperature:**	Not applicable
Means of extinction:	Water, CO_2, Dry Chemical, Foam.		
Special fire fighting procedures:	None known. A NIOSH-approved self-contained breathing apparatus (SCBA) should be worn when fighting fires involving chemicals.		
Hazardous combustion products:	None known. Thermal decomposition products such as oxides of carbon can be produced under fire conditions.		
Sensitivity to mechanical impact / static discharge:	Not susceptible to mechanical impact or to a static discharge.		

REACTIVITY DATA

Stability:	Stable.	**Conditions of reactivity:**	None known.
Incompatible materials:	None known.		
Hazardous decomposition products:	Thermal decomposition can yield CO and CO_2.		

HILTI ® is a registered trademark of Hilti Corp.

TOXICOLOGICAL PROPERTIES

Likely routes of exposure:	☐ None known ☒ Skin contact ☐ Skin absorption ☒ Eye contact ☐ Inhalation
Exposure limits:	None established.
Acute effects of exposure:	**Eyes** - Irritation or watering may occur but injury is unlikely. **Skin** - No effects expected. Irritation is possible with some individuals. **Inhalation** - No effects expected. **Ingestion** - Not considered a route of exposure. No adverse effects known.
Chronic effects of exposure:	None known.
Synergistic materials:	None known.

FIRST AID MEASURES

Eyes:	Flush with plenty of water. Call a physician if symptoms occur.
Skin:	Practice good hygiene; wash before eating or smoking.
Inhalation:	No effects expected.
Ingestion:	Not a likely route of exposure.
Other:	Referral to a physician is recommended if there is any question about the seriousness of the injury/exposure

PREVENTIVE MEASURES

Engineering controls:	General (natural or mechanically induced fresh air movements).
Eye protection:	Safety glasses with side shields are recommended.
Skin protection:	Impermeable gloves recommended.
Respiratory protection:	None normally required.
Other:	No additional measures are normally required.
Handling procedures and equipment:	For industrial use only. Do not get into eyes. Avoid prolonged or repeated contact with skin. Practice good hygiene practices; i.e., wash after using and before eating or smoking.
Storage requirements:	Keep out of reach of children. Store between 5° and 25° C.
Spill, leak or release:	Not applicable.
Waste disposal:	Consult with regulatory agencies or your corporate personnel for disposal methods that comply with local, provincial, and federal safety, health and environmental regulations.
Special shipping instructions:	None known.

REGULATORY INFORMATION

WHMIS classification:	None.
HMIS codes:	Health 0, Flammability 0, Reactivity 0, PPE A
IATA/ICAO Shipping Name:	Not regulated.
TDG shipping name:	Not regulated.

PREPARATION INFORMATION / CONTACTS

Prepared by:	Hilti, Inc., Tulsa, OK USA	Date of Preparation: Dec 2,2013	**Emergency phone number:**	1 800 424 9300
Customer Service:	Hilti (Canada) Corporation, Mississauga, Ontario; 1 800 363 4458			
Health / Safety contacts:	Hilti, Inc., Tulsa, OK USA; 1 800 879 6000, Jerry Metcalf (x1003704)			
Abbreviations used:	**N/E** = None Established. **N/Av** = Not Available. **R** = Respirable dust.			

The information and recommendations contained herein are based upon data believed to be correct; however, no guarantee or warranty of any kind expressed or implied is made with respect to the information provided.

Flexible Firestop Sealant (CP 606)

Product description

- An acrylic based firestop sealant that provides movement capability in fire rated joints and seals through-penetrations applications

Product features

- Silicone free
- Halogen, asbestos and solvent free
- Paintable
- Tested up to 33% movement with 500 cycles in accordance to UL 2079 and ASTM 1966
- Smoke and fume resistant
- Easy clean up with water
- Single component systems available
- Meets LEED™ requirements for indoor environmental quality credit 4.1 Low Emitting Materials, Sealants and Adhesives and 4.2 Paints and Coatings

Areas of application


- Sealing construction/expansion joints
- Top-of-wall joints
- Metal pipes
- Cable bundles
- HVAC penetrations

For use with

- Various base materials such as masonry, concrete, gypsum, etc.
- Wall and floor assemblies rated up to 3 hours

Examples

- Where a gypsum wall assembly meets the underside of a metal or concrete deck
- Sealing expansion joints to impede the passage of fire, smoke and toxic fumes
- Sealing around HVAC penetrations through fire-rated assemblies



Technical Data*	CP 606
Chemical basis	Acrylic based firestop sealant
Color	Available in red, white and gray
Application temperature	40°F to 104°F (5°C to 40°C)
Skin-forming time	Approx. 15 min
Curing time	Approx. 3 mm / 3 days
Average volume shrinkage (ASTM C1241)	22.2%
Movement capability	Approx. 10%
Temperature resistance	–22°F to 176°F (–30°C to 80°C)
Surface burning characteristics (ASTM E 84-96)	Flame Spread: 10 Smoke Development: 0
Sound transmission classification (ASTM E 90-99)	56 (Relates to specific construction)
Tested in accordance with	• UL 2079 • ASTM E 814 • ASTM E 1966 • CAN/ULC-S115 • ASTM E 84 • UL 1479 • ASTM G21 • CAN/ULC-S102

*At 73°F (23°C) and 50% relative humidity

CLASSIFIED C UL US

FILL, VOID OR CAVITY MATERIAL
FOR USE IN THROUGH-PENETRATION
FIRESTOP SYSTEMS AND
JOINT SYSTEMS
SEE UL FIRE RESISTANCE DIRECTORY
66Y7

FM APPROVED

Installation instructions for CP 606

Notice

- Before handling, read Material Safety Data Sheet and product label for safe usage and health information.
- Instructions below are general guidelines — always refer to the applicable drawing in the UL Fire Resistance Directory or Hilti Firestop Systems Guide for complete installation information
- The use of backing material is recommended to control the sealant depth and help ensure assembly seal is complete

Opening

1. Clean the opening. Surfaces to which CP 606 will be applied should be cleaned of loose debris, dirt, oil, wax and grease. The surface should be moisture and frost free.

Application of firestop


2. Insert fill of mineral wool or backer (as required).
3. Apply firestop over backer.
4. Smooth firestop sealant with a trowel before the skin forms. Once cured, CP 606 can only be removed mechanically.
5. For maintenance reasons, a penetration seal can be permanently marked with an identification plate and fastened in a visible position next to the seal.

Not for use


- On areas immersed in water

Storage

- Store only in the original packaging in a location protected from moisture at a temperature of 40°F to 77°F (5°C to 25°C)
- Observe expiration date on package



1. Clean opening | 2. Insert backing material compressed per UL System | 3. Apply CP 606 | 4. Smooth CP 606 | 5. Fasten identification plate (if required)



1. Clean opening | 2. Insert backing material | 3. Apply CP 606 | 4. Smooth CP 606 | 5. Fasten identification plate (if required)

Hilti Firestop
Saving lives
through innovation
and education

Hilti. Outperform. Outlast.

Date: Jul 4, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 04, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-06
PO-P18-120

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Drawing E-601-Automatic Transfer Switch #2

Contractor to review and confirm this is meant to be E-603, Final SLD

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-006

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-10
BY Konrad Goluch

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Provide 4-position switch as per specification 26 36 23 2.3 .1

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Responsibility lies with the contractor as per the Contract.

Do not hesitate to contact me if you have any questions or concerns.

THOMSON™
POWER SYSTEMS

Approval Drawings

Project Name/Reference: IQALUIT WTP

Customer: FRONTIER POWER PRODUCTS

Thomson Customer Order: C-058937/1 Rev# 0

WorkOrder/Serial Number: W-102488

Model Number TS 873B0400A1CN5BKKAA

Attached Drawings:

Physical Drawing	MBS870M136	Rev#	0
AC Schematic	MBS870E100	Rev#	4
AC Control Schematic	TSC900E100	Rev#	4
DC Control Schematic	TSC900E101	Rev#	4

Option Drawings:

STANDARD OPTION SCHEMATIC - PPR-10	TSC900E300	Rev#	3
STANDARD OPTION SCHEMATIC - CTKXXXX	TSC900E304	Rev#	3
STANDARD OPTION SCHEMATIC - BYPASS AUX	TSC900E352	Rev#	3

Features/Ratings:

Amperage:	400A
Voltage:	347 - 600V 3 Phase (4 Wire)
Poles:	3POLE
Frequency:	60HZ
Configuration	Double Side Bypass
Application	Standard ATS
Operation	Open Transition Transfer
Enclosure Type	NEMA 2 Enclosure
ATS Controller	TSC900

Utility (or Source 1) Switching Device:	Moulded Case Switch
Generator (or Source 2) Switching Device:	Moulded Case Switch
Approval Standard:	CSA C22.2 No. 178/ UL1008 -non SE ATS

System Options:

CTK0400	400A Current Tranformer Kit
LPM	Transfer Switch Load Power Metering CT K
PPR-10	Programmable Power Relay c/w 10A Form C
AUX-BG	Bypass Auxiliary Contact - Generator Side
AUX-BU	Bypass Auxiliary Contact - Utility Side

ATTACHED DOCUMENTS ARE DRAFT FOR REVIEW ONLY AND ARE SUBJECT TO CHANGE WITHOUT NOTICE.

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE STANDARD TERMS AND CONDITIONS.

THE INFORMATION CONTAINED IN THESE DRAWINGS IS THE PROPERTY OF THOMSON POWER SYSTEMS, IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

NOTE:
ANY PROGRAM SETTINGS SHOWN REFLECT FACTORY DEFAULT SETTINGS ONLY. FINAL SETTINGS WILL BE REQUIRED TO BE SET BY THE COMMISSIONING AUTHORITY. FAILURE TO DO SO MAY RESULT IN EQUIPMENT FAILURE.

SHOP DRAWING / SUBMITTAL REVIEW

☐ APPROVED ☐ APPROVED WITH CHANGES NOTED

☐ REVISE AND RESUBMIT ☐ REJECTED _____

SUBMITTAL WAS RECEIVED FOR DESIGN CONFORMITY AND GENERAL CONFORMANCE TO CONTRACT DOCUMENTS ONLY. THE CONTRACTOR FOR CONFIRMING AND CORRELATING DIMENSIONS AT JOB SITES FOR TOLERANCES, CLEARANCES, QUANTITIES, FABRICATION PROCESSES AND TECHNIQUES OF CONSTRUCTION, COORDINATION OF HIS WORK WITH OTHER TRADES AND FULL COMPLIANCE WITH CONTRACT


BY _____ DATE _____

COMPANY NAME _____


CITY _____ STATE/PROV _____

9087A - 198th Street, Langley, BC Canada V1M 3B1
Email: info@thomsonps.com www.thomsonps.com


REGAL®




FRONT VIEW




LHS VIEW
(SIDE COVER REMOVED)



INTERIOR FRONT VIEW
(DOOR NOT SHOWN)



VIEWED FROM REAR OF DOOR
(INSIDE OF ATS SECTION)



BASIC MODEL TS87xA	STANDARD ATS				
	CLOSING AND WITHSTAND RATING AVAILABLE AMPS (RMS) CLOSING & WITHSTAND RATINGS SHOWN ARE ONLY FOR ATS UTILITY AND/OR GENERATOR POWER SWITCHING DEVICE(S) THAT ARE NOT FACTORY SUPPLIED WITH INTEGRAL OVERCURRENT PROTECTION. PLEASE REFER TO PRODUCT INSTRUCTION MANUAL FOR FURTHER INFORMATION ON UPSTREAM PROTECTION REQUIREMENT.				
	MAX. VOLTAGE	RATED CURRENT (A)	@240V	@480V	@600V
TS 87xA-400	600	400	65,000	50,000	35,000

SHORT CIRCUIT CURRENT RATING–BYPASS SECTION				
SHORT CIRCUIT CURRENT RATINGS – MCS STYLE (ABB) 3, 4 & 5–BREAKER SLIDEBAR INTERLOCKED "CANADIAN" BYPASS LOWEST KA RATINGS APPLICABLE TO MCS'S & MCCB'S THAT ARE USED IN BYPASSES (CERTIFIED TO CSA #31)				
ATS RATING (AMPS)	BYPASS BREAKER FRAME (ABB)	@240V	@480V	@600V
400	T6H	65,000	50,000	35,000

CONNECTION DATA		
400A ATS	UTILITY (SRC1)	1–2C, 2/0–500MCM Cu/Al PER PHASE
	GENERATOR (SRC2)	1–2C, 2/0–500MCM Cu/Al PER PHASE
	LOAD	1–2C, 2/0–500MCM Cu/Al PER PHASE
	NEUTRAL	1–2C, 2/0–500MCM Cu/Al PER SOURCE
	GROUND	6C, #6–250MCM Cu/Al

GENERAL NOTES	
1	POWER SWITCHING DEVICES ARE MECHANICALLY INTERLOCKED SO THAT ONLY ONE DEVICE IS CLOSED AT A TIME
2	BYPASS SWITCHING DEVICES ARE MECHANICALLY INTERLOCKED THROUGH A SLIDE BAR INTERLOCK. BYPASS IS CLOSED TRANSITION. REFER BELOW CHART
3	NEMA 2 ENCLOSURE C/W DRIPHOOD
4	NEMA 12 ENCLOSURE C/W GASKETING
5	FOR 1 PHASE, 3 WIRE SOLID NEUTRAL APPLICATION, CONNECT PHASE TO 'A' & 'B'. OMIT 'C'
6	FOR 1 PHASE, 3 WIRE SWITCHED NEUTRAL APPLICATION, CONNECT PHASE TO 'A' & 'B'. CONNECT NEUTRAL TO 'C'
7	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

2.5" x 5"

W1

DANGER
PELIGRO

Arc Flash and Shock Hazard
Will cause severe injury or death. Wear flash-over line circuit-see diagram. Disconnect all sources of supply before servicing. This equipment must be installed and serviced only by qualified electrical personnel utilizing safe work practices and appropriate Personal Protective Equipment (PPE). Failure to comply may result in injury or death! Refer to NFPA 70E for minimum PPE requirements.

Risque d'Arc Electrique et d'Electrocution
Peut causer des blessures graves ou la mort. Pour d'un circuit sous tension - voir schema. Couper toutes les sources d'alimentation avant de faire l'entretien et les reparations. Ce materiel doit etre installé et entretenu uniquement par un electricien qualifié. Ce dernier doit connaître les pratiques de travail sécuritaires et porter l'équipment de protection individuelle approprié. Le non respect mai entrainer des blessures ou la mort! Reportez-vous a NFPA 70E pour le manuel des exigences minimales PPE.


Riesgo de Arco y Choque Eléctrico
Se causarán lesiones graves o muerte. Más de un circuito energizado - ver diagrama. Desconectar todas las fuentes de suministro antes de hacer mantenimiento. Este equipo solo se debe instalar y mantener por personal calificado, usando medidas de seguridad y equipo de protección personal adecuados. No seguir estas recomendaciones puede causar lesiones o muerte! Consultar la NFPA 70E para los requisitos mínimos del equipo de protección personal (PPE).

QTY = 1

SWITCHING DEVICE	INTERLOCK POSITION					
	UTILITY BYPASS	TRANSITION INTERLOCKING				GENERATOR BYPASS
	1	2	3	4	5	
NB	⊠	⊠				
NI		⊠	⊠			
LI			⊠	⊠		
GI				⊠	⊠	
GB					⊠	

BYPASS SLIDE BAR INTERLOCK

⊠ = SWITCH CLOSURE ALLOWED



SINGLE LINE DIAGRAM

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5 0 C – C – 1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS


No.	REVISIONS	BY	AUTH	DATE
1	GENERAL NOTES AND LOGO UPDATED	AP	OG	17–10–24

THOMSON POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 870
PHYSICAL LAYOUT & INSTALLATION DETAILS
400A, 2P/3P, NEMA 1/2/12 SD, MCS DOUBLE BYPASS, STD

CUSTOMER	THOMSON POWER SYSTEMS		
CUSTOMER ORDER No.	WORK ORDER No.		
C–XXXXX	W–XXXXX		
DRAWN BY	AUTH BY	DATE	REV
AP	OG	16–01–26	1
DRAWING/FILE No.		SHEET	
MBS870M136		10A	

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.



COLOR KEY	
BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

GENERAL NOTES	
1	FOR 1 PHASE, 3 WIRE SOLID NEUTRAL APPLICATION, CONNECT PHASE TO 'A' & 'B'. OMIT 'C'
2	FOR 1 PHASE, 3 WIRE SWITCHED NEUTRAL APPLICATION, CONNECT PHASE TO 'A' & 'B'. CONNECT NEUTRAL TO 'C'
3	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
4	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

FOR REVIEW ONLY

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5 0 C – C – 1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
4	GENERAL NOTES AND LOGO UPDATED	AP	OG	17–10–24
3	REMOVED T–STYLE OPTION	SR	OG	17–08–16
2	PRODUCT RANGE CHANGED TO 100–800A	SR	OG	17–01–24
1	WIRE HARNESS UPDATED AS PER ECR–0114744	AP	OG	16–07–22


THOMSON™ POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 870
MCS BYPASS AC SCHEMATIC, T–STYLE / S–STYLE, STD
100 – 800A

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER	THOMSON POWER SYSTEMS
CUSTOMER ORDER No.	C–XXXXXX
WORK ORDER No.	W–XXXXXX
DRAWN BY	AP
AUTH BY	OG
DATE	16–01–26
REV	4
DRAWING/FILE No.	MBS870E100
SHEET	20A

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.



GENERAL NOTES	
1	CONTROL TRANSFORMER IS RATED FOR 100VA FOR MCS ATS & 200VA FOR ATS MECHANISM USING TRIP & CLOSE COILS
2	100VA CONTROL TRANSFORMER DOES NOT INCLUDE A 2ND 120VAC SECONDARY WIRING (X3/X4)
3	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
4	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

VOLTAGE (X DENOTES HIGH POLARITY MARKER)

PT TAP	208	240	380	400	416	480	600
H1	X	X				X	X
H2			X	X			
H3	X						
H4					X	X	
H5		X	X	X	X		X

COLOR KEY	
BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
SOC-C-1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
4	TSC900 CONFIGURATION UPDATED	AP	OG	17-11-17
3	GENERAL NOTES AND LOGO UPDATED	AP	OG	17-10-24
2	UPDATED MOS CONTROL PLATE PID	SK	OG	17-08-16
1	WIRE HARNESS UPDATED AS PER ECR-0114744	AP	OG	16-07-22

THOMSON POWER SYSTEMS


AUTOMATIC TRANSFER SWITCH
TSC 900 TRANSFER SWITCH CONTROLLER
ATS AC CONTROL SCHEMATIC, STD
100 – 4000A

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER	THOMSON POWER SYSTEMS
CUSTOMER ORDER No.	C-XXXXXX
WORK ORDER No.	W-XXXXXX
DRAWN BY	AP
AUTH BY	OG
DATE	16-01-26
REV	4
DRAWING/FILE No.	TSC900E100
SHEET	20B

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.



PARAMETER	MODBUS RTU SETTINGS
SLAVE ID	1
PORT NAME	COM 4
BAUD RATE	57600
PARITY	NONE
STOP BUS	ONE

TSC900 FACTORY DEFAULT SETTINGS

NOTE : REFER TO OPTION DRAWINGS FOR APPLICABLE CHANGES TO FACTORY DEFAULT SETTINGS

PARAMETER	DEFAULT	RANGE
GENERATOR (SOURCE 2) START DELAY	3 SEC	0–60 SEC
GENERATOR (SOURCE 2) WARM UP DELAY	2 SEC	0–3600 SEC
GENERATOR (SOURCE 2) COOL DOWN DELAY	300 SEC	0–3600 SEC
UTILITY (SOURCE 1) RETURN DELAY	300 SEC	0–3600 SEC
TRANSFER NEUTRAL DELAY	3 SEC	0–120 SEC
TRANSFER FAIL DELAY	30 SEC	0–120 SEC
EXERCISE TIMER	PROG.	PROG.
GENERATOR (SOURCE 2) UNDER VOLTAGE DELAY	3 SEC	0–10 SEC
GENERATOR (SOURCE 2) UNDER FREQUENCY DELAY	5 SEC	0–10 SEC
GENERATOR (SOURCE 2) UNDER VOLTAGE PICK UP	90%	75–100%
GENERATOR (SOURCE 2) UNDER VOLTAGE DROP OUT	85%	70–95%
UTILITY (SOURCE 1) UNDER VOLTAGE DELAY	1 SEC	0–10 SEC
UTILITY (SOURCE 1) UNDER VOLTAGE PICK UP	90%	75–100%
UTILITY (SOURCE 1) UNDER VOLTAGE DROP OUT	85%	70–95%

ALL SETTINGS ARE FIELD ADJUSTABLE UNLESS NOTED. REFER TO THE TSC900 MANUAL FOR A COMPLETE LISTING OF ALL TSC900 SETTINGS.

GENERAL NOTES

1	"USD OPEN" AND "GSD OPEN" DIGITAL INPUTS ARE REQUIRED ONLY FOR ATS MECHANISMS USING TRIP AND CLOSE COILS. REFER TO SHEET 20A FOR DETAILS
2	"43TMS IN MANUAL MODE" DIGITAL INPUT IS REQUIRED ONLY FOR CLOSED TRANSITION ATS(s)
3	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
4	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

COLOR KEY

BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

FOR REVIEW ONLY

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5 0 C – C – 1
GRID COORDINATE
SHEET No.
DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
4	TSC900 CONFIGURATION UPDATED	AP	OG	17–11–17
3	GENERAL NOTES AND LOGO UPDATED	AP	OG	17–10–24
2	UPDATED MOS CONTROL PLATE PID	SK	OG	17–08–16
1	WIRE HARNESS UPDATED AS PER ECR–0114744	AP	OG	16–07–22

THOMSON™ POWER SYSTEMS


AUTOMATIC TRANSFER SWITCH
TSC 900 TRANSFER SWITCH CONTROLLER
ATS DC CONTROL SCHEMATIC, STD
100 – 4000A


DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER THOMSON POWER SYSTEMS
CUSTOMER ORDER No. C–XXXXXX
WORK ORDER No. W–XXXXXX
DRAWN BY AP | AUTH BY OG | DATE 16–01–26 | REV 4
DRAWING/FILE No. TSC900E101
SHEET 20C

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

☐ PPR–10 OPTION





PR1			
T1	TYPE	T2	REF
4	+h	7	A–5
1	-w		
5	+h	8	A–6
2	-w		
6	+h	9	A–7
3	-w		

PR2			
T1	TYPE	T2	REF
4	+h	7	B–5
1	-w		
5	+h	8	B–6
2	-w		
6	+h	9	B–7
3	-w		


PR3			
T1	TYPE	T2	REF
4	+h	7	C–5
1	-w		
5	+h	8	C–6
2	-w		
6	+h	9	C–7
3	-w		

PPR–10 OPTION NOTES	
1	FOR POWER RELAY FUNCTIONAL DESCRIPTION REFER TO FACTORY DEFAULT DIGITAL OUTPUT FUNCTION TABLE ON ATS DC CONTROL SCHEMATIC
2	THE NUMBER OF RELAYS SUPPLIED WILL BE PER ORDERED QUANTITY
3	CUSTOMER TO WIRE DIRECTLY TO RELAY TERMINALS
4	SPECIFIED QUANTITY OF PROGRAMMABLE POWER RELAYS ARE WIRED FOR CUSTOMER AS PER OPTION LIST
5	DC SUPPLY FOR THE RELAYS, BY DEFAULT IS 24VDC. PLEASE SPECIFY THE VOLTAGE RATING OTHER THAN 24VDC ON OPTION LIST

BILL OF MATERIALS		
PART DESCRIPTION	PART ID	QTY
RELAY, 24VDC COIL, 11 PIN SQ., /W LED	004095	3
RELAY SOCKET, 11 PIN, SQ., RAIL MOUNT	000399	3
FUSE HOLDER, 1P, 30A, 600V, 200KA, CC	002374	1
FUSE, 3A, 600VAC, CLASS CC	003633	1
TERM. BLK, RAIL MNT, 40A, 600V, WK4/U,	001881	10

GENERAL NOTES	
1	FOR MCS/MOS/PCS TYPE ATS, MOUNT THE RELAYS ON SIDE COVER WHERE SPACE PERMITS
2	FOR ICS ATS MOUNT THE RELAYS ON BACK PAN WHERE EVER THE SPACE PERMITS
3	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

PPR RELAY
[TYPICAL]



FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
50C – C – 1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
4	DRAWINGS UPDATED FOR TS970 PRODUCT LINE APPLICATION	SK	OG	18-03-08
3	GENERAL NOTES AND LOGO UPDATED	AP	OG	17-10-24
2	MOUNTING INSTRUCTION UPDATED	SK	OG	16-09-21
1	WIRE HARNESS UPDATED AS PER ECR-0114744	AP	OG	16-07-22


THOMSON POWER SYSTEMS™


AUTOMATIC TRANSFER SWITCH
MODEL TS 870 / 880 / 970
STANDARD OPTION SCHEMATIC – PPR–10
POWER AUX RELAY

CUSTOMER THOMSON POWER SYSTEMS
CUSTOMER ORDER No. C–XXXXXX
WORK ORDER No. W–XXXXXX
DRAWN BY AP | AUTH BY OG | DATE 16–01–26 | REV 4
DRAWING/FILE No. TSC900E300
SHEET 30A


© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

☐ CTKXXXX OPTION





ATS CONTROL PLATE



PART ID	OPTION KITS
CTK0100	100 AMPS
CTK0150	150 AMPS
CTK0250	200–250 AMPS
CTK0400	400 AMPS
CTK0600	600 AMPS
CTK0800	800 AMPS
CTK1200	1000–1200 AMPS
CTK1600	1600 AMPS
CTK2000	2000 AMPS

GENERAL NOTES	
1	CT'S TO BE MOUNTED ON THE LOAD SIDE OF THE ATS. CUSTOMER TO VERIFY POLARITY BEFORE CONNECTING THE CT SECONDARIES TO THE TRANSFER SWITCH CONTROLLER.
2	ATS CONTROL PLATE MOUNTED ON THE BACK SIDE OF DOOR FOR MCS / MOS / PCS AND FOR ICS MOUNTED ON THE BACKPAN.
3	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

BILL OF MATERIALS FOR CABLE HARNESS		
PART DESCRIPTION	PART ID	QTY
WIRE, 18AWG, GREY, TINNED, TEW, 600V,	002027	600 INCHES
TERM. BLK, RAIL MNT, 40A, 600V, WK4/U,	001861	6
TERM. BLK, ENDPLATE, WK 2.5-4/U,	001872	1
SCREW, SHT-MTL, RDH, ROB #8 X 5/8"	002070	2
MTG-RAIL, TYPE-35, SLOTTED(7.5X2-METERS)	002795	6
TERM. BLK, PARTITION PLATE, WK2.5-4/U,	004189	2
CONN, MINI-FIT, J, 94V-2, 2X1-WAY,FEMALE (J5/J6/J7)	012654	3
CONN, FEMALE CRIMP, MINI-FIT, JR. SERIES	010954	6
WIRE SLEEVE, 0.5", EXPANDO PT PLUS,	000458	175 INCHES
TERM BLK CROSS CONN.W SCRW WK4/U SR7	009677	3
TERM. BLK, EARTH TERMINAL, 10-24 AWG	005211	2

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: ____ DATE: ____

CROSS REFERENCE LEGEND
50C-C-1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
4	DRAWINGS UPDATED FOR TS970 PRODUCT LINE APPLICATION	SK	OG	18-03-08
3	GENERAL NOTES AND LOGO UPDATED	AP	OG	17-10-24
2	MOUNTING INSTRUCTION UPDATED	SK	OG	16-09-21
1	WIRE HARNESS UPDATED AS PER ECR-0114744	AP	OG	16-07-22


THOMSON POWER SYSTEMS™

AUTOMATIC TRANSFER SWITCH
MODEL TS 870 / 880 / 970
STANDARD OPTION SCHEMATIC – CTKXXXX
CURRENT TRANSFORMER KIT

CUSTOMER: THOMSON POWER SYSTEMS
CUSTOMER ORDER No.: C-XXXXXX
WORK ORDER No.: W-XXXXXX
DRAWN BY: AP | AUTH BY: OG | DATE: 16-01-26 | REV: 4
DRAWING/FILE No.: TSC900E304
SHEET: 30E


© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

☐ AUX BU/ BG OPTION




FOR MCS BYPASS ATS APPLICATION

☐ AUX BU OPTION



FOR MCS BYPASS ATS APPLICATION

☐ AUX BG OPTION




FOR MCS BYPASS ATS APPLICATION

BILL OF MATERIALS FOR MCS DOUBLE SIDE BYPASS			
PART DESCRIPTION	BREAKER	PART ID	QTY
BREAKER, 2-AUX CONTACT, TS3	100-200A	012350	5
BREAKER, AUX CONTACT CONN., TS3	100-200A	012357	5
BREAKER, 2-AUX CONTACT, T4-6	250-800A	012002	5


BILL OF MATERIALS FOR MCS SINGLE SIDE BYPASS			
PART DESCRIPTION	BREAKER	PART ID	QTY
BREAKER, 2-AUX CONTACT, TS3	100-200A	012350	3
BREAKER, AUX CONTACT CONN., TS3	100-200A	012357	3
BREAKER, 2-AUX CONTACT, T4-6	250-800A	012002	3

☐ AUX BU OPTION (ICS BYPASS – FIXED)




FOR DRAWOUT ATS SECTION AND FIXED BYPASS SECTION APPLICATION

☐ AUX BG OPTION (ICS BYPASS – FIXED)




FOR DRAWOUT ATS SECTION AND FIXED BYPASS SECTION APPLICATION

☐ AUX BU OPTION (ICS BYPASS – DRAWOUT)



FOR DRAWOUT ATS SECTION AND DRAWOUT BYPASS SECTION APPLICATION

☐ AUX BG OPTION (ICS BYPASS – DRAWOUT)



FOR DRAWOUT ATS SECTION AND DRAWOUT BYPASS SECTION APPLICATION

GENERAL NOTES	
1	GEN SIDE / UTILITY SIDE / DOUBLE SIDE BYPASS AUX OPTION FOR MCS ATS TYPE IS PROVIDED AS PER OPTION LIST
2	FOR MCS BYPASS, USE SUITABLE PART ID FOR AUX CONTACT BASED ON THE AMPERAGE RATING AS MENTIONED IN BILL OF MATERIAL
3	FOR MCS TS3 FRAME, USE AUX CONTACT AND ITS CONNECTION AS MENTIONED IN BILL OF MATERIAL. FOR T4-T6 FRAME, AUX. CONNECTION INCLUDED IN AUX CONTACT PART ID
4	FIXED / DRAW OUT BYPASS AUX OPTION FOR ICS ATS TYPE IS PROVIDED AS PER OPTION LIST
5	ICS ATS & BYPASS CONTACTS UTILIZED FROM EXISTING 4A-4B AUX CONTACTS WHICH ARE ORDERED WITHIN THE BREAKER
6	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

FOR REVIEW ONLY

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
SOC-C-1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
3	GENERAL NOTES AND LOGO UPDATED	AP	OG	17-10-24
2	MOUNTING INSTRUCTION UPDATED	SK	OG	16-09-21
1	WIRE HARNESS UPDATED AS PER ECR-0114744	AP	OG	16-07-22

THOMSON™ POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 870 / 880
STANDARD OPTION SCHEMATIC – BYPASS AUX
ATS BYPASSED OPTION

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER	THOMSON POWER SYSTEMS		
CUSTOMER ORDER No.	C-XXXXXX	WORK ORDER No.	W-XXXXXX
DRAWN BY	AP	AUTH BY	OG
DATE	16-01-26	REV	3
DRAWING/FILE No.	TSC900E352	SHEET	30M

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

Date: July 26, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 26, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

SE-07R1 (ELE-007)
PO-P18-120 Frontier

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [X] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Drawing E-601-Load Bank

STANTEC PROJECT #: 110126045
This review by Stantec is for general conformance with the design concept of Stantec's design of the:
- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

SUBMITTAL # ELE-07R1

Stantec


- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-30
BY Konrad Goluch

Power bank shall have exterior emergency power off switch on enclosure as spec 26 32 14 2.7 .5

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the contractor.

Do not hesitate to contact me if you have any questions or concerns.



KEY	DESCRIPTION	MFR PART NUMBER
MOTOR	0.75 HP-1725-TEFC-600/3/60 F56	LEESON A0090178
FAN FRAME	EMERSON 24"	FRAME-EMERSON 2DVP24
FAN BLADE	ALUMINUM 24"	DAYTON 3GTG4 CAST AL
MF1-MF3	FUSE 5A, 600VAC FAST ACTIVE	LITTELFUSE ATM5
MC	MOTOR CONTACTOR 3P, 7.5HP, 600V	MC18-120
M.OL	MOTOR OVERLOAD 1-1.6A	CG GT32 1-1.6
AFS	AIR FLOW SWITCH SPDT 5A/120	KFR-1, 90 PA
CF1-CF2	FUSE 1A, 600VAC FAST ACTIVE	LITTELFUSE ATM1
CF3	FUSE 5A, 250VAC FAST ACTIVE	LITTELFUSE OTM5
F20	FUSE 20A, 600VAC FAST ACTIVE	LITTELFUSE ATM20
F25	FUSE 25A, 600VAC FAST ACTIVE	LITTELFUSE ATM25
C1-C18	LOAD CONTACTOR 3P, 40A, 600V	MC32-120AC
R1, R2	INDICATOR LIGHT	AUS 22 RED LED
TR	TRANSFORMER 600-120, 250VA	HAMMOND SP250ACP
LR26	LOAD RESISTOR	NICHROME 60-20-26
LR19.6	LOAD RESISTOR	NICHROME 60-16.5-19.6
TLS	TEMPERATURE LIMIT SWITCH	SRL-260 MANUAL RESET
HTS	HIGH TEMP. SHUTDOWN RELAY	CG RPY002-120AC
S	ON-OFF SWITCH	AUS 22 BLACK
S1-S7	ON-OFF SWITCH ILLUMINATED	AUS 22 AMBER LED
PB1	ILLUM. PUSH-BUTTON N.O.	AUS 22 MM GREEN LED-120AC
PB2	ILLUM. PUSH-BUTTON N.C.	AUS 22 MM RED LED-120AC
HT	HEATER 120 VAC, 100W	SAIPWELL HG 14003
TH	THERMOSTAT N/C 0-60C	STEGO 01146.9-99
CC	CONTROL CONTACTOR 3P, 18A, 600V	MC18-120
DM1, DM2	DAMPER MOTOR C/W LIMIT SWITCH	SIEMENS GCA226.1U-120
□ TB1	REMOTE CONTROL TERMINALS	PHOENIX UK3N
◇ TB2	LOAD BANK TERMINALS	PHOENIX UK3N
(L)	COPPER BUSBAR PLATED	8" X 1" X 0.25"

NOTES:

1. BROKEN LINE WIRING IS BY INSTALLER.
2. LBCB SUPPLY BY OTHERS.
3. INTER-CONNECTIONS TERM. 1 TO 15 - #14 AWG.
4. CHECK FAN ROTATION FOR CORRECT OPERATION OF AIRFLOW DIRECTION.

REV.	BY	DATE	DESCRIPTION

INFORMATION INCLUDED IN THIS DRAWING IS PROPRIETARY AND IS NOT TO BE REPRODUCED, DISTRIBUTED OR DISCLOSED EXCEPT AS SPECIFICALLY AUTHORIZED IN WRITING BY JP POWER TECHNOLOGY INC.


SERIAL NO	F802
PO# 52855, JUNE 19, 2018	
TESTED BY	XX
DATE	JULY 20, 2018
DWG. NO	F802-1


JP POWER TECHNOLOGY INC.
EDMONTON, ALBERTA, TEL. 780-456-9167, FAX 780-478-7135

SIZE B


TITLE: OUTDOOR RESISTIVE LOAD BANK MODEL: SM-250D7 ELECTRICAL SCHEMATIC

CUSTOMER: FRONTIER POWER PRODUCT EDMONTON






SIDE VIEW



REMOTE CONTROL
H-14" (356), W-12" (305), H-6 (152)



NOTES:

1. ALL DIMENSIONS ARE SHOWN IN INCHES (MILLIMETERS)
2. WEIGHT-300 LBs, 136 KG
3. MAXIMUM AIR INLET TEMPERATURE IS 100F, 38C
4. MINIMUM CLEARANCE FOR AIR DISCHARGE-24 FT (7.3 MT)
5. REMOTE CONTROL PANEL- CEMA 1, GRAY 61 POWDER COAT PAINT
6. LOAD BANK ENCLOSURE- CEMA 3, 304 SS. GA18, NATURAL FINISH.

REV.	BY	DATE	DESCRIPTION

INFORMATION INCLUDED IN THIS DRAWING IS PROPRIETARY AND IS NOT TO BE REPRODUCED, DISTRIBUTED OR DISCLOSED EXCEPT AS SPECIFICALLY AUTHORIZED IN WRITING BY JP POWER TECHNOLOGY INC.

SERIAL NO	F802
PO# 52855, JUNE 19, 2018	
TESTED BY	XX
DATE	JULY 20, 2018
DWG. NO	F802-2

JP POWER TECHNOLOGY INC.
EDMONTON, ALBERTA, TEL. 780-456-9167, FAX 780-478-7135

SIZE B

TITLE: OUTDOOR RESISTIVE LOAD BANK
MODEL: SM-250D7
ENCLOSURE LAYOUT

CUSTOMER: FRONTIER POWER PRODUCT EDMONTON

Date: Jul 5, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 05, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-08
PO-P18-123

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 28 16 05 Intrusion Detection

Ref-ELE001R1(SE01R1) Additional Information that was not included

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-008

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [ ] Electrical
- [ ] Other _____

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-10

BY Konrad Goluch

See comments on ELE-001-R1

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.


Responsibility lies with the Contractor, not the Client.

Do not hesitate to contact me if you have any questions or concerns.

B520 Auxiliary Power Supply Module

www.boschsecurity.com

BOSCH
Invented for life



- Provides up to 2A of 12V standby current for Fire or Burglar Applications (4A of Burglary alarm current)
- Supervises up to two 12v 7-18Ah batteries independently for up to 36AH of capacity
- Provides up to 80 hours of standby time
- Uses the Bosch standard TR1850 plug-in transformer
- Easy to read rotary switch addressing

The B520 Auxiliary Power Supply Module is a fully supervised, addressable SDI2 bus device that provides an integrated auxiliary power supply solution for Bosch control panels.

System overview

The B520 Auxiliary Power Supply Module is an auxiliary power supply expansion device that connects to compatible control panels through the SDI2 bus. This module is supervised and communicates back to the control panel all status changes.
Industrial, commercial, and institutional facilities are typical installations for the B520 module. The B520 rotary switches allow for ease of use in device addressing. The SDI2 Out terminals provide auxiliary power for SDI2 expansion devices such as keypads. The AUX PWR terminals provides added auxiliary power capabilities for additional devices such as PIR's.

Functions

Supervision Monitoring
The module monitors and communicates status information over the SDI2 bus for the following:

- Operation (Heartbeat)
- Battery 1 (BATT 1)
- Battery 2 (BATT 2)
- AC input power (AC)
- Battery OK
- Low Battery
- Missing Battery

Indicators

- Heartbeat [icon]: Blue LED flashing On and Off when system is operating normally. A steady On or Off LED indicates a system error. Triple flash indicates communication failure.
- BATT 1 LED: Green steady On LED indicates the battery status of BATT 1 is operating normally. Flashing indicates low battery. Triple flash indicates battery charger failure. Off LED indicates a missing battery.
- BATT 2 LED: Green steady On LED indicates the battery status of BATT 2 is operating normally. Flashing indicates low battery. Triple flash indicates battery charger failure. Off LED indicates a missing battery.
- AC LED: Green steady On LED indicates the AC power is operational. A pulsating LED (3 pulses per sec.) occurs when a battery test is being performed. Flashing indicates low or failed AC.

Battery Charging
Fully charged batteries, connected to the battery terminals, sustain power to the B520 in the event that the AC power fails.

If AC power fails (is absent, or low) on the B520, the B520 automatically switches from primary power (AC) to secondary power (battery). When AC power is present, the B520 performs periodic battery tests to ensure battery life and usability.

Certifications and approvals

Region	
US	UL 365 – Police Station Connected Burglar Alarm Units and Systems
	UL 609 – Local Burglar Alarm Units and Systems
	UL 636 – Holdup Alarm Units and Systems
	UL 864 – Control Units and Accessories for Fire Alarm Systems
	UL 985 – Household Fire Warning System Units
	UL 1023 – Household Burglar Alarm System Units
	UL 1076 – Proprietary Burglar Alarm Units and Systems
	UL 1610 – Central Station Burglar Alarm Units
	FCC Part 15 Class B
Canada	CAN/ULC S303 – Local Burglar Alarm Units and Systems
	CAN/ULC S304 – Signal Receiving Centre and Premise Alarm Control Units
	ULC-ORD C1023 – Household Burglar Alarm System Units
	ULC-ORD C1076 – Propriety Burglar Alarm Units and Systems
	ICES-003 – Digital Apparatus

Region	Certification	
USA	UL	20121010-S5579
	CSFM	see our website

Installation/configuration notes

Mounting Considerations

You can mount the B520 Auxiliary Power Supply Module in a variety of enclosures for optimal situations.

Mounting in the D8103 requires the addition on the B12 Mounting plate.

The D8103 enclosure supports up to two 12V, 18Ah batteries. The B10 supports either one 12V, 18Ah or up to two 12V, 7Ah batteries.

Wiring Considerations

The B520 connects to a control panel using the SDI2 IN connections (PWR, A, B, COM). Use 12 AWG to 22 AWG (1.5 mm to 0.6 mm) wires from the power supply to the control panel.

The B520 provides auxiliary power to expansion modules via the SDI2 OUT (PWR, A, B, COM), or AUX Power (AUX PWR) connections using the screw terminal strip, or by using the interconnect wiring connection. Use 12 AWG to 22 AWG (1.5 mm to 0.6 mm) wires from the module to the SDI2 expansion module(s).

Parts included

Quantity	Component
1	B520 Auxiliary Power Supply module
1	Hardware pack
1	Literature pack

B520 Kit, B10 Enclosure

Kit contents include:

- B520 Aux Power Supply
- TR1850 transformer
- B10 white enclosure

Order number: **B520-B**

B520 Kit, D8103 Enclosure

Kit contents include:

- B520 Aux Power Supply
- TR1850 transformer
- B12 mounting plate
- D8103 gray, steel enclosure

Order number: **B520-C**

Technical specifications

Properties

Board Dimensions	11.43 cm x 17.62 cm x 2.9 cm (4.5 in x 6.94 in x 1.15 in)
Maximum Distance – Wire Size	305 m (1000 ft) - 0.65 mm (22 AWG) 305 m (1000 ft) – 2 mm (18 AWG) Unshielded wire only
Compatibility	GV4 Series control panels (Up to 8 B520 Auxiliary Power Supply Modules per control panel) D8103 Enclosure B10 Large Control Panel Enclosure B12 Mounting Plate for the D8103 Enclosure D8108A Attack Enclosure D2203 Enclosure BATB-40 Enclosure AE1, AE2 Enclosures D8004 Transformer Enclosure*
B501-10	Interconnect cables (10 per pack)

*The D8004 Transformer Enclosure is required when the B520 and TR1850 (18 VAC, 50 VA) Transformer are used in UL 864 Fire, or Combination Burg and Fire applications.

Power Input

Transformer Power Supply	TR1850 (18 VAC, 50 VA) TR1850-CA (18 VAC, 50 VA) for Canada

Power Output

Current Available (Maximum)	2.0 A SDI2 Out and AUX Power (Combined) (up to 4.0 A of alarm current for Burglar Applications)
Current Reserved for Charging Batteries	150 mA
Current Drawn from the Panel	15 mA
Voltage (rated range)	11.5 to 12.2 VDC (special application)
Battery Configuration	Supports two*, separate 12 V sealed lead acid batteries (7-18 Ah) for up to 36 amp. *Battery 1 is required for normal operations. Battery 2 is optional.

Enclosure Battery Considerations

D8103	Holds up to two 18 Ah, or two 7 Ah batteries
B10	Holds up to one 18 Ah, or two 7 Ah batteries

Environmental Considerations

Operating Temperature	+32° to +120° F (0° to +49°C)
Storage Temperature	-4° to 140° F (-20° to +60° C)
Relative Humidity	5% to 93% at +32° (+90°F) non-condensing
Use	Intended for indoor use.

Ordering information

B520 Auxiliary Power Supply Module
Provides auxiliary power to 12VDC devices or to SDI2 modules.
Order number **B520**

Accessories

B10 Medium Control Panel Enclosure
White, steel enclosure. Accepts an optional lock and tamper switch. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in x 12.5 in x 3 in).
Order number **B10**

D2203 Enclosure
Gray steel enclosure. Accepts an optional lock and tamper switch. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in x 12.5 in x 3 in).
Order number **D2203**

D8103 Enclosure
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).
Order number **D8103**

D8108A Attack Resistant Enclosure
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes lock and key set. B520, B4512, and B5512 require the B12 mounting plate.
Order number **D8108A**

AE1 Standard Enclosure (Gray)
Standard gray enclosure with keyed lock. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in x 12.5 in x 3 in).
Order number **AE1**

AE2 Standard Enclosure (Red)
Standard red enclosure with keyed lock. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in. x 12.5 in. x 3 in.).
Order number **AE2**

D8004 Transformer Enclosure
For applications such as fire alarm that might require a transformer enclosure.
Order number **D8004**

B12 Mounting Plate for D8103 Enclosure
Required for mounting select control panels and other devices in D8103, D8108A, D8109, or BATB Battery Box enclosures.
Order number **B12**

TR1850 Transformer
For use in North America. Plug-in transformer with input: 120 VAC, 60 Hz, 0.50 A; output 18 VAC, 50 VA output.
Order number **TR1850**

D101 Lock and Key Set
Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.
Order number **D101**

ICP-EZTS Dual Tamper Switch
Combination tamper switch with a wire loop for additional tamper outputs.
Order number **ICP-EZTS**

BATB-40 Battery Box\Enclosure
The BATB-40 Battery Box holds two dry or wet cell batteries. The box can be used with fire alarm systems or intrusion systems.
Order number **BATB-40**

B520 Kit, B10 Enclosure
B520 Auxiliary Power Supply kit. Includes a TR1850 transformer and a B10 White, steel enclosure.
Order number **B520-B**

B520 Kit, D8103 Enclosure
B520 Auxiliary Power Supply kit. Includes a TR1850 transformer, a B12 mounting plate, and a D8103 Gray, steel enclosure.
Order number **B520-C**

Represented by:

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com

© Bosch Security Systems 2014 | Data subject to change without notice
2536892171 | en, V6, 04. Nov 2014

Date: July 23, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 23, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-09R1 (ELE009)
PO-P18-152

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals
- Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [X] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record
- Bids due on:
- Other:

Qty	Type	MFG	Part

Section 26 52 01 Unit Equipment for Emergency Lighting

Section 26 53 00 Exit Signs

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-009-R1

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-30

BY Konrad Goluch

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the Contractor.

Do not hesitate to contact me if you have any questions or concerns.

WSA LIGHT ENERGY DESIGN LTD
101-5420 CANOTEK RD
OTTAWA, ON K1J 1E9
Phone: 613-745-0001
Fax: 613-745-0002
Contact: Strachan, Hayden

Iqaluit WWTP

18-21616-1

7/19/2018

Project 18-21616-1
Iqualuit WWTP

Submitted By
WSA LIGHT ENERGY DESIGN LTD

Type	Manufacturer/Brand	Catalog Number
DRH-XP	Aimlite	RMHZ-2112-24V6WLA/MR16/CM
BP1+2	Aimlite	EBHZ-2414411CD-2Z16WLA
EX-XP	Aimlite	RPZN21GRY
DRH	Aimlite	RMMD2-12-24V6WLA
BP# 3,5,6,7	Aimlite	EBST24144-2MD5WLA-WHT-ATD/AMP-VLT
BP #4	Aimlite	EBST24350-2MD5WLA-WHT-ATD/AMP-VLT
EX	Aimlite	RPSTUMWHT-UNVDC

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RMHZ-2112-24V6WLA/MR16/CM Notes 8-10 weeks	Type DRH-XP

RMHZ

Hazardous location remote fixture

6, 12 or 24VDC Models

Wall, Ceiling or Pendant Mount

Project: _____

Type: _____

Catalogue #: _____

Drawn by: _____

Date: _____

Designed to meet the strictest Codes, the RMHZ series of hazardous location remote fixtures provides safe and dependable operation. The RMHZ series housings are built with die cast, copper free aluminum, in a variety of Class and Division rated models. Available as 6V, 12V or 24V models with wall, ceiling or pendant mounted configuration.



FEATURES AND SPECIFICATIONS

CIRCUITRY - AC & AC/DC

- Single or double internal MR11 or MR16 lamp assemblies
- Quartz-halogen or LED lamps

MECHANICAL

- Die cast, copper free aluminum, grey finish
- Heavy-duty Pyrex glass lens
- Internal MR11 or MR16 lamp assembly is fully adjustable
- Wall, ceiling or pendant mounting (as specified)
- Wiring pre-pulled through fixture
- Wall and ceiling models c/w integrated die cast junction box
- Junction box c/w oversized integral mounting holes and tapped and plugged rigid holes
- Temperature code: T6

APPROVALS

- CSA Certified to C22.2 #137
- CSA Certified to C22.2 #141-15
- Class I, Division 1, Groups C & D
- Class I, Zone 1 & 2, Groups IIA & IIB

COMPLIANCE

- Meets requirements of ICES-005


LED

HAZARDOUS LOCATION


ICES 005

DIMENSIONS


PENDANT MOUNT



CEILING MOUNT



WALL MOUNT



OVERVIEW

Light source	Quartz or LED
DC voltage	6VDC, 12VDC or 24VDC

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RMHZ-2112-24V6WLA/MR16/CM Notes 8-10 weeks	Type DRH-XP

RMHZIII

ORDERING GUIDE - LED

RMHZ ____ ____ — ____ ____ ____ 1 1 CD / ____

Series	Head	Nbr of lamps	Voltage	Wattage	Lamp type	Mounting	Class	Div.	Group	Options
RMHZ	1 - Single 2 - Double (with J-Box)	1 - Single lamp per head 2 - Double lamp per head	06-24 - 6VDC to 24VDC operational 12-24 - 12VDC to 24VDC operational	4W - 4 watts 5W - 5 watts 6W - 6 watts 7W - 7 watts	LR - LED LA - LED LA - LED	C - Ceiling mount P - Pendant mount M - Wall mount	1	1	C D	LGD - Die cast lens guard

ORDERING GUIDE - INCANDESCENT

RMHZ ____ ____ — ____ ____ WQ ____ 1 1 CD / ____

Series	Head	Nbr of lamps	Voltage	Lamp	Lamp type	Mounting	Class	Div.	Group	Options
RMHZ	1 - Single 2 - Double (with J-Box)	1 - Single lamp per head 2 - Double lamp per head	06 - 6VDC 12 - 12VDC 24 - 24VDC	See lamp selection	WQ - Quartz halogen	C - Ceiling mount P - Pendant mount M - Wall mount	1	1	C D	LGD - Die cast lens guard

LAMP SELECTION

	6 Volts	12 Volts	24 Volts
MR11 • Small head			
Quartz halogen	10WQ	20WQ	20WQ

MOUNTING SHALL BE TO SUIT LOCATION

All products are subject to change or may be discontinued any time without notice.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number EBHZ-2414411CD-2Z16WLA Notes 8-10 weeks	Type BP1+2

EBHZ

Hazardous location battery unit

6, 12 or 24VDC Models

120/347VAC Input

Project: _____

Type: _____

Catalogue #: _____

Drawn by: _____

Date: _____

Designed to meet the strictest codes and standards, the EBHZ series of hazardous location battery units provides safe and dependable operation. The EBHZ series housings are built with die cast, copper free aluminum, in a variety of Class and Division rated models. Available in 6, 12 and 24VDC models in a range of capacities from 36 to 320W, for 30 minutes duration.



FEATURES AND SPECIFICATIONS

CIRCUITRY

- Range of input voltages 120 or 347VAC
- Single or double internal MR11 or MR16 lamp assemblies
- 6VDC, 12VDC or 24VDC emergency power output versions (as specified)
- Wattage capacities from 36 to 320W
- 30 minutes emergency power duration standard
- Diagnostic/pilot LED for AC ON
- High efficiency, rapid recovery, precision control charging system
- Brownout and short circuit protection
- Temperature compensated
- Large magnum terminal screw type connectors for remote load connection
- Maintenance free, sealed lead acid battery

MECHANICAL

- Die cast, copper free aluminum housing - grey aluminum finish
- Housing cavity accessed via large circular screw on/off cover plate
- Standard stainless steel one-way breather valve for release of gases and/or moisture condensation
- Housing c/w tapped and plugged rigid holes
- Solid state design and construction
- Oversized integral mounting holes/forks accept heavy-duty mounting hardware
- Internal MR11 or MR16 lamp assembly is fully adjustable
- Temperature code: T6

APPROVALS

- CSA Certified to C22.2 #137
- CSA Certified to C22.2 #141-15
- Class I, Division 1, Groups C & D
- Class I, Zone 1 & 2, Groups IIA & IIB

COMPLIANCE


- Meets requirements of ICES-005

HAZARDOUS LOCATION


ICES 005

DIMENSIONS

ENCLOSURE A



ENCLOSURE B



Dimensions are subject to change according to exact Class, Division & Group specifications.

OVERVIEW

Input voltage	120 or 347V AC
DC voltage	6VDC, 12VDC or 24VDC
Output power	36W - 320W

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number EBHZ-2414411CD-2Z16WLA Notes 8-10 weeks	Type BP1+2

EBHZIII

ORDERING GUIDE

EBHZ			1	1	CD		—			

Series	Voltage	Wattage	Class	Div.	Group	Input voltage	Head	Lamp/Head	Lamp
EBHZ	**06 -** 6VDC **12 -** 12VDC **24 -** 24VDC	See model rating below	1	1	C D	**Blank -** 120/347V	**1Z -** Single **2Z -** Double	**1 -** Single lamp assembly **2 -** Double lamp assembly	See lamp selection below 6WLA

LAMP SELECTION

	6 Volts	12 Volts	24 Volts
MR11 • Small head			
Quartz halogen	10WQ	20WQ	20WQ
MR16			
LED	4WLR, 5WLA	4WLR, 5WLA, 6WLA, 7WLA	4WLR, 5WLA, 6WLA, 7WLA

MODEL RATINGS

Wattage capacities

Model	Enclosure	Voltage	30 min.	60 min.	90 min.	120 min.
EBHZ06036	A	6VDC	36	18	12	9
EBHZ06050	A	6VDC	50	25	16	12
EBHZ06072	A	6VDC	72	36	24	18
EBHZ12036	A	12VDC	36	18	12	9
EBHZ12050	A	12VDC	50	25	16	12
EBHZ12072	A	12VDC	72	36	24	18
EBHZ12100	A	12VDC	100	50	33	25
EBHZ12160	B	12VDC	160	80	53	40
EBHZ12200	B	12VDC	200	100	66	50
EBHZ24144	A	24VDC	144	72	48	36
EBHZ24320	B	24VDC	320	160	106	80

All products are subject to change or may be discontinued any time without notice.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RPZN21GRY Notes 2-4 weeks	Type EX-XP

RPZN2

Hazardous location

AC, AC/DC & Self-Powered

Project: _____

Type: _____

Catalogue #: _____

Drawn by: _____

Date: _____

The RPZN2 series of Class I, Division II / Zone 2 rated running man are designed to perform in demanding hazardous applications. The unit maintains its sealed interior with a continuous integral gasket. As well LED pilot light and test switch are sealed type.



(self powered version)

FEATURES AND SPECIFICATIONS

ELECTRICAL - AC/DC

- LED ultra bright light source
- 120/347VAC Input, field selectable
- 3.6 Watt power consumption
- Emergency DC wattages as follows: **6VDC** = 1.8W **12VDC** = 1.8W **24VDC** = 1.8W

ELECTRICAL - SELF-POWERED

- LED ultra bright light source
- 120/347VAC Input, field selectable
- 4 Watt power consumption
- High-performance, sealed Ni-Cad battery
- 90 minutes emergency duration (standard)
- Solid state transfer and battery charger

MECHANICAL

- Heavy-duty non-metallic, reinforced construction
- One piece, molded and gasketed lens
- Bottom hinged cover secured with two screws
- One-way breather valve for release of gases and/or moisture condensation
- All external metal hardware is stainless steel
- Single face, wall mount only
- Grey finish housing, white faceplate standard

APPROVALS

- CSA Certified to C22.2 #137
- CSA Certified to C22.2 #141-15
- CSA Certified to C860-11
- Class I, Division 2, Groups A, B, C, D
- Class I, Zone 2, Groups IIA, IIB, IIC

COMPLIANCE


- Meets requirements of ICES-005


LED

HAZARDOUS LOCATION

ICES 005

DIMENSIONS







Comes standard (single face) with three pictogram legends for direction selection.

OVERVIEW

Light source	LED
Input voltage	120/347V AC
Input power	3.6W AC/DC 4W self-powered
DC voltage	6VDC, 12VDC or 24VDC
DC power	1.8W

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RPZN21GRY Notes 2-4 weeks	Type EX-XP

RPZN2III

ORDERING GUIDE

RPZN2	1	GRY	—	/

Series	Nbr of faces	Colour	Operation	Options
RPZN2	1 - Single face	GRY - Grey	UNVDC - Universal DC backup voltage from 6 to 24VDC BAT - Self-powered for 90 minutes	D U UR DR DL UL

TEMPERATURE CODES

	25°C	40°C
UNVDC	T6	T6
BAT	T6	T5

EXIT SIGN AS SPEC 26 53 00 2.1 .8, SELF POWERED NOT ALOWED.

Comments

All products are subject to change or may be discontinued any time without notice.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RMMD2-12-24V6WLA Notes stock-2 weeks	Type DRH

RMMD

Project:

Contractor:

COMPACT REMOTE

MR16 Surface Mount
Single, Double or Triple
6V, 12V, & 24V Lamps




Approvals:
CSA Certified to C22.2 #141.15

DESCRIPTION

The RMMD series of commercial MR16 remotes provides exceptional light output in a compact, traditional design. The die cast, all metal housing is fully adjustable with a friction lock tilt and swivel that can be locked in place with a rear mounted set screw. The canopy is designed to mount directly to typical electrical junction boxes. Available in 6V, 12V and 24V models, all utilizing low glare, MR16 quartz halogen or LED lamps.

DIMENSIONS



MECHANICAL

- Die cast, solid metal housing with die cast, twist lock lamp collar
- Complete adjustablity - both tilt and swivel
- 5" diameter canopy standard
- Two canopy mounting holes designed to match standard electrical junction boxes
- White paint finish is standard, black colour is optional
- MR16 lamp designed with low glare reflector and available in 6VDC, 12VDC or 24VDC

ORDERING GUIDE – LED

RMMD ____ — ____ ____ ____ / ____

Series	Number of heads	Voltage	Wattage	Lamp type	Colour	Options†
RMMD	**1** - Single head **2** - Double head ~~**3** - Triple head~~ **4** - Quad head (require 12" dia. canopy)	**06 - 24** - 6VDC to 24VDC operational	**4W** - 4 watts	**LR** - LED	**WHT** - White (standard) ~~**BLK** - Black~~	**LCP, VDR, WRG, LXG**
			5W - 5 watts	**LA** - LED		
		12 - 24 - 12VDC to 24VDC operational	**6W** - 6 watts ~~**7W** - 7 watts~~	**LA** - LED		

ORDERING GUIDE – INCANDESCENT

RMMD ____ — ____ ____ ____ / ____

Series	Number of heads	Voltage	Lamp	Colour	Options†
RMMD	**1** - Single head **2** - Double head **3** - Triple head **4** - Quad head (require 12" dia. canopy)	**06V** - 6VDC **12V** - 12VDC **24V** - 24VDC	See lamp selection chart	**WHT** - White (standard) **BLK** - Black	**LCP, VDR, WRG, LXG**

INCANDESCENT LAMP SELECTION

	6 Volts	12 Volts	24 Volts
MR16 - Small head			
Quartz halogen	08Q, 10Q, 12Q, 20Q	08Q, 10Q, 12Q, 20Q, 35Q, 50Q	10Q, 12Q, 20Q, 35Q, 50Q

† For detailed options descriptions, please consult the options page.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number EBST24144-2MD5WLA-WHT-ATD/AMP-VLT Notes (please note AUD is not included not on spec sheet?) 2-3 weeks	Type BP# 3,5,6,7

EBST


Project:

Contractor:

STEEL BATTERY UNIT

6V, 12V or 24V Models
18-720W Capacity
120/347VAC Input

Approvals:
CSA Certified to C22.2 #141.15





DESCRIPTION


The EBST series of commercial steel battery units is designed to provide efficient and reliable emergency lighting. Utilizing a sturdy, all steel housing, the EBST presents a modern and unobtrusive design. On higher capacity models, the cabinet front is sloped to allow better internal access and superior low angle light distribution. The EBST series is available in 6VDC, 12VDC and 24VDC versions in a range of wattage capacities between 18 and 720W, for 30 minutes duration. Units are typically supplied with two top mounted PAR18 or PAR36 type heads, however a wide range of head type, number and placement are available including MR16 type. The EBST can also accommodate a wide variety of options, including auto-testing self-diagnostics and remote testing.

MECHANICAL

- Rugged steel cabinet with ultraguard rust-coating
- 120VAC line cord supplied standard
- Universal spider knockout pattern and keyhole mounting slots stamped into back of cabinet
- Multiple conduit entry knockouts
- White powder coat finish standard, other finishes and Colours optional
- Lamp heads include PAR18 small style, PAR36 large style and die cast metal MR16 type
- Top head mounting is standard, side mount is optional

CIRCUITRY

- 120/347VAC 60Hz Input, field selectable
- High efficiency, rapid recovery, precision control charging system
- 6VDC, 12VDC or 24VDC emergency power output versions (as specified)
- Wattage capacities from 18 to 720W
- 30 Minutes emergency power duration standard
- Momentary push button test switch
- Diagnostic/pilot LEDs for AC ON and CHARGE
- Fully automatic, current limited charger
- Line latched, low voltage protection
- Solid state design and construction
- Brownout and short circuit protection
- Temperature compensated
- Load connection 72W and above
- Complete battery recharge in 24 hours
- Maintenance free, sealed lead acid battery
- Optional automatic-testing, self-diagnostic charger board:
  - Continuously monitors the operational status of the battery unit
  - Automatically performs battery and lamp load testing at preset intervals
  - Indicates any component malfunctions or automated test failures



Type SM – PAR18
Thermoplastic
18W max.

Type MD – MR16
Die cast
35W max.

Type MB – MR16
Die cast
35W max.

Type LG – PAR36
Thermoplastic
70W max.

ORDERING GUIDE

EBST ____ ____ — ____ ____ / ____

Series	Voltage	Wattage	Head/Lamp		Lamp	Colour	Options†
EBST	**06** - 6VDC **12** - 12VDC **24** - 24VDC	See model rating below 144	**0** - No Heads **1SM** - One PAR18 **2SM** - Two PAR18 **1LG** - One PAR36 **2LG** - Two PAR36	**1MD** - One MR16 **2MD** - Two MR16 **1MB** - One MR16 **2MB** - Two MR16	See lamp list below 5WLA	**WHT** - White (standard) **BLK** - Black **GRY** - Grey	**ATD, TDL*, LPD, BTD, VLT, AMP, ACT, DCT, FS4, RDS*, NLC, TLP, CAB, VDR, MTS, WRG, IRT, IRC**

† For detailed options descriptions, please consult the options page. * Specify AC voltage.

LAMP SELECTION

	6 Volts	12 Volts	24 Volts
PAR18 - Small head or LED Lamp			
LED	3WLJ, 4WLJ, 5WLA	3WLJ, 4WLJ, 5WLA, 6WLA, 7WLA	4WLR, 5WLA, 6WLA, 7WLA
Quartz halogen	08WQ, 10WQ, 12WQ	10WQ, 12WQ	12WQ
Tungsten	09WT	09WT, 12WT, 18WT	09WT, 18WT
MR16 - Small head c/w MR16 or LED Lamp			
LED	4WLR, 5WLA	4WLR, 5WLA, 6WLA, 7WA	4WLR, 5WLA, 6WLA, 7WLA
Quartz halogen	08WQ, 10WQ, 12WQ, 20WQ	08WQ, 10WQ, 12WQ, 20WQ, 35WQ	10WQ, 12WQ, 20WQ
PAR36 - Large head			
Quartz halogen	08WQ, 10WQ, 12WQ, 20WQ	10WQ, 12WQ , 20WQ, 35WQ	12WQ
Tungsten	09WT, 18WT, 25WT	09WT, 18WT, 25WT	09WT, 18WT, 25WT
Quartz sealed beam	08WSBQ, 10WSBQ, 12WSBQ, 20WSBQ	08WSBQ, 12WSBQ, 35WSBQ, 55WSBQ	70WSBQ
Tungsten sealed beam	08WSBT, 09WSBT, 18WSBT	25WSBT	N/A

MODEL RATINGS

		Wattage Capacities				
Model	Voltage	30 min.	60 min.	90 min.	120 min.	Cabinet
EBST-06018	6V	18	9	N/A	N/A	A
EBST-06036	6V	36	18	12	9	A
EBST-06050	6V	50	25	16	12	A
EBST-06072	6V	72	36	24	18	B
EBST-06100	6V	100	50	33	25	B
EBST-06160	6V	160	80	53	40	C
EBST-06180	6V	180	90	60	45	C
EBST-12036	12V	36	18	12	9	A
EBST-12050	12V	50	25	16	12	A
EBST-12072	12V	72	36	24	18	A
EBST-12100	12V	100	50	33	25	B
EBST-12144	12V	144	72	48	36	C
EBST-12160	12V	160	80	53	40	C
EBST-12200	12V	200	100	66	50	C
EBST-12250	12V	250	125	83	62	D
EBST-12360	12V	360	180	120	90	D
EBST-24144	24V	144	72	48	36	C
EBST-24200	24V	200	100	66	50	C
EBST-24320	24V	320	160	106	80	D
EBST-24350	24V	350	175	116	87	E
EBST-24550	24V	550	275	183	137	E
EBST-24720	24V	720	360	240	180	E

NOTE: Due to cabinet/space limitations, not all options are available for all models in any given combination. Please consult with your factory representative regarding specific options and exact cabinet dimension information.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number EBST24350-2MD5WLA-WHT-ATD/AMP-VLT Notes (please note AUD is not included not on spec sheet?) 2-3 weeks	Type BP #4

EBST


Project:

Contractor:

STEEL BATTERY UNIT

6V, 12V or 24V Models
18-720W Capacity
120/347VAC Input

Approvals:
CSA Certified to C22.2 #141.15





DESCRIPTION


The EBST series of commercial steel battery units is designed to provide efficient and reliable emergency lighting. Utilizing a sturdy, all steel housing, the EBST presents a modern and unobtrusive design. On higher capacity models, the cabinet front is sloped to allow better internal access and superior low angle light distribution. The EBST series is available in 6VDC, 12VDC and 24VDC versions in a range of wattage capacities between 18 and 720W, for 30 minutes duration. Units are typically supplied with two top mounted PAR18 or PAR36 type heads, however a wide range of head type, number and placement are available including MR16 type. The EBST can also accommodate a wide variety of options, including auto-testing self-diagnostics and remote testing.

MECHANICAL

- Rugged steel cabinet with ultraguard rust-coating
- 120VAC line cord supplied standard
- Universal spider knockout pattern and keyhole mounting slots stamped into back of cabinet
- Multiple conduit entry knockouts
- White powder coat finish standard, other finishes and Colours optional
- Lamp heads include PAR18 small style, PAR36 large style and die cast metal MR16 type
- Top head mounting is standard, side mount is optional

CIRCUITRY

- 120/347VAC 60Hz Input, field selectable
- High efficiency, rapid recovery, precision control charging system
- 6VDC, 12VDC or 24VDC emergency power output versions (as specified)
- Wattage capacities from 18 to 720W
- 30 Minutes emergency power duration standard
- Momentary push button test switch
- Diagnostic/pilot LEDs for AC ON and CHARGE
- Fully automatic, current limited charger
- Line latched, low voltage protection
- Solid state design and construction
- Brownout and short circuit protection
- Temperature compensated
- Load connection 72W and above
- Complete battery recharge in 24 hours
- Maintenance free, sealed lead acid battery
- Optional automatic-testing, self-diagnostic charger board:
  - Continuously monitors the operational status of the battery unit
  - Automatically performs battery and lamp load testing at preset intervals
  - Indicates any component malfunctions or automated test failures



Type SM – PAR18
Thermoplastic
18W max.

Type MD – MR16
Die cast
35W max.

Type MB – MR16
Die cast
35W max.

Type LG – PAR36
Thermoplastic
70W max.

ORDERING GUIDE

EBST — /

Series	Voltage	Wattage	Head/Lamp		Lamp	Colour	Options†
EBST	**06** - 6VDC **12** - 12VDC **24** - 24VDC	See model rating below 350	**0** - No Heads **1SM** - One PAR18 **2SM** - Two PAR18 **1LG** - One PAR36 **2LG** - Two PAR36	**1MD** - One MR16 **2MD** - Two MR16 **1MB** - One MR16 **2MB** - Two MR16	See lamp list below 5WLA	**WHT** - White (standard) **BLK** - Black **GRY** - Grey	**ATD, DL*, LPD, BTD, VLT, AMP, ACT, DCT, FS4, RDS*, NLC, TLP, CAB, VDR, MTS, WRG, IRT, IRC**

† For detailed options descriptions, please consult the options page. * Specify AC voltage.

LAMP SELECTION

	6 Volts	12 Volts	24 Volts
PAR18 - Small head or LED Lamp			
LED	3WLJ, 4WLJ, 5WLA	3WLJ, 4WLJ, 5WLA, 6WLA, 7WLA	4WLR, 5WLA, 6WLA, 7WLA
Quartz halogen	08WQ, 10WQ, 12WQ	10WQ, 12WQ	12WQ
Tungsten	09WT	09WT, 12WT, 18WT	09WT, 18WT
MR16 - Small head c/w MR16 or LED Lamp			
LED	4WLR, 5WLA	4WLR, 5WLA, 6WLA, 7WA	4WLR, 5WLA, 6WLA, 7WLA
Quartz halogen	08WQ, 10WQ, 12WQ, 20WQ	08WQ, 10WQ, 12WQ, 20WQ, 35WQ	10WQ, 12WQ, 20WQ
PAR36 - Large head			
Quartz halogen	08WQ, 10WQ, 12WQ, 20WQ	10WQ, 12WQ , 20WQ, 35WQ	12WQ
Tungsten	09WT, 18WT, 25WT	09WT, 18WT, 25WT	09WT, 18WT, 25WT
Quartz sealed beam	08WSBQ, 10WSBQ, 12WSBQ, 20WSBQ	08WSBQ, 12WSBQ, 35WSBQ, 55WSBQ	70WSBQ
Tungsten sealed beam	08WSBT, 09WSBT, 18WSBT	25WSBT	N/A

MODEL RATINGS

		Wattage Capacities				
Model	Voltage	30 min.	60 min.	90 min.	120 min.	Cabinet
EBST-06018	6V	18	9	N/A	N/A	A
EBST-06036	6V	36	18	12	9	A
EBST-06050	6V	50	25	16	12	A
EBST-06072	6V	72	36	24	18	B
EBST-06100	6V	100	50	33	25	B
EBST-06160	6V	160	80	53	40	C
EBST-06180	6V	180	90	60	45	C
EBST-12036	12V	36	18	12	9	A
EBST-12050	12V	50	25	16	12	A
EBST-12072	12V	72	36	24	18	A
EBST-12100	12V	100	50	33	25	B
EBST-12144	12V	144	72	48	36	C
EBST-12160	12V	160	80	53	40	C
EBST-12200	12V	200	100	66	50	C
EBST-12250	12V	250	125	83	62	D
EBST-12360	12V	360	180	120	90	D
EBST-24144	24V	144	72	48	36	C
EBST-24200	24V	200	100	66	50	C
EBST-24320	24V	320	160	106	80	D
EBST-24350	24V	350	175	116	87	E
EBST-24560	24V	560	280	180	137	E
EBST-24720	24V	720	360	240	180	E

NOTE: Due to cabinet/space limitations, not all options are available for all models in any given combination. Please consult with your factory representative regarding specific options and exact cabinet dimension information.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RPSTUMWHT-UNVDC Notes stock-2 weeks	Type EX

RPST

Project:

Contractor:

STEEL
NBC2010 Compliant



Approvals:
CSA Certified to C22.2 #141.15 and C860


DESCRIPTION
The clean lines of the RPST series of commercial steel signs present a fully modern appearance. The steel provides for a rigid, durable and lightweight sign. Available in AC only, AC/DC and internally self-powered versions.

CIRCUITRY - AC & AC/DC
- LED ultra bright light source
- 120/347VAC Input, field selectable
- 1.9W power consumption single or double face
- Emergency DC wattages as follows:
  6VDC = 0.9W **12VDC** = 0.9W **24VDC** = 0.9W

CIRCUITRY - SELF-POWERED
- LED ultra bright light source
- 120/347VAC Input, field selectable
- 2.0W power consumption single or double face
- High-performance, Ni-Cad battery
- 90 or 120 minutes emergency duration
- Solid state transfer and battery charger

MECHANICAL
Supply and install AimLite Steel LED Running Man sign in accordance with NBC2010, C22.2 No. 141. The equipment shall operate with universal AC input of 120/347V at less than 2.0W and universal DC input voltage from 6V to 24V. The housing shall be constructed of rugged steel and have a maximum depth of 2-1/4". The faceplates shall be open face type with a steel contour. The light source shall be high performing light emitting diodes (LED) and the LED lamps shall provide illumination in normal and emergency operation and shall be mounted inside the Running Man housing. A white LED sensitive diffuser shall be used to provide an evenly illuminated green and white legend. Universal models include ceiling or end mount, field installable canopy kit c/w spider plate. Universal models include ceiling or end mount, field installable canopy kit c/w spider plate.

The Running Man in a self powered configuration shall be equipped with a nickel cadmium battery and shall stay illuminated during emergency operation for at least 90 or 120 minutes upon AC fail.

DIMENSIONS




Comes standard (single face) with three pictogram legends for direction selection.



Comes standard (double face) with two pictogram legends.



For double face no arrow options, select "0" on the options column.

ORDERING GUIDE

RPST		M		—		/	

Series	Nbr of faces	Mounting	Colour	DC Voltage	Options†
RPST	**U** - Universal faces **1** - Single face **2** - Double face	**M** - Universal	**WHT** - White (standard) **BLK** - Black **GRY** - Grey **CUS** - Custom colour (please specify)	**NDC** - AC only **UNVDC** - Universal DC backup voltage from 6 to 24VDC **BAT** - Self-powered for 90 minutes **BAT1** - Self-powered for 120 minutes	**ATD*, WRG**, K5, LXG, SPW, BKO, BNO** **0** - No indicators (double face only) **D U UR DR DL UL** **Note:** Indicators option available for single & double option only.

† For detailed options descriptions, please consult the options page.
* ATD available with BAT and BAT1.
** Specify mounting.

Date: July 11, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd
NAME: Sandra Rousseau P.Eng
DATE: Jul 11, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-10
PO-P18-162

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 26 05 36 Cable Trays for Electrical Systems

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-010

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-30
BY Konrad

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the

Responsibility remains with the contractor as per the contract documents.

Do not hesitate to contact me if you have any questions or concerns.

Engineering Cable Tray Specification (cont'd)

Table 3

Steel Load / Span Class Designation

Side Rail Height (in.)	Series	Load Depth (in.) Nominal	NEMA Class	CSA Class
3-5/8	SH13/SP13/SS13	2-5/8	12A	C/3m
4	SH14/SP14/SS14 SH34/SP34/SS34	3	12C 20A	D/3m D/6m
5	SH25/SP25/SS25 SH45/SP45/SS45 SH55/SP55	4	20A 20B 20C	D/6m E/6m
6	SH16/SP16/SS16 SH36/SP36/SS36 SH46/SP46/SS46	5	20A 20B 20C	D/6m E/6m –
7	SH37/SP37/SS37	6	20C	–

**Must Confirm Class of Tray Required-Quoted Series 1

Straight Lengths

6 in. Straight Sections
Series 1-6, 3-6, 4-6

Ladder, ventilated and solid trough

Straight Section Number Selection P/N- SH1624L12-3

SH3624L12-6

Material Prefix	Series	Side Rail Height	Width	Bottom Type	Length
SP • Pregalvanized SH • Hot-dipped galvanized after fabrication SS • Stainless Steel 316	1 • Series 1 3 • Series 3 4 • Series 4	6 • (6 in.)	06 • (6 in.) 09 • (9 in.) 12 • (12 in.) 18 • (18 in.) 24 • (24 in.) 30 • (30 in.) 36 • (36 in.) 42 • (42 in.)	L06 • 6 in. rung spacing L09 • 9 in. rung spacing L12 • 12 in. rung spacing V • Ventilated ** S • Solid trough	3 • (3 meters) 6 • (6 meters) 144 • (12 ft.) 288 • (24 ft.)

** For load ratings of CSA Class C/NEMA 8C or less, please see an alternative ventilated series of cable tray called - One-Piece found on pages A160 to A191 of this catalogue.

Technical Specifications

All calculations and data are based on 42 in. wide cable trays with rungs spaced on 12 in. centers with tray supported as simple spans with deflection measured at the midpoint. Continuous spans may reduce deflection by as much as 50%.

Deflection factor: For lighter loads, deflection at any length can be calculated by multiplying the load by the deflection factor.


For Fittings consult pages A50 to A91.

Series		Support Span (Feet)							
		6	8	10	12	14	16	18	20
SP1-6	Load (lb.)/ft.	556	313	200	139	102	78	62	50
SH1-6	Deflection (in.)	0.122	0.216	0.338	0.486	0.662	0.865	1.095	1.351
SS1-6	Deflection Factor	0.0002	0.0007	0.0017	0.0036	0.0065	0.0111	0.0177	0.0270
SP3-6	Load (lb.)/ft.	833	469	300	208	153	117	93	75
SH3-6	Deflection (in.)	0.151	0.268	0.419	0.603	0.821	1.072	1.357	1.675
SS3-6	Deflection Factor	0.0002	0.0006	0.0014	0.0030	0.0055	0.0092	0.0146	0.0223
SP4-6	Load (lb.)/ft.	–	728	466	324	238	182	144	117
SH4-6	Deflection (in.)	–	0.312	0.487	0.702	0.955	1.247	1.579	1.949
SS4-6	Deflection Factor	–	0.0004	0.0011	0.0022	0.0041	0.0069	0.0110	0.0167

Straight Lengths

6 in. Straight Sections
Series 1-6, 3-6, 4-6

Ladder, ventilated and solid trough








Dimensions

SP1-6, SH1-6, SS1-6, SP3-6, SH3-6, SS3-6, SP4-6, SH4-6, SS4-6	
W (in.)	**Wi (in.)**
6	3.34
9	6.34
12	9.34
18	15.34
24	21.34
30	27.34
36	33.34
42	39.34

Technical Specifications

LOAD RATINGS: 1.5 Safety factor. All tray sections will support an additional 200 lb. concentrated load on any portion of tray (side rail, rung, etc.) above and beyond published load class.

Series	Dimensions	Side Rail Design Factors • 1 Pair	Classifications			
			NEMA	CSA	UL	ABS
SP1-6 **SH1-6** **SS1-6**		Ix = 4.44 in.^{4} Sx = 1.39 in.^{3} Area = 0.874 in.^{2}	**20A**	**D/6M**	UL cross sectional Area : 0.70 in.^{2}	Stainless steel only
SP3-6 **SH3-6** **SS3-6**		Ix = 5.373 in.^{4} Sx = 1.70 in.^{3} Area = 1.229 in.^{2}	**20A**	**E/6M**	UL cross sectional Area : 1.00 in.^{2}	Stainless steel only
SP4-6 **SH4-6** **SS4-6**		Ix = 7.173 in.^{4} Sx = 2.250 in.^{3} Area = 1.471 in.^{2}	**20C**	**Exceeds E/6M**	UL cross sectional Area : 1.00 in.^{2}	Stainless steel only

Fittings

45° / 30° Horizontal Bends

Part Numbering System

SHF 4 24 L HB45 12

- SHF: Prefix (SPF, SHF, SSF)
- 4: Side rail height
- 24: Width
- L: Bottom style
- HB45: Fitting type
- 12: Angle
- Nominal radius


Selection Guide

Prefix: SPF (Pregalv.) ,SHF (Hot-Dip) ,SSF (Stainless Steel)
Inside Tray Widths: 6, 9, 12, 18, 24, 30, 36, 42
Angle: 45º, 30º
Nominal Radius: 12, 24, 36, 48
Bottom Styles: L– Ladder, V– Ventilated, S– Solid
Side Rail Heights: 3 in., 4 in., 5 in., 6 in., 7 in.

P/N - SHF624LHB9024

45º Horizontal BEND






Nominal		Cat. No.	Dimensions		
Radius	Width		X	Y	Z
12	6	Prefix(†)-06-(*)-HB45-12	13-5/8	5-5/8	8
	9	Prefix(†)-09-(*)-HB45-12	14-11/16	6-1/16	8-9/16
	12	Prefix(†)-12-(*)-HB45-12	15-3/4	6-1/2	9-3/16
	18	Prefix(†)-18-(*)-HB45-12	17-7/8	7-3/8	10-7/16
	24	Prefix(†)-24-(*)-HB45-12	20	8-1/4	11-11/16
	30	Prefix(†)-30-(*)-HB45-12	22-1/16	9-1/8	12-15/16
	36	Prefix(†)-36-(*)-HB45-12	24-3/16	10	14-3/16
	42	Prefix(†)-42-(*)-HB45-12	26-5/16	10-15/16	15-7/16
24	6	Prefix(†)-06-(*)-HB45-24	22-1/16	9-1/8	12-15/16
	9	Prefix(†)-09-(*)-HB45-24	23-1/8	9-9/16	13-9/16
	12	Prefix(†)-12-(*)-HB45-24	24-3/16	10	14-3/16
	18	Prefix(†)-18-(*)-HB45-24	26-5/16	10-15/16	15-7/16
	24	Prefix(†)-24-(*)-HB45-24	28-7/16	11-13/16	16-11/16
	30	Prefix(†)-30-(*)-HB45-24	30-9/16	12-11/16	17-15/16
	36	Prefix(†)-36-(*)-HB45-24	32-11/16	13-9/16	19-1/8
	42	Prefix(†)-42-(*)-HB45-24	34-13/16	14-7/8	20-3/8
36	6	Prefix(†)-06-(*)-HB45-36	30-9/16	12-11/16	17-15/16
	9	Prefix(†)-09-(*)-HB45-36	31-5/8	13-1/8	18-9/16
	12	Prefix(†)-12-(*)-HB45-36	32-11/16	13-9/16	19-1/8
	18	Prefix(†)-18-(*)-HB45-36	34-13/16	14-7/16	20-3/8
	24	Prefix(†)-24-(*)-HB45-36	36-15/16	15-5/16	21-5/8
	30	Prefix(†)-30-(*)-HB45-36	39-1/16	16-3/16	22-7/8
	36	Prefix(†)-36-(*)-HB45-36	41-3/16	17-1/16	24-1/8
	42	Prefix(†)-42-(*)-HB45-36	43-5/16	17-15/16	25-3/8
48	6	Prefix(†)-06-(*)-HB45-48	39-1/16	16-3/16	22-7/8
	9	Prefix(†)-09-(*)-HB45-48	40-1/8	16-3/8	23-1/2
	12	Prefix(†)-12-(*)-HB45-48	41-3/16	17-1/16	24-1/8
	18	Prefix(†)-18-(*)-HB45-48	43-5/16	17-15/16	25-3/8
	24	Prefix(†)-24-(*)-HB45-48	45-7/16	18-13/16	26-5/8
	30	Prefix(†)-30-(*)-HB45-48	47-9/16	19-11/16	27-7/8
	36	Prefix(†)-36-(*)-HB45-48	49-11/16	20-9/16	29-1/8
	42	Prefix(†)-42-(*)-HB45-48	51-13/16	21-7/16	30-5/16

30º Horizontal BEND





Nominal		Cat. No.	Dimensions		
Radius	Width		X	Y	Z
12	6	Prefix(†)-06-(*)-HB30-12	11-5/8	3-1/8	6-3/16
	9	Prefix(†)-09-(*)-HB30-12	12-3/8	3-5/16	6-5/8
	12	Prefix(†)-12-(*)-HB30-12	13-1/2	3-1/2	7
	18	Prefix(†)-18-(*)-HB30-12	14-5/8	3-15/16	7-13/16
	24	Prefix(†)-24-(*)-HB30-12	16-1/8	4-5/16	8-5/8
	30	Prefix(†)-30-(*)-HB30-12	17-5/8	4-11/16	9-7/16
	36	Prefix(†)-36-(*)-HB30-12	19-1/8	5-1/8	10-1/4
	42	Prefix(†)-42-(*)-HB30-12	20-5/8	5-1/2	11-1/16
24	6	Prefix(†)-06-(*)-HB30-24	17-5/8	4-11/16	9-7/16
	9	Prefix(†)-09-(*)-HB30-24	18-3/8	4-15/16	9-13/16
	12	Prefix(†)-12-(*)-HB30-24	19-1/8	5-2/16	10-4/16
	18	Prefix(†)-18-(*)-HB30-24	20-5/8	5-8/16	11-1/16
	24	Prefix(†)-24-(*)-HB30-24	22-1/8	5-15/16	11-13/16
	30	Prefix(†)-30-(*)-HB30-24	23-5/8	6-5/16	12-10/16
	36	Prefix(†)-36-(*)-HB30-24	25-1/8	6-12/16	13-7/16
	42	Prefix(†)-42-(*)-HB30-24	26-5/8	7-1/8	14-1/4
36	6	Prefix(†)-06-(*)-HB30-36	23-5/8	6-5/16	12-5/8
	9	Prefix(†)-09-(*)-HB30-36	24-3/8	6-1/2	13-1/16
	12	Prefix(†)-12-(*)-HB30-36	25-1/8	6-3/4	13-7/16
	18	Prefix(†)-18-(*)-HB30-36	26-5/8	7-1/4	14-1/4
	24	Prefix(†)-24-(*)-HB30-36	28-1/8	7-1/2	15-1/16
	30	Prefix(†)-30-(*)-HB30-36	29-5/8	7-15/16	15-7/8
	36	Prefix(†)-36-(*)-HB30-36	31-1/8	8-5/16	16-11/16
	42	Prefix(†)-42-(*)-HB30-36	32-5/8	8-3/4	17-1/2
48	6	Prefix(†)-06-(*)-HB30-48	29-5/8	7-15/16	15-7/8
	9	Prefix(†)-09-(*)-HB30-48	30-3/8	8-1/8	16-1/4
	12	Prefix(†)-12-(*)-HB30-48	31-1/8	8-5/16	16-11/16
	18	Prefix(†)-18-(*)-HB30-48	32-5/8	8-3/4	17-1/2
	24	Prefix(†)-24-(*)-HB30-48	34-1/8	9-1/8	18-1/4
	30	Prefix(†)-30-(*)-HB30-48	35-5/8	9-9/16	19-1/16
	36	Prefix(†)-36-(*)-HB30-48	37-1/8	9-15/16	19-7/8
	42	Prefix(†)-42-(*)-HB30-48	38-5/8	10-5/16	20-11/16

(†) Insert side rail height. (*) Insert bottom style to complete CAT. NO. Includes 1 pair of splice plates with hardware.

Fittings

Horizontal Tees, Crosses

Part Numbering System

SHF 4 24 L HT 12


- SHF — Prefix: SPF, SHF, SSF
- 4 — Side rail height
- 24 — Width
- L — Bottom style
- HT — Fitting type
- 12 — Nominal radius

Selection Guide

Prefix: SPF (Pregalv.), SHF (Hot-Dip) ,SSF (Stainless Steel)
Inside Tray Widths: 6, 9, 12, 18, 24, 30, 36, 42
Nominal Radius: 12, 24, 36, 48
Bottom Styles: L– Ladder, V– Ventilated, S– Solid
Side Rail Heights: 3 in., 4 in., 5 in., 6 in., 7 in.


P/N- SHF624LHT24

Horizontal TEE



Nominal		Cat. No.	Dimensions	
Radius	Width		X	Y
12	6	Prefix(†)-06-(*)-HT12	15	30
	9	Prefix(†)-09-(*)-HT12	16-1/2	33
	12	Prefix(†)-12-(*)-HT12	18	36
	18	Prefix(†)-18-(*)-HT12	21	42
	24	Prefix(†)-24-(*)-HT12	24	48
	30	Prefix(†)-30-(*)-HT12	27	54
	36	Prefix(†)-36-(*)-HT12	30	60
	42	Prefix(†)-42-(*)-HT12	33	66
24	6	Prefix(†)-06-(*)-HT24	27	54
	9	Prefix(†)-09-(*)-HT24	28-1/2	57
	12	Prefix(†)-12-(*)-HT24	30	60
	18	Prefix(†)-18-(*)-HT24	33	66
	24	Prefix(†)-24-(*)-HT24	36	72
	30	Prefix(†)-30-(*)-HT24	39	78
	36	Prefix(†)-36-(*)-HT24	42	84
	42	Prefix(†)-42-(*)-HT24	45	90
36	6	Prefix(†)-06-(*)-HT36	39	78
	9	Prefix(†)-09-(*)-HT36	40-1/2	81
	12	Prefix(†)-12-(*)-HT36	42	84
	18	Prefix(†)-18-(*)-HT36	45	90
	24	Prefix(†)-24-(*)-HT36	48	96
	30	Prefix(†)-30-(*)-HT36	51	102
	36	Prefix(†)-36-(*)-HT36	54	108
	42	Prefix(†)-42-(*)-HT36	57	114
48	6	Prefix(†)-06-(*)-HT48	51	102
	9	Prefix(†)-09-(*)-HT48	52-1/2	105
	12	Prefix(†)-12-(*)-HT48	54	108
	18	Prefix(†)-18-(*)-HT48	57	114
	24	Prefix(†)-24-(*)-HT48	60	120
	30	Prefix(†)-30-(*)-HT48	63	126
	36	Prefix(†)-36-(*)-HT48	66	132
	42	Prefix(†)-42-(*)-HT48	69	138

Horizontal CROSS



Nominal		Cat. No.	Dimensions	
Radius	Width		X	Y
12	6	Prefix(†)-06-(*)-HX12	15	30
	9	Prefix(†)-09-(*)-HX12	16-1/2	33
	12	Prefix(†)-12-(*)-HX12	18	36
	18	Prefix(†)-18-(*)-HX12	21	42
	24	Prefix(†)-24-(*)-HX12	24	48
	30	Prefix(†)-30-(*)-HX12	27	54
	36	Prefix(†)-36-(*)-HX12	30	60
	42	Prefix(†)-42-(*)-HX12	33	66
24	6	Prefix(†)-06-(*)-HX24	27	54
	9	Prefix(†)-09-(*)-HX24	28-1/2	57
	12	Prefix(†)-12-(*)-HX24	30	60
	18	Prefix(†)-18-(*)-HX24	33	66
	24	Prefix(†)-24-(*)-HX24	36	72
	30	Prefix(†)-30-(*)-HX24	39	78
	36	Prefix(†)-36-(*)-HX24	42	84
	42	Prefix(†)-42-(*)-HX24	45	90
36	6	Prefix(†)-06-(*)-HX36	39	78
	9	Prefix(†)-09-(*)-HX36	40-1/2	81
	12	Prefix(†)-12-(*)-HX36	42	84
	18	Prefix(†)-18-(*)-HX36	45	90
	24	Prefix(†)-24-(*)-HX36	48	96
	30¥	Prefix(†)-30-(*)-HX36	51	102
	36¥	Prefix(†)-36-(*)-HX36	54	108
	42¥	Prefix(†)-42-(*)-HX36	57	114
48¥	6	Prefix(†)-06-(*)-HX48	51	102
	9	Prefix(†)-09-(*)-HX48	52-1/2	105
	12	Prefix(†)-12-(*)-HX48	54	108
	18	Prefix(†)-18-(*)-HX48	57	114
	24	Prefix(†)-24-(*)-HX48	60	120
	30	Prefix(†)-30-(*)-HX48	63	126
	36	Prefix(†)-36-(*)-HX48	66	132
	42	Prefix(†)-42-(*)-HX48	69	138

(†) Insert side rail height. (*) Insert bottom style to complete CAT. NO. Tees include 2 pairs / Crosses include 3 pairs of splice plates with hardware.
¥ Shipped with SPW-3/8HXHWK hardware kit.

Splice Plates

Splice Plate




Packaged in pairs with zinc plated hardware. Kit contents
4 bolts, 4 nuts, 4 washers
3/8 in. diameter.

Provided as standard with each straight and/or fitting.

Cat. No.	Material Prefix	Side Rail Height
(Prefix)-3-SSP (Prefix)-4-SSP (Prefix)-5-SSP (Prefix)-6-SSP (Prefix)-7-SSP	SPW SHW SSW	4 5 6 7

P/N- SHW6SSP

Expansion Splice Plate



Allows for a 1 in. expansion or contraction of tray system.

Packaged in pairs with hardware. Kit contents
8 bolts, 8 stop nuts, 4 serrated flange nuts 3/8 in. diameter.

Cat. No.	Material Prefix	Side Rail Height
(Prefix)-3-ESP (Prefix)-4-ESP (Prefix)-5-ESP (Prefix)-6-ESP (Prefix)-7-ESP	SPW SHW SSW	3 4 5 6 7

Transition Splice Plate




Cat. No.	Material	Description	Side Rail Height
XNM-XP400-(*)-SS6	Polyester/Fiberglass	Designed to make the transition. from aluminum to steel cable tray Works for all 6 in. side rails.	6

Each pair of plate:
8 x carriage bolt (3/8 x 1 in.) SS316
8 x 3/8 in. serrated flange nut SS316

Step Down Splice Plate






Connects side rails of different heights. Hardware included.
Kit contents 8 bolts, 8 nuts, 8 washers 3/8 in. diameter.

Cat. No.	Material Prefix	Side Rail Width (in.)
(Prefix)-(*)-(**)-SDS	SPW SHW SSW	4 5 6 7

(*) Insert side rail height 1.
(**) Insert side rail height 2.
Note: Side rail height 1 is greater than side rail height 2.

Horizontal Adjustable Plate





Furnished in pairs with hardware.

Cat. No.	Material Prefix	Side Rail Height (in.)	Tray Width (in.)
(Prefix)-(*)06HBP (Prefix)-(*)09HBP (Prefix)-(*)12HBP (Prefix)-(*)18HBP (Prefix)-(*)24HBP (Prefix)-(*)30HBP (Prefix)-(*)36HBP (Prefix)-(*)42HBP	SPW SHW SSW	3 4 5 6 7	06 09 12 18 24 30 36 42

(*) Insert side rail height.

Clamps and Hardware


Self-drilling – tapping screw



Cat. No.	Material	Description
SPW-10-SCR	Zinc plated steel	Self-drilling – tapping screw
SSW-10-SCR	Stainless steel	Self-drilling – tapping screw

Hold Down Clamp





Cat. No.	Material Prefix	Side Rail Height (in.)
(Prefix)-3-HDC	SPW SHW SSW	3
(Prefix)-4-HDC		4
(Prefix)-5-HDC		5
(Prefix)-6-HDC		6
(Prefix)-7-HDC		7

Note: Hardware included. Kit contains 1 bolt and 1 channel nut.

PN- SPW6HDC


Hold Down Clamp



Cat. No.	Type	Material	Design Load
SPWHDCS	Single	Pregalvanized	800 lb./pair
SHWHDCS	Single	Hot-dipped galvanized	
SSWHDCS	Single	Stainless steel 316	
SPWHDCD	Double	Pregalvanized	1500 lb./pair
SHWHDCD	Double	Hot-dipped galvanized	
SSWHDCD	Double	Stainless steel 316	

Conduit Clamp





Cat. No.	Type	Material
PU100CC	1	Pregalvanized
PU125CC	1-1/4	
PU150CC	1-1/2	
PU200CC	2	
PU250CC	2-1/2	
PU300CC	3	
PU400CC	4	

SQUARE D
by Schneider Electric

Job Name:	IQALUIT WASTE WATER TREATMENT UPGR	Square D Quotation #:	41720903
Job Location:	OTTAWA, ON	Quotation Revision #:	
		Sales Contact:	Michael Childs
		Sales Contact Location:	806
Purchaser:	92941–GUILLEVIN INT'L INC. (V4990)	Customer:	ARCTIC ELECTRIC
Purchaser PO #:		Customer PO #:	
User:		Architect:	
User Location:		Cons. Engineer:	
Drawing Status:	RECORD		

TABLE OF CONTENTS

SQUARE D FACTORY ORDER NUMBER: 41720903–001

Equipment Designation	Equipment Type	Drawing Type	Drawing Number	Page	Revision Level
1 Seperate VFDS	MODEL 6 MCC	ELEVATION	F41720903–001–01	1	A
			F41720903–001–01	2	A
			F41720903–001–01	3	A
		SEISMIC	S41720903–001–01	1	A
		ONE LINE DIAGRAM	041720903–001–01	1	A
		UNIT INFORMATION	I41720903–001–01	1	A
		ELEMENTARY	E41720903–001–01	1	A
			E41720903–001–01	2	A

STANTEC PROJECT #: 110126045

SUBMITTAL # VFDs

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural
☐ Structural
☐ Mechanical
☑ Electrical
☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED


☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-12-21

BY Evan Harris


REV	DESCRIPTION	BY	DATE										
A	RELEASE TO PRODUCTION	DU	12/19/2018	–	----	--	--/--/--	–	----	--	--/--/--		




DUAL DIMENSIONS: INCHES / MILLIMETERS

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	1 SEPERATE VFDS
JOB LOCATION:	OTTAWA, ON	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	KP	DRAWING TYPE:	ELEVATION
ENGR:	KP		
DATE:	DECEMBER 17, 2018		
DRAWING STATUS:	RECORD	DWG#	F41720903-001-01 PG 1 OF 3 REV A

REV	DESCRIPTION	BY	DATE										
A	RELEASE TO PRODUCTION	DU	12/19/2018	–	----	--	--/--/--	–	----	--	--/--/--		



TOP VIEW



FLOOR VIEW

CROSSED AREA REPRESENTS CONDUIT ENTRY AREA. NUMBERS IN BOXES INDICATE VERTICAL CLEARANCE TO NEAREST OBSTRUCTION.

DUAL DIMENSIONS: INCHES / MILLIMETERS

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	1 SEPERATE VFDS
JOB LOCATION:	OTTAWA, ON	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	KP	DRAWING TYPE:	ELEVATION
ENGR:	KP		
DATE:	DECEMBER 17, 2018		
DRAWING STATUS:	RECORD	DWG#	F41720903-001-01

REV	DESCRIPTION	BY	DATE								
A	RELEASE TO PRODUCTION	DU	12/19/2018	–	----	--	--/--/--	–	----	--	--/--/--
				–	----	--	--/--/--	–	----	--	--/--/--

GENERAL NOTES

Class 1 Type B Wiring

PRODUCT DESCRIPTION AND RATINGS

POWER SYSTEM DATA:

600V 3PH 3W 60Hz
SHORT CIRCUIT RATING: 22kA
POWER CONNECTS TO EXISTING
CONTROL POWER: 120Vac

BUS SYSTEM DATA:

MAIN HORIZONTAL BUS: 600 Amp Copper/Tin Plated / 1.5"
BUS BRACING: 42kA

HORIZONTAL GROUND BUS: .25" X 1.0" (6.35mm X 25.4mm) Tin Plated Copper
Units Securely Grounded To Structure

ENCLOSURE DATA:

ENCLOSURE TYPE: 20" DEEP Type 1A
EXTERIOR COLOR: Electrodeposition Finish ANSI 49 Medium Light Grey
INTERIOR COLOR: Electrodeposition Finish White
REMOVABLE 3" [76mm] LIFTING ANGLE

STRUCTURE MODIFICATIONS:

Rodent Barriers 1,3
Splice to M6 L

EQUIPMENT WEIGHT:

SHIPPING SPLIT # 1: 740.00 Lbs. (335.66 Kg.)
SHIPPING SPLIT # 2: 740.00 Lbs. (335.66 Kg.)
SHIPPING SPLIT # 3: 740.00 Lbs. (335.66 Kg.)
TOTAL LINEUP WEIGHT (APPROX): 2220.00 Lbs. (1006.99 Kg.)

PRODUCT ACCESSORIES:

Certified Test Report
Seismic Qualified IBC/ASCE7
Drip Hoods

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	1 SEPERATE VFDS
JOB LOCATION:	OTTAWA, ON	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	KP	DRAWING TYPE:	ELEVATION
ENGR:	KP		[redacted]
DATE:	DECEMBER 17, 2018		
DRAWING STATUS:	RECORD	DWG#	F41720903-001-01 PG 3 OF 3 REV A


REV	DESCRIPTION	BY	DATE								
A	RELEASE TO PRODUCTION	DU	12/19/2018	–	----	--	--/--/--	–	----	--	--/--/--


REQUIREMENTS FOR SEISMIC RATING

ANCHORING CONDITIONS:

To Maintain Seismic Qualifications, Equipment Must Be Installed Per Installation Manual 80459–641–XX And Per Any Seismic Anchoring Details Provided By Others. Do Not Install Equipment Before Approved Seismic Anchoring Details Have Been Obtained And Site Preparations Have Been Made In Accordance With The Approved Seismic Anchoring Details. All Post–Installed Anchors Shall Be Approved For Seismic Loads.

Consideration Must Be Made For Conduit Entry Into Each Section When Developing Mounting Pad Reinforcement Locations. See Conduit Entry Details For Dimensional Information.





Each MCC Section Must Be Anchored At Four Locations (See Above Details). Anchor Bolt Mounting Points Are .88/[22] Diameter Holes Located 1.50/[38] Above The Base Of The MCC Section. Use Dimensions From The Anchor Detail To Determine Mounting Locations.

The Belleville Washer (Shown In Detail Above) Used For Anchoring Connections Is A Tested Component And Is Required To Maintain Position Retention Of The Equipment. The Slip Critical Connection Performance Of The Bolted Connection Was Established To The Shake Table Tested Seismic Capacity Of The Equipment As Shown On The Equipment Seismic Certificate Supplied At The Time Of Order.

CENTER OF GRAVITY:

The CG Information Provided Below Should Only Be Used For Seismic Anchoring Calculations.

Elevation Center Of Gravity: 62.00/[1575] Up From Floor Except Masterpact NW Main Use 54.00/[1372] Up From Floor

Depth Center Of Gravity: 7.50/[191] or 10.00/[254] From Rear For 15.00/[381] or 20.00/[508] Deep Sections Respectively. Consult Factory For Sections Taller Than 94.50/[2400].

Vertical Center of Gravity: Use Centerline Of Section From Left To Right


SECTION WEIGHTS:

The Weights Shown Below Should Only Be Used For Calculating Seismic Anchoring Requirements And Do Not Represent Actual Section Weights As Shipped.

1200 Lbs. (544.3 Kg.)	35.00/[889] Wide Sections
1300 Lbs. (589.7 Kg.)	20.00/[508] Wide Sections
1500 Lbs. (680.4 Kg.)	25.00/[635] And 30.00/[762] Wide Sections*
*1900 Lbs. (861.8 Kg.)	30.00/[762] Wide Section With Masterpact NW Main
2250 Lbs. (1020.6 Kg.)	50.00/[1270] Wide Section With 18 Pulse Drive
2750 Lbs. (1247.4 Kg.)	65.00/[1651] Wide Section With 18 Pulse Drive

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	1 SEPERATE VFDS
JOB LOCATION:	OTTAWA, ON	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	KP	DRAWING TYPE:	SEISMIC
ENGR:	KP		
DATE:	DECEMBER 17, 2018		
DRAWING STATUS:	RECORD	DWG#	S41720903-001-01 PG 1 OF 1 REV A


REV	DESCRIPTION	BY	DATE										
A	RELEASE TO PRODUCTION	DU	12/19/2018	–	----	--	--/--/--	–	----	--	--/--/--		



JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	1 SEPERATE VFDS
JOB LOCATION:	OTTAWA, ON	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	KP	DRAWING TYPE:	ONE LINE DIAGRAM
ENGR:	KP		[redacted]
DATE:	DECEMBER 17, 2018		
DRAWING STATUS:	RECORD	DWG#	041720903-001-01 PG 1 OF 1 REV A

| REV | DESCRIPTION | BY | DATE | | |

REV	DESCRIPTION	BY	DATE
A	RELEASE TO PRODUCTION	DU	12/19/2018



JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	1 SEPERATE VFDS
JOB LOCATION:	OTTAWA, ON	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	KP	DRAWING TYPE:	ELEMENTARY
ENGR:	KP		
DATE:	DECEMBER 17, 2018	DWG#	E41720903-001-01
DRAWING STATUS:	APPROVAL	PG1 OF2	REV A

DRIVE CATALOG NUMBER ATV630D37Y6
HEATSHRINK WIRE MARKERS

REV	DESCRIPTION	BY	DATE	–	----	--	--/--/--
A	RELEASE TO PRODUCTION	DU	12/19/2018	–	----	--	--/--/--

ATV630 FACTORY CONFIGURATION WITH BYPASS – HEAVY DUTY – HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	----	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	----	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	----	MAX FREQUENCY	60	TFR	60
1	S.START	----	LOW SPEED	3	LSP	3
1	S.START	----	ACCELERATION	10	ACC	10
1	S.START	----	DECELERATION	10	DEC	10
5.2	---	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.2	---	DUAL RATING	DUAL RATING	HEAVY DUTY	DRT	HIGH
5.5	---	----	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.5	---	----	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.5	---	----	2–WIRE TYPE	LEVEL	TCT	LEL
5.5	---	----	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.5	---	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.5	---	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.5	---	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.5	---	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.11	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.11	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.11	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.11	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.11	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.12	---	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES
5.12	---	OUTPUT PHASE LOSS	OUTPUT PHASE LOSS	FUNCTION INACTIVE	OPL	FI

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	1 SEPERATE VFDS
JOB LOCATION:	OTTAWA, ON	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	KP	DRAWING TYPE:	ELEMENTARY
ENGR:	KP		SQUARE D by Schneider Electric
DATE:	DECEMBER 17, 2018		
DRAWING STATUS:	APPROVAL	DWG# E41720903-001-01	PG 2 OF 2 REV A

Date: Jan 21, 2019

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jan 21, 2019

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-14
PO-Guillevin-Quote-1135711

Attached are the following items:

- [ ] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 05 21 Wires and Cables (0-1000 V)-Fire Alarm Cable

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-014

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2019-01-24
BY Konrad Goluch

Minimum wire size as spec 26 05 21 2.4.2.4

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

Deca Cables Inc.
150 North Murray Street
P.O. Box 777
Trenton, Ontario K8V 5W6
Canada

Website: www.decacables.com
Telephone: (613) 392-3585
Facsimile: (613) 392-7908
Email: sales@decacables.com

ISO 9001:2008

PRODUCT DATA SHEET

Part No: 32-1805

CONSTRUCTION SPECIFICATIONS

Description	FIRE ALARM 5C 18 AWG UNSH AIA 300V
Conductor	18 AWG Solid Bare Copper
Conductor Diameter	0.0403"
Insulation Type	Semi Rigid PVC
Insulation Thickness	.015"
Conductor Identification	Black, Red, Green, Blue, Brown
Cable Assembly	Conductors are cabled together. A PVC jacket is applied over the cabled assembly. An aluminum armour is applied over the inner jacket. An outer PVC jacket is applied over the aluminum armour.
Ripcord	Polyester Ripcord included under the inner jacket
Inner Jacket	0.020" (minimum average), Flame Retardant Red PVC
Armour Type	Interlocked Aluminum Armour
Outer Jacket	0.045" (minimum average), Flame Retardant Red PVC
Overall Cable Diameter	0.509"
Jacket Print	"DECAGUARD" 5C18AWG 105C CSA FAS105 FT4 300V AIA SUN RES LL81646 ---- ROHS work order #, month, year, metre markings (every 1 metre)

ELECTRICALS

Voltage	300V	
Conductor Resistance	6.39	Ohms/Mft @20C

CERTIFICATIONS AND PHYSICAL PROPERTIES

CSA Certified	*CSA C22.2 No.208 Fire Alarm and Signal Cable	
Flame Test Rating	CSA FT4	
Temperature Rating	105C	
ROHS	Compliant	
Cable Weight	184	kg/km
Copper Content	37	kg/km
Max Pull Tension	41	kgs
Min Bending Radius	6.25	inches (installed)
Max Cable Length	8475	metres

Date: June 4, 2019

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 04, 2019

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-15R2 SU-ELE15R2
PO-Frontier Power

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [x] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 32 14 Power Generation Diesel-Silencer

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-15R2 (Generator Silencer)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [x] Mechanical
- [ ] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.


Stantec

- [x] REVIEWED
- [ ] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED


DATE 2019-06-05
BY Brendan Zrum, P.Eng


Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.




TOP VIEW





SIDE VIEW



OUTLET END VIEW

P/O # Quote#19710

Standard Specifications

- Material: CS-A36 (44W)
- Uninsulated
- Tolerance— 1/8"; ∠ ±2°
- Finish:
  1,100 F High Heat Black Paint
- Tolerance: ±1/8"
- Weight: 85 lbs

All dimensions are in inches (") unless otherwise stated. Do not scale.

Title: 5" Cylindrical Silencer -Standard- Critical Grade (25-30 dBA) Side In-End Out-Carbon Steel	Dwg.Nbr	Revision	Plot Scale	NTS
	SM2-5	0	Format	A
			Date	05/22/2019 09:01:39
Client/Project: Frontier Power WWTP W.O # Quote#19710				

SMS SILENCERS RESERVES THE PROPIETARY RIGHTS TO THIS DRAWING AND THE DATA SHOWN THEREON AND IS SUBMITTED IN CONFIDENCE ONLY. SAID DRAWING AND/OR DATA ARE NOT TO BE USED OR REPRODUCED FOR ANY PURPOSE WITHOUT WRITTEN CONSENT OF SMS SILENCERS

www.smssilencers.com
sales@smssilencers.com
Tel: 905-459-1512
Fax: 905-459-3138
15 Bramalea Raod Unit#7
Brampton, ON
L6T 2W4

SMS SILENCERS INC.

V.1.0 Dec 10 2016

Project ID# 26110-Brent | Dwg ID# 26111

SMS SILENCERS INC.

SMS Silencers Inc.
7-15 Bramalea Rd.
Brampton, ON, Canada L6T 2W4

Toll Free 800 459 1512
Phone 905 459 1512
Fax 905 459 3138

Company Info

Frontier Power Products Ltd.
7983 Progress Way
Delta, BC
V4G 1A3, Canada

Prepared by: Brent MacMillan

Contact info

Will Osburn
wosburn@frontierpower.com

WWTP

Genset Manufacturer:	Caterpillar
Genset Model:	G3306TA - 220bhp
Engine Manufacturer:	Caterpillar
Engine Model:	G3306TA

Engine Information

Exhaust Flow:	967.00 ACFM	**Max BP:**	27.00 in wg	**Temp:**	1000.00 Fahrenheit	**KW:**	165
Number of Outlets:	1	**Outlet Diameter:**	5.00	**Flex Length:**	18.00	**Fuel Type:**	Other

Engine Octave Band

Engine Exhaust: Sound Pressure Level (LP) measured @ 1.00 m in dB

60 Hz	125 Hz	250 Hz	500 Hz	1 KHz	2 KHz	4 KHz	8 KHz	dB	dBA
106.00	108.00	99.00	98.00	97.00	96.00	95.00	95.00	111.22	103.51

Catalytic Converter IL.

No Catalytic Converter sound data is given.

Exhaust Back Pressure Detail

No User Selection for Exhaust data is made.

Silencer(s) Sizing Result

Silencer(s) Results below is based on user Selection of One Silencer using SMS Default dBA correction & Near Field Distance attenuation:

Recommended Minimum Outlet Size 4"

Silencer Part #	Description	Outlet Size	Back Pressure
SM2-5-SIEO	5" Critical Grade Cylindrical Silencer (25-30 dBA)	5 in	5.13 in wg
Silencer(s)			**5.13 in wg**
Qty : 1 Flex Dia : 5.00 Flex Length 18.00"		Flex Connector :	0.20 in wg

Exhaust Velocity = 7,095.00 ft/min OR 36 m/s

Octave Band

Octave Band	63 Hz	125 Hz	250 Hz	500 Hz	1 kHz	2 kHz	4 kHz	8 kHz	dB	dBA
Engine SPL @ 1 m	106.00	108.00	99.00	98.00	97.00	96.00	95.00	95.00	111.22	103.51
Silencer #1 : SM2 dB @ 1 m	16.00	27.00	30.00	29.00	25.00	21.00	20.00	20.00	34.74	30.85
Catalytic Converter IL.	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00
dBA reduction correction	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00		
Resulting SPL @ 1 m	90.00	81.00	69.00	69.00	72.00	75.00	75.00	75.00	90.98	81.21
Distance Attenuation dB	10.14	10.14	10.14	10.14	10.14	10.14	10.14	10.14		
Resulting SPL @7.00 m	79.86	70.86	58.86	58.86	61.86	64.86	64.86	64.86	80.84	71.07

Calculated noise level is based on free field conditions.
No site conditions and no calculation safety factors are taken into consideration.
Typical resulting noise tolerance is +/- 5dBA. No noise result guarantees are implied.

Date: June 11, 2019

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 11, 2019

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

SE-16R2
PO-Guillevin-P19-078

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [x] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 12 17 Distribution Transformer

Provide a shop drawing for the 45kVA transformer

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-016-R2

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2019-06-12
BY Jamie McLeish

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

Hammond Power Solutions Inc.

NO.	DATE	BY	REVISION

TITLE: 3PH DISTRIBUTION TRANSFORMER NAMEPLATE INFORMATION

DES: PPICASSI
DATE: 19/05/24
SCALE: NTS

SHEET 1 OF 3

EDB SK3A0112PB4KB

HPS Sentinel ® K

Energy Efficient Distribution Transformer

Transformateur de Distribution à Bon Rendement Énergétique

Hammond Power Solutions
Guelph, ONT
Compton, CA
Baraboo, WI
Monterrey, MX

Part No. SK3A0112PB4KB


LR 3902

DRY TYPE TRANSFORMER
77US
E112313
LISTED

ALSO VERIFIED IN ACCORDANCE TO ENERGY STANDARD C802.2-12

Cust. Ref. / Ref. du Client		Serial No. / No. de Serie	
Phase	3	HV/HT	600V 108.3A
Type	K	BIL	10 kV
Cooling / Refroidissement	ANN	Term / Bornes	H1 H2 H3
kVA	112.5	LV/BT	208Y/120V 312A
Temp. Rise / Echauffement	80 °C	BIL	10 kV
Temp Class / Classe Temp	220 °C	Term / Bornes	X0 X1 X2 X3
Winding / Enroulement	CU	Energy Regulations	DOE 10 CFR PART 431:2016
Frequency / Frequence Hz	60	Reglements de Energetique	CEE ACT SOR/2018-201
Impedance % @ 100 °C	3.4	Suitable for non-sinusoidal current load with K-factor not to exceed / Convient à des courants non-sinusoïdaux avec facteur K n'excédant pas	4
Encl Type / Type De Coffrage	3R		
Wt LBS / Poids en lbs	950		

VOLTS	CURRENT / COURANT	% RATED VOLTAGE / % TENSION NOMINALE	CONNECTION EACH PHASE / CONNEXION PAR PHASE
630	103.1	105	1
615	105.6	102.5	2
600	108.3	100	3
585	111	97.5	4
570	114	95	5
555	117	92.5	6
540	120	90	7




SPACINGS BETWEEN ANY VENTILATED ENCLOSURE PANEL AND ANY ADJACENT WALL SHALL BE A MINIMUM OF 5 INCHES EXCEPT WHEN WALL MOUNTED USING APPROVED WALL MOUNTING KIT
ELECTROSTATIC SHIELD

SEISMIC QUALIFICATIONS, OSP-0136-10
AS FLOOR MOUNT ONLY
IBC 2012/ASCE 7-10
SDS<=2.0g Z/h=1 Ip=1.5


dp000746

0.0 ppicassinos 2019/05/24 09:34

FRONT VIEW



SIDE VIEW



All Dimensions in inches

ENCLOSURE COLOR :ANSI 61 GREY – OUTDOOR

HV TERMINAL DETAIL

MECHANICAL TYPE LUGS INCLUDED
SUITABLE FOR 250MCM–6 CU/AL
CONDUCTORS
1 CONDUCTOR PER PHASE

LV TERMINAL DETAIL

MECHANICAL TYPE LUGS INCLUDED
SUITABLE FOR 350MCM–6 CU/AL
CONDUCTORS
2 CONDUCTORS PER PHASE

CUSTOMER NOTES:

– HV TERMINATED AT TOP FRONT
– LV TERMINATED AT BOTTOM FRONT
200% RATED NEUTRAL X0 HAS QTY 2 LUGS

Hammond Power Solutions Inc.

TITLE: 3PH DISTRIBUTION TRANSFORMER

NO.	DATE	BY	REVISION


DES: PPICASSI
DATE: 19/05/24
SCALE: NTS

SHEET 2 OF 3

EDB SK3A0112PB4KB

0.0 ppicassinos 2019/05/24 09:34

ENCLOSURE BOTTOM VIEW



NOTE:
WHEN BOTTOM CABLE ENTRY IS OPTED, THE SPACE USED FOR CONDUITS IN THE FRONT OF THE TRANSFORMER SHOULD NOT OBSTRUCT MORE THAN 50% OF THE FRONT AIR INTAKE AREA DEFINED BETWEEN THE BOTTOM PLATE AND THE SUPPORTING LEGS.
SEE MANUAL FOR ADDITIONAL INFORMATION

Hammond Power Solutions Inc.

TITLE: 3PH DISTRIBUTION TRANSFORMER
ENCLOSURE BOTTOM VIEW

NO.	DATE	BY	REVISION

DES: PPICASSI
DATE: 19/05/24
SCALE: NTS

SHEET 3 OF 3

EDB SK3A0112PB4KB

0.0 ppicassinos 2019/05/24 09:34

ACCESSORIES (for transformers listed in sections 3, 4, 7, 10 and 11)

ANTI-VIBRATION PAD AND VIBRATION ISOLATOR KITS

All standard transformers come with installed internal vibration absorbing pads to minimize noise during operation. Optional external "anti-vibration" pad and "vibration isolator" (for higher noise dampening) kits can be used to reduce operating noise even further. All are resistant to industrial contaminants like oils, acids and alkalies.

ANTI-VIBRATION PAD KITS


Part No.	Case Style	Description
P1	NH Series	Set of four (4) rubber anti-vibration pads which replace the standard steel enclosure washers.
P2	NJ Series	



All Anti-Vibration Pad kits and Vibration Isolator kits contain a set of four (4) pads or isolators. Therefore only one kit is required per transformer.

VIBRATION ISOLATOR KITS

Part No.	Transformer Weight (Lb)	Description
NMP1	Up to 340 lbs	Set of four (4) molded neoprene and steel plate assemblies that virtually eliminate vibration noise between the transformer and the mounting surface.
NMP2	341 to 680 lbs	
NMP3	681 to 1040 lbs	
NMP4	1041 to 1740 lbs	
NMP5	1741 to 2330 lbs	
NMP6	2331 to 3450 lbs	
NMP7	3451 to 4690 lbs	



ACCESSORIES (for transformers listed in sections 8 and 10)


NQTW1 and NQTW2 Wall Mounting Kits

The **NQTW1 and NQTW2** wall mounting kits are specifically designed for HPS commercial or industrial encapsulated (potted) distribution transformer units up to a maximum of 45kVA or 800 pounds (363 kg). These mounting kits are designed for encapsulated (potted) units only, no drip plate is included/required. Please contact HPS customer service if you have any questions.

Note: Always measure and secure mounting brackets to the wall surface first, then lift the transformer (using appropriate lifting equipment) onto the brackets and attach using minimum Grade 8 hardware.

Enclosure Case Style	Mounting Type	Wall Mounting Kit Part Number
NQ0-NQ8	Wall	**Included**
NQS10	Wall or Floor	**NQTW2**
NQT3-NQT6	Wall	**Included**
NQT7-NQT8	Wall or Floor	**NQTW1**
NQT9A	Floor	**N/A**
NQT9*	Wall or Floor	**NQTW2**

*Applies to HPS Fortress line only.



© Hammond Power Solutions Inc.
Data subject to change without notice.

Date: May 10, 2019

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Mai 13, 2019

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

SE-17
P19-078-Guillevin

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Distribution-Switchboard/Panelboards

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-016 rev 1

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2019-05-14
BY Konrad Goluch

SPD to be connected to the panel busbar using circuit breaker size as indicated on drawings.
Bus bar bigger than specified - not action required.

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

IQALUIT WASTE WATER TREATMENT UPGRADE

Approval Drawing Package

Factory Order #: 41753775

05/09/2019

Distributor:
Guillevin

Contractor/Installer:
Artic Electric

Chris Saucier
Sales Representative

Phillip Hogel
Project Manager
North American Operating Division
613-688-4117
phillip.hogel@se.com

Life Is On Schneider Electric

Submittal Comments

Date: 05/09/2019

Job Name: IQALUIT WASTE WATER TREATMENT UPGRADE

Factory Order #: 41753775

Contractor Name: ARCTIC ELECTRIC

☐ **Approval**
> Release all manufacture
No re-submittal required

☐ **Rejected**
> No release
Re-submit all

☐ **Approved as Noted**
> Release all for manufacture.
Make necessary changes, show
Changes on construction Drawings

☐ **Partial Approval**
Revise and Resubmit
> Release approved sections for manufacture
Re-submit rejected section

The following information is pertinent with the return of this submittal. Please initial the applicable items that you have reviewed and have determined to be correct.

_____ > Lug sizes

_____ > Top or bottom entry for all equipment

_____ > Shipping splits

_____ > Nameplate information

_____ > Orientation of breakers

_____ > Wire sizes

_____ > Amperages of all bus and breakers

_____ > Surface or flush for panels

_____ > Size of all equipment

_____ > AIC ratings

_____ > Copper or aluminum bus

Customer Comments/Rejected Items:

Contractors Signature or Stamp:

_____

Schneider Electric

Approval Drawings

This Approval Drawing Package is submitted as our interpretation of the contract drawings and/or the specifications for this job.

It is the obligation of the electrical contractor and reviewing engineer to determine that the item quantities and accuracy of this submittal is correct as required for the job. Any inaccuracies or deviations must be addressed with Schneider Electric before release to manufacturing. Any releases of material to manufacturing by the above parties constitute an acceptance of the accuracy of the submittal. Any changes after release will be viewed as a change order, subject to pricing changes.

Please take the time to review this package for accuracy to prevent any after-shipment problems. This will allow the job to be shipped correctly and prevent any delay in energization.

Schneider Electric

Good day,

Schneider Electric is committed to delivering your equipment in good condition.

You are the documented receiver for the shipments on the project contained in this Approval Drawing Package.

Please be sure to receive each shipment correctly.

1: Review that material and check the quantities

2: Check for damage to any of the materials before signing the waybill.

If you see damage, or suspect there might be damage, indicate “Damaged” on the waybill. Take pictures of the damage, and contact your Schneider Electric representative for instructions.

- If you sign the waybill without noting the damage, you are accepting the shipment as complete and undamaged.
- Any damage reported after the waybill is signed will be your responsibility.

If you find concealed damage within 24 hours of receiving the shipment, call the carrier.

- Report the damage, and ask for an inspection by the carrier.

Thank you for working with Schneider Electric to ensure you have completed and undamaged shipments.

Schneider Electric

TABLE OF CONTENTS

SWITCHBOARD

BILL OF MATERIALS AND DRAWINGS

MDP-1

LITERATURE

Power-Style QED-2 Switchboard Brochure

Internal Modular SPD - Brochure

PowerLogic PM8000 Series Intermediate Metering Technical Data Sheet

PK Circuit Breaker Information

Micrologic Trip Units for PowerPact Circuit Breakers Brochure

PANELBOARDS

BILL OF MATERIALS AND DRAWINGS


LITERATURE

NQ Panelboard Handout


NQ SurgeLoc Internally Mounted SPDs

SERVICES

BILL OF MATERIALS



SWITCHBOARD



BILL OF MATERIALS AND DRAWINGS

Q2C Number: 41753775	**Quote Number:** 2	**Revision Number:** 1
Project Name: IQALUIT WASTE WATER TREATMENT UPGR		**Quote Name:**

Item No.	Qty.	Catalog Number / Details

SWITCHBOARD

001-00 1

Designation: MDP-1
Square D Custom Swbd
QED-2 Switchboard

Square D Custom Swbd
Designed and Tested in accordance with:
CSA C22.2 NO. 31
System Voltage - 600Y/347V 3Ph 4W 60Hz
System Ampacity - 800A
Source Description - Single Main
Bussing - Silver Plated Copper
Neutral Bus - 100%
Max Available Fault Current (RMS) - 22kA
Enclosure - Type 2
Drip Hood(s)
Accessibility: Front and Rear
Exterior Paint Color - ANSI 49
Ground Lug provided for each device
Copper Ground Bus
Certified Test Report Required
Seismic Qualified

Dimensions
---
1 - 24" Wide Section(s)
2 - 36" Wide Section(s)
3 - 24" Deep Enclosure(s)
Dimensions: 96.00" W X 24" Max D X 91.5" H
Approximate Weight: 2071.00 lbs / 939.41 kgs

Incoming Requirements

Suitable As Service Entrance
Entry Point: Left of Lineup, Through the Bottom
Connection Type: Cable in Bussed Auxiliary
SPD with Surge Rating 240kA
SPD Dry Contacts
Includes Surge Counter
Utility C/T Comp. per: IQALUIT
Provision for Utility CT's/PT's,
C/T Type - MV-7
Power Meter - PM8244
3 CTs PM8244 w/ Display - 3 phase 4 wire wye 800A

Mains
---
1 - 800AS/400AT 600V 100% Rated 50 kA 3 Pole UL, Fixed Mounted Electronic Trip Circuit Breaker: Type PK
Ammeter Trip Unit, Long Time, Short Time, Instantaneous
Padlock Attachment

Feeders
---
2 - 100AT 600V 80% Rated 25 kA 3 Pole UL, Group Mounted Thermal Magnetic Circuit

Item No.	Qty.	Catalog Number / Details
		Breaker: Type BJ 1 - 150AT 600V 80% Rated 25 kA 3 Pole UL, Group Mounted Thermal Magnetic Circuit Breaker: Type HJ 2 - 200AT 600V 80% Rated 25 kA 3 Pole UL, Group Mounted Thermal Magnetic Circuit Breaker: Type JJ 1 - 250AT 600V 80% Rated 25 kA 3 Pole UL, Group Mounted Thermal Magnetic Circuit Breaker: Type JJ 1 - 60AT 600V 80% Rated 25 kA 3 Pole UL, Group Mounted Thermal Magnetic Circuit Breaker: Type BJ Common Feeder Features: Padlock Attachment

SQUARE D
by Schneider Electric


Job Name:	IQALUIT WASTE WATER TREATMENT UPGR	Square D Quotation #:	41753775
Job Location:	OTTAWA, ON	Quotation Revision #:	
		Sales Contact:	Michael Childs
		Sales Contact Location:	806
Purchaser:	92941–GUILLEVIN INT'L INC. (V4990)	Customer:	ARCTIC ELECTRIC
Purchaser PO #:	2010–ROV975139D	Customer PO #:	
User:		Architect:	
User Location:		Cons. Engineer:	
Drawing Status:	APPROVAL		

TABLE OF CONTENTS

SQUARE D FACTORY ORDER NUMBER: 41753775–001

Equipment Designation	Equipment Type	Drawing Type	Drawing Number	Page	Revision Level
MDP–1	QED–2 SWITCHBOARD	ELEVATION VIEW	F41753775–001–01	1	–
		SIDE, TOP VIEW & FLOOR PLAN	F41753775–001–01	2	–
		CENTER OF GRAVITY	F41753775–001–01	3	–
		ONE LINE	041753775–001–01	1	–
		SCHEDULE	041753775–001–01	2	–
		ELEMENTARY DIAGRAMS	E41753775–001–03	1	–
			E41753775–001–09	1	–
		ISOMETRIC VIEW/COMPARTMENT DESIGNATION	I41753775–001–01	1	–

REV	DESCRIPTION	BY	DATE								
–	----	--	--/--/--	–	----	--	--/--/--	–	----	--	--/--/--
				–	----	--	--/--/--	–	----	--	--/--/--



SWITCHBOARD GENERAL NOTES

PRODUCT DESCRIPTION & RATINGS

Power System Data

600Y/347V 3Ph 4W 60Hz / 3 Phase Wye
Solidly Grounded
System Short Circuit Current Rating: 22kA RMS
Incoming Section 1 Cable Through the Bottom Left of Lineup

Bus System Data

800A Silver Plated Copper Main Bus
(1) .25x.875 IN/6x22 mm Cu Ground Bus

Enclosure Data

Type 2 Free Standing
Driphoods
Exterior Paint Color: ANSI 49
Front & Rear Accessibility Required
Handling: Rollers & Lifting Assemblies
Utility Sealing hardware installed on the line side

Estimated Shipping Weight

Shipping Split 1 559.00 lbs / 253.56 kgs
Shipping Split 2 1112.80 lbs / 504.76 kgs
Shipping Split 3 1020.50 lbs / 462.89 kgs
Complete Lineup 2692.30 lbs / 1221.21 kgs

Code Standards

CSA C22.2 NO. 31
Suitable for Service Entrance
Not Suitable for Mounting on Combustible Floor

Rating Nameplates

ST1-Section Bus 800A
ST2-Section Bus 800A
ST3-Section Bus 800A

PRODUCT INFORMATION

Wiring

All Gray SIS Wire and Min Size #14 Unless Otherwise Noted, and #12 Ground Wire.
NOTE: (90 Deg. C) insulated conductors must be sized per the (75 Deg. C) column of the CE Code Tables.
Except the supply cables entering Section 1, (Incoming Wireway) may be sized per the (90 Deg. C) column of the CE Code Tables.

Instruction Bulletins

Reference 80043-055 For Handling, Installation, Anchoring, Inspection And Maintenance Information

Product Accessories/Options

Certified Test Report
Seismic Qualified


DUAL DIMENSIONS: INCHES / MILLIMETERS

41753775001001


JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	MDP-1
JOB LOCATION:	OTTAWA ON	EQUIPMENT TYPE:	QED-2 SWITCHBOARD
DRAWN BY:	RANJITHA B	DRAWING TYPE:	ELEVATION VIEW
ENGR:	JOSEPH HADCHITI ENG.		
DATE:	MAY 03, 2019		
DRAWING STATUS:	APPROVAL	DWG#	F41753775-001-01

PG 1 OF 3 | REV –


REV	DESCRIPTION	BY	DATE	–	----	--	--/--/--	–	----	--	--/--/--
–	----	--	--/--/--	–	----	--	--/--/--	–	----	--	--/--/--



TOP VIEW – FRONT



LEFT SIDE VIEW



FLOOR PLAN – FRONT

NOTE: ALL DEVICES REQUIRING DRILLING OR INSERTION IN MOUNTING PAD SUCH AS CONDUIT, ANCHORING STUDS, SLEEVE INSERTS, ETC. SHOULD BE INSTALLED BEFORE SETTING EQUIPMENT IN PLACE.

DUAL DIMENSIONS: INCHES MILLIMETERS

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	MDP-1
JOB LOCATION:	OTTAWA ON	EQUIPMENT TYPE:	QED-2 SWITCHBOARD
DRAWN BY:	RANJITHA B	DRAWING TYPE:	SIDE, TOP VIEW & FLOOR PLAN
ENGR:	JOSEPH HADCHITI ENG.		
DATE:	MAY 03, 2019		
DRAWING STATUS:	APPROVAL	DWG#	F41753775-001-01

PG 2 OF 3 REV –

41753775001001


REV	DESCRIPTION	BY	DATE	–	----	--	--/--/--	–	----	--	--/--/--
–	----	--	--/--/--	–	----	--	--/--/--	–	----	--	--/--/--


REQUIREMENTS FOR SEISMIC RATING

ANCHORING CONDITIONS:

To Maintain Seismic Qualifications, Equipment Must Be Installed Per Manual (See General Notes) And Per Any Seismic Anchoring Details Provided By Others. Do Not Install Equipment Before Approved Seismic Anchoring Details Have Been Obtained And Site Prepararations Have Been Made In Accordance With The Approved Seismic Anchoring Details. All Post–Installed Anchors Shall Be Approved For Seismic Loads.

Consideration Must Be Made For Conduit Entry Into Each Section When Developing Mounting Pad Reinforcement Locations. See Conduit Entry Details (Floor Plan) For Dimensional Information.





MOUNTING DETAILS

Each Section Must Be Anchored At All Locations (Refer To Floor Plan And Mounting Detail Above). Anchor Bolt Mounting Points Are .75/[19] Digmeter Holes Located 1.50/[38] Or 3.00/[76] Above The Base of the Section. Use Dimensions From The Floor Plan To Determine Mounting Locations.

The Belleville Washer (Shown In Detail Above) Used For Anchoring Connections Is A Tested Component And Is Required To Maintain Position Retention Of The Equipment. The Slip Critical Connection Performance Of The Bolted Connection Was Established To The Shake Table Tested Seismic Capacity Of The Equipment As Shown On The Equipment Seismic Certificate Supplied At The Time Of Order.

CENTER OF GRAVITY CALCULATIONS:

Elevation Center Of Gravity: 55 in. (1387.00mm) Up From Floor
Vertical Center Of Gravity: Use Centerline Of Section From Left To Right
Depth Center Of Gravity: Use CenterLine Of The Section From Front To Rear

SECTION WEIGHT:

The Weights Given Below Are The Maximum For Each Section And Should Be Used For Calculating Seismic Anchoring Requirements


Section 1 559.00 lbs / 253.56 kgs
Section 2 1112.80 lbs / 504.76 kgs
Section 3 1020.50 lbs / 462.89 kgs

DUAL DIMENSIONS: INCHES MILLIMETERS

41753775001001

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	MDP–1
JOB LOCATION:	OTTAWA ON	EQUIPMENT TYPE:	QED–2 SWITCHBOARD
DRAWN BY:	RANJITHA B	DRAWING TYPE:	CENTER OF GRAVITY
ENGR:	JOSEPH HADCHITI ENG.		
DATE:	MAY 03, 2019		
DRAWING STATUS:	APPROVAL	DWG#	F41753775–001–01

REV	DESCRIPTION	BY	DATE								
–	----	--	--/--/--	–	----	--	--/--/--	–	----	--	--/--/--
				–	----	--	--/--/--	–	----	--	--/--/--



JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	MDP-1
JOB LOCATION:	OTTAWA ON	EQUIPMENT TYPE:	QED-2 SWITCHBOARD
DRAWN BY:	RANJITHA B	DRAWING TYPE:	ONE LINE
ENGR:	JOSEPH HADCHITI ENG.		
DATE:	MAY 03, 2019		
DRAWING STATUS:	APPROVAL	DWG#	041753775-001-01

PG 1 OF 2 | REV –

41753775001001

REV	DESCRIPTION	BY	DATE	–	----	--	--/--/--	–	----	--	--/--/--
–	----	--	--/--/--	–	----	--	--/--/--	–	----	--	--/--/--

POWER STYLE QED–2 SWITCHBOARD

SECT NO	CKT NO	GMD HEIGHT	DEVICE/FRAME RATING	TRIP AMP	FUSE/ TRIP	#P	DESIGNATION	N/P	LUG/WIRE INFORMATION				ACCESSORIES / NOTES
									QTY	PHASE WIRE RANGE	QTY	NEUT WIRE RANGE	
1	–	–	Incoming Connection	–	–	–	–	–	3	3/0 – 750 kcmil	3	3/0 – 750 kcmil	
2	M1	–	PK800A Plug A 100%	400A	A–LSI	3P	400A MAIN	No	–	–	–	–	PM,PLA
2	UCT	–	800A	–	–	–	IQALUIT	No	–	–	–	–	
3	–	13.5 in	240kA SPD	–	–	–	–	–	–	–	–	–	SPD
3	1	4.5 in	BJ	100A	–	3P	100A PNL 6B	No	1	#14 – 1/0 AWG	1	#14 – 1/0 AWG	PLA
3	2	4.5 in	HJ	150A	–	3P	150A TX–1	No	1	#6 – 3/0 AWG	1	#6 – 3/0 AWG	PLA
3	3	4.5 in	JJ	200A	–	3P	200A SPARE	No	1	3/0 – 350 kcmil	1	3/0 – 350kcmil	PLA
3	4	4.5 in	JJ	250A	–	3P	250A MCC–1	No	1	3/0 – 350 kcmil	1	3/0 – 350kcmil	PLA
3	5	4.5 in	JJ	200A	–	3P	200A TX–3	No	1	3/0 – 350 kcmil	1	3/0 – 350kcmil	PLA
3	6	4.5 in	BJ	100A	–	3P	100A SPARE	No	1	#14 – 1/0 AWG	1	#14 – 1/0 AWG	PLA
3	7	4.5 in	BJ	60A	–	3P	60A MCC–2	No	1	#14 – 1/0 AWG	1	#14 – 1/0 AWG	PLA


LEGEND	
PLA	Padlock Attachment–Fixed
PM	Power Meter PM8244
SPD	Surge Protection Device

41753775001001

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	MDP–1
JOB LOCATION:	OTTAWA ON	EQUIPMENT TYPE:	QED–2 SWITCHBOARD
DRAWN BY:	RANJITHA B	DRAWING TYPE:	SCHEDULE
ENGR:	JOSEPH HADCHITI ENG.		[redacted]
DATE:	MAY 03, 2019		
DRAWING STATUS:	APPROVAL	DWG#	041753775–001–01

PG 2 OF 2 | REV –

REV	DESCRIPTION	BY	DATE
–	----	--	--/--/--



MAIN METERING


NOTES:
1. USE 14 GAUGE WIRE MINIMUM, UNLESS OTHERWISE NOTED. USE 12 GAUGE GROUND WIRE FOR CANADIAN ORDERS.
2. CONTROL POWER CAN BE DRAWN FROM FUSED VOLTAGE INPUTS ONLY WHEN LINE-TO-NEUTRAL VOLTAGE IS BELOW 415V AC, OR SEPARATELY DERIVED 120V CONTROL POWER ALSO ACCEPTABLE.
3. USE DISPLAY CABLE SUPPLIED WITH POWER METER.
4. FOR ADDITIONAL INFORMATION AND COMMUNICATION WIRING SEE POWERLOGIC POWER METER SERIES 8000 INSTRUCTION BULLETIN.
5. MULTIPLE METERS MAY BE FED BY SAME DISCONNECT. INDIVIDUAL FUSING IS REQUIRED.

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	MDP-1
JOB LOCATION:	OTTAWA ON	EQUIPMENT TYPE:	QED-2 SWITCHBOARD
DRAWN BY:	RANJITHA B	DRAWING TYPE:	ELEMENTARY DIAGRAMS
ENGR:	JOSEPH HADCHITI ENG.		[redacted]
DATE:	MAY 03, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41753775-001-03	PG 1 OF 1 REV –

41753775001000 1

REV	DESCRIPTION	BY	DATE	–	----	--	--/--	–	----	--	--/--
–	----	--	--/--	–	----	--	--/--	–	----	--	--/--

I–LINE INTERIOR PANEL



NOTES:

1. DRY CONTACTS FOR REMOTE MONITOR, ETC. LOCATED ON REAR OF DISPLAY.
2. PATCH CABLES MUST BE PROTECTED WHERE THEY CROSS THE HINGE SIDE DOOR FLANGE FROM THE DISPLAY DOOR TO INSTRUMENT COMPARTMENT. PATCH CABLES MUST BE KEPT SEPARATED FROM POWER WIRING.
3. CABLES MUST BE AS SHORT AS POSSIBLE WITH A MINIMUM NUMBER OF LARGE RADIUS BENDS. MAXIMUM LENGTH OF CABLE FROM THE BUS TAPS TO THE DISCONNECT SHALL NOT EXCEED 8 FEET. ALL CONDUCTORS INCLUDING PHASES, NEUTRAL, & GROUND MUST BE TWISTED TOGETHER 1 TIME EVERY 2 FEET FOR AS LONG AS POSSIBLE ALONG THEIR ROUTING WITHIN THE SWITCHBOARD. MAXIMUM NUMBER OF BENDS SHALL NOT EXCEED 4 AND MINIMUM BEND RADIUS SHALL BE 3 INCHES. CABLES MUST BE SECURELY FASTENED THROUGHOUT THEIR LENGTH. ROUTE CABLES OUT HOLE IN INSTRUMENT COMPARTMENT IF BUS TAPS ARE AT BOTTOM.
4. FOR EQUIPMENT BUILT TO ANSI C37.20.1 OR CSA C22.2 No. 31–M89, SINGLE CONDUCTOR CABLE MAY BE TYPE SIS AND COLOR CODES MAY BE DISREGARDED FOR SINGLE CONDUCTORS.
5. CONNECT THE SPD NEUTRAL LUG TO THE GROUND BUS WHEN THE SYSTEM IS 3 PHASE, 4 WIRE AND THE NEUTRAL BUS IS NOT PRESENT WITHIN THE EQUIPMENT.
6. LEGACY–WHEN THE SPD IS MOUNTED IN A 19.5" METERING COMPARTMENT, CONNECT THE GROUND WIRE TO THE GROUND BUS EXTENSION ASSEMBLY THAT IS MOUNTED ON THE RIGHT SIDE OF THE SECTION.
7. SERIES 2–ROUTE NEUTRAL AND GROUND CABLE OUT THE CLOSEST GROMMET. LEAVE ADEQUATE SLACK IN THE WIRING TO ALLOW THE TVSS UNIT TO PULL FORWARD.


SURGE PROTECTIVE DEVICE (SPD)

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	MDP–1
JOB LOCATION:	OTTAWA ON	EQUIPMENT TYPE:	QED–2 SWITCHBOARD
DRAWN BY:	RANJITHA B	DRAWING TYPE:	ELEMENTARY DIAGRAMS
ENGR:	JOSEPH HADCHITI ENG.		[redacted]
DATE:	MAY 03, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41753775–001–09	PG 1 OF 1 REV –


41753775001001

REV	DESCRIPTION	BY	DATE
–	----	--	--/--/--


STANDARD LAYOUT FOR TYPICAL FOUR HIGH STACK SWITCHBOARD




STANDARD LAYOUT FOR TYPICAL MAIN/ SUBMAIN SECTION



TYPICAL I-LINE PANEL





DEVICE LOCATOR DESIGNATIONS

BPz = ANY DEVICE LOCATED ON COMPARTMENT BACK MOUNTING PANEL.
BPTz = TERMINAL BLOCK LOCATED ON COMPARTMENT BACK MOUNTING PANEL.
BKRz = CIRCUIT BREAKER.
Dz = DEVICES LOCATED ON DOOR.
Lz = ANY DEVICE LOCATED ON LEFT SIDE PANEL OF A COMPARTMENT.
LTz = TERMINAL BLOCK LOCATED ON LEFT SIDE PANEL OF A COMPARTMENT.
Rz = ANY DEVICE LOCATED ON RIGHT SIDE PANEL OF A COMPARTMENT.
RTz = TERMINAL BLOCK LOCATED ON RIGHT SIDE PANEL OF A COMPARTMENT.
XTz = TERMINAL BLOCK LOCATED ON BOTTOM PANEL OF A COMPARTMENT.
Xz = ANY DEVICE LOCATED ON BOTTOM PANEL OF A COMPARTMENT.

[XY2] SECTION/CELL LOCATION

COMPARTMENT OR CELL SUBDIVISION
1-4 = EACH COMPARTMENT OR CELL MAY BE SUBDIVIDED.

SECTION LOCATION = A,B,C,D,E.
A = TOP CELL
B = SECOND TO TOP CELL
C = SECOND TO BOTTOM CELL
D = BOTTOM CELL
E = BUS / CABLE COMPARTMENT

SECTION NUMBER
WHEN VIEWING LINE UP FROM THE FRONT, THE LEFT MOST VERTICAL SECTION IS SECTION 1.

[XY2] SECTION/CELL LOCATION BACK TO BACK

SECTION NUMBER
WHEN VIEWING LINE UP FROM THE FRONT, THE LEFT MOST VERTICAL SECTION IS SECTION 1.
F = FRONT
R = REAR

SPECIAL SPECIFIC DEVICE DESIGNATIONS

SSTz SHIPPING SPLIT TERMINAL BLOCK. — SST1 : 120Vac/Vdc, SST2 : 24Vdc, SST6 : MDGF Wiring
STz CURRENT TRANSFOMER SHORTING TERMINAL BLOCK.
xHz HEATER ELEMENTS
TCHz THERMOSTATS
GNDz SECTION GROUND BUS CONNECTION
PHTT = PHASE TAP TOP
PHTB = PHASE TAP BOTTOM
TBUS = THRU-BUS TAP

FROM/TO WIRING INFORMATION

1=BKR1-914#16,BRK1-913
- CONNECTION ON DEVICE AT OTHER END OF WIRE.
- DEVICE AT OTHER END OF WIRE
- TERMINAL NUMBER

EXPLANATION
WIRE CONNECTS TO THIS DEVICE, TERMINAL 1. THE OTHER END OF THE WIRE CONNECTS TO DEVICE "BKR1", TERMINAL "914". THE WIRE TYPE IS 16 AWG, SIS. THE WIRE ALSO CONNECTS TO DEVICE "BKR1", TERMINAL 913. WIRE TYPE OF THE SECOND CONNECTION IS TYPE IS 14 AWG, SIS.


10=[1D1]BKR2-Z1#18

EXPLANATION
WIRE CONNECTS TO THIS DEVICE, TERMINAL 10. THE OTHER END OF THE WIRE CONNECTS TO DEVICE "BKR2", IN COMPARTMENT "1D1", TERMINAL "Z1". TYPE IS 18 AWG, SIS.

WIRE AWG
IF NO WIRE SIZE IS GIVEN, WIRE IS 14 AWG, TYPE SIS.

SECTION/CELL LOCATION
IF NO SECTION/CELL LOCATION IS GIVEN, WIRE WILL STAY WITHIN THE CURRENT CELL.


TYPICAL WIRE SLEEVE MARKER
FROM [1B1]BKRA-F2+
TO [2D1]BKRD-F2+



ELEMENTARY & WIRING DIAGRAM LAYOUT INFORMATION (NOT TO SCALE)

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	MDP-1
JOB LOCATION:	OTTAWA ON	EQUIPMENT TYPE:	QED-2 SWITCHBOARD
DRAWN BY:	RANJITHA B	DRAWING TYPE:	ISOMETRIC VIEW/COMPARTMENT DESIGNATION
ENGR:	JOSEPH HADCHITI ENG.		
DATE:	MAY 03, 2019		
DRAWING STATUS:	APPROVAL	DWG# I41753775-001-01	PG 1 OF 1 REV –


41753775001000101



LITERATURE

POWER-STYLE® QED Switchboards

Setting standards for today,
building foundations for tomorrow



SQUARE D
Schneider Electric







With a tradition of distinction

SQUARE D® POWER-STYLE® Switchboards set the standard for the system solutions of today and those of tomorrow

These **quality** products are built according to your specifications in strict adherence to NEC, NEMA and UL standards at factories certified to ISO 9002 quality standards. The **versatility** in our switchboard design helps you meet and exceed today's complex electrical distribution requirements. Features include front or rear accessibility, fixed or drawout construction, and individually or group-mounted circuit breakers or fusible switches. POWER-STYLE switchboards are also designed with **durability** in mind. Sturdy frames and standard bolted base channels all contribute to durability.

Quality, versatility and durability also define our SPEED-D® ready-to-assemble switchboards. Living up to its name, the SPEED-D line offers shipment of service section switchboards that's measured in days, not weeks.

One of the most important advantages you'll see in SQUARE D switchboards is our focus on system solutions. Our switchboards are designed to maximize the capabilities of our overcurrent protection devices, metering options and other switchboard accessories.

We also offer power monitoring and communications systems as simple or complex as your application requires. You can choose to communicate with a single PC, multiple PCs or over the Internet, using our Transparent Ready™ Internet communications system. Start with a simple monitoring and communications system and expand as your power system grows.

Our focus on customer needs does not stop here. SQUARE D Services offers a complete line of solutions through our national network of service locations. We can offer comprehensive solutions related to new installation, maintenance and testing services.

With Square D/Schneider Electric you can create an efficient electrical distribution system that meets your needs today, while building a foundation for the future. This is the SQUARE D difference.

We have an efficient solution designed to meet your needs

	Commercial	Industrial
QED-S	Office buildings Strip malls Retail stores Grocery stores Nursing homes Hospitals	Automotive plants Paper mills Manufacturing facilities Refineries Textile plants Pharmaceuticals
QED-2	Office buildings Strip malls Retail stores Grocery stores Nursing homes Hospitals	Automotive plants Paper mills Manufacturing facilities Refineries Textile plants Pharmaceuticals
QED-6	Universities Public buildings Communication Centers High-rise offices Hospitals	Automotive plants Manufacturing facilities Refineries Textile plants Chemical plants Pharmaceuticals Semiconductor manufacturing


Standards

The POWER-STYLE QED switchboards in this brochure are designed, manufactured and tested to meet the latest revisions of the following appropriate standards.

UL 50	Enclosures for Electrical Equipment
UL 98	Enclosed and Deadfront Switches
UL 489	Molded Case Circuit Breakers
UL 891	Deadfront Switchboards
UL 943	Ground Fault Circuit Interrupters
UL 977	Fused Power Circuit Devices
UL 1053	Ground Fault Sensing and Relaying Equipment
NEC Article 834	Switchboards
NFPA 70	National Electrical Code® (NEC®)
ANSI/IEEE C12.1	Code for Electricity Metering
ANSI C39.1	Electrical Analog Indicating Instruments
ANSI C57.13	Instrument Transformers
NEMA AB 1	Molded Case Circuit Breakers and Molded Case Switches
NEMA PB 2	Switchboards


Federal Specifications

W-C-375B/GEN	Molded Case Circuit Breakers
W-C-870	Fuseholders
W-S-865	Enclosed Knife Switch




QED-S switchboard

Front accessible, group-mounted panels to 2,500 A



QED-2 switchboard

Individually mounted mains to 5,000 A, distribution sections to 4,000 A, group-mounted to 1,200 A



QED-6 switchboard

Individually mounted mains to 5,000 A, front and rear access with dedicated loadside cable entry

POWER-STYLE® QED-2





QED-2 combination section

POWER-STYLE QED-2 switchboards are designed to distribute electrical power and give you economies of floor space without compromising performance or versatility. They provide circuit breaker or fusible overcurrent protection for services rated to 5,000 A with a maximum voltage of 600 VAC or 250 VDC. QED-2 switchboards can be used as service entrance equipment or as distribution centers in commercial, industrial or institutional applications. For additional flexibility, they can be customized to meet your specific application requirements.

A Solid Foundation

QED-2 switchboards are available as single or multiple mains or as distribution sections. Individually mounted mains use SQUARE D P- and R-frame electronic or MICROLOGIC® molded case circuit breakers through 2,500 A, MASTERPACT® NW two-step stored energy electronic trip circuit breakers, circuit breakers for fixed or drawout applications through 5,000 A and fusible switches through 5,000 A.

Efficient Distribution Options

QED-2 distribution sections include both I-LINE circuit breaker and QMB fusible switch group-mounted panels. With I-LINE plug-on circuit breaker construction, the line end of the circuit breaker plugs directly onto the I-LINE panel bus assembly. This design allows you to quickly install and wire circuit breakers from the fronts of the switchboard. In addition, I-LINE circuit breakers are keyed to mounting slots in the support pan for automatic alignment and faster installation. I-LINE switchboard sections are available in single- or double-row construction.

High Ampacities

If you require higher feeder ampacities, QED-2 switchboards are available with individually mounted branch devices up to 4,000 A. They include both thermal-magnetic and electronic trip molded case circuit breakers or BOLT-LOC Type BP fusible switches. For equipment ground fault protection, you can use electronic trip circuit breakers or fusible switches with the Type GC equipment ground fault system. With QED-2 switchboards, you can also specify options such as automatic throw-over systems.

Features

- Front accessible load connections
- Front and rear alignment standard
- Switchboard fed by cable, busway, transformer, QED switchboard or other
- Switchboard ratings through 5000 A, 200kA; higher amperages available
- Thermal-magnetic, electronic, MICROLOGIC® or stored energy fix- and drawout-mounted circuit breaker mains and feeders
- Fix-mounted fusible switch mains and feeders
- Group-mounted circuit breaker and fusible switch mains and feeders
- Main devices in six sub-division or single main configurations
- Main and branch devices in single section configuration
- Main lugs in separate section in line-up or behind devices
- Group-mounted mains and branches
- Thermal-magnetic and electronic circuit breakers with standard, high, extra-high or current limiting capability
- Exclusive MICROLOGIC trip circuit breakers, 80% or 100% rated
- Zone selective interlocking on MICROLOGIC® circuit breakers, group-mounted 100 A/250 A thermal-magnetic circuit breakers with add-on ground fault and bolted pressure fusible switches
- POWERLOGIC® system customer metering including custom communications capability and interwiring
- All options available on circuit breakers and fusible switches
- Custom engineering including main-tie-mains, multiple sets of through bus, reduced heights and engineered houses
- Optional start-up service and training

Options

Hot and cold sequence utility metering, customer metering and the POWERLOGIC monitoring and control system, equipment ground fault protection, automatic throw-over systems, transfer switches and zone selective interlocking.



QED-2 switchboards provide versatility and performance for today's complex commercial, industrial and utility applications.

Solutions for Maximum Flexibility...

If you're looking for an overcurrent device to meet your specific application, no one matches the selection found in the POWER-STYLE® QED switchboard family. All QED switchboards feature a choice of molded case circuit breakers or fusible switches.

You can select thermal-magnetic, current limiting, electronic or MICROLOGIC® circuit breakers in a configuration designed to meet your specific needs. The unique I-LINE construction from Square D/ Schneider Electric, for example, gives you the capacity of group mounting circuit breakers (up to 1,200 A) for faster installation, mounting flexibility and efficient use of space. You can also select individually mounted circuit breakers rated up to 5,000 A in fixed or drawout construction.

You can further enhance the flexibility of POWER-STYLE QED switchboards with other options, such as equipment ground fault protection with MICROLOGIC® electronic trip circuit breakers or BOLT-LOC Type BP switches with the TYPE GC equipment ground fault system. On 100 A and 250 A circuit breakers, an equipment ground fault module is available with two levels of protection to give you the backup protection you need for power-critical operations.

POWER-STYLE® QED Metering Options



MICROLOGIC Trip Units



POWERLOGIC Circuit Monitor



Utility metering

You can see versatility in the number and types of metering options available for the POWER-STYLE® QED switchboard family. They include customer metering featuring the advanced capabilities of the POWERLOGIC® monitoring and control system and MICROLOGIC® trip units. Utility metering options are also available to meet local utility requirements.

Customer Metering from A to Z.

The POWERLOGIC system provides over 50 meter values, which can be displayed locally on multiple POWERLOGIC circuit monitors or remotely on personal computers. On-board event and data logging, waveform capture and automated controls are also provided by the POWERLOGIC system. Now Square D/Schneider Electric not only offers the toughest switchboard in the industry, but the smartest one as well!

Effective electrical distribution is more than just the transmission of power. Capturing, understanding and managing power information can substantially increase your system efficiency and lower life cycle costs.

These trip units provide advanced functionality such as communications interfaces, POWERLOGIC power metering, and local/remote monitoring capability, which allows for integration and coordination of your electrical system. With the appropriate MICROLOGIC trip unit, you can:

- Communicate with breakers
- Gather power information and energy usage patterns
- Monitor events and deviations from the norm
- Remotely control breakers for better process loading
- Perform predictive maintenance

Because the trip units, which offer increasing levels of functionality, are interchangeable, you can upgrade equipment easily as your needs expand.

Utility Metering.

Square D/Schneider Electric provides utility current transformer (UCT) metering compartments to meet your local utility specifications. The UCT compartment has either single- or double-hinged doors with sealable hasps and screws. UCTs are available in full-height (90") or half-height (45") compartments. Depending upon your utility's requirements, we will provide either hot sequence CT compartments (metering ahead of the main disconnect) or cold sequence CT compartments (metering on the load side of the main disconnect).

POWER-STYLE® QED Selection Information

	QED-S		QED-2		QED-6	
RATING	**RATING**		**RATING**		**RATING**	
400-4000 A		✓		✓		✓
400-5000 A				✓		✓
6000 A				✓		
INCOMING						
CABLE		✓		✓		✓
BUSWAY				✓		✓
TRANSFORMER				✓		✓
THROUGH BUS TO QED				✓		
MAIN DEVICE						
Individual Fixed						
BOLTED PRESSURE SWITCH	4000 A	✓	5000 A	✓		
THERMAL-MAGNETIC CIRCUIT BREAKER	2500 A	✓	2500 A	✓	2500 A	✓
ELECTRONIC CIRCUIT BREAKER	2500 A	✓	2500 A	✓	2500 A	✓
MICROLOGIC® CIRCUIT BREAKER	2500 A	✓	2500 A	✓		
STORED ENERGY	4000 A	✓	5000 A	✓	5000 A	✓
Individual Drawout						
MASTERPACT NW CIRCUIT BREAKER			5000 A	✓	5000 A	✓
Group						
THERMAL-MAGNETIC CIRCUIT BREAKER (I-LINE)	1200 A	✓	1200 A	✓		
ELECTRONIC CIRCUIT BREAKER (I-LINE)	1200 A	✓	1200 A	✓		
MICROLOGIC CIRCUIT BREAKER (I-LINE)	1200 A	✓	1200 A	✓		
FUSIBLE SWITCH (QMB)	1200 A	✓	1200 A	✓		
FEEDER						
Individual Fixed						
BOLTED PRESSURE SWITCH	4000 A	✓	4000 A	✓		
THERMAL-MAGNETIC CIRCUIT BREAKER	2500 A	✓	2500 A	✓	1200 A	✓
ELECTRONIC CIRCUIT BREAKER	2500 A	✓	2500 A	✓		
MICROLOGIC CIRCUIT BREAKER	2500 A	✓	2500 A	✓	1200 A	✓
STORED ENERGY CIRCUIT BREAKER	4000 A	✓	4000 A	✓		
Individual Drawout						
MASTERPACT® NT CIRCUIT BREAKER					1200 A	✓
MASTERPACT NW CIRCUIT BREAKER			4000 A	✓		
Group						
THERMAL-MAGNETIC CIRCUIT BREAKER (I-LINE)	1200 A	✓	1200 A	✓		
ELECTRONIC CIRCUIT BREAKER (I-LINE)	1200 A	✓	1200 A	✓		
MICROLOGIC CIRCUIT BREAKER (I-LINE)	1200 A	✓	1200 A	✓		
FUSIBLE SWITCH (QMB)	1200 A	✓	1200 A	✓		
UTILITIES						
SELECTED		✓				
ALL				✓		
CUSTOMER METERING						
POWER METER (A, V, W, COMM.)		✓		✓		✓
CIRCUIT MONITOR (A, V, W, WAVEFORM, COMM.)		✓		✓		✓
ACCESS						
FRONT		✓		✓		
FRONT & REAR		✓		✓		
COMPARTMENTALIZATION						
CIRCUIT BREAKER						✓
BUSSING						✓
LOAD LUGS						✓
OPTIONS						
SELECTED		✓				
ALL				✓		
ENGINEERING						
STANDARD		✓				
CUSTOM				✓		

You can create an efficient electrical distribution system that meets your needs today, while building a foundation for the future. This is the SQUARE D difference.

POWER-STYLE®
Switchboards

The Difference is in the Details

- 100% rated phase and neutral through bus
- No deration of through bus
- Through bus extends the entire section (no through bus extensions required for additional sections)
- Captive splice bars
- Continuously plated bussing
- Front and rear alignment
- I-LINE® group-mounted distribution requires no additional hardware kit to add future circuit breakers
- Sectionalized shipment available for easier handling
- Removable lifting bars on NEMA Type 1 Enclosures
- NEMA Type 1 or 3R Non-Walk-In Enclosures
- ANSI 49 corrosion-resistant paint finish
- Removable top plate
- UL891 Labeled
- Switchboard frame suitable for use as floor sills
- 80% and 100% rated MICROLOGIC® electronic trip circuit breakers through 1200 A for group-mounted distribution
- POWERLOGIC® system customer metering from ammeter, voltmeter, wattmeter to waveform capture, data logging, alarm/relay functions, disturbance monitoring and programmable logic



SPEED-D® Service Section Switchboards

UL listed and available from distributor or warehouse stock, these switchboards contain a EUSERC utility metering compartment and a main circuit breaker with either a 42-circuit NQOD interior or a 27" I-LINE interior. It is also available with a QMB interior for six circuit main applications. Each section is suitable for use as service entrance equipment and is available in either Type 1 or Type 3R construction. Accessories include an indoor underground pull section, outdoor (3R) underground pull section, lug landing kit and loadside wireway.

- Mains rating: 400, 600, or 800 A
- Voltage: 120/240, 208Y/120, 240/120, or 480Y/277 VAC
- Systems: 1Ø3W or 3Ø4W
- Dimensions: Type 1 enclosure – 90" high, 14" deep, 36" wide
- Type 3R enclosure – 90" high, 24.5" deep, 36" wide

© 2002 Schneider Electric
All rights reserved
Document Number 2700BR0202

SQUARE D
Schneider Electric

Visit www.SquareD.com for more information.

Internal Modular SPDs

Square D Internally Mounted Surge Protective Devices

Square D™ brand Surgelogic™ internal modular Surge Protective Devices (SPDs) deliver specification grade performance for service entrance or critical branch panel applications. This multi-phase system provides suppression for all critical modes inside electrical equipment and shorter lead lengths with superior SPD performance.




SQUARE D™

by Schneider Electric

Internal Modular SPDs Features





Internal panel modular Surge Protective Devices (SPDs) provide superior design and service life for a wide variety of commercial, industrial, or institutional applications. Square D brand Surgelogic SPDs offer first-rate performance and surge suppression for demanding service entrance applications or as part of a suppression network. The robust modular construction reduces possible down time and maintenance costs.

Superior Performance

Surgelogic SPDs utilize a high-energy suppression circuit that provides 10 modes of suppression from 100,000 to 480,000 peak Amps of surge current rating per phase. Modular SPDs feature circuity that provides not only transient surge suppression, but also noise filtration.

Installation

Integral solutions come professionally pre-wired into electrical gear and panels from the factory insuring short lead lengths and high performance. All units are tested at the factory before delivery to their final destination, maintaining Square D brand's high standard of quality. There is also no need for additional enclosures or installation labor costs.

Warranty

Surgelogic internal modular SPDs have a 10-year warranty.

FEATURES	ADVANTAGES	BENEFITS
Integral to electrical gear and panels	SPDs are professionally installed inside electrical gear and panels	Delivers high levels of SPD performance and saves on enclosure and installation expenses
100,000 to 480,000 Amp Capacity (depending on model)	Longer service life and suppression against high-energy lightning strikes	High performance surge suppression even in severe electrical conditions
EMI/RFI Noise Rejection	Increased transient suppression	Improves surge suppression to the equipment
Advanced Diagnostics	Allows for visual indication/testing of the suppressor's functionality	Provides immediate response if suppressor is damaged
Suppression Status Alarms	Allows multiple methods of alarm notification	Provides immediate notification through audible, visual and remote signaling if reduced suppression occurs
Coordinated Fuse Technology	Coordinated fusing allows disconnection methods for thermal and high-current events	Provides premium surge suppression while managing both thermal and high-current end-of-life events

Schneider Electric USA, Inc. 800 Federal Street Andover, MA 01810, USA Telephone: (978) 794-0800 TAG: (800) 577-7353 www.schneider-electric.com/us

Document Number 9990-0116Rev02 Nov 2017 bw

© 2011-2017 Schneider Electric. All rights reserved.

Internal Modular SPDs
Features (continued)

NF Panelboard



NF panelboards are primarily used for lighting and power distribution up to 600 Amps. These panelboards follow current National Electric Code changes, provide electrical capacity up to 84 circuit breakers, and will allow up to 72 circuits with surge protection installed. NF panels are designed with 200% rated copper neutrals for non-linear loads. (NF max volts 600/347 Vac)

SPD available surge current ratings: 100, 120, 160, 200, 240 kA

QED Switchboard



QED Switchboards are made for use as service entrance equipment or as distribution centers in commercial, institutional, and industrial applications. QEDs are extremely versatile providing front accessible load connections with multiple breaker and fusible switch options. QEDs enable easy access to power monitoring equipment such as products from our Square D brand PowerLogic™ brand. (Max volts 600 Vac, max current 4,000 Amps)

SPD available surge current ratings:
120, 160, 240, 320, 480 kA

Internal SPDs



Performance

Surge Current Rating per Phase	Up to 480kA
Short Circuit Current Rating	200kA
Modes of Protection	6, 10
Fusing	Individually fused MOVs
Thermal Fusing	Yes
Overcurrent Fusing	Yes
Sine Wave Tracking	Yes
EMI/RFI Filtering	Up to -42 dB
Operating Frequency	50/60 Hz

Mechanical Description

Connection Method	#10-#2 AWG Terminals
Mounting Method/Circuit Type	Parallel
Operating Altitude	Sea Level-12,000' (3,658 m)
Storage Temperature	-40˚ F (-40˚ C) to 149˚ F (65˚ C)
Operating Temp.	-4˚ F (-20˚ C) to 149˚ F (65˚ C)
LCD Operating Temp.	32˚ F (0˚ C) to 149˚ F (65˚ C)
Operating Humidity	0 to 95% non-condensing

Diagnostics

Push to test diagnostic switches, red and green status LEDs per phase (internal redundant status LEDs are green), module status LEDs per mode, dry contacts, audible alarm with disable switch, surge counter.

Options

- Remote monitor

Safety and Performance

Type 2 SPD: cURus per UL 1449 4th Edition and CAN/CSA C22.2 No. 8-M1986.
Complies with UL 96A 12th Edition Master Label requirements for Lightning Protection Systems.


Type 1 SPD: URus per UL 1449 4th Edition and CAN/CSA C22.2 No. 8-M1986.
Complies with UL 96A 12th Edition Master Label requirements for Lightning Protection Systems.

© 2011-2017 Schneider Electric. All rights reserved.

Internal Modular SPDs
Features (continued)

Power-Zone Switchgear





The Square D brand Power-Zone™ 4 low voltage metal-enclosed drawout switchgear is designed to provide superior electrical distribution and power quality management. Power-Zone 4 switchgear is designed to deliver maximum uptime, system selectivity, and ease of maintenance. All of these features are packed into one of the smallest footprints available for low voltage drawout switchgear. (Max volts 600 Vac, max current 5,000 Amps)

SPD available surge current ratings:
120, 160, 240, 320, and 480 kA

QMB Panelboard





When specifications or electrical codes call for a fusible panelboard, the QMB family offers superior performance and time-saving installation features. The reliability of the QMB panelboard makes it the product of choice for large commercial and industrial applications. (Max volts 600 Vac, max current 400 Amps)

SPD available surge current ratings: 120, 160, 240 kA

Motor Control Center





The feature-rich modular design minimizes space and maximizes ease-of-use and accessibility of motor control devices. The Model 6 MCC has integrated industry-leading components into the smallest and one of the most flexible footprints possible to meet industry's power, control, and automation needs. (Max volts 480 Vac, max current 2,500 Amps)

SPD available surge current ratings: 120, 160, 240 kA

Busway



Square D brand I-Line™ Busway is engineered to replace old cable and conduit systems. This next-generation power distribution system is loaded with exceptional features, including a 200% neutral and a 100% isolated ground path. (Max volts 600 Vac, max current 5,000 Amps)

SPD available surge current ratings: 120, 160, 240 kA

© 2011-2017 Schneider Electric. All rights reserved.

Internal Modular SPDs Specifications

WYE Configured SPD Specifications

Voltage	Surge Current per Phase	Modes of Protection	Configuration	Model Number	MCOV	I_n	VPR L-N	VPR L-G	VPR L-L	VPR N-G
120/240V	120kA	6	1 Ø, 3-wire+G	TVS1IMA12_	150V	20kA	700V	800V	1200V	700V
208Y/120V ■	120kA	10	3 Ø, Wye, 4-wire+G	TVS2IMA12_	150V	20kA	700V	800V	1200V	700V
480Y/277V ▲	120kA	10	3 Ø, Wye, 4-wire+G	TVS4IMA12_	320V	20kA	1200V	1200V	2000V	1200V
600Y/347V	120kA	10	3 Ø, Wye, 4-wire+G	TVS8IMA12_	420V	20kA	1500V	1500V	2500V	1500V
120/240V	160kA	6	1 Ø, 3-wire+G	TVS1IMA16_	150V	20kA	700V	800V	1200V	700V
208Y/120V ■	160kA	10	3 Ø, Wye, 4-wire+G	TVS2IMA16_	150V	20kA	700V	800V	1200V	700V
480Y/277V ▲	160kA	10	3 Ø, Wye, 4-wire+G	TVS4IMA16_	320V	20kA	1200V	1200V	2000V	1200V
600Y/347V	160kA	10	3 Ø, Wye, 4-wire+G	TVS8IMA16_	420V	20kA	1500V	1500V	2500V	1500V
120/240V	240kA	6	1 Ø, 3-wire+G	TVS1IMA24_	150V	20kA	700V	800V	1200V	700V
208Y/120V ■	240kA	10	3 Ø, Wye, 4-wire+G	TVS2IMA24_	150V	20kA	700V	800V	1200V	700V
480Y/277V ▲	240kA	10	3 Ø, Wye, 4-wire+G	TVS4IMA24_	320V	20kA	1200V	1200V	2000V	1200V
600Y/347V	240kA	10	3 Ø, Wye, 4-wire+G	TVS8IMA24_	420V	20kA	1500V	1500V	2500V	1500V
120/240V	320kA	6	1 Ø, 3-wire+G	TVS1IMA32_	150V	20kA	700V	800V	1200V	700V
208Y/120V ■	320kA	10	3 Ø, Wye, 4-wire+G	TVS2IMA32_	150V	20kA	700V	800V	1200V	700V
480Y/277V ▲	320kA	10	3 Ø, Wye, 4-wire+G	TVS4IMA32_	320V	20kA	1200V	1200V	2000V	1200V
600Y/347V	320kA	10	3 Ø, Wye, 4-wire+G	TVS8IMA32_	420V	20kA	1500V	1500V	2500V	1500V
120/240V	480kA	6	1 Ø, 3-wire+G	TVS1IMA48_	150V	20kA	700V	800V	1200V	700V
208Y/120V ■	480kA	10	3 Ø, Wye, 4-wire+G	TVS2IMA48_	150V	20kA	700V	800V	1200V	700V
480Y/277V ▲	480kA	10	3 Ø, Wye, 4-wire+G	TVS4IMA48_	320V	20kA	1200V	1200V	2000V	1200V
600Y/347V	480kA	10	3 Ø, Wye, 4-wire+G	TVS8IMA48_	420V	20kA	1500V	1500V	2500V	1500V

■ 208Y/120 series also applies to the following voltage 220Y/127 ▲ 480Y/277 series also applies to the following voltages 380Y/220, 400Y/230, and 415Y/240

High-Leg Delta (HLD) Configured SPD Specifications

Voltage	Surge Current per Phase	Modes of Protection	Configuration	Model Number	MCOV	I_n	VPR L-N	VPR H-N	VPR L-G	VPR H-G	VPR L-L	VPR H-L	VPR N-G
240/120HLD	120kA	10	3 Ø, HLD*, 4-wire+G	TVS3IMA12_	150V	20kA	700V	1200V	800V	1200V	1200V	1500V	700V
240/120HLD	160kA	10	3 Ø, HLD*, 4-wire+G	TVS3IMA16_	150V	20kA	700V	1200V	800V	1200V	1200V	1500V	700V
240/120HLD	240kA	10	3 Ø, HLD*, 4-wire+G	TVS3IMA24_	150V	20kA	700V	1200V	800V	1200V	1200V	1500V	700V
240/120HLD	320kA	10	3 Ø, HLD*, 4-wire+G	TVS3IMA32_	150V	20kA	700V	1200V	800V	1200V	1200V	1500V	700V
240/120HLD	480kA	10	3 Ø, HLD*, 4-wire+G	TVS3IMA48_	150V	20kA	700V	1200V	800V	1200V	1200V	1500V	700V

Model numbers not recognized as line items in Schneider Electric ordering system until a suffix code is applied

TYPE 2 WYE AND HLD MODEL NUMBER SUFFIX CODES

- P NQ/NF panelboard *(Not available in 320 and 480 kA)*
- B QED switchboard
- B2 QED series 2 switchboard
- Z PZ3/PZ4 switchgear *(Not available in TVS1 or TVS3)*
- Q QMB panelboard *(Not available in 320 and 480 kA)*
- M Motor Control Center *(Not available in 320 and 480 kA)*

TYPE 1 WYE AND HLD MODEL NUMBER SUFFIX CODES

- P1 NQ/NF panelboard *(Not available in 320 and 480 kA)*
- B1 QED switchboard
- B21 QED series 2 switchboard
- Z1 PZ3/PZ4 switchgear *(Not available in TVS1 or TVS3)*
- Q1 QMB panelboard *(Not available in 320 and 480 kA)*
- M1 Motor Control Center *(Not available in 320 and 480 kA)*

Schneider Electric USA, Inc. 800 Federal Street Andover, MA 01810, USA Telephone: (978) 794-0800 TAG: (800) 577-7353 www.schneider-electric.com/us

© 2011-2017 Schneider Electric. All rights reserved.

Document Number 9990-0116Rev02 Nov 2017 bw

Internal Modular SPDs
Specifications (continued)

Delta/High-Resistance Ground (HRG) Configured SPD Specifications

Voltage	Surge Current per Phase	Modes of Protection	Configuration	Model Number	MCOV	I_n	VPR			
							L-N	L-G	L-L	N-G
240V DELTA	100kA	6	3 Ø, Delta, 3-wire+G	TVS6IMA10_	300V	20kA	N/A	1200V	1200V	N/A
480V DELTA ■	100kA	6	3 Ø, Delta, 3-wire+G	TVS5IMA10_	640V	20kA	N/A	1800V	2000V	N/A
600V DELTA ▲	100kA	6	3 Ø, Delta, 3-wire+G	TVS9IMA10_	700V	10kA	N/A	2500V	2500V	N/A
240V DELTA	120kA	6	3 Ø, Delta, 3-wire+G	TVS6IMA12_	300V	20kA	N/A	1200V	1200V	N/A
480V DELTA ■	120kA	6	3 Ø, Delta, 3-wire+G	TVS5IMA12_	640V	20kA	N/A	1800V	2000V	N/A
600V DELTA ▲	120kA	6	3 Ø, Delta, 3-wire+G	TVS9IMA12_	700V	10kA	N/A	2500V	2500V	N/A
240V DELTA	160kA	6	3 Ø, Delta, 3-wire+G	TVS6IMA16_	300V	20kA	N/A	1200V	1200V	N/A
480V DELTA ■	160kA	6	3 Ø, Delta, 3-wire+G	TVS5IMA16_	640V	20kA	N/A	1800V	2000V	N/A
600V DELTA ▲	160kA	6	3 Ø, Delta, 3-wire+G	TVS9IMA16_	700V	10kA	N/A	2500V	2500V	N/A
600V DELTA ▲	180kA	6	3 Ø, Delta, 3-wire+G	TVS9IMA18_	700V	10kA	N/A	2500V	2500V	N/A
240V DELTA	200kA	6	3 Ø, Delta, 3-wire+G	TVS6IMA20_	300V	20kA	N/A	1200V	1200V	N/A
480V DELTA ■	200kA	6	3 Ø, Delta, 3-wire+G	TVS5IMA20_	640V	20kA	N/A	1800V	2000V	N/A
600V DELTA ▲	200kA	6	3 Ø, Delta, 3-wire+G	TVS9IMA20_*	700V	10kA	N/A	2500V	2500V	N/A
240V DELTA	240kA	6	3 Ø, Delta, 3-wire+G	TVS6IMA24_	300V	20kA	N/A	1200V	1200V	N/A
480V DELTA ■	240kA	6	3 Ø, Delta, 3-wire+G	TVS5IMA24_	640V	20kA	N/A	1800V	2000V	N/A
600V DELTA ▲	240kA	6	3 Ø, Delta, 3-wire+G	TVS9IMA24_*	700V	10kA	N/A	2500V	2500V	N/A
240V DELTA	320kA	6	3 Ø, Delta, 3-wire+G	TVS6IMA32_	300V	20kA	N/A	1200V	1200V	N/A
480V DELTA ■	320kA	6	3 Ø, Delta, 3-wire+G	TVS5IMA32_	640V	20kA	N/A	1800V	2000V	N/A
600V DELTA ▲	320kA	6	3 Ø, Delta, 3-wire+G	TVS9IMA32_	700V	10kA	N/A	2500V	2500V	N/A
240V DELTA	480kA	6	3 Ø, Delta, 3-wire+G	TVS6IMA48_	300V	20kA	N/A	1200V	1200V	N/A
480V DELTA ■	480kA	6	3 Ø, Delta, 3-wire+G	TVS5IMA48_	640V	20kA	N/A	1800V	2000V	N/A

■ 480V Delta series also applies to the following voltage 480Y/277V HRG
▲ 600V Delta series also applies to the following voltage 600Y/347V HRG
* *Note: 200kA and 240kA in 600V DELTA are 6 module systems and will require more installation room*

Model numbers not recognized as line items in Schneider Electric ordering system until a suffix code is applied

TYPE 2 DELTA MODEL NUMBER SUFFIX CODES

B QED switchboard
B2 QED series 2 switchboard
M Motor Control Center *(Not available in 320 and 480 kA for all voltages, 600V DELTA not available also in 200 and 240 kA)*
Z PZ3/PZ4 switchgear *(Not available in TVS1 or TVS3)*

TYPE 1 DELTA MODEL NUMBER SUFFIX CODES

B1 QED switchboard
B21 QED series 2 switchboard
M1 Motor Control Center *(Not available in 320 and 480 kA for all voltages, 600V DELTA not available also in 200 and 240 kA)*
Z1 PZ3/PZ4 switchgear *(Not available in TVS1 or TVS3)*



SPD OPTIONS

Remote Monitor - TVS12RMU
The remote monitor has a single red/green LED status indicator, audible alarm with enable/disable button, and can be wired up to 1,000' feet away. This device connects directly to the dry contact interface of the SPD and will alarm if the SPD enters a fault condition.

Schneider Electric USA, Inc.
800 Federal Street
Andover, MA 01810
Telephone: (978) 794-0800
www.schneider-electric.com/us

Schneider Electric México, S.A. de C.V.
Calz. J. Rojo Gómez 1121-A
Col. Gpe. del Moral 09300 México, D.F.
Tel. 55-5804-5000
www.schneider-electric.com.mx

Schneider Electric Canada, Inc.
5985 McLaughlin Road
Mississauga, ON L5R 1B8 Canada
Tel:1-800-565-6699
www.schneider-electric.ca

© 2011-2017 Schneider Electric. All rights reserved. Schneider Electric, Square D, Surgelogic, PowerLogic, and Power-Zone are trademarks owned by Schneider Electric Industries SAS or its affiliated companies. All other trademarks are the property of their respective owners.

PowerLogic PM8000 series

Intermediate metering

Technical data sheet



Schneider Electric

PM8000 series
Functions and characteristics

PB113688



PowerLogic PM8000 series meter.

PB113691



PowerLogic PM8000 series meter - rear view.

PB113692



PowerLogic PM8000 DIN rail mounted meter.

The PowerLogic PM8000 series meter is a highly accurate, extremely reliable power and energy meter with unmatched flexibility and usability. The meter combines accurate 3-phase energy and power measurements with data logging, power quality analysis, alarming and I/O capabilities not typically available in such a compact meter.

The PM8000 series meters are compliant with stringent international standards that guarantee their metering accuracy and power quality measurements. Ideal for industrial and critical power installations that are responsible for maintaining the operation and profitability of a facility.

Applications and benefits

- ■ Maximize profits by providing the highest output possible with the least amount of risk to availability.
- ■ Optimize availability and reliability of electrical systems and equipment.
- ■ Monitor power quality (PQ) for compliance and to prevent problems.
- ■ Meters fully supported by StruxureWare Power Monitoring Expert and PowerSCADA Expert Software.

Main characteristics

- ■ Precision metering:
- □ IEC 61557-12 PMD Sx K70 3000m 0.2 (performance measuring and monitoring functions).
- □ Class 0.2S accuracy IEC 62053-22, ANSI C12.20 Class 0.2 (active energy).
- □ Industry leading Class 0.5S* accuracy for reactive energy (IEC 62053-24).
- □ Cycle-by-cycle RMS measurements updated every ½ cycle.
- □ Full 'multi-utility' WAGES metering support.
- □ Net metering.
- □ Anti-tamper protection seals.

- ■ PQ compliance reporting and basic PQ analysis.
- □ Monitors and logs parameters in support of international PQ standards,
  - IEC 61000-4-30 Class S
  - IEC 62586 PQI-S
  - EN 50160
- □ Generates onboard PQ compliance reports accessible via onboard web pages:
  - Basic event summary and pass/fail reports, such as EN 50160 for power frequency, supply voltage magnitude, supply voltage dips, short and long interruptions, temporary over voltages, voltage unbalance and harmonic voltage.
  - ITIC (CBEMA) and SEMI curves, with alarm categorization to support further analyses.
  - NEMA Motor Derating curve.
  - Basic meter provides EN 50160 but can be configured to provide IEEE 519.
- □ Harmonic analysis:
  - THD on voltage and current, per phase, min/max, custom alarming.
  - Individual harmonic magnitudes and angles on voltage and current, up to the 63rd harmonic.
- □ High resolution waveform capture: triggered manually or by alarm, captured waveforms available directly from the meter via FTP in a COMTRADE format.
- □ Disturbance detection and capture: sag/swell on any current and voltage channel, alarm on disturbance event, waveform capture with per-event information.
- □ Patented disturbance direction detection: provides indication of the captured disturbance occurring upstream or downstream of the meter; timestamped results provided in the event log, with degree of certainty of disturbance direction.

- ■ Used with StruxureWare Power Monitoring Expert software, provides detailed PQ reporting across entire network:
- □ EN 50160 report.
- □ IEC 61000-4-30 report.
- □ PQ compliance summary.
- □ ISO 50001.
- □ Display of waveforms and PQ data from all connected meters.
- ■ Onboard data and event logging.
- □ 512MB of standard non-volatile memory. 10 MB of standard non-volatile memory dedicated to capture billing data, events, and waveforms.

*Certification pending

PM8000 series
Functions and characteristics (cont.)

PB113670



PowerLogic remote display.

PB113671



PowerLogic I/O module.

PB113669



PowerLogic PM8000 series meter with remote display.

- □ No data gaps due to network outages or server downtime.
- □ Min/Max log for standard values.
- □ 50 user-definable data logs, recording up to 16 parameters on a cycle-by-cycle or other user definable interval.
- □ Continuous logging or 'snapshot' triggered by setpoint and stopped after defined duration.
- □ Trend energy, demand and other measured parameters.
- □ Forecasting via web pages: average, minimum and maximum for the next four hours and next four days.
- □ Time-of-use in conjunction with StruxureWare software.
- □ Event log: alarm conditions, metering configuration changes, and power outages, timestamped to 1 millisecond.

- ■ Alarming and control.
- □ 50+ definable alarms to log critical event data, trigger waveform recording, or perform control function.
- □ Trigger on any condition, with cycle-by-cycle and 1-second response time.
- □ Combine alarms using Boolean logic and to create alarm levels.
- □ Alarm notification via email text message.
- □ In conjunction with StruxureWare Power Monitoring Expert, software alarms and alarm frequency are categorized and trended for easy evaluation of worsening/improving conditions.

- ■ Excellent quality: ISO 9001 and ISO 14000 certified manufacturing.

Usability

- ■ Easy installation and setup.
- □ Panel and DIN rail mounting options, remote display option.
- □ Pluggable connectors.
- □ Free setup application simplifies meter configuration.

- ■ Front panel.
- □ Easy to read colour graphic display.
- □ Simple, intuitive menu navigation with multi-language (8) support.

- ■ Flexible remote communications.
- □ Multiple simultaneously operating communication ports and protocols allow interfacing with other automation systems; (e.g. waveforms, alarms, billing data, etc.) can be uploaded for viewing/analysis while other systems access real-time information.
- □ Supports Modbus, ION, DNP3, IEC 61850.
- □ Dual port Ethernet: 10/100base-TX; daisy-chaining capability removes need for additional switches.
- □ Create redundant network loop using Rapid Spanning Tree Protocol (RSTP) and managed Ethernet switches.
- □ Customize TCP/IP port numbers enable/disable individual ports.
- □ RS-485 2-wire connection, up to 115200 baud, Modbus RTU and ION protocols, DNP3 is also supported via RS-485.
- □ Ethernet to serial gateway with Modbus Master functionality, connecting to 31 downstream serial Modbus devices. Also supports Modbus Mastering over TCP/IP (Ethernet) network.
- □ Full function web server with factory and customizable pages to access real-time and PQ compliance data.
- □ Push historical data via email.
- □ Advanced security: Up to 16 configurable user accounts.

- ■ Time synchronization via:
- □ GPS clock (RS485) or IRIG-B (digital input) to +/- 1 millisecond.
- □ Also supports Network Time Protocol (NTP/SNTP) and time set function from StruxureWare software server.

Adaptability

- ■ ION™ frameworks allow customizable, scalable applications, object-oriented programming, compartmentalizes functions, and increases flexibility and adaptability.

PM8000 series
Functions and characteristics (cont.)

PB113686



PowerLogic PM8000 series meter with I/O modules.

□ Applications include: access and aggregate data from Modbus devices on serial port or across the network (Modbus TCP/IP), logging and/or processing data by totalizing, unit conversion or other calculations, applying complex logic for alarming or control operations, data visualization via web pages.

Standard meter I/O
■ 3 digital status/counter inputs.
■ 1 KY (form A) energy pulse output for interfacing with other systems.

Modular I/O options
■ Optional expansion modules (up to 4 per meter) add digital/analogue I/O.

Option modules include:

■ Digital module
□ 6 digital status/counter inputs.
□ 2 Form C relay outputs, 250 V, AC / 30 V DC, max current 8A at 250 V AC or 5 A at 24 V DC, 20k cycles (resistive).

■ Analogue module
□ 4 analogue inputs (4-20mA; 0-30 V).
□ 2 analogue outputs (4-20mA; 0-10 V) for interfacing with building management sensors and systems.

Reference numbers	
Meter	**Description**
METSEPM8240	DIN96 panel mount meter
METSEPM8243	DIN rail mount meter
METSEPM8244	DIN rail mount meter with remote display
Accessories	**Description**
METSEPM89RD96	Remote display, 3 metre cable, mounting hardware for 30mm hole (nut & centering pin), mounting hardware for DIN96 cutout (92x92mm) adapter plate
METSEPM8000SK	Terminal covers for utility sealing
METSEPMAK	Adapters for mounting meter and remote display back to back & ANSI 4", 0.3 metre (1 ft.) Ethernet cable
METSECAB10	Display Cable, 10 metres
METSEPM89M2600	Digital I/O module (6 digital inputs & 2 relay outputs)
METSEPM89M0024	Analogue I/O module (4 analogue inputs & 2 analogue outputs)

PM8000 series
Functions and characteristics (cont.)

PB113696



PowerLogic™ PM8000 bottom view DIN mounting.

Features guide		PM8000
General		
Use on LV and MV systems		■
Current accuracy (5A Nominal)		0.1 % reading
Voltage accuracy (57 V LN/100 V LL to 400 V LN/690 V LL)		0.1 % reading
Active energy accuracy		0.2 %
Number of samples/cycle or sample frequency		256
Instantaneous rms values		
Current, voltage, frequency		■
Active, reactive, apparent power	Total and per phase	■
Power factor	Total and per phase	■
Current measurement range (autoranging)		0.05 - 10A
Energy values		
Active, reactive, apparent energy		■
Settable accumulation modes		■
Demand values		
Current	Present and max. values	■
Active, reactive, apparent power	Present and max. values	■
Predicted active, reactive, apparent power		■
Synchronisation of the measurement window		■
Setting of calculation mode	Block, sliding	■
Power quality measurements		
Harmonic distortion	Current and voltage	■
Individual harmonics	Via front panel and web page	63
	Via StruxureWare software	127
Waveform capture		■
Detection of voltage swells and sags		■
Fast acquisition	1/2 cycle data	■
EN 50160 compliance checking		■
Customizable data outputs (using logic and math functions)		■
Data recording		
Min/max of instantaneous values		■
Data logs		■
Event logs		■
Trending/forecasting		■
SER (Sequence of event recording)		■
Time stamping		■
GPS synchronisation (+/- 1 ms)		■
Memory (in Mbytes)		512
Display and I/O		
Front panel display		■
Wiring self-test		■
Pulse output		1
Digital or analogue inputs(max)		27 digital 16 analogue
Digital or analogue outputs (max, including pulse output)		1 digital 8 relay 8 analogue
Communication		
RS 485 port		1
Ethernet port		2
Serial port (Modbus, ION, DNP3)		■
Ethernet port (Modbus/TCP, ION TCP, DNP3 TCP, IEC 61850 (2))		■
Ethernet gateway		■
Alarm notification via email		■
HTTP web server		■
SNMP with custom MIB and traps for alarms		■
SMTP email		■
NTP time synchronization		■
FTP file transfer		■

PM8000 series
Functions and characteristics (cont.)

Electrical characteristics		PM8000
Type of measurement		True rms to 256 samples per cycle
Measurement accuracy	Current & voltage	Class 0.2 as per IEC 61557-12
	Active Power	Class 0.2 as per IEC 61557-12
	Power factor	Class 0.5 as per IEC 61557-12
	Frequency	Class 0.2 as per IEC 61557-12
	Active energy	Class 0.2S IEC 62053-22 (In=5A) Class 0.2 IEC 61557-12, ANSI C12.20 Class 0.2
	Reactive Energy	Class 0.5S IEC 62053-24*
Data update rate		1/2 cycle or 1 second
Input-voltage characteristics	Specified accuracy voltage	57 VLN/100 VLL to 400 VLN/690 VLL
	Impedance	5 MΩ per phase
	Specified accuracy frequency - Frequency	42 to 69Hz (50/60Hz nominal)
	Limit range of operation - frequency	20 to 450Hz
Input-current characteristics	Rated nominal current	1A (0.5S), 5A (0.2S) , 10A (0.2 ANSI)
	Specified accuracy current range	Starting Current: 5mA Accurate Range: 50mA - 10A
	Permissible overload	200 A rms for 0.5s, non-recurring
	Impedance	0.0003 Ω per phase
	Burden	0.024 VA at 10A
Power supply	AC	90-415 V AC ±10% (50/60Hz ± 10%)
	DC	120-300 V DC ±10%
	Ride-through time	100 ms (6 cycles at 60 Hz) min., any condition 200 ms (12 cycles at 60 Hz) typ., 120 V AC 500 ms (30 cycles at 60 Hz) typ., 415 V AC
	Burden	Meter Only: 18 VA max at 415 V AC, 6W at 300 V DC Fully optioned meter: 36 VA max at 415 V AC, 17W at 300 V DC.
Input/outputs	Meter Base Only	3 form A digital inputs (30 V AC/60 V DC) 1 form A (KY) solid state digital output (30V AC/60 V DC, 75mA).
	Optional	Digital - 6 form A digital inputs (30 V AC / 60 V DC) wetted + 2 form C relay outputs (250 V AC / 30 V DC, 8 A at 250 V AC or 5 A at 24 V DC)
		Analogue - 4 analogue inputs (4-20mA, 0-30 V DC) + 2 analogue outputs (4-20mA, 0-10 V DC).
Mechanical characteristics		
Weight		Integrated Display Model 0.581 kg DIN rail mounted Model 0.528 kg IO modules 0.140 kg Remote display 0.300 kg
IP degree of protection		IP 54, UL type 12: Panel mount and Remote display, front. IP 30: Panel mount rear, DIN rail mount, I/O modules.
Dimensions	Panel mount model	96 x 96 x 77.5 mm
	DIN model	90.5 x 90.5 x 90.8 mm
	Remote display	96 x 96 x 27 mm
	IO modules	90.5 x 90.5 x 22 mm
Environmental conditions		
Operating temperature		-25ºC to +70ºC
Remote Display Unit		-25ºC to +60ºC
Storage temperature		-40ºC to +85ºC
Humidity rating		5% to 95% non-condensing
Installation category		III
Operating altitude (maximum)		3000m above sea level

PM8000 series
Functions and characteristics (cont.)

Electromagnetic compatibility	
Product standards	IEC 62052-11 and IEC 61326-1
Immunity to electrostatic discharge	IEC 61000-4-2
Immunity to radiated fields	IEC 61000-4-3
Immunity to fast transients	IEC 61000-4-4
Immunity to surges	IEC 61000-4-5
Immunity to conducted disturbances	IEC 61000-4-6
Immunity to power frequency magnetic fields	IEC 61000-4-8
Immunity to conducted disturbances, 2-150kHz	CLC/TR 50579
Immunity to voltage dips & interruptions	IEC 61000-4-11
Immunity to ring waves	IEC 61000-4-12
Conducted and radiated emissions	EN 55022, EN 55011, FCC part 15, ICES-003
Surge withstand Capability (SWC)	IEEE C37.90.1
Safety	
Safety Construction	IEC/EN 61010-1 ed.3, CAT III, 400 VLN / 690 V LL UL 61010-1 ed.3 and CSA-C22.2 No. 61010-1 ed.3, CAT III, 347 V LN / 600 V LL IEC/EN 62052-11, protective class II
Communication (1)	
Ethernet to serial line gateway	Communicates directly with up to 32 unit load ION slave devices.
Web server	Customisable pages, new page creation capabilities, HTML/XML compatible.
Serial port RS 485	Baud rates of 2400 to 115200, pluggable screw terminal connector.
Ethernet port(s)	2x 10/100Base-TX, RJ45 connector (UTP).
Protocol	Modbus, ION, DNP3, IEC 61850, HTTP, FTP, SNMP, SMTP, DPWS, RSTP, NTP, SNTP, GPS protocols.
Firmware characteristics	
High-speed data recording	Down to 1/2 cycle interval burst recording, stores detailed characteristics of disturbances or outages. Trigger recording by a user-defined setpoint, or from external equipment.
Harmonic distortion	Up to 63rd harmonic (127th via StruxureWare software) for all voltage and current inputs.
Sag/swell detection	Analyse severity/potential impact of sags and swells: magnitude and duration data suitable for plotting on voltage tolerance curves per phase triggers for waveform recording, control.
Disturbance direction detection	Determine the location of a disturbance more quickly and accurately by determining the direction of the disturbance relative to the meter. Analysis results are captured in the event log, along with a timestamp and confidence level indicating level of certainty.
Instantaneous	High accuracy of standard speed (1s) and high-speed (1/2 cycle) measurements, including true rms per phase and total for: voltage, current, active power (kW),reactive power (kvar), apparent power (kVA), power factor, frequency, voltage and current unbalance, phase reversal.
Load profiling	Channel assignments (800 channels via 50 data recorders) configurable for any measurable parameter, including historical trend recording of energy, demand, voltage, current, power quality, or any measured parameter. Trigger recorders based on time interval, calendar schedule, alarm/event condition, or manually.
Trend curves	Historical trends and future forecasts to better manage demand, circuit loading, and other parameters. Provides average, min, max and standard deviation every hour for last 24 hours, every day for last month, every week for last 8 weeks and every month for last 12 months.
Waveform captures	Simultaneous capture of all voltage and current channels sub-cycle disturbance capture, maximum cycles is 100,000 (16 samples/cycle x 96 cycles, 10MBytes memory), max 256 samples/cycle.
Alarms	Threshold alarms: adjustable pickup and dropout setpoints and time delays, numerous activation levels possible for a given type of alarm, user-defined or automatic alarm threshold settings, user-defined priority levels (optional automatic alarm setting).

***(1)** All the communication ports may be used simultaneously.*

PM8000 series
Functions and characteristics (cont.)

Firmware characteristics (cont.)	
Advanced security	Up to 16 users with unique access rights. Perform resets, time sync, or meter configurations based on user privileges.
Memory	512MB (10MB for programming and interval logging).
Firmware update	Update via the communication ports.
Display characteristics	
Integrated or Remote display	320x240 (1/4 VGA) Colour LCD, configurable screens , 5 buttons and 2 LED indicators (alarm and meter status).
Languages	English, French, Spanish, Russian, Portugese,German, Italian, Chinese.
Notations	IEC, IEEE.
The HMI menu includes	
Alarms	Active alarms, historic alarms.
Basic Reading	Voltage, current, frequency, power summary.
Power	Power summary, demand, power factor.
Energy	Energy total, delivered, received.
Events	Timestamped verbose event log.
Power Quality	EN 50160, harmonics, phasor diagrams.
Inputs/Outputs	Digital inputs, digital outputs, analogue inputs, analogue outputs.
Nameplate	Model, serial and FW version.
Custom Screens	Build your own metrics.
Setup Menu	Meter setup, communications setup, display setup, date/time/clock setup, alarm setup, language setup, time of use setup, resets, password setup.

Schneider Electric Industries SAS
35, Rue Joseph Monier,
CS 30323
F - 92506 Rueil Malmaison Cedex

RCS Nanterre 954 503 439
Capital social 896 313 776
www.schneider-electric.com

As standards, specifications and designs develop from time to time, please ask for confirmation of the information given in this document.

Design: Schneider Electric
Photos: Schneider Electric

© 2015 - Schneider Electric - All rights reserved

PLSED310058EN

07-2015

THIS PAGE WAS INTENTIONALLY LEFT BLANK

Section 1—General Information

Introduction

PowerPact® M-frame, P-frame and R-frame and Compact® NS630b–NS3200 electronic trip molded case circuit breakers are designed to protect electrical systems from damage caused by overloads, short circuits, and ground faults. All circuit breakers are designed to open and close a circuit by nonautomatic means and to open the circuit automatically on a predetermined overcurrent. Electronic trip molded case circuit breakers use an electronic trip system to signal the circuit breaker to open automatically.

The PowerPact M-frame (800 A frame size), P-frame (1200 A frame size) and R-frame (2500 A frame size) circuit breakers are dual rated to UL489 and IEC 60947-2. The Compact NS630b–NS1600 (1600 A frame size) and NS1600b–NS3200 (3200 A frame) circuit breakers are rated to IEC 60947-2 only.

M-frame molded case circuit breakers are equipped with a basic ET1.0I electronic trip system, which has a fixed long-time (overload) setting and an adjustable instantaneous (short-circuit) trip setting. P-frame, R-frame and NS630b–NS3200 molded case circuit breakers are available with a basic ET 1.0I electronic trip system and with a more advanced Micrologic® trip system. Electronic trip motor circuit protectors (trip system ET 1.0M), which trip on short circuit only, and automatic molded case switches, which trip at a predetermined self-protection level only, are also available for special applications. All of these circuit breakers are available brand labeled as Square D, Merlin Gerin or Federal Pacific.

For information on other molded case circuit breakers manufactured by Square D, see the data bulletins *Thermal-Magnetic and Magnetic-Only Molded Case Circuit Breaker, Class 601* and *Electronic Trip Molded Case Circuit Breakers, Class 602*.

Features and Benefits

M-frame, P-frame, R-frame and NS630b–NS3200 electronic trip circuit breakers:

- Provide overload and short-circuit protection
- Are true RMS sensing devices
- Provide means to manually disconnect power to the circuit
- Provide enhanced coordination by their adjustability
- Provide high interrupting ratings and withstand ratings

Circuit breakers with Micrologic trip units can also:

- Provide integral equipment ground-fault protection or alarm
- Provide communications
- Provide power monitoring
- Provide protective relaying functions
- Provide zone-selective interlocking (ZSI), which can reduce damage in the event of a fault

Specifications

Electronic trip molded case circuit breakers have a molded case made of a glass-reinforced insulating material (thermal set composite resin) that provides high dielectric strength. These circuit breakers:

- Are available in either dual-rated UL/IEC or IEC-only constructions
- Dual-rated UL/IEC circuit breakers are also CSA and ANCE certified
- Are manufactured in unit-mount, I-Line® and drawout (P-frame and NS630b–NS1600) constructions
- Are available with either type ET or Micrologic electronic tripping systems
- Provide optional power monitoring, communications, protective relaying, integral ground-fault protection for equipment and zone-selective interlocking functions

© 2007 Schneider Electric All Rights Reserved

- Share common tripping of all poles
- Can be mounted and operated in any position
- Are equipped with an externally-accessible test port for use with hand-held and full-function test sets
- Are available in motor circuit protector and automatic molded case switch constructions
- Can be reverse connected, without restrictive LINE and LOAD markings
- Meet the requirements of NEC® Sections 240.6 by providing a means to seal the rating plug and trip unit adjustments

Codes and Standards

M-frame, P-frame, R-frame and NS630b–NS3200 electronic trip circuit breakers and switches are manufactured and tested in accordance with the following standards:

Table 1: Standards

M-Frame, P-Frame and R-Frame Circuit Breakers	P-Frame and R-Frame Switches	NS630b–NS3200 Circuit Breakers	NS630b–NS3200 Switches
UL 489[1] IEC Standard 60947-2 CSA 22.2 No 5-02 Federal Specification W-C-375B/GEN NEMA AB1 NMX J-266 UTE, VDE, BS, CEI, UNE	UL 489[2] IEC Standard 60947-3 CSA 22.2 No 5-02 Federal Specification W-C-375B/GEN NEMA AB1 NMX J-266 UTE, VDE, BS, CEI, UNE	IEC Standard 60947-2 Federal Specification W-C-375B/GEN NEMA AB1 UTE, VDE, BS, CEI, UNE	IEC Standard 60947-3 Federal Specification W-C-375B/GEN NEMA AB1 UTE, VDE, BS, CEI, UNE

1 PowerPact® M-frame circuit breaker is in UL File E10027.
PowerPact P-frame circuit breaker is in UL File E63335.
PowerPact R-frame circuit breaker is in UL FIle E10027.

2 PowerPact P-frame switch is in UL File E103740.
PowerPact R-frame switch is in UL FIle E33117.

Circuit breakers should be applied according to guidelines detailed in the National Electrical Code® (NEC®) and other local wiring codes.

Circuit Breaker Ratings

Interrupting Rating

The interrupting rating is the highest current at rated voltage the circuit breaker is designed to safely interrupt under standard test conditions. Circuit breakers must be selected with interrupting ratings equal to or greater than the available short-circuit current at the point where the circuit breaker is applied to the system (unless it is a branch device in a series rated combination). Interrupting ratings are shown on the front of the circuit breaker.

Table 2: UL/IEC Circuit Breaker Interrupting Ratings

Circuit Breaker	UL/CSA Rating (60 Hz)						IEC 60947-2 Rating (50/60 Hz)			
	3 Phase			Grounded B Phase			240 Vac		380/415 Vac	
	240 Vac	480 Vac	600 Vac	240 Vac 2P	240 Vac 3P	480 Vac 3P	Icu	Ics	Icu	Ics
MG	65 kA	35 kA	18 kA	65 kA	65 kA	35 kA	50 kA	25 kA	35 kA	20 kA
MJ	100 kA	65 kA	25 kA	65 kA	65 kA	35 kA	65 kA	35 kA	50 kA	25 kA
PG	65 kA	35 kA	18 kA	65 kA	65 kA	35 kA	50 kA	25 kA	35 kA	20 kA
PJ	100 kA	65 kA	25 kA	65 kA	100 kA	14 kA	65 kA	35 kA	50 kA	25 kA
PK	65 kA	50 kA	50 kA	65 kA	65 kA	35 kA	50 kA	25 kA	50 kA	25 kA
PL	125 kA	100 kA	—	65 kA	100 kA	14 kA	125 kA	65 kA	85 kA	45 kA
RG	65 kA	35 kA	18 kA	—	65 kA	35 kA	50 kA	25 kA	35 kA	20 kA
RJ	100 kA	65 kA	25 kA	100 kA	100 kA	35 kA	65 kA	35 kA	50 kA	25 kA
RK	65 kA	65 kA	65 kA	—	65 kA	35 kA	85 kA	65 kA	70 kA	55 kA
RL	125 kA	100 kA	50 kA	125 kA	125 kA	35 kA	125 kA	65 kA	85 kA	45 kA

© 2007 Schneider Electric All Rights Reserved

Table 3: IEC Only Circuit Breaker Interrupting Ratings (50/60 Hz)

Circuit Breaker	220/240 Vac		380/415 Vac		440 Vac		500/525 Vac		660/690 Vac	
	Icu	Ics	Icu	Ics	Icu	Ics	Icu	Ics	Icu	Ics
NS630b–NS1600 N Interrupting Rating	50 kA	75% Icu	50 kA	75% Icu	50 kA	75% Icu	40 kA	75% Icu	30 kA	75% Icu
NS630b–NS1600 H Interrupting Rating	70 kA	50% Icu	70 kA	50% Icu	65 kA	50% Icu	50 kA	50% Icu	42 kA	50% Icu
NS630b–NS1000 L Interrupting Rating	150 kA	100% Icu	150 kA	100% Icu	130 kA	100% Icu	100 kA	100% Icu	25 kA	100% Icu
NS1600b–NS3200 N Interrupting Rating	85 kA	75% Icu	70 kA	75% Icu	65 kA	100% Icu	65 kA	100% Icu	65 kA	100% Icu
NS1600b–NS3200 H Interrupting Rating	125 kA	75% Icu	85 kA	75% Icu	85 kA	75% Icu	—	—	—	—

Application Ratings

The voltage rating is the highest voltage for the electrical system on which the circuit breaker can be applied. The frequency rating indicates the system frequency for which the circuit breaker is intended. The withstand rating is used to improve system coordination by maximizing the current level at which the circuit breaker trips with no intentional delay. The withstand rating is the level of RMS symmetrical current that a circuit breaker can carry in a closed position for a stated period of time.

Table 4: Voltage, Frequency and Withstand Ratings

Circuit Breaker	Voltage Rating	Frequency Rating[1]	Withstand Rating at 480 Vac[2]
MG, MJ	600 Vac	60 Hz (UL), 50/60 Hz (IEC)	10 kA (0.5 sec)
PG, PK	600 Vac	60 Hz (UL), 50/60 Hz (IEC)	25 kA (0.5 sec)
PJ	600 Vac	60 Hz (UL), 50/60 Hz (IEC)	10 kA (0.5 sec)
PL	480 Vac	60 Hz (UL), 50/60 Hz (IEC)	10 kA (0.5 sec)
R-frame (RG, RJ, RK, RL)	600 Vac	60 Hz (UL), 50/60 Hz (IEC)	32 kA (3 sec)
NS630b–NS1600 N interrupting rating	690 Vac	50/60 Hz (IEC)	25 kA (0.5 sec)
NS630b–NS1600 H interrupting rating	690 Vac	50/60 Hz (IEC)	25 kA (0.5 sec)
NS630b–NS1000 L interrupting rating	690 Vac	50/60 Hz (IEC)	10 kA (0.5 sec)
NS1600b–NS3200 N interrupting rating	690 Vac	50/60 Hz (IEC)	32 kA (3 sec)
NS1600b–NS3200 H interrupting rating	440 Vac	50/60 Hz (IEC)	32 kA (3 sec)

[1] May also be used at 400 Hz with derating, see data bulletin *Determining Current-Carrying Capacity in Special Applications*.

[2] A system coordination study should be done for optimum circuit breaker coordination.

Ampere Rating (Continuous Current Rating)

The ampere rating (or continuous current rating) (Ir) is the maximum current that a circuit breaker can carry. The sensor size (In) is the maximum ampere rating for a specific circuit breaker and is based on the size of the sensor plug inside the circuit breaker (sensor plugs are an integral part of the circuit breaker and cannot be removed or replaced). This value is printed below the trip unit on the sensor plug.

NOTE: The maximum ampere rating a circuit breaker family can carry is called the frame size. Sensor size is less than or equal to frame size.

The ampere rating of a type ET electronic trip circuit breaker is equal to the current sensor size (In).

The ampere rating of a Micrologic® electronic trip circuit breaker is determined by the mathematical equation:

Ampere Rating = Sensor Size x Rating Plug Setting (Ir = In x Rating Plug Setting)

The rating plug varies the circuit breaker ampere rating as a function of its sensor size. Rating plugs have nine dial settings; the multiplier values corresponding with each setting are printed on the rating plug. The maximum setting range is 0.4–1.0 x In.

© 2007 Schneider Electric All Rights Reserved

Enclosure Sizes

All ET electronic trip UL/IEC M-frame, P-frame and R-frame circuit breakers are available as standard rated circuit breakers. Micrologic electronic trip UL/IEC circuit breakers are also available in 100% rated constructions. Because the additional heat generated when applying circuit breakers at 100% of continuous current rating, the use of specially designed enclosures and 90°C (194° F) rated wire sized per the 75°C (167° F) NEC chart is required

Circuit breakers with 100% rating can also be used in applications requiring only 80% continuous loading.

Table 5: Minimum Enclosure Sizes for Fixed-Mounted Circuit Breakers

Circuit Breaker Rating	Enclosure Dimensions (h x w x d) in/[mm]		Ventilation Area			
	3P Circuit Breaker	4P Circuit Breaker	Top		Bottom	
M-Frame, ≤ 800 A, Standard Rated	51.9 x 20.25 x 7.75 [1318.3 x 514.4 x 196.9]	51.9 x 23.01 x 7.75 [1318.3 x 584.4 x 196.9]	—	—	—	—
P-Frame, ≤ 800 A, 100% Rated P-Frame, ≤ 1200 A, Standard Rated	51.9 x 20.25 x 7.75 [1318.3 x 514.4 x 196.9]	51.9 x 23.01 x 7.75 [1318.3 x 584.4 x 196.9]	—	—	—	—
P-Frame, > 1200 A, 100% Rated	62.25 x 23 x 14.75 [1581.2 x 584.2 x 374.7]	62.25 x 25.76 x 14.75 [1581.2 x 654.2 x 374.7]	16.5 $in.^2$	10,645 mm^2	16.5 $in.^2$	10,645 mm^2
R-Frame, Standard Rated[1]	30 x 21 x 7 [762 x 533 x 178]	30 x 25.5 x 7 [762 x 648 x 178]	—	—	—	—
R-Frame, 100% Rated[1]	30 x 21 x 7 [762 x 533 x 178]	30 x 25.5 x 7 [762 x 648 x 178]	40.25 $in.^2$	26,000 mm^2	40.25 $in.^2$	26,000 mm^2

[1] RLTB or RL3TB kits may extend beyond end of enclosure when using minimum enclosure size.

Operating Conditions

Temperature

To meet the requirements of the UL489 Standard, molded case circuit breakers are designed, built and calibrated for use on 50/60 Hz ac systems in a 40°C (104°F) ambient environment. Electronic trip circuit breakers, however, are designed to react only to the magnitude of the current flowing through the circuit breaker and are inherently ambient insensitive. Both UL/IEC and IEC-only circuit breakers may be operated at temperatures between -25°C and +70°C (-13°F and158°F). For temperatures other than 40°C (104°F), the circuit breakers must be re-rated as shown.

Table 6: Temperature Rerating Values per ANSI C37.20.1

Maximum Ambient Temperature											
°F	140	122	**104**	86	77	68	50	32	14	-4	-22
°C	60	50	**40**	30	25	20	10	0	-10	-20	-30
Current	0.83	0.92	**1.00**	1.07	1.11	1.14	1.21	1.27	1.33	1.39	1.44

Altitude

CIrcuit breakers are suitable for use at altitudes up to 13,100 ft. (4000 m). For altitudes higher than 6560 ft. (2000 m), circuit breakers must be derated as shown.

Table 7: Altitude Rerating Values Per ANSI C37.20.1 Table 10

Altitude	≤ 6,600 ft. (≤ 2,000 m)	8,500 ft. (2,600 m)	13,000 ft. (3,900 m)
Voltage	1.00	0.95	0.80
Current	1.00	0.99	0.96

© 2007 Schneider Electric All Rights Reserved

Extreme Atmospheric Conditions

PowerPact® circuit breakers have successfully passed the tests defined below for extreme atmospheric conditions.

Dry cold and dry heat:

- IEC 68-2-1—Dry cold at -55°C
- IEC 68-2-2—Dry heat at +85°C

Damp heat (tropicalization)

- IEC 68-2-30—Damp heat (temperature 55°C and relative humidity of 95%)
- IEC 68-2-52 level 2—Salt mist

The materials used in the PowerPact circuit breakers will not support the growth of fungus and mold.

Vibration


PowerPact circuit breakers meet IEC 60068-2-6 Standards for vibration.

- 2 to 13.2 Hz and amplitude 0.039 in. (1 mm)
- 13.2 to 100 Hz constant acceleration

Storage Temperature

Circuit breakers with trip units without LCD displays may be stored in the original packaging at temperatures between -58°F (-50°C) and 185°F (85°C). For circuit breakers with trip units with LCD displays, this range is -40°F (-40°C) to 185°F (85°C).

Trip System



ET
Electronic
Trip Unit

Micrologic
Electronic
Trip Unit

The trip system causes the circuit breaker to open automatically under overload, short-circuit or equipment ground-fault conditions. Electronic trip circuit breakers give the customer more versatility to achieve coordination with features such as adjustable instantaneous pickup and high withstand ratings.

The ET and Micrologic trip systems consist of current sensors, a microprocessor-based trip unit, and a tripping coil. The tripping coil is a flux transfer solenoid that requires no external power source. All ET and Micrologic protective functions are completely fault powered.

Micrologic Trip System

Features found in Micrologic® electronic trip circuit breakers, such as universally interchangeable rating plugs, adjustable long-time pickups and 100% ratings also provide capacity for future growth.

The integral equipment ground-fault sensing capabilities available with Micrologic trip systems mean that there are fewer parts and pieces to purchase, mount and wire. These capabilities include integral ground-fault protection for equipment, which causes the circuit breaker to trip when a ground fault is detected, as well as integral ground-fault alarm, which does not trip the circuit breaker but sends an alarm when a ground fault is detected.

Certain Micrologic trip systems also offer the customer true power management system solutions through communication. These trip units can communicate with other circuit breakers in the system and also with a power monitoring system. Communication is by Modbus® and does not require proprietary software.

Communication between trip units allows zone-selective interlocking (ZSI) between circuit breakers at different levels in the system. ZSI reduces fault stress by allowing the upstream circuit breaker closest to the fault to ignore its preset delay time and trip without any intentional delay on a short circuit or ground fault. For more information on ZSI, see data bulletin *Reducing Fault Stress with Zone-Selective Interlocking.*

© 2007 Schneider Electric All Rights Reserved

Communication with a power monitoring system through a communications network allows a ground fault to be reported without interrupting power to the system. It also allows the power monitoring system to remotely report power usage, current flow, and trip history.

Instantaneous OFF Feature

Micrologic® 5.0 and 6.0 Standard, A, P and H electronic trip units provide the unique ability to turn the instantaneous tripping function OFF. Turning off the instantaneous trip function increases the current level at which the circuit breaker will trip with no intentional delay to the level of the short-time withstand rating. This current level is typically much higher than any of the pickup levels provided by the adjustable instantaneous feature. Therefore, using the instantaneous OFF feature improves coordination by allowing the user to take advantage of the circuit breaker withstand rating.

Motor Circuit Protectors

An instantaneous trip version of the electronic trip circuit breaker is also available for motor circuit protection. These motor circuit protectors comply with NEC requirements for providing short-circuit protection when installed as part of a Listed combination controller having motor overload protection.

Electronic trip motor circuit protectors are similar in construction to ET electronic trip circuit breakers.They are designed as disconnect devices for use in combination with motor starters. These motor circuit protectors provide short-circuit protection only and have an adjustable amperage pickup so they can be set to open instantaneously at current values slightly above the motor starting inrush current. This setting coordinates the pickup time-current response of the motor circuit protector with the overload relay of the motor starter to give the best possible protection.

Current interrupting ratings for these UL Recognized components are established in combination with motor starters and properly-sized overload relays and contactors.

Automatic Molded Case Switches

P-frame, R-frame and NS630b–NS3200 circuit breakers are also available in automatic molded case switch construction. Automatic switches are similar in construction to electronic trip circuit breakers, except that the switches open instantaneously at a factory-set non-adjustable trip point calibrated to protect only the molded case switch itself. Because of their molded case construction, they are more compact than conventional disconnect switches and accept electrical accessories for added flexibility.

Molded case switches are intended for use as disconnect devices only. UL489 requires molded case switches to be protected by a circuit breaker or fuse of equivalent rating. Molded case switches are labeled with their appropriate withstand ratings. The withstand rating of a switch is defined as the maximum current at rated voltage that the molded case switch will withstand without damage when protected by a circuit breaker with an equal continuous current rating.

Table 8: P-, and R-Frame Withstand Ratings[1]

Voltage	Interrupting Rating			
	G	J	K	L
240 Vac	65 kA	100 kA	65 kA	125 kA
480 Vac	35 kA	65 kA	50 kA	100 kA
600 Vac	18 kA	25 kA	50 kA	50 kA

[1] The withstand rating is the fault current at rated voltage that the molded case switch will withstand without damage when protected by a circuit breaker with an equal continuous current rating.

© 2007 Schneider Electric All Rights Reserved

Internal Operating Mechanism

Manually-Operated Circuit Breakers

M-frame, P-frame, R-frame and NS630b–NS3200 manually-operated circuit breakers have a single operating handle that acts directly through the operating mechanism against the contact blades. Multi-pole circuit breakers have a common trip bar for positive action of all poles on manual and automatic operation. These circuit breakers have a trip-free mechanism that allows them to trip even though the operating handle may be restricted (by a handle operating mechanism or padlock attachment) in the I/ON position. If not restricted, the operating handle moves to a position between I/ON and O/OFF when the circuit breaker is tripped.

The face of the manually-operated circuit breakers is marked with standard ON/OFF and international I/O markings to indicate handle position. In addition, the I/OFF portion of the circuit breaker handle is color coded green.

Electrically-Operated Circuit Breakers

P-frame and NS630b–NS1600 circuit breakers are also available with a two-step stored-energy mechanism which can be charged manually or using a motor. The closing time is less than five cycles. Closing and opening operations can be initiated by remote control or by push buttons on the front cover. An O-C-O (open-close-open) cycle is possible without recharging.

The face of electrically-operated circuit breakers is also marked ON/OFF and I/O, and equipped with a position indicator to show contact position.

Push-to-Trip Button

The push-to-trip button located on the face of each manually-operated circuit breaker is a standard feature on these circuit breakers. This allows the user to manually trip the circuit breaker without risking exposure to live parts. During normal on-off operation, the handle opens and closes the circuit breaker contact but does not exercise the tripping mechanism.

Use the push-to-trip button to:

- Exercise the circuit breaker mechanism
- Check the auxiliary and alarm switch circuits

Circuit Breaker Mounting and Connections

Unit-Mount Circuit Breakers

Table 9: Circuit Breaker Mounting and Connections

Circuit Breaker	Unit-mount Construction		I-Line® Construction	Drawout Construction
	Cable Connection	Bus Connection		
M-Frame	X	X	X	—
P-Frame	X	X	X	X
R-Frame	X[1]	X	X[2]	—
NS630b–NS1250	X	X	—	—
NS1600–NS3200	—	X	—	—

1 Must use RLTB terminal pad kit

2 Through 1200 A, 100% rated only

Fixed-mounted M-frame, P-frame, R-frame and NS630b–NS3200 individually-mounted circuit breakers are supplied with four mounting screws. These mounting screws are inserted through mounting holes molded into the circuit breaker case and threaded into the circuit breaker mounting enclosure. To properly support the circuit breaker, all four mounting screws must be used.

© 2007 Schneider Electric All Rights Reserved

Unit-mount M-frame, P-frame and NS630b–NS1250 circuit breakers can be ordered with mechanical line and load side lugs. The standard lugs can be removed for the installation of compression-type lugs or bus connections. All lugs are UL Listed for their proper application and marked for use with aluminum and copper (Al/Cu) or copper only (Cu) conductors. Lugs suitable for copper and aluminum conductors are made of tin-plated aluminum. Lugs suitable for use with copper conductors only are made of copper.

See individual frame sections for frame-specific connection information.

I-Line® Circuit Breakers

M-frame circuit breakers through 800 A and P-frame and R-frame circuit breakers through 1200 A are available in I-Line construction for easy installation and removal in I-Line panelboards and switchboards. I-Line circuit breakers use “blow-on” type line side connectors. In case of a short circuit, increased magnetic flux causes the plug-on connectors of the circuit breaker to tighten their grasp on the panelboard or switchboard bus bars. The I-Line connectors and circuit breaker mounting bracket are integral parts of I-Line circuit breakers and cannot be removed or replaced. I-Line circuit breakers come with mechanical load side lugs.

Drawout Circuit Breakers

P-frame manually-operated circuit breakers and switches are also available in drawout construction. The drawout assembly mechanism allows the circuit breaker to be racked in four positions (connected, test, disconnect or withdrawn).

P-frame cradles are ordered separately and are available with factory and field-installed accessories. See Section 8—Accessories for details.

Catalog Numbering System

The M-frame, P-frame, R-frame and NS630b–NS3200 circuit breakers and cradles follow a “smart” catalog numbering system. The following tables are intended as a tool to decipher existing catalog numbers. **They are not intended for use in building catalog numbers, as some combinations may not be available.** To build a catalog number, please see the *Digest*, the product selector or contact the local field office.

M-Frame, P-Frame and R-Frame Circuit Breaker Catalog Numbers

Table 10: Catalog Number for M-Frame, P-Frame and R-Frame (UL/IEC Dual-rated) Circuit Breakers

Field Position	Field Description	Options	Description
1	Brand Name	(blank)	Square D®
		N	Merlin Gerin®
		F	Federal Pioneer®
		P	Federal Pacific®
2	Circuit Breaker Frame	M	800 A Max.
		P	1200 A Max.
		R	3000 A Max.
3	Interrupting Rating	G	35 kA @ 480 Vac
		J	65 kA @ 480 Vac
		K[1]	P-Frame: 50 kA @ 600 Vac R-Frame: 65 kA @ 600 Vac
		L[1]	100 kA @ 480 Vac

Continued on next page

© 2007 Schneider Electric All Rights Reserved

Table 10: Catalog Number for M-Frame, P-Frame and R-Frame (UL/IEC Dual-rated) Circuit Breakers *(continued)*

Field Position	Field Description	Options	Description
4	Connection	F	No Lugs
		L	Lugs on Both Ends
		M	Lugs on I/ON End
		P	Lugs on O/OFF End
		A	I-Line
		D[1]	Drawout
5	Poles	2	2P
		3	3P
		4[1]	4P
6	Voltage Rating	4	480 V
		6	600 V
7–9	Ampere Rating	###	Circuit Breaker Rating
		000[1]	Automatic Switch Value
10	Standard or 100% Rated	(none)	Standard Rated
		C[1]	100% rated
11–14	Circuit Breaker Trip System	(none)	ET1.0 (M-Frame)
		(none)	ET1.0I (P-Frame, R-Frame)
		U31[1]	Micrologic® 3.0 Trip Unit
		U33[1]	Micrologic 5.0 Trip Unit
		U41[1]	Micrologic 3.0A Trip Unit
		U43[1]	Micrologic 5.0A Trip Unit
		U44[1]	Micrologic 6.0A Trip Unit
		U63[1]	Micrologic 5.0P Trip Unit
		U64[1]	Micrologic 6.0P Trip Unit
		U73[1]	Micrologic 5.0H Trip Unit
		U74[1]	Micrologic 6.0H Trip Unit
	Automatic Switch Trip System	S60[1]	600 A
		S80[1]	800 A
		S10[1]	1000 A
		S12[1]	1200 A
		S16[1]	1600 A
		S20[1]	2000 A
		S25[1]	2500 A
	Motor Circuit Protector Trip System	M68[1]	1200–9600 A
		M69[1]	1500–9600 A
		M70[1]	1800–9600 A
15	Rating Plug	A–H[1]	See Table 66
16-17	Modbus® Communication	E1[1]	Modbus BCM
18	I-Line® Phasing	See *Digest, Product Selector*	
For Factory-Installed Accessories, See *Product Selector*			

[1] Not available on M-frame circuit breakers.

© 2007 Schneider Electric All Rights Reserved

- *Dielectric Withstand*—the circuit breaker is subjected to twice the voltage rating at which the interrupting test was conducted, but not less than 900 V.

  Between line and load terminals with the circuit breaker in the tripped and in the OFF positions.

  Between terminals of opposite polarity with the circuit breaker closed.

  Between live parts and the overall enclosure with the circuit breaker both open and closed.

When the sample circuit breakers pass these tests, circuit breakers of the same construction can be marked or labeled with the current interrupting rating for the higher fault currents.

IEC Requirements

The IEC markings on a circuit breaker indicates that the circuit breaker meets the requirements of IEC Standard 60947-2 for circuit breakers and 60947-3 for automatic switches. These requirements include the following tests:

Table 14: IEC Test Sequence

Sequence	Category of Devices	Tests
General Performance Characteristics (Sequence 1)	All Circuit Breakers	• Tripping Limits and Characteristics • Dielectric Properties • Mechanical and Electrical Endurance • Overload • Dielectric Voltage Withstand • Temperature Rise • 145% Calibration (3 Poles in Series or 3-Phase Test)
Rated Service Short-circuit Breaking Capacity (Ics) (Sequence 2)	All Circuit Breakers	• Rated service short circuit breaking capacity (O-t-CO-t-CO) • Electrical Endurance (5% of with Current Operations of Sequence 1) • Dielectric Voltage Withstand • Temperature Rise • 145% Calibration (3 poles in series or 3-phase test)
Rated Ultimate Short-circuit Breaking Capacity (Icu) (Sequence 3)	Circuit Breakers of Utilization Category A Circuit Breakers of Utilization Category B	• 200% Calibration (Each Pole Separately) • Rated Ultimate Short Circuit Breaking Capacity (O-t-CO) • Dielectric Voltage Withstand • 250% Calibration (Each Pole Separately)
Rated Short-time Withstand Current (Icw) (Sequence 4)	Circuit Breakers of Utilization Category B	• 200% Calibration (Each Pole Separately) • Rated Short-Time Withstand Current • Temperature Rise • Short-Circuit Breaking Capacity at Maximum Short-Time Withstand Current (O-t-CO) • Dielectric Voltage Withstand • 200% Calibration (Each Pole Separately)
Combined Sequence	Circuit Breakers of Utilization Category B: When Icw = Ics Replaces Sequences 2 and 4 When Icw = Ics = Icu Replaces Sequences 2, 3 and 4	• 200% Calibration (Each Pole Separately) • Rated Short-Time Withstand Current Icw • Rated Service Short-Circuit Breaking Capacity at Ics (O-CO-CO) at Maximum Relay Temp. • 145% Calibration (3 Poles in Series or 3-Phase Test) • Dielectric Voltage Withstand • Temperature Rise • 200% Calibration (Each Pole Separately)
Individual Pole Short-Circuit Test Sequence (Annex H)	Circuit Breakers for Use in IT Systems	• Individual Pole Short-Circuit Breaking Capacity • Dielectric Voltage Withstand • 250% Calibration (Each Pole Separately)

© 2007 Schneider Electric All Rights Reserved

Continuous Current Rating

All circuit breakers marked as 100% rated can be continuously loaded to 100% of their rating.

Because of additional heat generated when applying circuit breakers at 100% of continuous current rating, the use of specially-designed enclosures and 90°C (194°F) wire is required. The 90°C (194°F) wire must be sized according the ampacity of the 75°C (167°F) wire column in the NEC. Minimum enclosure size and ventilation specifications are indicated on the circuit breaker and in it's instruction bulletin and in Section 1.

Circuit breakers with 100% rating can also be used in applications requiring only 80% continuous loading.

Interrupting Ratings

Table 42: Interrupting Ratings

Mounting	Circuit Breaker	Ampere Rating (A)		Interrupting Ratings						
		Basic Electronic Trip Units	Micrologic® Trip Units	UL/CSA/NMX			IEC 60947-2			
							240 Vac		380/415 Vac	
				240 Vac	480 Vac	600 Vac	Icu	Ics	Icu	Ics
Individually-Mounted	PG	600, 800, 1000, 1200	250, 400, 600, 800, 1000, 1200	65 kA	35 kA	18 KA	50 kA	25 kA	35 kA	20 kA
	PJ			100 kA	65 kA	25 kA	65 kA	35 kA	50 kA	25 kA
	PK			65 kA	50 kA	50 KA	50 kA	25 kA	50 kA	25 kA
	PL			125 kA	100 kA	—	125 kA	65 kA	85 kA	45kA
I-Line®	PG	600, 700, 800, 900, 1000, 1200	250, 400, 600, 800, 1000, 1200	65 kA	35 kA	18 KA	50 kA	25 kA	35 kA	20 kA
	PJ			100 kA	65 kA	25 kA	65 kA	35 kA	50 kA	25 kA
	PK			65 kA	50 kA	50 KA	50 kA	25 kA	50 kA	25 kA
	PL			125 kA	100 kA	—	125 kA	65 kA	85 kA	45 kA

Automatic Molded Case Switches

Automatic molded case switches are available in individually-mounted and I-Line constructions from 600–1200 A. Automatic switches are similar in construction to electronic trip circuit breakers except that long-time tripping is not present. The switches open instantaneously at a non-adjustable magnetic trip point calibrated to protect only the molded case switch itself. They must be used in conjunction with a circuit breaker or fuse of equivalent rating.

Table 43: Automatic Switch Information

Circuit Breaker	Ampere Rating	Voltage Rating	Catalog Number	Withstand Rating			Trip Point (±10%)
				240 Vac	480 Vac	600 Vac	
PJ 2P[1], 3P	600	600 Vac	PJL36000S60	100 kA	65 kA	25 kA	10 kA
	800	600 Vac	PJL36000S80	100 kA	65 kA	25 kA	10 kA
	1000	600 Vac	PJL36000S10	100 kA	65 kA	25 kA	10 kA
	1200	600 Vac	PJL36000S12	100 kA	65 kA	25 kA	10 kA
PL 2P, 3P	600	480 Vac	PLL34000S60	125 kA	100 kA	—	10 kA
	800	480 Vac	PLL34000S80	125 kA	100 kA	—	10 kA
	1000	480 Vac	PLL34000S10	125 kA	100 kA	—	10 kA
	1200	480 Vac	PLL34000S12	125 kA	100 kA	—	10 kA
PK 2P, 3P	600	600 Vac	PKL36000S60	65 kA	50 kA	50 kA	24 kA
	800	600 Vac	PKL36000S80	65 kA	50 kA	50 kA	24 kA
	1000	600 Vac	PKL36000S10	65 kA	50 kA	50 kA	24 kA
	1200	600 Vac	PKL36000S12	65 kA	50 kA	50 kA	24 kA

[1] For 2P, replace the leading 3 in the catalog number following the prefix with a 2 (PJL36000S60 becomes PJL26000S60).

© 2007 Schneider Electric All Rights Reserved

THIS PAGE WAS INTENTIONALLY LEFT BLANK

Micrologic trip units

The full range of PowerPact circuit breakers now feature Micrologic electronic trip units (energy model). Micrologic trip units are the intelligence behind a coordinated electrical distribution system that delivers improved operating efficiency and extended equipment life. All Micrologic trip units provide impeccable, electronic circuit protection with adjustable protection settings for maximum system coordination and flexibility. Sophisticated functionality, such as energy and power quality metering capabilities, is integrated in the more advanced trip units. Combined with quality PowerPact accessories, Micrologic trip units also enable circuit breakers to be networked and remotely controlled leading to substantial savings in electrical system operating costs. These interchangeable, microprocessor controlled devices provide the new generation of protection, measurement and control functions, delivering not only greater electrical system safety but also improved system integration and coordination.



Micrologic P trip unit for PowerPact P and R



Micrologic H trip unit for PowerPact P and R



Micrologic E trip unit for PowerPact P and R



Standard Micrologic trip unit for PowerPact H, J, and L



Ammeter or Energy trip unit for Powerpact H, J and L

Simple: an easy installation and use

Choose the model that meets your needs

The Micrologic trip unit family includes five models with varying levels of functionality. The simplest units provide basic overcurrent protection including long-time, instantaneous, and optional short-time adjustments for overloads and short circuits. Advanced units offer sophisticated functions such as ground fault protection and zone selective interlocking. They also incorporate a variety of communications options and energy metering capabilities – right inside the circuit breaker. With advanced trip units, use a network to communicate breaker information, gather power information and energy usage patterns, monitor events, and remotely control breakers for increased efficiency and savings. The breakers become part of an integrated, coordinated electrical system. For maximum flexibility in product selection, Micrologic trip units consist of five models with progressively increasing levels of functionality.

Choose the right model for each application

PowerPact H-, J- and L-Frame	Standard (S)	Ammeter (A)	Energy (E)		
15 – 600 A					
PowerPact P- and R-Frame	**Standard (S)**	**Ammeter (A)**	**Energy (E)**	**Power (P)**	**Harmonic (H)**
up to 3000 A					

Adj. protections True RMS Thermal imaging	Current meter LED trip ind. ZSI	Power and energy meter	Frequency Power factor	Total harmonic distortion


Motor protection trip units

Also available are Micrologic trip units dedicated to managing motor applications at 600 A or below. Three levels of functionality are available with the motor trip unit offer.

- **1.3M:** Provides cable protection for short-circuits, and must be combined with an external thermal protection relay. This trip unit features an adjustable short-circuit protection threshold and fixed instantaneous protection.
- **2 M:** Provides thermal relay type protection in addition to short-circuit protection. Adjustable settings are included for the thermal protection threshold, the tripping class, and the short-circuit protection. Additional protections include phase unbalance and phase loss protection.
- **6 E-M:** Provides the same protection functions as the Micrologic 2-M units with the addition of ground fault, locked rotor protection, under-load protection and long start protection. They also incorporate energy metering and maintenance indicators similar to the Micrologic Energy trip unit.

Mounting dimensions

Common mounting dimensions across the entire range means that the mounting pattern never has to change even when panel designs change.



H-Frame and a J-Frame PowerPact circut breaker.


Choice of terminal options

Terminal options include unique snap-in lugs that make converting between bus bar and lug options easy. If the application calls for lugs on the line side, load side or both, conversions are simple, making the PowerPact H- and J-Frame circuit breakers ideal for applications that require configuring products at the point of use.

The terminal nut or mechanical lug is set on a plastic retainer that slides and snaps into place. Making it possible to easily convert to a distrubution lug that provides multiple cable outputs for downstream components.



Bus bar option



Lug option

PowerPact H- and J-Frame with Micrologic circuit breakers – 15 A to 250 A

Well-suited to a wide range of applications, the Powerpact H- and J-Frame molded case circuit breakers feature a full complement of field installable accessories, field installable trip units, and improved interrupting ratings. These molded case circuit breakers deliver unmatched design flexibility and share identical mounting holes, handle locations, trim dimensions, and accessories, allowing customers to standardize equipment designs for 15 A to 250 A applications.

PowerPact H- and J-Frame circuit breakers come in many interruption ratings and are designed to limit let-through currents to provide better protection for downstream components. Interrupting ratings (AIR) include D-18 kA, G-35 kA, J-65 kA and L-100 kA at 480 Vac. Available as standard or 100% rated circuit breakers, the H-Frame ranges from 15 A to 150 A and the J-Frame from 70 A to 250 A.

Available trip units:

- **Thermal magnetic:** Circuit protection provided by individual thermal (overload) and magnetic (short circuit) sensing elements in each pole.
- **Standard electronic:** Adjustable overcurrent protection including long-time, instantaneous, and optional short-time.
- **Ammeter:** Adjustable long-time, short-time, instantaneous and optional ground fault protection is coupled with integrated current metering and maintenance indicators.
- **Energy:** Power and energy metering is integrated with exceptional long-time, short-time, instantaneous, and optional ground fault protections. Beyond energy metering, this trip unit delivers many advanced functions including power quality (harmonics) measurement.

PowerPact L-Frame with Micrologic circuit breaker – 70 A to 600 A

Designed to accept common accessories and the full range of electronic trip options available for PowerPact H- and J-Frame, the newest addition to the PowerPact family of molded case circuit breakers delivers the same impeccable protection and flexibility. PowerPact L-Frame is also available as standard or 100% rated, and has a choice of many interruption ratings to support different application needs. Interrupting ratings (AIR) include D-18 kA, G-35 kA, J-65 kA and L-100 kA at 480 Vac.

Available trip units:

- **Standard electronic:** Adjustable overcurrent protection including long-time, instantaneous, and optional short-time.
- **Ammeter:** Adjustable long-time, short-time, instantaneous, and optional ground fault protection is coupled with integrated current metering and maintenance indicators.
- **Energy:** Power and energy metering is integrated with exceptional long-time, short-time, instantaneous, and optional ground fault protections. Beyond energy metering, this trip unit delivers many advanced functions including power quality (harmonics) measurement.

PowerPact P- and R-Frame with Micrologic circuit breakers – 100 A to 3000 A

The compact P- and R-Frame circuit breakers permit smaller footprint and higher density installations. These circuit breakers are available in standard and 100% rated construction up to 3000 A to meet a broad range of commercial and industrial application needs. Common accessories make stocking and installation easy.

Built-in Modbus™ protocol provides an open communications platform and can be combined with a selection of four interchangeable Micrologic trip units.

- **Standard:** Adjustable overcurrent protection including long-time, instantaneous, and optional short-time.
- **Ammeter:** Adjustable long-time, short-time, instantaneous, and optional ground fault protection is coupled with integrated current metering and an optional Modbus communication interface.
- **Power:** Combines power monitoring and metering functions, with long-time, short-time, instantaneous/optional ground fault adjustments, and advanced relay functions, and has a standard Modbus communication interface.
- **Harmonics:** All of the functionality of the Power trip unit, plus enhanced monitoring and metering capabilities, basic power quality (harmonics) measurement, and waveform capture.



PowerPact L-Frame with Micrologic




PowerPact P-Frame with Micrologic




PowerPact R-Frame with Micrologic

THIS DOCUMENT HAS BEEN REDACTED FROM A LARGER DOCUMENT (DOC# 0600BR1101 PUBLISHED SEPTEMBER 2011)



PANELBOARDS



BILL OF MATERIALS AND DRAWINGS

Q2C Number: 41753775	**Quote Number:** 2	**Revision Number:** 1
Project Name: IQALUIT WASTE WATER TREATMENT UPGR		**Quote Name:**

Item No.	Qty.	Catalog Number / Details

PANELBOARDS

002-00 1

Designation: CDP-1
NQ ML PNLB (INT,BOX,FRT)
NQ Panelboard
Consisting of
208Y/120V 3Ph 4W 60Hz SCCR: 22kA
Fully Rated
SPD 120kA per Phase/60kA per Mode
SPD line to grd protect
w/SPD Surge Counter
w/SPD Dry Contacts
Main Lug Only: 400A
Incoming Conductors: 1 - 1/0 - 750, (2) 1/0 - 350 kcmil
Bus: Copper: Silver/Tin Plated
CU Ground Bar
30 Circuit Interior
Type 2 (Driphood)Box: 50H x 20W x 5.75D
Incoming: Bottom Trim: Surface with Door
Box Cat No: MH50H Front Cat No: NC50VS
Ref. Drawing: PBA709A
Feeders:
4 - 100A/3P QOB-VH
1 - 30A/3P QOB-VH SPD DISC
1 - 15A/3P QOB-VH HPL
Optional Features:
Ship Completely Assembled,Copper Solid Neutral,Drip Hood,Seismic Qualification - IBC/ASCE7/CBC/NBCC,SPD Model BIA,Copper Ground Bar

003-00 1


Designation: 2A
NQ ML PNLB (INT,BOX,FRT)
NQ Panelboard
Consisting of
208Y/120V 3Ph 4W 60Hz SCCR: 10kA
Fully Rated
Main Lug Only: 225A
Incoming Conductors: 1 - #6 - 350 kcmil
Bus: Copper: Silver/Tin Plated
CU Ground Bar
72 Circuit Interior
Type 2 (Driphood)Box: 44H x 20W x 5.75D
Incoming: Bottom Trim: Surface with Door
Box Cat No: MH44H Front Cat No: NC44S
Ref. Drawing: PBA701A
Feeders:
6 - 15A/3P QOB-VH
1 - 15A/2P QOB
23 - 15A/1P QOB-VH
17 - 15A/1P QOB Prepared Space
Optional Features:
Ship Completely Assembled,Copper Solid Neutral,Drip Hood,Seismic Qualification - IBC/ASCE7/CBC/NBCC,Copper Ground Bar

Q2C Number: 41753775 **Quote Number:** 2 **Revision Number:** 1

Project Name: IQALUIT WASTE WATER TREATMENT UPGR **Quote Name:**


Item No.	Qty.	Catalog Number / Details
004-00	1	**Designation:** 2C NQ ML PNLB (INT,BOX,FRT) NQ Panelboard Consisting of 208Y/120V 3Ph 4W 60Hz SCCR: 10kA Fully Rated Main Lug Only: 100A Incoming Conductors: 1 - #6 - 2/0 AWG Bus: Copper: Silver/Tin Plated CU Ground Bar 42 Circuit Interior Type 2 (Driphood)Box: 38H x 20W x 5.75D Incoming: Bottom Trim: Surface with Door Box Cat No: MH38H Front Cat No: NC38S Ref. Drawing: PBA701A Feeders: 1 - 25A/2P QOB 2 - 15A/2P QOB 25 - 15A/1P QOB 11 - 15A/1P QOB Prepared Space Optional Features: Ship Completely Assembled,Copper Solid Neutral,Drip Hood,Seismic Qualification - IBC/ASCE7/CBC/NBCC,Copper Ground Bar

REV	DESCRIPTION	BY	DATE				
—	————	——	——/——	—	————	——	——/——




TYPICAL BOX WITH INTERIOR


TYPICAL BOX SIDE VIEW



TYPICAL FRONT



ENDWALL WITH KNOCKOUTS
(OTHER ENDWALL IS BLANK)



TYPICAL MOUNTING OF QO, QOB BREAKERS

DUAL DIMENSIONS: INCHES / MILLIMETERS

MAXIMUM MAIN LUGS AMPERE RATING	MAXIMUM NUMBER OF CIRCUITS	H		A		B	
		IN	MM	IN	MM	IN	MM
100A	18	26.00	660	21.00	533	11.00	279
	30	32.00	813	27.00	686	15.00	381
225A	30	32.00	813	27.00	686	15.00	381
	42 & 54	38.00	965	33.00	838	15.00	381
	72	44.00	1118	39.00	991	15.00	381
	84	50.00	1270	45.00	1143	15.00	381
100A WITH SUB FEED LUGS OR FEED THRU LUGS	18	26.00	660	21.00	533	15.00	381
	30	32.00	813	27.00	686	15.00	381
225A WITH SUB FEED LUGS	30	38.00	965	33.00	838	15.00	381
	42 & 54	44.00	1118	39.00	991	15.00	381
	72	50.00	1270	45.00	1143	15.00	381
	84	56.00	1422	51.00	1295	15.00	381
225A WITH FEED THRU LUGS	30 & 42	38.00	965	33.00	838	15.00	381
	54	44.00	1118	39.00	991	15.00	381
	72	50.00	1270	45.00	1143	15.00	381
	84	56.00	1422	51.00	1295	15.00	381
225A WITH SUB FEED BREAKER	30	50.00	1270	45.00	1143	15.00	381
	42 & 54	56.00	1422	51.00	1295	15.00	381
	72	62.00	1575	57.00	1448	15.00	381
	84	68.00	1727	63.00	1600	15.00	381

REFER TO DP CATALOG CLASS 1640 FOR ADDITIONAL INFORMATION

FOR TYPE 3R APPLICATIONS USE IN CONJUNCTION WITH PBA711

NQ PANELBOARDS MEET THE APPLICABLE REQUIREMENTS OF UL AND CSA.

BOX: CODE GAUGE GALVANIZED STEEL. ONE ENDWALL IS BLANK, THE OTHER HAS KNOCKOUTS.


FRONT: MONO-FLAT CONSTRUCTION WITH CONCEALED TRIM SCREWS AND DOOR HINGES. ANSI 49 GRAY BAKED ENAMEL FINISH ELECTRODEPOSITED OVER CLEANED PHOSPHATIZED STEEL.

LOCK: FLUSH LOCK WITH BRUSHED STAINLESS STEEL ESCUTCHEON. NSR-251 KEY.


JOB NAME:	———	EQUIPMENT DESIGNATION:	———
JOB LOCATION:	———	EQUIPMENT TYPE:	NQ MLO 100A/225A TYPE 1
DRAWN BY:	———	DRAWING TYPE:	———
ENGR:	———		
DATE:	AUGUST 2007		
DRAWING STATUS:	———	DWG# PBA701A	PG 01 OF 01 REV —

SQUARE D
Schneider Electric


REV	DESCRIPTION	BY	DATE	—	————	——	——/——
—	————	——	——/——	—	————	——	——/——




TYPICAL BOX WITH INTERIOR




TYPICAL BOX
SIDE VIEW



TYPICAL FRONT



TYPICAL MOUNTING OF
QO, QOB BREAKERS



ENDWALL WITH KNOCKOUTS
(OTHER ENDWALL IS BLANK)

DUAL DIMENSIONS: INCHES / MILLIMETERS

MAXIMUM MAIN LUGS AMPERE RATING	MAXIMUM NUMBER OF CIRCUITS	H		A	
		IN	MM	IN	MM
400A	30 & 42	50.00	1270	45.00	1143
	54	56.00	1422	51.00	1295
	72	62.00	1575	57.00	1448
	84	68.00	1727	63.00	1600
400A WITH SUB FEED LUGS	30 & 42	50.00	1270	45.00	1143
	54	56.00	1422	51.00	1295
	72	62.00	1575	57.00	1448
	84	68.00	1727	63.00	1600
400A WITH FEED THRU LUGS	30 & 42	56.00	1422	51.00	1295
	54	62.00	1575	57.00	1448
	72	68.00	1727	63.00	1600
	84	74.00	1880	69.00	1753
400A WITH SUB FEED BREAKERS	30 & 42	74.00	1880	69.00	1753
	54	80.00	2032	75.00	1905
	72	86.00	2184	81.00	2057
600A *	30 & 42	50.00	1270	45.00	1143
	54	56.00	1422	51.00	1295
	72	62.00	1575	57.00	1448
	84	68.00	1727	63.00	1600
600A WITH FEED THRU LUGS	30 & 42	62.00	1575	57.00	1448
	54	68.00	1727	63.00	1600
	72	74.00	1880	69.00	1753
	84	80.00	2032	75.00	1905
600A WITH SUB FEED BREAKERS	30 & 42	74.00	1880	69.00	1753
	54	80.00	2032	75.00	1905
	72	86.00	2184	81.00	2057

* FOR TYPE 3R ENCLOSURE INCREASE HEIGHT DIMENSION BY 12.00/[305]

REFER TO DP CATALOG CLASS 1640 FOR ADDITIONAL INFORMATION

FOR TYPE 3R APPLICATIONS USE IN CONJUNCTION WITH PBA711

NQ PANELBOARDS MEET THE APPLICABLE REQUIREMENTS OF UL AND CSA.

BOX: CODE GAUGE GALVANIZED STEEL. ONE ENDWALL IS BLANK, THE OTHER HAS KNOCKOUTS.

FRONT: GRAY BAKED ENAMEL FINISH ELECTRODEPOSITED OVER CLEANED PHOSPHATIZED STEEL. FRONT IS VENTED AND MOUNTS TO ENCLOSURE WITH SCREWS. DOOR HINGES ARE CONCEALED.


LOCK: FLUSH LOCK WITH BRUSHED STAINLESS STEEL ESCUTCHEON. NSR–251 KEY.

JOB NAME:	———	EQUIPMENT DESIGNATION:	———
JOB LOCATION:	———	EQUIPMENT TYPE:	NQ MLO 400A/600A TYPE 1
DRAWN BY:	———	DRAWING TYPE:	———
ENGR:	———		
DATE:	AUGUST 2007		
DRAWING STATUS:	———	DWG# PBA709A	PG 01 OF 01 REV —

SQUARE D
Schneider Electric

REV	DESCRIPTION	BY	DATE	–	----	--	--/--/--
–	----	--	--/--/--	–	----	--	--/--/--

CKT NO	ACCESSORIES	TYPE	RATING AMP/P
1			
3		QOB–VH	100/3
5			
7			
9		QOB–VH	100/3
11			
13			
15	DISCONNECTS POWER TO SPD,SPD DISCONNECT	QOB–VH	30/3
17			
	Surge Counter Dry Contacts	SPD 120kA/3	



RATING AMP/P	TYPE	ACCESSORIES	CKT NO
			2
100/3	QOB–VH		4
			6
			8
100/3	QOB–VH		10
			12
			14
15/3	QOB–VH	HLO Fixed Off/On	16
			18
	SPD 120kA/3	Surge Counter Dry Contacts	

PHYSICAL DATA

ENCLOSURE Type 2
Surface with Door
FRONT CAT#: NC50VS
BOX CAT#: MH50H

DIMENSIONS:
50''(1270mm)Hx20"(508mm)Wx5.75''(146mm)D
PBA: 709A

BUSSING: COPPER
Silver/Tin Plated

OPTIONAL FEATURES:
SEISMICALLY QUALIFIED : IBC/ASCE7/CBC/NBCC
SHIP COMPLETELY ASSEMBLED
DRIP HOOD
Copper GROUND BAR
COPPER SOLID NEUTRAL
Maximum Panel Weight 125.
Depth Center of Gravity 5.75
Elevation Center of Gravity 25.0
Vertical Center of Gravity 10.0
SPD DRY CONTACTS
SPD SURGE COUNTER
SPD PEAK SURGE RATING/PHASE: 120kA
SPD LINE TO GRD PROTECT

ELECTRICAL DATA

SYSTEM: 208Y/120V 3Ph 4W 60Hz
System Ampacity: 400A
22kA SYMS. SCCR

MAIN: MAIN LUGS : 400A
Bottom FEED
INCOMING CONDUCTORS(S) PER NEC, CEC, NOM:
Wire Bending Space:
Phase Lugs:1 – 1/0 – 750, (2) 1/0 – 350 kcmil

----------BRANCH SUMMATION----------


4 – 100A/3P QOB–VH
1 – 30A/3P QOB–VH SPD DISC
1 – 15A/3P QOB–VH HPL

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	CDP–1
JOB LOCATION:	806	EQUIPMENT TYPE:	NQ (Circuit Breaker Type) PANEL 1 OF 1
DRAWN BY:	(Q2C)	DRAWING TYPE:	ONE LINE DIAGRAM
ENGR:			SQUARE D by Schneider Electric
DATE:	May 09 2019		
DRAWING STATUS:	QUOTE	DWG# 041753775–01	PG 1 OF 1 REV –

REV	DESCRIPTION	BY	DATE	–	----	--	--/--/--
–	----	--	--/--/--	–	----	--	--/--/--

CKT NO	ACCESSORIES	TYPE	RATING AMP/P
1		QOB–VH	15/3
3			
5			
7		QOB–VH	15/3
9			
11			
13		QOB–VH	15/3
15			
17			
19		QOB	15/2
21			
23		QOB–VH	15/1
25		QOB–VH	15/1
27		QOB–VH	15/1
29		QOB–VH	15/1
31		QOB–VH	15/1
33		QOB–VH	15/1
35		QOB–VH	15/1
37		QOB–VH	15/1
39		QOB–VH	15/1
41		QOB–VH	15/1
43		QOB–VH	15/1
45	PREPARED SPACE	QOB	15/1
47	PREPARED SPACE	QOB	15/1
49	PREPARED SPACE	QOB	15/1
51	PREPARED SPACE	QOB	15/1
53	PREPARED SPACE	QOB	15/1
55	PREPARED SPACE	QOB	15/1
57	PREPARED SPACE	QOB	15/1
59	PREPARED SPACE	QOB	15/1
61			
63			
65			
67			
69			
71	BLANK		

RATING AMP/P	TYPE	ACCESSORIES	CKT NO
			2
15/3	QOB–VH		4
			6
			8
15/3	QOB–VH		10
			12
			14
15/3	QOB–VH		16
			18
15/1	QOB–VH		20
15/1	QOB–VH		22
15/1	QOB–VH		24
15/1	QOB–VH		26
15/1	QOB–VH		28
15/1	QOB–VH		30
15/1	QOB–VH		32
15/1	QOB–VH		34
15/1	QOB–VH		36
15/1	QOB–VH		38
15/1	QOB–VH		40
15/1	QOB–VH		42
15/1	QOB	PREPARED SPACE	44
15/1	QOB	PREPARED SPACE	46
15/1	QOB	PREPARED SPACE	48
15/1	QOB	PREPARED SPACE	50
15/1	QOB	PREPARED SPACE	52
15/1	QOB	PREPARED SPACE	54
15/1	QOB	PREPARED SPACE	56
15/1	QOB	PREPARED SPACE	58
15/1	QOB	PREPARED SPACE	60
			62
			64
			66
			68
			70
		BLANK	72



PHYSICAL DATA

ENCLOSURE Type 2
Surface with Door
FRONT CAT#: NC44S
BOX CAT#: MH44H

DIMENSIONS:
44''(1118mm)Hx20"(508mm)Wx5.75''(146mm)D
PBA: 701A

BUSSING: COPPER
Silver/Tin Plated

OPTIONAL FEATURES:
SEISMICALLY QUALIFIED : IBC/ASCE7/CBC/NBCC
SHIP COMPLETELY ASSEMBLED
DRIP HOOD
Copper GROUND BAR
COPPER SOLID NEUTRAL
Maximum Panel Weight 110.
Depth Center of Gravity 5.75

(Continued on next page.)

ELECTRICAL DATA

SYSTEM: 208Y/120V 3Ph 4W 60Hz
System Ampacity: 225A
10kA SYMS. SCCR

MAIN: MAIN LUGS : 225A
Bottom FEED
INCOMING CONDUCTORS(S) PER NEC, CEC, NOM:
Wire Bending Space:
Phase Lugs:1 – #6 – 350 kcmil

----------BRANCH SUMMATION----------

6 – 15A/3P QOB–VH	1 – 15A/2P QOB
23 – 15A/1P QOB–VH	17 – 15A/1P–PS QOB

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	2A
JOB LOCATION:	806	EQUIPMENT TYPE:	NQ (Circuit Breaker Type) PANEL 1 OF 1
DRAWN BY:	(Q2C)	DRAWING TYPE:	ONE LINE DIAGRAM
ENGR:			SQUARE D by Schneider Electric
DATE:	May 09 2019		
DRAWING STATUS:	QUOTE	DWG# 041753775–01	PG 1 OF 2 REV –

REV	DESCRIPTION	BY	DATE	–	----	--	--/--/--
–	----	--	--/--/--	–	----	--	--/--/--

PHYSICAL DATA CONTINUED


Elevation Center of Gravity 22.0

Vertical Center of Gravity 10.0

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	2A
JOB LOCATION:	806	EQUIPMENT TYPE:	NQ (Circuit Breaker Type) PANEL 1 OF 1
DRAWN BY:	(Q2C)	DRAWING TYPE:	ONE LINE DIAGRAM
ENGR:			SQUARE D by Schneider Electric
DATE:	May 09 2019		
DRAWING STATUS:	QUOTE	DWG# 041753775-01	PG 2 OF 2 REV –

REV	DESCRIPTION	BY	DATE	–	----	--	--/--/--
–	----	--	--/--/--	–	----	--	--/--/--

CKT NO	ACCESSORIES	TYPE	RATING AMP/P
1		QOB	25/2
3			
5		QOB	15/2
7			
9		QOB	15/1
11		QOB	15/1
13		QOB	15/1
15		QOB	15/1
17		QOB	15/1
19		QOB	15/1
21		QOB	15/1
23		QOB	15/1
25		QOB	15/1
27		QOB	15/1
29		QOB	15/1
31		QOB	15/1
33	PREPARED SPACE	QOB	15/1
35	PREPARED SPACE	QOB	15/1
37	PREPARED SPACE	QOB	15/1
39	PREPARED SPACE	QOB	15/1
41	PREPARED SPACE	QOB	15/1



RATING AMP/P	TYPE	ACCESSORIES	CKT NO
15/2	QOB		2
			4
15/1	QOB		6
15/1	QOB		8
15/1	QOB		10
15/1	QOB		12
15/1	QOB		14
15/1	QOB		16
15/1	QOB		18
15/1	QOB		20
15/1	QOB		22
15/1	QOB		24
15/1	QOB		26
15/1	QOB		28
15/1	QOB		30
15/1	QOB	PREPARED SPACE	32
15/1	QOB	PREPARED SPACE	34
15/1	QOB	PREPARED SPACE	36
15/1	QOB	PREPARED SPACE	38
15/1	QOB	PREPARED SPACE	40
15/1	QOB	PREPARED SPACE	42

PHYSICAL DATA

ENCLOSURE Type 2
Surface with Door
FRONT CAT#: NC38S
BOX CAT#: MH38H

DIMENSIONS:
38''(965mm)Hx20"(508mm)Wx5.75''(146mm)D
PBA: 701A

BUSSING: COPPER
Silver/Tin Plated

OPTIONAL FEATURES:
SEISMICALLY QUALIFIED : IBC/ASCE7/CBC/NBCC
SHIP COMPLETELY ASSEMBLED
DRIP HOOD
Copper GROUND BAR
COPPER SOLID NEUTRAL
Maximum Panel Weight 95.0
Depth Center of Gravity 5.75
Elevation Center of Gravity 19.0
Vertical Center of Gravity 10.0

ELECTRICAL DATA


SYSTEM: 208Y/120V 3Ph 4W 60Hz
System Ampacity: 100A
10kA SYMS. SCCR

MAIN: MAIN LUGS : 100A
Bottom FEED
INCOMING CONDUCTORS(S) PER NEC, CEC, NOM:
Wire Bending Space:
Phase Lugs:1 – #6 – 2/0 AWG

----------BRANCH SUMMATION----------

1 – 25A/2P QOB	2 – 15A/2P QOB
25 – 15A/1P QOB	11 – 15A/1P–PS QOB

JOB NAME:	IQALUIT WASTE WATER TREATMENT UPGR	EQUIPMENT DESIGNATION:	2C
JOB LOCATION:	806	EQUIPMENT TYPE:	NQ (Circuit Breaker Type) PANEL 1 OF 1
DRAWN BY:	(Q2C)	DRAWING TYPE:	ONE LINE DIAGRAM
ENGR:			SQUARE D by Schneider Electric
DATE:	May 09 2019		
DRAWING STATUS:	QUOTE	DWG# 041753775–01	PG 1 OF 1 REV –



LITERATURE

NQ Lighting Panelboards



Developed with electrical contractor input, the NQ family of lighting and appliance panelboards sets new standards for ease of installation and durability. Plus, new design innovations increase the availablity of these panelboards by offering complete ready to install products.

Features

- 240Vac, 48Vdc maximum
- 600A maximum main circuit breakers or main lugs
- 150A maximum branch circuit breakers
- 10,000A through 200,000A SCCR
- Both fully rated and series rated systems are available
- Interiors are field convertible to top or bottom feed
- Interiors are available in plated copper or aluminum bus
- Interiors accept both bolt-on and plug-on branch circuit breakers
- Complete line of UL/cUL listed interiors with 200% rated neutrals for non-linear loads
- Suitable for use as service entrance equipment
- 20" wide trims and boxes common for NQ and NF panelboards
- Mono-flat® or hinged trims

Factory Options

- 1P3W or 3P4W – 600A main lugs and main breaker panelboards
- Sub-feed and thru-feed lugs
- Sub-feed circuit breakers
- Optional 200% rated neutrals up to 400A
- Split bus bars
- TVSS
  - 100,000A – 240,000A surge current rating
  - All voltage systems
- Lighting contactors
- Customer equipment space

"Ready-to-Install" Panels and Kits Available from Stock

- 100A – 600A MLO 1P3W and 3P4W Interiors
- NEMA 1 and 3R/12 enclosures
- 100A – 400A main circuit breaker kits
- TVSS interiors
  - 120,000A or 160,000A surge current ratings
- 100A – 400A sub-feed and thru-feed lugs
- Sub-feed circuit breaker kits
  - 1 – 225A sub-feed circuit breaker per 225A panelboard
  - 2 – 225A sub-feed circuit breakers per 400A panelboard
- 200% neutral kits up to 400A
- Copper neutrals and equipment ground bars



THIS PAGE WAS INTENTIONALLY LEFT BLANK

NQ SurgeLoc SPD

Square D Internally Mounted Surge Protective Devices

Square D™ brand Surgelogic™ internal SurgeLoc Surge Protective Device (SPD) delivers specification grade performance for service entrance or critical branch panel applications. This multi-phase system provides suppression for all critical modes inside electrical equipment and shorter lead lengths for superior SPD performance.



SQUARE D™

by Schneider Electric

NQ SurgeLoc SPD Features



Internal NQ panel Surge Protective Devices (SPDs) provide superior design and service life for a wide variety of commercial, industrial, or institutional applications. Square D brand Surgelogic SPDs offer first-rate surge suppression performance for demanding service entrance applications or as part of a suppression network. The robust construction reduces potential down time and maintenance costs due to voltage surges.

Superior Performance

The SurgeLoc SPD product utilizes a high-energy suppression circuit that provides 6-10 modes of suppression from 80,000 to 240,000 peak Amps of surge current rating per phase. These devices feature circuity that provides not only transient surge suppression, but also noise filtration.

Ordering/Installation

SurgeLoc can be ordered from your local Schneider Electric distributor as a merchandised product or factory installed as part of a complete panelboard assembly. Factory orders come professionally assembled and pre-wired into the electrical panel insuring minimum lead lengths and high performance. All factory installed units are tested before delivery to their final destination, maintaining Square D brand's high standard of quality and customer satisfaction.

Warranty

SurgeLoc internal SPDs have a 10-year warranty.

FEATURES	ADVANTAGES	BENEFITS
Integral to electrical gear and panels	SPDs are professionally installed inside electrical gear and panels	Delivers high levels of SPD performance and saves on enclosure and installation expenses
80,000 to 240,000 Amp Capacity (depending on model)	Longer service life and suppression against high-energy lightning strikes	High performance surge suppression even in severe electrical conditions
EMI/RFI Noise Rejection	Increased noise filtering	Improves operating performance of connected equipment
Advanced Diagnostics	Allows for visual indication/testing of the suppressor's functionality	Provides immediate response if suppressor is damaged
Suppression Status Alarms	Allows multiple methods of alarm notification	Provides immediate notification through audible, visual and remote signaling if reduced suppression occurs
Coordinated Fuse Technology	Coordinated fusing allows disconnection methods for thermal and high-current events	Provides premium surge suppression while managing both thermal and high-current end-of-life events

Schneider Electric USA, Inc. 1751 S. 4800 W., Salt Lake City, UT 84104, USA Telephone: (801)-977-9009 Fax: (801)-977-0200 www.surgelogic.com

Document Number 9990-0130B September 2013 bw

NQ SurgeLoc SPD Features (continued)

NQ Panelboard



NQ panelboards are primarily used for lighting and power distribution up to 600 Amps. These panelboards, following the 2008 National Electric Code changes, provide electrical capacity up to 84 circuit breakers. NQ panels are designed with 200% rated copper neutrals for non-linear loads. (NQ max volts 240 Vac, max 200kA Short Circuit Current)

When selecting a panelboard with a SurgeLoc SPD, an additional 12 circuit positions (6 adjacent mounting spaces per side) or 4.5 inches of space on each side are required. For example, if the desired number of circuits is 30, a 42 circuit panelboard is required.

NQ SPD available surge current ratings:
80,100,120,160, 200, 240 kA

Internal SPDs



Performance

Surge Current Rating per Phase	Up to 240kA
Short Circuit Current Rating	200kA
Modes of Protection	6, 10
Fusing	Individually fused MOVs
Thermal Fusing	Yes
Overcurrent Fusing	Yes
Sine Wave Tracking	Yes
EMI/RFI Filtering	Up to -50 dB
Operating Frequency	50/60 Hz

Mechanical Description

Connection Method	10 AWG, Stranded
Mounting Method/Circuit Type	Parallel
Operating Altitude	Sea Level-12,000' (3,658 m)
Storage Temperature	-40˚ F (-40˚ C) to 149˚ F (65˚ C)
Operating Temp.	-40˚ F (-40˚ C) to 104˚ F (40˚ C)
LCD Operating Temp.	32˚ F (0˚ C) to 122˚ F (50˚ C)
Operating Humidity	0 to 95% non-condensing

Diagnostics

Push to test diagnostic button, red and green status LEDs per phase, dry contacts, audible alarm with disable switch and surge counter.

Options

- Remote monitor

Safety and Performance

Type 1 SPD: cULus Listed per UL 1449 3rd Edition, UL 67 12th Edition, CSA C22.2 No. 29 5th Edition, and CSA C22.2 No. 8 M-1986.

Complies with UL 96A 12th Edition Master Label requirements for Lightning Protection Systems

NQ SurgeLoc SPD Specifications

WYE Configured SPD Specifications

Voltage	Surge Current per Phase	Modes of Protection	Configuration	Model Number	MCOV	I_n	VPR			
							L-N	L-G	L-L	N-G
120/240V	80kA	6	1 Ø, 3-wire+G	SSP01BIA08PBQ1	150V	20kA	700V	700V	1200V	700V
208Y/120V ■	80kA	10	3 Ø, Wye, 4-wire+G	SSP02BIA08PBQ1	150V	20kA	700V	700V	1200V	700V
120/240V	100kA	6	1 Ø, 3-wire+G	SSP01BIA10PBQ1	150V	20kA	700V	700V	1200V	700V
208Y/120V ■	100kA	10	3 Ø, Wye, 4-wire+G	SSP02BIA10PBQ1	150V	20kA	700V	700V	1200V	700V
120/240V	120kA	6	1 Ø, 3-wire+G	SSP01BIA12PBQ1	150V	20kA	700V	700V	1200V	700V
208Y/120V ■	120kA	10	3 Ø, Wye, 4-wire+G	SSP02BIA12PBQ1	150V	20kA	700V	700V	1200V	700V
120/240V	160kA	6	1 Ø, 3-wire+G	SSP01BIA16PBQ1	150V	20kA	700V	700V	1200V	700V
208Y/120V ■	160kA	10	3 Ø, Wye, 4-wire+G	SSP02BIA16PBQ1	150V	20kA	700V	700V	1200V	700V
120/240V	200kA	6	1 Ø, 3-wire+G	SSP01BIA20PBQ1	150V	20kA	700V	700V	1200V	700V
208Y/120V ■	200kA	10	3 Ø, Wye, 4-wire+G	SSP02BIA20PBQ1	150V	20kA	700V	700V	1200V	700V
120/240V	240kA	6	1 Ø, 3-wire+G	SSP01BIA24PBQ1	150V	20kA	700V	700V	1200V	700V
208Y/120V ■	240kA	10	3 Ø, Wye, 4-wire+G	SSP02BIA24PBQ1	150V	20kA	700V	700V	1200V	700V

■ 208Y/120 series also applies to the following voltage 220Y/127

High-Leg Delta (HLD) Configured SPD Specifications

Voltage	Surge Current per Phase	Modes of Protection	Configuration	Model Number	MCOV	I_n	VPR						
							L-N	H-N	L-G	H-G	L-L	H-L	N-G
240/120HLD	80kA	10	3 Ø, HLD, 4-wire+G	SSP03BIA08PBQ1	150V	20kA	800V	1200V	800V	1000V	1200V	1500V	700V
240/120HLD	100kA	10	3 Ø, HLD, 4-wire+G	SSP03BIA10PBQ1	150V	20kA	800V	1200V	800V	1000V	1200V	1500V	700V
240/120HLD	120kA	10	3 Ø, HLD, 4-wire+G	SSP03BIA12PBQ1	150V	20kA	800V	1200V	800V	1000V	1200V	1500V	700V
240/120HLD	160kA	10	3 Ø, HLD, 4-wire+G	SSP03BIA16PBQ1	150V	20kA	800V	1200V	800V	1000V	1200V	1500V	700V
240/120HLD	200kA	10	3 Ø, HLD, 4-wire+G	SSP03BIA20PBQ1	150V	20kA	800V	1200V	800V	1000V	1200V	1500V	700V
240/120HLD	240kA	10	3 Ø, HLD, 4-wire+G	SSP03BIA24PBQ1	150V	20kA	800V	1200V	800V	1000V	1200V	1500V	700V

Model numbers not recognized as line items in Schneider Electric ordering system until a suffix code is applied

Schneider Electric USA, Inc.
1751 S. 4800 W.
Salt Lake City, UT 84104
Telephone: (801)-977-9009
www.surgelogic.com


Schneider Electric México, S.A. de C.V.
Calz. J. Rojo Gómez 1121-A
Col. Gpe. del Moral 09300 México, D.F.
Tel. 55-5804-5000
www.schneider-electric.com.mx

Schneider Electric Canada, Inc.
5985 McLaughlin Road
Mississauga, ON L5R 1B8 Canada
Tel:1-800-565-6699
www.schneider-electric.ca


© 2013 Schneider Electric. All rights reserved. Schneider Electric, Square D, and Surgelogic are trademarks owned by Schneider Electric Industries SAS or its affiliated companies.
All other trademarks are the property of their respective owners.

Document Number 9990-0130B

September 2013 bw



SERVICES



BILL OF MATERIALS

Q2C Number: 41753775	**Quote Number:** 2	**Revision Number:** 1
Project Name: IQALUIT WASTE WATER TREATMENT UPGR		**Quote Name:**

Item No.	Qty.	Catalog Number / Details
		SERVICES
005-00	1	**Designation:** Kyle RIngelstein OTTAWA SERVICE CSSQ41753775 ARC FLASH Coordination Study Short Circuit Study Arc Flash Analysis - Electrical Studies provided for new Schneider Electric equipment only, as per this bill of material

Date: July 11, 2019

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 11, 2019

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-18R4 SU-ELE18R4
PO-P19-108 Nedco

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [x] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 24 19 Motor Control Centres

STANTEC PROJECT #: 110126045 SUBMITTAL # ELE 018-R4

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other _____

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2019-07-12

BY Jamie McLeish

Note, contractor remains responsible for the shop drawing content and coordination with other disciplines. Stantec's review does not relieve the contractor of their contractual responsibility.

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the contractor.

Do not hesitate to contact me if you have any questions or concerns.

SQUARE D
by Schneider Electric

Job Name:	IQALUIT WWTP MCC UPGRADES	Square D Quotation #:	41428112
Job Location:	SALABERRY–DE–VALLEYFIELD, QC	Quotation Revision #:	
		Sales Contact:	CURTIS DADSWELL
		Sales Contact Location:	817
Purchaser:	23010–NEDCO DIV OF REXEL CANADA	Customer:	ARCTIC ELECTRIC
Purchaser PO #:	(WR2)14265D	Customer PO #:	
User:		Architect:	
User Location:		Cons. Engineer:	
Drawing Status:	APPROVAL		

TABLE OF CONTENTS

SQUARE D FACTORY ORDER NUMBER: 41428112–001


Equipment Designation	Equipment Type	Drawing Type	Drawing Number	Page	Revision Level
MCC – 1	MODEL 6 MCC	ELEVATION	F41428112–001–01	1	C
			F41428112–001–01	2	C
			F41428112–001–01	3	C
		SEISMIC	S41428112–001–01	1	C
		ONE LINE DIAGRAM	O41428112–001–01	1	C
			O41428112–001–01	2	C
		UNIT INFORMATION	I41428112–001–01	1	C
			I41428112–001–01	2	C
			I41428112–001–01	3	C
			I41428112–001–01	4	C
			I41428112–001–01	5	C
		ELEMENTARY	E41428112–001–01	1	C
			E41428112–001–02	1	C
			E41428112–001–03	1	C
			E41428112–001–04	1	C
			E41428112–001–04	2	C
			E41428112–001–05	1	C
			E41428112–001–05	2	C
			E41428112–001–06	1	C
			E41428112–001–06	2	C
			E41428112–001–07	1	C
			E41428112–001–07	2	C
			E41428112–001–08	1	C
			E41428112–001–08	2	C
			E41428112–001–09	1	C
			E41428112–001–09	2	C
			E41428112–001–10	1	C
			E41428112–001–10	2	C
			E41428112–001–11	1	C
			E41428112–001–11	2	C
			E41428112–001–12	1	C
			E41428112–001–13	1	C

TABLE OF CONTENTS

SQUARE D FACTORY ORDER NUMBER: 41428112-001

Equipment Designation	Equipment Type	Drawing Type	Drawing Number	Page	Revision Level
			E41428112-001-13	2	C


REV	DESCRIPTION	BY	DATE								
–	----	--	--/--/--	A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019
				B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--




DUAL DIMENSIONS: INCHES / MILLIMETERS

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEVATION
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	F41428112–001–01

REV	DESCRIPTION	BY	DATE									
B	REAPPROVAL	TA	06/21/2019	A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



TOP VIEW



FLOOR VIEW

CROSSED AREA REPRESENTS CONDUIT ENTRY AREA. NUMBERS IN BOXES INDICATE VERTICAL CLEARANCE TO NEAREST OBSTRUCTION.

DUAL DIMENSIONS: INCHES / MILLIMETERS

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEVATION
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	F41428112-001-01

REV	DESCRIPTION	BY	DATE									
B	REAPPROVAL	TA	06/21/2019	A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--

GENERAL NOTES

Class 1 Type B Wiring

PRODUCT DESCRIPTION AND RATINGS

POWER SYSTEM DATA:

600V 3PH 3W 60Hz
SHORT CIRCUIT RATING: 65kA
POWER ENTERS: Main Fusible Switch Top Section 1
CONTROL POWER: 120Vac

BUS SYSTEM DATA:

MAIN HORIZONTAL BUS: 800 Amp Copper/Tin Plated / 1.5"
BUS BRACING: 65kA
VERTICAL BUS: 300 Amp Tin Plated Copper
HORIZONTAL GROUND BUS: .25" X 1.0" (6.35mm X 25.4mm) Tin Plated Copper
Units Securely Grounded To Structure

ENCLOSURE DATA:

ENCLOSURE TYPE: 20" DEEP Type 1A
EXTERIOR COLOR: Electrodeposition Finish ANSI 49 Medium Light Grey
INTERIOR COLOR: Electrodeposition Finish White
REMOVABLE 3" [76mm] LIFTING ANGLE

STRUCTURE MODIFICATIONS:

Ground Bus Lug : Main Section
Rodent Barriers 1,12
Manual Bus Shutters 1,2,3,4,5,6,7,8,9,10,11,12
Premium Barrier System 1,2,3,4,5,6,7,8,9,10,11,12
Copper Vertical Ground Bus 1,2,3,4,5,6,7,8,9,10,11,12
Wire Retainers 1,2,3,4,5,6,7,8,9,10,11,12

EQUIPMENT WEIGHT:

SHIPPING SPLIT # 1: 2250.00 Lbs. (1020.60 Kg.)
SHIPPING SPLIT # 2: 2250.00 Lbs. (1020.60 Kg.)
SHIPPING SPLIT # 3: 2250.00 Lbs. (1020.60 Kg.)
SHIPPING SPLIT # 4: 2250.00 Lbs. (1020.60 Kg.)
TOTAL LINEUP WEIGHT (APPROX): 9000.00 Lbs. (4082.40 Kg.)

PRODUCT ACCESSORIES:

Seismic Qualified IBC/ASCE7
Drip Hoods

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEVATION
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	F41428112-001-01 PG 3 OF 3 REV C


REV	DESCRIPTION	BY	DATE									
B	REAPPROVAL	TA	06/21/2019	A	APPROVAL RESUBMIT	RN	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--


REQUIREMENTS FOR SEISMIC RATING

ANCHORING CONDITIONS:

To Maintain Seismic Qualifications, Equipment Must Be Installed Per Installation Manual 80459–641–XX And Per Any Seismic Anchoring Details Provided By Others. Do Not Install Equipment Before Approved Seismic Anchoring Details Have Been Obtained And Site Preparations Have Been Made In Accordance With The Approved Seismic Anchoring Details. All Post–Installed Anchors Shall Be Approved For Seismic Loads.

Consideration Must Be Made For Conduit Entry Into Each Section When Developing Mounting Pad Reinforcement Locations. See Conduit Entry Details For Dimensional Information.





Each MCC Section Must Be Anchored At Four Locations (See Above Details). Anchor Bolt Mounting Points Are .88/[22] Diameter Holes Located 1.50/[38] Above The Base Of The MCC Section. Use Dimensions From The Anchor Detail To Determine Mounting Locations.

The Belleville Washer (Shown In Detail Above) Used For Anchoring Connections Is A Tested Component And Is Required To Maintain Position Retention Of The Equipment. The Slip Critical Connection Performance Of The Bolted Connection Was Established To The Shake Table Tested Seismic Capacity Of The Equipment As Shown On The Equipment Seismic Certificate Supplied At The Time Of Order.

CENTER OF GRAVITY:

The CG Information Provided Below Should Only Be Used For Seismic Anchoring Calculations.

Elevation Center Of Gravity: 62.00/[1575] Up From Floor Except Masterpact NW Main Use 54.00/[1372] Up From Floor

Depth Center Of Gravity: 7.50/[191] or 10.00/[254] From Rear For 15.00/[381] or 20.00/[508] Deep Sections Respectively. Consult Factory For Sections Taller Than 94.50/[2400].

Vertical Center of Gravity: Use Centerline Of Section From Left To Right


SECTION WEIGHTS:

The Weights Shown Below Should Only Be Used For Calculating Seismic Anchoring Requirements And Do Not Represent Actual Section Weights As Shipped.

1200 Lbs. (544.3 Kg.)	35.00/[889] Wide Sections
1300 Lbs. (589.7 Kg.)	20.00/[508] Wide Sections
1500 Lbs. (680.4 Kg.)	25.00/[635] And 30.00/[762] Wide Sections*
*1900 Lbs. (861.8 Kg.)	30.00/[762] Wide Section With Masterpact NW Main
2250 Lbs. (1020.6 Kg.)	50.00/[1270] Wide Section With 18 Pulse Drive
2750 Lbs. (1247.4 Kg.)	65.00/[1651] Wide Section With 18 Pulse Drive

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	SEISMIC
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	S41428112–001–01 PG 1 OF 1 REV C

REV	DESCRIPTION	BY	DATE
B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019
C	APPROVAL RESUBMITAL	MLC	07/11/2019
–	----	--	--/--/--
–	----	--	--/--/--




JOB NAME:	IQALUIT WWTP MCC UPGRADES
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC
DRAWN BY:	CAD
ENGR:	MLC
DATE:	MAY 21, 2019
DRAWING STATUS:	APPROVAL

EQUIPMENT DESIGNATION:	MCC – 1
EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWING TYPE:	ONE LINE DIAGRAM

[redacted]

DWG# 041428112-001-01 | PG 1 OF 2 | REV C

REV	DESCRIPTION	BY	DATE
B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019
C	APPROVAL RESUBMITAL	MLC	07/11/2019
–	----	--	--/--/--
–	----	--	--/--/--



JOB NAME:	IQALUIT WWTP MCC UPGRADES
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC
DRAWN BY:	CAD
ENGR:	MLC
DATE:	MAY 21, 2019
DRAWING STATUS:	APPROVAL

EQUIPMENT DESIGNATION:	MCC – 1
EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWING TYPE:	ONE LINE DIAGRAM

[redacted]

DWG# 041428112-001-01 | PG 2 OF 2 | REV C

| REV | DESCRIPTION | BY | DATE | | |

REV	DESCRIPTION	BY	DATE						
B	REAPPROVAL	TA	06/21/2019	A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--

UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
3K	P-03-640	ATV930	U40	5	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112-001-04
3S	ASD OUTPUT REACTOR FOR P-03-640	OUTPUT REACTOR																E41428112-001-04
3V	SPACE	SPACE																
4A	ASD LINE REACTOR FOR B-102-130	LINE REACTOR																E41428112-001-05
4D	B-102-130	ATV930	D22	25	FU SW 60		CONTROL TRANSFORMER	300	1.25	3.20			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112-001-05
4N	ASD OUTPUT REACTOR FOR B-102-130	OUTPUT REACTOR																E41428112-001-05
4Q	SPACE	SPACE																
4U	SPACE	SPACE																
5A	ASD LINE REACTOR FOR B-102-120	LINE REACTOR																E41428112-001-06
5D	B-102-120	ATV930	D22	25	FU SW 60		CONTROL TRANSFORMER	300	1.25	3.20			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112-001-06
5N	ASD OUTPUT REACTOR FOR B-102-120	OUTPUT REACTOR																E41428112-001-06
5Q	SPACE	SPACE																
5U	SPACE	SPACE																
6A	ASD LINE REACTOR FOR B-102-110	LINE REACTOR																E41428112-001-07
6D	B-102-110	ATV930	D22	25	FU SW 60		CONTROL TRANSFORMER	300	1.25	3.20			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112-001-07
6N	ASD OUTPUT REACTOR FOR B-102-110	OUTPUT REACTOR																E41428112-001-07
UNIT LOC	**UNIT NAMEPLATES**	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	PRI	SEC	NO	NC	ON LIGHT	OFF LIGHT	ADDL P/L	SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
									FUSE SIZE		INTERLOCKS		PILOT DEVICES: LED 22 mm **					

JOB NAME:	IQALUIT WWTP MCC UPGRADES
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC
DRAWN BY:	CAD
ENGR:	MLC
DATE:	MAY 21, 2019
DRAWING STATUS:	APPROVAL

EQUIPMENT DESIGNATION:	MCC – 1
EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWING TYPE:	UNIT INFORMATION

[redacted]

DWG# I41428112-001-01 | PG 2 OF 5 | REV C

REV	DESCRIPTION	BY	DATE		REV	DESCRIPTION	BY	DATE
B	REAPPROVAL	TA	06/21/2019		C	APPROVAL RESUBMITAL	MLC	07/11/2019
A	APPROVAL RESUBMIT	RN	06/19/2019		–	----	--	--/--/--
–	----	--	--/--/--					

UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
6Q	SPACE	SPACE																
6U	SPACE	SPACE																
7A	P-02-610	ATV930	U22	3	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PIT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112-001-08
7I	ASD OUTPUT REACTOR FOR P-02-610	OUTPUT REACTOR																E41428112-001-08
7L	P-02-620	ATV930	U22	3	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PIT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112-001-09
7T	ASD OUTPUT REACTOR FOR P-02-620	OUTPUT REACTOR																E41428112-001-09
7W	SPACE	SPACE																
8A	P-02-440	FVNR	NEMA 2	20	FU SW 60		CONTROL TRANSFORMER	100	.50	1.00	2	1	RED			HOA SS	#14 AWG MTW CONTROL WIRE, 600V SYSTEM, CLASS 10/20 O/L (SELECTABLE), CLASS J FUSE CLIPS,	E41428112-001-03
																	MOTOR LOGIC O/L NEMA SIZE 2, N.C. ISOLATED AUX O/L CONTACTS, STD WIRE LABELS	
8E	P-02-450	FVNR	NEMA 2	20	FU SW 60		CONTROL TRANSFORMER	100	.50	1.00	2	1	RED			HOA SS	#14 AWG MTW CONTROL WIRE, 600V SYSTEM, CLASS 10/20 O/L (SELECTABLE), CLASS J FUSE CLIPS,	E41428112-001-03
																	MOTOR LOGIC O/L NEMA SIZE 2, N.C. ISOLATED AUX O/L CONTACTS, STD WIRE LABELS	
8I	P-02-460	FVNR	NEMA 2	20	FU SW 60		CONTROL TRANSFORMER	100	.50	1.00	2	1	RED			HOA SS	#14 AWG MTW CONTROL WIRE, 600V SYSTEM, CLASS 10/20 O/L (SELECTABLE), CLASS J FUSE CLIPS,	E41428112-001-03
																	MOTOR LOGIC O/L NEMA SIZE 2, N.C. ISOLATED AUX O/L CONTACTS, STD WIRE LABELS	
8M	SPACE	SPACE																
8Q	SPACE	SPACE																

UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
									FUSE SIZE		INTERLOCKS		PILOT DEVICES: LED 22 mm **					

JOB NAME:	IQALUIT WWTP MCC UPGRADES
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC
DRAWN BY:	CAD
ENGR:	MLC
DATE:	MAY 21, 2019
DRAWING STATUS:	APPROVAL

EQUIPMENT DESIGNATION:	MCC – 1
EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWING TYPE:	UNIT INFORMATION

[redacted]

DWG# I41428112-001-01 | PG 3 OF 5 | REV C

REV	DESCRIPTION	BY	DATE	REV	DESCRIPTION	BY	DATE
B	REAPPROVAL	TA	06/21/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--
–	----	--	--/--/--				

UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
8U	SPACE	SPACE																
9A	DDR-02-311	ATV930	U22	3	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112-001-10
9I	ASD OUTPUT REACTOR FOR DDR-02-311	OUTPUT REACTOR																E41428112-001-10
9L	DDR-02-321	ATV930	U22	3	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112-001-11
9T	ASD OUTPUT REACTOR FOR DDR-02-321	OUTPUT REACTOR																E41428112-001-11
9W	SPACE	SPACE																
10A	SPACE	SPACE																
10C	SPACE	SPACE																
10E	SPACE	SPACE																
10I	P-03-630	ATV930	U40	5	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112-001-12
10Q	ASD OUTPUT REACTOR FOR P-03-630	OUTPUT REACTOR																E41428112-001-12
10T	SPACE	SPACE																
11A	SPACE	SPACE																
11C	P-04-770	6" BRANCH SW			FU SW 30												14-2AWG 1 LUG/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112-001-13
11E	P-04-780	6" BRANCH SW			FU SW 30												14-2AWG 1 LUG/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112-001-13
UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #

JOB NAME:	IQALUIT WWTP MCC UPGRADES
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC
DRAWN BY:	CAD
ENGR:	MLC
DATE:	MAY 21, 2019
DRAWING STATUS:	APPROVAL

EQUIPMENT DESIGNATION:	MCC – 1
EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWING TYPE:	UNIT INFORMATION

[redacted]

DWG# I41428112-001-01 | PG 4 OF 5 | REV C

REV	DESCRIPTION	BY	DATE						
B	REAPPROVAL	TA	06/21/2019	A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--

UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
11G	P-04-790	6" BRANCH SW			FU SW 30												14-2AWG 1 LUG/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112-001-13
11I	SPACE	SPACE																
11M	SPACE	SPACE																
11Q	SPACE	SPACE																
11U	SPACE	SPACE																
12A	SPACE	SPACE																
12E	P-04-970	6" BRANCH SW			FU SW 30												14-2AWG 1 LUG/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112-001-13
12G	P-04-980	6" BRANCH SW			FU SW 30												14-2AWG 1 LUG/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112-001-13
12I	SPACE	SPACE																
12M	SPACE	SPACE																
12Q	SPACE	SPACE																
12U	SPACE	SPACE																
UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	PRI FUSE SIZE	SEC FUSE SIZE	NO INTERLOCKS	NC INTERLOCKS	ON LIGHT PILOT DEVICES: LED 22 mm **	OFF LIGHT PILOT DEVICES: LED 22 mm **	ADDL P/L	SS / PB	OTHER UNIT FEATURES	ELEMENTARY #


JOB NAME:	IQALUIT WWTP MCC UPGRADES
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC
DRAWN BY:	CAD
ENGR:	MLC
DATE:	MAY 21, 2019
DRAWING STATUS:	APPROVAL

EQUIPMENT DESIGNATION:	MCC – 1
EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWING TYPE:	UNIT INFORMATION

[redacted]

DWG# I41428112-001-01 | PG 5 OF 5 | REV C


REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019



POWER FUSES NOT INCLUDED

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-01	PG 1 OF 1 REV C


REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019



JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–02	PG 1 OF 1 REV C

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

14M




POWER FUSE NOT INCLUDED

HEAT SHRINK WIRE LABELS

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-03	PG 1 OF 1 REV C

REV	DESCRIPTION	BY	DATE							
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	-	----	-- --/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	-	----	-- --/--/--




REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–04	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE							
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	-	----	-- --/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	-	----	-- --/--/--



DRIVE CATALOG NUMBER ATV930D22Y6


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC - 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-05	PG1 OF2 REV C

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–05	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE							
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	-	----	-- --/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	-	----	-- --/--/--



DRIVE CATALOG NUMBER ATV930D22Y6


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC - 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	E41428112-001-06 PG1 OF2 REV C

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–06	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE
A	APPROVAL RESUBMIT	RN	06/19/2019
B	REAPPROVAL	TA	06/21/2019
C	APPROVAL RESUBMITAL	MLC	07/11/2019



DRIVE CATALOG NUMBER ATV930D22Y6

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC - 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	E41428112-001-07


PG1 OF2 REV C

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–07	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE							
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	-	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	-	----	--	--/--/--




REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–08	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE							
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	-	----	-- --/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	-	----	-- --/--/--




REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–09	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE							
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	-	----	-- --/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	-	----	-- --/--/--



MOTOR
9A BFC 930_DRIVE
9A FLR LINE_REACTOR
9A LLR LOAD_REACTOR
9A BRR BRAKE
9A BAR AUXR
9A BCR RCR
9A BBR BRKR
9A BFR RUNR
9A BDR DRR
9A BAR BRKR
9A BAR AUXR
9A BAR CANR
9A BAR RUNR
9A BAR BRKR
9A BAR AUXR
9A BAR BRK

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–10	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE							
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	-	----	-- --/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	-	----	-- --/--/--




REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–11	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE							
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	-	----	-- --/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	-	----	-- --/--/--




REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–12	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE				
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019
				C	APPROVAL RESUBMITAL	MLC	07/11/2019



POWER FUSES NOT INCLUDED

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–13	PG 1 OF 1 REV C

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Fév 04, 2019

VEOLIA

SHOP DRAWINGS

Network Architecture

Date : 2019-02-04

General Information			
Project	WWTP UPGRADE - IQALUIT		
Client:	Kudlik Construction Ltd.	Project Number	2018-062
To:	Sandra Rousseau P.Eng., Project Manger	E-mail:	srousseau@kudlik.biz
Contractor	Veolia Water Technologies Canad Inc.	Project Number	5000218036
Address	4105 Sartelon, Ville St. Laurent PQ, H4S 2B3		
Project Manger:	Clément Bekaert	E-mail:	clement.bekaert@veolia.com
Phone:	514-334-7230 x 3243	Cell:	514-246-6232

Information on the Equipment			
Specialty:	Electrical / automation		
Equipment:	Control panel(s) Spidflow		
Drawing Reference:			
Specification reference:	46.71.24		
Article:			
Revision:	Rev01		
Titre:	Main Panel Electrical Drawings		
Numero client:	DA-Veolia-ED-01-Main Panel		
Numero Veolia	5000218036_EPL_0001_AU_VWT		
Envoyer pour:	Approbation/Information:	Approbation	

Consultant Approval

Ensure there is space within LCP-02-300 for the ten digital input signals to be pulled to CPL-901's PLC as shown on P&IDs (P611 & P613). These signals are:

XA-02-310
YI-02-310
LAL-02-333
LAH-02-330
LAH-02-332
XA-02-320
YI-02-320
LAL-02-343
LAH-02-342
LAH-02-340

SHOP DRAWINGS ARE REVIEWED UNLESS NOTED OTHERWISE
REVIEWED AS MODIFIED [X]
REVISE & RESUBMIT [ ]
SEAL & SIGNATURE REQUIRED [ ]
Stantec
DATE March 6/19
SIGNATURE Ellie Brun
REVIEW BY STANTEC IS FOR THE SOLE PURPOSE OF ASCERTAINING GENERAL CONFORMITY WITH DESIGN. CONTRACTOR IS RESPONSIBLE FOR DIMENSIONS, FABRICATION AND CONSTRUCTION METHODS, COORDINATION OF SUB-TRADES, DETAIL DESIGN OF COMPONENTS AND ERRORS OR OMISSIONS ON SHOP DRAWINGS.

4105 Sartelon
Ville St. Laurent, PQ
H4S-2B3

Phone: 514-334-7230
Fax: 514-334-5070
www.veoliawatertechnologies.ca

WWTP UPGRADE
IQALUIT - WASTE WATER PROJECT
CONTROL PANEL LCP-02-300
PROJET #5000218036

Jan 29, 2019 16:26:52 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-EPL-0001-AU-VWT-001.dwg - rasiarn

STD: "B" 11x17 REF: A6798A BAR = 1" AT PLOT SCALE

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY COPYRIGHT, PATENT AND/OR OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE, THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO RIGHTS ARE GRANTED BY CONVEYING, RECEIVING OR POSSESSING THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, PRINTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR PURPOSES OTHER THAN THE SPECIFIC PROJECT RELATED TO THE INTENDED PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
TITLE PAGE

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, H4J 0S4 (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0001-AU-VWT		–	01 OF 06	1

DESCRIPTION	DRAWING NUMBER
MAIN CONTROL PANEL LCP-02-300	
TITLE PAGE	5000218036-EPL-0001-AU-VWT-001
LEGEND & DRAWING LIST	5000218036-EPL-0001-AU-VWT-002
EXTERNAL LAYOUT	5000218036-EPL-0001-AU-VWT-003
INTERNAL LAYOUT	5000218036-EPL-0001-AU-VWT-004
TERMINAL LAYOUT	5000218036-EPL-0001-AU-VWT-005
BILL OF MATERIAL	5000218036-EPL-0001-AU-VWT-006
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-001
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-002
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-003
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-004
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-005
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-006
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-007
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-008
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-009
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-010
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-011
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-012
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-013
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-014
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-015
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-016
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-017
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-018
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-019
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-020
ELECTRICAL SCHEMATICS	5000218036-ELD-0001-AU-VWT-021

LEGEND

- LOW PRESSURE
- HIGH PRESSURE
- LOW LEVEL
- HIGH LEVEL
- LIMIT SWITCH
- LIMIT SWITCH
- LOW FLOW
- HIGH FLOW
- RELAY CONTACT
- RELAY CONTACT
- RELAY CONTACT
- ON DELAY TIMER
- OFF DELAY TIMER
- GROUND
- ISOLATED GROUND
- FUSE (POWER)
- FUSE (CONTROL)
- DISTRIBUTION BLOCK
- MAINTAINED TWO SELECTOR SWITCH
- MAINTAINED 3 POSITIONS SELECTOR SWITCH
- SPRING RETURN FROM LEFT 3 POSITIONS SELECTOR SWITCH
- SPRING RETURN FROM RIGHT 3 POSITIONS SELECTOR SWITCH
- SPRING RETURN FROM BOTH 3 POSITIONS SELECTOR SWITCH
- PUSH BUTTON
- PUSH BUTTON
- PULL BUTTON
- PULL BUTTON
- EMERGENCY STOP BUTTON
- POTENTIOMETER
- CURRENT TRANSFORMER
- THERMOSTAT
- THERMOSTAT
- 1 POLE CIRCUIT BREAKER
- COOLING FAN
- RECEPTACLE 120VAC WITH RJ45
- RECEPTACLE 120VAC DUPLEX
- PILOT LIGHT
- PUSH TO TEST PILOT LIGHT
- RELAY COIL
- RELAY COIL WITH SURGE SUPPRESSOR
- CONTACTOR COIL
- CONTACTOR COIL WITH SURGE SUPPRESSOR
- ALARM
- RESISTOR
- SOLENOID
- PULL CORD
- ZERO SPEED DETECTOR
- POWER BLOCK FOR FIELD WIRING
- TERMINAL
- WIRING JUNCTION
- KNIFE TERMINAL
- 3 POLES THERMAL MAGNETIC CIRCUIT BREAKER
- 3 POLES MAGNETIC CIRCUIT BREAKER
- 3 POLES FUSIBLE DISCONNECT SWITCH
- 3 POLES DISCONNECT SWITCH
- 3 POLES CONTACTOR
- 3 POLES OVERLOAD RELAY
- 1 POLE TRANSFORMER (H3, H2, H1, X2, X4, X1, X3)

WIRE COLOR CODE

MINIMAL 18AWG GAUGE	
POWER 120VAC	BLACK
CONTROL 120VAC	RED
NEUTRAL	WHITE
24VDC	BLUE
0VDC	BLUE/WHITE
DRY CONTRACT	YELLOW, 14AWG
NON-ISOLATED GROUND	GREEN
ISOLATED GROUND	GREEN/YELLOW
TWISTED PAIR	(+) BLACK & (-) WHITE

WIRE NUMBER

XX XX XX
- XX — LINE NUMBER
- XX — PAGE NUMBER
- XX — PANEL NUMBER

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROVIDED IN ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED IN WHOLE OR IN PART FOR ANY PURPOSE THAT IS EXPRESSLY SUBMITTED AND HAS NOT/OR LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT, THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, IN WHOLE OR IN PART, IN CONNECTION WITH ANY PROJECT OTHER HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE: CONTROL PANEL LCP-02-300
LEGEND & DRAWING LIST

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc. Canada, Tel: (514) 334-7230


PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0001-AU-VWT		–	02 OF 06	1


STD: "B" 11x17 | REF: A6798A | BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:26:53 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-EPL-0001-AU-VWT-002.dwg – rasiani


NAME-PLATES

ENCLOSURE NEMA 4X-SS304 / 72H'' X 36W'' X 16D''
CSA APPROVAL





NAME-PLATES DETAILS :



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND ITS AFFILIATES (VWT). ANY INTELLECTUAL PROPERTY RIGHTS INCLUDED IN THIS DOCUMENT ARE PROPRIETARY TO VWT AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS SUBMITTED AND MUST BE RETURNED AT VWT'S REQUEST. BY ACCEPTANCE OF THIS SUBMISSION OF THIS DOCUMENT, THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF VWT AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF VWT. ALL THE DESIGN CONCEPTS AND INFORMATION CONTAINED IN THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER THAT IS DETRIMENTAL TO THE INTERESTS OF VWT. ALL COPYRIGHTS AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A

TITLE: CONTROL PANEL LCP-02-300
INTERNAL LAYOUT

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, H4S 2B3 T (514) 334-7230


PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL	0001-AU-VWT	–	03 OF 06	1

STD "B" 11x17 | REF: A6798A | BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:26:55 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\800-DESIGN\800-DRAWINGS\LCP-02-300\REV 1\5000218036-EPL-0001-AU-VWT-003.dwg - rsalam

Jan 29, 2019 16:26:57 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000 DRAWINGS\LCP-02-300\REV 1\5000218036-EPL-0001-AU-VWT-004.dwg rostam

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17



REV	DESCRIPTION	DATE	RCVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE DISCLOSED TO ANY THIRD PARTY UNLESS SUCH DISCLOSURE IS EXPRESSLY GRANTED AND NO IMPLIED LICENCE IS GRANTED. OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT, THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, IN WHOLE OR IN PART, IN CONTEXTS OR FOR PURPOSES NOT INTENDED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE: CONTROL PANEL LCP-02-300 INTERNAL LAYOUT

CLIENT: WWTP UPGRADE CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0001-AU-VWT	–	04 OF 06	1

ITEM	DESCRIPTION	PART NUMBER	MANUF.	QTY	BY
1	NEMA 4X ENCLOSURE, SS304, DIM 72"H x 36"W x 16"D C/W CP7236, CMFXSS	CSD723616SSR	HOFFMAN	1	ENV
2	DATA POCKET 6"H x 6"W x 0.75"D	–	–	1	ENV
3	LED LIGHT 23 IN, 120V 10W C/W CABLE LS2-PC6 + SIMPLE OUTLET 120VAC 2963860 PHOENIX	LS2-239-4	PREMISE	1	ENV
4	DOOR SWITCH 1NO	FLKDS	HAMMOND	2	ENV
5	COOLING FILTER FAN NEMA12 24VDC C/W OUTLET FILTER RITTAL 3239.200 + 3239.080 (2X)	3239.124	RITTAL	1	ENV
6	COOLING THERMOSTAT 0@60DEG C, 1NO CONTACT	FGT-200	DBK	1	ENV
7	SAFETY RELAY 24VDC	440R-G23216	ALLEN-BRADLEY	1	ENV
8	UNMANAGED ETHERNET SWITCH, 8 PORT	IES-180B	WEIDMULLER	1	ENV
9	POWER SUPPLY 24VDC, 480W, 20AMP	1606XLS480EC	ALLEN-BRADLEY	1	ENV
10	GND LUG, COPPER	CB3536CY	PANDUIT	1	ENV
11	GND BAR, COPPER	4C-190	NSI	1	ENV
12	FUSE HOLDER 1 POLE TYPE CC C/W FUSE, ATMR-20(1X)	USCC1	MERSEN	1	ENV
12 –	– –	– –	– –	– –	ENV
13	2 POLES RELAY, 120VAC COIL C/W BASE 700-HN222	700-HK32A1	ALLEN-BRADLEY	A/R	ENV
14	BREAKER 1P, 277VCA, CURVE C, XA ACCORDING TO THE TERMINAL LAYOUT PAGE	M9FXXXX	SCHNEIDER	A/R	ENV
15	RELAY 2POT COIL 24VDC C/W BASE 700-HN222	700-HK32Z24	ALLEN-BRADLEY	A/R	ENV
16	SIMPLE OUTLET, 120VAC	2963860	PHOENIX CONTACT	3	ENV
17	TERMINAL 2 LEVEL WDK 2.5 C/W END PLATE 1059100000	1021500000	WEIDMULLER	LOT	ENV
18	TERMINAL 3 LEVEL DLD 2.5 C/W END PLATE 1784210000	1784180000	WEIDMULLER	LOT	ENV
19	TERMINAL 600VAC/DC, 20A WDU 2.5 C/W END PLATE 1050000000	1020000000	WEIDMULLER	LOT	ENV
20	KNIFE TERMINAL 300VAC/DC, 10A, WTR 2.5 C/W END PLATE 1050000000	1855610000	WEIDMULLER	LOT	ENV
21	TERMINAL 1 LEVEL WDU 4 C/W END PLATE 1050000000	1020100000	WEIDMULLER	LOT	ENV
22	TERMINAL 1 LEVEL WDU 6 C/W SEPARATOR 1050100000	1020200000	WEIDMULLER	LOT	ENV
23	WHITE PILOT LIGHT, 30mm 120VAC	9001SKP3BW31	SQUARE D	1	ENV
24	RED PILOT LIGHT, 30mm 24VDC	9001SKP3SR31	SQUARE D	1	ENV
25	BLACK PUSH BUTTON, 30mm NEMA4X	9001SKR1U	SQUARE D	1	ENV
26	RED EMERGENCY STOP PUSH BUTTON, 30mm C/W CONTACT	9001SKR16H2	SQUARE D	1	ENV
27	END ANCHOR WEW 35/2	1061200000	WEIDMULLER	A/R	ENV
28	FUSE HOLDER ¼ X 1¼ WSI 4/2	1880430000	WEIDMULLER	A/R	ENV
29	FUSE TERMINAL C/W END PLATE 1492-N37	9532440000	WEIDMULLER	A/R	ENV
30	FAST ACTING MINI FUSE 5X20MM 250VAC XA C/W SPARE	GMA-X	BUSSMANN	A/R	ENV
31	FUSE, FAST ACTING, 1/4 x 1-1/4, XA	AGC-X	BUSSMANN	A/R	ENV

VEOLIA PARTS LIST

ITEM	DESCRIPTION	PART NUMBER	MANUF.	QTY	BY
100	PanelView Plus 7 Performance Terminal, Touch Screen, 12 WXGA 24VDC	2711P-T12W22D9P	ALLEN-BRADLEY	1	VEO
101	MODEM, 24VDC	E-WON	FLEXY20500-00	1	VEO
102	PLC POWER SUPPLY 120VAC, 200VA	1769-PA4	ALLEN-BRADLEY	2	VEO
103					VEO
104	INPUT CARD, 16 PTS, 24VDC	1769-IQ16	ALLEN-BRADLEY	7	VEO
105	OUTPUT CARD, 16 PTS	1769-OW16	ALLEN-BRADLEY	3	VEO
106	ANALOG OUTPUT CARD, 8 PTS	1769-OF8C	ALLEN-BRADLEY	2	VEO
107	ANALOG INPUT CARD, 16PTS	1756-IF16	ALLEN-BRADLEY	1	VEO
108	PLC CPU	1769-L33ERM	ALLEN-BRADLEY	1	VEO
109	RIGHT END CAP	1769-ECR	ALLEN-BRADLEY	1	VEO
110	EXPANSION CABLE RIGHT TO LEFT CABLE	1769-CRL3	ALLEN-BRADLEY	1	VEO
111	EXPANSION CABLE RIGHT TO LEFT CABLE	1769-CRL3	ALLEN-BRADLEY	1	VEO
112	UPS, 1000VA, 120VAC, 1PH	PW9130L1000T-XL	EATON	1	VEO

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	RA	HZ	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. ANY UNAUTHORIZED USE, DISCLOSURE OR REPRODUCTION IS PROHIBITED. THIS DOCUMENT AND THE INFORMATION CONTAINED HEREIN WAS PREPARED FOR THE EXCLUSIVE USE OF V.W.T. AND IS SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED OR USED IN WHOLE OR IN PART FOR ANY OTHER MARKETS WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE PURPOSE OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL YOU REMOVE OR ALTER THIS CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE. YOU AGREE NOT TO USE IN A MANNER CONTRARY TO THE INTERESTS OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
BILL OF MATERIAL


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc. Canada. Tel. (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
50002180.36-EPL – 0001-AU-VWT	–	06 OF 06	1

STD: "B" 11x17 | REF: A6798A | BAR = 1" AT PLOT SCALE

Jan 29, 2019 - 16:26:56 - G:\Projets A67XX\A6798A - VEOLIA - 50002180.36 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\50002180.36-EPL-0001-AU-VWT-006.dwg - rosiani



WIRING
VEOLIA
CUSTOMER
INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION IT CONTAINS MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS CONVEYED WHATSOEVER BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. THEY MUST NOT BE USED IN CONNECTION WITH ANY WORK OTHER THAN THE DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY ANY PARTY FOR ANY PURPOSE IN THE ABSENCE OF V.W.T. ALL COPYRIGHT, MORAL AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
500021 8036-ELD – 0001-AU-VWT		–	01 OF 21	1

STD. "B" 11x17 | REF.: A6798A | BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:00 - G:\Projets A67XX\A6798A - VEOLIA - 500021 8036 Iqaluit WWTP Upgrade\DOC\DESIN\000-DRAWINGS\LCP-02-300\REV 1\500021 8036-ELD-0001-AU-VWT-001.dwg - rastoni



BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE, MAY NOT BE USED, DISCLOSED OR REPRODUCED WITHOUT THE PRIOR WRITTEN CONSENT OF V.W.T. AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THE DESIGN CONCEPTS AND INFORMATION CONTAINED IN THIS DOCUMENT HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OR DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc. Canada, Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	02 OF 21	1

Jan 29, 2019 16:27:00 – G:\Projets A6?XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-002.dwg – rosloni



BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE EXCLUSIVE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED SOLELY FOR THE PURPOSE FOR WHICH THE DOCUMENT WAS SUBMITTED AND NOT FOR ANY OTHER PURPOSE. BY ACCEPTANCE OR REFERENCE BY THE SUBMISSION OF THIS DOCUMENT, THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, MODIFIED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. AND UPON REQUEST THEY MUST BE RETURNED. THE RECEIPT OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN (FOR AMENDED PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT, IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–
DATE	–
CHECKER	–
DATE	–
ENGINEER	–
DATE	–
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc. Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	03 OF 21	1	

Jan 29, 2019 16:27:02 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-003.dwg – rgsan



BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT AND ARE SUBMITTED IN CONFIDENCE. THEY MUST NOT BE DISCLOSED, USED OR REPRODUCED FOR PURPOSES FOR WHICH THE DOCUMENT IS NOT EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF VWT AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, TRANSMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF VWT. IF YOU ARE NOT THE INTENDED RECIPIENT OF THIS DOCUMENT, YOU MUST RETURN THE DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTERESTS OF VWT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THIS DOCUMENT OR ITS CONTENTS CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT		–	04 OF 21	1

Jan 29, 2019 16:27:03 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-004.dwg – rosiarn



CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. ANY USE IS PROHIBITED IN ALL APPLICABLE LAWS, UNLESS SO AGREED TO EXPRESSLY IN WRITING BY VWT. ALL THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE. THE RECIPIENT UNDERTAKES TO KEEP ALL SUCH PRIVILEGED INFORMATION IF VWT AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF VWT. VWT ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER NOT RELATED TO THE INTENT OF THIS DOCUMENT. IN ADDITION, IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF VWT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

REV	DESCRIPTION	DATE	DESIGNED	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT		–	05 OF 21	1

STD: "B" 11x17
REF: A6798A
BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:03 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-005.dwg – rasloni



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND INTELLECTUAL (OR INDUSTRIAL) PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE THE EXCLUSIVE PROPERTY OF V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TO BE DISCLOSED TO ANY THIRD PARTY AND MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO REPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PROPRIETARY INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED TO ANY THIRD PARTY OR USED FOR ANY PURPOSE OTHER THAN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OF THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED BY THE RECIPIENT OR ANY THIRD PARTY IN VIOLATION OF V.W.T. AS COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sarbois, Saint-Laurent, QC, Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT		–	06 OF 21	1

STD: "B" 11x17
REF: A6798A
BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:05 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-006.dwg - rasian



CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROVIDED BY ALL APPLICABLE LAW, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. ALL RIGHTS ARE RESERVED. CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION AND MUST NOT BE DISCLOSED, REPRODUCED, LOANED OR TRANSMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE EXPRESS PURPOSE FOR WHICH THE DOCUMENT IS SUBMITTED. ANY USE OF THESE DESIGN CONCEPTS AND INFORMATION SHALL THIS DOCUMENT BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	07 OF 21	1

STD: "B" 11x17 | REF: A67984 | BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:05 - G:\Projets A67XX\A67984 - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-007.dwg - rasiani



RACK 00 SLOT 01 DIGITAL INPUT 1769-IQ16		
IN 0	I:001.00	ALARM RESET
IN 1	I:001.01	EMERGENCY STOP
IN 2	I:001.02	EMERGENCY STOP RELAY
IN 3	I:001.03	UPS ALARM
IN 4	I:001.04	POWER
IN 5	I:001.05	DAF 1 HIGH LEVEL SIGNAL LSH-02-330
IN 6	I:001.06	DAF 1 SUBNATANT VALVE OPEN SIGNAL OPEN STATUS ZSO-02-625
IN 7	I:001.07	DAF 1 SUBNATANT VALVE CLOSED SIGNAL CLOSE STATUS ZSC-02-625
		DC COM
IN 8	I:001.08	DAF 1 SLUDGE SCRAPPER REM HI-DDR-02-311
IN 9	I:001.09	DAF 1 SLUDGE SCRAPPER RUNNING YI-DDR-02-311
IN 10	I:001.10	DAF 1 SLUDGE SCRAPPER OVERLOAD UA-DDR-02-311
IN 11	I:001.11	DAF 1 HIGH LEVEL SLUDGE SIGNAL LSH-02-332
IN 12	I:001.12	DAF 1 LOW LEVEL SLUDGE SIGNAL LSL-02-333
IN 13	I:001.13	DAF 1 SPIDFLOW CONTROL VALVE OPEN SIGNAL OPEN STATUS ZSO-02-309
IN 14	I:001.14	DAF 1 SPIDFLOW CONTROL VALVE CLOSED SIGNAL CLOSE STATUS ZSC-02-309
IN 15	I:001.15	DAF 1 SPIDFLOW CONTROL VALVE OPEN SIGNAL OPEN STATUS ZSO-02-310
		DC COM

010841 010842 010843 010844 010845 010846 010847 010848 010849 010850 010851 010852 010853 010854 010855 010856 010857 010858 010859 010860 010861 010862 010863 010864 010865 010866 010867 010868 010869 010870 010871 010872 010873 010874 010875 010876 010877 010878 010879 010880

Jan 29, 2019 16:27:07 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-008.dwg - rasam

BAR = 1" AT PLOT SCALE

REF: A6798A

STD - "B" 11x17

WIRING
- - - - VEOLIA
——— CUSTOMER
——— INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. (V.W.T.) AND IS PROTECTED BY COPYRIGHT. THIS DOCUMENT IS ESPRIOR AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIENARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY ELEMENTED AND MUST BE RETURNED AT ANY TIME IF SO DEMANDED BY THE SUBMITTER OF THIS DOCUMENT. THEY ARE OTHERWISE BY THE SUBMITTER OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND THE RECIPIENT AGREES TO MAINTAIN THEM AS SUCH. THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN IN CONNECTION WITH ANY OTHER PROJECT THAN THE ONE FOR WHICH IT IS PREPARED AND ISSUED BY V.W.T. IN RELATION TO THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN SHALL NOT BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.


		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4760 Sartelon, Saint-Laurent, Qc, Canada, Tel (514) 334-7730

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	08 OF 21	1



WIRING
VEOLIA
CUSTOMER
INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION IT CONTAINS MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. AND THEY MUST NOT BE USED IN WHOLE OR IN PART FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE INTENT OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED FOR THE BENEFIT OF THIRD PARTIES WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. ALL COPYRIGHT, MORAL AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC., 4105 Sartelon Saint-Laurent, Qc. Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT		–	09 OF 21	1

STD: "B" 11x17 REF: A6798A BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:08 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-009.dwg – rasloni



BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

WIRING
VEOLIA
CUSTOMER
INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE USED IN WHOLE OR IN PART FOR ANY PURPOSE WHICH IS EXPRESSLY SUBMITTED AND HAS NOT BEEN LICENCED IN COMMITTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT, THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, IN WHOLE OR IN PART, IN CONTEXTS OR FOR PURPOSES NOT INTENDED BY V.W.T. OR FOR ANY USE OF THE DESIGN CONCEPTS HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE – –
CHECKER	DATE – –
ENGINEER	DATE – –
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel.: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT		–	10 OF 21	1

Jan 29, 2019 16:27:09 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-010.dwg – rosiani



BAR = 1" AT PLOT SCALE

REF: A6798A

STD. "B" 11x17

WIRING
VEOLIA
CUSTOMER
INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT LAWS. ANY DESIGN CONCEPTS, DESIGN DETAILS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED HEREBY. THIS DOCUMENT AND ITS CONTENTS SHALL REMAIN CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT FULLY COMPLY WITH THE TERMS AND CONDITIONS OF THE CONTRACT. SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	


TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon Saint-Laurent Qc Canada, Tel: (514) 334-7238

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT	–	11 OF 21	1

Jan 29, 2019 - 16:27:10 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-011.dwg - rosiani



RACK 00 SLOT 05 DIGITAL INPUT 1769-IQ16		
IN 0	I:005.00	ESD SWITCH FROM P-02-450 SIGNAL HS-ESD-02-450
IN 1	I:005.01	START – STOP SWITCH P-02-450 SIGNAL HS-02-450
IN 2	I:005.02	DAF 2 WHITE WATER PUMP 3 REM HI-P-02-460
IN 3	I:005.03	DAF 2 WHITE WATER PUMP 3 RUNNING YI-P-02-460
IN 4	I:005.04	DAF 2 WHITE WATER PUMP 3 OVERLOAD UA-P-02-460
IN 5	I:005.05	ESD SWITCH FROM P-02-460 SIGNAL HS-ESD-02-460
IN 6	I:005.06	START – STOP SWITCH P-02-460 SIGNAL HS-02-460
IN 7	I:005.07	DAF 2 WHITE WATER STRAINER 1 IN VALVE OPEN STATUS ZSO-02-531
		DC COM
IN 8	I:005.08	DAF 2 WHITE WATER STRAINER 1 IN VALVE CLOSE STATUS ZSC-02-531
IN 9	I:005.09	DAF 2 WHITE WATER STRAINER 1 OUT VALVE OPEN STATUS ZSO-02-532
IN 10	I:005.10	DAF 2 WHITE WATER STRAINER 1 OUT VALVE CLOSE STATUS ZSC-02-532
IN 11	I:005.11	DAF 2 WHITE WATER STRAINER 2 IN VALVE OPEN STATUS ZSO-02-541
IN 12	I:005.12	DAF 2 WHITE WATER STRAINER 2 IN VALVE CLOSE STATUS ZSC-02-541
IN 13	I:005.13	DAF 2 WHITE WATER STRAINER 2 OUT VALVE OPEN STATUS ZSO-02-542
IN 14	I:005.14	DAF 2 WHITE WATER STRAINER 2 OUT VALVE CLOSE STATUS ZSC-02-542
IN 15	I:005.15	SPARE
		DC COM

011241 011242 011243 011244 011245 011246 011247 011248 011249 011250 011251 011252 011253 011254 011255 011256 011257 011258 011259 011260 011261 011262 011263 011264 011265 011266 011267 011268 011269 011270 011271 011272 011273 011274 011275 011276 011277 011278 011279 011280

BAR = 1" AT PLOT SCALE

REF: A6798A

STD: "B" 11x17

WIRING

VEOLIA

CUSTOMER

INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
THIS WRITTEN INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE AND MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THEY WERE SUBMITTED. NO LICENSE, EXPRESS OR IMPLIED, UNDER ANY PATENT LICENCE IS GRANTED OR IMPLIED BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, MODIFIED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. AND UPON REQUEST TO RETURN THEM TO V.W.T. IN THE EVENT THAT DESIGNS AND DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DESIGNS IN THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE
–	–
CHECKER	DATE
–	–
ENGINEER	DATE
–	–
SCALE:	N/A


TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon Saint-Laurent, Qc. Canada. Tel (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	12 OF 21	1

Jan 29, 2019 16:27:10 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-012.dwg – rsalani



BAR = 1" AT PLOT SCALE

REF: A6798A

STD. "B" 11x17

WIRING

VEOLIA

CUSTOMER

INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE COPYRIGHT, TRADE SECRET AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS CREATED OTHERWISE. BY THE SUBMISSION OF THIS DOCUMENT, EACH VIEWER AGREES TO PROTECT THE CONFIDENTIAL NATURE THEREOF AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS, WRITTEN CONSENT OF VWT. VWT ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN ANY MODIFIED FORM FOR ANY PURPOSE WHATSOEVER, UNLESS SPECIFICALLY AUTHORIZED BY VWT IN WRITING. IN NO EVENT SHALL THE DISCLOSURE OF THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF VWT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4760 Garlain Saint-Laurent, Qc. Canada Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	13 OF 21	1

Jan 29, 2019 16:27:12 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-013.dwg – rasiani

Jan 29, 2019 16:27:13 - C:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOCUMENTS\DESIGN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VW1-014.dwg - rasion

BAR = 1" AT PLOT SCALE

REF: A6798A

SIZE: "B" 11x17

[010416]

011401	010416	0V1	
011402			
011403			
011404			010416
011405			
011406			010416
011407			
011408			010416
011409			
011410			010416
011411			
011412			010416
011413			
011414			010416
011415			
011416			010416
011417			
011418			010416
011419			
011420			
011421			
011422			010416
011423			
011424			010416
011425			
011426			010416
011427			
011428			010416
011429			
011430			010416
011431			
011432			010416
011433			
011434			010416
011435			
011436			010416
011437			
011438			
011439	010416	0V1	
011440			

RACK 00 SLOT 07
DIGITAL INPUT
1769-IQ16

011404	IN 0	I:007.00	SPARE
011406	IN 1	I:007.01	SPARE
011408	IN 2	I:007.02	SPARE
011410	IN 3	I:007.03	SPARE
011412	IN 4	I:007.04	SPARE
011414	IN 5	I:007.05	SPARE
011416	IN 6	I:007.06	SPARE
011418	IN 7	I:007.07	SPARE
			DC COM
011422	IN 8	I:007.08	SPARE
011424	IN 9	I:007.09	SPARE
011426	IN 10	I:007.10	SPARE
011428	IN 11	I:007.11	SPARE
011430	IN 12	I:007.12	SPARE
011432	IN 13	I:007.13	SPARE
011434	IN 14	I:007.14	SPARE
011436	IN 15	I:007.15	SPARE
			DC COM

011441 011442 011443 011444 011445 011446 011447 011448 011449 011450 011451 011452 011453 011454 011455 011456 011457 011458 011459 011460 011461 011462 011463 011464 011465 011466 011467 011468 011469 011470 011471 011472 011473 011474 011475 011476 011477 011478 011479 011480

WIRING

- VEOLIA
- CUSTOMER
- INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	SG	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND/OR ITS AFFILIATES AND, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERRED. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THIS DOCUMENT IS EXPRESSLY SUBMITTED AND NO OTHER LICENCE IS GRANTED. IF THERE IS NO WRITTEN AGREEMENT OF THIS DOCUMENT, THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF VWT AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF VWT. VWT ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR CONCEPTS, INFORMATION CONTAINED HEREIN OR DERIVED HEREFROM IN WHOLE OR IN PART, OR IN A MANNER THAT DOES NOT CONFORM TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF VWT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	


TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	14 OF 22	5



WIRING

VEOLIA

CUSTOMER

INTERNAL WIRING

REV	DESCRIPTION	DATE	DESIGNED	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. (VWT) AND SHALL NOT BE USED, RELEASE OR LICENSED BY VWT TO ANY THIRD PARTY WITHOUT THE EXPRESS WRITTEN CONSENT OF VWT. ANY USE, RELEASE OR LICENSE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN IN A MANNER THAT DOES NOT FULLY RESPECT THE RIGHTS OF VWT IS STRICTLY PROHIBITED. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF VWT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230


PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	15 OF 21	1

REF: A6798A

STD: "B" 11x17

BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:14 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOCUMENTS\DESIGN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-015.dwg - rosan



WIRING

- VEOLIA
- CUSTOMER
- INTERNAL WIRING

REV	DESCRIPTION	DATE	DESIGNED	CHKD	APVD	ECN
Z						
E	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERRED, DISCLOSED OR LOANED UNDER ANY EXPRESS OR IMPLIED AGREEMENT. THIS DOCUMENT MUST BE USED SOLELY FOR THE PURPOSE FOR WHICH IT IS SUBMITTED AND NO REPLICA LICENCE IS GRANTED OR IMPLIED BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PURPOSE, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

	DESIGNER	DATE
	–	–
	CHECKER	DATE
	–	–
	ENGINEER	DATE
	–	–
	SCALE:	N/A

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	16 OF 21	1

STD: "B" 11x17
REF: A6798A
BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:15 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP
\prg\dgn\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-016.dwg – rasini



Jan 29, 2019 16:27:15 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-WWT-017.dwg - rosiani

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
Z						
E	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THIS DOCUMENT AND THE INFORMATION CONTAINED HEREIN MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, MODIFIED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY FOR ANY USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED TO THE DETRIMENT OR DESTRUCTION, TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.


DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7730

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036 – ELD	– 0001 – AU – WWT	–	17 OF 21	1



WIRING
VEOLIA
CUSTOMER
INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS, PURSUANT TO ALL APPLICABLE LAW, RECORDED AS WE SAVED TO DEPENDENT AND OWNED INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ITS ENTIRETY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY WAYS WHATSOEVER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY FOR ANY USE OF THE DESIGN CONCEPTS OR INFORMATION CONTAINED HEREIN IF THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE USED FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. BY ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

	DATE
DESIGNER	–
CHECKER	–
ENGINEER	–
SCALE: N/A	

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 6105 Sartelon, Saint-Laurent, Qc. Canada. Tel. (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT		–	18 OF 21	1

STD: "B" 11x17
REF: A6798A
BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:17 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-018.dwg – rosiam



WIRING
VEOLIA
CUSTOMER
INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND TRADE SECRET LAWS. ANY USE OF THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERRED OR LICENSED AND MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF VWT AND THEY MUST NOT BE DISCLOSED TO ANY PERSON OR ENTITY OTHER THAN THOSE TO WHOM THEY ARE ORIGINALLY ISSUED, REPRODUCED OR DISCLOSED IN ANY MANNER WHOLE OR IN PART IN ANY FORM OR BY ANY MEANS WITHOUT THE EXPRESS WRITTEN CONSENT OF VWT. VWT ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT FULFILL THE INTENDED PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN ANY MANNER THAT DEFAMES OR DISPARAGES OF VWT. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE: CONTROL PANEL LCP-02-300 ELECTRICAL SCHEMATIC


CLIENT: WWTP UPGRADE CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc. Canada, Tel (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	19 OF 21	1

STD: "B" 11x17 | REF: A6798A | BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:17 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-019.dwg – rasanl



WIRING
VEOLIA
CUSTOMER
INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. ANY USE OF THIS DOCUMENT BY THE RECIPIENT FOR ANY PURPOSE OTHER THAN THAT FOR WHICH IT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF VWT AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF VWT. YOU AGREE TO BE BOUND BY THE FOREGOING TERMS FOR THE USE OF THIS DOCUMENT AND THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF VWT AND ITS CLIENTS. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada. Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD	0001-AU-VWT	–	20 OF 21	1

STD. "B" 11x17 | REF: A6798A | BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:19 - G:\Projets A6?XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\0000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-020.dwg - rasmi



WIRING

- VEOLIA
- CUSTOMER
- INTERNAL WIRING

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-03	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED IN ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE, AND SHALL REMAIN, THE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND ARE NOT TRANSFERABLE. THIS DOCUMENT IS LOANED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED NOTWITHSTANDING 17.01.1 AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, RELAYED OR USED IN WHOLE OR IN PART FOR ANY PURPOSE WITHOUT THE WRITTEN CONSENT OF V.W.T. VEOLIA WATER TECHNOLOGIES CANADA INC. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN ANY MANNER THAT MAY INFRINGE UPON THE RIGHTS OF VEOLIA WATER TECHNOLOGIES CANADA INC. OR ANY OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	–
DATE	–
CHECKER	–
DATE	–
ENGINEER	–
DATE	–
SCALE:	N/A

TITLE
CONTROL PANEL LCP-02-300
ELECTRICAL SCHEMATIC

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc. Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-ELD – 0001-AU-VWT		–	21 OF 21	1

STD. "B" 11x17 | REF.: A6798A | BAR = 1" AT PLOT SCALE

Jan 29, 2019 16:27:20 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\LCP-02-300\REV 1\5000218036-ELD-0001-AU-VWT-021.dwg – rasloni

WWTP UPGRADE
CITY OF IQALUIT
CONTROL JUNCTION BOX
JB-001
PROJECT: 5000218036

BAR = 1" AT PLOT SCALE

REF: A6798A

STD. "B" 11x17

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF V.W.T. AND IS PROTECTED BY COPYRIGHT. IT IS PRODUCED IF AN UPGRADE LABS, REQUIRE BE NOT USED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED. THIS DOCUMENT MUST NOT BE COPIED IN WHOLE OR IN PART. IT IS CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT, OR PORTIONS THEREOF, FOR PURPOSES OTHER THAN THOSE INTENDED AT THE TIME OF ISSUE. V.W.T. MAKES NO WARRANTY THAT USERS HEREOF TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, MORAL AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	–	–
CHECKER	–	–
ENGINEER	–	–
SCALE:	N/A	

TITLE: JB-001 CONTROL JUNCTION BOX TITLE PAGE

CLIENT: WWTP UPGRADE CITY OF IQALUIT

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc. Canada, Tel: (514) 334-7230

PROJECT DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0002-AU-VWT	–	01 OF 05	1

Jan 29, 2019 15:45:36 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\5000218036-EPL-0002-AU-VWT-001.dwg – rasiani

Jan 29, 2019 15:45:38 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\5000218036-EPL-0002-AU-VWT-002.dwg - rastoni

BAR = 1" AT PLOT SCALE

REF: A6798A

STD "B" 11x17

DRAWING LIST

DESCRIPTION	DRAWING NUMBER
CONTROL JUNCTION BOX JB-001	
TITLE PAGE	5000218036-EPL-0002-AU-VWT-001
LEGEND & DRAWING LIST	5000218036-EPL-0002-AU-VWT-002
EXTERNAL & INTERNAL LAYOUT	5000218036-EPL-0002-AU-VWT-003
BILL OF MATERIAL	5000218036-EPL-0002-AU-VWT-004
TERMINAL LAYOUT	5000218036-EPL-0002-AU-VWT-005
FIELD WIRING	5000218036-EID-0002-AU-VWT-001
FIELD WIRING	5000218036-EID-0002-AU-VWT-002

LEGEND

LOW PRESSURE
HIGH PRESSURE
LOW LEVEL
HIGH LEVEL
LIMIT SWITCH
LIMIT SWITCH
LOW FLOW
HIGH FLOW
RELAY CONTACT
RELAY CONTACT
RELAY CONTACT
ON DELAY TIMER
OFF DELAY TIMER
GROUND
ISOLATED GROUND
FUSE (POWER)
FUSE (CONTROL)
DISTRIBUTION BLOCK

MAINTAINED TWO SELECTOR SWITCH
MAINTAINED 3 POSITIONS SELECTOR SWITCH
SPRING RETURN FROM LEFT 3 POSITIONS SELECTOR SWITCH
SPRING RETURN FROM RIGHT 3 POSITIONS SELECTOR SWITCH
SPRING RETURN FROM BOTH 3 POSITIONS SELECTOR SWITCH
PUSH BUTTON
PUSH BUTTON
PULL BUTTON
PULL BUTTON
EMERGENCY STOP BUTTON
POTENTIOMETER
CURRENT TRANSFORMER
THERMOSTAT
THERMOSTAT
1 POLE CIRCUIT BREAKER

COOLING FAN
RECEPTACLE 120VAC WITH RJ45
RECEPTACLE 120VAC DUPLEX
PILOT LIGHT
PUSH TO TEST PILOT LIGHT
RELAY COIL
RELAY COIL WITH SURGE SUPPRESSOR
CONTACTOR COIL
CONTACTOR COIL WITH SURGE SUPPRESSOR
ALARM
RESISTOR
SOLENOID
PULL CORD
ZERO SPEED DETECTOR

POWER BLOCK FOR FIELD WIRING
TERMINAL
WIRING JUNCTION
KNIFE TERMINAL

3 POLES THERMAL MAGNETIC CIRCUIT BREAKER
3 POLES MAGNETIC CIRCUIT BREAKER
3 POLES FUSIBLE DISCONNECT SWITCH
3 POLES DISCONNECT SWITCH
3 POLES CONTACTOR
3 POLES OVERLOAD RELAY
1 POLE TRANSFORMER (H3, H2, H1, X2, X4, X1, X3)

WIRE COLOR CODE	
MINIMAL 18AWG GAUGE	
POWER 120VAC	BLACK
CONTROL 120VAC	RED
NEUTRAL	WHITE
24VDC	BLUE
0VDC	BLUE/WHITE
DRY CONTRACT	YELLOW, 14AWG
NON-ISOLATED GROUND	GREEN
ISOLATED GROUND	GREEN/YELLOW
TWISTED PAIR	(+) BLACK & (-) WHITE

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE CONFIDENTIAL TO VWT AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE AND MUST NOT BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF VWT, AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REWRITTEN OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF VWT. VWT ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL VWT BE LIABLE FOR ANY USE OF THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER CONTRARY TO THE INTEGRITY OF VWT ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A


TITLE: JB-001 CONTROL JUNCTION BOX LEGEND & DRAWING LIST

CLIENT: WWTP UPGRADE CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc. Canada. Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0002-AU-VWT	–	02 OF 05	1

ENCLOSURE NEMA 4X FIERGLASS / 14H'' X 12W'' X 6D'' (PJ14126RL)
cUL APPROVAL



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-09	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND ITS AFFILIATED LIKE, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THEY ARE SUPPLIED AS EXPRESSLY SUBMITTED AND NO IMPLIED LICENCE IS GRANTED HEREUNDER. BY ACCEPTANCE OF THIS DOCUMENT, THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS OR INFORMATION CONTAINED HEREIN FOR ANY PURPOSE OTHER THAN THE PURPOSE FOR WHICH THIS DOCUMENT IS SUPPLIED, OR IN A MANNER THAT DOES NOT REFER TO OR INCLUDE THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	-	DATE -
CHECKER	-	DATE -
ENGINEER	-	DATE -
SCALE:	N/A	

TITLE: JB-001
CONTROL JUNCTION BOX
EXTERNAL & INTERNAL LAYOUT

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4100 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL	0002-AU-VWT	-	03 OF 05	1

STD: "B" 11x17
REF: A6798A
BAR = 1" AT PLOT SCALE

Jan 29, 2019 15:45:39 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\5000218036-EPL-0002-AU-VWT-003.dwg - rasion

Jan 29, 2019 15:45:39 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\5000218036-EPL-0002-AU-VWT-004.dwg - rasloni

BAR = 1" AT PLOT SCALE
REF.: A6798A
STD: "B" 11x17

A

TB-ANALOG
011808+
011808–
SH
011814+
011814–
SH
012021+
012021–
SH
012129+
012129–
SH
012045+
012045–
SH
–
–
–

C

A

TB-120VAC	
010144	N
–	N

D

A

TB-DIGITAL	
010814	010404
010816	010404
010818	010404
010828	010404
010830	010404
010832	010404
010834	010404
010836	010404
010904	010406
–	–

D

TERMINAL DESCRIPTION
A) ID(WAD8)
B) WDU6
C) WDU4
D) WDK2.5
E) DLD2.5
F) FUSE WSI 4/2
G) FUSE WSI 4
H) FUSE KDKS 1/EN4
J) WTR 2.5
K) WDU 2.5

REV.	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. AND THEY MUST NOT BE USED IN ANY MANNER BY THE RECIPIENT OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. OR ITS AFFILIATES. ACCEPTANCE OF INSTRUCTIONS, PAYMENT TERMS AND REMINDERS, MUST MAKE CLEAR THAT THE RECIPIENT OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE: JB-001
CONTROL JUNCTION BOX
TERMINAL LAYOUT

CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230

PROJECT / DRAWING	INTERNAL	SHEET	REV
5000218036-EPL – 0002-AU-VWT	–	04 OF 05	1

ITEM	DESCRIPTION	PART NUMBER	MANUF.	QTY	BY
1	NEMA 4X ENCLOSURE, C/W PAN 14R1311 DIM 14"H x 12"W x 6"D, FIBERGLASS REINFORCED POLYESTER	PJ14126RL	HAMMOND	1	ENV
2	TERMINAL 600VAC/DC, 30A WDU 4 C/W END PLATE 1050000000	1020100000	WEIDMULLER	A/R	ENV
3	TERMINAL 600VAC/DC, 50A WDU 6 C/W END PLATE 1050000000 OR SEPERATOR 1050100000	1020200000	WEIDMULLER	A/R	ENV
5	KNIFE TERMINAL 300VAC/DC, 10A, WTR 2.5 C/W END PLATE 1050000000	1855610000	WEIDMULLER	A/R	ENV
6	TERMINAL 2 LEVEL 300VAC/DC, 10A, WDK 2.5 C/W END PLATE 1059100000	1021500000	WEIDMULLER	A/R	ENV
7	TERMINAL 3 LEVEL 300VAC/DC, 10A, DLD 2.5 C/W END PLATE 1784210000	1784180000	WEIDMULLER	A/R	ENV
8	FUSE TERMINAL ¼ X 1¼, 300VAC/DC, 15A, WSI 4/2 C/W END PLATE 1880450000	1880430000	WEIDMULLER	A/R	ENV
9	FUSE TERMINAL 5 X 20mm, 300VAC/DC, 15A, WSI 4	1886580000	WEIDMULLER	A/R	ENV
10	FUSE TERMINAL 2 LEVEL 5 X 20mm, 300VAC/DC, 10A, KDKS 1/EN4 C/W END PLATE 9503330000	9503350000	WEIDMULLER	A/R	ENV
11	FUSE TERMINAL 2 LEVEL ¼ X 1¼, 300VAC/DC, 10A, KDKS 1/35DB C/W END PLATE 9532470000	9532440000	WEIDMULLER	A/R	ENV
12	END STOPPER WEW 35/2	1061200000	WEIDMULLER	A/R	ENV
13	COPPER GROUND BAR, #4-14	4C-190	NSI-INDUSTRIES	A/R	ENV
14	COPPER GROUND LUG, 600VAC, #6-14, STR	CB35-36-LY	PANDUIT	A/R	ENV

Jan 29, 2019 15:45:41 – G:\Projets A67XX\A6798A – VEOLIA – 5000218036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\JB-001\5000218036-EPL-0002-AU-VWT-005.dwg – rosiani

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17

REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, REGULATIONS, COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T AND ARE CONFIDENTIAL IN NATURE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED SOLELY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED BY V.W.T AND SHALL NOT BE LOANED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THIS DOCUMENT IS CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, REMITTED OR USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T AND THEIR LEGAL COUNSEL. V.W.T DISCLAIMS ANY LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OTHER THAN THE ONE THAT THEY RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS AND CLAIMS. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS

DESIGNER	–	DATE –
CHECKER	–	DATE –
ENGINEER	–	DATE –
SCALE:	N/A	

TITLE
JB-001
CONTROL JUNCTION BOX
BILL OF MATERIAL

CLIENT
WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230


PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036-EPL	0002-AU-VWT	–	05 OF 05	1

Jan 29, 2019 - 15:45:41 - G:\Projets A67XX\A6798A - VEOLIA - 5000218036 Iqaluit WWTP Upgrade\DOC\DESIGN\000-DRAWINGS\JB-001\5000218036-EID-0002-AU-VWT-001.dwg - rasloni

BAR = 1" AT PLOT SCALE

REF.: A6798A

STD. "B" 11x17



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-09	HZ	RA	-	-

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND TRADE SECRET LAWS. ANY AND ALL RIGHTS ARE RESERVED. ALL INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO V.W.T. AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY MUST BE USED ONLY FOR THE PURPOSE FOR WHICH THE DOCUMENT IS EXPRESSLY SUBMITTED AND NO IMPLICIT LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF V.W.T. AND THEY MUST NOT BE DISCLOSED, REPRODUCED, TRANSMITTED, STORED, USED IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF V.W.T. V.W.T. ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE STATED PURPOSE OF THIS DOCUMENT. ANY UNAUTHORIZED USE OR DISCLOSURE OF THIS DOCUMENT SHALL ENTITLE V.W.T. TO CONSIDER SUCH USE AS ACCEPTANCE OF THE TERMS, CONDITIONS AND RESTRICTIONS SET FORTH IN THIS NOTICE AND AGREEMENT TO BE LIABLE TO V.W.T. FOR ANY CONSEQUENCES OR DAMAGES RESULTING THEREFROM. THIS DOCUMENT IS NOT TO BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF V.W.T. ALL COPYRIGHT, PATENT AND OTHER INTELLECTUAL PROPERTY RIGHTS ARE RESERVED. ACCEPTANCE OF THE DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

		DATE
DESIGNER	-	-
CHECKER	-	-
ENGINEER	-	-
SCALE:	N/A	

TITLE: JB-001
CONTROL JUNCTION BOX
FIELD WIRING


CLIENT: WWTP UPGRADE
CITY OF IQALUIT

VEOLIA
VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7230

PROJECT	DRAWING	INTERNAL	SHEET	REV
5000218036 – EID – 0002 – AU – VWT		-	01 OF 02	1

Jan 29, 2019 - 15:45:41 - G:\Projets A67XX\A6798A - VEOLIA - 500021B036 Iqaluit WWTP Upgrade\DOC\DESSIN\000-DRAWINGS\VB-001\500021B036-EID-0002-AU-VWT-002.dwg - rasiani

BAR = 1" AT PLOT SCALE
REF: A6798A
STD: "B" 11x17



REV	DESCRIPTION	DATE	REVD	CHKD	APVD	ECN
1	FOR APPROVAL	2019-01-09	HZ	RA	–	–

CONFIDENTIALITY AND INTELLECTUAL PROPERTY NOTICE
ALL INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF VEOLIA WATER TECHNOLOGIES CANADA INC. AND IS, WHERE APPLICABLE, PROTECTED BY ALL APPLICABLE LAWS, INCLUDING BUT NOT LIMITED TO COPYRIGHT AND OTHER INTELLECTUAL PROPERTY LAWS. THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN ARE PROPRIETARY TO VWT AND ARE SUBMITTED IN CONFIDENCE. THEY ARE NOT TRANSFERABLE. THEY SHALL NOT BE DISCLOSED, REPRODUCED, LOANED, RESOLD OR USED IN ANY WAY EXCEPT AS EXPRESSLY SUBMITTED AND NO RIGHT OR LICENCE IS GRANTED OTHERWISE BY THE SUBMISSION OF THIS DOCUMENT. THEY ARE CONFIDENTIAL AND PRIVILEGED INFORMATION OF VWT AND THEY MUST NOT BE DISCLOSED, REPRODUCED, LOANED, RESOLD OR USED IN ANY WAY IN ANY OTHER MANNER WITHOUT THE EXPRESS WRITTEN CONSENT OF VWT. VWT ASSUMES NO RESPONSIBILITY OR LIABILITY FOR THE USE OF ANY PART OF THIS DOCUMENT IN ANY OTHER MANNER THAN THAT FOR WHICH IT WAS PREPARED, NOR FOR THE USE OF ANY INFORMATION CONTAINED HEREIN FOR ANOTHER PROJECT, OR IN A MANNER THAT DOES NOT RELATE TO THE FITNESS OR PURPOSE OF THIS DOCUMENT. IN NO EVENT SHALL THIS DOCUMENT OR THE DESIGN CONCEPTS AND INFORMATION CONTAINED HEREIN BE USED IN A MANNER DETRIMENTAL TO THE INTEREST OF VWT. BY ACCEPTANCE OF THIS DOCUMENT, THE RECIPIENT AGREES TO BE BOUND BY THE FOREGOING RESTRICTIONS. ACCEPTANCE OF THIS DELIVERY OF THIS DOCUMENT CONSTITUTES AGREEMENT TO THESE TERMS AND CONDITIONS.

DESIGNER	DATE –
CHECKER	DATE –
ENGINEER	DATE –
SCALE:	N/A

TITLE: JB-001 CONTROL JUNCTION BOX FIELD WIRING

CLIENT: WWTP UPGRADE CITY OF IQALUIT

VEOLIA

VEOLIA WATER TECHNOLOGIES CANADA INC. 4105 Sartelon, Saint-Laurent, Qc, Canada, Tel: (514) 334-7266

PROJECT	DRAWING	INTERNAL	SHEET	REV
500021B036-EID	0002-AU-VWT	–	02 OF 02	1

24VAC control circuit, 40VA class II transformer, fuse protected on output, heavy-duty across-the-line linear reversing contactor with mechanical interlock.

- **B2/C2 Units:**
  C2 wiring is standard. B2 can be set very easily by moving one wire. Available options: delay on reverse, timer to close, double limits, etc...
  Certifications: CSA C22.2-247.92 and compliant to UL325 5th Ed. PRIOR to August 2010 revision.

Note: CSA C22.2-247.92 and UL325 apply to units intended to be used in ordinary locations in accordance with the Canadian Electrical Code, Part I and the National Electrical Code, NFPA 70, respectively.

Main Options

- **Control Accessories:**
Angled terminal strip allows for the connection of 3-button stations (one supplied with the operator), non-monitored sensing edges, non-monitored photo cells, one push-button radio control (external strip), ceiling pull switches, key switches, loop detectors, external interlocks, universal auxiliary output module. 2A fuse protected 24VAC output is available for accessory power supply. NEMA 4/12 or NEMA 4X protected monitored photo cells upgrade available.

- **Environmental Modifications:**
NEMA 4/12 and NEMA 4X enclosures. For NEMA 7/9, consult inside sales.

- **Mechanical Accessories:**
Wall or hood mounting bracket, chain spreader, etc...consult inside sales.

- **Mechanical Modifications:**
Left hand chain hoist, electrically activated drum-band type solenoid brake, cast iron flanged pillow block bearings on output shaft, limit shaft speed-up, etc...consult inside sales.

Motor Selection

Maximum Size of Door in Square Feet

Horse Power	Rolling Doors					Sectional Doors				
	Insulated Steel	16 ga. Steel	Steel Grilles 20 ga. Steel	Alu. Door 22 ga. Steel	Alu. Grilles 24 ga. Steel	Steel 18 ga. ins.	Steel 18 ga. 20 ga. ins.	Wood Steel 20 ga. 22 & 24 ga. ins.	Aluminum Steel 22 & 24 ga.	Fiber Glass
1/2	157	236	260	319	358	196	245	314	343	392
3/4	206	294	358	451	515	270	319	441	490	549
1	255	358	446	574	613	294	392	490	564	613

General Guideline

Operator Range

Current Consumption (Amp.)

Horse Power	120V 1 Ph	240V 1Ph	208/ 240V 3 Ph	480V 3 Ph	600V 3 Ph
1/2	8.0	4.0	2.1	1.0	0.8
3/4	11.2	5.6	3.2	1.5	1.2
1	13.6	6.8	4.4	2.1	1.6

General Guideline

Manaras-Opera OPH SS 2011/04/21 Rev 8 - Printed in Canada

STANTEC PROJECT #: 110126045

SUBMITTAL # Overhead Door Operator

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- ☐ Architectural
- ☐ Structural
- ☐ Mechanical
- ☑ Electrical
- ☐ Other

Stantec

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

- ☑ REVIEWED
- ☐ REVIEWED, AS NOTED
- ☐ REVISE AND RESUBMIT
- ☐ NOT REVIEWED

DATE June 27, 2018

BY Chester Martinez, E.I.T.

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Jul 03, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

TDS AND SHOP DRAWINGS

DA-IC-01R1-Ultrasonic level sensor and transducer **Date :** 2018-07-03

INFORMATION

Project : **WASTEWATER PLANT - IQALUIT**	
Client : Kudlik Construction Ltd. To Sandra Rousseau P.Eng./ Project Manager	Project number : **2018-062**
Contractor : Norclair inc.	Project number Norclair : **P1039**
Address : 1100, Montee Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Dominic Papineau	E-mail: dpapineau@norclair.ca
Phone: 450-688-4012 # 720	Cell.: 514-409-1832

Information, subcontractor or supplier

Sub supplier : VISION Solutions de Procédés	
Contact : Nacère Irid	Phone : 574-733-1800 #231

Information on the equipment or the proposed materials

Speciality : Instruments and controls

Equipment :

Ultrasonic controllers Level Measurement no. SITRANS LUT420

and Level Measurement Echomax XPS Ultrasonic transducers

Drawing reference :

Specification reference : 40 05 23	Division :
Article :	Number Page : 20

CONSULTANT APPROVAL

No comments

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-01 R1 (2018-07-03)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-JUL-03

BY David Hutchison, P.Eng.

1100, Montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Overview



The SITRANS LUT400 series controllers are compact, single point, long-range ultrasonic controllers for continuous level or volume measurement of liquids, slurries, solids, and high accuracy monitoring of open channel flow.

Benefits

- Small 1/2 DIN enclosure [144 h x 144 d x 146 w mm (5.7 x 5.7 x 5.75 inch)] with standard universal mounting bracket for wall, pipe, and DIN rail, plus an optional panel mount
- Easy to use HMI display with local four-button programming, menu-driven parameters, and Wizard support for key applications
- English, German, French, Spanish, Chinese, Italian, Portuguese, and Russian texts on the HMI.
- Level, Volume, OCM Flow monitoring
- Three relays combined with a suite of pump, alarm, and relay control features
- HART Communications
- EDDs for SIMATIC PDM, AMS Device Manager, and Field Communicator 375/475, plus DTMs for FDTs (Field Device Tools)
- Web browser for local programming from an intuitive web-based interface
- Two discrete inputs for backup level override and pump interlock functions
- Echo profile and trend views from the local display
- Patented digital receiver for improved performance in electrically noisy applications (close proximity to VSDs)
- Real time clock with daylight savings time, supporting an integrated datalogger and energy saving algorithms for minimizing pump operation during high cost energy periods
- Removable terminal blocks for ease of wiring
- MCERTS Certified for Open Channel Flow

Application

The SITRANS LUT400 comes in three different models, depending on the application, level of performance and functionality required:

- SITRANS LUT420 Level Controller: Level or volume measurement of liquids, slurries, and solids, as well as basic pump control functions, and basic data logging capability
- SITRANS LUT430 Level, Pump and Flow Controller: Includes all features of the LUT420 plus a full suite of advanced pump control and alarm functionality, open channel flow monitoring, and basic flow data logging capability
- SITRANS LUT440 High Accuracy OCM: Our most featured, highest accuracy model. Includes all features of the LUT430, plus the industry's best accuracy (± 1 mm within 3 m), full suite of advanced control functionality, and enhanced flow logging capability
- Key Applications: wet wells, reservoirs, flumes/weirs, chemical storage, liquid storage, hoppers, crusher bins, dry solids storage

© Siemens AG 2017

Technical specifications

Mode of Operation	Ultrasonic level, volume, pump, and open channel flow
Measuring range	0.3 … 60 m (1 … 196 ft), transducer dependent
Input	
Discrete	0 ... 50 V DC switching level Logical 0 ≤ 10 V DC Logical 1 = 10 ... 50 V DC Max. 3 mA
Output	
Transducer frequency	10 ... 52 kHz
Ultrasonic transducer	Compatible transducers: All Echo-Max and ST-H series transducers
Relays	• 1 SPDT Form C, NO or NC relay, rated 1A at 250 V AC, non-inductive and 3A at 30 V DC • 2 SPST Form A, NO relays, rated 5A at 250 V AC, non-inductive and 3 A at 30 V DC
mA output	4 … 20 mA, isolated
Max. load	600 Ω max. in ACTIVE mode, 750 Ω max. in PASSIVE mode
Resolution	0.1 % of range
Accuracy	
Error in measurement	• Standard operation: ± 1 mm (0.04 inch) plus 0.17 % of measured distance • High accuracy OCM: ± 1 mm (0.04 inch), within 3 m (9.84 ft) range
Resolution	• Standard operation: 0.1 % of range or 2 mm (0.08 inch), whichever is greater • High accuracy OCM: 0.6 mm (0.02 inch), within 3 m (9.84 ft) range
Temperature compensation	• -40 ... +150 °C (-40 ... +300 °F) • Integral temperature sensor in transducer • External TS-3 temperature sensor (optional) • Programmable fixed temperature values
Rated operating conditions	
Installation conditions	
• Location	Indoor/outdoor
• Installation category	II
• Pollution degree	4
Ambient conditions	
• Ambient temperature (enclosure)	-20 … +50 °C (-4 … +122 °F)

Design	
Weight	
• Enclosure with display lid	1.3 kg (2.87 lb)
• Enclosure with blank lid	1.2 kg (2.65 lb)
Material (enclosure)	Polycarbonate
Degree of protection	
• Enclosure with display or blank lid	IP65/Type 4X/NEMA 4X
• Enclosure with blank lid and knock-out removed	IP20
Remote display lid	IP65/Type 3/NEMA 3
Cable	
Transducer and mA output signal	• Transducer, mA output: 2 copper conductors, twisted, with foil shield/drain wire, 300 V 0.5 … 0.75 mm² (22 … 18 AWG) • Relay/power to be copper conductors per local requirements to meet 250 V 5 A contact rating
Max. separation between transducer and transceiver	365 m (1 200 ft)
Displays and controls	60 x 40 mm (2.36 x 1.57 inch) removable LCD, 240 x 160 pixels resolution, operational up to 5 m from enclosure base
Programming	
• Primary	4 Local push buttons
• Secondary	• PC running SIMATIC PDM • PC running Emerson AMS Device Manager • PC running a web browser • PC running a Field Device Tool (FDT) • Field Communicator 375/475 (FC375/FC475)
Memory	• 512 kB flash EPROM • 1.5 MB flash for data logging
Power supply	
AC version	100 ... 230 V AC ± 15 %, 50/60 Hz, 36 VA Fuse: 5 x 20 mm, Slow Blow, 0.25 A, 250 V
DC version	10 … 32 V DC, 10 W Fuse: 5 x 20 mm, Slow Blow, 1.6 A, 125 V
Certificates and approvals	
General	$CSA_{US/C}$, CE, FM, UL listed, RCM, MCERTS certified for Open Channel Flow
Hazardous	
• Non-incendive (Canada)	CSA Class I, Div. 2, Groups A, B, C, D; Class II, Div. 2, Groups F, G; Class III
• Shipping	Lloyd's Register, ABS
Communication	HART 7.0, USB

		SITRANS LUT420	SITRANS LUT430	SITRANS LUT440
Category	**Feature**	**Level Controller**	**Level, pump and flow controller**	**High accuracy OCM controller**
Operations	Level, space, and distance measurement	✓	✓	✓
	Open channel flow measurement		✓	✓
	Volume conversion	✓	✓	✓
Specifications	Compatible with EchoMax and ST-H transducers	✓	✓	✓
	Standard accuracy: ± 1 mm + 0.17 % of measured distance	✓	✓	✓
	High accuracy: ± 1 mm within 3 meters			✓
	Mounting options: wall or panel, pipe, DIN-rail	✓	✓	✓
Data logging and communications	HART communications	✓	✓	✓
	4 ... 20 mA output (active and passive)	✓	✓	✓
	Integrated datalogger for measurement value and alarms	✓	✓	✓
	Integrated datalogger for fixed rate flow logging		✓	✓
	Integrated datalogger for variable rate flow logging triggered by changes in flow condition			✓
	Daily data logging for maximum, minimum and average flow, daily totalized volume, and minimum and maximum temperature		✓	✓
Flow monitoring	High accuracy open channel flow measurement			✓
	9 digit daily and running flow totalizers		✓	✓
	High and low flowrate alarms		✓	✓
	External totalizer and sampler control		✓	✓
	MCERTS Class 1 Certification			✓
	MCERTS Class 2 Certification		✓	
Pump control	Energy saving algorithms for pump control		✓	✓
	Wall cling reduction	✓	✓	✓
	Pump run-on functionality		✓	✓
	Pump start and power resumption delays		✓	✓
	Alternate duty pump routines	✓	✓	✓
	Fixed duty and service ratio pump routines		✓	✓
	Pumped volume totalizer		✓	✓
	Submergence detection	✓	✓	✓
	Discrete input pump interlocks		✓	✓
	Time to spill calculation		✓	✓

© Siemens AG 2017

SITRANS LUT400 series

Selection and Ordering data		Article No.
SITRANS LUT420 and LUT430 Compact ultrasonic level controllers for continuous short to long-range level or volume measurement of liquids, slurries, and solids. Both units include basic relay functions for pumps, alarms, and other controls, plus onboard data logging. LUT430 offers additional advanced pump control and alarm functionality, open channel flow monitoring, and basic flow data logging capability. Functionality varies by model. ↗ Click on the Article No. for the online configuration in the PIA Life Cycle Portal.		**7ML5050-** 0 - 0
Model		
SITRANS LUT420 - Level controller	⬟	A
SITRANS LUT430 - Level, Pump & Flow controller	⬟	B
Enclosure display options		
With display	⬟	A
With remote panel mount display [Includes panel mount cable extension, 2.5 m (8.2 ft)]	⬟	B
No display (blank lid provided) Note: Enclosure includes back-plate for wall and pipe mounting, and an integrated clip for DIN-rail mounting. DIN-rail mounting for standard TS35 x 7.5 and TS35 x 15 mm DIN-rail to IEC 60715, EN 60715	⬟	C
Input voltage		
100 ... 230 V AC ± 15 %	⬟	1
10 ... 32 V DC	⬟	2
Cable inlet		
3 cable inlets, cable glands not supplied	⬟	1
3 cable inlets, 3 M20 plastic cable glands supplied	⬟	2
Number of measurement points		
Single point system (includes one transducer input, one mA output, and one external temperature sensor input)	⬟	1
Communications and I/O		
HART, 2 discrete inputs, 3 relays	⬟	D
Approvals		
General purpose CE, FM, $CSA_{US/C}$, UL, RCM	⬟	A
Hazardous locations CSA Class I, II, III, Div. 2, Groups A, B, C, D, F, G		C

⬟ We can offer shorter delivery times for configurations designated with the Quick Ship Symbol ⬟. For details see page 10/11 in the appendix.

Selection and Ordering data		Order code
Further designs		
Please add "**-Z**" to Article No. and specify Order code(s).		
Manufacturer's test certificate M to DIN 55350, Part 18 and to ISO 9000	⬟	**C11**
Stainless steel tag [69 x 50 mm (2.71 x 1.97 inch)]: Measuring-point number/identification (max. 27 characters) specify in plain text	⬟	**Y15**
Namur NE43 failsafe setting - device preset to failsafe < 3.6 mA	⬟	**N07**
Operating Instructions		Article No.
English		**A5E33329501**
German		**A5E35690863**
Note: The Operating Instructions should be ordered as a separate line item on the order. All literature is available to download for free, in a range of languages, at http://www.siemens.com/processinstrumentation/documentation		

Selection and Ordering data	Article No.
Accessories	
Tag, stainless steel, 12 x 45 mm (0.47 x 1.77 inch), one text line, suitable for enclosure	**7ML1930-1AC**
TS-3 Temperature Sensor - see TS-3 on page 4/181	**7ML1813-...**
Panel mount cable extension, 2.5 m (8.2 ft)	**7ML1930-1GF**
Qty 3 cable glands and retaining nuts	**7ML1930-1GB**
USB cable, 2 m (6.56 ft) - Standard USB-A to USB-mini B	**7ML1930-1GD**
Hart modem/USB (for use with a PC and SIMATIC PDM)	**7MF4997-1DB**
Sunshield, 304 stainless steel	**7ML1930-1GE**
SITRANS RD100, loop powered display - see Chapter 7	**7ML5741-...**
SITRANS RD200, universal input display with Modbus conversion - see Chapter 7	**7ML5740-...**
SITRANS RD300, dual line display with totalizer and linearization curve and Modbus conversion - see Chapter 7	**7ML5744-...**
SITRANS RD500 web, universal remote monitoring solution for instrumentation - see Chapter 7	**7ML5750-...**
Spare parts	
Panel mount retrofit kit (convert standard unit with display to panel mount version)	**7ML1830-1PA**
Terminal block replacement kit (5 piece kit with one of each removable terminal)	**7ML1830-1PB**
Wall/Pipe mount plate	**7ML1830-1PC**
Enclosure (include blank label)	**7ML1830-1PD**
SITRANS LUT400 Lid (with Display)	**7ML1830-1PE**
SITRANS LUT400 Lid (blank)	**7ML1830-1PF**
Fuse - AC (0.25 A, 250 V, Slow Blow)	**7ML1830-1PG**
Fuse - DC (1.6 A, 125 V, Slow Blow)	**7ML1830-1PH**
Panel mount gasket and fastener kit	**7ML1830-1PK**
DIN-rail clip	**7ML1830-1PL**

⬟ We can offer shorter delivery times for configurations designated with the Quick Ship Symbol ⬟. For details see page 10/11 in the appendix.

Selection and Ordering data	Article No.
SITRANS LUT440 ↗ The SITRANS LUT440 is the most accurate and featured model in the LUT400 series. It includes high accuracy open channel monitoring, relay functions for external samplers, totalizers, alarms, and enhanced data logging, as well as all pump and control functions available with other models in the LUT400 series. ↗ Click on the Article No. for the online configuration in the PIA Life Cycle Portal.	**7ML5050-** 0 ■■■■ - ■■■ 0
Model	
SITRANS LUT440 - High accuracy Open Channel Monitor[1] ⬟	C
Enclosure display options	
With display ⬟	A
With remote panel mount display [includes panel mount cable extension, 2.5 m (8.2 ft)] ⬟	B
No display (blank lid provided) ⬟	C
Note: Enclosure includes back-plate for wall and pipe mounting, and an integrated clip for DIN-rail mounting. DIN-rail mounting for standard TS35 x 7.5 and TS35 x 15 mm DIN-rail to IEC 60715, EN 60715	
Input voltage	
100 ... 230 V AC ± 15 % ⬟	1
10 ... 32 V DC ⬟	2
Cable inlet	
3 cable inlets, cable glands not supplied ⬟	1
3 cable inlets, 3 M20 plastic cable glands supplied ⬟	2
Number of measurement points	
Single point system (includes one transducer input, one mA output, and one external temperature sensor input) ⬟	1
Communications and I/O	
HART, 2 discrete inputs, 3 relays ⬟	D
Approvals	
General purpose CE, FM, $CSA_{US/C}$, UL, RCM ⬟	A
Hazardous locations CSA Class I, II, III, Div. 2, Groups A, B, C, D, F, G	C

[1] Compatible with all EchoMax Transducers. High accuracy OCM performance with the use of an XRS-5 transducer and TS-3 temperature sensor (each sold separately).

⬟ We can offer shorter delivery times for configurations designated with the Quick Ship Symbol ⬟. For details see page 10/11 in the appendix.


Selection and Ordering data	Order code
Further designs	
Please add "**-Z**" to Article No. and specify Order code(s).	
Manufacturer's test certificate M to DIN 55350, Part 18 and to ISO 9000 ⬟	**C11**
Stainless steel tag [69 x 50 mm (2.71 x 1.97 inch)]: ⬟ Measuring-point number/identification (max. 27 characters) specify in plain text	**Y15**
Namur NE43 failsafe setting - device preset to failsafe < 3.6 mA ⬟	**N07**
Operating Instructions	Article No.
English	**A5E33329501**
German	**A5E35690863**
Note: The Operating Instructions should be ordered as a separate line item on the order.	
All literature is available to download for free, in a range of languages, at http://www.siemens.com/processinstrumentation/documentation	

Selection and Ordering data	Article No.
Accessories	
Tag, stainless steel, 12 x 45 mm (0.47 x 1.77 inch), one text line, suitable for enclosure	**7ML1930-1AC**
TS-3 Temperature Sensor - see TS-3 on page 4/181	**7ML1813-...**
Panel mount cable extension 2.5 m (8.2 ft)	**7ML1930-1GF**
Qty 3 cable glands and retaining nuts	**7ML1930-1GB**
USB cable 2 m (6.56 ft) - Standard USB-A to USB-mini B	**7ML1930-1GD**
HART modem/USB (for use with PC and SIMATIC PDM)	**7MF4997-1DB**
Sunshield, 304 stainless steel	**7ML1930-1GE**
SITRANS RD100, loop powered display - see Chapter 7	**7ML5741-...**
SITRANS RD200, universal input display with Modbus conversion - see Chapter 7	**7ML5740-...**
SITRANS RD300, dual line display with totalizer and linearization curve and Modbus conversion - see Chapter 7	**7ML5744-...**
SITRANS RD500 web, universal remote monitoring solution for instrumentation - see Chapter 7	**7ML5750-...**
Spare parts	
Panel mount retrofit kit (convert standard unit with display to panel mount version)	**7ML1830-1PA**
Terminal block replacement kit (5 piece kit with one of each removable terminal)	**7ML1830-1PB**
Wall/Pipe mount plate	**7ML1830-1PC**
Enclosure (include blank label)	**7ML1830-1PD**
SITRANS LUT400 Lid (with Display)	**7ML1830-1PE**
SITRANS LUT400 Lid (blank)	**7ML1830-1PF**
Fuse - AC (0.25 A, 250 V, Slow Blow)	**7ML1830-1PG**
Fuse - DC (1.6 A, 125 V, Slow Blow)	**7ML1830-1PH**
Panel mount gasket and fastener kit	**7ML1830-1PK**
DIN-rail clip	**7ML1830-1PL**


⬟ We can offer shorter delivery times for configurations designated with the Quick Ship Symbol ⬟. For details see page 10/11 in the appendix


© Siemens AG 2017

Dimensional drawings



SITRANS LUT400, dimensions in mm (inch)






SITRANS LUT400, dimensions in mm (inch)

© Siemens AG 2017

4

Schematics



SITRANS LUT400 connections

© Siemens AG 2017

Overview



EchoMax XPS transducers use ultrasonic technology to measure level in a wide range of liquids and solids.

Benefits

- Integral temperature compensation
- Low ringing effect reduces blanking distance
- Optional foam facing for dusty applications
- Self-cleaning and low-maintenance
- Chemically resistant
- Hermetically sealed

Application

XPS transducers can be fully immersed, are resistant to steam and corrosive chemicals, and can be installed without flanges.

The XPS series offers versions for various measuring ranges up to 30 m (100 ft) and up to a max. temperature of 95 °C (203 °F).

During operation, the EchoMax transducers emit acoustic pulses in a narrow beam. The level monitor measures the propagation time between pulse emission and its reflection (echo) to calculate the distance.

Technical specifications

Input	XPS-10	XPS-15 (standard and F models)	XPS-30
Measuring range	0.3 ... 10 m (1 ... 33 ft)	Standard: 0.3 ... 15 m (1 ... 50 ft) XPS-15F: 0.45 ... 15 m (1.5 ... 50 ft)	0.6 ... 30 m (2 ... 100 ft)
Output			
Frequency	44 kHz	44 kHz	30 kHz
Beam angle	12°	6°	6°
Environmental			
Location	Indoors/outdoors		
Ambient temperature	-40 ... +95 °C (-40 ... +203 °F)	Standard: -40 ... +95 °C (-40 ... +203 °F) XPS-15F: -20 ... +95 °C (-4 ... +203 °F)	-40 ... +95 °C (-40 ... +203 °F)
Pollution degree	4		
Pressure	8 bar g (120 psi g) Flanged: 0.5 bar g (7.25 psi g)	8 bar g (120 psi g) Flanged: 0.5 bar g (7.25 psi g)	0.5 bar g (7.25 psi g) Flanged: 0.5 bar g (7.25 psi g)
Design			
Weight	0.8 kg (1.8 lb)	1.3 kg (2.8 lb) Flanged: 2 kg (4.4 lb)	4.3 kg (9.5 lb)
Power supply	Operation of transducer only with approved Siemens controllers		
Material	Standard: PVDF Flanged: PVDF with CPVC flange Option: PTFE face with CPVC flange	Standard: PVDF Flanged: PVDF with CPVC flange Option: PTFE face with CPVC flange	Standard: PVDF Flanged: PVDF with CPVC flange Option: PTFE face with CPVC flange
Color	Blue	Standard: Blue XPS-15F: Gray	Blue
Process connection	1" NPT or 1" BSPT	Standard: 1" NPT or 1" BSPT XPS-15F: 1" NPT	1.5" universal thread (NPT or BSPT)
Degree of protection	IP66/68	IP66/68	IP66/68
Cable	2-wire twisted pair/braided and foil shielded 0.5 mm^2 (20 AWG) PVC jacket		
Separation	Max. 365 m (1 200 ft)		
Certificates and approvals	Standard: CE, CSA, FM, ATEX, IECEx	Standard: CE, CSA, FM, ATEX, IECEx XPS-15F: FM Class I, Div. 1, Groups A, B, C, and D, Class II Div. 1, Groups E, F, and G, Class III	CE, CSA, FM, ATEX, IECEx

1) EMC certificate available on request.

© Siemens AG 2017

EchoMax XPS

Selection and Ordering data		Article No.
EchoMax XPS-10 ultrasonic transducer	↗	**7ML1115-**
High-frequency ultrasonic transducer designed for a wide variety of liquid and solid applications, for use with approved controllers. Includes integral temperature sensor. Measuring range: min. 0.3 m, max.10 m		■■■■ **0**
↗ Click on the Article No. for the online configuration in the PIA Life Cycle Portal.		
Mounting thread and facing		
1" NPT [(Taper), ANSI/ASME B1.20.1]	⬟	**0**
1" NPT [(Taper), ANSI/ASME B1.20.1] with foam facing[1]		**1**
1" NPT [(Taper), ANSI/ASME B1.20.1] with PTFE facing[2]		**2**
R 1" [(BSPT), EN 10226]	⬟	**3**
R 1" [(BSPT), EN 10226] with foam facing[1]		**4**
R 1" [(BSPT), EN 10226] with PTFE facing[2]		**5**
Cable length		
5 m (16.40 ft)	⬟	**B**
10 m (32.81 ft)	⬟	**C**
30 m (98.43 ft)	⬟	**E**
50 m (164.04 ft)		**F**
100 m (328.08 ft)		**K**
Mounting flange		
None	⬟	**A**
3" ASME, 150 lb, flat faced		**C**
4" ASME, 150 lb, flat faced		**D**
6" ASME, 150 lb, flat faced		**E**
8" ASME, 150 lb, flat faced		**F**
DN 80, PN 10/16, Type A, flat faced		**G**
DN 100, PN 10/16, Type A, flat faced		**J**
DN 150, PN 10/16, Type A, flat faced		**L**
JIS10K3B Style		**M**
JIS10K4B Style		**P**
JIS10K6B Style (Note: Flange bolting patterns and facings dimensionally correspond to the applicable ASME B16.5 or EN 1092-1, or JIS B 2220 standard.)		**R**
Approvals		
ATEX 2GD Ex mb IIC T4 Gb, Ex tb IIIC T135 °C Db; IECEx SIR 13.0009X Ex mb IIC T4 Gb, Ex tb IIIC T135 °C Db; FM Class I, Div. 2, Groups A, B, C, D; Class II, Div. 1, Groups E, F, G; Class III	⬟	**3**
CSA Class I, Div. 1, Groups A, B, C, D, Class II, Div. 1, Groups E, F, G, Class III[3]	⬟	**4**

[1] Not available with flanged versions
[2] Available with flanged versions only
[3] Valid with mounting thread and facing options 0 ... 2 only

⬟ We can offer shorter delivery times for configurations designated with the Quick Ship Symbol ⬟. For details see page 10/11 in the appendix.

Selection and Ordering data	Order code
Further designs	
Please add "**-Z**" to Article No. and specify Order code(s).	
Stainless steel tag [69 x 50 mm (2.71 x 1.97 inch)]: Measuring point number/ identification (max. 27 characters) specify in plain text	**Y15**
Operating Instructions	Article No.
Quick Start guide, multi-language	**A5E32282889**
Note: The Operating Instructions should be ordered as a separate line item on the order.	
All literature is available to download for free, in a range of languages, at http://www.siemens.com/processinstrumentation/documentation	
Accessories	
Tag, stainless steel with hole, 12 x 45 mm (0.47 x 1.77 inch), one text line for fastening on sensors	**7ML1930-1BJ**
Submergence shield kit	**7ML1830-1BH**
Easy Aimer 2, aluminum, NPT with ¾" x 1" PVC coupling	**7ML1830-1AQ**
Easy Aimer 2, aluminum with M20 adapter and 1" and 1½" BSPT aluminum couplings	**7ML1830-1AX**
Easy Aimer 304, NPT with 1" stainless steel coupling	**7ML1830-1AU**
Easy Aimer 304, with M20 adapter and 1" and 1½" BSPT 304 stainless steel couplings	**7ML1830-1GN**
Universal box bracket, mounting kit	**7ML1830-1BK**
Channel bracket, wall mount	**7ML1830-1BL**
Extended channel bracket, wall mount	**7ML1830-1BM**
Channel bracket, floor mount	**7ML1830-1BN**
Extended channel bracket, floor mount	**7ML1830-1BP**
Bridge channel bracket, floor mount (see Mounting Brackets on page 4/179 for more information)	**7ML1830-1BQ**
1" NPT locknut, plastic	**7ML1830-1DS**
1" BSPT locknut, plastic	**7ML1830-1DR**
Plastic adapter 1" BSP - 20 mm	**7ML1830-1EA**
Plastic adapter 1" NPT	**7ML1930-1FX**
Plastic adapter 1" NPT/M20	**7ML1830-1EF**

Selection and Ordering data		Article No.
EchoMax XPS-15 ultrasonic transducer High-frequency ultrasonic transducer designed for a wide variety of liquid and solid applications, for use with approved controllers. Includes integral temperature sensor. Measuring range: min. 0.3 m, max. 15 m		**7ML1118-** ■■■■ **0**
↗ Click on the Article No. for the online configuration in the PIA Life Cycle Portal.		
Mounting thread and facing		
1" NPT [(Taper), ANSI/ASME B1.20.1]	⬟	**0**
1" NPT [(Taper), ANSI/ASME B1.20.1] with foam facing[1]		**1**
1" NPT [(Taper), ANSI/ASME B1.20.1] with PTFE facing[2]		**2**
R 1" [(BSPT), EN 10226]	⬟	**3**
R 1" [(BSPT), EN 10226] with foam facing[1]		**4**
R 1" [(BSPT), EN 10226] with PTFE facing[2]		**5**
Cable length		
5 m (16.40 ft)	⬟	**B**
10 m (32.81 ft)	⬟	**C**
30 m (98.43 ft)	⬟	**E**
50 m (164.04 ft)		**F**
100 m (328.08 ft)		**K**
Mounting flange		
None	⬟	**A**
6" ASME, 150 lb, flat faced		**D**
8" ASME, 150 lb, flat faced		**E**
DN 150, PN 10/16, Type A, flat faced		**J**
DN 200, PN 10, Type A, flat faced		**K**
JIS10K 6B		**N**
JIS10K 8B		**P**
(Note: Flange bolting patterns and facings dimensionally correspond to the applicable ASME B16.5 or EN 1092-1, or JIS B 2220 standard.)		
Approvals		
ATEX 2GD Ex mb IIC T4 Gb, Ex tb IIIC T135 °C Db; IECEx SIR 13.0009X Ex mb IIC T4 Gb, Ex tb IIIC T135 °C Db; FM Class I, Div. 2, Groups A, B, C, D; Class II, Div. 1, Groups E, F, G; Class III	⬟	**3**
CSA Class I, Div. 1, Groups A, B, C, D, Class II, Div. 1, Groups E, F, G, Class III[3]	⬟	**4**

1) Not available with flanged versions
2) Available with flanged versions only
3) Available with mounting options 0 ... 2 only

⬟ We can offer shorter delivery times for configurations designated with the Quick Ship Symbol ⬟. For details see page 10/11 in the appendix.

Selection and Ordering data	Order code
Further designs	
Please add "**-Z**" to Article No. and specify Order code(s).	
Stainless steel tag [69 x 50 mm (2.71 x 1.97 inch)]: ⬟ Measuring point number/ identification (max. 27 characters) specify in plain text	**Y15**
Operating Instructions	Article No.
Quick Start guide, multi-language	**A5E32282889**
Note: The Operating Instructions should be ordered as a separate line item on the order.	
All literature is available to download for free, in a range of languages, at http://www.siemens.com/processinstrumentation/documentation	
Accessories	
Tag, stainless steel with hole, 12 x 45 mm (0.47 x 1.77 inch), one text line for fastening on sensors	**7ML1930-1BJ**
Submergence shield kit	**7ML1830-1BJ**
Universal box bracket, mounting kit	**7ML1830-1BK**
Channel bracket, wall mount	**7ML1830-1BL**
Extended channel bracket, wall mount	**7ML1830-1BM**
Channel bracket, floor mount	**7ML1830-1BN**
Extended channel bracket, floor mount	**7ML1830-1BP**
Bridge channel bracket, floor mount (see Mounting Brackets on page 4/179 for more information)	**7ML1830-1BQ**
1" NPT locknut, plastic	**7ML1830-1DS**
1" BSPT locknut, plastic	**7ML1830-1DR**
Easy Aimer 2, aluminum, NPT with ¾" x 1" PVC coupling	**7ML1830-1AQ**
Easy Aimer 2, aluminum with M20 adapter and 1" and 1½" BSPT aluminum couplings	**7ML1830-1AX**
Easy Aimer 304, NPT with 1" stainless steel coupling	**7ML1830-1AU**
Easy Aimer 304, with M20 adapter and 1" and 1½" BSPT 304 stainless steel couplings	**7ML1830-1GN**
Plastic adapter 1" BSP - 20 mm	**7ML1830-1EA**
Plastic adapter 1" NPT	**7ML1930-1FX**
Plastic adapter 1" NPT/M20	**7ML1830-1EF**

⬟ We can offer shorter delivery times for configurations designated with the Quick Ship Symbol ⬟. For details see page 10/11 in the appendix.

© Siemens AG 2017

EchoMax XPS

Selection and Ordering data	Article No.
EchoMax XPS-15F ultrasonic transducer ↗ High-frequency ultrasonic transducer designed for a wide variety of liquid and solid applications, for use with approved controllers. Includes integral temperature sensor. Measuring range: min. 0.45 m, max. 15 m ↗ Click on the Article No. for the online configuration in the PIA Life Cycle Portal.	**7ML1171-** ■■■■ **0**
Mounting thread and facing	
1" NPT [(Taper), ANSI/ASME B1.20.1]	**1**
Cable length	
5 m (16.40 ft)	**B**
10 m (32.81 ft)	**C**
30 m (98.43 ft)	**D**
50 m (164.04 ft)	**E**
100 m (328.08 ft)	**F**
Mounting flange, flush mount	
None	**A**
6" ASME, 150 lb, flat faced	**B**
8" ASME, 150 lb, flat faced (Note: Flange bolting patterns and facings dimensionally correspond to the applicable ASME B16.5, or EN 1092-1, or JIS B 2220 standard.)	**C**
Approvals	
FM Class I, Div. 1, Groups A, B, C, and D, Class II Div. 1, Groups E, F, and G, Class III	**1**

Selection and Ordering data	Order code
Further designs Please add "**-Z**" to Article No. and specify Order code(s).	
Stainless steel tag [69 x 50 mm (2.71 x 1.97 inch)]: Measuring point number/ identification (max. 27 characters) specify in plain text	**Y15**
Operating Instructions All literature is available to download for free, in a range of languages, at http://www.siemens.com/processinstrumentation/documentation	
Accessories	Article No.
Tag, stainless steel with hole, 12 x 45 mm (0.47 x 1.77 inch), one text line for fastening on sensors	**7ML1930-1BJ**
Submergence shield kit	**7ML1830-1BJ**
Universal box bracket, mounting kit	**7ML1830-1BK**
Channel bracket, wall mount	**7ML1830-1BL**
Extended channel bracket, wall mount	**7ML1830-1BM**
Channel bracket, floor mount	**7ML1830-1BN**
Extended channel bracket, floor mount	**7ML1830-1BP**
Bridge channel bracket, floor mount (see Mounting Brackets on page 4/179 for more information)	**7ML1830-1BQ**
1" NPT locknut, plastic	**7ML1830-1DS**
Easy Aimer 2, aluminum, NPT with ¾" x 1" PVC coupling	**7ML1830-1AQ**
Easy Aimer 304, NPT with 1" stainless steel coupling	**7ML1830-1AU**

Selection and Ordering data	Article No.
EchoMax XPS-30 ultrasonic transducer ↗ High-frequency ultrasonic transducer designed for a wide variety of liquid and solid applications, for use with approved controllers. Includes integral temperature sensor. 1½" universal thread compatible with 1½" NPT and R 1½" [(BSPT), EN 10226] Measuring range: min. 0.6 m (1.97 ft), max. 30 m (98.43 ft) ↗ Click on the Article No. for the online configuration in the PIA Life Cycle Portal.	**7ML1123-** ■■■■ **0**
Mounting thread and facing	
1½" universal thread	**0**
1½" universal thread, foam facing[1]	**1**
1½" universal thread, PTFE facing[2]	**2**
Cable length	
5 m (16.40 ft)	**B**
10 m (32.81 ft)	**C**
30 m (98.43 ft)	**E**
50 m (164.04 ft)	**F**
100 m (328.08 ft)	**K**
Mounting flange	
None	**A**
6" ASME, 150 lb, flat faced	**D**
8" ASME, 150 lb, flat faced	**E**
DN 150, PN 10/16, Type A, flat faced	**J**
DN 200, PN 10, Type A, flat faced	**K**
JIS10K 6B	**N**
JIS10K 8B (Note: Flange bolting patterns and facings dimensionally correspond to the applicable ASME B16.5 or EN 1092-1, or JIS B 2220 standard.)	**P**
Approvals	
ATEX 2G 1D Ex mb IIC T4 Gb, Ex ta IIIC T135 °C Da; IECEx SIR 13.0009X Ex mb IIC T4 Gb, Ex ta IIIC T135 °C Da	**5**

[1] Not available with flanged versions

[2] Available with flanged versions only

Selection and Ordering data	Order code
Further designs	
Please add "**-Z**" to Article No. and specify Order code(s).	
Stainless steel tag [69 x 50 mm (2.71 x 1.97 inch)]: measuring-point number/identification (max. 27 characters) specify in plain text	**Y15**
Operating Instructions	Article No.
Quick Start guide, multi-language	**A5E32282889**
Note: The Operating Instructions should be ordered as a separate line item on the order.	
All literature is available to download for free, in a range of languages, at http://www.siemens.com/processinstrumentation/documentation	
Accessories	
Tag, stainless steel with hole, 12 x 45 mm (0.47 x 1.77 inch), one text line for fastening on sensors	**7ML1930-1BJ**
1½" BSPT locknut, plastic	**7ML1830-1DP**
Easy Aimer 2, aluminum, NPT with 1½" galvanized coupling	**7ML1830-1AN**
Easy Aimer 304, NPT with 1½" stainless steel coupling	**7ML1830-1AT**
Easy Aimer 2, aluminum with M20 adapter and 1" and 1½" BSPT aluminum couplings	**7ML1830-1AX**
Easy Aimer 304, with M20 adapter and 1" and 1½" BSPT 304 stainless steel couplings	**7ML1830-1GN**
Adapter 1½" BSP	**7ML1830-1EB**

Selection and Ordering data	Article No.
EchoMax XPS-30C ultrasonic transducer ↗ High-frequency ultrasonic transducer designed for a wide variety of liquid and solid applications, for use with approved controllers. Includes integral temperature sensor. 1½" universal thread compatible with 1½" NPT and R 1½" [(BSPT), EN 10226] Measuring range: min. 0.6 m (1.97 ft), max. 30 m (98.43 ft)	**7ML1155-** ■■■■ **1**
↗ Click on the Article No. for the online configuration in the PIA Life Cycle Portal.	
Mounting thread and facing	
1½" universal thread	**0**
1½" universal thread, foam facing[1]	**1**
1½" universal thread, PTFE facing[2]	**2**
Cable length	
5 m (16.40 ft)	**B**
10 m (32.81 ft)	**C**
30 m (98.43 ft)	**E**
50 m (164.04 ft)	**F**
100 m (328.08 ft)	**K**
Mounting flange	
None	**A**
6" ASME, 150 lb, flat faced	**D**
8" ASME, 150 lb, flat faced	**E**
DN 150, PN 10/16, Type A, flat faced	**J**
DN 200, PN 10, Type A, flat faced	**K**
JIS10K 6B	**N**
JIS10K 8B (Note: Flange bolting patterns and facings dimensionally correspond to the applicable ASME B16.5 or EN 1092-1, or JIS B 2220 standard.)	**P**
Approvals	
CSA, Class I, Div. 2, Groups A, B, C, D; Class II, Div. 1, Groups E, F, G; Class III	**4**


Selection and Ordering data	Order code
Further designs	
Please add "**-Z**" to Article No. and specify Order code(s).	
Stainless steel tag [69 mm x 50 mm (2.71 x 1.97 inch)]: Measuring-point number / identification (max. 27 characters) specify in plain text	**Y15**
Operating Instructions	Article No.
Quick Start guide, multi-language	**A5E32282889**
Note: The Operating Instructions should be ordered as a separate line item on the order.	
All literature is available to download for free, in a range of languages, at http://www.siemens.com/processinstrumentation/documentation	
Accessories	
Easy Aimer 2, aluminum, NPT with 1½" galvanized coupling	**7ML1830-1AN**
Easy Aimer 304, NPT with 1½" stainless steel coupling	**7ML1830-1AT**
1½" BSPT locknut, plastic	**7ML1830-1DP**
Adapter 1½" BSP	**7ML1830-1EB**

[1] Not available with flanged version
[2] Available for flanged versions only

4

© Siemens AG 2017


Dimensional drawings



XPS ultrasonic transducer

Version			
Dimension	**XPS-10**	**XPS-15**	**XPS-30**
A	88 mm (3.464 inch)	121 mm (4.764 inch)	175 mm (6.890 inch)
B	122 mm (4.803 inch)	132 mm (5.197 inch)	198 mm (7.795 inch)
C	According to ASME, DIN, and JIS		
E	124 mm (4.882 inch)	158 mm (6.220 inch)	n/a
F	152 mm (5.984 inch)	198 mm (7.795 inch)	n/a
J	28 mm (1.1 inch)	28 mm (1.1 inch)	28 mm (1.1 inch)

Schematics



* For SITRANS LUT400, MultiRanger 100/200, HydroRanger 200

Mounting
Make particularly sure that the radiating face of the transducer is protected from damage. Mount the transducer so that it is above the maximum material level by at least the blanking value. On liquid applications, the transducer must be mounted so that the axis of transmission is perpendicular to the liquid surface. On solids applications, an Easy Aimer should be used to facilitate aiming the transducer. Consider the optional temperature sensor when mounting the transducer.

Interconnection
Do not route cable openly or near high voltage or current runs, contactors and SCR control drives. For optimum isolation against electrical noise, run cable separately in a grounded metal conduit. Seal all thread connections to prevent ingress of moisture.

XPS ultrasonic transducer connections

Application

EA 304 aiming device

The Easy Aimer 304 flange is a stainless steel aiming device for alignment of Siemens ultrasonic transducers used for level measurement of bulk solids.

The sensor must be mounted aimed towards the low level draw point in the silo. The sensor can be rotated through 360° and angled at 0 to 27° off vertical. It must be mounted using an access plate with welded studs or a flange in order to isolate the mounting holes from the pressurized environment. When installed properly, the EA 304 aiming device is capable of withstanding pressures up to 0.5 bar (Europe) or 15 psi (North America). It can even be used in corrosive and aggressive environments.


Application

EA 2 aiming device

The Easy Aimer 2 flange is a cast aluminum aiming device for alignment of Siemens ultrasonic transducers.


The flange has graduated adjustments and an adjustable insertion length. When used for applications with bulk solids, the sensor is mounted so that it is aimed towards the lower level draw point in the silo. The sensor can be rotated through 360° and angled at 0 to 20° off vertical. It must be mounted using an access plate with welded studs or a flange in order to isolate the mounting holes from the pressurized environment. When installed properly, the EA 2 aiming device is capable of withstanding pressures up to 0.5 bar (Europe) or 15 psi (North America). It can even be used in corrosive and aggressive environments.

Dimensional drawings



EA 304 aiming device, dimensions in mm (inch)

Dimensional drawing



EA 2 aiming device, dimensions in mm (inch)

© Siemens AG 2017

EA aiming devices

Selection and Ordering data	Article No.
Easy aimer Used on solids applications to aim transducers for optimal performance. Available in a 304 stainless steel model, or a cast aluminum model.	
Easy Aimer 2, aluminum with M20 adapter and 1" and 1½" BSPT aluminum couplings	**7ML1830-1AX**
Easy Aimer 304, with M20 adapter and 1" and 1½" BSPT 304 stainless steel couplings	**7ML1830-1GN**
Easy Aimer 2, aluminum, BSPT conduit	**7ML1830-1AL**
Easy Aimer 2, aluminum, NPT with 1½" galvanized coupling[1)]	**7ML1830-1AN**
Easy Aimer 2, aluminum, NPT with 1" galvanized coupling	**7ML1830-1AP**
Easy Aimer 2, aluminum, NPT with ¾" x 1" PVC coupling	**7ML1830-1AQ**
Easy Aimer 304, BSPT conduit	**7ML1830-1AS**
Easy Aimer 304, NPT with 1½" stainless steel coupling[1)]	**7ML1830-1AT**
Easy Aimer 304, NPT with 1" stainless steel coupling	**7ML1830-1AU**
Operating Instructions	
All literature is available to download for free, in a range of languages, at http://www.siemens.com/processinstrumentation/documentation	

1) For use with XPS-30 transducers only

Application

Siemens mounting brackets permit simple, fast installation of ultrasonic transducers. These rugged, high quality mounting brackets are constructed of 304 (1.4301) stainless steel and are suitable for use indoors and outdoors. They adjust to fit almost any application, saving you the time and expense of building custom brackets. Each kit includes all mounting parts.

FMS-200
universal box bracket system

Mounting of units with 1 inch or 2 inch threaded connection.

Distance from sensor to wall or beam: 20 ... 31 cm (8 ... 12 inch).

The unique box design also acts as a sun shield for transducers with 1 inch threaded connections.

FMS-210
wall mounting set

Mounting of transducers with 1 inch threaded connection.

Distance from transducer to wall or beam:
12 ... 48 cm (5 ... 19 inch).

FMS-220
extended wall mounting set

Mounting of transducers with 1 inch threaded connection.

Distance from transducer to wall or beam:
32 ... 98 cm (13 ... 39 inch).

FMS-310
floor mounting set

Mounting of transducers with 1 inch threaded connection.

Distance from transducer to floor: 20 ... 48 cm (8 ... 19 inch).

Distance from mounting support: 5 ... 57 cm (2 ... 22 inch).

FMS-320
extended floor mounting set

Mounting of transducers with 1 inch threaded connection.

Distance from transducer to floor: 20 ... 48 cm (8 ... 19 inch).

Distance from mounting support: 41 ... 108 cm (16 ... 43 inch).


FMS-350
floor mounting set, bridge

Mounting of transducers with 1 inch threaded connection.

Distance from transducer to floor: 20 ... 48 cm (8 ... 19 inch), anywhere along the complete width of the bridge [166 cm (65 inch)].

This kit is particularly suitable for measurements on open channels (OCM) by providing a very stable mount for the transducer above a flume or weir.

Integration



FMS mounting brackets

© Siemens AG 2017

FMS mounting brackets

Selection and Ordering data	Article No.
Mounting brackets for XPS-10 sensors	
FMS-200 universal box bracket set	**7ML1830-1BK**
FMS-210 wall mounting set	**7ML1830-1BL**
FMS-220 extended wall mounting set	**7ML1830-1BM**
FMS-310 floor mounting set	**7ML1830-1BN**
FMS-320 extended floor mounting set	**7ML1830-1BP**
FMS-350 floor mounting set, bridge	**7ML1830-1BQ**
Additional Operating Instructions	
FMS-200	**7ML1998-5BK61**
FMS-210	**7ML1998-5BL61**
FMS-220	**7ML1998-5BM61**
FMS-310	**7ML1998-5BN61**
FMS-320	**7ML1998-5BP61**
FMS-350	**7ML1998-5BQ61**
Note: The Operating Instructions should be ordered as a separate line item on the order.	
All literature is available to download for free, in a range of languages, at http://www.siemens.com/processinstrumentation/documentation	

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Jun 18, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

TDS AND SHOP DRAWINGS

DA-IC-02-Flowmeter (FQIT) - 200mm

Date : 2018-06-18

INFORMATION

Project : **WASTEWATER PLANT - IQALUIT**

Client : Kudlik Construction Ltd. To Sandra Rousseau P.Eng./ Project Manager	Project number : **2018-062**
Contractor : Norclair inc.	Project number Norclair : **P1039**
Address : 1100, Montee Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Steven Wieland	E-mail: swieland@norclair.ca
Phone: 450-688-4012 # 708	Cell.: 514-608-0619

Information, subcontractor or supplier

Sub supplier : Endress + Hauser Canada Ltée

Contact : Éric Carpentier	Phone : 514-733-0254

Information on the equipment or the proposed materials

Speciality : Instruments and controls

Equipment :

Flowmeter (FQIT) - 200mm

Drawing reference :

Specification reference : 40 05 23	Division :
Article :	Number Page : 4

Tag number : FQIT-01-150

CONSULTANT APPROVAL

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-02-Flowmeter (2018-06-18)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-JUN-21

BY David Hutchison, P.Eng.

1100, Montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Endress+Hauser
People for Process Automation

Drawing #		Project	**IQALUIT**
		Customer	**NORCLAIR**

Instrument description

5W4C2H-CKL7/0
5W4C2H-C6ALHA0DUA1K0A+Z1
Promag W 400, 5W4C2H, DN200 8"

C6 Approval: CSA C/US NI Cl.I Div.2 Gr. ABCD
A Design: Insertion length short ISO/DVGW until DN400, DN450-2000 1:1
L Power Supply: 100-240VAC/24VAC/DC
H Output; Input: 4-20mA HART, pulse/freq.,switch output
A Housing: Compact, alu, coated
0 Cable, Remote Version: Not used
D Electrical Connection: Thread NPT1/2
U Liner: Polyurethane
A1K Process Connection: Cl.150, carbon steel, flange ASME B16.5
0 Electrodes: 1.4435/316L
A Calibration Flow: 0.5%

Adress: 1100 Montee Masson
Laval QC H7E 4P2

Contact: **Jean-François Lessard**

Telephone: **450-688-4012**
Fax
E-mail jflessard@norclair.ca

Manufacturer

Endress+hauser Canada Ltée
6800 Côte de liesse, suite 100
Ville Saint-Laurent, Québec, Canada
H4T 2A7

Telephone 514 733-0254**x2286**
Fax 514 733-2924
E-mail eric.carpentier@ca.endress.com

Prepare by	**Eric Carpentier**

built as		Drawing for	
As is	**X**	Approbation:	**X**
Equivalent:		Information:	
Substitution:		Coordination:	


Tag number FQIT-01-150


Revision	Initial	Date
1	**EC**	**15 juin, 2018**

Endress+Hauser
People for Process Automation

Drawing #		Project	**IQALUIT**

MECHANICAL





Supply voltage

Order code "Power supply"	**Terminal numbers**	**terminal voltage**		**Frequency range**
Option **L** (wide range power unit)	1 (L+/L), 2 (L-/N)	DC 24 V	±25%	–
		AC 24 V	±25%	50/60 Hz, ±4 Hz
		AC 100 to 240 V	−15 to +10%	50/60 Hz, ±4 Hz

Signal transmission 0-20 mA/4-20 mA HART and additional outputs and inputs

Order code for "Output" and "Input"	**Terminal numbers**							
	Output 1		**Output 2**		**Output 3**		**Input**	
	26 (+)	**27 (-)**	**24 (+)**	**25 (-)**	**22 (+)**	**23 (-)**	**20 (+)**	**21 (-)**
Option **H**	▪ 4-20 mA HART (active) ▪ 0-20 mA (active)		Pulse/frequency output (passive)		Switch output (passive)		-	

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Jun 26, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

TDS AND SHOP DRAWINGS

DA-IC-03-CPL900 panel modif POWER SUPPLY **Date :** 2018-06-22

INFORMATION

Project : **WASTEWATER PLANT - IQALUIT**	
Client : Kudlik Construction Ltd. To Sandra Rousseau P.Eng./ Project Manager	Project number : **2018-062**
Contractor : Norclair inc.	Project number Norclair : **P1039**
Address : 1100, Montee Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Steven Wieland	E-mail: swieland@norclair.ca
Phone: 450-688-4012 # 708	Cell.: 514-608-0619

Information, subcontractor or supplier

Sub supplier : Entreprise LM	
Contact :	Phone : 514-523-2831

Information on the equipment or the proposed materials

Speciality : Instruments and controls	
Equipment : CPL-900 control panel package	
Drawing reference :	
Specification reference : 40 05 23	Division :
Article :	Number Page : 4
POWER SUPPLY in stocl (vs 25 days delays)	

CONSULTANT APPROVAL

The proposed power supply alternate is acceptable.

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-03R1 (2018-06-22)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-06-26

BY David Hutchison, P.Eng.

1100, Montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Date : 2018-06-18
Project No : 110126045

IQALUIT WASTEWATER TREATMENT PLANT UPGRADE CPL 900

Entreprises L.M.

CPL-900			EQUIVALENT			
Manufacturier	**Part Number**	**Description**	**Manufacturier**	**Part Number**	**Description**	**Data Sheet**
N-TRON	116TX	16 PORT ETHERNET SWITCH, C/W DIN MOUNT C	WEIDMULLER	1241000000	IE-SW-VL16-16TX	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
OMRON	G2R1SNDC24S	RELAY WITH LED INDICATOR	SCHNEIDER	RXG13BD	1CO 10A RELAY-LTBLED 24VDC	https://www.schneider-electric.us/en/product/RXG13BD/interfa
OMRON	P2RF-05-E	RELAY SOCKET	SCHNEIDER	RGZE1S35M	1CO SEPARATE TERMINAL SOCKET WITH CL	https://www.schneider-electric.us/en/product/RGZE1S35M/soc
HOFFMAN	A56P44F1	FULL SIZE MOUNTING PANEL	EXM	885 SP6048	PLAQUE DE FOND POUR 5500 DDS6048	http://www.exmweb.com/index.php?option=com_content&vie
HOFFMAN	ALFSWD	DOOR SWITCH	EXM	889 FLRDS	REMOTE DOOR SWITCH - SERIES FLRDS	889 flrds.pdf (PDF)
HOFFMAN	F8T5	FLUORESCENT LIGHT BULB	EXM	880 LED18	NEON LIGHTS 18"	880 led18.pdf (PDF)
HOFFMAN	LF120V18	120 VAC FLUORESCENT LIGHT KIT				
ALLEN BRADLEY	1492-SPM1B030	30A SINGLE POLE CIRCUIT BREAKER	SCHNEIDER	MG17407	PROTECTEUR SUPPLEMENTAIRE 30A 1P	https://www.schneider-electric.us/en/product/MG17407/multi
ALLEN BRADLEY	1606-XLS480E	24VDC POWER SUPPLY 20A	WEIDMULLER	1469510000	PRO ECO 480W 24V 20A	http://catalog.weidmueller.com/catalog/Start.do?localeId=hk_C
ALLEN BRADLEY	1492-SP1B150	15A SINGLE POLE CIRCUIT BREAKER	SCHNEIDER	G17406	DISJONCTEUR A BOITIER MOULE 15A	https://www.schneider-electric.us/en/product/MG17406/multi
ALLEN BRADLEY	1492-SP1B100	10A SINGLE POLE CIRCUIT BREAKER	SCHNEIDER	MG24116	COURBURE B C60N 1 POLE 10 A	https://www.schneider-electric.us/en/product/MG24116/multi
ALLEN BRADLEY	1756PA75/B	PLC POWER SUPPLY	ALLEN BRADLEY	1756PA72	PLC POWER SUPPLY	1756-td005_-en-e
PHOENIX CONTACT	UTB 2,5 - 3044636	2-TIER FEED THROUGH TERMINAL BLOCK	WEIDMULLER	1041100000	WDK 2.5 ZQV PLUGGABLE JUMPER	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
PHOENIX CONTACT	UTTB 2,5 - 3044636	END COVERS FOR ITEM 24	WEIDMULLER	1059100000	AP FOR WDK 2.5,WM,BG	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
PHOENIX CONTACT	ST 2,5-PE/L/L-3036097	2-TIER FEED SPRING CAGE TERMINAL BLOCK (2 T	WEIDMULLER	1131750000	ZDLD 2.5-2N/PE/L/L	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
PHOENIX CONTACT	D-ST 2,5-3L-3L-3036660	END COVERS FOR ITEM 26	WEIDMULLER	1782340000	ZAP/TW ZDLD 2.5-2N	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
PHOENIX CONTACT	UT 4-L/HESI-3214325	FUSED MODULAR TERMINAL BLOCK WITH FEED	WEIDMULLER	1833600000	WDK 2.5/TR-DU/O TNHE	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
			WEIDMULLER	7921570000	SIHA3/G20,LED,10-36VAC/DC	http://catalog.weidmueller.com/catalog/Start.do?localeId=en&C
			WEIDMULLER	1839850000	WAP WDK 2.5N/TR-DU	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
PHOENIX CONTACT	FBS 10-6 - 3030365	PLUG IN BRIDGE	WEIDMULLER	1693880000	ZQV 2.5N/10 GE (YELLOW)	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
			WEIDMULLER	1608940000	ZQV 2.5/10	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
			WEIDMULLER	1054460000	WQV 2.5/10 FOR WDU 2.5,10 PO	http://catalog.weidmueller.com/procat/Product.jsp;jsessionid=E
PHOENIX CONTACT	FBS 20-6 - 3030365	PLUG IN BRIDGE	WEIDMULLER	1909000000	ZQV 2.5N/20 YELLOW	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
			WEIDMULLER	1908960000	ZQV 2.5/20 YL	http://catalog.weidmueller.com/procat/Product.jsp;jsessionid=E
			WEIDMULLER	1577570000	WQV 2.5/20 FOR WDU 2.5,20 PO	http://catalog.weidmueller.com/procat/Product.jsp;jsessionid=E
PHOENIX CONTACT	UM8-0830943	TERMINAL BLOCK MARKERS	WEIDMULLER	1609801044	DEK 5/5 MC-10 NEUT. WS (WHITE)	http://catalog.weidmueller.com/catalog/Start.do?localeId=en_C
T&B	ADR21	GROUND LUG #2/0	BURNDY	K2A26U	RACCORD ALUM/CUI 14-2/0AWG 1/4	https://ecat.burndy.com/Comergent/en/US/adirect/burndy?cm
PANDUIT	G3X4LG6	WIRE DUCT 3"X4	LEGRAND	636118	TRANSCAB CABLE DUCTING BASE+COVER W	https://www.legrand.com/ecat_export/636118-cable-ducting-b
PANDUIT	C3LG6	3" WIRE DUCT COVER	LEGRAND	636118	TRANSCAB CABLE DUCTING BASE+COVER W	https://www.legrand.com/ecat_export/636118-cable-ducting-b

Allen-Bradley

1756 ControlLogix Power Supplies Specifications

Standard Power Supplies Catalog Numbers	1756-PA72, 1756-PA72K, 1756-PA75, 1756-PA75K, 1756-PB72, 1756-PB72K,1756-PB75, 1756-PB75K,1756-PC75, 1756-PH75
Standard Slim Power Supplies Catalog Numbers	1756-PA50, 1756-PA50K, 1756-PB50, 1756-PB50K
ControlLogix-XT Power Supplies Catalog Numbers	1756-PAXT, 1756-PBXT
ControlLogix-XT Slim Power Supplies Catalog Numbers	1756-PA30XT, 1756-PB30XT
Redundant Power Supplies Catalog Numbers	1756-PA75R, 1756-PA75RK,1756-PB75R, 1756-PB75RK
Redundant Power Supplies Chassis Adapter Catalog Number	1756-PSCA2, 1756-PSCA2K
ControlLogix-XT Redundant Power Supplies Catalog Numbers	1756-PAXTR, 1756-PBXTR
ControlLogix-XT Redundant Power Supplies Chassis Adapter Catalog Number	1756-PSCA2XT
Redundant Power Supply Power Cable Catalog Numbers	1756-CPR2, 1756-CPR2D, 1756-CPR2U

Topic	Page
Standard AC Power Supplies	2
Standard DC Power Supplies	4
1756 ControlLogix-XT Power Supplies	8
Redundant Power Supplies	11
Power Load and Transformer Sizing	19
Additional Resources	21

ControlLogix® power supplies are used with the 1756 chassis to provide 1.2V, 3.3V, 5V, and 24V DC power directly to the chassis backplane. Standard, Slim, ControlLogix-XT™, and redundant power supplies are available.

Summary of Changes


This manual contains new and updated information as indicated in this table.

Topic	Page
Added these power supplies: 1756-PA50K, 1756-PB50K, 1756-PA72K, 1756-PA75K, 1756-PB72K, 1756-PB75K, 1756-PA75RK, 1756-PB75RK, and 1756-PSCA2K	Throughout


Standard AC Power Supplies

Mounting Dimensions

1756-PA72, 1756-PA72K, 1756-PA75, 1756-PA72K



1756-PA50, 1756-PA50K



Dimensions are in cm (in.).

Technical Specifications - Standard AC Power Supplies

Attribute	1756-PA50, 1756-PA50K	1756-PA72/C, 1756-PA72K/C	1756-PA75/B, 1756-PA75K/B
Input voltage range[1]	85…265V AC		
Input voltage, nom	120V/240V AC		
Input frequency range	47…63 Hz		
Input power, max	81 W/91VA @ 50 °C (122 °F) 68 W/77VA @ 60 °C (140 °F)	100VA/100 W	
Output power, max	60 W @ 0…+50 °C (+32…+122 °F)[3] 50 W @ 0…+60 °C (+32…+140 °F)[4]	75 W @ 0…+60 °C (+32…+140 °F)[6]	
Inrush current, max	20 A		
Hold up time[2]	4 cycles @85...265V AC, 50/60 Hz, 60 W 5 cycles @85...265V AC, 50/60 Hz, 50 W	5 cycles @ 85V AC, 50/60 Hz 6 cycles @ 120V AC, 50/60 Hz 6 cycles @ 200V AC, 50/60 Hz 6 cycles @ 240V AC, 50/60 Hz	2 cycles @ 85V AC, 60 Hz 6 cycles @ 120V AC, 60 Hz 20 cycles @ 220V AC, 60 Hz
Current capacity @ 1.2V DC	1.5 A		
Current capacity @ 3.3V DC	2 A	4 A	
Current capacity @ 5.1V DC	8 A @ 50 °C (122 °F) 6 A @ 60 °C (140 °F)	10 A	13 A
Current capacity @ 24V DC	2.5 A @ 50 °C (122 °F) 2.0 A @ 60 °C (140 °F)	2.8 A	
Isolation voltage	250V (continuous), Reinforced Insulation Type, Power Input to Backplane Type tested @ 3150V DC for 60 s	250V (continuous), Reinforced Insulation Type, Power Input to Backplane Type tested at 3500V DC for 60 s	
Weight, approx	0.77 kg (1.7 lb)	0.95 kg (2.10 lb)	
Dimensions (HxWxD), approx	14.0 x 7.8 x 14.5 cm (5.51 x 3.07 x 5.71 in.)	14.0 x 11.2 x 14.5 cm (5.51 x 4.41 x 5.71 in.)	
Module location	Left side of 1756 chassis		
Chassis	1756-A4, 1756-A7, 1756-A10, 1756-A13, 1756-A17		
Chassis compatibility	Series A Series B Series C		Series B Series C
Wire size	2.5 mm^2 (14 AWG) solid or stranded copper wire rated at 90 °C (194 °F), or greater, 1.2 mm (3/64 in.) insulation max		

Technical Specifications - Standard AC Power Supplies

Attribute	1756-PA50, 1756-PA50K	1756-PA72/C, 1756-PA72K/C	1756-PA75/B, 1756-PA75K/B
Wire category	1 - on power ports[5]		
Conductor screw torque	0.8 N•m (7 lb•in)		
North American temperature code	T4		
Enclosure type rating	None (open-style)		

(1) UL certification for 120/240V AC, 50/60 Hz nominal. Rockwell Automation specified 85…265V AC, 47…63 Hz.
(2) The hold up time is the time between input voltage removal and DC power failure.
(3) The combination of all output power (5.1V backplane, 24V backplane, 3.3V backplane, and 1.2V backplane) cannot exceed 60 W @ 50 °C (122 °F) maximum temperature.
(4) The combination of all output power (5.1V backplane, 24V backplane, 3.3V backplane, and 1.2V backplane) cannot exceed 50 W @ 60 °C (140 °F) maximum temperature.
(5) Use this conductor category information to plan conductor routing as described in the system level installation manual. See the Industrial Automation Wiring and Grounding Guidelines, publication 1770-4.1.
(6) The combination of all output power (5.1V backplane, 24V backplane, 3.3V backplane, and 1.2V backplane) cannot exceed 75 W.

Environmental Specifications - Standard AC Power Supplies

Attribute	1756-PA50, 1756-PA50K	1756-PA72/C, 1756-PA72K/C, 1756-PA75/B, 1756-PA75K/B
Temperature, operating IEC 60068-2-1 (Test Ad, Operating Cold), IEC 60068-2-2 (Test Bd, Operating Dry Heat), IEC 60068-2-14 (Test Nb, Operating Thermal Shock)	0 °C < Ta < +60 °C (+32 °F < Ta < +140 °F)	
Temperature, surrounding air, max	60 °C (140 °F)	
Temperature, non-operating IEC 60068-2-1 (Test Ab, Unpackaged Nonoperating Cold), IEC 60068-2-2 (Test Bb, Unpackaged Nonoperating Dry Heat), IEC 60068-2-14 (Test Na, Unpackaged Nonoperating Thermal Shock)	-40…+85 °C (-40…+185 °F)	
Relative humidity IEC 60068-2-30 (Test Db, Unpackaged Damp Heat)	5…95% noncondensing	
Vibration IEC 60068-2-6 (Test Fc, Operating)	2 g @ 10…500 Hz	
Shock, operating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	30 g	
Shock, nonoperating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	50 g[1]	
Emissions	IEC 61000-6-4	
ESD immunity IEC 61000-4-2	6 kV contact discharges 8 kV air discharges	
Radiated RF immunity IEC 61000-4-3	10V/m with 1 kHz sine-wave 80% AM from 80…2000 MHz 10V/m with 200 Hz 50% Pulse 100% AM @ 900 MHz 10V/m with 200 Hz 50% Pulse 100% AM @ 1890 MHz 3V/m with 1 kHz sine-wave 80% AM from 2000…2700 MHz	
EFT/B immunity IEC 61000-4-4	±4 kV at 5 kHz on power ports	
Surge transient immunity IEC 61000-4-5	±1 kV line-line (DM) and ±2 kV line-earth (CM) on power ports	
Conducted RF immunity IEC 61000-4-6	10V rms with 1 kHz sine-wave 80% AM from 150 kHz…80 MHz	
Voltage variation IEC 61000-4-11	30% dips for 1 period at 0° and 180° on AC supply ports 60% dips for 5 and 50 periods on AC supply ports ±10% fluctuations for 15 min on AC supply ports >95% interruptions for 250 periods on AC supply ports	
Damped oscillatory wave immunity IEC 61000-4-18	±2.5 kV line-line (DM) and ±2.5 kV line-earth (CM) on power ports	–

(1) Series C chassis have a maximum nonoperating shock value of 30 g. If you select a Series C chassis for use with your power supply, you are limited to a maximum nonoperating shock value of 30 g.

Certifications - Standard AC Power Supplies


Certification[1]	1756-PA50, 1756-PA50K	1756-PA72/C, 1756-PA72K/C	1756-PA75/B, 1756-PA75K/B
UL	–	UL Listed Industrial Control Equipment. See UL File E65584.	
c-UL-us	UL Listed Industrial Control Equipment, certified for US and Canada. See UL File E65584. UL Listed for Class I, Division 2 Group A,B,C,D Hazardous Locations, certified for U.S. and Canada. See UL File E194810.	–	
CSA	–	CSA Certified Process Control Equipment. See CSA File LR54689C. CSA Certified Process Control Equipment for Class I, Division 2 Group A,B,C,D Hazardous Locations. See CSA File LR69960C.	
FM	FM Approved Equipment for use in Class I Division 2 Group A,B,C,D Hazardous Locations		
CE	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B) European Union 2014/35/EU LVD, compliant with: • EN 61010-2-201; Control Equipment Safety Requirements	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B) European Union 2014/35/EU LVD, compliant with: • EN 61131-2; Programmable Controllers (Clause 11)	
RCM	Australian Radiocommunications Act, compliant with: • EN 61000-6-4; Industrial Emissions		
KC	Korean Registration of Broadcasting and Communications Equipment, compliant with: • Article 58-2 of Radio Waves Act, Clause 3		
EAC	Russian Customs Union TR CU 020/2011 EMC Technical Regulation Russian Customs Union TR CU 004/2011 LV Technical Regulation		

(1) See the Product Certification link at http://www.ab.com for Declarations of Conformity, Certificates, and other certification details.


Standard DC Power Supplies

Mounting Dimensions

1756-PB72, 1756-PB72K, 1756-PB75, 1756-PB75K, 1756-PC75, 1756-PH75



1756-PB50, 1756-PB50K



Dimensions are in cm (in.).

Technical Specifications - Standard DC Power Supplies

Attribute	1756-PB50, 1756-PB50K	1756-PB72/C, 1756-PB72K/C	1756-PB75/B, 1756-PB75K/B	1756-PC75/B	1756-PH75/B
Input voltage range	18…32V DC[2]			30…60V DC[5]	90…143V DC[6]
Input voltage, nom	24V DC			48V DC	125V DC
Input power, max	85 W @ 50 °C (122 °F) 70 W @ 60 °C (140 °F)	95 W			

Technical Specifications - Standard DC Power Supplies

Attribute	1756-PB50, 1756-PB50K	1756-PB72/C, 1756-PB72K/C	1756-PB75/B, 1756-PB75K/B	1756-PC75/B	1756-PH75/B
Output power, max	60 W @ 0…50 °C (32…122 °F) 50 W @ 0…60 °C (32…140 °F)	75 W @ 0…60 °C (32…140 °F)[4]			
Inrush current, max	30 A				
Hold up time[1]	30 ms @18...32V DC, 60 W 40 ms @18...32V DC, 50 W	35 ms @ 18V DC 40 ms @ 24V DC 40 ms @ 32V DC		50 ms @ 30…60V DC nom	50 ms @ 90…143V DC nom
Current capacity @ 1.2V	1.5 A				
Current capacity @ 3.3V	2 A	4 A			
Current capacity @ 5.1V	8 A @ 50 °C (122 °F) 6 A @ 60 °C (140 °F)	10 A	13 A		
Current capacity @ 24V	2.5 A @ 50 °C (122 °F) 2.0 A @ 60 °C (140 °F)	2.8 A			
Isolation voltage	250V (continuous), Reinforced Insulation Type, Power Input to Backplane Type tested @ 3150V DC for 60 s	250V (continuous), Reinforced Insulation Type, Power Input to Backplane Type tested @ 3500V DC for 60 s			
Weight, approx	0.77 kg (1.7 lb)	0.95 kg (2.10 lb)			
Dimensions (HxWxD), approx	14.0 x 7.8 x 14.5 cm (5.51 x 3.07 x 5.71 in.)	14.0 x 11.2 x 14.5 cm (5.51 x 4.41 x 5.71 in.)			
Module location	Left side of 1756 chassis				
Chassis	1756-A4, 1756-A7, 1756-A10, 1756-A13, 1756-A17				
Chassis compatibility	Series A Series B Series C		Series B Series C		
Wire size	2.5 mm^2 (14 AWG) solid or stranded copper wire rated at 90 °C (194 °F), or greater, 1.2 mm (3/64 in.) insulation max				
Wire category	1 - on power ports[3]				
Conductor screw torque	0.8 N•m (7 lb•in)				
North American temperature code	T4				
ATEX temperature code	T4			–	
IEC temperature code	T4			–	
Enclosure type rating	None (open-style)				

(1) The hold up time is the time between input voltage removal and DC power failure.
(2) UL certification for 24V DC nominal. Rockwell Automation specified 18…32V DC.
(3) Use this conductor category information to plan conductor routing as described in the system level installation manual. See the Industrial Automation Wiring and Grounding Guidelines, publication 1770-4.1.
(4) The combination of all output power (5.1V backplane, 24V backplane, 3.3V backplane, and 1.2V backplane) cannot exceed 75 W.
(5) UL Certification for 48V DC nominal. Rockwell Automation specified 30…60V DC.
(6) UL certification for 125V DC nominal. Rockwell Automation specified 90…143V DC.

Environmental Specifications - Standard DC Power Supplies

Attribute	1756-PB50, 1756-PB50K	1756-PB72/C, 1756-PB72K/C 1756-PB75/B, 1756-PB75K/B	1756-PC75/B, 1756-PH75/B
Temperature, operating IEC 60068-2-1 (Test Ad, Operating Cold), IEC 60068-2-2 (Test Bd, Operating Dry Heat), IEC 60068-2-14 (Test Nb, Operating Thermal Shock)	0 °C < Ta < +60 °C (+32 °F < Ta < +140 °F)		
Temperature, surrounding air, max	60 °C (140 °F)		
Temperature, nonoperating IEC 60068-2-1 (Test Ab, Unpackaged Nonoperating Cold), IEC 60068-2-2 (Test Bb, Unpackaged Nonoperating Dry Heat), IEC 60068-2-14 (Test Na, Unpackaged Nonoperating Thermal Shock)	-40…+85 °C (-40…+185 °F)		
Relative humidity IEC 60068-2-30 (Test Db, Unpackaged Damp Heat)	5…95% noncondensing		
Vibration IEC 60068-2-6 (Test Fc, Operating)	2 g @ 10…500 Hz		
Shock, operating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	30 g		
Shock, nonoperating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	50 g(1)		
Emissions	IEC 61000-6-4		
ESD immunity IEC 61000-4-2	6 kV contact discharges 8 kV air discharges		
Radiated RF immunity IEC 61000-4-3	10V/m with 1 kHz sine-wave 80% AM from 80…2000 MHz 10V/m with 200 Hz 50% Pulse 100% AM @ 900 MHz 10V/m with 200 Hz 50% Pulse 100% AM @ 1890 MHz 3V/m with 1 kHz sine-wave 80% AM from 2000…2700 MHz		
EFT/B immunity IEC 61000-4-4	±4 kV at 5 kHz on power ports		
Surge transient immunity IEC 61000-4-5	±1 kV line-line (DM) and ±2 kV line-earth (CM) on power ports		
Conducted RF immunity IEC 61000-4-6	10V rms with 1 kHz sine-wave 80% AM from 150 kHz…80 MHz		
Voltage variation IEC 61000-4-29	10 ms interruption on DC supply ports(2) 60% dips for 100 ms on DC supply ports 100% dips for 50 ms on DC supply ports ±20% fluctuations for 15 min on DC supply ports 5 s interruptions on DC supply ports(3)		

(1) Series C chassis have a maximum nonoperating shock value of 30 g. If you select a Series C chassis for use with your power supply, you are limited to a maximum nonoperating shock value of 30 g.
(2) Short interruption test verifies ride through. The supply remains fully functional under this condition.
(3) Long interruption test verifies that repetitive inrush surge currents do not create any unsafe conditions. The supply fully shuts down and starts up in this test.

Certifications - Standard DC Power Supplies

Certification[1]	1756-PB50, 1756-PB50K	1756-PB72/C, 1756-PB72K/C 1756-PB75/B, 1756-PB75K/B	1756-PC75/B, 1756-PH75/B
UL	–		UL Listed Industrial Control Equipment. See UL File E65584.
c-UL-us	UL Listed Industrial Control Equipment, certified for US and Canada. See UL File E65584. UL Listed for Class I, Division 2 Group A,B,C,D Hazardous Locations, certified for US and Canada. See UL File E194810.		–
CSA	–	CSA Certified Process Control Equipment. See CSA File LR54689C. CSA Certified Process Control Equipment for Class I, Division 2 Group A,B,C,D Hazardous Locations. See CSA File LR69960C.	
FM	FM Approved Equipment for use in Class I Division 2 Group A,B,C,D Hazardous Locations		–
CE	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B) • EN 61000-6-4; Industrial Emissions European Union 2014/35/EU LVD, compliant with: • EN 61010-2-201; Control Equipment Safety Requirements	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B) European Union 2014/35/EU LVD, compliant with: • EN 61131-2; Programmable Controllers (Clause 11)	
RCM	Australian Radiocommunications Act, compliant with: • EN 61000-6-4; Industrial Emissions		
Ex	European Union 2014/34/EU ATEX Directive, compliant with: • EN 60079-0; General Requirements • EN 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • DEMK013ATEX1325026X		–
IECEx	IECEx System, compliant with: • IEC 60079-0; General Requirements • IEC 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • IECEx UL 14.0008X		–
KC	Korean Registration of Broadcasting and Communications Equipment, compliant with: • Article 58-2 of Radio Waves Act, Clause 3		
EAC	Russian Customs Union TR CU 020/2011 EMC Technical Regulation Russian Customs Union TR CU 004/2011 LV Technical Regulation		

(1) When marked. See the Product Certification link at http://www.ab.com for Declarations of Conformity, Certificates, and other certification details.


1756 ControlLogix-XT Power Supplies

The ControlLogix-XT products include control and communication system components that, when used with FLEX I/O-XT™ products, provide a complete control system solution that you can use in environments where temperatures range from -20...+70 °C (-4...+158 °F).


When used independently, the ControlLogix-XT system can withstand environments where the temperature ranges from -25...+70 °C (-13...+158 °F).

Mounting Dimensions

1756-PAXT and 1756-PBXT



1756-PA30XT and 1756-PB30XT



Dimensions are in cm (in.).

Technical Specifications - ControlLogix-XT Power Supplies

Attribute	1756-PAXT	1756-PBXT	1756-PA50XT	1756-PA30XT	1756-PB50XT	1756-PB30XT
Input voltage range	85…265V AC[1]				18…32V DC[5]	18…32V DC[6]
Input voltage, nom	120/240V AC				24V DC	
Input frequency range	47…63 Hz				85 W @ 50 °C (122 °F) 70 W @ 60 °C (140 °F)	
Input power, max	82VA 64 W	70 W	81 W/91VA @ 50 °C (122 °F) 68 W/77VA @ 60 °C (140 °F)	60VA 50 W	60 W @ 0…50 °C (32…122 °F) 50 W @ 0…60 °C (32…140 °F)	50 W
Output power, max	42 W @ -25…+70 °C (-13…+158 °F)	52 W @ -25…+70 °C (-13…+158 °F)	60 W @ 0…+50 °C (+32…+122 °F)[3] 50 W @ 0…+60 °C (+32…+140 °F)[4]	30 W @ -25…+70 °C (-13…+158 °F)	30 A	30 W @ -25…+70 °C (-13…+158 °F)
Inrush current, max	20 A				30 ms @18...32V DC, 60 W 40 ms @18...32V DC, 50 W	
Current capacity @ 1.2V	1.5 A					
Current capacity @3.3V	4 A	4 A	2 A	2 A	2 A	2 A
Current capacity @ 5.1V	8 A	10 A	8 A @ 50 °C (122 °F) 6 A @ 60 °C (140 °F)	6 A	8 A @ 50 °C (122 °F) 6 A @ 60 °C (140 °F)	6 A
Current capacity @ 24V	1.75 A	2.1 A	2.5 A @ 50 °C (122 °F) 2.0 A @ 60 °C (140 °F)	1.25 A	2.5 A @ 50 °C (122 °F) 2.0 A @ 60 °C (140 °F)	1.25 A

Technical Specifications - ControlLogix-XT Power Supplies

Attribute	1756-PAXT	1756-PBXT	1756-PA50XT	1756-PA30XT	1756-PB50XT	1756-PB30XT
Isolation voltage	250V (continuous), Reinforced Insulation Type, Power Input to BackplaneT ype tested @ 3260V DC for 60 s		250V (continuous), Reinforced Insulation Type, Power Input to Backplane Type tested @ 3150V DC for 60 s		250V (continuous), Reinforced Insulation Type, Power Input to Backplane Type tested @ 3150V DC for 60 s	
Weight, approx	0.95 kg (2.10 lb)	0.95 kg (2.10 lb)	0.77 kg (1.7 lb)	0.77 kg (1.7 lb)	0.77 kg (1.7 lb)	0.77 kg (1.7 lb)
Dimensions (HxWxD), approx	14.0 x 11.2 x 14.5 cm (5.51 x 4.41 x 5.71 in.)	14.0 x 11.2 x 14.5 cm (5.51 x 4.41 x 5.71 in.)	14.0 x 7.8 x 14.5 cm (5.51 x 3.07 x 5.71 in.)	14.0 x 7.8 x 14.5 cm (5.51 x 3.07 x 5.71 in.)	14.0 x 7.8 x 14.5 cm (5.51 x 3.07 x 5.71 in.)	14.0 x 7.8 x 14.5 cm (5.51 x 3.07 x 5.71 in.)
Module location	Left side of 1756 chassis					
Chassis	1756-A4LXT/B, 1756-A5XT/B, 1756-A7LXT/B, 1756-A7XT/B, 1756-A7XT/C, 1756-A10XT/C					
Wire size	2.5 mm^2 (14 AWG) solid or stranded copper wire rated at 90 °C (194 °F), or greater, 1.2 mm (3/64 in.) insulation, max					
Wire category	1 - on power ports(2)					
Conductor screw torque	0.8 N•m (7 lb•in)					
North American temperature code	T4	T4	T4	T4	T4	T4
ATEX temperature code	–					
IEC temperature code	–					
Enclosure type rating	None (open-style)					

(1) UL certification for 120/240V AC, 50/60 Hz nominal. Rockwell Automation specified 85…265V AC, 47…63 Hz.
(2) Use this conductor category information to plan conductor routing as described in the system level installation manual. See the Industrial Automation Wiring and Grounding Guidelines, publication 1770-4.1.
(3) The combination of all output power (5.1V backplane, 24V backplane, 3.3V backplane, and 1.2V backplane) cannot exceed 60 W @ 50 °C (122 °F) maximum temperature.
(4) The combination of all output power (5.1V backplane, 24V backplane, 3.3V backplane, and 1.2V backplane) cannot exceed 50 W @ 60 °C (140 °F) maximum temperature.
(5) UL certification for 24V DC nominal. Rockwell Automation specified 18…32V DC.
(6) UL certification for 24V DC nominal. Rockwell Automation specified 18…32V DC.

Environmental Specifications - ControlLogix-XT Power Supplies

Attribute	1756-PAXT	1756-PA30XT	1756-PBXT	1756-PB30XT
Temperature, operating IEC 60068-2-1 (Test Ad, Operating Cold), IEC 60068-2-2 (Test Bd, Operating Dry Heat), IEC 60068-2-14 (Test Nb, Operating Thermal Shock)	-25 °C < Ta < +70 °C (-13 °F < Ta < +158 °F)			
Temperature, surrounding air, max	70 °C 158 °F)			
Temperature, nonoperating IEC 60068-2-1 (Test Ab, Unpackaged Nonoperating Cold), IEC 60068-2-2 (Test Bb, Unpackaged Nonoperating Dry Heat), IEC 60068-2-14 (Test Na, Unpackaged Nonoperating Thermal Shock)	-40…+85 °C (-40…+185 °F)			
Relative humidity IEC 60068-2-30 (Test Db, Unpackaged Damp Heat)	5…95% noncondensing			
Vibration IEC 60068-2-6 (Test Fc, Operating)	2 g @ 10…500 Hz			
Shock, operating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	30 g			
Shock, nonoperating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	50 g(1)			
Emissions	IEC 61000-6-4			
ESD immunity IEC 61000-4-2	6 kV contact discharges 8 kV air discharges			

Environmental Specifications - ControlLogix-XT Power Supplies

Attribute	1756-PAXT	1756-PA30XT	1756-PBXT	1756-PB30XT
Radiated RF immunity IEC 61000-4-3	10V/m with 1 kHz sine-wave 80% AM from 80…2000 MHz 10V/m with 200 Hz 50% Pulse 100% AM at 900 MHz 10V/m with 200 Hz 50% Pulse 100% AM at 1890 MHz 3V/m with 1 kHz sine-wave 80% AM from 2000…2700 MHz			
EFT/B immunity IEC 61000-4-4	±4 kV at 5 kHz on power ports			
Surge transient immunity IEC 61000-4-5	±1 kV line-line (DM) and ±2 kV line-earth (CM) on power ports			
Conducted RF immunity IEC 61000-4-6	10V rms with 1 kHz sine-wave 80% AM from 150 kHz…80 MHz			
Voltage variation IEC 61000-4-11	30% dips for 1 period at 0° and 180° on AC supply ports 60% dips for 5 and 50 periods on AC supply ports ±10% fluctuations for 15 min on AC supply ports >95% interruptions for 250 periods on AC supply ports		–	
Voltage variation IEC 61000-4-29	–		10 ms interruption on DC supply ports(2) 60% dips for 100 ms on DC supply ports 100% dips for 50 ms on DC supply ports ±20% fluctuations for 15 min on DC supply ports 5 s interruptions on DC supply ports(3)	
Damped oscillatory wave immunity IEC 61000-4-18	–	±2.5 kV line-line (DM) and ±2.5 kV line-earth (CM) on power ports	–	±2.5 kV line-line (DM) and ±2.5 kV line-earth (CM) on power ports

(1) Series C chassis have a maximum nonoperating shock value of 30 g. If you select a Series C chassis for use with your power supply, you are limited to a maximum nonoperating shock value of 30 g.
(2) Short interruption test verifies ride through. The supply remains fully functional under this condition.
(3) Long interruption test verifies that repetitive inrush surge currents do not create any unsafe conditions. The supply fully shuts down and starts up in this test.

Certifications - ControlLogix-XT Power Supplies

Certification(1)	1756-PAXT	1756-PA30XT	1756-PBXT	1756-PB30XT
c-UL-us	UL Listed Industrial Control Equipment, certified for US and Canada. See UL File E65584. UL Listed for Class I, Division 2 Group A,B,C,D Hazardous Locations, certified for US and Canada. See UL File E194810.			
CE	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B) European Union 2014/35/EU LVD, compliant with: • EN 61131-2; Programmable Controllers (Clause 11)	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B) European Union 2014/35/EU LVD, compliant with: • EN 61010-2-201; Control Equipment Safety Requirements	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B) European Union 2014/35/EU LVD, compliant with: • EN 61131-2; Programmable Controllers (Clause 11)	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B) European Union 2014/35/EU LVD, compliant with: • EN 61010-2-201; Control Equipment Safety Requirements
RCM	Australian Radiocommunications Act, compliant with: EN 61000-6-4; Industrial Emissions			
Ex	–		European Union 2014/34/EU ATEX Directive, compliant with: • EN 60079-0; General Requirements • EN 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc X • DEMKO13ATEX1325026X	
IECEx	–		IECEx System, compliant with: • IEC 60079-0; General Requirements • IEC 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • IECEx UL 14.0008X	
KC	Korean Registration of Broadcasting and Communications Equipment, compliant with: • Article 58-2 of Radio Waves Act, Clause 3			
EAC	Russian Customs Union TR CU 020/2011 EMC Technical Regulation Russian Customs Union TR CU 004/2011 LV Technical Regulation			

(1) When marked. See the Product Certification link at http://www.ab.com for Declarations of Conformity, Certificates, and other certification details.

Redundant Power Supplies

To build a redundant power supply system, you need the following.


Cat. No.	Description	Amount
1756-PA75R/A, 1756-PA75RK/A, 1756-PAXTR, 1756-PB75R/A, 1756-PB75RK/A, or 1756-PBXTR	Redundant power supply	2
1756-CPR2[1] 1756-CPR2D[2] or 1756-CPR2U[2]	Redundant power supply cable (Length = 0.91 m [3 ft])	2
1756-PSCA2, 1756-PSCA2K, or 1756-PSCA2XT	Redundant power supply chassis adapter[3]	1
User-supplied	Annunciator wiring[4] (Length, max = 10 m [32.8 ft])	2

(1) Cable bend radius is 12.7 cm (5.0 in.).
(2) Requires 10.16 cm (4.0 in.) of clearance next to the chassis adapter.
(3) The 1756-PSCA2 or 1756-PSCA-2XT chassis adapter is a passive device. The adapter funnels power from the redundant power supplies to the single power connector on the ControlLogix® series B chassis backplane.
(4) Optional user-provided annunciator wiring can be connected to the solid-state relay for status and troubleshooting.


System Configuration Recommendations

We recommend that you use one of these methods to configure your redundant power supply system.


Recommended Configurations for a System That Uses One Chassis




Recommended Configurations for a System That Uses Two Chassis



Mounting Dimensions





Dimensions are in cm (in.).

Redundant Power Supply Features

The redundant power supplies offer the same features as the standard power supplies, and the following:

- Redundant operation
- Automatic chassis load sharing between the redundant power supplies
- Status indicators for visual operating status of the pair
- Solid-state relay for system recognition of supply status when wired to an input module
- The ControlLogix redundant power supply system is designed to account for operational anomalies in only the power supply (the chassis adapter and power supply cables are excluded)

Technical Specifications - ControlLogix Redundant Power Supplies

Attribute	1756-PA75R, 1756-PA75RK	1756-PB75R, 1756-PB75RK
Input voltage range	85…265V AC[1]	18…32V DC[2]
Input voltage	120V/240V AC, 50/60 Hz	24V DC
Input frequency range	47…63 Hz	–
Input power, max	120VA 115 W	110 W
Output power, max	75 W @ 0…60 °C (32…140 °F)	
Inrush current, max	20 A	30 A
Hold up time[3]	2 cycles @ 60 Hz 2 cycles @ 50 Hz	20 ms
Current capacity @ 1.2V	1.5 A	
Current capacity @ 3.3V	4 A	
Current capacity @ 5.1V	13 A	
Current capacity @ 24V	2.8 A	
Annunciator power	240V AC 50/60 Hz, 240V DC, 50 mA, resistive only	90V DC for ATEX/IECEx
Isolation voltage	250V (continuous), Reinforced Insulation Type, Power Input to Backplane, Power Input to Annunciator, Annunciator to Backplane Type tested at 3250V DC for 60 s	

Technical Specifications - ControlLogix Redundant Power Supplies

Attribute	1756-PA75R, 1756-PA75RK	1756-PB75R, 1756-PB75RK
Dimensions (HxWxD), approx	17.5 x 14.5 x 13.7 cm (6.9 x 5.7 x 5.4 in.)	
Weight, approx	1.45 kg (3.2 lb)	
Chassis	1756-A4, 1756-A7, 1756-A10, 1756-A13, 1756-A17	
Wire size	Power: 2.5 mm^2 (14 AWG) solid or stranded copper wire rated at 90 °C (194 °F), or greater, 1.2 mm (3/64 in.) insulation max Annunciator: 0.25…2.5 mm^2 (22…14 AWG) solid or stranded copper wire rated at 90 °C (194 °F), or greater, 1.2 mm (3/64 in.) insulation max	
Wire category (4)	3 - on annunciator ports 1 - on power ports 3 - on 1756-CPR2 connections	
Pilot duty rating	Annunciator - not rated	
Conductor screw torque	0.79 N•m (7 lb•in)	
North American temperature code	T3C	T4
ATEX temperature code	–	T4
IEC temperature code	–	T4
Enclosure type rating	None (open-style)	

(1) UL certification for 120/240V AC, 50/60 Hz nominal. Rockwell Automation specified 85…265V AC, 47…63 Hz.
(2) UL certification for 24V DC nominal. Rockwell Automation specified 18…32V DC.
(3) The hold up time is the time between input voltage removal and DC power failure.
(4) Use this conductor category information to plan conductor routing. See the Industrial Automation Wiring and Grounding Guidelines, publication 1770-4.1.

Environmental Specifications - Redundant Power Supplies

Attribute	1756-PA75R, 1756-PA75RK	1756-PB75R, 1756-PB75RK
Temperature, operating IEC 60068-2-1 (Test Ad, Operating Cold), IEC 60068-2-2 (Test Bd, Operating Dry Heat), IEC 60068-2-14 (Test Nb, Operating Thermal Shock)	0…60 °C (32…140 °F)	
Temperature, surrounding air, max	60 °C 140 °F)	
Temperature, nonoperating IEC 60068-2-1 (Test Ab, Unpackaged Nonoperating Cold), IEC 60068-2-2 (Test Bb, Unpackaged Nonoperating Dry Heat), IEC 60068-2-14 (Test Na, Unpackaged Nonoperating Thermal Shock)	-40…+85 °C (-40…+185 °F)	
Relative humidity IEC 60068-2-30 (Test Db, Unpackaged Damp Heat)	5…95% noncondensing	
Vibration IEC 60068-2-6 (Test Fc, Operating)	2 g @ 10…500 Hz	
Shock, operating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	30 g	
Shock, nonoperating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	50 g	
Emissions	IEC 61000-6-4	
ESD immunity IEC 61000-4-2	6 kV contact discharges 8 kV air discharges	
Radiated RF immunity IEC 61000-4-3	10V/m with 1 kHz sine-wave 80% AM from 80…2000 MHz 10V/m with 200 Hz 50% Pulse 100% AM @ 900 MHz 10V/m with 200 Hz 50% Pulse 100% AM at 1890 MHz 3V/m with 1 kHz sine-wave 80% AM from 2000…2700 MHz	
EFT/B immunity IEC 61000-4-4	±4 kV at 5 kHz on power ports ±4 kV at 5 kHz on annunciator ports	
Surge transient immunity IEC 61000-4-5	±1 kV line-line (DM) and ±2 kV line-earth (CM) on power ports	

Environmental Specifications - Redundant Power Supplies

Attribute	1756-PA75R, 1756-PA75RK	1756-PB75R, 1756-PB75RK
Conducted RF immunity IEC 61000-4-6	15V rms with 1 kHz sine-wave 80% AM from 150 kHz…80 MHz	
Conducted audio immunity IEC 945	2 W max from rated frequency to the 200th harmonic on AC supply ports	
Voltage variation IEC 61000-4-11	30% dips for 1 period at 0° and 180° on AC supply ports 60% dips for 5 and 50 periods on AC supply ports ±10% fluctuations for 15 min on AC supply ports >95% interruptions for 250 periods on AC supply ports	–
Voltage variation IEC 61000-4-29	–	10 ms interruption on DC supply ports(1) 60% dips for 100 ms on DC supply ports 100% dips for 50 ms on DC supply ports ±20% fluctuations for 15 min on DC supply ports 5 s interruptions on DC supply ports(2)

(1) Short interruption test verifies ride through. The supply remains fully functional under this condition.
(2) Long interruption test verifies that repetitive inrush surge currents do not create any unsafe conditions. The supply fully shuts down and starts up in this test.

Certifications - Redundant Power Supplies

Certification(1)	1756-PA75R, 1756-PA75RK	1756-PB75R, 1756-PB75RK
c-UL-us	UL Listed Industrial Control Equipment, certified for US and Canada. See UL File E65584. UL Listed for Class I, Division 2 Group A,B,C,D Hazardous Locations, certified for U.S. and Canada. See UL File E194810.	
CSA	CSA Certified Process Control Equipment. See CSA File LR54689C. CSA Certified Process Control Equipment for Class I, Division 2 Group A,B,C,D Hazardous Locations. See CSA File LR69960C.	
FM	FM Approved Equipment for use in Class I Division 2 Group A,B,C,D Hazardous Locations	
CE	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B) European Union 2014/35/EU LVD, compliant with: • EN 61131-2; Programmable Controllers (Clause 11)	
RCM	Australian Radiocommunications Act, compliant with: • EN 61000-6-4; Industrial Emissions	
Ex	–	European Union 2014/34/EU ATEX Directive, compliant with: • EN 60079-0; General Requirements • EN 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • DEMKO13ATEX1325026X
IECEx	–	IECEx System, compliant with: • IEC 60079-0; General Requirements • IEC 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • IECEx UL 14.0008X
KC	Korean Registration of Broadcasting and Communications Equipment, compliant with: • Article 58-2 of Radio Waves Act, Clause 3	
EAC	Russian Customs Union TR CU 020/2011 EMC Technical Regulation Russian Customs Union TR CU 004/2011 LV Technical Regulation	

(1) When marked. See the Product Certification link at http://www.ab.com for Declarations of Conformity, Certificates, and other certification details.

Technical Specifications - ControlLogix-XT Redundant Power Supplies

Attribute	1756-PAXTR	1756-PBXTR
Input voltage range	85…265V AC[2]	18…32V DC
Input voltage	120V/240V AC	24V DC
Input frequency range	47…63 Hz	–
Input power, max	75VA 65 W	81 W
Output power, max	42 W @ 0…60 °C (32…140 °F)	52 W
Inrush current, max	20 A	30 A
Current capacity @ 1.2V	1.5 A	
Current capacity @ 3.3V	4 A	
Current capacity @ 5.1V	8 A	10 A
Current capacity @ 24V	1.75 A	2.1 A
Annunciator power	240V AC 50/60 Hz, 240V DC, 50 mA, resistive only	240V AC 50/60 Hz, 240V DC, 50 mA, resistive only 90V DC for ATEX/IECEx
Isolation voltage	250V (continuous), Reinforced Insulation Type, Power Input to Backplane, Power Input to Annunciator, Annunciator to Backplane Type tested at 3250V DC for 60 s	
Dimensions (HxWxD), approx	17.5 x 14.5 x 13.7 cm (6.9 x 5.7 x 5.4 in.)	
Weight, approx	1.45 kg (3.2 lb)	
Chassis	1756-A4/B, 1756-A7/B, 1756-A10/B, 1756-A13/B, 1756-A17/B, 1756-A4LXT/B, 1756-A5XT/B, 1756-A7LXT/B, 1756-A7XT/B 1756-A4/C, 1756-A7/C, 1756-A10/C, 1756-A13/C, 1756-A17/C, 1756-A7XT/C	
Wire size	Power: 2.5 mm^2 (14 AWG) solid or stranded copper wire rated at 90 °C (194 °F), or greater, 1.2 mm (3/64 in.) insulation max Annunciator: 0.25…2.5 mm^2 (22…14 AWG) solid or stranded copper wire rated at 90 °C (194 °F), or greater, 1.2 mm (3/64 in.) insulation max	
Wire category [1]	1 - on power ports 3 - on annunciator ports 3 - on 1756-CPR2 connections	
Pilot duty rating	Annunciator - not rated	
Conductor screw torque	0.79 N•m (7 lb•in)	
North American temperature code	T4A	
ATEX temperature code	–	T4
IEC temperature code	–	T4
Enclosure type rating	None (open-style)	

(1) Use this conductor category information to plan conductor routing. See Industrial Automation Wiring and Grounding Guidelines, publication 1770-4.1.

(2) UL certification for 120/240V AC, 50/60 Hz nominal. Rockwell Automation specified 85…265V AC, 47…63 Hz.

Environmental Specifications - XT Redundant Power Supplies

Attribute	1756-PAXTR	1756-PBXTR
Temperature, operating IEC 60068-2-1 (Test Ad, Operating Cold), IEC 60068-2-2 (Test Bd, Operating Dry Heat), IEC 60068-2-14 (Test Nb, Operating Thermal Shock)	-25…+70 °C (13…+158 °F)	
Temperature, surrounding air, max	70 °C (158 °F)	
Temperature, nonoperating IEC 60068-2-1 (Test Ab, Unpackaged Nonoperating Cold), IEC 60068-2-2 (Test Bb, Unpackaged Nonoperating Dry Heat), IEC 60068-2-14 (Test Na, Unpackaged Nonoperating Thermal Shock)	-40…+85 °C (-40…+185 °F)	
Relative humidity IEC 60068-2-30 (Test Db, Unpackaged Damp Heat)	5…95% noncondensing	
Vibration IEC 60068-2-6 (Test Fc, Operating)	2 g @ 10…500 Hz	
Shock, operating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	30 g	
Shock, nonoperating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	50 g	
Emissions	IEC 61000-6-4	
ESD immunity IEC 61000-4-2	6 kV contact discharges 8 kV air discharges	
Radiated RF immunity IEC 61000-4-3	10V/m with 1 kHz sine-wave 80% AM from 80…2000 MHz 10V/m with 200 Hz 50% Pulse 100% AM @ 900 MHz 10V/m with 200 Hz 50% Pulse 100% AM at 1890 MHz 3V/m with 1 kHz sine-wave 80% AM from 2000…2700 MHz	
EFT/B immunity IEC 61000-4-4	±4 kV at 5 kHz on power ports ±4 kV at 5 kHz on annunciator ports	
Surge transient immunity IEC 61000-4-5	±1 kV line-line (DM) and ±2 kV line-earth (CM) on power ports	
Conducted RF immunity IEC 61000-4-6	15V rms with 1 kHz sine-wave 80% AM from 150 kHz…80 MHz	10V rms with 1 kHz sine-wave 80% AM from 150 kHz…80 MHz
Conducted audio immunity IEC 945	2 W max from rated frequency to the 200th harmonic on AC supply ports	
Voltage variation IEC 61000-4-11	30% dips for 1 period at 0° and 180° on AC supply ports 60% dips for 5 and 50 periods on AC supply ports ±10% fluctuations for 15 min on AC supply ports >95% interruptions for 250 periods on AC supply ports	–
Voltage variation IEC 61000-4-29	–	10 ms interruption on DC supply ports(1) 60% dips for 100 ms on DC supply ports 100% dips for 50 ms on DC supply ports ±20% fluctuations for 15 min on DC supply ports 5 s interruptions on DC supply ports(2)

(1) Short interruption test verifies ride through. The supply remains fully functional under this condition.
(2) Long interruption test verifies that repetitive inrush surge currents do not create any unsafe conditions. The supply fully shuts down and starts up in this test.

Certifications - XT Redundant Power Supplies

Certification[1]	1756-PAXTR	1756-PBXTR
c-UL-us	UL Listed Industrial Control Equipment, certified for US and Canada. See UL File E65584. UL Listed for Class I, Division 2 Group A,B,C,D Hazardous Locations, certified for U.S. and Canada. See UL File E194810.	
CE	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B) European Union 2014/35/EU LVD, compliant with: • EN 61131-2; Programmable Controllers (Clause 11)	
RCM	Australian Radiocommunications Act, compliant with: • EN 61000-6-4; Industrial Emissions	
Ex	–	European Union 2014/34/EU ATEX Directive, compliant with: • EN 60079-0; General Requirements • EN 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • DEMKO13ATEX1325026X
IECEx	–	IECEx System, compliant with: • IEC 60079-0; General Requirements • IEC 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • IECEx UL 14.0008X
KC	Korean Registration of Broadcasting and Communications Equipment, compliant with: • Article 58-2 of Radio Waves Act, Clause 3	
EAC	Russian Customs Union TR CU 020/2011 EMC Technical Regulation Russian Customs Union TR CU 004/2011 LV Technical Regulation	

(1) When marked. See the Product Certification link at http://www.ab.com for Declarations of Conformity, Certificates, and other certification details.

Redundant Power Supply Chassis Adapter

Technical Specifications - Redundant Power Supplies Chassis Adapter

Attribute	1756-PSCA2, 1756-PSCA2K	1756-PSCA2XT
Current capacity @ 1.2V DC	1.5 A	
Current capacity @ 3.3V DC	4 A	
Current capacity @ 5.1V DC	15 A	
Current capacity @ 24V DC	2.8 A	
Wire category [1]	3 - on 1756-CPR2 connections	
North American temperature code	T5	T4A
ATEX temperature code	T4	
IEC temperature code	T4	
Enclosure type rating	None (open-style)	

(1) Use this conductor category information to plan conductor routing. See the Industrial Automation Wiring and Grounding Guidelines, publication 1770-4.1.

Environmental Specifications - Redundant Power Supplies Chassis Adapter

Attribute	1756-PSCA2, 1756-PSCA2K	1756-PSCA2XT
Temperature, operating IEC 60068-2-1 (Test Ad, Operating Cold), IEC 60068-2-2 (Test Bd, Operating Dry Heat), IEC 60068-2-14 (Test Nb, Operating Thermal Shock)	0…60 °C (32…140 °F)	-25…+70 °C (-13…+158 °F)
Temperature, surrounding air, max	60 °C (140 °F)	70 °C (158 °F)
Temperature, nonoperating IEC 60068-2-1 (Test Ab, Unpackaged Nonoperating Cold), IEC 60068-2-2 (Test Bb, Unpackaged Nonoperating Dry Heat), IEC 60068-2-14 (Test Na, Unpackaged Nonoperating Thermal Shock)	-40…+85 °C (-40…+185 °F)	
Relative humidity IEC 60068-2-30 (Test Db, Unpackaged Damp Heat)	5…95% noncondensing	
Vibration IEC 60068-2-6 (Test Fc, Operating)	2 g @ 10…500 Hz	
Shock, operating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	30 g	
Shock, nonoperating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	50 g	
Emissions	IEC 61000-6-4	
ESD immunity IEC 61000-4-2	6 kV contact discharges 8 kV air discharges	
Radiated RF immunity IEC 61000-4-3	10V/m with 1 kHz sine-wave 80% AM from 80…2000 MHz 10V/m with 200 Hz 50% Pulse 100% AM at 900 MHz 10V/m with 200 Hz 50% Pulse 100% AM at 1890 MHz 3V/m with 1 kHz sine-wave 80% AM from 2000…2700 MHz	

Certifications - Redundant Power Supplies Chassis Adapter

Certification(1)	1756-PSCA2, 1756-PSCA2K	1756-PSCA2XT
c-UL-us	UL Listed Industrial Control Equipment, certified for US and Canada. See UL File E65584. UL Listed for Class I, Division 2 Group A,B,C,D Hazardous Locations, certified for U.S. and Canada. See UL File E194810.	
CSA	CSA Certified Process Control Equipment. See CSA File LR54689C. CSA Certified Process Control Equipment for Class I, Division 2 Group A,B,C,D Hazardous Locations. See CSA File LR69960C.	–
FM	FM Approved Equipment for use in Class I Division 2 Group A,B,C,D Hazardous Locations	–
CE	European Union 2014/30/EU EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B)	
RCM	Australian Radiocommunications Act, compliant with: • EN 61000-6-4; Industrial Emissions	
Ex	European Union 2014/34/EU ATEX Directive, compliant with: • EN 60079-0; General Requirements • EN 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • DEMKO13ATEX1325026X	European Union 2014/34/EU ATEX Directive, compliant with: • EN 60079-0; General Requirements • EN 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • DEMKO13ATEX1325026X
IECEx	IECEx System, compliant with: • IEC 60079-0; General Requirements • IEC 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • IECEx UL 14.0008X	IECEx System, compliant with: • IEC 60079-0; General Requirements • IEC 60079-15; Potentially Explosive Atmospheres, Protection "n" • II 3 G Ex nA IIC T4 Gc • IECEx UL 14.0008X
KC	Korean Registration of Broadcasting and Communications Equipment, compliant with: • Article 58-2 of Radio Waves Act, Clause 3	
EAC	Russian Customs Union TR CU 020/2011 EMC Technical Regulation Russian Customs Union TR CU 004/2011 LV Technical Regulation	

(1) When marked. See the Product Certification link at http://www.ab.com for Declarations of Conformity, Certificates, and other certification details.

Power Load and Transformer Sizing

The following graphs show the input power requirements for slim and standard power supplies, given the power that they are providing to the modules in the chassis.

Follow these steps to determine the power requirements for your chassis.


1. Calculate the Backplane Power load by adding the power draw (in watts) for all planned modules.

   For module power draws, refer to the module specification tables in the ControlLogix Selection Guide, publication 1756-SG001.
2. Locate the Backplane Power load on the vertical (y) axis of the graph and determine the corresponding Real Power (input-power) rating on the horizontal (x) axis.


   The Real Power value is the amount of power that is consumed by the power supply.

Slim Power Supply Power Requirements


1756-PA50, 1756-PA50K @ 50 °C (AC)




1756-PA30XT (AC)




1756-PA50, 1756-PA50K @ 60 °C (AC)




1756-PB30XT (DC)



1756-PB50, 1756-PB50K @ 50 °C (DC)




1756-PB50, 1756-PB50K @ 60 °C (DC)




Apparent Power (Watts) = Transformer Load (VA) = Real Power (Watts)

Standard Power Supply Power Requirements


1756-PA72/C, 1756-PA72K/C, 1756-PA75/B (AC), 1756-PA75K/B (AC)




1756-PB72/C, 1756-PB72K/C, 1756-PB75/B (AC), 1756-PB75K/B (DC)




1756-PH75/B, 1756-PC75/B (DC)




1756-PAXT (AC)




1756-PAXTR (AC)




1756-PBXT (DC)




1756-PBXTR (DC)



1756-PA75R/A, 1756-PA75RK/A(AC)



1756-PB75R/A, 1756-PB75RK/A (DC)



Apparent Power (Watts) = Transformer Load (VA) = Real Power (Watts)

Additional Resources

These documents contain additional information concerning related products from Rockwell Automation.

Resource	Description
ControlLogix Chassis Specifications Technical Data, publication 1756-TD006	Provides technical specifications for ControlLogix chassis.
ControlLogix Selection Guide, publication 1756-SG001	Provides overview of the ControlLogix system and its products.
ControlLogix Power Supply Installation Instructions, publication 1756-IN619	Provides information on how to install ControlLogix standard power supplies.
ControlLogix Redundant Power Supply Installation Instructions, publication 1756-IN620	Provides information on how to install ControlLogix redundant power supplies.
ControlLogix Chassis Installation Instructions, publication 1756-IN621	Provides information on how to install ControlLogix chassis.
ControlLogix System User Manual, publication 1756-UM001	Provides information on how to install, configure, program, and use ControlLogix systems.
Industrial Automation Wiring and Grounding Guidelines, publication 1770.4.1	Provides general guidelines for installing a Rockwell Automation® industrial system.
Product Certifications website, http://www.rockwellautomation.com/global/certification/overview.page	Provides declarations of conformity, certificates, and other certification details.

You can view or download publications at http://www.rockwellautomation.com/literature/. To order paper copies of technical documentation, contact your local Allen-Bradley distributor or Rockwell Automation sales representative.

Rockwell Automation Support

Use the following resources to access support information.

Technical Support Center	Knowledgebase Articles, How-to Videos, FAQs, Chat, User Forums, and Product Notification Updates.	www.rockwellautomation.com/knowledgebase
Local Technical Support Phone Numbers	Locate the phone number for your country.	www.rockwellautomation.com/global/support/get-support-now.page
Direct Dial Codes	Find the Direct Dial Code for your product. Use the code to route your call directly to a technical support engineer.	www.rockwellautomation.com/global/support/direct-dial.page
Literature Library	Installation Instructions, Manuals, Brochures, and Technical Data.	www.rockwellautomation.com/literature
Product Compatibility and Download Center (PCDC)	Get help determining how products interact, check features and capabilities, and find associated firmware.	www.rockwellautomation.com/global/support/pcdc.page

Documentation Feedback

Your comments will help us serve your documentation needs better. If you have any suggestions on how to improve this document, complete the How Are We Doing? form at http://literature.rockwellautomation.com/idc/groups/literature/documents/du/ra-du002_-en-e.pdf.

Rockwell Automation maintains current product environmental information on its website at http://www.rockwellautomation.com/rockwellautomation/about-us/sustainability-ethics/product-environmental-compliance.page.

Allen-Bradley, ControlLogix, ControlLogix-XT, FLEX I/O-XT, LISTEN. THINK. SOLVE, Rockwell Automation, and Rockwell Software are trademarks of Rockwell Automation, Inc.
Trademarks not belonging to Rockwell Automation are property of their respective companies.

Rockwell Otomasyon Ticaret A.Ş., Kar Plaza İş Merkezi E Blok Kat:6 34752 İçerenköy, İstanbul, Tel: +90 (216) 5698400

www.rockwellautomation.com

Power, Control and Information Solutions Headquarters

Americas: Rockwell Automation, 1201 South Second Street, Milwaukee, WI 53204-2496 USA, Tel: (1) 414.382.2000, Fax: (1) 414.382.4444
Europe/Middle East/Africa: Rockwell Automation NV, Pegasus Park, De Kleetlaan 12a, 1831 Diegem, Belgium, Tel: (32) 2 663 0600, Fax: (32) 2 663 0640
Asia Pacific: Rockwell Automation, Level 14, Core F, Cyberport 3, 100 Cyberport Road, Hong Kong, Tel: (852) 2887 4788, Fax: (852) 2508 1846

Publication 1756-TD005H-EN-E - November 2017
Supersedes Publication 1756-TD005G-EN-E - June 2017

Copyright © 2017 Rockwell Automation, Inc. All rights reserved. Printed in the U.S.A.

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng.

DATE: Jun 18, 2018

STANTEC PROJECT #: 110126045

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

SUBMITTAL # DA-IC-03-CPL900 (2018-06-18)

Stantec

☐ REVIEWED

☑ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-JUN-21

BY David Hutchison, P.Eng.

TDS AND SHOI

DA-IC-03-CPL900 panel

INFORMATION	
Project : **WASTEWATER PLANT - IQALUIT**	
Client : Kudlik Construction Ltd. To Sandra Rousseau P.Eng./ Project Manager	Project number : **2018-062**
Contractor : Norclair inc.	Project number Norclair : **P1039**
Address : 1100, Montee Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Steven Wieland	E-mail: swieland@norclair.ca
Phone: 450-688-4012 # 708	Cell.: 514-608-0619

Information, subcontractor or supplier	
Sub supplier : Entreprise LM	
Contact :	Phone : 514-523-2831

Information on the equipment or the proposed materials	
Speciality : Instruments and controls	
Equipment : CPL-900 control panel package	
Drawing reference :	
Specification reference : 40 05 23	Division :
Article :	Number Page : 26

Please note that material not shown in the equivalent table are as per specifications. Thank you for getting back to us ASAP as orders would ideally be placed Friday June 22nd.

CONSULTANT APPROVAL

[DH] Alternatives are acceptable. Contractor is responsible for ensuring new components fit within the existing cabinet.
[DH] All labels and lamecoids to be provided in English

STANTEC PROJECT #: 110126045

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

SUBMITTAL # DA-IC-03-CPL900 (2018-06-18)

Stantec

☐ REVIEWED

☑ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-JUN-21

BY David Hutchison, P.Eng.

1100, Montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Date : 2018-06-18
Project No : 110126045

IQALUIT WASTEWATER TREATMENT PLANT UPGRADE CPL 900

Entreprises L.M.

CPL-900			EQUIVALENT			
Manufacturier	**Part Number**	**Description**	**Manufacturier**	**Part Number**	**Description**	**Data Sheet**
N-TRON	116TX	16 PORT ETHERNET SWITCH, C/W DIN MOUNT (	WEIDMULLER	1241000000	IE-SW-VL16-16TX	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
OMRON	G2R1SNDC24S	RELAY WITH LED INDICATOR	SCHNEIDER	RXG13BD	1CO 10A RELAY-LTBLED 24VDC	https://www.schneider-electric.us/en/product/RXG13BD/inter
OMRON	P2RF-05-E	RELAY SOCKET	SCHNEIDER	RGZE1S35M	1CO SEPARATE TERMINAL SOCKET WITH CL	https://www.schneider-electric.us/en/product/RGZE1S35M/so
HOFFMAN	A56P44F1	FULL SIZE MOUNTING PANEL	EXM	885 SP6048	PLAQUE DE FOND POUR 5500 DDS6048	http://www.exmweb.com/index.php?option=com_content&vie
HOFFMAN	ALFSWD	DOOR SWITCH	EXM	889 FLRDS	REMOTE DOOR SWITCH - SERIES FLRDS	889 flrds.pdf (PDF)
HOFFMAN	F8T5	FLUORESCENT LIGHT BULB	EXM	880 LED18	NEON LIGHTS 18"	880 led18.pdf (PDF)
HOFFMAN	LF120V18	120 VAC FLUORESCENT LIGHT KIT				
ALLEN BRADLEY	1492-SPM1B030	30A SINGLE POLE CIRCUIT BREAKER	SCHNEIDER	MG17407	PROTECTEUR SUPPLEMENTAIRE 30A 1P	https://www.schneider-electric.us/en/product/MG17407/mult
ALLEN BRADLEY	1606-XLS480E	24VDC POWER SUPPLY 20A	WEIDMULLER	1469510000	PRO ECO 480W 24V 20A	http://catalog.weidmueller.com/catalog/Start.do?localeId=hk
ALLEN BRADLEY	1492-SP1B150	15A SINGLE POLE CIRCUIT BREAKER	SCHNEIDER	G17406	DISJONCTEUR A BOITIER MOULE 15A	https://www.schneider-electric.us/en/product/MG17406/mult
ALLEN BRADLEY	1492-SP1B100	10A SINGLE POLE CIRCUIT BREAKER	SCHNEIDER	MG24116	COURBURE B C60N 1 POLE 10 A	https://www.schneider-electric.us/en/product/MG24116/mult
PHOENIX CONTACT	UTB 2,5 - 3044636	2-TIER FEED THROUGH TERMINAL BLOCK	WEIDMULLER	1041100000	WDK 2.5 ZQV PLUGGABLE JUMPER	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
PHOENIX CONTACT	UTTB 2,5 - 3044636	END COVERS FOR ITEM 24	WEIDMULLER	1059100000	AP FOR WDK 2.5,WM,BG	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
PHOENIX CONTACT	ST 2,5-PE/L/L-3036097	2-TIER FEED SPRING CAGE TERMINAL BLOCK (2	WEIDMULLER	1131750000	ZDLD 2.5-2N/PE/L/L	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
PHOENIX CONTACT	D-ST 2,5-3L-3L-3036660	END COVERS FOR ITEM 26	WEIDMULLER	1782340000	ZAP/TW ZDLD 2.5-2N	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
PHOENIX CONTACT	UT 4-L/HESI-3214325	FUSED MODULAR TERMINAL BLOCK WITH FEED	WEIDMULLER	1833600000	WDK 2.5/TR-DU/O TNHE	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
			WEIDMULLER	7921570000	SIHA3/G20,LED,10-36VAC/DC	http://catalog.weidmueller.com/catalog/Start.do?localeId=en&
			WEIDMULLER	1839850000	WAP WDK 2.5N/TR-DU	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
PHOENIX CONTACT	FBS 10-6 - 3030365	PLUG IN BRIDGE	WEIDMULLER	1693880000	ZQV 2.5N/10 GE (YELLOW)	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
			WEIDMULLER	1608940000	ZQV 2.5/10	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
			WEIDMULLER	1054460000	WQV 2.5/10 FOR WDU 2.5,10 PO	http://catalog.weidmueller.com/procat/Product.jsp;jsessionid=
PHOENIX CONTACT	FBS 20-6 - 3030365	PLUG IN BRIDGE	WEIDMULLER	1909000000	ZQV 2.5N/20 YELLOW	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
			WEIDMULLER	1908960000	ZQV 2.5/20 YL	http://catalog.weidmueller.com/procat/Product.jsp;jsessionid=
			WEIDMULLER	1577570000	WQV 2.5/20 FOR WDU 2.5,20 PO	http://catalog.weidmueller.com/procat/Product.jsp;jsessionid=
PHOENIX CONTACT	UM8-0830943	TERMINAL BLOCK MARKERS	WEIDMULLER	1609801044	DEK 5/5 MC-10 NEUT. WS (WHITE)	http://catalog.weidmueller.com/catalog/Start.do?localeId=en
T&B	ADR21	GROUND LUG #2/0	BURNDY	K2A26U	RACCORD ALUM/CUI 14-2/0AWG 1/4	https://ecat.burndy.com/Comergent/en/US/adirect/burndy?cm
PANDUIT	G3X4LG6	WIRE DUCT 3"X4	LEGRAND	636118	TRANSCAB CABLE DUCTING BASE+COVER W	https://www.legrand.com/ecat_export/636118-cable-ducting-b
PANDUIT	C3LG6	3" WIRE DUCT COVER	LEGRAND	636118	TRANSCAB CABLE DUCTING BASE+COVER W	https://www.legrand.com/ecat_export/636118-cable-ducting-b

City of Iqaluit

WWTP Upgrade

Process automation (Division 47)

CPL-900
R0: For approval before assembling

Dessiné Par / Drawn By: O. Chalifoux-Lauzon Préparé Par / Prepared By: O. Chalifoux-Lauzon Dernière maj / Last update: 18 juin 2018	Projet / Project: WWTP Upgrade ---- Dessin De / Drawing Of: Cover Page Page / de: 01 / 21	Client / Customer: City of Iqaluit ---- Projet / Project: Pxxxxxx / xxxxxx Dessin N° / Drawing N°: CPL900.DWG	Entreprises L.M. inc. 3006 Ste-Catherine est, Montréal, Québec, H1W 2B8 Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526

A															
B															
C															
D															
E															
F															
G															
H															
I															

Dessiné Par / Drawn By:
O. Chalifoux-Lauzon

Préparé Par / Prepared By:
O. Chalifoux-Lauzon

Dernière maj / Last update:
18 juin 2018

Projet / Project:
WWTP Upgrade

Dessin De / Drawing Of:
Bill of materials


Page / de:
02 / 21

Client / Customer:
City of Iqaluit

Projet / Project:
Pxxxxxx / xxxxxx


Dessin N° / Drawing N°:
CPL900.DWG


Entreprises L.M. inc
3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
	Dessin De / Drawing Of: Mechanical drawing	Page / de: 03 / 21	Projet / Project: Pxxxxxx / xxxxxx
Dernière maj / Last update: 18 juin 2018			Dessin N° / Drawing N°: CPL900.DWG

3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526








UPS ALARM STATUS WIRING DIAGRAM

NAMEPLATE SCHEDULE

ITEM	TEXT DESCRIPTION	COLOUR	SIZE (WxH)	QTY
A	IQALUIT/INSTRUMENTATION/CONTROL PANEL/ CPL-900	BLK/WHT Letters	150X115	1
B	LAPTOP ONLY	BLK/WHT Letters	100X25	1
C	UPS	BLK/WHT Letters	75X25	1
D	WARNING/VOLTAGES FROM MORE/THAN ONE SOURCE	RED/WHT Letters	175X75	1
E	LEVEL BULBS	BLK/WHT Letters	100X25	1
F	BEACON RELAYS	BLK/WHT Letters	100X25	1

Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade ----	Client / Customer: City of Iqaluit ----	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon		Projet / Project: Pxxxxxx / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: Mechanical layout	Page / de: 04 / 21	Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



Légende:
Indentification pour les borniers triples étages (ou relais slim)


XXX / XXX — Étage inférieure de la borne
XXX — Étage supérieur de la borne

Légende:
Indentification pour les borniers triples étages (ou relais slim)


XXX / XXX / XXX — Étage inférieure de la borne
XXX / XXX — Étage centrale de la borne
XXX — Étage supérieur de la borne

Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	Projet / Project: Pxxxxxx / xxxxxx	Entreprises L.M. inc.
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: Terminals (1/2)	Page / de: 05 / 21	Dessin N° / Drawing N°: CPL900.DWG


3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



G TS06 RELAY OUTPUT
PC-102 | PC-107 NO SCALE



H TS07-TS09 ANALOG INPUT
PC-102 | PC-107 NO SCALE



I TS10-TS11 ANALOG OUTPUT
PC-102 | PC-107 NO SCALE

Légende:
Indentification pour les borniers triples étages (ou relais slim)


XXX / XXX — Étage inférieure de la borne
XXX / XXX — Étage supérieur de la borne

Légende:
Indentification pour les borniers triples étages (ou relais slim)

XXX / XXX / XXX — Étage inférieure de la borne
XXX / XXX / XXX — Étage centrale de la borne
XXX / XXX / XXX — Étage supérieur de la borne


Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: Terminals (2/2)	Page / de: 05 / 21	Projet / Project: Pxxxxxx / xxxxxx
			Dessin N° / Drawing N°: CPL900.DWG

3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
	Dessin De / Drawing Of: Controls (1/2)	Page / de: 07 / 21	Projet / Project: Pxxxxxx / xxxxxx
Dernière maj / Last update: 18 juin 2018			Dessin N° / Drawing N°: CPL900.DWG

3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	Projet / Project: Pxxxxxx / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: Controls (2/2) — Page / de: 08 / 21	Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: Communication	Page / de: 09 / 21	Projet / Project: Pxxxxxx / xxxxxx Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526


DESCRIPTION	PLC TAG
WET WELL LEVEL INDICATION FAULT STATUS	XA-01-100
WET WELL LEVEL LOW LOW ALARM	LALL-01-111
WET WELL LEVEL LOW ALARM	LAL-01-112
WET WELL LEVEL HIGH ALARM	LAH-01-113
WET WELL LEVEL HIGH HIGH ALARM	LAHH-01-114
WET WELL P-01-110 RUN STATUS	YI-01-110
WET WELL P-01-110 FAULT STATUS	XA-01-110
WET WELL P-01-110 AUTO STATUS	HI-01-110
WET WELL P-01-110 MOTOR FAULT	UA-01-110
WET WELL P-01-110 ESD TRIGGERED	HA-01-110
WET WELL OUTLET FLOW TOTALIZATION PULSE	FQI-01-150
CPL-900 UPS FAULT STATUS	XA-01-960
CPL-900 UPS BATTERY LOW	EAL-01-960
CPL-900 UPS ON BYPASS	ES-01-960A
CPL-900 UPS ON UTILITY	ES-01-960B
CPL-900 UPS BYPASS SWITCH IN BYPASS MODE	ES-01-962




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: IO	Page / de: 10 / 21	Projet / Project: Pxxxxxx / xxxxxx
			Dessin N° / Drawing N°: CPL900.DWG

3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526


DESCRIPTION	PLC TAG
PUMP P-01-120 RUN STATUS	YI-01-120
PUMP P-01-120 FAULT STATUS	XA-01-120
PUMP P-01-120 AUTO STATUS	HI-01-120
PUMP P-01-120 MOTOR FAULT STATUS	UA-01-120
PUMP P-01-120 ESD TRIGGERED	HA-01-120
SCREEN SCRN-01-210 RUN STATUS	YI-01-210
SCREEN SCRN-01-210 FAULT STATUS	XA-01-210
SCREEN SCRN-01-210 LEVEL HIGH ALARM	LAH-01-210
SCREEN SCRN-01-210 POWER LOSS/ESD TRIGGERED	HA-01-210
DISPOSAL TRAILER MOTOR VALVE OEPN STATUS	ZSO-01-112
DISPOSAL TRAILER MOTOR VALVE CLOSED STATUS	ZSC-01-112
PF-01-310 INCOMING KNIFE VALVE OPEN STATUS	ZSO-01-111
PF-01-310 INCOMING KNIFE VALVE CLOSED STATUS	ZSC-01-111
PF-01-310 RUN STATUS	YI-01-310
PF-01-310 FAULT STATUS	XA-01-310
PRIMARY EFFLUENT KNIFE VALVE OPEN STATUS	ZSO-01-121




Dessiné Par / Drawn By: O. Chalifoux-Lauzon Préparé Par / Prepared By: O. Chalifoux-Lauzon Dernière maj / Last update: 18 juin 2018	Projet / Project: WWTP Upgrade ---- Dessin De / Drawing Of: IO Page / de: 11 / 21	Client / Customer: City of Iqaluit ---- Projet / Project: Pxxxxxx / xxxxxx Dessin N° / Drawing N°: CPL900.DWG	Entreprises L.M. inc 3006 Ste-Catherine est, Montréal, Québec, H1W 2B8 Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526


See previous page
(Input supply)
See previous page
(GND)
PRIMARY EFFLUENT KNIFE VALVE CLOSED STATUS
ZSC-01-121
HEADWORKS LOWER GAS DETECTION 1 FAULT STATUS
XA-01-901
HEADWORKS LOWER GAS DETECTION 2 FAULT STATUS
XA-01-902
HEADWORKS UPPER GAS DETECTION 1 FAULT STATUS
XA-01-903
HEADWORKS UPPER GAS DETECTION 2 FAULT STATUS
XA-01-904
SPARE
SPARE
SPARE


DESCRIPTION	PLC TAG
PUMP P-01-130 RUN STATUS	YI-01-130
PUMP P-01-130 FAULT STATUS	XA-01-130
PUMP P-01-130 AUTO STATUS	HI-01-130
PUMP P-01-130 MOTOR FAULT STATUS	UA-01-130
PUMP P-01-130 ESD TRIGGERED	HA-01-130
SCREEN SCRN-01-220 RUN STATUS	YI-01-220
SCREEN SCRN-01-220 FAULT STATUS	XA-01-220
SCREEN SCRN-01-220 LEVEL HIGH ALARM	LAH-01-220
SCREEN SCRN-01-220 POWER LOSS/ESD TRIGGERED	HA-01-220
PF-01-320 INCOMING KNIFE VALVE OPEN STATUS	ZSO-01-320
PF-01-320 INCOMING KNIFE VALVE CLOSED STATUS	ZSC-01-320
PF-01-320 RUN STATUS	YI-01-320
PF-01-320 FAULT STATUS	XA-01-320
PLC-901 DC POWER SUPPLY #1 DC VOLTAGE FAULT	XA-02-970
PLC-901 DC POWER SUPPLY #2 DC VOLTAGE FAULT	XA-02-971
PLC-901 SPD SURGE INDICATION	XA-02-900




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: IO	Page / de: 13 / 21	Projet / Project: Pxxxxxx / xxxxxx
		Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	Projet / Project: Pxxxxxx / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: IO	Page / de: 14 / 21	Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	Projet / Project: Pxxxxxx / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: IO	Page / de: 15 / 21	Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
	Dessin De / Drawing Of: IO	Page / de: 16 / 21	Projet / Project: Pxxxxxx / xxxxxx
Dernière maj / Last update: 18 juin 2018			Dessin N° / Drawing N°: CPL900.DWG


3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade ----	Client / Customer: City of Iqaluit ----	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon		Projet / Project: Pxxxxxx / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: IO	Page / de: 17 / 21	Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	Projet / Project: Pxxxxxx / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: IO	Page / de: 18 / 21	Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: IO	Page / de: 19 / 21	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526
		Projet / Project: Pxxxxxx / xxxxxx	
		Dessin N° / Drawing N°: CPL900.DWG	



Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	Projet / Project: Pxxxxxx / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: IO	Page / de: 20 / 21	Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	Projet / Project: Pxxxxxx / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: IO	Page / de: 21 / 21	Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



Légende:

Couleur des plaques signalétiques: Blanc
Texte gravé: Noir
Hauteur du texte: 1/4"


Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 18 juin 2018	Dessin De / Drawing Of: Étiquettes	Page / de: 27 / 21	Projet / Project: Pxxxxxx / xxxxxx
		Dessin N° / Drawing N°: CPL900.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526

Enclosure lights - Series 880 LED

The 880 LED are designed to illuminate the interiors of small to large enclosures with the very low power consumption that the LED lights provide. The light bars are motion activated using the built-in motion sensor that eliminates the need for a door switch. The time the LED lights stay on, without movement, is adjustable at 3, 5 or 10 minutes. The light bars are made from extruded aluminum and feature an integrated 120/240 Volts, 11.5 Amps USA/Canada standard receptacle, so that electrical devices (e.g. power tools) can be easily plugged in when needed. A 5 foot cord with an USA/Canada 120/240 Volts plug is provided. The LED bars come complete with a set of 2 mounting brackets (880 LEDB) that are easily clipped along the length of the LED bar and can be fixed to the enclosure with the included M5 screws or optional right angle mounting bracket.



CATALOG NUMBER	A	QTY LEDS	WATTS	SHIP WGHT LBS.
880 LED12	12”	24	3	8
880 LED18	18”	36	3	9
880 LED24	24”	48	6	10
880 LED36	36”	64	6	12



LED bar mounting bracket

The 880 LEDB mounting brackets are used for holding the 880 LED light in the enclosure. The light has grooves along the sides to receive the clipping brackets. The brackets can be fixed to the enclosure with the included M5 screws. (Sold in pairs)



CATALOG NUMBER	PIECES	SHIP WGHT LBS.
880 LEDB	2	1

Right angle mounting bracket

The 880 LEDRB are designed to fasten the 880 LED by its mounting brackets to any type of enclosures.
Sold in pairs and supplied with installation hardware.



CATALOG NUMBER	PIECES	SHIP WGHT LBS.
880 LEDRB	2	1

Data subject to change without notice.


Remote door switch - Series FLRDS

The FLRDS series remote door switch can be applied in the ES family (881 FLRDS), in the Mtrx family (886 FLRDS), in the 5412 DDS cabinet and the 9000 series cabinets (889 FLRDS). It is a cost effective solution to power on/off the light within an enclosure. The bracket is designed to operate on all Mtrx doors and side door, with or without stiffeners. Consists of switch, steel bracket and hardware.




For use with 'ES' series enclosures:

CATALOG NUMBER	SHIP WGHT LBS.
881 FLRDS	1



For use with Mtrx modular cabinets:

CATALOG NUMBER	SHIP WGHT LBS.
886 FLRDS	1



For use with 'DDS' double door cabinets and 9000 series cabinets:

CATALOG NUMBER	SHIP WGHT LBS.
889 FLRDS	1

Remote door switch - Series RDS

The 886 RDS remote door switch is a robust solution to power on/off a light within an enclosure. The switch is designed to operate on all Mtrx doors and side doors, with or without stiffeners. Consists of switch, mounting bracket and hardware.



For use with Mtrx modular cabinets:

CATALOG NUMBER	SHIP WGHT LBS.
886 RDS	1

Data subject to change without notice.

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Jun 27, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

TDS AND SHOP DRAWINGS

DA-IC-04-Level switch

Date : 2018-06-27

INFORMATION	
Project : **WASTEWATER PLANT - IQALUIT**	
Client : Kudlik Construction Ltd. To Sandra Rousseau P.Eng./ Project Manager	Project number : **2018-062**
Contractor : Norclair inc.	Project number Norclair : **P1039**
Address : 1100, Montee Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Steven Wieland	E-mail: swieland@norclair.ca
Phone: 450-688-4012 # 708	Cell.: 514-608-0619

Information, subcontractor or supplier	
Sub supplier : Xylem	
Contact : Hugo Chartier	Phone : 450-688-4012 ext. 706

Information on the equipment or the proposed materials	
Speciality : Instruments and controls	
Equipment : Level switch	
Drawing reference :	
Specification reference : 40 05 23	Division :
Article :	Number Page : 2

CONSULTANT APPROVAL

No comments.

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-04 R0 (2018-06-27)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- ☐ Architectural
- ☐ Structural
- ☐ Mechanical
- ☑ Electrical
- ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- ☑ REVIEWED
- ☐ REVIEWED, AS NOTED
- ☐ REVISE AND RESUBMIT
- ☐ NOT REVIEWED


DATE 2018-JUN-27

BY David Hutchison, P.Eng.

1100, Montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

xylem	Station Equipment ENM-10 Level Regulator P/N 582 88 XX	DOCUMENT NO. ES 6.1.1 SUPERSEDES: 11/2010 — ISSUED: 02/2013



DESCRIPTION:

THE ENM–10 CONTAINS A MECHANICAL SWITCH IN A SEALED PLASTIC CASING. IT IS USED TO ACTIVATE ELECTRICAL DEVICES, SUCH AS PUMPS AND ALARMS, BASED ON THE LEVEL OF A LIQUID.

OPERATION:

THE ENM–10 LEVEL SENSOR IS SUSPENDED FROM ITS OWN CABLE. WHEN LIQUID REACHES THE SENSOR IT TILTS AND AN ECCENTRIC WEIGHT ACTIVATES A MECHANICAL SWITCH. THE ENM–10 DOES NOT FLOAT, BUT REMAINS SUSPENDED IN THE LIQUID.

MATERIALS:

BODY: POLYPROPYLENE (GREY)
STRAIN RELIEF: EPDM RUBBER
CABLE: SEE TABLE
WEIGHT: ZINC

Project: Iqaluit WWTP Upgrade
Our Ref: 18-25-0213

OPERATING PARAMETERS:


AMBIENT TEMPERATURE RANGES: 0° TO 60°C.

ELECTRICAL: CONDUCTORS: QTY. 3, 0.75mm DIA. (#19AWG)
INTERRUPTING CAPACITY OF MICRO SWITCH: AC RESISTIVE LOAD, 250V, 10A.
AC INDUCTIVE LOAD, 250V, 3A.(COSø=0.5)
DC 30V,5A


* WITH GOLD PLATED MICRO SWITCH: SAME AS ABOVE EXCEPT DC 24V 10mA


CSA APPROVED: LR 24026–6






SENSOR POSITION





SWITCH POSITION



- 4x for lift station
- 2x for building sump

SELECTION CHART

SPECIFIC GRAVITY	CABLE LENGTH meter	BODY LENGTH (L) mm	(M) MINIMUM FOR GOOD OPERATION	P/N N.B.R./P.V.C. GREY CABLE	P/N P.V.C. GREY CABLE	P/N P.V.C. RED CABLE	WEIGHT kg.	
0.65 – 0.80	20	194	250	582 88 09	582 88 18	N/A	2.0	
0.80 – 0.95	20	177	240	582 88 10	582 88 19	N/A	2.0	
0.95 – 1.10	6	163	225	582 88 11	582 88 20	582 88 55	1.2	
0.95 – 1.10	13	162	225	582 88 12	582 88 21	582 88 56	1.6	
0.95 – 1.10	20	162	225	582 88 13	582 88 22	582 88 57	2.0	*
0.95 – 1.10	30	162	225	582 88 36	582 88 82	N/A	3.0	
0.95 – 1.10	50	162	225	582 88 37	582 88 83	N/A	4.0	
0.95 – 1.10	100	162	225	582 88 38	N/A	N/A	7.0	
0.95 – 1.10	150	162	225	582 88 39	N/A	N/A	10.0	
1.05 – 1.20	20	142	205	582 88 14	582 88 23	N/A	2.0	
1.20 – 1.30	20	133	200	582 88 15	582 88 24	N/A	2.0	
1.30 – 1.40	20	130	195	582 88 16	582 88 25	N/A	2.0	
1.40 – 1.50	20	126	195	582 88 17	582 88 26	N/A	2.0	

* 594 79 20 WITH GOLD PLATED CONTACT IS DESIGN FOR LOW CURRENT, SLOW MOVEMENTS AND OIL.

N/A= NON AVALABLE

DIMENSIONS ARE IN mm

Qty: (6) Level Regulator c/w 30M of cable

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Jul 18, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

TDS AND SHOP DRAWINGS

DA-IC-05R2 – (Color Printer) **Date :** 2018-07-18

INFORMATION	
Project : **WASTEWATER PLANT - IQALUIT**	
Client : Kudlik Construction Ltd. To Sandra Rousseau P.Eng./ Project Manager	Project number : **2018-062**
Contractor : Norclair inc.	Project number Norclair : **P1039**
Address : 1100, Montee Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Dominic Papineau	E-mail: dpapineau@norclair.ca
Phone: 450-688-4012 # 720	Cell.: 514-409-1832

Information, subcontractor or supplier	
Sub supplier : Entreprises L.M.	
Contact : Marion Fleury	Phone : (514) 521-0882

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : **Color** Printer	
Drawing reference :	
Specification reference : **47 10 02** (Page 02 / XX)	Division :
Article :	Number of pages: 9

CONSULTANT APPROVAL

Provide spare toner cartridge in addition to included toner
Provide all necessary cables for connecting PCs via WWTP network

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-05R2 (2018-07-18)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Electrical
☐ Structural ☐ Other
☐ Mechanical

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED

☑ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-JUL-20

BY David Hutchison, P.Eng.

1100, Montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Xerox® WorkCentre® 6515 Color Multifunction Printer



System Specifications	WorkCentre 6515N	WorkCentre 6515DN	WorkCentre 6515DNI
One-sided Speed 8.5 x 11 in. 8.5 x 14 in. / 216 x 356 mm A4 / 210 x 297 mm	Up to 30 ppm Color and Black and White Up to 24 ppm Color and Black and White Up to 28 ppm Color and Black and White		
Two-sided Speed 8.5 x 11 in. 8.5 x 14 in. / 216 x 356 mm A4 / 210 x 297 mm	NA	Up to 18 ppm Color and Black and White Up to 17 ppm Color and Black and White Up to 19 ppm Color and Black and White	
Monthly Duty Cycle[1]	Up to 50,000 pages / month		
Recommended Average Monthly Print Volume[2]	Up to 3,000 pages		
Processor	1.05 GHz		
Memory	2 GB		
Connectivity	10/100/1000Base-T Ethernet High-Speed USB 3.0		10/100/1000Base-T Ethernet High-Speed USB 3.0 Wi-Fi 802.11n Wi-Fi Direct®
Paper Handling			
Document Feeder			
Capacity[3]	Single-pass Duplex Automatic Document Feeder (DADF): 50 sheets		
Sizes	Custom Sizes: 5.5 x 5.5 in. to 8.5 x 14 in. / 139.7 x 139.7 mm to 216 x 356 mm		
Weights	16 lb. bond to 45 lb. cover / 60 to 125 gsm		
Bypass Tray			
Capacity[3]	50 sheets		
Sizes	Custom Sizes: 3 x 5 in. to 8.5 x 14 in. / 76 x 127 mm to 216 x 356 mm		
Weights	16 lb. bond to 58 lb. cover / 60 to 220 gsm		

Media Types	Bond Plain Card Stock Custom Envelopes Glossy Card Stock Hole punched Labels Letterhead Lightweight Cardstock Lightweight Glossy Card Stock Preprinted Recycled	
Tray 1		
Capacity[3]	250 sheets	
Sizes	Custom Sizes 3 x 5.8 in. to 8.5 x 14 in. / 76 x 147 mm to 216 x 356 mm	
Weights	16 lb. bond to 65 lb. cover / 60 to 176 gsm	
Media Types	Bond Plain Card Stock Custom Envelopes Glossy Card Stock Hole punched Labels Letterhead Lightweight Cardstock Lightweight Glossy Card Stock Preprinted Recycled	
Optional Tray 2		
Capacity[3]	550 sheets	
Sizes	Custom Sizes: 3 x 7.5 in. to 8.5 x 14 in. / 76 x 191 mm to 216 x 356 mm	
Weights	16 lb. bond to 65 lb. cover / 60 to 176 gsm	
Media Types	Bond Plain Card Stock Custom Glossy Card Stock Hole punched Letterhead Lightweight Cardstock Lightweight Glossy Card Stock Preprinted Recycled	
Total Capacity		
Device Standard Capacity[3]	300 sheets	
Device Total Capacity[3]	850 sheets	
Paper Output		
Output Capacity[3]	150 sheets	
Automatic 2-Sided	NA	Standard

Xerox® WorkCentre® 6515 Color Multifunction Printer

Device Specifications	
Electrical Requirements	
North America	Voltage: 120 VAC +/- 10 % Frequency: 60 Hz +/- 3 Hz, 12A
Europe	Voltage: 220-240 VAC +/- 10 % Frequency: 50 Hz +/- 3 Hz, 6A
Power Consumption	
Operation[4]	120V: Maximum 350 watts 220V: Maximum 370 watts
Standby Mode[4]	120V: Maximum 51 watts 220V: Maximum 52 watts
Power Off Mode[4]	120V: Maximum 0.2 watts 220V: Maximum 0.3 watts
Sleep Mode[4]	120V: Maximum 1.1 watts 220V: Maximum 1.2 watts
Warm-up (from Sleep Mode)	As fast as 27 seconds
Operating Environment	
Required Temperature Range Storage Operating	 -4˚F to 104˚F / -20˚C to 40˚C 41˚F to 90˚F / 5˚C to 32˚C
Required Relative Humidity	15 % to 85 %
Sound Power Levels Operating Standby	 6.84 B or less 4.25 B or less
Sound Pressure Levels Operating Standby	 52.5 dB(A) or less 26.3 dB(A) or less
Dimensions and Weights (unpackaged)	
Workcentre 6515N, DN, and DNI	Width: 16.5 in. / 420 mm Depth: 19.9 in. / 506 mm Height: 19.7 in. / 500 mm Weight: 67.7 lb. / 30.7 kg
550-sheet Paper Tray	Width: 16.5 in. / 420 mm Depth: 18.3 in. / 465 mm Height: 5.9 in. / 150 mm Weight: 14.8 lb. / 6.7 kg
Dimensions and Weights (packaged)	
Phaser 6510N, DN and DNI	Width: 25 in. / 634 mm Depth: 22.8 in. / 580 mm Height: 26 in. / 659 mm Weight: 79.8 lb. / 36.2 kg
550-sheet Paper Tray	Width: 21.1 in. / 535 mm Depth: 23 in. / 584 mm Height: 9.8 in. / 248 mm Weight: 18.7 lb. / 8.5 kg

Xerox® WorkCentre® 6515 Color Multifunction Printer

System Certification/Regulatory Compliance	
Certifications	c TUV us FCC 47CFR15-B ICES/NMB-3 “A” CE NOM EAC UkrSepro BIS GS FCC 47CFR68 ISED DC-01 Citrix™ Certified Cerner Apple® AirPrint® certification Google Cloud Print™ Certification Mopria® certified Wi-Fi Alliance Certified Blue Angel MEDITECH ECOLOGO® EPEAT (United States) ENERGY STAR® To view the latest list of certifications, go to www.xerox.com/OfficeCertifications.
Copy	
Document Scanner	Single-pass Duplex Automatic Document Feeder (DADF) with 50-sheet capacity
Document Scanner Size	Platen: Up to 8.5 x 11.7 in / A4 DADF: 8.5 x 14 in. / 216 x 356 mm
Simplex Speed	Black and White: Up to 21 cpm (copies per minute) 8.5 x 11 in. / A4 / 210 x 297 mm Color: Up to 13 cpm (copies per minute) 8.5 x 11 in. / A4 / 210 x 297 mm
Duplex Speed	Black and White: Up to 9 cpm (copies per minute) 8.5 x 11 in. / A4 / 210 x 297 mm Color: Up to 8 cpm (copies per minute) 8.5 x 11 in. / A4 / 210 x 297 mm
First-Copy-Out Time	As fast as 12 seconds from the Platen
Sides (input:output)	1:1, 1:2, 2:2, and 2:1
Quantity	1 to 999
Resolution	Up to 600 x 600 dpi
Reduction/Enlargement	Variable zoom from 25 % to 400 % in 1 % increments
Concurrency	Concurrent scanning and printing
Copy Features	Automatic Background Suppression Book Copying Book Copying with Center Erase Collation Darkness Control Edge Erase ID Card Copy N-up Reduce/Enlarge (25 %-400 %) Image Shift Original Type Sample Copy Sharpness
Print	
First-print-out Time	As fast as 12 seconds Color and Black and White
Print Resolution	Up to 1200 x 2400 dpi

Xerox® WorkCentre® 6515 Color Multifunction Printer

Page Description Languages	Adobe® PostScript® 3™ PCL® 5e, 6 PDF TIFF
Maximum Print Area	4 mm edge of paper
Print Features	Banner Sheets Booklet Print Cover / Separators Draft Mode Fit to Page N-up Overlays PANTONE® Color Calibrated Solid-color Simulations Personal Print Proof Print RAM Collation Run Black Saved Print Secure Print Watermarks
Print from USB	Allows walk-up printing from Type A USB port Supports direct printing from computer via Type B USB port Supported file formats: PDF, JPEG, TIFF, XPS
Operating Systems	Windows®, 7, 8, 10, Server 2000, Server 2003, Server 2008, Server 2008 R2, Server 2012 Mac OS® version 10.10 and higher Citrix® Redhat® Enterprise Linux® IBM® AIX® 5 HP-UX® 11iv2 Oracle® Solaris 9, 10 Fedora Core 12-15 SUSE®
Network Protocols	TCP/IP: HTTP/HTTPS, IPP, LPR/LDP, Raw Socket Printing/Port 9100, IPv4/IPv6, WSD SMB SMTP, Secure SMTP LDAP, Secure LDAP Bonjour® / AirPrint® FTP Most protocols not in use can be disabled
Administrative Protocols	DHCP, SNMP v2/3, WINS, DHCP Autonet, TLS, SNTP, MDNS
Font Capability	136 PostScript fonts 88 PCL fonts
Mobile Solutions and Mobile Device Apps	
Xerox® Mobile Express Driver®	Makes it easy for mobile users to find, use and manage Xerox® and non-Xerox® devices in every new location. Plug into a new network, and Mobile Express Driver automatically discovers available printers and provides status and capability information. Save a list of “favorite” printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to IT.
Xerox® Global Print Driver®	A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for end-users, reducing the number of support calls, and simplifying print services management.
Apple® AirPrint®	Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network.
Google Cloud Print™	Google Cloud Print connects print devices to the web, enabling users to print the applications they use every day from smartphones, tablets, Chromebook™ notebook computers and any other web-connected device.

Xerox® WorkCentre® 6515 Color Multifunction Printer

Xerox® Print Service Plug-in for Android™ (Free at Google Play™ Store)	The Xerox® Print Service Plug-in for Android KitKat (4.4 or greater) devices streamlines mobile printing without third-party apps or additional print drivers. You can easily print photos, Web pages and documents when your mobile device is connected to printers or multifunction printers using a wireless network. A robust print option set includes two-sided printing, stapling and secure code release. A free download is available from the Google Play™ store.
Xerox® Mobile Link App (Free at Google Play™ Store and Apple® App Store)	The Xerox® Mobile Link App allows you to scan, email and fax from your phone or tablet by connecting with our multifunction printers and send data to and print data from cloud storage. It is easy to create Mobile Link One-Touch Workflows between a mobile device and a multifunction printer. Using a manual address or QR code identification for pairing, automatic device discovery makes it easy to find and pair a mobile device with a nearby Xerox® multifunction printer.
Xerox® Wireless Print Solutions Adapter (Optional)	The Xerox® Wireless Print Solutions Adapter seamlessly connects your Xerox® printer or MFP to modern mobile and desktop workflows, regardless of your office environment. For more information, visit **www.xerox.com/WPSA**
Xerox® Print Management and Mobility Suite, Xerox® Print Management and Mobility Service	Xerox® Print Management and Mobility Suite is a modular set of workflows designed to save customers time and money by providing effective control over their print fleet, while enabling worker productivity and mobility through a set of robust workflows. Xerox enables ultimate customer flexibility by offering these capabilities in both an on-premises server version and with a cloud based-version of this solution.
Scan	
Capability	Color and Black-and-white
Concurrency	Scan while the system is printing copy or network print jobs, or while it is transferring scan to network or fax jobs
Input Speed - Black and White	Scan up to 37 ipm – 8.5 x 11 in. / A4 / 210 x 297 mm
Input Speed - Color	Scan up to 21 ipm – 8.5 x 11 in. / A4 / 210 x 297 mm
Resolution	Optical – 600 x 600 dpi
Bit Depth	24-bit Color / 8-bit Grayscale
Maximum Scan Area	Platen: Up to 8.5 x 11.7 in. / A4 Document Feeder: Up to 8.5 x 14 in. / 216 x 356 mm
Network Filing Protocol	FTP SMTP SMB/SMB2
File Formats	JPG Single-page and Multi-page TIFF PDF Searchable PDF with integrated OCR
Scan Driver Compatibility	WIA TWAIN
Supported Scan Destinations	Scan to Email (local address book or LDAP integration) Scan to Network (via FTP/SMB) Scan to USB Memory Device Scan to Email (SMTP) Scan to WSD Scan to Application (TWAIN Network) Scan to WIA (WSD Scan) Scan to Mac 10.9 or later (Network/Mac ICA) Scan to Network Computer (SMB/FTP) Scan to Multiple Destinations in a Single Scan Job

Xerox® WorkCentre® 6515 Color Multifunction Printer

Security	
Security Features	Simultaneous HTTP and HTTPS support IPsec 802.1x Authentication S/MIME IP Filtering Secure Print Secure Fax Receive SNMP v3 LDAP (SASL) Network Authentication Kerberos Authentication (Unix / Linux / Windows ADS)
Fax[5]	
Fax Speed	33.6 Kbps
Memory	4 MB
Resolution	Up to 400 x 400 dpi
Compression	MH/MR/MMR/JBIG
Fax Features	Broadcast Sending (up to 200 destinations) Delayed Start (up to 24 hours) Fax Address Book (up to 200 speed dials) Fax Forward to Email Fax Forwarding and Local Print Polling Receive Reject Junk Fax Secure Fax Receive
Device Management	
Xerox® CentreWare® Web	
	• A Web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system • Works with any SNMP-managed printer from any manufacturer • Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management
Xerox® Embedded Web Server - Integrated Device Web Page	
Device Status	• Tray status/contents • Consumables status • Billing/Usage • Quick Links
Job Submission	Print-ready files (PS, PCL®, PDF, XPS, JPEG)
Device Administration	Allows simple, remote installation setting of configuration options and management of the device.
Browsers	Microsoft® Internet Explorer 11 Microsoft Edge™ 38 Mozilla™ Firefox® 48 Apple® Safari® 9.1 Google Chrome™ 52
Remote Print Services	
Xerox® MeterAssistant® Service	Automates the process of collecting and submitting meter reads for tracking and billing of Xerox® device usage. Eliminates the need for time-consuming end-user involvement and ensures that meter reads are submitted to Xerox on time.
Xerox® SuppliesAssistant® Service	Automatically orders supplies for Xerox® output devices based on actual usage, eliminating the need to manually manage supplies inventory.
Maintenance Assistant	Offers a fast (and free) way to resolve potential issues and receive assistance and automate the troubleshooting/repair process. Diagnostic data is sent to Xerox, allowing for problems to be solved faster with increased uptime.

Xerox® WorkCentre® 6515 Color Multifunction Printer

What's In The Box	
	• WorkCentre 6515 Color Multifunction Printer • Standard Capacity Print cartridge: One of each (Cyan, Magenta, Yellow: 1,000 print capacity[6]; Black: 1,500 print capacity[6] • Software and Documentation CD (with User Manual, Quick Install Guide, Safety, Regulatory, Recycling and Disposal Guides, Print Drivers, and Warranty Statement) • Installation Guide • Quick Use Guides • Power cord • Fax cord

Supplies and Accessories	Quantity	Part Number
Supplies		
Extra-High Capacity Print Cartridges	Cyan: 4,300 standard pages[6] Magenta: 4,300 standard pages[6] Yellow: 4,300 standard pages[6]	106R03690 106R03691 106R03692
High Capacity Print Cartridges	Black 5,500 standard pages[6] Cyan: 2,400 standard pages[6] Magenta: 2,400 standard pages[6] Yellow: 2,400 standard pages[6]	106R03480 106R03477 106R03478 106R03479
Standard Capacity Print Cartridges	Black: 2,500 standard pages[6] Cyan: 1,000 standard pages[6] Magenta: 1,000 standard pages[6] Yellow: 1,000 standard pages[6]	106R03476 106R03473 106R03474 106R03475
Drum Cartridges	Black: 48,000 pages[7] Cyan: 48,000 pages[7] Magenta: 48,000 pages[7] Yellow: 48,000 pages[7]	108R01420 108R01417 108R01418 108R01419
Waste Cartridge	30,000 pages[7]	108R01416
Accessories		
550-sheet Paper Tray		097S04765
Wireless Network Adapter		497K16750

[1] Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.
[2] Expected regular monthly throughput.
[3] Paper capacities are based on 20 lb. / 75 gsm stock; capacities will vary with different weight stocks.
[4] Power states defined per ENERGY STAR® Program requirements for Imaging Equipment.
[5] Requires analog phone line.
[6] Average standard pages. Declared Yield in accordance with ISO/IEC 19798. Yield will vary based on image, area coverage and print
[7] Approximate pages. Declared Yield based on letter-/A4-size 20 lb. (75 gsm) pages. Yield will vary based on media type, size, weight, orientation, and usage patterns.

Return spent imaging supplies through the Xerox Green World Alliance collection/reuse/recycling program. For more information, visit **www.xerox.com/about-xerox/recycling**.

For more information, visit us at **www.xerox.com**

©2018 Xerox Corporation. All rights reserved. Xerox®, Xerox and Design®, CentreWare®, Global Print Driver®, MeterAssistant®, Mobile Express Driver®, SuppliesAssistant® and WorkCentre® are trademarks of Xerox Corporation in the United States and/or other countries. As an ENERGY STAR® partner, Xerox Corporation has determined that this product meets the ENERGY STAR guidelines for energy efficiency (DN and DNI configurations). ENERGY STAR and the ENERGY STAR mark are registered U.S. marks. The information in this brochure is subject to change without notice. Updated 1/18 BR19949 65XSS-02UF

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Jul 05, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

TDS AND SHOP DRAWINGS

DA-IC-06-Quote Scada

Date : 2018-07-05

INFORMATION	
Project : **WASTEWATER PLANT - IQALUIT**	
Client : Kudlik Construction Ltd. To Sandra Rousseau P.Eng./ Project Manager	Project number : **2018-062**
Contractor : Norclair inc.	Project number Norclair : **P1039**
Address : 1100, Montee Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Dominic Papineau	E-mail: dpapineau@norclair.ca
Phone: 450-688-4012 # 720	Cell.: 514-409-1832

Information, subcontractor or supplier	
Sub supplier : Inductive automation	
Contact : Réf. : Entreprises LM	Phone : 1-800-266-7798

Information on the equipment or the proposed materials	
Speciality : Instruments and controls	
Equipment : Quote Scada, Custom Package and basic Care Contract – 1 year term	
Drawing reference :	
Specification reference :	Division :
Article :	Number Page : 2

CONSULTANT APPROVAL

No comments

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-05 (2018-07-05)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-JUL-09

BY David Hutchison, P.Eng.

1100, Montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

inductive automation

PO Box 2030
Folsom, CA 95763
(800) 266-7798
(916) 932-1194 (Fax)

QUOTE

Taken: May 1, 2018
Expires: May 31, 2018
Quote #1110766

Bill To:	*Ship To:*
Enterprises LM Olivier Chalifoux-Lauzon 3006 Sainte-Catherine E. Montral, QC H1W 2B8 Canada	Enterprises LM Olivier Chalifoux-Lauzon 3006 Sainte-Catherine E. Montral, QC H1W 2B8 Canada

Qty	*Product*	*Unit Price*	*Retail*	*Price*
1	Custom Package (Wastewater Treatment Plant Future) / 1 Client Includes Vision Limited (1 client), Tag Historian, Alarm Notification, Voice Notification and AB Driver modules			
1	Basic Care Contract - 1 Year Term Does not include phone support. Best for customers who want access to technical support reps via email, but don't require issues expedited via phone support. Includes email support and free upgrades to any modules purchased.			

Comments: Please send purchase order to:

Your Account Manager,
Vannessa Garcia
916-456-1045 x231
vannessa@inductiveautomation.com

THANK YOU!

This is a quote on the product(s) named above.
This item was quoted on May 1, 2018.
Quote expires on May 31, 2018.
Payment Terms: Net 30.

Thank you for your business!

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Jul 13, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-07 (Strobes and horns) **Date :** 2018-07-12

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Dominic Papineau, Project Manager	E-mail: dpapineau@norclair.ca
Phone : 450-688-4012 # 720	Cell. : 514-409-1832

Information, subcontractor or supplier	
Sub/supplier : Lumen	
Contact : Anthony Nadji	Phone : 514-493-4127

Information on the equipment	
Speciality : **Instruments and controls**	
Equipment : Strobes and horns	
Drawing reference : I201 to I207	
Specification reference : **47 30 02** (Page 10) and **RFI-036**	Division : Field control devices
Article : 2.14.4 & 2.14.6	Number of pages : 14

CONSULTANT APPROVAL

No comments

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-07 (2018-07-13)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-JUL-16

BY David Hutchison, P.Eng.

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Strobe lights (indooor/outdoor, non-XP)

17x



AST - 1 BASE MOUNT STROBE WARNING LIGHT

APPLICATIONS:

- to visually indicate warnings or hazards in high noise level areas where audible signals may not be heard
- to indicate the starting and stopping of operations in a manufacturing environment
- to indicate faulty equipment

FEATURES:

- solid state power supply
- low power consumption (12 watts)
- intensity 2,000,000 candlepower (peak)
- Polycarbonate fresnel lens
- cast zinc alloy housing with a grey epoxy finish for superior corrosion resistance
- designed for intermittent visual signaling as well as longer duration signaling applications
- flash rate - 60 flashes/minute
- flash tube life - minimum 10 million flashes at 60 flashes/minute
- 1/2 conduit entry
- weatherproof

9001 ISO Certified

Made in Canada

C SP US

Applied Strobe Technology Company Limited

INDUSTRIAL STROBE WARNING LIGHTS

8345 Stanley Avenue, Niagara Falls, Ontario, Canada L2G 0C8 905-374-3077, Fax 905-374-6114

e-mail: sales@appliedstrobe.com www.appliedstrobe.com

Temperature Range
-40 C to +85 C

Electrical Ratings

Supply Voltage Range	Frequency	Current Range (avg)	Inrush Current (max)
90 to 130 VAC	50/60Hz	.118 A to .090 A	.250 A
220 to 250 VAC	50/60Hz	.072 A to .055 A	.220 A
10 to 30 VDC	-	.8 A to .4 A	1.30 A
50 to 60 VDC	-	.360 A to .300 A	. 820 A
90 to 130VDC	-	.175A to .090 A	. 250 A
220 to 250VDC	-	.070A to .055 A	. 220 A

Net Weight: 4.5 lbs

Ordering Information

Model No	Input Voltage
AST-1-90-130-AC	90 - 130 VAC
AST-1-220-250-AC	220 - 250 VAC
AST-1-10-30-DC	10 - 30 VDC
AST-1-90-130-DC	90 - 130 VDC
AST-1-220-250-DC	220 - 250 VDC
AST-1-50-60-DC	50 - 60 VDC

Lens Colors

AM	- Amber Lens	5x
BL	- Blue Lens	12x
RE	- Red Lens	
GR	- Green Lens	
CL	- Clear Lens	
PU	- Purple Lens	

Ordering Example

AST-1-10-30-DC-RE

Replacement Parts

Circuit Board


AST-1 - 90-130-AC -Board	90 - 130	VAC	Circuit Board
AST-1-220-250-AC -Board	220 - 250	VAC	Circuit Board
AST-1 - 10 - 30-DC -Board	10 - 30	VDC	Circuit Board
AST-1 - 90-130-DC -Board	90 - 130	VDC	Circuit Board
AST-1-220-250-DC -Board	220 - 250	VDC	Circuit Board
AST-1 - 50 - 60-DC -Board	50 - 60	VDC	Circuit Board


Flash Tube

AST-FT 3050 Flash Tube

Lenses

AST-1-Lens-RE	Red Lens
AST-1-Lens-AM	Amber Lens
AST-1-Lens-BL	Blue Lens
AST-1-Lens-GR	Green Lens
AST-1-Lens-CL	Clear Lens
AST-1-Lens-PU	Purple Lens





BASE MOUNT STROBE

Strobe lights (indooor, XP-rated)

6x



AST - 14 PENDANT MOUNT HAZARDOUS AREA STROBE WARNING LIGHT

COMPLIANCES:

Class I - Div. 2, Groups A,B,C,D
Class II - Groups E,F,G
Class III - Enclosure 3
Temp Code: See Electrical Ratings
CSA# - LR56828-2
** Type 3 and/or 4X (where applicable)

* **New - 55°C starting and operating temperature**
Note: Performance tested to start and operate at - 55° C

LISTED
15UD

Visual Signal Appliance, Fire Alarm for Use in Hazardous Locations

15 - 30 VDC input - 4 wire Clear Lens Only
21 - 30 VDC sync input - 4 wire Clear Lens Only

APPLICATIONS:

- to visually indicate warnings or hazards in high noise level areas where audible signals may not be heard
- to indicate the starting and stopping of operations in a manufacturing environment
- to indicate faulty equipment

FEATURES:

- solid state power supply
- low power consumption (12 watts)
- intensity 2,000,000 candlepower (peak)
- Polycarbonate fresnel lens
- cast zinc alloy housing with a grey epoxy finish for superior corrosion resistance
- may be operated in any position
- designed for intermittent visual signalling as well as longer duration signalling applications
- lens sealed in guard
- flash rate - 60 flashes/minute - alternate flash rate available
- flash tube life - minimum 10 million flashes at 60 flashes/minute
- 3/4 conduit entry
- weatherproof

9001 ISO Certified

Made in Canada

C US

Applied Strobe Technology Company Limited
INDUSTRIAL STROBE WARNING LIGHTS
8345 Stanley Avenue, Niagara Falls, Ontario, Canada L2G 0C8 905-374-3077, Fax 905-374-6114
e-mail: sales@appliedstrobe.com www.appliedstrobe.com


Operating Temperature Range

-40 C to +85 C (AST-14-S)
-55 C to +85 C (AST-14-L)

Electrical Ratings

Supply Voltage Range	Frequency	Current Range (avg)	Inrush Current (max)	T Code @ 40° C	T Code @ 85° C
90 to 130 VAC	50/60Hz	.118 A to .090 A	.250 A	T3C	T3
220 to 250 VAC	50/60Hz	.072 A to .055 A	.220 A	T3A	T2C
10 to 30 VDC	-	.8 A to .4 A	1.30 A	T3A	T2C
50 to 60 VDC	-	.360 A to .300 A	. 820 A	T2D	T2B
90 to 130VDC	-	.175 A to .090 A	. 250 A	T3C	T3
220 to 250VDC	-	.070 A to .055 A	. 220 A	T3A	T2C
15 to 30 VDC		.8 A to .4 A	1.30 A	T3A	T2C
21 to 30 VDC	-	.5 A	1.30 A	T3A	T2C

Net Weight: 4.5 lbs



Ordering Information

Model No	Input Voltage
AST-14- * -90-130-AC	90 - 130 VAC
AST-14- * -220-250-AC	220 - 250 VAC
AST-14- * -10-30-DC	10 - 30 VDC
AST-14- * -90-130-DC	90 - 130 VDC
AST-14- * -220-250-DC	220 - 250 VDC
AST-14- * -50-60-DC	50 - 60 VDC
AST-14- L -15-30-DC	15 - 30 VDC
AST-14- Sync -21-30-DC	21 - 30 VDC

NOTE: * - **S** for standard temperature range and - **L** for low temperature range

Lens Colors

AM	- Amber Lens	3x
BL	- Blue Lens	3x
RE	- Red Lens	
GR	- Green Lens	
CL	- Clear Lens	
PU	- Purple Lens	

Ordering Example

AST-14-S-10-30-DC-RE

ULC Approved

AST-14-L-15-30-DC-CL-ULC
AST-14-Sync-21-30-DC-CL

Replacement Parts

Circuit Board

AST-14- * -90-130-AC -Board	90 - 130	VAC	Circuit Board
AST-14- * -220-250-AC -Board	220 - 250	VAC	Circuit Board
AST-14-* -10-30-DC -Board	10 - 30	VDC	Circuit Board
AST-14-*-90-130-DC -Board	90 - 130	VDC	Circuit Board
AST-14-*-220-250-DC -Board	220 - 250	VDC	Circuit Board
AST-14-*-50-60-DC -Board	50 - 60	VDC	Circuit Board
AST-14-L-15-30-DC -Board -ULC	15 - 30	VDC	4 wire Circuit Board
AST-14-Sync-21-30-DC -Board	21 - 30	VDC	4 wire Circuit Board

NOTE: * - **S** for standard temperature range and - **L** for low temperature range

Flash Tube

AST-FT 3050 Flash Tube

Lenses

AST-14-Guard-Lens-RE	Red Lens
AST-14-Guard-Lens-AM	Amber Lens
AST-14-Guard-Lens-BL	Blue Lens
AST-14-Guard-Lens-GR	Green Lens
AST-14-Guard-Lens-CL	Clear Lens
AST-14-Guard-Lens-PU	Purple Lens

Bulletin 855H — General-purpose Electronic Horns

Single- or dual-circuit, selectable tone horns, with volume control, for use in general signaling applications.



855H – SG 10 GPA

a b c

a	
Mounting Type	
Code	**Description**
FG	Semi-flush wall plate, gray housing
SG	Surface base with two conduit entrances, gray housing

b	
Voltage	
Code	**Description**
24	24V AC/DC
10	120V AC
20	240V AC
30	10…30V DC
45	40…260V AC/DC, 50/60 Hz

c	
Horn Type	
Code	**Description**
GPA (1)	General-purpose, 108 dB(A) max, single stage/circuit, three tones
GPE (2)	Enhanced version, 113 dB(A) max @ 1 m (3.3 ft), two stage, three tones, volume control

(1) Not valid with voltage codes 30 and 45 (Table b).
(2) Not valid with mounting type FG (Table a) or with voltage codes 24, 10, and 20 (Table b).

Accessories — Bulletin 855H General-purpose Electronic Horns

	Description	Cat. No.
	M20 hole plug replacement kit (1)	855H-AHPK

(1) For use with mounting type SG only.

Specifications — Bulletin 855H General-purpose Electronic Horns

Table 5 - Environmental

Attribute		Value
Ingress Ratings	Semi-flush Mount	UL Type 3R/13, IP54
	Surface Mount	UL Type 4/4X/13/3R, IP66
Temperature Ranges	Operating	-25…+55 °C (-13…+131 °F)
	Storage	-40…+70 °C (-40…+158 °F)

Table 6 - Materials

Part	Material
Housings including horn cover and base	Polycarbonate
O-ring	NBR
Gasket (mounting type FG)	EPDM/SBR closed-cell foam

Table 7 - Performance Ratings

Attribute		Performance Rating
Sound Output	Standard (GPA)	105±3 dB(A) @ 1 m (3.3 ft)
	Enhanced (GPE)	110±3 dB(A) @ 1 m (3.3 ft)

Table 8 - Operating Voltage and Currents

Attribute	Horn Type	DC Voltage	AC Voltage		
Input Voltage Ranges	Standard (GPA)	24V DC (±25%)	24V AC, 50/60 Hz (±10%)	120V AC, 50/60 Hz (±10%)	240V AC, 50/60 Hz (±10%)
	Enhanced (GPE)	10…30V DC	40…260V AC/DC		
Input Currents @ Nominal Voltage	Standard (GPA)	62 mA	220 mA	40 mA	50 mA
	Enhanced (GPE)	105 mA	—	36 mA	18 mA

Standards Compliance


- UL 464
- CSA C22.2 No. 205
- EN/IEC 60947-1
- EN/IEC 60947-5-1
- EN 6100-6-2
- EN 6100-6-3

Certifications

- c-UL-us Listed (File No. S6583, Guides UCST, UCST7)
- CE Marked

Approximate Dimensions — Bulletin 855H General-purpose Electronic Horns

Dimensions in millimeters (inches). Dimensions are not intended to be used for manufacturing purposes.



Semi-flush Mount **Surface Mount**

Bulletin 855XM — Hazardous Location Metal Horns

Alarm Horn Sounders





855XM	–	C	G	M	D24	D	A	4
		a	b	c	d	e	f	g

a	
Product Type	
Code	**Description**
H	Horn only
C	Horn with attached xenon strobe

b	
Housing Color	
Code	**Description**
G	Gray

c	
Conduit Entry	
Code	**Description**
M	Two M20 x 1.5 mm conduit entries

d	
Voltage	
Code	**Description**
D24	20…28V DC (3)
D30	10…30V DC (4)
A10	115…125V AC 60 Hz
A20	215…250V AC 50 Hz

e	
Horn Type	
Code	**Description**
D	116 dB (A) @ 1 m (3.3 ft), 64 tones, 4 stages

f	
Beacon Type (1) (2)	
Code	**Description**
Blank	No light
A	5 J, strobe
B	10 J, strobe

g	
Lens Color (1)(2)	
Code	**Description**
Blank	No light
4	Red
5	Amber
7	Clear

(1) Beacon type and lens color must be Blank for Cat. No. 855XM-H.
(2) Beacon type and lens color cannot be Blank for Cat. No. 855XM-C.
(3) Voltage code D24 only valid with beacon code A and B (Table f).
(4) Voltage code D30 not valid with beacon code A and B (Table f).

Specifications — Bulletin 855XM

Table 132 - Mechanical

Device	The following are reference guidelines for maximum shock and vibration standards for the 855XM horn.	
	Shock [G]	Vibration [G]
Metal horn	40	3
Metal horn with attached beacon	30	3

Table 133 - Environmental

Attribute	Device	Value	
Ingress rating	Horn and horn with attached beacon	UL Type 4/4X/13/3R, IP66	
		Operating	Storage
Temperature range	Electronic horn	-40…+50°C (-40…+122 °F) (1)	-40…+70 °C (-40…+158 °F)
	Horn with attached beacon	-40…+50 °C (-40…+122 °F)	-40…+70 °C (-40…+158 °F)

(1) -40…+158 °F (-40…+70 °C) for Class 1/Div.2

Table 134 - Materials

Part	Material
Housing (gray powder coat)	Marine grade aluminum (Al Si12 Cu)
Screws	Stainless steel
Beacon lens	Polycarbonate over glass
Lens cage	Stainless steel
Gasket (Cover to Base)	O-ring Fluorosilicone UL
Gasket (Screw Mounting Hole)	Fiber washer

Table 135 - Performance Ratings

Device	Sound Output @ 1 m (3.3 ft) (1)	Volume Control	No. of Tones	Stages
Metal Horn	116 dB(A), max	Adjustable -12 dB(A)	64	4
	Light Output (Xenon Strobe Beacon- 5 J)		Light Output (Xenon Strobe Beacon- 10 J)	
Red LED Beacon	14.6 cd eff/120,000 cd peak		42.83 cd eff/240,000 cd peak	
Amber LED Beacon	45.8 cd eff/350,000 cd peak		130.9 cd eff/700,000 cd peak	
Clear LED Beacon	80.6 cd eff/500,000 cd peak		243.1 cd eff/1,000,000 cd peak	

(1) SPL data ±3 dB(A). Measured at optimum voltage.

Table 136 - Operating Voltage and Current Consumption

Device	Operating Voltage	Nominal Maximum	Inrush	Leakage Immunity
Horns				
855XM-HGMD30D	10…30V DC	160 mA @ 12V DC	611 mA, 11 ms	>3 mA
		313 mA @ 24V DC	1809 mA, 9 ms	
		225 mA @ 30V DC	2483 mA, 7 ms @ 30V DC	
855XM-HGMA10D	115V AC 60 Hz ±10%	89 mA @ 115V AC 60 Hz	710 mA, 8 ms	
855XM-HGMA20D	230V AC 50 Hz ±10%	52 mA @ 230V AC 60 Hz	350 mA, 7 ms	
Horns with Beacon				
855XM-CGMD24DA***x***	20…28V DC	513 mA @ 24V DC (5 J)	1932 mA, 10 ms	>3 mA
855XM-CGMD24DB***x***	20…28V DC	876 mA @ 24V DC (10 J)	2074 mA, 11 ms	
855XM-CGMA10DA***x***	115…125V AC, 60 Hz	174 mA @ 115V AC (5 J)	975 mA, 3 ms	
855XM-CGMA10DB***x***	115…125V AC, 60 Hz	320 mA @ 115V AC (10 J)	1031 mA, 3 ms	
855XM-CGMA20DA***x***	215…250V AC, 50 Hz	63 mA @ 230V ACDC (5 J)	1607 mA, 3 ms	
855XM-CGMA20DB***x***	215…250V AC, 50 Hz	100 mA @ 230V AC (10 J)	1628 mA, 3 ms	

Table 137 - Flashing Frequency

Device	Frequency
Horns with strobe	1 Hz

Table 138 - Miscellaneous

Attribute	Value
Cable entry	Two M20x 1.5 mm threaded holes
Terminal blocks	0.5…2.5 mm^2 (20…14 AWG)
Grounding stud	M5

Table 139 - ATEX/IECEx Certification

Zone	Group	Temperature Code
855XM Hazardous Location Metal Horn		
Zone 2	Group IIA (propane) Group IIB (ethylene) Group IIC (hydrogen/acetylene)	T1 (450 °C [842 °F]) T2 (300 °C [572 °F]) T3 (200 °C [392 °F]) T4 (135 °C [275 °F])
Zone 22 (1)	Group IIIA (combustible flyings) Group IIIB (non-conductive dust) Group IIIC (conductive dust)	—
855XM-C Hazardous Location Metal Horn with Strobe		
Zone 2	Group IIA (propane) Group IIB (ethylene) Group IIC (hydrogen/acetylene)	T1 (450 °C [842 °F]) T2 (300 °C [572 °F])
Zone 22 (2)	Group IIIA (combustible flyings) Group IIIB (non-conductive dust) Group IIIC (conductive dust)	—

(1) Maximum surface temperature for dust applications is 90 °C (194 °F).
(2) Maximum surface temperature for dust applications is 90 °C (194 °F) for Cat. No. 855XM-CGMxxxDA* and 230 °F (110 °C) for Cat. No. 855XM-CGMxxxDB*.

Table 140 - Class/Zone Ratings — US

Device	Rating
Horn	• Class I, Zone 2 AEx nA IIC T4 Gc (Ta -40…+50 °C [-40…+122 °F]) • Class I, Zone 22 AEx tc IIIC T90 °C Dc (Ta -40…+50 °C [-40…+122 °F])
Horn with 5 J strobe	• Class I, Zone 2 AEx nA IIC T2 Gc (Ta -40…+50 °C [-40…+122 °F]) • Class I, Zone 22 AEx tc IIIC 120 °C Dc (Ta -40…+50 °C [-40…+122 °F])
Horn with 10 J strobe	• Class I, Zone 2 AEx nA IIC T1 Gc (Ta -40…+50 °C [-40…+122 °F]) • Class I, Zone 2 AEx nA IIC T2 Gc for (Ta -40…+40 °C [-40…+104 °F]) • Class I, Zone 22 AEx tc IIIC 120 °C Dc (Ta -40…+50 °C [-40…+122 °F])

All horns (with and without strobe) comply with the following:

- ANSI/UL 60079-0-2013
- ANSI/UL 60079-15-2013
- ISA60079-31-2013

Table 141 - Class/Zone Ratings — Canada

Device	Rating
Horn	• Ex nA IIC T4 Gc X (Ta -40…+50 °C [-40…+122 °F]) • Ex tc IIIC T90 °C Dc (Ta -40…+50 °C [-40…+122 °F]) • Class II Div 2 FG T5 (Ta -40…+50 °C [-40…+122 °F])
Horn with 5 J strobe	• Ex nA IIC T2B Gc X (Ta -40…+50 °C [-40…+122 °F]) • Ex nA IIC T2C Gc X (Ta -40…+45 °C [-40…+113 °F]) • Ex tc IIIC T120 °C Dc (Ta -40…+50 °C [-40…+122 °F]) • Class II, Div 2 FG T4A (Ta -40…+50 °C [-40…+122 °F])
Horn with 10 J strobe	• Ex nA IIC T1 Gc X (Ta -40…+50 °C [-40…+122 °F]) • Ex nA IIC T2 Gc X (Ta -40…+40 °C [-40…+104 °F]) • Ex tc IIIC T120 °C Dc (Ta -40…+50 °C [-40…+122 °F]) • Class II, Div 2 FG T4A (Ta -40…+50 °C [-40…+122 °F])

All horns (with and without strobe) comply with the following:

- CAN/CSA C22.2 No. 60079-0:11
- CAN/CSA C22.2 No. 60079-15:12
- CAN/CSA C22.2 No. 60079-31:12

Table 142 - Class/Division Ratings — US and Canada

Device	Rating
Horn	• Class I Div 2, ABCD T3C (Ta -40…+70 °C [-40…+158 °F]) • Class I Div 2, ABCD T4 (Ta -40…+65 °C [-40…+149 °F]) • Class I Div 2, ABCD T4A (Ta -40…+50 °C [-40…+122 °F]) • Class II Div 2, FG T5 (Ta -40…+50 °C [-40…+122 °F]) • Class II Div 2, FG T6 (Ta -40…+45 °C [-40…+113 °F]) • Class III Div 1 & 2 (Ta -40…+50 °C [-40…+122 °F])
Horn with 5 J strobe	• Class I Div 2, ABCD T2B (Ta -40…+70 °C [-40…+158 °F]) • Class I Div 2, ABCD T2C (Ta -40…+55 °C [-40…+131 °F]) • Class I Div 2, ABCD T2D (Ta -40…+40 °C [-40…+104 °F]) • Class II Div 2, FG T5 (Ta -40…+50 °C [-40…+122 °F]) • Class III Div 1&2 (Ta -40…+50 °C [-40…+122 °F])
Horn with 10 J strobe	• Class I Div 2, ABCD T1 (Ta -40…+70 °C [-40…+158 °F]) • Class I Div 2, ABCD T2 (Ta -40…+50 °C [-40…+122 °F]) • Class II Div 2, FG T4A (Ta -40…+50 °C [-40…+122 °F]) • Class II Div 2, FG T5 (Ta -40…+104 °F [-40…+40 °C]) • Class III Div 1&2 (Ta -40…+50 °C [-40…+122 °F])

All horns (with and without strobe) comply with the following:

- ANSI/ISA 12.12.01 – 2013
- CSA C22.2 No. 213-M1987
- CSA C22.2 No. 157-92:2006

Standards Compliance





























- c-UL-us Listed UL464/UL 1608 File No. E305533
- CSA C22.2 No. 213-M1987
- CSA C22.2 No. 157-92: 2006
- CE — European Explosive Atmosphere Directive 94/9/EC and European EMC Directive 2004/108/EC
- EN60079-0:2012/IEC60079-0: ed. 6.0 (2011-06)
- EN60079-15:2010/IEC60079-15: ed. 4.0 (2010-01)
- EN60079-31:2009/IEC60079-31:2009 ed. 1.0 (corr. 1 2009)

Certifications






























- CE Marked
- UL Listed for:
  - Class I, Division 2, Groups A, B, C, and D
  - Class II, Division 2, Groups F and G
  - Class III, Division 1 and 2 (see Temperature Codes in Table 139 on page 109)
- ATEX/IECEx: Zone 2 Groups IIA, B, C and Zone 22 Groups IIIA, B, and C
- Ex Rating (Horn): II 3G Ex nA IIC T4 Gc and II 3D Ex tc IIIC T90 °C Dc (Ta -40…+50 °C [-40…+122 °F])
- Ex Rating (Horn with 5 J Strobe): II 3G Ex nA IIC T2 Gc and II 3D Ex tc IIIC T90 °C Dc (Ta -40…+50 °C [-40…+122 °F])
- Ex Rating (Horn with 10 J Strobe): II 3G Ex nA IIC T1 Gc and II 3D Ex tc IIIC T110 °C Dc (Ta -40…+50 °C [-40…+122 °F]); [II 3G Ex nA IIC T2 Gc for Ta -40…+40 °C (-40…+104 °F)]

Tone Selection Table for 855XM

Tone Selection – To select the required first stage tone, set the tone switches 1…6 to the tone setting shown in the following table. The table also shows which 2nd, 3rd, and 4th stage tones are available for use with the selected first stage tone if more that one tone output is required.

Stage 1 Tone No.	Tone Description	Tone Visual	Switch						Stage 2 Alarm (S2)	Stage 3 Alarm (S3)	Stage 4 Alarm (S2+S3)
			1	2	3	4	5	6			
1	1000 Hz PFEER toxic gas		0	0	0	0	0	0	3	2	44
2	1200/500 @ 1 Hz DIN / PFEER P.T.A.P.		1	0	0	0	0	0	1	3	44
3	1000 @ 0.5 Hz(1 s on/1 s off) PFEER gen. alarm		0	1	0	0	0	0	1	2	44
4	1.4…1.6 kHz 1 s, 1.6…1.4 kHz 0.5 s NF C 48-265		1	1	0	0	0	0	44	24	1
5	544 (100 ms)/440 (400 ms) NF S 32-001		0	0	1	0	0	0	52	19	1
6	1500/500 - (0.5 s on/0.5 s off) x3 + 1 s gap AS4428		1	0	1	0	0	0	7	44	1
7	500…1500 Hz sweeping 2 s on/1 s off AS4428		0	1	1	0	0	0	6	44	1
8	500/1200 Hz @ 0.26 Hz(3.3 s on/0.5 s off) Netherlands - NEN 2575		1	1	1	0	0	0	44	24	35
9	1000 (1 s on/1 s off) x7 + (7 s on/1 s off) IMO Code 1a		0	0	0	1	0	0	18	34	1
10			1	0	0	1	0	0	21	34	1
11	420 (0.5 s on/0.5 s off) x3 + 1 s gap ISO 8201 temporal pattern		0	1	0	1	0	0	44	1	8
12	1000 (0.5 s on/0.5 s off) x3 + 1 s gap ISO 8201 temporal pattern		1	1	0	1	0	0	44	1	8
13	422/775 - (0.85 s on/0.5 s off) x3 + 1 s gap NFPA - temporal		0	0	1	1	0	0	44	1	8
14	1000/2000 @ 1 Hz Singapore		1	0	1	1	0	0	23	3	35
15	300 continuous		0	1	1	1	0	0	44	24	35
16	440 continuous		1	1	1	1	0	0	44	24	35
17	470 continuous		0	0	0	0	1	0	44	24	35
18	500 continuous IMO Code 2 (low)		1	0	0	0	1	0	44	24	35
19	554 continuous		0	1	0	0	1	0	64	24	35
20	660 continuous		1	1	0	0	1	0	44	24	35
21	800 IMO Code 2 (high)		0	0	1	0	1	0	44	24	35
22	1200 continuous		1	0	1	0	1	0	44	24	35
23	2000 continuous		0	1	1	0	1	0	15	3	35
24	2400 continuous		1	1	1	0	1	0	48	20	35
25	440 @ 0.83 Hz (50 cycles/min) intermittent		0	0	0	1	1	0	1	44	8
26	470 @ 0.9 Hz - 1.1 s intermittent		1	0	0	1	1	0	1	44	8
27	470 @ 5 Hz - (5 cycles/s) intermittent		0	1	0	1	1	0	1	44	8
28	544 @ 1.14 Hz - 0.875 s intermittent		1	1	0	1	1	0	44	24	8
29	655 @ 0.875 Hz intermittent		0	0	1	1	1	0	1	44	8
30	660 @ 0.28 Hz - 1.8 s on/1.8 s off intermittent		1	0	1	1	1	0	44	24	8
31	660 @ 3.34 Hz - 150 ms on/150 ms off intermittent		0	1	1	1	1	0	30	24	8
32	745 @ 1 Hz intermittent		1	1	1	1	1	0	44	24	8
33	800 - 0.25 s on/1 s off intermittent		0	0	0	0	0	1	53	24	8


Tone Selection – To select the required first stage tone, set the tone switches 1…6 to the tone setting shown in the following table. The table also shows which 2nd, 3rd, and 4th stage tones are available for use with the selected first stage tone if more that one tone output is required.

Stage 1 Tone No.	Tone Description	Tone Visual	Switch						Stage 2	Stage 3	Stage 3
			1	2	3	4	5	6			
34	800 @ 2 Hz IMO Code 3.a (high) intermittent		1	0	0	0	0	1	56	24	8
35	1000 @ 1 Hz intermittent		0	1	0	0	0	1	44	24	8
36	2400 @ 1 Hz intermittent		1	1	0	0	0	1	21	24	8
37	2900 @ 5 Hz intermittent		0	0	1	0	0	1	53	24	8
38	363/518 @ 1 Hz alternating		1	0	1	0	0	1	1	8	19
39	450/500 @ 2 Hz alternating		0	1	1	0	0	1	1	8	19
40	554/440 @ 1 Hz alternating		1	1	1	0	0	1	44	24	19
41	554/440 @ 0.625 Hz alternating		0	0	0	1	0	1	1	8	19
42	561/760 @ 0.83 Hz (50 cycles/min) alternating		1	0	0	1	0	1	1	8	19
43	780/600 @ 0.96 Hz alternating		0	1	0	1	0	1	1	8	19
44	800/1000 @ 2 Hz alternating		1	1	0	1	0	1	5	24	19
45	970/800 @ 2 Hz alternating		0	0	1	1	0	1	1	8	19
46	800/1000 @ 0.875 Hz alternating		1	0	1	1	0	1	53	24	19
47	2400/2900 @ 2 Hz alternating		0	1	1	1	0	1	57	24	19
48	500/1200 @ 0.3 Hz sweeping		1	1	1	1	0	1	44	24	12
49	560/1055 @ 0.18 Hz sweeping		0	0	0	0	1	1	44	24	12
50	560/1055 @ 3.3 Hz sweeping		1	0	0	0	1	1	44	24	12
51	600/1250 @ 0.125 Hz sweeping		0	1	0	0	1	1	44	24	12
52	660/1200 @ 1 Hz sweeping		1	1	0	0	1	1	64	24	12
53	800/1000 @ 1 Hz sweeping		0	0	1	0	1	1	56	24	12
54	800/1000 @ 7 Hz sweeping		1	0	1	0	1	1	57	24	12
55	800/1000 @ 50 Hz sweeping		0	1	1	0	1	1	54	24	12
56	2400/2900 @ 7 Hz sweeping		1	1	1	0	1	1	57	24	12
57	2400/2900 @ 1 Hz sweeping		0	0	0	1	1	1	47	24	12
58	2400/2900 @ 50 Hz sweeping		1	0	0	1	1	1	54	24	12
59	2500/3000 @ 2 Hz sweeping		0	1	0	1	1	1	44	24	12
60	2500/3000 @ 7.7 Hz sweeping		1	1	0	1	1	1	44	24	12
61	800 motor siren		0	0	1	1	1	1	44	24	12
62	1200 motor siren		1	0	1	1	1	1	44	24	12
63	2400 motor siren		0	1	1	1	1	1	44	24	12
64	Simulated bell		1	1	1	1	1	1	44	21	12


Approximate Dimensions — Bulletin 855X

Dimensions in millimeters (inches). Dimensions are not intended to be used for manufacturing purposes.

855XM Hazardous Location Metal Horn



855XM-C Hazardous Location Metal Horn with Xenon Strobe



REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Jul 17, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-08 (Building temperature transmitters)

Date : 2018-07-17

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Dominic Papineau, Project Manager	E-mail: dpapineau@norclair.ca
Phone : 450-688-4012 # 720	Cell. : 514-409-1832

Information, subcontractor or supplier	
Sub/supplier : Thermo Kinetics	
Contact : Normand Hadd	Phone : (514) 856-0370

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : Building temperature transmitters	
Drawing reference :	
Specification reference : : **47 30 02** (Page 10 / xx)	Division :
Article :	Number of pages : 15

CONSULTANT APPROVAL

Comments within

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-08 (2018-07-17)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED

☑ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-JUL-26

BY David Hutchison, P.Eng.

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca


PRODUCT REFERENCE GUIDE

THERMO KINETICS
MEASUREMENT & CONTROL

6x
To be mounted on wall
for room temperature
monitoring

Resistance Temperature Detectors

Probes & Assemblies



PRODUCT FEATURES

- Rugged Construction
- Accurate and Stable Probes
- General Purpose, Tip Sensitive, High Temperature and High Vibration Probes and Assemblies
- 2, 3 and 4 Wire Configurations
- General Purpose or Spring Loaded Mounting, with or without Thermowells
- Nipple, Nipple-Union-Nipple or Bushing Extension Hardware
- CSA Approved Assemblies for Hazardous Locations
- Averaging RTDs
- Custom Configurations
- Head Mounted Transmitter Options

Please visit our website for our other Product Literature Guides : T-PAK® Thermocouples, Industrial Thermocouples, Thermowells, Protection Tubes, Calibration Services

toll free 1-800-268-0967 • www.thermo-kinetics.com

Toronto • Montréal • Québec • Calgary • Edmonton • Vancouver

® Registered Trademark of Thermo-Kinetics Company Limited

GENERAL

Resistance Temperature Detectors (RTDs) are used for industrial temperature measurements where high accuracy and long-term stability are required. The 100 ohm platinum element is the most common for industrial applications. The 3-wire lead configuration is used for industrial temperature measurements and provides adequate compensation for leadwire resistance. The 4-wire arrangement fully eliminates all leadwire effects and is used in applications where high accuracy is required.

TOLERANCE & ACCURACY

Tolerance of an RTD is a measure of its conformity to the ITS-90 Temperature-Resistance curve, and is normally expressed as an allowable deviation from the normal resistance at 0 ºC. It consists of a manufacturing tolerance on the reference point (eg: how close is the resistance to 100 Ω at 0 ºC) and a materials tolerance on the Temperature Coefficient of Resistance (eg: how close does the wire conform to an alpha of .00385).

At the reference temperature, only the manufacturing tolerance applies (since this is where the RTD element is "adjusted" to 100 Ω). At other temperatures, the materials tolerance must be added. As the temperature increases or decreases, the tolerance becomes wider. At higher temperatures, the material tolerance has the larger influence.

DIN/IEC 60751 (replaces DIN 43760) defines Class B and Class A tolerances.

Temp	Resistance	Class B		Class A	
ºC	Ω	Ω	ºC	Ω	ºC
-200	18.52	±0.56	±1.3	±0.24	±0.55
-100	60.26	±0.32	±0.8	±0.14	±0.35
0	100.00	±0.12	±0.3	±0.06	±0.15
100	138.51	±0.30	±0.8	±0.13	±0.35
200	176.86	±0.48	±1.3	±0.20	±0.55
300	212.05	±0.64	±1.8	±0.27	±0.75
400	247.09	±0.79	±2.3	±0.33	±0.95
500	280.98	±0.93	±2.8	±0.38	±1.15
600	313.71	±1.06	±3.3	±0.43	±1.35
650	329.64	±1.13	±3.6	±0.46	±1.45
700	345.28	±1.17	±3.8	--	--
800	375.70	±1.28	±4.3	--	--
850	390.48	±1.34	±4.6	--	--

NOTE: Tolerances apply to the element, not to final probe.

Class B: ± (0.30 + .005 x |t|) ºC
Class A: ± (0.15 + .002 x |t|) ºC

|t| = absolute value of temperature in ºC

Elements with narrower tolerances are available (eg: 1/3 B, 1/5 B, etc). No standard exists for these fractional tolerance elements; it depends on the manufacturer of the element. For example, a 1/10 B element would normally have a manufacturing tolerance of 0.03 ºC, but the material tolerance would depend on the manufacturer's choice of wire (class B, class A or other).


Accuracy is dependent on the tolerance of the RTD, the measurement temperature, the accuracy of the readout device, the effects of the interconnecting leadwire and the installation.

For highest accuracy use a calibrated Class B element with a precision transmitter (or meter) that can be characterized to match the RTD calibration.

Platinum elements with other temperature-resistance curves are available (eg: JIS). Copper and Nickel elements are also available as replacements to match existing instrumentation.

SPECIFICATIONS

ELEMENT MATERIAL:	Platinum, DIN/IEC 60751
ELEMENT RESISTANCE:	10, 100, 500, 1000 Ω
TOLERANCE:	±0.12% of resistance at 0 ºC (Class B) ±0.06% of resistance at 0 ºC (Class A)
STABILITY:	0.05% of resistance/year at 0 ºC
TEMPERATURE COEFFICIENT:	.00385 Ω/Ω/ºC
TEMPERATURE RANGE:	-50 ºC to 250 ºC (R1,R2) -200 ºC to 500 ºC (R3,R5) -200 ºC to 550 ºC (R4)
LEAD CONFIGURATION:	2, 3 or 4 wire
LEAD MATERIAL:	Stranded copper for 260 ºC Stranded ni-clad copper for 500 ºC Solid nickel for 550 ºC
LEAD INSULATION:	Teflon for 260 ºC probes Fiberglass for 500 ºC probes MgO for 550 ºC probes
PROBE MATERIAL:	316 stainless steel
PROBE TIP:	Stainless steel Copper alloy for tip sensitive probe
PROBE SIZE:	0.25" OD
VIBRATION:	20g over 10 to 1K Hz
RESPONSE TIME:	30 sec nominal for SS tip 15 sec nominal for copper tip
SELF HEATING:	20 mW/ºC for SS tip 40 mW/ºC for copper tip
PRESSURE RATING:	500 psig over temperature range
INSULATION RESISTANCE:	1000 MΩ at 500 VDC



ORDERING INFORMATION


A 6-part catalog number is used to specify a complete RTD probe.

R21 - D100A3 - 012.0 - 68 - A024 - 03

1: Style Code
2: Element Code
3: Length
4: Termination Code
5: Leadwire Code
6: Option Code

Example: The above catalog number identifies a general purpose RTD probe with a .250" OD stainless steel sheath 12" long, a 100 ohm platinum (DIN) element with 3-lead configuration, a heavy duty cast iron head and a stainless steel compression fitting with 1/4" NPT.

1: STYLE CODE



R1x: General Purpose probe, 0.250" OD, 316 SS sheath and tip, internal leads are teflon insulated, stranded copper (22 ga for simplex, 24 ga for duplex), 260°C maximum temperature.

R2x: Tip Sensitive probe, 0.250" OD, 316 SS sheath, copper alloy tip, internal leads are teflon insulated, stranded copper (22 ga simplex, 24 ga for duplex), 260°C maximum temperature


R3x: Medium Temperature probe, 0.250" OD, 316 SS sheath & tip, internal leads are fiberglass insulated, stranded ni-clad copper (22 ga for simplex, 24 ga for duplex), 500°C maximum temperature.

R4x: High Temperature probe, 0.250" OD, 316 SS sheath & tip, internal leads are solid nickel, MgO insulated, 600°C maximum temperature. This construction can be supplied in long lengths and coiled.

R5x: High Vibration probe, 0.250" OD, 316 SS sheath & tip, internal leads are solid nickel, MgO insulated, 500°C maximum temperature.

Other constructions, diameters, materials, etc, are available on special order. Contact factory for details.

2: ELEMENT CODE



(a) MATERIAL:
D: Platinum (IEC) · = 0.003850 Ω/Ω/°C
S: Platinum (JIS) · = 0.003916 Ω/Ω/°C

(b) BASE RESISTANCE:
10, 100, 500, 1000 for D
100 for S


(c) TOLERANCE:
A: ±0.12% of resistance at 0 °C (Standard)
E: ±0.06% of resistance at 0 °C (Optional)
F: ±0.04% of resistance at 0 °C (Optional)*
H: ±0.012% of resistance at 0 °C (Optional)(range of 0-100 °C only)*

* available in 4-wire lead configuration only.

2: ELEMENT CODE (cont'd)


(d) LEADWIRE CONFIGURATION:

2-Wire (Code 2)




The 2-wire connection provides no lead wire compensation. Reasonable accuracy can only be obtained if leadwire resistance is negligible compared to the ohms/degree change of the RTD.

3-Wire (Code 3)




The 3-wire connection allows for leadwire compensation in Wheatstone bridge and constant current circuits. These compensating circuits assume that all leads are of equal resistance. This arrangement is most common for industrial temperature measurements.

4-Wire (Code 4)



The 4-wire, type A connection enables complete compensation for the effect of leadwire resistance in potentiometric or compensated bridge measurements. This arrangement is normally used in metrology applications for measurements of the highest precision.

4-Wire Type B (Code 5)










The 4-wire, type B connection is essentially a 2-lead RTD with a compensating loop, and is used in bridge-type differential temperature measurements on equal-ratio bridge networks.

3. LENGTH


Specify probe length ("X") in inches (eg: 012.0 = 12") 3in
Minimum recommended length: 3"

4: TERMINATION CODE

TERMINATION	CODE	DESCRIPTION
	10	22 ga insulated, stranded copper leads. (Teflon for R1x & R2x; Fiberglass for R3x & R4x.) Specify length Y in inches under "LEADWIRE" 'Construction Type' O (standard length = 6")
	11	Potting adaptor with flexible leadwire. Specify 'Construction Type' and length (Y) under "LEAD WIRE" Use "OPTIONS" to specify fittings, connectors, etc.
	12	Retractile cable, 100°C PVC jacket, 1' coiled, extends to 5.' Specify Y (coiled length) under "LEADWIRE" (Pg 8). Use 'Construction Type' O. (standard length = 1')
	15 16 17 18 19	1/2 x 1/2 MOUNTING ADAPTER 1/2" x 1/2" NPT, S/S Specify "Y" length (Std = 6") Welded to Probe Spring Loaded Spring Loaded, O-Ring Compression Bolt, Metal Ferrule Compression Bolt, Teflon Seal
	20 21 22 23 24	For 14-0008/14-0022 Heads (X = A + N + 2.25"). For 14-0304/7, 14-0804/7 Heads (X = A + N + 2.00"). For 14-1080A/1080S/1086S, 14-0018 Heads (X = A + N + 1.75"). For 14-0007 Head (X = A + N + 2.25"). For 14-1304/7 Heads (X = A + N + 2.25").
	25 27	3-Pole Plug (200°C) High-Temp 3-Pole plug (425°C)
	30 31	Open type, micro terminal block (200°C) High-Temp open type micro terminal block (425°C)
	35 36 37 38	Miniature weatherproof plastic terminal head Brass Comp Fitting (200°C) High-Temp miniature W/P plastic terminal head Brass Comp Fitting(425°C) Miniature weatherproof plastic terminal head S/S Comp Fitting (200°C) High-Temp miniature W/P plastic terminal head S/S Comp Fitting(425°C)


4: TERMINATION CODE (cont'd)

Screw Cover Terminal Head
Mounted to probe with compression fitting



HEAD					Compression Fitting	
Style	Material	Type*2	Haz Loc*3	Fig	Brass	Stainless
General Purpose	Aluminum	4	--	1	65	67
	Cast Iron	4	--	1	66	68
	Stainless	4X	--	3	--	64
Heavy Duty	Aluminum	4	B C D	4	42	43
	Cast Iron	--	--	2	46	48
	Stainless	4X	B C D	4	--	44

Screw Cover Terminal Head
1/2" X 1/2" NPT SS Mounting Adapter
Fixed probe



HEAD					Welded	Compression Adapter
Style	Material	Type*2	Haz Loc*3	Fig		
General Purpose	Aluminum	4	--	1	70	91
	Cast Iron	4	--	1	75	93
	Stainless	4X	--	3	C1	C6
Heavy Duty	Aluminum	4	B C D	4	A1	A6
	Cast Iron	--	--	2	55	83
	Stainless	4X	B C D	4	B1	B6

4x


Thread engagement:
.35" for 1" NPT


If used with a thermowell
X = TW bore length 1/2"


2x, TT-01-950 & TT-01-951

*1 Cast Iron body, Aluminum cap
*2 CSA or Nema type
*3 Heads meet requirements for Class 1 Div 1 & 2 (Class I Zone 1 & 2).
For Explosion Proof assemblies, refer to RTD Assemblies starting on page 11.


4x


Fig. 1


Fig. 2



Fig. 3

2x



Fig.4

4: TERMINATION CODE (cont'd)

Screw Cover Terminal Head
1/2" X 1/2" NPT SS Mounting Adapter
Spring-Loaded Probe




Note: If used with a thermowell,
X = A (bore length of thermowell)



* Thread Engagement
.35" for 1/2" NPT

HEAD					CAPTIVE T/B		SPRG-LOADED ADAPTER	
Style	Material	Type*1	Haz Loc*2	Fig	Std	O-Ring	Std	O-Ring
General Purpose	Aluminum	4	--	1	71	72	73	74
	Cast Iron	4	--	1	76	77	78	79
	Stainless	4X	--	3	C2	C3	C4	C5
Heavy Duty	Aluminum	4	B C D	4	A2	A3	A4	A5
	Cast Iron	--	--	2	56	57	58	59
	Stainless	4X	B C D	4	B2	B3	B4	B

Division 2 (Zone 2) Assemblies
Remote Mounted Head
Flexible Armour **



HEAD				Transmitter	Class I*2	Class II*3
Style	Material	Type*1	Fig			
Heavy Duty	Aluminum	4	4	None	9K	8K
			4	TK 381	9T	8T
			4	IPAQ-H	9E	8E
	Stainless	4X	4	None	9L	8L
			4	TK 381	9U	8U
			4	IPAQ-H	9F	8F

*1 CSA or Nema type
*2 Head meets requirements for Class 1 Div 1 & 2 (Class I Zone 1 & 2).
For Explosion Proof assemblies, refer to RTD Assemblies starting on page 11.
*3 Armour is PVC jacketed for Class II applications.

5: LEADWIRE CODE

Leadwire extension can be accomplished by extending the internal leads or by attaching a jacketed cable (via a potting adaptor).

CONTRUCTION TYPE

CONSTR. CODE	LEADWIRE EXTENSION	FOR STYLE CODE	REQUIRED TERM CODE
O	Teflon Insulated Leadwire, No Jacket	R1, R2	10
	Teflon Insulated Leadwire, No Jacket	R3, R4, R5	11
Q	F/G Insulated Leadwire, No Jacket	R1, R2, R3	10
	F/G Insulated Leadwire, No Jacket	R4, R5	11
P	PVC Jacketed Cable, Unshielded	All	11
R	PVC Jacketed Cable, Shielded	All	11
T	Teflon Jacketed Cable, Shielded	All	11
W	Teflon Jacketed Cable, Shielded, SS Overbraid	All	11
A	Flex Armour (3/16" ID), Teflon Insluated Leads	All	11
B	Flex Armour (3/16" ID), PVC Jacketed, Teflon Insulated Leads	All	11
C	Flex Armour (3/16" ID), F.G Insulated Leads	R3, R4, R5	11
D	Flex Armour (3/16" ID), PVC Jacketed, F/G Insulated Leads	R3, R4, R5	11

Use O000 when leadwire not applicable (for Term Codes other than 10 & 11).

6: OPTION CODE

CODE	DESCRIPTION
000	None
2	Brass Compression Fitting (Metal Ferrule) –1/4" NPT*
3	Brass Compression Fitting (Teflon Seal) – 1/4" NPT*
4	Brass Compression Fitting (Metal Ferrule) –1/2" NPT
5	Brass Compression Fitting (Teflon Seal) –1/2" NPT
6	S.S. Compression Fitting (Metal Ferrule) – 1/4" NPT*
7	S.S. Compression Fitting (Teflon Seal) – 1/4" NPT*
8	S.S. Compression Fitting (Metal Ferrule) – 1/2" NPT
9	S.S. Compression Fitting (Teflon Seal) – 1/2" NPT
C	Transmitter (or Indicator) Configuration
D	3-Pole Plug (at end of leadwire)
E	3-Pole Plug & Mating Jack (at end of leadwire)
F	Brazed Transition
G	Self Grip Spring
H	Spade Lugs (at end of leadwire)
J	1/2" x 1/2" NPT Adapter, Welded to Probe
K	1/2" x 1/2" NPT Spring-Loaded Adapter
L	1/2" x 1/2" NPT Spring-Loaded Adapter with O-Ring Seal
M	1/2" x 1/2" NPT Compression Adaptor, Fixed (Metal Ferrule)
N	1/2" x 1/2" NPT Compression Adaptor, Adjustable (Teflon Seal)
P	Paper Tag
S	Stainless Steel Tag
X	Special

* For other NPT sizes, use Option X & specify size.

RESISTANCE VS TEMPERATURE TABLE – DIN/IEC 60751, Ro = 100Ω TCR = .00385Ω/Ω/ºC

Temp (ºC)	0	1	2	3	4	5	6	7	8	9
0	100.000	100.391	100.781	101.172	101.562	101.953	102.343	102.733	103.123	103.513
10	103.903	104.292	104.682	105.071	105.460	105.849	106.238	106.627	107.016	107.405
20	107.794	108.182	108.570	108.959	109.347	109.735	110.123	110.510	110.898	111.286
30	111.673	112.060	112.447	112.835	113.221	113.608	113.995	114.382	114.768	115.155
40	115.541	115.927	116.313	116.699	117.085	117.470	117.856	118.241	118.627	119.012
50	119.397	119.782	120.167	120.552	120.936	121.321	121.705	122.090	122.474	122.858
60	123.242	123.626	124.009	124.393	124.777	125.160	125.543	125.926	126.309	126.692
70	127.075	127.458	127.840	128.223	128.605	128.987	129.370	129.752	130.133	130.515
80	130.897	131.278	131.660	132.041	132.422	132.803	133.184	133.565	133.946	134.326
90	134.707	135.087	135.468	135.848	136.228	136.608	136.987	137.367	137.747	138.126
100	138.505	138.885	139.264	139.643	140.022	140.400	140.779	141.158	141.536	141.914
110	142.293	142.671	143.049	143.426	143.804	144.182	144.559	144.937	145.314	145.691
120	146.068	146.445	146.822	147.198	147.575	147.951	148.328	148.704	149.080	149.456
130	149.832	150.208	150.583	150.959	151.334	151.710	152.085	152.460	152.835	153.210
140	153.584	153.959	154.333	154.708	155.082	155.456	155.830	156.204	156.578	156.952
150	157.325	157.699	158.072	158.445	158.818	159.191	159.564	159.937	160.309	160.682
160	161.054	161.427	161.799	162.171	162.543	162.915	163.286	163.658	164.030	164.401
170	164.772	165.143	165.514	165.885	166.256	166.627	166.997	167.368	167.738	168.108
180	168.478	168.848	169.218	169.588	169.958	170.327	170.696	171.066	171.435	171.804
190	172.173	172.542	172.910	173.279	173.648	174.016	174.384	174.752	175.120	175.488
200	175.856	176.224	176.591	176.959	177.326	177.693	178.060	178.427	178.794	179.161
210	179.528	179.894	180.260	180.627	180.993	181.359	181.725	182.091	182.456	182.822
220	183.188	183.553	183.918	184.283	184.648	185.013	185.378	185.743	186.107	186.472
230	186.836	187.200	187.564	187.928	188.292	188.656	189.019	189.383	189.746	190.110
240	190.473	190.836	191.199	191.562	191.924	192.287	192.649	193.012	193.374	193.736
250	194.098	194.460	194.822	195.183	195.545	195.906	196.268	196.629	196.990	197.351
260	197.712	198.073	198.433	198.794	199.154	199.514	199.875	200.235	200.595	200.954
270	201.314	201.674	202.033	202.393	202.752	203.111	203.470	203.829	204.188	204.546
280	204.905	205.263	205.622	205.980	206.338	206.696	207.054	207.411	207.769	208.127
290	208.484	208.841	209.198	209.555	209.912	210.269	210.626	210.982	211.339	211.695
300	212.052	212.408	212.764	213.120	213.475	213.831	214.187	214.542	214.897	215.252
310	215.608	215.962	216.317	216.672	217.027	217.381	217.736	218.090	218.444	218.798
320	219.152	219.506	219.860	220.213	220.567	220.920	221.273	221.626	221.979	222.332
330	222.685	223.038	223.390	223.743	224.095	224.447	224.799	225.151	225.503	225.855
340	226.206	226.558	226.909	227.260	227.612	227.963	228.314	228.664	229.015	229.366
350	229.716	230.066	230.417	230.767	231.117	231.467	231.816	232.166	232.516	232.865
360	233.214	233.564	233.913	234.262	234.610	234.959	235.308	235.656	236.005	236.353
370	236.701	237.049	237.397	237.745	238.093	238.440	238.788	239.135	239.482	239.829
380	240.176	240.523	240.870	241.217	241.563	241.910	242.256	242.602	242.948	243.294
390	243.640	243.986	244.331	244.677	245.022	245.367	245.713	246.058	246.403	246.747
400	247.092	247.437	247.781	248.125	248.470	248.814	249.158	249.502	249.845	250.189
410	250.533	250.876	251.219	251.562	251.906	252.248	252.591	252.934	253.277	253.619
420	253.962	254.304	254.646	254.988	255.330	255.672	256.013	256.355	256.696	257.038
430	257.379	257.720	258.061	258.402	258.743	259.083	259.424	259.764	260.105	260.445
440	260.785	261.125	261.465	261.804	262.144	262.483	262.823	263.162	263.501	263.840
450	264.179	264.518	264.857	265.195	265.534	265.872	266.210	266.548	266.886	267.224
460	267.562	267.900	268.237	268.574	268.912	269.249	269.586	269.923	270.260	270.597
470	270.933	271.270	271.606	271.942	272.278	272.614	272.950	273.286	273.622	273.957
480	274.293	274.628	274.963	275.298	275.633	275.968	276.303	276.638	276.972	277.307
490	277.641	277.975	278.309	278.643	278.977	279.311	279.644	279.978	280.311	280.644
500	280.978	281.311	281.643	281.976	282.309	282.641	282.974	283.306	283.638	283.971
510	284.303	284.634	284.966	285.298	285.629	285.961	286.292	286.623	286.954	287.285
520	287.616	287.947	288.277	288.608	288.938	289.268	289.599	289.929	290.258	290.588
530	290.918	291.247	291.577	291.906	292.235	292.565	292.894	293.222	293.551	293.880
540	294.208	294.537	294.865	295.193	295.521	295.849	296.177	296.505	296.832	297.160
550	297.487	297.814	298.142	298.469	298.795	299.122	299.449	299.775	300.102	300.428
560	300.754	301.080	301.406	301.732	302.058	302.384	302.709	303.035	303.360	303.685
570	304.010	304.335	304.660	304.985	305.309	305.634	305.958	306.282	306.606	306.930
580	307.254	307.578	307.902	308.225	308.549	308.872	309.195	309.518	309.841	310.164
590	310.487	310.810	311.132	311.454	311.777	312.099	312.421	312.743	313.065	313.386
600	313.708	314.029	314.351	314.672	314.993	315.314	315.635	315.956	316.277	316.597
610	316.918	317.238	317.558	317.878	318.198	318.518	318.838	319.157	319.477	319.796
620	320.115	320.435	320.754	321.073	321.391	321.710	322.029	322.347	322.666	322.984
630	323.302	323.620	323.938	324.256	324.573	324.891	325.208	325.526	325.843	326.160
640	326.477	326.794	327.110	327.427	327.744	328.060	328.376	328.692	329.008	329.324
650	329.640									

RESISTANCE VS TEMPERATURE TABLE – DIN/IEC 60751, Ro = 100Ω TCR = .00385Ω/Ω/ºC

Temp (ºC)	0	-1	-2	-3	-4	-5	-6	-7	-8	-9
-200	18.5201									
-190	22.8255	22.3965	21.9672	21.5376	21.1076	20.6772	20.2465	19.8154	19.3840	18.9522
-180	27.0964	26.6708	26.2449	25.8186	25.3920	24.9651	24.5379	24.1103	23.6824	23.2541
-170	31.3350	30.9126	30.4898	30.0667	29.6434	29.2197	28.7956	28.3713	27.9467	27.5217
-160	35.5433	35.1238	34.7040	34.2839	33.8635	33.4429	33.0219	32.6006	32.1791	31.7572
-150	39.7232	39.3064	38.8894	38.4721	38.0545	37.6367	37.2186	36.8002	36.3815	35.9626
-140	43.8764	43.4622	43.0478	42.6331	42.2182	41.8030	41.3876	40.9719	40.5559	40.1397
-130	48.0048	47.5930	47.1810	46.7688	46.3563	45.9436	45.5307	45.1175	44.7040	44.2904
-120	52.1098	51.7003	51.2906	50.8806	50.4705	50.0601	49.6495	49.2386	48.8276	48.4163
-110	56.1930	55.7856	55.3780	54.9702	54.5622	54.1540	53.7456	53.3370	52.9281	52.5191
-100	60.2558	59.8504	59.4448	59.0391	58.6331	58.2269	57.8205	57.4139	57.0072	56.6002
-90	64.2996	63.8960	63.4923	63.0884	62.6843	62.2800	61.8756	61.4709	61.0661	60.6611
-80	68.3254	67.9236	67.5217	67.1195	66.7172	66.3147	65.9120	65.5092	65.1062	64.7030
-70	72.3345	71.9344	71.5340	71.1335	70.7328	70.3320	69.9310	69.5299	69.1286	68.7271
-60	76.3278	75.9292	75.5304	75.1315	74.7324	74.3331	73.9337	73.5341	73.1344	72.7346
-50	80.3063	79.9091	79.5117	79.1143	78.7166	78.3189	77.9210	77.5229	77.1247	76.7263
-40	84.2707	83.8748	83.4789	83.0828	82.6865	82.2902	81.8937	81.4970	81.1003	80.7033
-30	88.2217	87.8271	87.4325	87.0377	86.6428	86.2478	85.8526	85.4573	85.0619	84.6663
-20	92.1599	91.7666	91.3732	90.9797	90.5861	90.1923	89.7985	89.4044	89.0103	88.6160
-10	96.0859	95.6938	95.3016	94.9093	94.5169	94.1244	93.7317	93.3390	92.9461	92.5530
0	100.0000	99.6091	99.2181	98.8270	98.4358	98.0444	97.6529	97.2613	96.8696	96.4778

RESISTANCE – TEMPERATURE EQUATIONS

For industrial measurements, the relationship between resistance and temperature can be approximated by the Callendar–Van Dusen equation:

$Rt = Ro \bullet [1 + At + Bt^2 + C(t-100)t^3]$

$A = \alpha(1+\delta/100)$

$B = -\alpha \times \delta \times 10^{-4}$

$C = -\alpha \times \beta \times 10^{-8}$
(= 0 if t >0)

Calibration Coefficients (100Ω Pt, DIN/IEC 60751)	
A	3.9083×10^{-3}
B	-5.775×10^{-7}
C	-4.183×10^{-12}
α	0.003850
δ	1.49990
β	0.10863


R_0 = resistance at t = 0ºC
R_{100} = resistance at t = 100ºC
R_h = resistance at t = t_h (a high temperature – eg: freezing point of tin or zinc)
R_l = resistance at t = t_l (a low temperature – eg: boiling point of oxygen)

(alpha) $\alpha = (R_{100}-R_0) \div 100 \times R_0$ (Temperature coefficient of resistance)


(delta) $\delta = [t_h - (R_h-R_0) \div (R_0 \times \alpha)] \div [(t_h \div 100-1) \times (t_h \div 100)]$ (Callendar constant)

(beta) $\beta = [t_l - \{(R_l-R_0) \div \alpha \times R_0 + \delta \times (t_l \div 100-1) \times (t_l \div 100)\}] \div [(t_l \div 100-1) \times (t_l \div 100)^3]$ (Van Dusen constant)
= 0 (if t>0)


CONNECTION DIAGRAMS




2 Wire




4-Wire, type A




3 Wire




4-Wire, type B




Duplex 2-Wire




1061-CU
3-Pole Plug - Simplex




Duplex 3-Wire




14-0014 Terminal Block
(for HD head – Simplex)



14-0342 Terminal Block
(for GP head – Simplex
Non Spring Loaded)



14-0036 Terminal Block
(for GP head – Duplex)



14-0343-6 Terminal Block
(for GP head – Duplex or
Simplex Spring Loaded)

THERMO KINETICS MEASUREMENT & CONTROL
1-800-268-0967
www.thermo-kinetics.com

Mississauga
(905) 670-2266
Fax (905) 670-8530

Montréal
(514) 856-0370
Fax (514) 856-0373

Québec
(418) 655-6505
Fax (514) 856-0373

Calgary
(403) 252-2522
Fax (403) 252-2778


Edmonton
(780) 448-1580
Fax (780) 463-5164

Vancouver
(604) 231-0711
Fax (604) 270-3644

® Registered Trademark of Thermo-Kinetics Company Limited.
Specifications subject to change without notice.

IPAQ-L

6x
To be mounted in
PCL-900 and PCL-901



Universal Programmable 2-wire Transmitters

IPAQ-L/-LX are universal, isolated 2-wire transmitters for temperature and other measurement applications. They combine competitive pricing, functionality and simple configuration.
Useful error correction functions improve the accuracy.

- Fully universal, linearized and isolated
- Accepts RTD, T/C, mV and Ω
- Sensor error and system (sensor/transmitter) error correction for highest total accuracy
- Full access to all features while in operation
- NAMUR compliant
- Consistent sensor break function
- Simplified loop check-up with calibration output
- Test output without breaking the loop (IPAQ-L)
- IPRO, easy-to-use Windows configuration software


Configured for -50 - 50C

Specifications:


Input RTD		3-, 4-wire connection
Pt100 (α=0.00385)		-200 to +1000 °C / -328 to +1832 °F
Pt1000 (α=0.00385)		-200 to +200 °C / -328 to +392 °F
PtX 10 ≤ X ≤ 1000 (α=0.00385)		Upper range depending on X-value
Pt100 (α=0.003902)		-200 to +1000 °C / -328 to +1832 °F
Pt100 (α=0.003916)		-200 to +1000 °C / -328 to +1832 °F
Ni100[1], Ni120[2]		-60 to +250 °C / -76 to +482 °F
Ni1000[1]		-100 to +150 °C / -148 to +302 °F
Cu10[3]		-200 to +260 °C / -328 to +500 °F
Input Potentiometer/resistance		3-, 4-wire connection. 0 to 2000 Ω
Input Thermocouples		Types B, C, E, J, K, L, N, R, S, T, U
Input mV		-10 to +500 mV
Sensor failure		User definable output
Adjustments-Zero		Any value within range limits
Adjustments-Minimum spans		
Pt100, Pt1000, Ni100, Ni1000		10 °C / 18 °F
Potentiometer		10 Ω
T/C, mV		2 mV
Output		4-20 / 20-4 mA, temperature linear
Operating temperature		-20 to +70 °C / -4 to +158 °F
Galvanic isolation		1500 VAC, 1 min
Power supply	IPAQ-L	7.5 to 36 VDC
	IPAQ-LX	8 to 30 VDC
Intrinsic safety (Mounting in safe area)		
IPAQ-LX ATEX:		II (1) G [EEx ia] IIC
IPAQ-LX FM:		IS Class I-III, DIV 1, GP A-G
IPAQ-LX CSA:		Class I, Groups A-D; Class II, Groups E-G; Class III
Typical accuracy		±0.1 % of span
Mounting		Rail acc. to DIN EN50022, 35 mm

[1] DIN 43760 [2] Edison No. 7 [3] Edison No. 15

Input connections




Output connections




[1] Ri ≤ 10 Ω

Output load diagram



R_{LOAD}=(U-7.5)/0.022 (IPAQ-L)
R_{LOAD}=(U-8)/0.022 (IPAQ-LX)

Dimensions



mm/inches

Ordering information

IPAQ-L	70IPL00001
IPAQ-LX (ATEX)	70IPLX0001
IPAQ-LX (FM, CSA)	70IPLX1001
PC Configuration Kit	70CFG00092
Configuration	70CAL00001

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Jul 20, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-09 (Fixed gas detectors)

Date : 2018-07-20

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Dominic Papineau, Project Manager	E-mail: dpapineau@norclair.ca
Phone : 450-688-4012 # 720	Cell. : 514-409-1832

Information, subcontractor or supplier	
Sub/supplier : Contro-Valve	
Contact : Marc-André Ouellette	Phone : (514) 217-5072

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : Fixed gas detectors	
Drawing reference :	
Specification reference : : **47 30 03**	Division :
Article :	Number of pages : 15

CONSULTANT APPROVAL

Comments within.

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-09

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED

☑ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-JUL-24

BY David Hutchison, P.Eng.

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

ULTIMA® X5000 **Gas Monitor**

The future looks bright.

MSA
The Safety Company


Simple retrofits have identical footprint and wiring to ULTIMA X Gas Monitor series.

Bluetooth® wireless technology allows mobile device to act as HMI screen and controller.

GET IT ON Google Play

Download the X/S Connect App from the Google Play store.

Reduce setup time by at least 50% with the X/S Connect App



Intuitive display features new design equipped with organic LED (OLED) display, with full word text in 9 languages. Bright green, yellow and red status LEDs for extreme visibility.

Industry-first, touch-button interface provides intuitive, tool-free user experience.

Instrument status indicators illuminate power, fault and alarm conditions.

Advanced Sensor Technology

POWERED BY XCell® SENSORS

WITH TruCal®

- Patented XCell Sensors with TruCal technology extend calibration cycles for as long as 18 months, actively monitor sensor integrity and compensate for environmental factors and electrochemical sensor drift.*
- Worry-free operation; automatically self-checks four times per day.
- Three-year warranty and five-year expected life for XCell Sensors.
- **SafeSwap** enables safe and quick XCell Sensor replacement without powering off gas detector.
- **Dual sensor capability** doubles sensing power with half the footprint of a single gas sensor transmitter.

SafeSwap®

Ranges to be:
0 - 100 ppm H2S
0 - 100% LEL



*Only CO & H_2S XCell Sensors

Applications

- Chemical
- Oil and gas
- Petrochemical
- Utilities
- Wastewater
- General industry

Ultima5000 (XP cl 1 div 2), H2S & LEL
AIT-01-901 w/ AE-01-901A & AE-01-902B
AIT-01-902 w/ AE-01-902A & AE-01-902B
AIT-01-903 w/ AE-01-903A & AE-01-903B
AIT-01-904 w/ AE-01-904A & AE-01-904B

ULTIMA® X5000 **Gas Monitor**


MSA
The Safety Company

PRODUCT SPECIFICATIONS			
COMBUSTIBLE GAS SENSOR TYPE	Catalytic Bead (XCell Comb) Infrared (XIR PLUS)		
TOXIC GAS & OXYGEN SENSOR TYPE	Carbon Dioxide CO_2 (XIR PLUS) Carbon Monoxide CO (XCell Toxic) Carbon Monoxide CO H_2-Resistant (XCell Toxic) Hydrogen Sulfide H_2S (XCell Toxic) Oxygen O_2 (XCell O_2)		
SENSOR MEASURING RANGES	Combustible: 0-100% LEL H_2S: 0-10, 0-50, 0-100 ppm CO_2: 0-2%, 0-5% Vol CO: 0-100, 0-500, 0-1000 ppm CO-H_2 Resist: 0-100 ppm O_2: 0-25%		
TYPICAL SENSOR LIFE	5 years – XCell Sensors 10 years - infrared		
SENSOR PERFORMANCE*	**T90 (TYPICAL)**	**REPEATABILITY**	**ZERO DRIFT (PER YEAR)**
XIR PLUS	<2 sec.	+/- 1% LEL or Vol	<2% full scale
XCELL COMB	<30 sec.	+/- 1% LEL	<5% LEL
XCELL H_2S	<23 sec.	+/- 3%	<1% full scale
XCELL O_2	<11 sec.	+/- 0.1% Vol	0.2% Vol
XCELL CO	<11 sec.	+/- 3%	<1% full scale
APPROVALS CLASSIFICATION	**US Divisions** Class I Div 1 Groups A-D, T5, Type 4X, IP66 Class II Div 1 Groups E-G, T6; Class III **US Zones** Class I Zone 1 AEx db IIC T5 Gb Class II Zone 21 AEx tb IIIC T85°C Db **Global Zones** Ex db IIC T5 Gb Ex tb IIIC T85°C Db		
WARRANTY	X5000 Transmitter: 2 years XIR PLUS: 10 years source, 5 years electronics XCell Sensors: 3 years		
APPROVALS	CSA, ATEX, IECEx, CE Marking. Complies with C22.2 No. 152, FM 6320 RED, FCC Suitable for SIL 2		
ENVIRONMENTAL SPECIFICATIONS			
OPERATING TEMPERATURE RANGE	XCell: -40°C to +60°C XIR PLUS: -40°C to +60°C *(may differ by gas, see manual)*		
STORAGE TEMPERATURE RANGE	-40°C to +60°C		
RELATIVE HUMIDITY (NON-CONDENSING)	10-95% (XCell Toxics & O_2) 0-95% (XCell Comb) 0-95% (XIR PLUS)		

** Typical response at standard temperature and pressure test conditions*

MECHANICAL SPECIFICATIONS		
INPUT POWER	10 to 30 VDC, 3 wire, <5W nominal	
SIGNAL OUTPUT	Dual 4-20 mA current source, HART	
BLUETOOTH (OPTIONAL)	Bluetooth Low Energy (BLE) v4.3 or higher	
RELAY RATINGS	5A @ 30VDC; 5A @220 VAC (3X) SPDT – fault, warn, alarm	
RELAY MODES	Common, discrete, horn	
NOMINAL MAX POWER (W/ RELAYS)	XIR PLUS XCell Comb XCell Toxic & O_2 XIR PLUS and XCell Comb XIR PLUS and XCell Toxic & O_2 Dual XIR PLUS Dual XCell Toxic & O_2 Dual XCell Comb Dual XCell Comb and XCell Toxic & O_2	6.7W 5.5W 2.8W 9.6W 7.0W 11.6W 3.6W 10.6W 5.5W
EMC DIRECTIVE	Complies with EN 50270, EN 61000-6-4, EN 61000-6-3	
DISPLAY	Organic LED (multi-lingual) with Contrast Ratio of 2000:1 and View Angle of 160°	
HART	HART 7, HART device description language available	
FAULTS MONITORED	Low supply voltage, RAM checksum error, flash checksum error, EEPROM error, internal circuit error, relay, invalid sensor configuration, sensor faults, calibration faults, general system	
WIRING REQUIREMENTS	3-wire (single sensor) or 4-wire (dual sensor) shielded cable. *Refer to manual for mounting distances and wire gauge.*	

DIMENSIONS



Note: This Bulletin contains only a general description of the products shown. While uses and performance capabilities are described, under no circumstances shall the products be used by untrained or unqualified individuals and not until the product instructions including any warnings or cautions provided have been thoroughly read and understood. Only they contain the complete and detailed information concerning proper use and care of these products. Specifications subject to change without notice.

Corporate Headquarters:
MSA – The Safety Company
1000 Cranberry Woods Drive
Cranberry Township, PA 16066
United States
+1-724-776-8600
info.us@MSAsafety.com

Additional locations can be found on our web site:
www.MSAsafety.com

ID 0720-185-MC / Feb 2018

© MSA 2017 Printed in U.S.A.

A - X5000 - ⬭ - ⬭ - ⬭ - ⬭ - ⬭ - ⬭ - ⬭ - ⬭

Material
0 = Stainless Steel - 3/4" NPT
2 = Stainless Steel - M25

Approvals
F = FM/CSA
A = ATEX/IEC

Bluetooth
0 = Yes
1 = No

Outputs
0 = Analog/HART
1 = Analog/HART/Relays


Place Holder
0 = Future Use

Sensor #1
Check Sensor Label
See Read First


Sensor #2
Check Sensor Label
See Read First

Tag
0 = None
1 = Stainless Steel affixed tag


Read First



EXAMPLE SENSOR ATO LABEL





MOUNTING BRACKET
(REQUIRED FOR XIR PLUS SENSORS)
(PART NUMBER 10179361)




MAIN BOARD WITHOUT RELAYS


CUSTOMER	
P.O. NO.	
MSA NO.	
LOCATION	
TAG NO.	
TOTAL NO. OF UNITS	








SHORT LID
(USED FOR MAIN BOARD WITHOUT RELAYS OR JUNCTION BOX BOARD)



DEEP LID
(USED FOR MAIN BOARD WITH RELAYS)



NOTES:
1. DIMENSIONS SHOWN ARE IN INCHES [MILLIMETERS]
2. MAIN HOUSING AND REMOTE JUNCTION BOX HAVE THE SAME DIMENSIONS.

REVISIONS

D	9-4-2017 ADDED SHT FOR REVISED WIRE LENGTH TABLES & PICTORIALS C:#8000000021543	
LRB		JD

DIRECTED DATA: **Production** REVISION: **1**

www.MSAsafety.com
THIS DRAWING IS THE PROPERTY OF MSA - THE SAFETY COMPANY AND IS MADE AVAILABLE TO YOU IN CONFIDENCE AND SUBJECT TO THE FOLLOWING: NO PERMISSION IS GRANTED TO PUBLISH, USE, REPRODUCE, TRANSMIT OR DISCLOSE THIS DRAWING OR ANY PART OF IT IN ANY FORM OR BY ANY MEANS, OTHER THAN WITH THE PRIOR WRITTEN CONSENT OF MSA - THE SAFETY COMPANY. THIS DRAWING IS NOT TO BE USED FOR THE MANUFACTURE OF ARTICLES FOR MSA - THE SAFETY COMPANY.

MSA STANDARD SHOP PRACTICES APPLY

THIRD ANGLE PROJECTION


DO NOT SCALE DWG.


DRAWN BY	DATE	JOB NO. 3001299& PH0705	APPROVAL AGENCY CODE: NIOSH ATR. DOC.:
W.JE	9-29-2016		
CHECKED BY			
C.STARTA	3-28-2017		
PROJECT ENGR.			
N.CICCONE	3-28-2017		
QUALITY ASSURANCE			
J.DANNHARDT	3-28-2017		
MANUFACTURING			
M.JRINSAK	3-28-2017		


INSTALLATION OUTLINE, ULTIMA X5000

CADD REF: SK3015-1051 SCALE: 1:2

SHEET SIZE **D** **SK3015-1051** SHEET 1 OF 4








IT IS RECOMMEND TO USE BRAIDED SHIELDED CABLE. THE SHIELD SHOULD BE TERMINATED 360° INTERNAL TO THE MAIN HOUSING AS SHOWN.

FOR DUAL REMOTED CONFIGURATIONS, TERMINATE THE BRAIDED SHIELD AT THE ADDITIONAL CLIPS IN THE MAIN HOUSING.

ALL BRAIDED SHIELD CABLES SHOULD BE TERMINATED ONLY IN THE MAIN TRANSMITTER HOUSING LOCATION



REVISIONS
REV. 1

DOCUMENT STATUS	REVISION
Production	1

MSA The Safety Company www.MSAsafety.com
MSA STANDARD SHOP PRACTICES APPLY
THIS DRAWING IS THE PROPERTY OF MSA - THE SAFETY COMPANY AND IS MADE AVAILABLE TO YOU IN CONFIDENCE AND SUBJECT TO THE FOLLOWING: NO PERMISSION IS GRANTED TO PUBLISH, USE, REPRODUCE, TRANSMIT OR DISCLOSE THE CONTENTS OF THIS DRAWING TO ANY THIRD PARTY WHATSOEVER WITHOUT THE PRIOR WRITTEN CONSENT OF MSA - THE SAFETY COMPANY EXCEPT FOR THE MANUFACTURE OF ARTICLES FOR MSA - THE SAFETY COMPANY.

THIRD ANGLE PROJECTION

DO NOT SCALE DWG.

DRAWN BY	DATE	JOB NO. 30012996 PH0705
W.JE	9-29-2016	APPROVAL AGENCY CODE: NIOSH ATR. DOC.:
CHECKED BY		
C.STARTA	3-28-2017	
PROJECT ENGR.		
N.CICCONE	3-28-2017	
QUALITY ASSURANCE		
J.DANNHARDT	3-28-2017	
MANUFACTURING		
M.JERNSAK	3-28-2017	

INSTALLATION OUTLINE, ULTIMA X5000

CADD REF: SK3015-1051 SCALE: 1:2

SHEET SIZE D

SK3015-1051

SHEET 2 OF 4




TABLE 1

MAXIMUM WIRE LENGTH TO MAIN TRANSMITTER WITH SINGLE SENSOR

Sensor Mounting	Sensor 1	Max Power (W)	Max Distance (FT) To Transmitter			
			24 VDC Supply			
			18 AWG	16 AWG	14 AWG	12 AWG
MOUNTED ON TRANSMITTER	Echem	2.8	2211	3337	5314	8440
	Catalytic	5.5	1548	2335	3719	5907
	XIR Plus	6.7	1184	1787	2846	4520
REMOTE MOUNTED ON JUNCTION BOX (UP TO 328 ft)	Echem	2.8	2210	3335	5313	8439
	Catalytic	5.5	1504	2294	3679	5867
	XIR Plus	6.7	1090	1697	2759	4435




TABLE 2

MAXIMUM WIRE LENGTH TO MAIN TRANSMITTER WITH 2 SENSORS

Sensor Mounting	Sensor 1	Sensor 2	Max Power (W)	Max Distance (FT) To Transmitter			
				24 VDC Supply			
				18 AWG	16 AWG	14 AWG	12 AWG
TWO SENSORS Mounted on Transmitter	Echem	Echem	3.6	2078	3136	4994	7932
		Catalytic	5.3	1473	2223	3541	5623
		XIR Plus	7.0	1076	1623	2585	4106
	Catalytic	Echem	5.3	1473	2223	3541	5623
		Catalytic	10.6	1151	1736	2765	4392
		XIR Plus	10.9	893	1347	2146	3408
	XIR Plus	Echem	7.0	1076	1623	2585	4106
		Catalytic	10.9	893	1347	2146	3408
		XIR Plus	11.6	* Limit sensor must be remote mounted if using two XIR Plus sensors			
ONE SENSOR mounted on junction box (328 ft Max), ONE SENSOR on transmitter	Echem	Echem	3.6	2096	3154	5012	7952
		Catalytic	5.3	1441	2193	3512	5596
		XIR Plus	7.0	982	1536	2501	4024
	Catalytic	Echem	5.3	1441	2193	3512	5596
		Catalytic	10.6	1124	1711	2741	4368
		XIR Plus	10.9	763	1225	2029	3295
	XIR Plus	Echem	7.0	982	1536	2501	4024
		Catalytic	10.9	763	1225	2029	3295
		XIR Plus	11.6	731	1135	1843	2961




TABLE 3

MAXIMUM WIRE LENGTH TO MAIN TRANSMITTER WITH 2 REMOTED SENSORS

Sensor Mounting	Sensor 1	Sensor 2	Max Power (W)	Max Distance (FT) To Transmitter			
				24 VDC Supply			
				18 AWG	16 AWG	14 AWG	12 AWG
TWO SENSORS mounted on junction box up to 328ft for 24V	Echem	Echem	2.8	2079	3134	4992	7932
		Catalytic	5.3	1421	2173	3492	5576
		XIR Plus	7.0	962	1516	2481	4004
	Catalytic	Echem	5.3	1421	2173	3492	5576
		Catalytic	10.6	1104	1691	2721	4348
		XIR Plus	10.9	743	1205	2009	3275
	XIR Plus	Echem	7.0	962	1516	2481	4004
		Catalytic	10.9	743	1205	2009	3275
		XIR Plus	11.6	711	1115	1823	2941

NOTES:

1. WHEN SIZING A SYSTEM'S 24V SUPPLY, A 1 AMP INRUSH CURRENT WITH A 1ms DURATION SHOULD BE CONSIDERED FOR EACH ULTIMA X5000 ON THE POWER SUPPLY

REVISIONS

REV. 1

DOCUMENT STATUS: Production — REVISION: 1

MSA The Safety Company — www.MSAsafety.com

MSA STANDARD SHOP PRACTICES APPLY


THIS DRAWING IS THE PROPERTY OF MSA - THE SAFETY COMPANY AND IS MADE AVAILABLE TO YOU IN CONFIDENCE AND SUBJECT TO THE FOLLOWING: NO PERMISSION IS GRANTED TO PUBLISH, USE, REPRODUCE, TRANSMIT OR DISCLOSE THIS DRAWING OR THE INFORMATION CONTAINED THEREIN TO OTHERS WITHOUT THE PRIOR WRITTEN CONSENT OF MSA - THE SAFETY COMPANY EXCEPT FOR THE MANUFACTURE OF ARTICLES FOR MSA - THE SAFETY COMPANY.

THIRD ANGLE PROJECTION — DO NOT SCALE DWG.

JOB NO. 50012996 PHD705 | APPROVAL AGENCY CODE: | NIOSH ATR. DOC.:

DRAWN BY W.JE 9-29-2016	INSTALLATION OUTLINE, ULTIMA X5000
CHECKED BY C.STARTA 3-28-2017	
PROJECT ENGR. N.CICCONE 3-28-2017	
QUALITY ASSURANCE J.DANNHARDT 3-28-2017	
MANUFACTURING M.ZIRHSAK 3-28-2017	CADD REF: N/A — SCALE: 1:1

SHEET SIZE: D — SK3015-1051 — SHEET 3 OF 4



REVISIONS
REV. 1

DRAWING STATUS: Production	REVISION: 1

MSA The Safety Company — www.MSAsafety.com

MSA STANDARD SHOP PRACTICES APPLY

THIS DRAWING IS THE PROPERTY OF MSA - THE SAFETY COMPANY AND IS MADE AVAILABLE TO YOU IN CONFIDENCE AND SUBJECT TO THE FOLLOWING: NO PERMISSION IS GRANTED TO PUBLISH, USE, REPRODUCE, TRANSMIT OR DISCLOSE THIS DRAWING OR THE INFORMATION CONTAINED THEREIN, NOR MAY ANYTHING BE MADE FROM WRITTEN CONSENT OF MSA - THE SAFETY COMPANY EXCEPT FOR THE MANUFACTURE OF ARTICLES FOR MSA - THE SAFETY COMPANY.

THIRD ANGLE PROJECTION

DO NOT SCALE DWG.

JOB NO. 50012996 PH0705 | APPROVAL AGENCY CODE: | NIOSH ATTR. DOC.:

	DRAWN BY	DATE
	W.JE	9-29-2016
	CHECKED BY	
	C.STARTA	3-28-2017
	PROJECT ENGR.	
	N.CICCONE	3-28-2017
	QUALITY ASSURANCE	
	J.DANNHARDT	3-28-2017
	MANUFACTURING	
	M.JIRHSAK	3-28-2017

INSTALLATION OUTLINE, ULTIMA X5000

CADD REF: N/A | SCALE: 1:2

SHEET SIZE: D | SK3015-1051 | SHEET 4 OF 4

TRIGARD® **Monitoring System**

for Oxygen, Toxics and Combustible Gases

Trigard (non-XP)

_

CO:

AIT-02-801 w/ AE-02-801

_

H2S:

AIT-02-905 w/ AE-02-905

AIT-02-907 w/ AE-02-907

AIT-02-908 w/ AE-02-908

AIT-02-909 w/ AE-02-909

AIT-03-906 w/ AE-03-906

AIT-03-910 w/ AE-03-910

The MSA TRIGARD Monitoring System is designed for monitoring toxic gases; combustible gases; and oxygen deficiency or enrichment. It is an affordable monitoring solution for a variety of applications, including water and wastewater plants, lab space, boiler rooms, commercial and general industry.



TRIGARD® Monitoring System for Oxygen, Toxics and Combustible Gases Features

- Stand-alone gas monitor for up to three MSA sensors
- Adjustable range
- Multiple sensor mounting options
- AC- or DC-powered
- On-board relays
- NEMA 4X design
- LCD display with highly visible LED indicators
- Piezo horn with horn silence button
- Long-life, MSA-designed sensors
- Simple push-button calibration
- Available as single-point or 3-point unit
- Optional battery backup

Because every life has a ***purpose...***

Advanced Features

- **Sensor Disconnect Under Power**
  - MSA's patented feature allows for sensor change-out without declassifying a hazardous area.
- **Interchangeable Smart Sensors**
  - Pre-calibrated sensor modules are ready for installation out of the box. Sensors can be replaced in the field without the use of tools. The unit quickly recognizes the new sensor type and reconfigures alarm and relay settings to optimize the new sensor.
- **State-of-the-Art Display**
  - Liquid crystal display conveniently alternates between sensor reading and gas type, and features scrolling messaging, indicating ongoing diagnostic checks such as sensor "end-of-life" condition.
- **World-Class Design**
  - Features a single-board design for high reliability and easier serviceability.
  - Mounting enclosure is separate from the electronics and sensor, enabling problem-free installation and servicing.
- **Onboard LEDs and Relays**
  - "Quick-check" LEDs and four relay outputs allow for increased indication of alarm and fault conditions.
  - "Quick-check" LEDs, viewable from up to 50 feet, indicate NORMAL (green) and ALERT (red) status conditions.
  - Field-program-mable alarm levels and normally energized/de-energized, normally opened/closed and latching/non-latching relay functions offer three levels of alarm and a fault.
- **Options**
  - One or two strobes
  - Back-up battery
  - Internal power supply
- **Sensor Options**
  - Oxygen, toxic and combustible sensors
  - Integral mounting
  - Remote General Purpose
  - Remote Explosion Proof
  - Pre-wired shielded cable for sensors in 25, 50 and 100 ft. lengths (oxygen & toxic only)

Specifications	
GAS TYPE	Toxic, oxygen and combustible (catalytic bead or infrared)
GAS SAMPLING	Diffusion
OUTPUT TYPE	1 sensor: 4-20 mA, 3-wire or ModBus RTU; 2 or 3 sensors: ModBus RTU only
SENSOR LOCATION	Local or remote sensor (up to 100 ft.)
ENCLOSURE	General-purpose polycarbonate enclosure
SENSOR TEMPERATURE RANGE	14˚F to 104˚F (typical)
ACCURACY	Repeatability +1% FS (typical)
SENSOR LIFE	18 months to 2 years
RELAYS	5 Amp SPDT; 4 relays (3 alarm, 1 fault) @220 VAC or 30 VDC
POWER INPUT	12-30 VDC (standard), 100-256 VAC (optional)
ALARM TYPE	Piezo horn (95 dB) with horn silence button
BATTERY BACKUP	Optional (1,200 mAh)
ENVIRONMENTAL PROTECTION	Designed to meet NEMA 4X





Factory-assembled remote sensors are available in 25-, 50- and 100-foot lengths.

Note: This bulletin contains only a general description of the products shown. While uses and performance capabilities are described, under no circumstances shall the products be used by untrained or unqualified individuals and not until the product instructions including any warnings or cautions provided have been thoroughly read and understood. Only they contain the complete and detailed information concerning proper use and care of these products.

ID 07-2109-MC / September 2014
© MSA 2014 Printed in U.S.A.

MSA – The Safety Company
1000 Cranberry Woods Drive,
Cranberry Township, PA 16066 USA
Phone 724-776-8600
www.MSAsafety.com

U.S. Customer Service Center
Phone 1-800-MSA-INST
Fax 1-800-967-0398


MSA Canada
Phone 1-800-672-2222
Fax 1-800-967-0398


MSA Mexico
Phone 01 800 672 7222
Fax 52-44 2227 3943


MSA International
Phone 724-776-8626
Toll Free 1-800-672-7777
Fax 724-741-1559
Email msa.international@msasafety.com


A - TRIGARD - 1 - 2 - 3 - 4 - 5 - 6 - 7 - 8 - 9 - 10 - 11 - 12 - 13

1	2	3	4	5	6	7	8	9	10	11	12	13
Model Type A = MSA 4X	Sensor Output M=MODBUS R=MILLIAMP OUTPUT 4-20, 3 WIRE	Power Supply Options 0=None 1=Internal 100-240 VAC/90 VDC	Battery Backup 0=None B=Battery Installed	Sensor 1 Station Check Sensor Label	Sensor 1 Option 0=External 1=10' Cable 2=25' Cable 3=100' Cable 4=2M3 (Channel Purpose Remote) 5=XX (Explosion Proof Remote)	Sensor 2 Station Check Sensor Label	Sensor 2 Option 0=External 1=10' Cable 2=25' Cable 3=100' Cable 4=2M3 (Channel Purpose Remote) 5=XX (Explosion Proof Remote)	Sensor 3 Station Check Sensor Label	Sensor 3 Option 0=External 1=10' Cable 2=25' Cable 3=100' Cable 4=2M3 (Channel Purpose Remote) 5=XX (Explosion Proof Remote)	Strobes 0=None 1=Red 2=Red and Amber	Enclosure Hardware 0=None 1=Sun Shield with Mounting Bracket 2=Mounting Bracket	Custom Features 0=None 1=Custom Operations Necessary









NOTE:
1. INSTRUMENT HOUSING IS MADE OF POLYCARBONATE PLASTIC.
2. DIMENSIONS SHOWN IN INCHES [MILLIMETERS].
3. SENSOR INLET MUST FACE DOWN.
4. OPTION ONLY AVAILABLE ON MODBUS OUTPUT UNITS.
5. ONLY AVAIABLE ON UNITS WITH INTERNAL AC POWER SUPPLY.
6. ONLY ON UNITS WITHOUT AC POWER CORD OPTION.
7. ONLY ON UNITS WITHOUT RED OR AMBER STROBES.
8. INSTRUMENT IS FOR USE IN NON-HAZARDOUS AREAS ONLY.
9. FOR "RG" OR "RX" SENSORS, WIRE NOT PROVIDED.
10. BATTERY LIFE 24 HOURS (MAX) WITH UP TO 3 ELECTROCHEMICAL SENSORS.
11. CONNECT BATTERY (+) LEAD PRIOR TO OPERATION.
12. DISCONNECT BATTERY (+) LEAD TO SHUT DOWN.
13. ALLOW SYSTEM TO CHARGE FOR 24 HOURS BEFORE USING.
14. ALARM RELAYS RATED: 5 AMPS @ 125 VAC (NON-INDUCTIVE), 5 AMPS @ 30 VDC (NON-INDUCTIVE).

REVISIONS		
1	12-18-2008	INITIAL RELEASE EXTENSIVELY REVISED
GJT		ST
JAN 30 2009		

CUSTOMER _____
P.O. NO. _____
MSA NO. _____
LOCATION _____
TAG NO. _____
TOTAL NO. OF UNITS _____

AUTHORIZED COUNTRY

MSA — MINE SAFETY APPLIANCES CO., PITTSBURGH, PA 15230, USA

MSA STANDARD SHOP PRACTICES APPLY

THIS DRAWING IS THE PROPERTY OF MSA AND IS MADE AVAILABLE TO YOU IN CONFIDENCE AND SUBJECT TO THE FOLLOWING: NO PERMISSION IS GRANTED TO PUBLISH, USE, REPRODUCE, TRANSMIT OR DISCLOSE THIS DRAWING, OR ANY INFORMATION CONTAINED THEREIN TO OTHERS WITHOUT THE PRIOR WRITTEN CONSENT OF MSA EXCEPT FOR THE MANUFACTURE OF ARTICLES FOR MSA SCHUTZWERKE NACH DIN 34 BEACHTEN. MSA AUER GmbH.

DO NOT SCALE DRG.

CODE SYMBOLS
CRITICAL ⚠
MAJOR A ⚠ MINOR (NO MARK)
MAJOR B ⚠
100 % INSPECTION ⚠


TOLERANCES UNLESS OTHERWISE SPECIFIED
FRACTIONAL ± 1/64
2 PL DEC. ± 0.01
3 PL DEC. ± 0.005
ANGULAR ± 1 deg.
SEE MSA STANDARD SHOP PRACTICES FOR DRILLED HOLE TOLERANCES

JOB NO.	30010260 PH0729	APPROVAL AGENCY CODE: NO | NIOSH ATTR. DOC.: .
DRAWN BY	DATE	
GJT	12-12-2005	
CHECKED BY		
M.BRADLEY	1-29-09	
PROJ. ENGR.		
S.TURNER	1-29-09	
QUALITY ASSURANCE		
J.DANNHARDT	1-29-09	
MANUFACTURING		
J.BRYER	1-29-09	


INSTALLATION OUTLINE, TRIGARD

CADD REF: SK3015-1032 | SCALE: 1.000

D. | SK3015-1032 | SHEET 1 OF 7



SUN SHIELD (OPTIONAL)
(NOT AVAILABLE WITH STROBE OPTIONS)



MOUNTING BRACKET (OPTIONAL)

REVISIONS
REV. 1
JAN 30 2009

AUTHORIZED COUNTRY

MSA
MSA STANDARD SHOP PRACTICES APPLY

MINE SAFETY APPLIANCES CO.
PITTSBURGH, PA 15230, USA

THIS DRAWING IS THE PROPERTY OF MSA AND IS MADE AVAILABLE TO YOU IN CONFIDENCE AND SUBJECT TO THE FOLLOWING: NO PERMISSION IS GRANTED TO PUBLISH, USE, REPRODUCE, TRANSMIT OR DISCLOSE THIS DRAWING, OR ANY INFORMATION CONTAINED THEREIN TO OTHERS WITHOUT THE PRIOR WRITTEN CONSENT OF MSA EXCEPT FOR THE MANUFACTURE OF ARTICLES FOR MSA SCHUTZVERMERK NACH DIN 34 BEACHTEN. MSA AUER GmbH.

DO NOT SCALE DRG.

CODE SYMBOLS
CRITICAL ⚠
MAJOR A ⚠ MINOR (NO MARK)
MAJOR B ⚠
100 % INSPECTION ⚠

TOLERANCES UNLESS OTHERWISE SPECIFIED
FRACTIONAL ± 1/64
2 PL DEC. ± 0.01
3 PL DEC. ± 0.005
ANGULAR ± 1 deg.
REF. MSA STANDARD SHOP PRACTICES FOR DRILLED HOLE TOLERANCES


JOB NO. 30010260 PH0729
DRAWN BY — DATE
GJT 12-12-2005
CHECKED BY
M.BRADLEY 1-29-09
PROJ. ENGR.
S.TURNER 1-29-09
QUALITY ASSURANCE
J.DANNHARDT 1-29-09
MANUFACTURING
J.BRYER 1-29-09

APPROVAL AGENCY CODE: NO | NIOSH ATTR. DOC.: .


INSTALLATION OUTLINE, TRIGARD

CADD REF: SK3015-1032
SCALE: 1.000


D.
SK3015-1032
SHEET 2 OF 7




EXPLOSION PROOF XE REMOTE
(RX OPTION)




XE REMOTE WITH OPTIONAL MOUNTING BRACKET
MOUNTING BRACKET PART NUMBER 10047562



EXPLOSION PROOF XIR REMOTE
(RX OPTION)
XIr SENSOR MUST BE MOUNTED AS SHOWN



GENERAL PURPOSE XA REMOTE
(RG OPTION)
SEE NOTE 8




XA REMOTE WITH OPTIONAL MOUNTING BRACKET
MOUNTING BRACKET PART NUMBER 10047561

NOTES:(Continued)
15. CHECK TAG FOR AREA CLASSIFICATION.


REVISIONS
REV. 1
JAN 30 2009

AUTHORIZED COUNTRY	MSA — MINE SAFETY APPLIANCES CO., PITTSBURGH, PA 15230, USA	THIS DRAWING IS THE PROPERTY OF MSA AND IS MADE AVAILABLE TO YOU IN CONFIDENCE AND SUBJECT TO THE FOLLOWING: NO PERMISSION IS GRANTED TO PUBLISH, USE, REPRODUCE, TRANSMIT OR DISCLOSE THIS DRAWING, OR ANY INFORMATION CONTAINED THEREIN TO OTHERS WITHOUT THE PRIOR WRITTEN CONSENT OF MSA EXCEPT FOR THE MANUFACTURE OF ARTICLES FOR MSA SCHUTZWERKE NACH DIN 34 BEACHTEN. MSA AUER GmbH.	DO NOT SCALE DRG.
	MSA STANDARD SHOP PRACTICES APPLY	JOB NO. 30010260 PH0729	APPROVAL AGENCY CODE: NO [NIOSH ATTR. DOC.: .
	CODE SYMBOLS	DRAWN BY GJT 12-12-2005	INSTALLATION OUTLINE, TRIGARD
	CRITICAL ⚠ MAJOR A ⚠ MINOR (NO MARK) MAJOR B ⚠ 100 % INSPECTION ⚠	CHECKED BY M.BRADLEY 1-29-09	
		PROJ. ENGR. S.TURNER 1-29-09	
	TOLERANCES UNLESS OTHERWISE SPECIFIED	QUALITY ASSURANCE J.DANNHARDT 1-29-09	
	FRACTIONAL ± 1/64	MANUFACTURING J.BRYER 1-29-09	CADD REF: SK3015-1032 — SCALE: 1.000
	2 PL DEC. ± 0.01		
	3 PL DEC. ± 0.005		
	ANGULAR ± 1 deg.	D.	SK3015-1032 — SHEET 3 OF 7
	SEE MSA STANDARD SHOP PRACTICES FOR DRILLED HOLE TOLERANCES		


REVISIONS
REV. 1
JAN 30 2009




TRIGARD SHOWN WITH 25', 50' AND 100' SENSOR OPTIONS



TRIGARD SHOWN WITH "RG" AND "RX" SENSOR OPTIONS
(SEE NOTE 18)




XE/XIR COMBUSTIBLE SENSORS



NOTES:(Continued)
16. - - - - - INDICATES FIELD CONNECTIONS BY OTHERS.
17. CABLE GLANDS SUPPLIED WITH 25', 50' AND 100' SENSOR OPTIONS ONLY.
18. REMOTE WIRING DISTANCE IS 100 FT. [30.48 METERS] MAX.

AUTHORIZED COUNTRY	MSA	MINE SAFETY APPLIANCES CO. PITTSBURGH, PA 15230, USA	THIS DRAWING IS THE PROPERTY OF MSA AND IS MADE AVAILABLE TO YOU IN CONFIDENCE AND SUBJECT TO THE FOLLOWING: NO PERMISSION IS GRANTED TO PUBLISH, USE, REPRODUCE, TRANSMIT OR DISCLOSE THIS DRAWING, OR ANY INFORMATION CONTAINED THEREIN TO OTHERS WITHOUT THE PRIOR WRITTEN CONSENT OF MSA EXCEPT FOR THE MANUFACTURE OF ARTICLES FOR MSA SCHUTZVERMERK NACH DIN 34 BEACHTEN. MSA AUER GmbH.
	MSA STANDARD SHOP PRACTICES APPLY		DO NOT SCALE DRG.
	CODE SYMBOLS	JOB NO. 30010260 PH0729	APPROVAL AGENCY CODE: NO | NIOSH ATTR. DOC.: .
	CRITICAL ⚠	DRAWN BY DATE GJT 12-12-2005	
	MAJOR A ⚠ MINOR (NO MARK)	CHECKED BY M.BRADLEY 1-29-09	INSTALLATION OUTLINE, TRIGARD
	MAJOR B ⚠	PROJ. ENGR. S.TURNER 1-29-09	
	100 % INSPECTION ⚠	QUALITY ASSURANCE J.DANNHARDT 1-29-09	
	TOLERANCES UNLESS OTHERWISE SPECIFIED	MANUFACTURING J.BRYER 1-29-09	CADD REF: SK3015-1032 SCALE: 1.000
	FRACTIONAL ± 1/64		
	2 PL DEC. ± 0.01		
	3 PL DEC. ± 0.005		
	ANGULAR ± 1 deg.		
	REF. MSA STANDARD SHOP PRACTICES FOR DRILLED HOLE TOLERANCES	D.	SK3015-1032 SHEET 4 OF 7

REVISIONS
REV. 1
JAN 30 2009




Milliamp P.C. BOARD ASSEMBLY SHOWN

XE/XIR COMBUSTIBLE SENSORS

COLOR CODE			
BLACK	= K	GREEN	= G
BROWN	= N	BLUE	= B
RED	= R	VIOLET	= V
ORANGE	= O	GRAY	= A
YELLOW	= Y	WHITE	= W
PINK	= P	TAN	= T

AUTHORIZED COUNTRY	MSA	MINE SAFETY APPLIANCES CO. PITTSBURGH, PA 15230, USA	THIS DRAWING IS THE PROPERTY OF MSA AND IS MADE AVAILABLE TO YOU IN CONFIDENCE AND SUBJECT TO THE FOLLOWING: NO PERMISSION IS GRANTED TO PUBLISH, USE, REPRODUCE, TRANSMIT OR DISCLOSE THIS DRAWING, OR ANY INFORMATION CONTAINED THEREIN TO OTHERS WITHOUT THE PRIOR WRITTEN CONSENT OF MSA EXCEPT FOR THE MANUFACTURE OF ARTICLES FOR MSA SCHUTZVERMERK NACH DIN 34 BEACHTEN. MSA AUER GmbH.
	MSA STANDARD SHOP PRACTICES APPLY		DO NOT SCALE DRG.
	CODE SYMBOLS: CRITICAL ⚠, MAJOR A ⚠, MAJOR B ⚠, 100 % INSPECTION ⚠, MINOR (NO MARK)	JOB NO. 30010260 PH0729	APPROVAL AGENCY CODE: NO | NIOSH ATTR. DOC.: .
		DRAWN BY / DATE: GJT 12-12-2005	INSTALLATION OUTLINE, TRIGARD
		CHECKED BY: M.BRADLEY 1-29-09	
		PROJ. ENGR.: S.TURNER 1-29-09	
	TOLERANCES UNLESS OTHERWISE SPECIFIED: FRACTIONAL ± 1/64; 2 PL DEC. ± 0.01; 3 PL DEC. ± 0.005; ANGULAR ± 1 deg.	QUALITY ASSURANCE: J.DANNHARDT 1-29-09	
	REF. MSA STANDARD SHOP PRACTICES FOR DRILLED HOLE TOLERANCES	MANUFACTURING: J.BRYER 1-29-09	CADD REF: SK3015-1032 | SCALE: 1.000
		D.	SK3015-1032 | SHEET 6 OF 7

REVISIONS
REV. 1
JAN 30 2009



NOTES:(Continued)

18. BATTERY BACKUP RUNTIME VARIES WITH TEMPERATURE, SENSOR CONFIGURATION AND BATTERY CONDITION. RUNTIME WITH 1 TOXIC SENSOR IS 24 HOURS MINIMUM AT ROOM TEMPERATURE. RUNTIME WITH 2 COMBUSTIBLE XIR UNITS AND 1 TOXIC SENSOR IS 20 MINUTES MINIMUM AT ROOM TEMPERATURE.

COLOR CODE			
BLACK	= K	GREEN	= G
BROWN	= N	BLUE	= B
RED	= R	VIOLET	= V
ORANGE	= O	GRAY	= A
YELLOW	= Y	WHITE	= W
PINK	= P	TAN	= T

AUTHORIZED COUNTRY

MSA — MINE SAFETY APPLIANCES CO., PITTSBURGH, PA 15230, USA

MSA STANDARD SHOP PRACTICES APPLY

THIS DRAWING IS THE PROPERTY OF MSA AND IS MADE AVAILABLE TO YOU IN CONFIDENCE AND SUBJECT TO THE FOLLOWING: NO PERMISSION IS GRANTED TO PUBLISH, USE, REPRODUCE, TRANSMIT OR DISCLOSE THIS DRAWING, OR ANY INFORMATION CONTAINED THEREIN TO OTHERS WITHOUT THE PRIOR WRITTEN CONSENT OF MSA EXCEPT FOR THE MANUFACTURE OF ARTICLES FOR MSA SCHUTZWERKE NACH DIN 34 BEACHTEN. MSA AUER GmbH.

DO NOT SCALE DRG.

CODE SYMBOLS
CRITICAL ⚠
MAJOR A ⚠ MINOR (NO MARK)
MAJOR B ⚠
100 % INSPECTION ⚠

TOLERANCES UNLESS OTHERWISE SPECIFIED
FRACTIONAL ± 1/64
2 PL DEC. ± 0.01
3 PL DEC. ± 0.005
ANGULAR ± 1 deg.
SEE MSA STANDARD SHOP PRACTICES FOR DRILLED HOLE TOLERANCES

JOB NO. 30010260 PH0729

	DRAWN BY	DATE
	GJT	12-12-2005
CHECKED BY	M.BRADLEY	1-29-09
PROJ. ENGR.	S.TURNER	1-29-09
QUALITY ASSURANCE	J.DANNHARDT	1-29-09
MANUFACTURING	J.BRYER	1-29-09

APPROVAL AGENCY CODE: NO | NIOSH ATTR. DOC.: .

INSTALLATION OUTLINE, TRIGARD

CADD REF: SK3015-1032 — SCALE: 1.000

D. — SK3015-1032 — SHEET 7 OF 7

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng
DATE: Jul 25, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

TDS AND SHOP DRAWINGS

DA-IC-10 – (NAS and UPS)

Date : 2018-07-25

INFORMATION	
Project : **WASTEWATER PLANT - IQALUIT**	
Client : Kudlik Construction Ltd. To Sandra Rousseau P.Eng./ Project Manager	Project number : **2018-062**
Contractor : Norclair inc.	Project number Norclair : **P1039**
Address : 1100, Montee Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Dominic Papineau	E-mail: dpapineau@norclair.ca
Phone: 450-688-4012 # 720	Cell.: 514-409-1832

Information, subcontractor or supplier	
Sub supplier : Entreprises L.M.	
Contact : Marion Fleury	Phone : (514) 521-0882

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : **NAS and UPS**	
Drawing reference :	
Specification reference : **47 10 02** (Page 2 / XX)	Division :
Article :	Number of pages:

CONSULTANT APPROVAL

Comments within.

STANTEC PROJECT #: 110126045

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- ☐ Architectural
- ☐ Structural
- ☐ Mechanical
- ☐ Electrical
- ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

SUBMITTAL # DA-IC-10 (2018-07-25)

Stantec

- ☐ REVIEWED
- ☑ REVIEWED, AS NOTED
- ☐ REVISE AND RESUBMIT
- ☐ NOT REVIEWED

DATE 2018-JUL-25

BY David Hutchison, P.Eng.

1100, Montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

My Cloud™ EX2 Ultra
NAS

High-performance backup, sharing, syncing and access from anywhere.



Keep your media in a single place on this high-performance NAS solution, and access it from anywhere. With My Cloud EX2 Ultra NAS, you'll be able to automatically sync content across computers, easily share files and folders, and enjoy multiple backup options so you can create your own personalized system with ease.



My Cloud EX2 Ultra
NAS



Product Features

Centralized storage for anywhere access
Keep your photos, videos, music and documents in a single place, and with MyCloud.com or the My Cloud app, you can access or share from anywhere with an internet connection.

Multiple RAID options
My Cloud EX2 Ultra NAS features a variety of RAID settings, so you can customize your system with the configuration that's best for you. Options include RAID 0 for enhanced performance, RAID 1 for mirrored data protection, as well as JBOD and spanning support for non-RAID configurations.

Featuring ultra-reliable WD Red™ NAS drives
My Cloud EX2 Ultra comes pre-configured with WD Red™ hard drives, specifically built for NAS systems to provide improved performance within 24×7 environments. The My Cloud EX2 Ultra is also available in a diskless version to create a custom NAS with compatible hard drives.

Updated for high-performance
Upgraded with the powerful Marvell® ARMADA™ 385 1.3GHz dual-core processor, you'll get ultra-fast transfer rates and high-performance streaming. You'll also be treated to 1GB of DDR3 memory, allowing you to multitask with ease.

Smooth media streaming
Enjoy high-performance streaming with this powerful NAS system. Combined with the Plex™ Media Server, your HD content will be organized and prepared for streaming to your PC, mobile device, game console, or other certified media player.

Powered by My Cloud OS 3 software
WD's My Cloud OS 3 comes with a variety of tools and apps. Create a folder to share content with family and friends. Automatically synchronize your data between all your computers and make sure your content is always up to date. Easily transfer content between your NAS and a supported cloud service like Dropbox™, OneDrive, or Google Drive™.*

Sync your content across all your computers
With WD Sync, you can automatically synchronize your media and files across your computers and your My Cloud device, so you can be confident your content is always up to date and accessible with all your devices.

Keep an eye on your home, wherever you're at
Equipped with award-winning Milestone ARCUS™ Surveillance software, delivering a powerful surveillance system for your home. Compatible with thousands of industry-leading cameras, support for up to 10 connected cameras and two (2) free camera licenses included, making this NAS the perfect surveillance solution to keep watch on what matters to you most.

Enhanced data protection
With backup software like WD SmartWare™ or Acronis, PC users can customize when and where their content is saved, while Mac users have full access to Apple Time Machine for personalized backup. You can even automatically back up your data to a separate My Cloud NAS device, or any supported cloud service like Amazon S3, ElephantDrive or Acronis*. 256-bit AES volume encryption, when enabled, helps to securely store files across your entire network.

Customize your NAS with popular apps
My Cloud EX2 Ultra supports a full suite of popular applications for a personalized experience. Use apps like Plex, Milestone ARCUS Surveillance, Dropbox, WordPress, and more*.

My Cloud™
Mobile App

Product Specifications

INTERFACE
Gigabit Ethernet
USB 3.0 expansion port (x2)

DIMENSIONS

Height:	6.75 in (171.45 mm)
Depth:	6.10 in (154.94 mm)
Width:	3.90 in (99.06 mm)
Weight:	20TB 5.1 lbs (2.32kg)
	16TB 5.0 lbs (2.3kg)
	12TB 5.2 lbs (2.4 kg)
	8TB 5.0 lbs (2.3kg)
	6TB 4.61 lbs (2.0
	4TB 3.4 lbs (1.6k
	0TB 1.8 lbs (0.8

SYSTEM REQUIREMENTS
- Windows 10, Windows 8, Windows 7 or Windows Vista operating systems
- Mac OS X El Capitan, Yosemite, Mavericks or Mountain Lion operating systems
- DLNA™/UPnP™ devices for streaming
- Router for Internet connection
- Internet Explorer 10 or higher
- Safari 6 or higher
- Firefox™ 30 or higher
- Google Chrome™ 31 or higher on supported Windows and Mac OS platforms

Compatibility may vary depending on user's hardware configuration and operating systems.

CAPACITIES AND MODELS
20TB WDBVBZ0200JCH
16TB WDBVBZ0160JCH
12TB WDBVBZ0120JCH
8TB WDBVBZ0080JCH
6TB WDBVBZ0060JCH
4TB WDBVBZ0040JCH
0TB WDBVBZ0000NCH

16TB version required.
8TB usable space @ RAID 1 requires x2 disk capacity

KIT CONTENTS
Network Attached Storage
Ethernet cable
AC adapter
Quick Install Guide

OPERATING SPECIFICATION
Operating temperature: 5°C
Non-op. temperature: -20°C to 65°C

ED WARRANTY
onfigured
3 years Worldwide

Diskless
2 years Worldwide



WD, the WD logo, My Cloud, WD Red, WD SmartWare and WD Sync are registered trademarks or trademarks of Western Digital Corporation or its affiliates in the U.S. and/or other countries. All other marks that may be mentioned herein are the property of their respective owners. Product specifications subject to change without notice. Pictures shown may vary from actual product.
© 2017 Western Digital Corporation or its affiliates.
*App or Cloud service registration may be required. App or Cloud services may be changed, terminated or interrupted at any time and may vary by country.
As used for storage capacity, one terabyte (TB) = one trillion bytes. Total accessible capacity varies depending on operating environment and RAID/JBOD configuration.
As used for transfer rate or interface, megabyte per second (MB/s) = one million bytes per second, and gigabit per second (Gb/s) = one billion bits per second.

4178-707149-A01 June 2017

Product Brochure



Eaton 5S UPS

The energy-efficient UPS for desktops and workstations.

Eaton® 5S features and benefits:

Power management: Enhance your power protection capabilities and ensure safe system shutdown with the Eaton UPS Companion software. The 5S interface is auto-recognized when plugged into computers with Windows, Macintosh and Linux environments.

LCD display: Access critical UPS information including battery time and outage tracking in a single screen view with the user friendly LCD.

Data protection: Safeguard your work and data with the UPS Companion software by gracefully shutting down your equipment during power outages.

Eco-Control: Save up to 30 percent on energy consumption by shutting down non-essential peripherals when the computer is turned off.

Convenient form factor: Fit the 5S easily into tight spaces with its slim form factor. The versatile 5S can be used as a tower or as a desktop monitor stand.

Surge protection:
Provide surge protection for network phone lines, cable TV and satellite applications.

Battery health check:
Schedule daily, weekly or monthly health checks to verify battery performance and ensure that it delivers power during the next outage.

Eaton UPS Companion software:

The Eaton UPS Companion software provides safe system shutdown for small offices and residential users looking for an easy way to enhance the protection capabilities of their Eaton UPS. In addition, the Eaton UPS Companion provides energy usage and cost data, resulting in a better understanding of the power requirements of the protected equipment.

The main features of the UPS Companion software:

- Safe system shutdown
- Energy use and cost reporting
- Easy access to UPS status and events
- Configuration of UPS parameters
- Multiple language support
- Automatic software updates



The 5S fits in small spaces and can also be used as a monitor stand.

Powering Business Worldwide

5S UPS MODEL SELECTION GUIDE*

Catalog number	Rating (VA/watts)	Input connection	Output receptacles	Dimensions (H x W x D), in	Net weight, lb	LCD	Eco Control
Tower 120V, 50/60 Hz models							
5S550	550/330	5-15P	(8) 5-15R	9.8 x 3.4 x 10.2	12.3	No	No
5S700	700/420	5-15P	(8) 5-15R	9.8 x 3.4 x 10.2	14.3	No	No
5S700LCD	700/420	5-15P	(8) 5-15R	9.8 x 3.4 x 10.2	13.1	Yes	Yes
5S1000LCD	1000/600	5-15P	(10) 5-15R	9.8 x 3.4 x 15.0	21.4	Yes	Yes
5S1500LCD	1500/900	5-15P	(10) 5-15R	9.8 x 3.4 x 15.0	25.5	Yes	Yes
Tower 208 or 230V 50/60 Hz models							
5S700G	700/420	C14	(6) C13	9.8 x 3.4 x 10.2	13.1	No	No
5S1500G	1500/900	C14	(8) C13	9.8 x 3.4 x 15.0	24.6	No	No

*For complete battery runtimes, please visit Eaton.com/5S.

Services and support

Eaton provides product support 24 hours a day, 7 days a week. From battery replacement to full UPS service plans, Eaton has one of the top service models in the industry.

Three-year warranty

The 5S warranty covers both UPS and the batteries for three years. No other manufacturer in the industry offers a warranty as comprehensive.

What's in the box


- 5S UPS
- USB cable
- User manual

5S UPS front panel



Model displayed above: 5S1500LCD

5S UPS rear panel



To interact with the Eaton 5S UPS, please visit:
Eaton.com/5S

Eaton
Electrical Sector
1000 Eaton Boulevard
Cleveland, OH 44122 USA
Eaton.com

Powerquality.eaton.com

©2013 Eaton
All Rights Reserved
Printed in USA
BR153014EN
May 2013

Eaton is a registered trademark of Eaton Corporation.

All other trademarks are property of their respective owners.

Powering Business Worldwide

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Oct 16, 2018

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-11 Emergency shut down (ESD)

Date : 2018-10-16

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Dominic Papineau, Project Manager	E-mail: dpapineau@norclair.ca
Phone : 450-688-4012 # 720	Cell. : 514-409-1832

Information, subcontractor or supplier	
Sub/supplier : Quantum Electrique	
Contact :	Phone :

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : Emergency shut down (ESD)	
Drawing reference : I501	
Specification reference : :	Division :
Article :	Number of pages : 7

CONSULTANT APPROVAL

Comments within.

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-11 (2018-10-16)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED

☑ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-10-23

BY David Hutchison

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Hazardous location
3x

4C EDS / EFS Series Control Stations

FlexStation™ Control Station Components

Cl. I, Div. 1 & 2, Groups B (Div. 2 only) C, D
Cl. II, Div. 1 & 2, Groups E, F, G
Cl. III
Zone 1 & 2 Group IIB
NEMA 3R, 7B* (Div. 2) CD, 9 EFG, 12

Applications:

Five modular components – operators, contact blocks, covers, legend plates, and bodies – are combined to provide a variety of control stations which are:


- For use indoors or outdoors, in areas which are hazardous due to the presence of flammable gases and vapors, or combustible dust.
- Used in conjunction with magnetic starters or contactors for remote control of motors and other electrical apparatus.
- For installation in petroleum refineries, chemical, petrochemical, and other industrial process facilities; grain processing and storage facilities; and other heavy industrial applications where Class I, Class II, or Class III hazards are present.

Features:

- Momentary contact pushbuttons, maintained contact pushbuttons, and pilots lights offer a choice of functions.
- Selector switches in 2 or 3 position configurations including keyed and spring return options.
- Single-hole, two-hole, and three-hole covers for one, two, or three devices respectively per station.
- Rugged control devices for safe, reliable operation in industrial applications.
- Bodies, with extra room for wire pulling and termination, also include two integral mounting feet for fast, secure installation.
- Bodies have ½", ¾", or 1" dead-end or through-feed conduit hubs with integral bushing for protection of wire insulation.
- Covers and bodies are available in *Feraloy*® or copper-free aluminum for light weight and corrosion resistance.
- DL legend plates have large lettering to give clear indication of device function. Space is available for field markings.

Certifications and Compliances:

- NEC
  - Class I, Division 1 & 2, Groups B* (Div. 2), C, D
  - Class II, Division 1 & 2, Groups E, F, G
  - Class III
- Zone 1 & 2 Group IIB*
- NEMA: 3R, 7B (Div. 2) CD, 9EFG, 12
- UL Standard: 1203



Standard Materials:

- Bodies, covers – *Feraloy*® or copper-free aluminum.
- Pushbuttons and guards – Type 6 / 6 nylon.
- Operating shafts, bearings – stainless steel.

Standard Finishes:

- *Feraloy*® iron alloy – electrogalvanized and aluminum acrylic paint.
- Copper-free aluminum – natural.
- Stainless steel – natural.


Options:

Description	Suffix
Copper-free aluminum bodies and covers Corro-free™ epoxy finish for use in severely corrosive environments. FlexStation covers and bodies.	SA S752

Electrical Ratings:

- Pushbuttons and selector switches – 600 VAC heavy duty (NEMA A600).
- Pilot lights – 120 VAC.

Dimensions
In Inches:



†Covers have same length and width as back boxes.
*For Class I, Division 1, Group B or Zone 1 Hydrogen applications, use the EFS(C) complete control station catalog numbers see page 528.

 Copyright© 2013 Eaton's Crouse-Hinds Business


Crouse-Hinds by EATON

STEP 5 – Select Back Box

Back Boxes - for use with DS441 and DS442 covers or with 1 gang and 2 gang DS/DSD Series covers




Dead End	Through Feed	Hub Size	Back Box Arrangement
EDS171	**EDSC171**	½"	Single gang back box
EDS271	**EDSC271**	¾"	Single gang back back box
EDS371	**EDSC371**	1"	Single gang back box
EDS172	**EDSC172**	½"	Double gang back box
EDS272	**EDSC272**	¾"	Double gang back box
EDS372	**EDSC372**	1"	Double gang back box



Options:	Suffix
Aluminum body	**SA**
Exterior epoxy powder coat finish	**S752**
Interior & exterior epoxy powder coat finish	**S753**

Back Boxes – for use with DS443-SA cover or with 1½ gang DS511 (3-operator) Series covers



Dead End	Through Feed	Hub Size	Back Box Arrangement
EFD1491 SA	**EFDC1491 SA**	½"	1½ gang back box
EFD2491 SA	**EFDC2491 SA**	¾"	1½ gang back box
EFD3491 SA	**EFDC3491 SA**	1"	1½ gang back box

Options	Suffix
Exterior epoxy powder coat finish	**S752**
Interior & exterior epoxy powder coat finish	**S753**

Copyright© 2014 Eaton's Crouse-Hinds Business

EDS / EFS Series Control Stations

DSD Cover and Device Sub-assemblies

Cl. I. Div. 1 & 2, Groups B*, C, D† Explosionproof
Cl. II, Div. 1, Groups E, F, G Dust-Ignitionproof
Cl. II, Div. 2, Groups F, G Raintight
Cl. III Wet Locations
NEMA 3, 7B*CD, 9EFG

For use with EDSCM modular control device bodies see page 519 and EDS/EDSC back boxes.

Features:

- Large machine screws for fastening covers to bodies
- Lockout hole for padlock having 1/4" hasp is provided when used with covers for front lever and side rocker type operation
- Lockout provisions on front operated pushbutton (marked "STOP" and "OFF") and all selector switch covers
- For covers with front lever and side rocker type operating handles, threaded type shafts and bushings are used to ensure flametightness
- Accurately ground flange for flametight joint when mated with ground flange on back box

Certifications and Compliances:

(When used with EDSCM & EDS bodies):

- NEC/CEC:
  - Class I, Division 1 & 2, Groups C, D†
  - Class I, Division 2, Groups B, C, D
  - Class II, Division 1, Groups E, F, G
  - Class II, Division 2, Groups F, G
  - Class III
- NEMA/EEMAC: 3, 7B (Div. 2) CD, 9EFG
- UL Standards: 894, 698
- CSA Standard: C22.2 No. 30

Pushbuttons, Pilot Lights & Selector Switches (when used with EFS bodies):

- NEC/CEC:
  - Class I, Division 1 & 2, Groups B, C, D
  - Class II, Division 1, Groups E, F, G
  - Class II, Division 2, Groups F, G
  - Class III
- NEMA/EEMAC: 3, 7BCD, 9EFG
- UL Standard: 1203
- CSA Standard: C22.2 No. 30

Standard Materials:

- Covers, front operated – Feraloy iron alloy and copper-free aluminum
- Covers, side operated – copper-free aluminum
- Shafts and shaft bushings – stainless steel
- Rocker handles, pushbuttons and guards – type 6 / 6 nylon
- Sealing enclosures – copper-free aluminum

CPS delayed action receptacle cover:

- Receptacle housing – copper-free aluminum
- Insulation – diallyl phthalate (DAP)
- Contacts – brass

Standard Finishes:

- Feraloy – electrogalvanized and aluminum acrylic paint
- Copper-free aluminum – natural



Options:

The following special options are available by adding suffix to Cat. #:

Description	Suffix
• Lockout provision on front operated pushbutton cover (standard on buttons marked "STOP" and "OFF")	S153
• Three-position selector switches with modified operation: Momentary contact clockwise operation, spring return to center, maintained contact counter-clockwise operation	S634
Momentary contact counter-clockwise operation, spring return to center, maintained contact clockwise operation	S635
• Momentary red emergency "STOP" button – front operated mushroom button, breaks normally closed contacts only (DL02 legend plate included – must specify legend text)	S111
• Bodies and covers – copper-free aluminum	SA
• For 24 VDC operation on pilot lights	S300
• Maintained red emergency "STOP" button with lockout – front operated mushroom button breaks normally closed and makes normally open contacts (push to stop), lockout standard (will not fit with a pilot light if transformer is required)	S769
• Spring return to center from right and left (For DEV43 or DEV44 only)	S842
• Key Operated – removable from all positions	S847 K1‡
• Key Operated – removable from left position for DEV42 or from center for DEV43 and DEV44	S847 K2‡
• Key Operated – removable from right position for DEV42 or from left for DEV43 and DEV44	S847 K3‡
• Key Operated – removable from right position for DEV43 and DEV44	S847 K4‡

Ordering Information: Manual Motor Starters

Poles	Max. H.P.	Max. Volts A.C.	Cat. #
With Allen-Bradley Bulletin 600 Switches			
1	1	115–230	**DSD910** ①
2	1	115–230	**DSD911** ①
With General Electric Switches			
1	1	115–230	**DSD912** ①§
2	1	115–230	**DSD913** ①§
With Cutler-Hammer Switches			
1	1	115–230	**DSD914** ①§
2	1	115–230	**DSD915** ①§
With Arrow-Hart Switches Without Overload Protection			
2	5	250 (30A)	**DSD916**
2	7.5	600 (30A)	**DSD916**
3	7.5	250 (30A)	**DSD917**
3	15	600 (20A)	**DSD917**



† When a CPS receptacle cover device is used, the assembly meets requirements for Class I, Groups C and D areas only.

* For pushbuttons, pilot lights, & selector switches, use EFS back box with required external conduit seal for 1 inch hub size, within 5 feet for Class I, Division 1, Group B applications.

‡ Additional key lock housings available; please contact Customer Service.

§ A comparable factory sealed cover will fit on the EDSCM21 body, EDS and EDSC bodies and in bottom gang of EDSCM33 and EDSCM63 bodies. To order, add suffix S701 to catalog number.

① Includes one interchangeable heater. To select heater see pages 479–480. Symbol 0 (zero) may be used to indicate heater omitted.

 Copyright© 2016 Eaton

EDS / EFS Series Control Stations

DSD Cover and Device Sub-Assemblies

Cl. I. Div. 1 & 2, Groups B*, C, D†
Cl. II, Div. 1, Groups E, F, G
Cl. II, Div. 2, Groups F, G
Cl. III
NEMA 3, 7B*CD, 9EFG

Explosionproof
Dust-Ignitionproof
Raintight
Wet Locations


DSD918


DSD922


DSD933


DSD962


DSD970


CPS152R


ENR5201

For use with EDSCM modular control device bodies see page 519 & EFS/EDS back boxes.

Ordering Information

Front Operated Pushbutton Stations
600 VAC Heavy Duty, Factory Sealed

Number of Cover Buttons	Normal Position	Diagram	Cat. #
1	1 Circuit Universal		**DSD918** ①
1	2 Circuits Universal		**DSD919** ①
	2 Circuits	A B	**DSD920** ①■
2	2 Circuits Universal		**DSD921** ①
2	2 Circuits Start-Stop unless otherwise specified	A B	**DSD922** ①■
2	2 Circuits Universal Mushroom Head		**DSD970** ①
3 (2-operator)	3 Circuits Universal		**DSD962** ①
3 (3-operator)	3 Circuits Universal		**DS511** ① **SA§**
3 (3-operator)	3 Circuits Universal Double pilot light - single pushbutton combo		**DS513** ① **SA§**
3 (3-operator)	3 Circuits Universal Double pushbutton - single pilot light combo		**DS514** ① **SA§**

Front Operated General Use Snap Switch

Style	Amperes 120 VAC	277 VAC	Cat. #
1-Pole	20	20	**DSD933‡**
2-Pole	20	20	**DSD934‡**
3-Pole	▲	▲	**DSD935✪**
3-Way	20	20	**DSD936‡**
4-Way	20	20	**DSD937‡**
1-Pole	30	30	**DSD939‡**
2-Pole	30	30	**DSD940‡**
3-Way	30	30	**DSD941‡**

Delayed Action Receptacles
Factory Sealed

Rating	Cat. #
20 A, 1 HP, 125–250 VAC 60 Hertz 20 A, 18 VDC	**CPS152R** **(2 wire, 3 pole)**
30 A, 1½ HP, 125–250 VAC 60 Hertz; 7 A, ½ HP, 480 VAC, 60 Hertz	**CPS532R** **(2 wire, 3 pole)**
30 A, 3 HP, 125–250 VAC 60 Hertz; 7A, 1 HP, 480 VAC, 60 Hertz	**CPS732R** **(3 wire, 4 pole)**

General Purpose, Dead Front
Factory Sealed

Rating	Cat. #	Diagram
20 A, 125 VAC	**ENR5201**	5-20R
20 A, 250 VAC	**ENR6202**	6-20R

①If desired, markings on indicating plates may be added to catalog number. Select from the list of standard markings below:

START	OFF	RESET	LIGHT ON
STOP	RUN	TRIP	HAND
ON	JOG	TEST	AUTOMATIC
EMERGENCY	OPEN	DOWN	RAISE
FORWARD	CLOSE	IN	LOWER
REVERSE	UP	OUT	

* For pushbuttons, pilot lights, & selector switches, use EFS back box with required external conduit seal for 1 inch hub size, within 5 feet for Class I, Division 1, Group B applications.
† When a CPS receptacle cover device is used, the assembly meets requirements for Class I, Groups C and D areas only.
■ Two universal contact blocks, must be wired as two circuits with one normally open and one normally closed. 1 green button, 1 red button, and lockout provision provided as standard.
▲16 Amp., 125V.
10 Amp., 250V.
‡ To order a comparable factory sealed cover for EDS, EDSC, EDSCM21 and the bottom gang of EDSCM33 and EDSCM63 bodies, add suffix S697. Factory sealed for Class I, Division 2, Group B.
✪ Cannot be factory sealed.
§ Can only be used with EFD Series 1½ gang back boxes. Pushbuttons include contact blocks. Standard pushbutton color is black. For optional colors - red, green - write in color. Example: DS511 GREEN BLACK RED-SA. First color is for uppermost button. For optional legend markings write in marking after device operator color. Example: DS513-J3 JOG-J1 STOP GREEN-SA.

 Copyright© 2013 Eaton's Crouse-Hinds Business

Crouse-Hinds by EATON



DSD951



DSD925



DSD947-J1-J1



DSD958



DSD957



DSD961-J1

For use with EDSCM modular control device bodies see page 519 & EFS/EDS back boxes.

Ordering Information
Side Operated Pushbutton Station
600 VAC Heavy Duty, Factory Sealed

Normal Position	Diagram	Cat. #
1 Circuit Universal		DSD949 ③
2 Circuits Universal		DSD950 ③
2 Circuits 1 Open - A 1 Closed - B Start-Stop unless otherwise specified	A B	DSD951 ③

Selector Switches
Maintained Contact 600 VAC Heavy Duty, Factory Sealed

	Style	Position 1	Position 2	Position 3	Cat. #
Two Position	Two Circuit	A1 A2			DSD923 ④
	Four Circuit	A1 A2 B1 B2			DSD924 ④
Three Position	Two Circuit	A1 A2			DSD925 ④
		A1 A2 B1 B2			DSD926 ④
	Four Circuit	A1 A2 B1 B2			DSD927 ④

* For pushbuttons, pilot lights, & selector switches, use EFS back box with required external conduit seal for 1 inch hub size, within 5 feet for Class I, Division 1, Group B applications.
‡LED pilot lights can be furnished in place of standard incandescent pilot lamps. Add suffix LED to Cat. No. after last color symbol.
§ Can only be used with EFD Series 1½ gang back boxes. Pushbuttons include contact blocks. Standard pushbutton color is black. For optional colors - red, green - write in color. Example: DS511 GREEN BLACK RED-SA. First color is for uppermost button. For optional legend markings write in marking after device operator color. Example: DS513-J3 JOG-J1 STOP GREEN-SA.

Pilot Light Devices‡
Factory Sealed

Description	Diagram	Cat. #
With one pilot light		DSD948 ①
With two pilot lights (Not available with a transformer)		DSD947 ①
With one pilot light and transformer		DSD948 ① ②
With one pilot light and pushbutton station		DSD958 ①
With one pilot light and 1 double pushbutton station		DSD961 ①
With one pilot light & transformer and 1 double pushbutton station		②
Triple pilot light		A§
Double pilot light - single pushbutton combo		A§
Double pushbutton - single pilot light combo		DS514 ① SA§
With one pilot light & 2 position selector switch, two circuit (pos. 1 - N.O., pos. 2 - N.C.)	A1 A2	DSD973 ① ④
With one pilot light & 2 position selector switch, four circuit (pos. 1 - N.O., pos. 2 - N.C. for both switches)	A1 A2 B1 B2	DSD974 ① ④
With one pilot light & 3 position selector switch, two circuit (pos. 1 - N.O., pos. 2 - open, pos. 3 - N.C.)	A1 A2	DSD975 ① ④
With one pilot light & 3 position selector switch, four circuit (pos. 1 - N.O., pos. 2 - open, pos. 3 - N.C. for both switches)	A1 A2 B1 B2	DSD976 ① ④
With one pilot light & 3 position selector switch, four circuit (pos. 1 - N.C., pos. 2 - N.O., pos. 3 - N.O. for switch A; pos. 1 - N.O., pos. 2 - N.O., pos. 3 - N.C. for switch B)	A1 A2 B1 B2	DSD977 ① ④

Wire light to be lit when E-stop is activated

Blank Cover

Description	Cat. #
Blank Cover	DSD957

① Add color symbol for each pilot light from table below.

Color	Symbol	Color	Symbol	Color	Symbol
Red	J1	Amber	J6	Blue	J11
Green	J3	Clear	J10		

② Add suffix below for transformer primary voltage:

Transformers – Voltages above 125

Nom. Volts 50–60Hz Transformer	Primary Voltage Range	Suffix
220 / 110	220–240	T2
440 / 110	440–480	T4
550 / 110	550–600	T5

③ If desired, markings on indicating plates may be added to catalog number. Select from the list of standard markings below:

START	OFF	RESET	LIGHT ON
STOP	RUN	TRIP	HAND
ON	JOG	TEST	AUTOMATIC
EMERGENCY	OPEN	DOWN	RAISE
FORWARD	CLOSE	IN	LOWER
REVERSE	UP	OUT	

④ Specify indicating plate markings. Standard indicating plate markings available are as follows:

Two-Position

RUN, JOG	FAST, SLOW	IN, OUT
HAND, AUTOMATIC	OPEN, CLOSE	RAISE, LOWER
FORWARD, REVERSE	UP, DOWN	START, STOP
	ON, OFF	

Three-Position

JOG, OFF, RUN	1, OFF, 2
AUTOMATIC, OFF, HAND	OPEN, OFF, CLOSE
FORWARD, OFF, REVERSE	UP, OFF, DOWN
FAST, OFF, SLOW	

Copyright© 2014 Eaton's Crouse-Hinds Business

Emergency Stop Pushbutton Stations ❶❷

Pushbutton Station	Description	Catalog Number	Price	Dimensions Length	Width	Depth
	**Type 4/13 (IP66) - Oil & Dust Tight –** Gray aluminium					
	30mm twist-to-release E-stop	**D7-1MPB13 -✪▼-◆**	**178.78**			
	40mm twist-to-release E-stop	**D7-1MPB14 -✪▼-◆**	**183.88**	3.28"	3.34"	4.93"
	60mm twist-to-release E-stop	**D7-1MPB16 -✪▼-◆**	**188.48**			
	**Type 4/13 (IP66) - Oil & Dust Tight –** Gray aluminium					
	40mm twist-to-release keyed E-stop	**D7-1MPBK14-✪▼-◆**	**239.51**	3.28"	3.34"	4.93"
	**Type 4/4X/13 (IP66) - Dust Tight and Corrosion Proof –** Yellow plastic					
	30mm twist-to-release E-stop	**D7-1YPB13-✪▼-◆**	**88.74**			
	40mm twist-to-release E-stop	**D7-1YPB14-✪▼-◆**	**91.92**	3.34"	3.50"	4.05"
	60mm twist-to-release E-stop	**D7-1YPB16-✪▼-◆**	**98.44**			
	**Type 4/4X/13 (IP66) - Dust Tight and Corrosion Proof –** Yellow plastic					
	40mm twist-to-release keyed E-stop	**D7-1YPBK14-✪▼-◆**	**149.47**	3.34"	3.50"	4.05"

✪ = **P -** D7P Plastic devices, no price change

M - D7M Metal devices, add $1.92

▼ = See Base Mount Contact Block table

◆ = **ER -** Emergency Stop Ring (D7-15YE112), add $3.39



Base Mount Contact Block Codes ❷

▼ Code	Contacts	Adder
X10	1NO	Std.
X01	1NC	Std.
X20	2NO	12.90
X02	2NC	12.90
X11	1NO/1NC	12.90
X30	3NO	25.80
X03	3NC	25.80
X21	2NO/1NC	25.80
X12	1NO/2NC	25.80

Enclosure Accessories

Component	Catalog Number	Price Ea.	Pkg. Qty.
Ground Screw Kit This accessory is used for grounding on D7 plastic enclosures only.	**D7-AGS2**	**.84**	**10**

Ordering Example

• Specify Catalog Number	
• Replace (▼) with Contact Block Code and Operator Type	**See Contact Block Code table on this page**
• Include price adder when applicable	

❶ Will accept one stack of base mount contact blocks (1-3 contact blocks).
❷ Accepts two piece snap-in legends and 60 mm emergency stop legends.

3x units:
FQIT-02-152
FQIT-02-156
FQIT-02-172

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Mar 28, 2019

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-12R1 Thermal mass flowmeter

Date : 2019-03-28

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Hugo Chartier, Project Manager	E-mail: hchartier@norclair.ca
Phone : 450-688-4012 # 706	Cell. : 514-703-0263

Information, subcontractor or supplier	
Sub/supplier : **Endress & Hauder**	
Contact : **Stéphane Raymond**	Phone : **514-940-2288**

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : **Thermal Mass Flowmeter**	
Drawing reference :	
Specification reference : **47 30 02 data sheets**	Division :
Article :	Number of pages : **10**

New review needed. See page 5 and following.
HC, 2019-03-28

CONSULTANT APPROVAL
SHOP DRAWINGS ARE REVIEWED UNLESS NOTED OTHERWISE

REVIEWED AS MODIFIED	X
REVISE & RESUBMIT	
SEAL & SIGNATURE REQUIRED	

Stantec

DATE April 23

SIGNATURE

REVIEW BY STANTEC IS FOR THE SOLE PURPOSE OF ASCERTAINING GENERAL CONFORMITY WITH DESIGN. CONTRACTOR IS RESPONSIBLE FOR DIMENSIONS, FABRICATION AND CONSTRUCTION METHODS, COORDINATION OF SUB-TRADES, DETAIL DESIGN OF COMPONENTS, AND ERRORS OR OMISSIONS ON SHOP DRAWINGS.

STANTEC PROJECT #: 110126045
SUBMITTAL # DA-IC-12 (2019-01-24)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE 2018-JAN-28
BY David Hutchison, P.Eng.

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Endress+Hauser
People for Process Automation

DRAWING NUMBER	2002597302	PROJECT	Iqaluit
			Norclair Inc.

65I-20AA0AD5RABABA
t-mass 65I

Link to the product information:
www.ca.endress.com/65I

Thermal mass flowmeter for gases. Insertion type for circular pipes and rectangular ducts.

additional specifications

Language	English	
Process pressure	14.69200	psi a
Pipe type	Circular	
Internal diameter	6.998	Inch
Channel 1		
Gas type 1	Air	
Mol-% gas 1	100.000	%
Assign line 1	Mass flow	
Assign line 2	Totalizer 1	
Assign totalizer 1	Mass flow	
Unit totalizer 1		lb
Assign totalizer 2	Mass flow	
Unit totalizer 2		lb
Assign current output	Mass flow	
Current span	4-20 mA HART US	
Value 20 mA	16,500.000	lb/h
Time constant	1.000	s
Failsafe mode current output	Min. current	
Assign pulse output	Mass flow	
Pulse value	200.000	lb
Pulse width	20.000	ms
Output signal	Passive - positive	
Failsafe mode pulse output	Fallback value	

1x TAG-stainless steel label 50061469
FQIT-02-152
FQIT-02-156
FQIT-02-172

20	Insertion Tube Length: 235 mm 9"
A	Material Insertion Tube; Sensor: Stainl. steel; Stainl. steel
A	Process Connection: 1" MNPT, thread ANSI, compression fitting, Stainl. steel
0	Seal: PEEK, -40...+130oC/-40...+266oF
A	Surface cleaning: Basic version
D	Calibration: Factory calibration
5	Additional Test, certificate: CRN approval
R	Approval: FM NI Cl.I Div.2/CSA Cl.I Div.2, ABCD + Zone 2
A	Housing: Compact Alu, IP67 NEMA4X
B	Cable Entry: Thread NPT 1/2
A	Display; Operation: 85-260VAC, 2-line + push buttons
B	Adjustment; Software Feature: Default Gas (Air 1.013bar a/14.692psi a)
A	Output, Input: 4-20mA HART + frequency
1	>>>Marking: Tagging (TAG), see additional spec.

	Initiales	ISSUED DATE
	SR	December 18 2018

1100 Montee Masson
Laval, Qc
H7E 4P2

Hugo Chartier

Téléphone: **450-688-4012**
FAX **450-688-9123**
EMAIL hchartier@norclair.ca

SUPPL
anada Ltée
6800 Côte de liesse, suite 100
Québec, Canada
H4T 2A7

Téléph 254 X2288
FAX 514 733-2924
EMAIL stephane.raymond@endress.com

ISSUED BY	Stephane Raymond
ISSUE	OR
AS IS:	X
Équivalent:	Information:
Substitution:	Coordination:

ENGINEER APPROUVAL STAMP


Volume
Nm3
kg
2000 Nm3/h
1 Nm3
100ms on / 100ms off
(200ms @ 50% duty)

Endress+Hauser
People for Process Automation

DRAWWING NUMBER	2002597302	PROJECT	Iqaluit

MECANICAL CONSTRUCTION

t-mass 65I: Compact insertion version




Engineering unit mm (in)

Length tmass 65I	V	W	L	L_R
235	235.1	252.6	475.6	417.6

Endress+Hauser
People for Process Automation

DRAWWING NUMBER	2002597302	PROJECT	Iqaluit

ELECTRICAL CONNECTIONS



Connecting the transmitter, cable cross-section max. 2.5 mm² (14 AWG)

A View A (field housing)
B View C (wall-mount housing)

**)* fixed communication board
***)* flexible communication board
a Connection compartment cover
b Cable for power supply: 85 to 260 V AC, 20 to 55 V AC, 16 to 62 V DC
Terminal No. 1: L1 for AC, L+ for DC
Terminal No. 2: N for AC, L- for DC
c Ground terminal for protective ground
d Signal cable: see Terminal assignment → ` 11
Fieldbus cable:
Terminal No. 26: DP (B) / PA (+) / FF (+) / MODBUS RS485 (B) / (PA, FF: with reverse polarity protection)
Terminal No. 27: DP (A) / PA (–) / FF (–) / MODBUS RS485 (A) / (PA, FF: with reverse polarity protection)
e Ground terminal for signal cable shield / fieldbus cable / RS485 line
f Service adapter for connecting service interface FXA 193 (Fieldcheck, FieldCare)
g Signal cable: see Terminal assignment → ` 11
Cable for external termination (only for PROFIBUS DP with permanent assignment communication board):
Terminal No. 24: +5 V
Terminal No. 25: DGND

Applicator Sizing - Flow

Project :

Customer:
Contact person:
Phone:
eMail:
C.Project No.:
Fax:

TAG : ---

Timestamp: ---
Review number: ---
Sales order number:

Sizing Sheet

General Parameters

Fluid	Air (Gas) ✓	Ref. Temperature	0 °C
State	Gas	Ref. Pressure	1.013 bar_a
Character	Clean	Atmospheric Pressure	1.0133 bar_a
Abrasivity	Not abrasive	Standard	ASME (ANSI)
Fluid Group (PED)	Normal Fluid (Fluid group 2)		
Fluid type	Newtonian		

Operating Conditions

	minimum	nominal	maximum 100	
Requested Flow	1.6	13.1	50	m3/min
Pressure	22	22	22	psi_g
Temperature	60	60	60	°C
Density	2.6455	2.6455	2.6455	kg/m3
Z-factor	1	1	1	
Viscosity	0.02021	0.02021	0.02021	cP
Design pressure (min/max)	22		22	psi_g
Design Temp. (min/max)	60		60	°C

Flowmeter : t-mass 65I

Generation: 2 Device model: 0

Flow Principle	Thermal (t-mass)
Operating range min.	0.478 m3/min
Calibrated Flow	47.839 m3/min ✓
Operating range max.	95.679 m3/min ✓
Material (sensor) *	SS 1.4404 / 316L
Process connection*	Cl 150 1" MNPT ASME, 1.4404/316L Compr. fitting
PED category ** :	In observance of the selected process conditions and medium, Applicator categorizes this application as PED Art.4.3. Applicator doesn't suggest an instrument with PED option. The sensor's volume under pressure is smaller than the limiting value.

Extended Order Code

Qty	Item	Description	Extended Order Code
1	Flowmeter	t-mass 65I	65I-20AA (full model # on previous page)
1	Accessory	Customer connection C1	ensure C2 connection is also ordered

*The user is responsible for the selection of process-wetted materials in view of their corrosion resistance. Endress+Hauser makes no guarantees and assumes no liability for the corrosion resistance of the materials selected here for the application described above.

** The PED category is an Endress+Hauser recommendation and depends on the fluid category, process data as well from the max. permissible pressure of the selected pressure rating. The fluids of the Applicator data base are classified to 67/548/EWG.

Under no circumstances is Endress+Hauser liable for errors, neither in the Software and in its documentation, nor for any errors and consequential damage which may arise out of their use. The results in Applicator apply to parameters entered by the user. A change in these parameters could lead to different results. Mandatory data are in the according technical information (TI).

Endress+Hauser
People for Process Automation

Applicator Sizing - Flow

Project :

Customer:
Contact person:
Phone:
eMail:
C.Project No.:
Fax:

TAG : ---

Timestamp: —
Review number: ---
Sales order number:

Sizing Sheet

Sizing and Calculated Results

	minimum	nominal	maximum 100	
Requested Flow	1.6	13.1	50	m3/min
Velocity	1.302	10.66	40.7	m/s
Pressure loss	0	0	0.01	psi
Measurement error Mass***	4.48	1.5	1.82	%
Reynolds No.	27 520	225 321	860 004	

***For error calculation, the specified reference conditions for the calibration of the flowmeter according to ISO/IEC 17025 apply. Further information in technical documentation.

Warning(s)

Notice(s)

Message(s)

1. Note: For t-mass it is recommended to select "Corrected volume units e.g. Nm3/h or mass units.

Under no circumstances is Endress+Hauser liable for errors, neither in the Software and in its documentation, nor for any errors and consequential damage which may arise out of their use. The results in Applicator apply to parameters entered by the user. A change in these parameters could lead to different results. Mandatory data are in the according technical information (TI).

Endress+Hauser
People for Process Automation

Applicator Sizing - Flow

Project :

Customer:
Contact person:
Phone:
eMail:
C.Project No.:
Fax:

TAG : ---

Timestamp: ---
Review number: ---
Sales order number:

Fluid properties sheet

Fluid

Fluid name	Air (Gas)	State	Gas
Chemical formula		Calculation standard	NEL

Fluid description

Medium character	Clean
Fluid group (PED)	Normal Fluid (Fluid group 2)
Fluid type	Newtonian
Fluid stability	Stable

Gas mixture Component	Fraction	
1 Air (Gas)	100 Mole%	100 Mass%
2	0 Mole%	0 Mass%
3	0 Mole%	0 Mass%
4	0 Mole%	0 Mass%
5	0 Mole%	0 Mass%
6	0 Mole%	0 Mass%
7	0 Mole%	0 Mass%
8	0 Mole%	0 Mass%

Basic fluid parameters

Tc (Critical temperature)	-140.6 °C	Tm (Melting point)	-209.7 °C
Pc (Critical pressure)	546.648 psi	Tb (Boiling point)	-195.8 °C
Rho_c (Critical density)	324 kg/m3		

Calculated results

Density nom.	2.6455 kg/m3	Pressure nom.	22 psi_g
Molar mass	28.964 kg/kmol	Temperature nom.	60 °C
Z-factor nom.	1		
Viscosity nom.	0.02021 cP		
Sound velocity nom.	365.6 m/s		
Thermal capacity nom.	1.009 kJ/(kg*K)		
Heat conductivity nom.	0.029 W/(m K)		
Rel. humidity nom.	%		

Reference values: Normal conditions (SI):

Atmospheric pressure	1.0133 bar_a
Density normal	1.2929 kg/m3
Temperature (Normal conditions SI)	0 °C
Pressure (Normal conditions SI)	1.0133 bar_a

Standard conditions (US):

Atmospheric pressure	1.0133 bar_a
Density standard	1.2254 kg/m3
Temperature (Standard conditions US)	59 °F
Pressure (Standard conditions US)	14.696 psi_a

Under no circumstances is Endress+Hauser liable for errors, neither in the Software and in its documentation, nor for any errors and consequential damage which may arise out of their use. The results in Applicator apply to parameters entered by the user. A change in these parameters could lead to different results. Mandatory data are in the according technical information (TI).

Endress+Hauser
People for Process Automation

Applicator Sizing - Flow

Project :

Customer:
Contact person:
Phone:
eMail:
C.Project No.:
Fax:

TAG : ---

Timestamp: ---
Review number: ---
Sales order number:

Installation sheet

Flowmeter / Accessories

Extended Order Code

Qty	Item	Description	Extended Order Code
1	Flowmeter	t-mass 65I	65I-20AA
1	Accessory	Customer connection C1	


Installation data :

Insertion depth X	225.844 mm
Insertion tube length	235 mm
Pipe inner diameter 20°C	6.357 inch
Wall thickness	0.134 inch
C1 = Height process connection	120 mm
C2 = Height sensor connection	52 mm
C = Total height of connection	172 mm

Pipe data

Pipe standard	ASME (ASME B36.10 / B36.19)
Pipe size	6"
Prefered dimension for PN	sched. 10 / 10S

A= Internal diameter or internal height (duct vertical installation) or internal width (duct horizontal installation)
B= Wall thickness
C= Height of connection



*The Enduser is responsible for the correct selection of the piping. Applicator does not calculate necessary pipe wall thickness according to application data. Endress + Hauser takes no liability for the suitability of the pipe dimensions.

Warning(s)

Notice(s)

Message(s)

1. Note: For t-mass it is recommended to select "Corrected volume units e.g. Nm3/h or mass units.

Under no circumstances is Endress+Hauser liable for errors, neither in the Software and in its documentation, nor for any errors and consequential damage which may arise out of their use. The results in Applicator apply to parameters entered by the user. A change in these parameters could lead to different results. Mandatory data are in the according technical information (TI).

Endress+Hauser
People for Process Automation

Applicator Sizing - Flow

Project :

Customer:
Contact person:

Phone:
eMail:

C.Project No.:
Fax:

TAG : ---

Timestamp: ---
Sales order number:

Review number: ---

Chart Sheet


Flowmeter: t-mass 65I

Generation: 2

Flow Principle	Thermal (t-mass)
Operating range min.	0.478 m3/min
Calibrated Flow	47.839 m3/min
Operating range max.	95.679 m3/min

Device model: 0

Fluid	Air (Gas)
Temperature	60 °C
Density	2.6455 kg/m3
Viscosity	0.02021 cP



Flow rate (m3/min)	Pressure loss (psi)	Measurement error Mass(%)***
1.6	0	4.485
6.44	0	1.5
11.28	0	1.5
16.12	0.001	1.5
20.96	0.001	1.5
25.8	0.002	1.5
30.64	0.003	1.5
35.48	0.004	1.5
40.32	0.006	1.5
45.16	0.007	1.5
50	0.009	1.816

***For error calculation, the specified reference conditions for the calibration of the flowmeter according to ISO/IEC 17025 apply. Further information in technical documentation.

Under no circumstances is Endress+Hauser liable for errors, neither in the Software and in its documentation, nor for any errors and consequential damage which may arise out of their use. The results in Applicator apply to parameters entered by the user. A change in these parameters could lead to different results. Mandatory data are in the according technical information (TI).

Endress+Hauser
People for Process Automation

Under no circumstances is Endress+Hauser liable for errors, neither in the Software and in its documentation, nor for any errors and consequential damage which may arise out of their use. The results in Applicator apply to parameters entered by the user. A change in these parameters could lead to different results. Mandatory data are in the according technical information (TI).

Endress+Hauser
People for Process Automation

2x units:
LIT-03-111
LIT-03-121

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jan 28, 2019

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-13 Ultrasonic level sensor (non-XP)

Date : 2019-01-24

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Hugo Chartier, Project Manager	E-mail: hchartier@norclair.ca
Phone : 450-688-4012 # 706	Cell. : 514-703-0263

Information, subcontractor or supplier	
Sub/supplier : Endress & Hauder	
Contact : Stéphane Raymond	Phone : 514-940-2288

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : Ultrasonic level sensor (non-XP)	
Drawing reference :	
Specification reference : 47 30 02 data sheets	Division :
Article :	Number of pages : 7

CONSULTANT APPROVAL

Comments within

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-13 (2019-01-24)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Electrical
☐ Structural ☑ Other Instrumentation
☐ Mechanical

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE 2018-JAN-28

BY David Hutchison, P.Eng.

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Endress+Hauser
People for Process Automation

DRAWING NUMBER	2002597302	PROJECT	Iqaluit
			Norclair Inc.

FDU91-SN6AA
Prosonic S FDU91

Link to the product information:
www.ca.endress.com/FDU91

Level, ultrasonic, contactless.
Sensor for connection to FMU90/FMU95.
Application: liquids, solids.
Sensor: PVDF.
Measuring range: 10m/32ft (liquid), 5m/16ft (solid).
Max -40...80oC/176oF.
Max 4bar/60psi abs.
Blocking distance: 30cm/1ft.
:: High availability:
Self cleaning effect of sensor membrane.

S	Approval: CSA Cl.I,II,III Div.1+2 Gr.A-G, zone 1,2
N	Process Connection: Thread ANSI NPT1, PVDF
6	Cable Length: 30m/98ft
A	Heater: W/o
A	Additional Option: Basic version

Contractor responsible for confirming length is sufficient

1100 Montee Masson
Laval, Qc
H7E 4P2

Hugo Chartier

Téléphone: **450-688-4012**
FAX **450-688-9123**
EMAIL hchartier@norclair.ca

SUPPLIER

Endress+hauser Canada Ltée
6800 Côte de liesse, suite 100
Ville Saint-Laurent, Québec, Canada
H4T 2A7


Téléphone: 514 733-0254 X2288

ISSUED BY	Stéphane Raymond

ISSUED PRODUCT		DRAW.ISSUED FOR	
AS IS:	X	APPROUVAL:	X
Équivalent:		Information:	
Substitution:		Coordination:	

ENGINEER APPROUVAL STAMP

	Initiales	ISSUED DATE
	SR	December 18 2018



First Angle Projection

Disclaimer:

To ensure the accuracy of the information contained in this document every reasonable effort has been made. Endress+Hauser may not make any warranties,express or implied, with respect to the accuracy, the completeness or the technical or commercial usefulness of this document. Endress+Hauser may modify or replace this document any time.

© 18.12.2018 Endress+Hauser

Order Code :
FDU91-SN6AA

Product Description :
Prosonic S FDU91

www.addresses.endress.com


Endress+Hauser

People for Process Automation

Endress+Hauser
People for Process Automation

DRAWWING NUMBER	2002597302	PROJECT	Iqaluit

ELECTRICAL CONNECTIONS



A Without sensor heater
B With sensor heater
C Grounding at the terminal box
D Grounding at the transmitter FMU90

1 Shield of the sensor cable
2 Terminal box
3 Shield of the extension cable

Colours of the strands: YE = yellow; BK = black; RD = red; BU = blue; BN = brown; GNYE = green-yellow

Endress+Hauser
People for Process Automation

DRAWING NUMBER	2002597302	PROJECT	Iqaluit
			Norclair Inc.

FMU90-N11CA111AA1A
Prosonic S FMU90

Link to the product information:
www.ca.endress.com/FMU90

Evaluation: level/flow,
Continuous + switch output.
Application: up to 2 sensors,
Ex/non Ex: FDU90/FDU91/FDU91F/FDU92/
FDU93/FDU95.
32 points linearization.
Incl. Setup-/diagnostic software.
:: Simple guided setup:
automatic sensor recognition FDU9x,
menu-guided clear text commissioning.

N	Approval: CSA General Purpose
1	Application: Level + pump control, alternating
1	Housing, Material: Field mounting PC, IP66 NEMA4x
C	Operation: Illuminated display + keypad
A	Power Supply: 90-253VAC
1	Level Input: 1x sensor FDU9x/8x
1	Switch Output: 1x relay, SPDT
1	Output: 1x 0/4-20mA HART
A	Additional Input: W/o
A	Datalog Function: Basic version
1	Language: DE, EN, NL, FR, ES, IT, PT
A	Additional Option: Basic version

Loss of Echo

	Initiales	ISSUED DATE
	SR	**December 18 2018**

1100 Montee Masson
Laval, Qc
H7E 4P2

Hugo Chartier

Téléphone: **450-688-4012**
FAX **450-688-9123**
EMAIL hchartier@norclair.ca

SUPPLIER


Endress+hauser Canada Ltée
6800 Côte de liesse, suite 100
Ville Saint-Laurent, Québec, Canada
H4T 2A7


Téléphone: 514 733-0254 X2288
FAX 514 733-2924
EMAIL stephane.raymond@endress.com


ISSUED BY **Stéphane Raymond**

ISSUED PRODUCT		DRAW.ISSUED FOR	
AS IS:	**X**	APPROUVAL:	**X**
Équivalent:		Information:	
Substitution:		Coordination:	

ENGINEER APPROUVAL STAMP







First Angle Projection

Disclaimer:

To ensure the accuracy of the information contained in this document every reasonable effort has been made. Endress+Hauser may not make any warranties,express or implied, with respect to the accuracy, the completeness or the technical or commercial usefulness of this document. Endress+Hauser may modify or replace this document any time.

© 18.12.2018 Endress+Hauser

Order Code :
FMU90-N11CA111AA1A

Product Description :
Prosonic S FMU90

www.addresses.endress.com


Endress+Hauser

People for Process Automation

Endress+Hauser
People for Process Automation

DRAWWING NUMBER	2002597302	PROJECT	Iqaluit

ELECTRICAL CONNECTIONS



L00-FMU90xxx-04-00-00-xx-001

Terminals of the Prosonic S (the terminals depicted in grey are not present in every instrument version)

A Basic terminal area
B – E Optional terminal areas (present if the respective option has been selected in the product structure)

2x units
FQIT-02-328
FQIT-03-695

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jan 28, 2019

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-15 Flowmeter (final effluent and TWAS)

Date : 2019-01-24

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Hugo Chartier, Project Manager	E-mail: hchartier@norclair.ca
Phone : 450-688-4012 # 706	Cell. : 514-703-0263

Information, subcontractor or supplier	
Sub/supplier : Endress & Hauder	
Contact : Stéphane Raymond	Phone : 514-940-2288

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : Flowmeter (final effluent and TWAS)	
Drawing reference :	
Specification reference : 47 30 02 data sheets	Division :
Article :	Number of pages : 7

CONSULTANT APPROVAL

Comments within

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-15 (2019-01-24)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE 2018-JAN-28

BY David Hutchison, P.Eng.

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Endress+Hauser
People for Process Automation

Drawing #	2002597302	Project	IQALUIT
		Customer	NORCLAIR

Instrument description

5W4C3F-4497/0
5W4C3F-C6ALHA0DUA1K0A+Z1
Promag W 400, 5W4C3F, DN350 14"

C6 Approval: CSA C/US NI Cl.I Div.2 Gr. ABCD
A Design: Insertion length short ISO/DVGW until DN400, DN450-2000 1:1
L Power Supply: 100-240VAC/24VAC/DC
H Output; Input: 4-20mA HART, pulse/freq.,switch output
A Housing: Compact, alu, coated
0 Cable, Remote Version: Not used
D Electrical Connection: Thread NPT1/2
U Liner: Polyurethane
A1K Process Connection: Cl.150, carbon steel, flange ASME B16.5
0 Electrodes: 1.4435/316L
A Calibration Flow: 0.5%

4-20 mA = 0 - 200 L/s
Pulse @ 200L
Pulse timing: 100ms ON, 100ms OFF

Adress: 1100 Montee Masson
Laval QC H7E 4P2

Contact: **Jean-François Lessard**

450-688-4012

jflessard@norclair.ca

Endress+hauser Canada Ltée
6800 Côte de liesse, suite 100
Ville Saint-Laurent, Québec, Canada
H4T 2A7

Telephone 514 733-0254**x2288**
Fax 514 733-2924
E-mail stephane.raymond@endress.com


Prepare by	Stephane Raymond


built as		Drawing for	
As is	X	Approbation:	X
Equivalent:		Information:	
Substitution:		Coordination:	

Tag number FQIT-02-328

Revision	Initial	Date
0	**SR**	**January 24 2019**

Due to a transition phase from DIN 2501 to EN 1092-1 (2013) you may still receive flanges according DIN. Additional details and dimensions are available in the Operating Instructions (BA)





First Angle Projection

Disclaimer:

To ensure the accuracy of the information contained in this document every reasonable effort has been made. Endress+Hauser may not make any warranties,express or implied, with respect to the accuracy, the completeness or the technical or commercial usefulness of this document. Endress+Hauser may modify or replace this document any time.

© 24.01.2019 Endress+Hauser

Order Code :
5W4C3F-C6ALHA0DUA1K0A+Z1

Product Description :
Promag W 400, 5W4C3F, DN350 14"

www.addresses.endress.com

Endress+Hauser

People for Process Automation

Supply voltage

Order code "Power supply"	**Terminal numbers**	**terminal voltage**		**Frequency range**
Option **L** (wide range power unit)	1 (L+/L), 2 (L-/N)	DC 24 V	±25%	–
		AC 24 V	±25%	50/60 Hz, ±4 Hz
		AC 100 to 240 V	−15 to +10%	50/60 Hz, ±4 Hz

Signal transmission 0-20 mA/4-20 mA HART and additional outputs and inputs

Order code for "Output" and "Input"	**Terminal numbers**							
	Output 1		**Output 2**		**Output 3**		**Input**	
	26 (+)	**27 (-)**	**24 (+)**	**25 (-)**	**22 (+)**	**23 (-)**	**20 (+)**	**21 (-)**
Option **H**	▪ 4-20 mA HART (active) ▪ 0-20 mA (active)		Pulse/frequency output (passive)		Switch output (passive)		-	

Endress+Hauser
People for Process Automation

Drawing #	2002597302	Project	IQALUIT
		Customer	NORCLAIR

Instrument description

5W4C80-9F26/0
5W4C80-C6ALHA0DUA1K0A+Z1
Promag W 400, 5W4C80, DN80 3"

C6 Approval: CSA C/US NI Cl.I Div.2 Gr. ABCD
A Design: Insertion length short ISO/DVGW until DN400, DN450-2000 1:1
L Power Supply: 100-240VAC/24VAC/DC
H Output; Input: 4-20mA HART, pulse/freq.,switch output
A Housing: Compact, alu, coated
0 Cable, Remote Version: Not used
D Electrical Connection: Thread NPT1/2
U Liner: Polyurethane
A1K Process Connection: Cl.150, carbon steel, flange ASME B16.5
0 Electrodes: 1.4435/316L
A Calibration Flow: 0.5%

4-20 mA = 0 - 5 L/s
Pulse @ 10L
Pulse timing:
100ms ON, 100ms OFF

Note: product is thickened sludge
Solids content ~3-5%

Adress: 1100 Montee Masson
Laval QC H7E 4P2

Contact: **Jean-François Lessard**
450-688-4012
jflessard@norclair.ca

Manufacturer

Endress+hauser Canada Ltée
6800 Côte de liesse, suite 100
Ville Saint-Laurent, Québec, Canada
H4T 2A7

Phone 514 733-0254**x2288**
Fax 514 733-2924
E-mail stephane.raymond@endress.com


Prepare by	Stephane Raymond

built as		Drawing for	
As is	X	Approbation:	X
Equivalent:		Information:	
Substitution:		Coordination:	

Tag number FQIT-03-695

Revision	Initial	Date
0	**SR**	**January 24 2019**

Due to a transition phase from DIN 2501 to EN 1092-1 (2013) you may still receive flanges according DIN. Additional details and dimensions are available in the Operating Instructions (BA)



First Angle Projection

Disclaimer:

To ensure the accuracy of the information contained in this document every reasonable effort has been made. Endress+Hauser may not make any warranties,express or implied, with respect to the accuracy, the completeness or the technical or commercial usefulness of this document. Endress+Hauser may modify or replace this document any time.

© 24.01.2019 Endress+Hauser

Order Code :
5W4C80-C6ALHA0DUA1K0A+Z1

Product Description :
Promag W 400, 5W4C80, DN80 3"

www.addresses.endress.com

Endress+Hauser

People for Process Automation

Supply voltage

Order code "Power supply"	**Terminal numbers**	**terminal voltage**		**Frequency range**
Option **L** (wide range power unit)	1 (L+/L), 2 (L-/N)	DC 24 V	±25%	–
		AC 24 V	±25%	50/60 Hz, ±4 Hz
		AC 100 to 240 V	−15 to +10%	50/60 Hz, ±4 Hz

Signal transmission 0-20 mA/4-20 mA HART and additional outputs and inputs

Order code for "Output" and "Input"	**Terminal numbers**							
	Output 1		**Output 2**		**Output 3**		**Input**	
	26 (+)	**27 (-)**	**24 (+)**	**25 (-)**	**22 (+)**	**23 (-)**	**20 (+)**	**21 (-)**
Option **H**	▪ 4-20 mA HART (active) ▪ 0-20 mA (active)		Pulse/frequency output (passive)		Switch output (passive)		-	

1x unit
PIT-02-195

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jan 28, 2019

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-16 Pressure monitor (PIT)

Date : 2019-01-24

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Hugo Chartier, Project Manager	E-mail: hchartier@norclair.ca
Phone : 450-688-4012 # 706	Cell. : 514-703-0263

Information, subcontractor or supplier	
Sub/supplier : Endress & Hauder	
Contact : Stéphane Raymond	Phone : 514-940-2288

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : Pressure monitor (PIT)	
Drawing reference :	
Specification reference : 47 30 02 page 7	Division :
Article :	Number of pages : 4

CONSULTANT APPROVAL

Comments within

STANTEC PROJECT #: 110126045
SUBMITTAL # DA-IC-16 (2019-01-24)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE 2018-JAN-28
BY David Hutchison, P.Eng.

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Endress+Hauser
People for Process Automation

Drawing #	2002606968	Project	IQALUIT
		Customer	NORCLAIR

Instrument description

PMP55-56QX2/0
PMP55-CD12ID1HGCU5JA1A
Cerabar M PMP55

CD Approval: CSA C/US General Purpose
1 Output: 4-20mA
2 Display, Operation: W/o LCD, push button on electronics
I Housing: F31 Alu
D Electrical Connection: Thread NPT1/2, IP66/68 NEMA4X/6P
1H Sensor Range: 1bar/100kPa/15psi gauge, 10mH2O/33ftH2O/400inH2O overload: 10bar/1MPa/150psi
G Reference Accuracy: Standard
C Calibration; Unit: Sensor range; kPa/MPa
U5J Process Connection: Thread ANSI MNPT1, 316L, flush mount
A Membrane Material: 316L
1 Fill Fluid: Silicone oil
A Diaphragm Seal Connection: Direct

4-20 mA = 0 - 100 kPa

Adress: 1100 Montee Masson
Laval QC H7E 4P2

ct: **Hugo Chartier**

Telephone: **450-688-4012**
Fax
E-mail hchartier@norclair.ca

Manufacturer

Endress+hauser Canada Ltée
6800 Côte de liesse, suite 100
Ville Saint-Laurent, Québec, Canada
H4T 2A7


Telephone 514 733-0254**x2288**
Fax 514 733-2924
E-mail stephane.raymond@endress.com

Prepare by	Stephane Raymond

built as		Drawing for	
As is	X	Approbation:	X
Equivalent:		Information:	
Substitution:		Coordination:	

Tag number

Revision	Initial	Date
0	**SR**	**January 24 2019**



First Angle Projection

Disclaimer:

To ensure the accuracy of the information contained in this document every reasonable effort has been made. Endress+Hauser may not make any warranties,express or implied, with respect to the accuracy, the completeness or the technical or commercial usefulness of this document. Endress+Hauser may modify or replace this document any time.

© 24.01.2019 Endress+Hauser


Order Code :
PMP55-CD12ID1HGCU5JA1A

Product Description :
Cerabar M PMP55

www.addresses.endress.com

Endress+Hauser

People for Process Automation



1 *External grounding terminal (only for devices with certainly approvals or if "Measuring point" (TAG) is ordered)*
2 *Internal grounding terminal*
3 *Supply voltage → 22*
4 *4...20 mA for HART devices*
5 *For HART and FOUNDATION Fieldbus devices: With a handheld terminal, all the parameters can be configured anywhere along the bus line via menu operation.*
6 *Terminals*
7 *For HART devices: test terminals, see section "Taking 4 to 20 mA test signal" → 22*

3x units
FQIT-04-798
FQIT-04-799
FQIT-04-999

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng.
DATE: Jan 30, 2019

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-17 Flowmeter (polymer)

Date : 2019-01-25

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Hugo Chartier, Project Manager	E-mail: hchartier@norclair.ca
Phone : 450-688-4012 # 706	Cell. : 514-703-0263

Information, subcontractor or supplier	
Sub/supplier : Endress & Hauder	
Contact : Stéphane Raymond	Phone : 514-940-2288

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : Flowmeter (polymer)	
Drawing reference :	
Specification reference : **47 30 02 data sheets**	Division :
Article :	Number of pages : 7

CONSULTANT APPROVAL

See comments within.

SHOP DRAWINGS ARE REVIEWED UNLESS NOTED OTHERWISE
REVIEWED AS MODIFIED [X]
REVISE & RESUBMIT [ ]
SEAL & SIGNATURE REQUIRED [ ]
Stantec
DATE February 7/19
SIGNATURE Ellie Brun
REVIEW BY STANTEC IS FOR THE SOLE PURPOSE OF ASCERTAINING GENERAL CONFORMITY WITH DESIGN. CONTRACTOR IS RESPONSIBLE FOR DIMENSIONS, FABRICATION AND CONSTRUCTION METHODS, COORDINATION OF SUB-TRADES, DETAIL DESIGN OF COMPONENTS, AND ERRORS OR OMISSIONS ON SHOP DRAWINGS.

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Endress+Hauser
People for Process Automation

Drawing #	2002597302	Project	IQALUIT
		Customer	NORCLAIR

Instrument description

50H08-F3K0/0
50H08-HAAA1RA0BAAD+Z1
Promag 50H08, DN08 5/16"

H Process Connection: Cl.150, PVDF, flange ANSI B16.5
A Seal: O-ring, EPDM
A Electrodes: 1.4435/316L + grounding rings
A Calibration: 0.5%
1 Additional Test, certificate: w/o
R Approval: FM NI Cl. I Div. 2 / CSA Cl. I Div. 2
A Housing: Compact Alu, IP67 NEMA4X
0 Cable, Remote Version: Not used
B Cable Entry: Thread NPT 1/2
A Power Supply; Display: 85-260VAC, WEA, 2-line + push buttons, WEA= language DE+EN+FR+IT+ES+PT+NL
A Adjustment; Software Feature: Factory setup; basic version
D Output, Input: 4-20mA SIL HART + freq.+ status+stat.In
Z1 >>Marking: Tagging (TAG), see additional spec.Date: 24-Jan

→ Pulse output: 100ms on / 100ms off
→ Calibrate to 0-01 L/s

Adress: 1100 Montee Masson
Laval QC H7E 4P2

Contact: **Hugo Chartier**
Telephone: **450-688-4012**
Fax
E-mail hchartier@norclair.ca

Manufacturer

Endress+hauser Canada Ltée
6800 Côte de liesse, suite 100
Ville Saint-Laurent, Québec, Canada
H4T 2A7

Telephone 514 733-0254**x2288**
Fax 514 733-2924
E-mail stephane.raymond@endress.com

Prepare by	Stephane Raymond

built as		Drawing for	
As is	X	Approbation:	X
Equivalent:		Information:	
Substitution:		Coordination:	


Tag number FQIT-04-798
FQIT-04-799


Modification of diameter by E&H using their sizing tool and data provided by Veolia:
(https://www.ca.endress.com/en/product-tools/life-cycle-management/planning-engineering-traceability/applicator-select-size-instrument)
Flow range: 30-600 l/h
Pressure range: 80 psig
Temperature range: 0-20 degC
Viscosity: 400cP
Stantec to review sizing. HC, 2019-01-25

Revision	Initial	Date
0	**SR**	**January 25 2019**

4B

Tag: FQIT-04-798
FQIT-04-799





First Angle Projection

Disclaimer:

To ensure the accuracy of the information contained in this document every reasonable effort has been made. Endress+Hauser may not make any warranties,express or implied, with respect to the accuracy, the completeness or the technical or commercial usefulness of this document. Endress+Hauser may modify or replace this document any time.

© 25.01.2019 Endress+Hauser

Order Code :
50H08-HAAA1RA0BAAD+Z1

Product Description :
Promag 50H

www.addresses.endress.com

Endress+Hauser

People for Process Automation

u.B.

Terminal assignment, Promag 50

Order code for "Input/Output"	Terminal No. (inputs/outputs)			
	20 (+) / 21 (–)	22 (+) / 23 (–)	24 (+) / 25 (–)	26 (+) / 27 (–)
W	–	–	–	Current output HART
A	–	–	Frequency output	Current output HART
D	Status input	Status output	Frequency output	Current output HART
H	–	–	–	PROFIBUS PA
J	–	–	+5 V (external termination)	PROFIBUS DP
S	–	–	Frequency output, Ex i	Current output, Ex i, active, HART
T	–	–	Frequency output, Ex i	Current output, Ex i, passive, HART

Ground terminal → 🖹 10

4.B.

Endress+Hauser
People for Process Automation

Drawing #	2002597302	Project	IQALUIT
		Customer	NORCLAIR

Instrument description

50H15-DDR0/0
50H15-HAAA1RA0BAAD+Z1
Promag 50H15, DN15 1/2"

H Process Connection: Cl.150, PVDF, flange ANSI B16.5
A Seal: O-ring, EPDM
A Electrodes: 1.4435/316L + grounding rings
A Calibration: 0.5%
1 Additional Test, certificate: w/o
R Approval: FM NI Cl. I Div. 2 / CSA Cl. I Div. 2
A Housing: Compact Alu, IP67 NEMA4X
0 Cable, Remote Version: Not used
B Cable Entry: Thread NPT 1/2
A Power Supply; Display: 85-260VAC, WEA, 2-line + push buttons, WEA= language DE+EN+FR+IT+ES+PT+NL
A Adjustment; Software Feature: Factory setup; basic version
D Output, Input: 4-20mA SIL HART + freq.+ status+stat.In
Z1 >>Marking: Tagging (TAG), see additional spec.Date: 24-Jan

Pulse output: 1s on / 1s off

Calibrate to 0-1 L/s

Adress: 1100 Montee Masson
Laval QC H7E 4P2

Contact: **Hugo Chartier**
Telephone: **450-688-4012**
Fax
E-mail hchartier@norclair.ca

Manufacturer

Endress+hauser Canada Ltée
6800 Côte de liesse, suite 100
Ville Saint-Laurent, Québec, Canada
H4T 2A7

Telephone 514 733-0254**x2288**
Fax 514 733-2924
E-mail stephane.raymond@endress.com

Prepare by	Stephane Raymond

built as		Drawing for	
As is	X	Approbation:	X
Equivalent:		Information:	
Substitution:		Coordination:	


Tag number FQIT-04-999


Modification of diameter by E&H using their sizing tool and data provided by Veolia:
(https://www.ca.endress.com/en/product-tools/life-cycle-management/planning-engineering-traceability/applicator-select-size-instrument)
Flow range: 150-3000 l/h
Pressure range: 80 psig
Temperature range: 0-20 degC
Viscosity: 400cP
Stantec to review sizing.HC, 2019-01-25

Revision	Initial	Date
0	**SR**	**January 25 2019**

4/5

Tag: FQIT-04-999





First Angle Projection

Disclaimer:

To ensure the accuracy of the information contained in this document every reasonable effort has been made. Endress+Hauser may not make any warranties,express or implied, with respect to the accuracy, the completeness or the technical or commercial usefulness of this document. Endress+Hauser may modify or replace this document any time.

© 25.01.2019 Endress+Hauser

Order Code :
50H15-HAAA1RA0BAAD+Z1

Product Description :
Promag 50H

www.addresses.endress.com

Endress+Hauser

People for Process Automation

Terminal assignment, Promag 50

Order code for "Input/Output"	Terminal No. (inputs/outputs)			
	20 (+) / 21 (–)	22 (+) / 23 (–)	24 (+) / 25 (–)	26 (+) / 27 (–)
W	–	–	–	Current output HART
A	–	–	Frequency output	Current output HART
D	Status input	Status output	Frequency output	Current output HART
H	–	–	–	PROFIBUS PA
J	–	–	+5 V (external termination)	PROFIBUS DP
S	–	–	Frequency output, Ex i	Current output, Ex i, active, HART
T	–	–	Frequency output, Ex i	Current output, Ex i, passive, HART

Ground terminal → 10

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng

DATE: Mar 20, 2019

We think the panel is too small for all wires

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-18 CPL-901 Panel

Date : 2019-03-20

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Hugo Chartier, Project Manager	E-mail: hchartier@norclair.ca
Phone : 450-688-4012 # 706	Cell. : 514-703-0263

Information, subcontractor or supplier	
Sub/supplier : Entreprises LM	
Contact : Olivier Chalifoux-Lauzon	Phone : 514-904-2947

Information on the equipment

Speciality : **Instrumentation and Control**

Equipment : CPL-901

Drawing reference :

Specification reference : 47 30 01

Article :

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-IC-18 (2019-03-20)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☒ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED

☑ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2019-APR-04

BY David Hutchison

See notes within.
- Regarding panel capacity, utilize intermediate junction boxes and/or condulets to collect multiple runs of cable into one entry. Only OK for cables of similar type (eg P- cables of similar voltage, analog C- cables, and discrete C- cables).
- Utilize bottom entry for cables where possible
- Reduce excess spare cable and trim excess insulation in the panel
- PLC I/O card wiring harnesses (terminal strip to PLC card wiring only, not field wiring) may be reduced by one size (eg. #18 for analog signals, #16 for discrete signals).

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

City of Iqaluit

WWTP Upgrade

Process automation (Division 47)

CPL-901
R0: For approval before assembling

Dessiné Par / Drawn By: O. Chalifoux-Lauzon Préparé Par / Prepared By: O. Chalifoux-Lauzon Dernière maj / Last update: 19 mars 2019	Projet / Project: WWTP Upgrade/CPL-901 ---- Dessin De / Drawing Of: Cover Page Page / de: 01 / 25	Client / Customer: City of Iqaluit ---- Projet / Project: P103901 / xxxxxx Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG	Entreprises L.M. inc. 3006 Ste-Catherine est, Montréal, Québec, H1W 2B8 Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526


ITEM	DESCRIPTION	MANUFACTURER	PART NUMBER	QTY	
1	TYPE 12 ENCLOSURE (72X60X24)	HOFFMAN	A726024FSDG	1	
2	FULL SIZE MOUNTING PANEL	HOFFMAN	A72P48F1	1	
3	SIDE MOUNTING PANEL	HOFFMAN	A72SMP20	2	
4	LAPTOP FOLDING SHELF (LOCATED ON EXTERIOR OF PLC-900)	HOFFMAN	AA615HLF1818	1	
5	120 VAC FLUORESCENT LIGHT KIT	HOFFMAN	LF120V18	1	
6	DOOR SWITCH	HOFFMAN	ALFSWD	1	
7	FLUORESCENT LIGHT BULB	HOFFMAN	F8T5	1	
8	PLC POWER SUPPLY	AB	1756-PA75/B	1	
9	CONTROLLOGIX CONTROLLER	AB	1756-L82E	1	
10	DC DIGITAL INPUT MODULE	AB	1756-IB32	5	
11	Left Blank Intentionally	-	-	-	
12	RELAY OUTPUT MODULE, INDIVIDUALLY ISOLATED	AB	1756-OW16I	3	
13	Left Blank Intentionally	-	-	-	
14	ANALOG INPUT MODULE	AB	1756-IF16	3	
15	Left Blank Intentionally	-	-	-	
16	ANALOG OUTPUT MODULE	AB	1756-OF8I	2	
17	SLOT FILLER	AB	1756N-2	2	
18	17 SLOT CHASSIS	AB	1756-A17	1	
19	30A SINGLE POLE CIRCUIT BREAKER	AB	1492-SPM1B030	1	
20	24VDC POWER SUPPLY 20A	AB	1606-XLS480E	2	
21	15A SINGLE POLE CIRCUIT BREAKER	AB	1492-SP1B150	1	
22	10A SINGLE POLE CIRCUIT BREAKER	AB	1492-SP1B100	1	
23	WSI 4/2 FUSED TERMINAL BLOCK	WEIDMULLER	1880410000/1880420000	AS REQ.	
24	WSKI 2.5 FEED-THROUGH TERMINAL BLOCK	WEIDMULLER	1020000000	AS REQ.	
22	WTR 2.5 KNIFE SWITCH TERMINAL BLOCK	WEIDMULLER	1855610000	AS REQ.	
23	WPE 1.5/ZZ PROTECTIVE EARTH TERMINAL	WEIDMULLER	1016500000	AS REQ.	NOTE 1
24	2-TIER FEED THROUGH TERMINAL BLOCK	PHOENIX CONTACT	UTB 2,5 - 3044636	AS REQ.	
25	END COVERS FOR ITEM 24	PHOENIX CONTACT	UTTB 2,5 - 3044636	AS REQ.	
26	2-TIER FEED SPRING CAGE TERMINAL BLOCK (2 TIER + GROUND)	PHOENIX CONTACT	ST 2,5-PE/I/L-3036097	AS REQ.	
27	END COVERS FOR ITEM 26	PHOENIX CONTACT	D-ST 2,5-3L-3036660	AS REQ.	
28	FUSED MODULAR TERMINAL BLOCK WITH FEED THROUGH	PHOENIX CONTACT	UT 4-LHIESS-3214325	AS REQ.	
29	PLUG IN BRIDGE (10 POSITIONS)	PHOENIX CONTACT	FBS 10-6 - 3030365	AS REQ.	
30	PLUG IN BRIDGE (20 POSITIONS)	PHOENIX CONTACT	FBS 20-6-3030365	AS REQ.	
31	TERMINAL BLOCK MARKERS	PHOENIX CONTACT	UM8 - 0830943	AS REQ.	NOTE 1
32	WQB B/24 CROSS CONNECTION STRIPS	WEIDMULLER	1579060000	AS REQ.	
33	SCHT SS GROUP LABEL CARRIER	WEIDMULLER	1631930000	AS REQ.	
34	STR SS PROTECTIVE STRIPS	WEIDMULLER	1631940000	AS REQ.	
35	WEW 35/2 END BRACKET	WEIDMULLER	1061200000	AS REQ.	
36	WAP END PLATE (WDU/SS)	WEIDMULLER	1050000000	AS REQ.	
37	WAP END PLATE (WSI/S)	WEIDMULLER	1880450000	AS REQ.	
38	WS 12/5 TERMINAL MARKERS, CUSTOM NUMBERS	WEIDMULLER	1609870000	AS REQ.	
39	WS 12/6 TERMINAL MARKERS, CUSTOM NUMBERS	WEIDMULLER	1609910000	AS REQ.	
40	DIN RAIL TS35 SLOTTED	WEIDMULLER	5145000000	AS REQ.	
41	FUSE HOLDER (DIN RAIL MOUNT)	WEIDMULLER	7914760001	1	
42	GROUND BAR NSCH 15X2 80A	WEIDMULLER	2802000000	1	
43	PRESSURE PIECE DKSUE	WEIDMULLER	2801000000	AS REQ.	
44	CLAMPING SCREW BFSC M5X8	WEIDMULLER	2967000000	AS REQ.	
45	BUSBAR HOLDER BASE SH1	WEIDMULLER	4014600000	AS REQ.	
46	BUSBAR HOLDER CLIP SH1	WEIDMULLER	6359000000	AS REQ.	
47	GROUND LUG #2/0	T&B	ADR21	4	
48	WIRE DUCT 3"X4"	PANDUIT	G3X4LG6	AS REQ.	
49	3" WIRE DUCT COVER	PANDUIT	C3LG6	AS REQ.	
50	1A GLASS FUSE	BUSSMANN	GMA-1-R	AS REQ.	
51	2A GLASS FUSE	BUSSMANN	GMA-2-R	AS REQ.	
52	4A GLASS FUSE	BUSSMANN	GMA-4-R	AS REQ.	
53	5A GLASS FUSE	BUSSMANN	GMA-5-R	AS REQ.	
54	10A GLASS FUSE	BUSSMANN	GMA-10-R	AS REQ.	
55	15A GLASS FUSE	BUSSMANN	GMA-15-R	AS REQ.	
56	200mA GLASS FUSE	WEIDMULLER	430400000	AS REQ.	
57	ASK 1EN/LD FUSED TERMINAL BLOCK C/W LED INDICATION	WEIDMULLER	9123140001	AS REQ.	
58	16 PORT ETHERNET SWITCH, C/W DIN MOUNT OPTION	N-TRON	116TX	2	
59	Left Blank Intentionally	-	-	-	
60	INTRINSIC SAFETY BARRIER 2-CHANNEL, RELAY OUT, 24VDC	TURCK	IM1-22EX-R	4	
61	UNINTERRUPTIBLE POWER SUPPLY (UPS)	EATON POWERWARE	9130 3000	1	
62	UPS RELAY OUTPUT CARD	EATON POWERWARE	10140618	1	
63	120VAC RAIL MOUNT SIMPLEX RECEPTACLE	WEIDMULLER	9915480000	2	
64	PROTALK PLUS ALARM DIALER	BARNETT ENGINEERING	B1290	1	
65	PROTALK PLUS BATTERY BACKUP AND POWER SUPPLY	BARNETT ENGINEERING	B1294 & B1256	1	
66	SURGE PROTECTION DEVICE (SPD) 120VAC, 15A, C/W FORM C DRY RELAY CONTACTS OPTION	TOTAL PROTECTION SOLUTIONS	TK-LTE120-15A-DIN2-DRC	1	
67	Left Blank Intentionally	-	-	-	
68	OMRON RELAY WITH LED INDICATOR	OMRON	G2R-1-SND	3	
69	OMRON RELAY SOCKET	OMRON	P2RF-05-E	3	
70	UPS WRAP-AROUND BY PASS, 15A, 120VAC, C/W AUTOMATIC TRANSFER SWITCH AND FORM C OUTPUT	ALWAYS ON	BPS12015-ATS-DCC	1	
71	24 VDC POWER SUPPLY REDUNDANCY MODULE	AB	1606-XLSRED40	1	
72	15A, 120 VAC, TAMPER RESISTENT DUPLEX RECEPTACLE	LEVITION	T5320-W	1	
73	CLEAR PLASTIC DUPLEX RECEPTACLE COVER	INTERMATIC	WP3100C	1	
74	RJ45 CAT 6 ETHERNET DATA PORT	WEIDMULLER	IE-FCM-RJ45-C	1	
75	Left Blank Intentionally	-	-	-	
76	REMOVEABLE TERMINAL BLOCK	AB	1756-TBCH	13	
77	REMOVEABLE TERMINAL BLOCK	AB	1756-TBNH	1	
78	15.6" HMI TOUCHSCREEN MONITOR c/w 24V/12V CONVERTER	ELO	E331799	1	
79	HMI COMPUTER SYSTEM	AXIOMTEK	eBOX560-880-FL	1	

1 BILL OF MATERIALS
PC-203 NO SCALE

NAMEPLATE SCHEDULE

ITEM	TEXT DESCRIPTION	COLOUR	SIZE (WxH)	QTY
A	IQALUIT WWTP/SECONDARY/TREATMENT/INSTRUMENTATION/CONTROL PANEL/CP-901	BLK/WHT Letters	150X110	1
B	WARNING/VOLTAGES FROM MORE/THAN ONE SOURCE	RED/WHT Letters	175X75	1
C	LAPTOP ONLY	BLK/WHT Letters	100X25	1
D	UPS	BLK/WHT Letters	75X25	1
E	WIRELESS ONLY	BLK/WHT Letters	100X25	1

2 NAMEPLATE SCHEDULE
PC-203 NO SCALE




UPS ALARM STATUS WIRING DIAGRAM

3 UPS RELAY CARD
PC-203 NO SCALE


Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: Bill of materials	Page / de: 02 / 25	Projet / Project: P103901 / xxxxxx
			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG

Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
	Dessin De / Drawing Of: Mechanical drawing	Page / de: 03 / 25	Projet / Project: P103901 / xxxxxx
Dernière maj / Last update: 19 mars 2019			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG

3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: Mechanical layout	Page / de: 04 / 25	Projet / Project: P103901 / xxxxxx
			Dessin N° / Drawing N° : WWTP IQALUIT CPL901_R00.DWG

3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: Terminals (1/2)	Page / de: 05 / 25	Projet / Project: P103901 / xxxxxx — Dessin N° / Drawing N° : WWTP IQALUIT CPL901_R00.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



G

TS10-TS12 ANALOG INPUT

PC-202 | PC-208 NO SCALE (16 INPUT)




H


TS13-TS14 ANALOG OUTPUT

PC-202 | PC-208 NO SCALE (8 OUTPUT)

Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: Terminals (2/2) — Page / de: 06 / 25	Projet / Project: P103901 / xxxxxx — Dessin N° / Drawing N° : WWTP IQALUIT CPL901_R00.DWG	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8 Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901 ----	Client / Customer: City of Iqaluit ----	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon		Projet / Project: P103901 / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: PLC Rack	Page / de: 07 / 25	Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: Controls (1/2)	Page / de: 08 / 25	Projet / Project: P103901 / xxxxxx
			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG

Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



ANTICIPATED DRAWS		
SOURCE	CURRENT	POWER (W)
CB1	16A	1920
120VAC UPS	15A	1800
24VDC POWER SUPPLY	6.75A	162


Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
	Dessin De / Drawing Of: Controls (2/2)	Page / de: 09 / 25	Projet / Project: P103901 / xxxxxx
Dernière maj / Last update: 19 mars 2019			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG

3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526

DESCRIPTION	PLC TAG	TS01		DC INPUT MODULE 1756-IB32 SLOT 01
			FROM FUDC1 SEE DRAWING PAGE 9	
PROCESS AERATION BLOWER INCOMING LOW PRESSURE ALARM	PAL-02-130	1	FUDC1	
		2		1 I:01/00
B-02-110 RUN STATUS	YI-02-110	3	SD1/	TS01-
		4		2 I:01/01
B-02-110 FAULT STATUS	XA-02-110	5	SD1/	TS01-
		6		3 I:01/02
B-02-110 AUTO STATUS	HI-02-110	7	SD1/	TS01-
		8		4 I:01/03
B-02-110 MOTOR FAULT	UA-02-110	9	SD1/	TS01-
		10		5 I:01/04
B-02-110 ESD TRIGGERED	HA-02-110	11	SD1/	TS01-
		12		6 I:01/05
F-02-115 RUN STATUS	YI-02-115	13	SD1/	TS01-
		14		7 I:01/06
F-02-115 FAULT STATUS	XA-02-115	15	SD1/	TS01-
		16		8 I:01/07
F-02-115 AUTO STATUS	HI-02-115	17	SD1/	TS01-
		18		9 I:01/08
PROCESS AERATION F-02-115 HIGH PRESSURE SWITCH	PSH-02-118	19	SD1/	TS01-
		20		10 I:01/09
PROCESS AERATION B-02-110 LOW PRESSURE SWITCH	PSL-02-108	21	SD1/	TS01-
		22		11 I:01/10
PROCESS AERATION B-02-110 HIGH TEMPERATURE SWITCH	TSH-02-180	23	SD1/	TS01-
		24		12 I:01/11
PROCESS AIR MBBR #2 FV-02-150 FAULT STATUS	XA-02-150	25	SD1/	TS01-
		26		13 I:01/12
PROCESS AIR MBBR #2 FV-02-150 AUTO STATUS	HI-02-150	27	SD1/	TS01-
		28		14 I:01/13
PROCESS AIR MBBR #2 FQIT-02-152 FLOW TOTALIZATION PULSE	FQI-02-152	29	SD1/	TS01-
		30		15 I:01/14
T-02-210 PRIMARY EFFLUENT KNIFE VALVE OPEN STATUS	ZSO-02-211	31	SD1/	TS01-
		32		16 I:01/15
				17 GND-0
				18 GND-0
T-02-210 PRIMARY EFFLUENT KNIFE VALVE CLOSED STATUS	ZSC-02-211	33	SD1/	TS01-
		34		19 I:01/16
T-02-210 PRIMARY EFFLUENT KNIFE VALVE OPEN STATUS	ZSO-02-221	35	SD1/	TS01-
		36		20 I:01/17
T-02-210 PRIMARY EFFLUENT KNIFE VALVE CLOSED STATUS	ZSC-02-221	37	SD1/	TS01-
		38		21 I:01/18
T-02-210 CELL 1-1 GAS ANALYZER FAULT STATUS	XA-02-211	39	SD1/	TS01-
		40		22 I:01/19
T-02-210 CELL 1-1 HIGH LEVEL SWITCH	LSH-02-213	41	SD1/	TS01-
		42		23 I:01/20
T-02-210 CELL 1-2 GAS ANALYZER FAULT STATUS	XA-02-212	43	SD1/	TS01-
		44		24 I:01/21
T-02-210 CELL 1-2 HIGH LEVEL SWITCH	LSH-02-214	45	SD1/	TS01-
		46		25 I:01/22
MBBR H2S GAS DETECTION FAULT STATUS	XA-02-909	47	SD1/	TS01-
		48		26 I:01/23
DAF #1 H2S GAS DETECTION FAULT STATUS	XA-02-907	49	SD1/	TS01-
		50		27 I:01/24
DAF #1 RUN STATUS	YI-02-310	51	SD1/	TS01-
		52		28 I:01/25
DAF #1 FAULT STATUS	XA-02-310	53	SD1/	TS01-
		54		29 I:01/26
P-04-770 RUN STATUS	YI-04-770	55	SD1/	TS01-
		56		30 I:01/27
P-04-770 FAULT STATUS	XA-04-770	57	SD1/	TS01-
		58		31 I:01/28
P-04-770 AUTO STATUS	HI-04-770	59	SD1/	TS01-
		60		32 I:01/29
P-04-770 MOTOR FAULT	UA-04-770	61	SD1/	TS01-
		62		33 I:01/30
P-04-770 ESD TRIGGERED	HA-04-770	63	SD1/	TS01-
		64		34 I:01/31
		65	DC GND COM1	TS01- 35 GND-1
			FROM COM1 SEE DRAWING PAGE 9	36 GND-1



Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901 ----	Client / Customer: City of Iqaluit ----	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon		Projet / Project: P103901 / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: IO	Page / de: 10 / 25	Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



DESCRIPTION	PLC TAG	TSO2
B-02-120 RUN STATUS	YI-02-120	1
B-02-120 FAULT STATUS	XA-02-120	2
B-02-120 AUTO STATUS	HI-02-120	3
B-02-120 MOTOR FAULT	UA-02-120	4
B-02-120 ESD TRIGGERED	HA-02-120	5
F-02-125 RUN STATUS	YI-02-125	6
F-02-125 FAULT STATUS	XA-02-125	7
F-02-125 AUTO STATUS	HI-02-125	8
PROCESS AERATION F-02-125 HIGH PRESSURE SWITCH	PSH-02-128	9
PROCESS AERATION B-02-120 LOW PRESSURE SWITCH	PSL-02-143	10
PROCESS AERATION B-02-120 HIGH TEMPERATURE SWITCH	TSH-02-185	11
PROCESS AIR MBBR #2 FV-02-155 FAULT STATUS	XA-02-155	12
PROCESS AIR MBBR #2 FV-02-155 AUTO STATUS	HI-02-155	13
PROCESS AIR MBBR #2 FQIT-02-156 FLOW TOTALIZATION PULSE	FQI-02-156	14
T-02-220 CELL 2-1 GAS ANALYZER FAULT STATUS	XA-02-221	15
T-02-220 CELL 2-1 HIGH LEVEL SWITCH	LSH-02-223	16
T-02-220 CELL 2-2 GAS ANALYZER FAULT STATUS	XA-02-222	33
T-02-220 CELL 2-2 HIGH LEVEL SWITCH	LSH-02-224	34
DAF #2 H2S GAS DETECTION FAULT STATUS	XA-02-908	35
DAF #2 RUN STATUS	YI-02-320	36
DAF #2 FAULT STATUS	XA-02-320	37
T-02-310 MIXED LIQOUR BFV OPEN STATUS	ZSO-02-312	38
T-02-310 MIXED LIQOUR BFV CLOSED STATUS	ZSC-02-312	39
T-02-310 DAF #1 HIGH LEVEL ALARM	LAH-02-330	40
DAF #1 THICKENED WATER LOW LEVEL ALARM	LAL-02-333	41
DAF #1 THICKENED WATER HIGH LEVEL ALARM	LAH-02-332	42
FINAL EFFLUENT FQIT-02-328 FLOW TOTALIZATION PULSE	FQI-02-328	43
P-04-780 RUN STATUS	YI-04-780	44
P-04-780 FAULT STATUS	XA-04-780	45
P-04-780 AUTO STATUS	HI-04-780	46
P-04-780 MOTOR FAULT	UA-04-780	47
P-04-780 ESD TRIGGERED	HA-04-780	48

FROM FUDC2
SEE DRAWING PAGE 9

FUDC2

SO2/

DC GND
COM2


FROM COM2
SEE DRAWING PAGE 9

DC INPUT MODULE
1756-IB32
SLOT 02


TO:02-	1	I:02/00
TO:02-	2	I:02/01
TO:02-	3	I:02/02
TO:02-	4	I:02/03
TO:02-	5	I:02/04
TO:02-	6	I:02/05
TO:02-	7	I:02/06
TO:02-	8	I:02/07
TO:02-	9	I:02/08
TO:02-	10	I:02/09
TO:02-	11	I:02/10
TO:02-	12	I:02/11
TO:02-	13	I:02/12
TO:02-	14	I:02/13
TO:02-	15	I:02/14
TO:02-	16	I:02/15
	17	GND-0
	18	GND-0
TO:02-	19	I:02/16
TO:02-	20	I:02/17
TO:02-	21	I:02/18
TO:02-	22	I:02/19
TO:02-	23	I:02/20
TO:02-	24	I:02/21
TO:02-	25	I:02/22
TO:02-	26	I:02/23
TO:02-	27	I:02/24
TO:02-	28	I:02/25
TO:02-	29	I:02/26
TO:02-	30	I:02/27
TO:02-	31	I:02/28
TO:02-	32	I:02/29
TO:02-	33	I:02/30
TO:02-	34	I:02/31
TO:02-	35	GND-1
TO:02-	36	GND-1

Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: IO	Page / de: 11 / 25	Projet / Project: P103901 / xxxxxx
			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG
			Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526

DESCRIPTION	PLC TAG	TS03		DC INPUT MODULE 1756-IB32 SLOT 03
			FROM FUDC3 SEE DRAWING PAGE 9	
		1	FUDC3	
B-02-130 RUN STATUS	YI-02-130	2	S03/	TS03- 1 I:03/00
B-02-130 FAULT STATUS	XA-02-130	3	S03/	TS03- 2 I:03/01
		4		
B-02-130 AUTO STATUS	HI-02-130	5	S03/	TS03- 3 I:03/02
		6		
B-02-130 MOTOR FAULT	UA-02-130	7	S03/	TS03- 4 I:03/03
		8		
B-02-130 ESD TRIGGERED	HA-02-130	9	S03/	TS03- 5 I:03/04
		10		
F-02-135 RUN STATUS	YI-02-135	11	S03/	TS03- 6 I:03/05
		12		
F-02-135 FAULT STATUS	XA-02-135	13	S03/	TS03- 7 I:03/06
		14		
F-02-135 AUTO STATUS	HI-02-135	15	S03/	TS03- 8 I:03/07
		16		
PROCESS AERATION F-02-135 HIGH PRESSURE SWITCH	PSH-02-138	17	S03/	TS03- 9 I:03/08
		18		
PROCESS AERATION B-02-130 LOW PRESSURE SWITCH	PSL-02-146	19	S03/	TS03- 10 I:03/09
		20		
PROCESS AERATION B-02-130 HIGH TEMPERATURE SWITCH	TSH-02-190	21	S03/	TS03- 11 I:03/10
		22		
PROCESS AIR MBBR #2 FV-02-170 FAULT STATUS	XA-02-170	23	S03/	TS03- 12 I:03/11
		24		
PROCESS AIR MBBR #2 FV-02-170 AUTO STATUS	HI-02-170	25	S03/	TS03- 13 I:03/12
		26		
PROCESS AIR MBBR #2 FQT-02-172 FLOW TOTALIZATION PULSE	FQI-02-172	27	S03/	TS03- 14 I:03/13
		28		
T-02-320 MIXED LIQUOR BFV OPEN STATUS	ZSO-02-332	29	S03/	TS03- 15 I:03/14
		30		
T-02-320 MIXED LIQUOR BFV CLOSED STATUS	ZSC-02-332	31	S03/	TS03- 16 I:03/15
		32		
				17 GND-0
				18 GND-0
T-02-320 DAF #2 HIGH LEVEL ALARM	LAH-03-342	33	S03/	TS03- 19 I:03/16
		34		
DAF #2 THICKENED WATER LOW LEVEL ALARM	LAL-02-343	35	S03/	TS03- 20 I:03/17
		36		
DAF #2 THICKENED WATER HIGH LEVEL ALARM	LAH-02-342	37	S03/	TS03- 21 I:03/18
		38		
PDS-04-700 RUN STATUS	YI-04-700	39	S03/	TS03- 22 I:03/19
		40		
PDS-04-700 FAULT STATUS	XA-04-700	41	S03/	TS03- 23 I:03/20
		42		
PDS-04-700 HIGH LEVEL ALARM	LAH-04-700	43	S03/	TS03- 24 I:03/21
		44		
PDS-04-700 LOW PRESSURE ALARM	PAL-04-700	45	S03/	TS03- 25 I:03/22
		46		
PDS-04-700 ESD TRIGGERED	HA-04-700	47	S03/	TS03- 26 I:03/23
		48		
AIT-03-910 H2S GAS DETECTOR FAULT STATUS	XA-03-910	49	S03/	TS03- 27 I:03/24
		50		
DAF #1 POLYMER FLOW TOTALIZATION PULSE	FQI-04-798	51	S03/	TS03- 28 I:03/25
		52		
DAF #2 POLYMER FLOW TOTALIZATION PULSE	FQI-04-799	53	S03/	TS03- 29 I:03/26
		54		
P-04-790 RUN STATUS	YI-04-790	55	S03/	TS03- 30 I:03/27
		56		
P-04-790 FAULT STATUS	XA-04-790	57	S03/	TS03- 31 I:03/28
		58		
P-04-790 AUTO STATUS	HI-04-790	59	S03/	TS03- 32 I:03/29
		60		
P-04-790 MOTOR FAULT	UA-04-790	61	S03/	TS03- 33 I:03/30
		62		
P-04-790 ESD TRIGGERED	HA-04-790	63	S03/	TS03- 34 I:03/31
		64	DC GND	
		65	COM3	TS03- 35 GND-1
			FROM COM3 SEE DRAWING PAGE 9	36 GND-1




Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901 ----	Client / Customer: City of Iqaluit ----	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon		Projet / Project: P103901 / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: IO	Page / de: 12 / 25	Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




DESCRIPTION	PLC TAG	TS04		DC INPUT MODULE 1756-IB32 SLOT 04
		FROM FUDC4 SEE DRAWING PAGE 9		
P-02-610 RUN STATUS	YI-02-610	1	S04/	I:04/00
P-02-610 FAULT STATUS	XA-02-610	2	S04/	I:04/01
P-02-610 AUTO STATUS	HI-02-610	3	S04/	I:04/02
P-02-610 MOTOR FAULT	UA-02-610	4	S04/	I:04/03
P-02-610 ESD TRIGGERED	HA-02-610	5	S04/	I:04/04
TWAS PUMP #1 HIGH PRESSURE SWITCH	PAH-02-619	6	S04/	I:04/05
T-03-630 TWAS AERATED TANK #1 LEVEL FAULT STATUS	XA-03-111	7	S04/	I:04/06
T-03-630 TWAS AERATED TANK #1 HIGH HIGH LEVEL	LAHH-03-112	8	S04/	I:04/07
T-03-630 TWAS AERATED TANK #1 LOW LOW LEVEL	LALL-03-113	9	S04/	I:04/08
P-03-630 RUN STATUS	YI-03-630	10	S04/	I:04/09
P-03-630 FAULT STATUS	XA-03-630	11	S04/	I:04/10
P-03-630 AUTO STATUS	HI-03-630	12	S04/	I:04/11
P-03-630 MOTOR FAULT	UA-03-630	13	S04/	I:04/12
P-03-630 ESD TRIGGERED	HA-03-630	14	S04/	I:04/13
BFP FEED PUMP #1 HIGH PRESSURE SWITCH	PAH-03-669	15	S04/	I:04/14
BFP-03-650 FQIT-03-695 INLET FLOW TOTALIZATION PULSE	FQI-03-695	16	S04/	I:04/15
		17		GND-0
		18		GND-0
BFP-03-650 RUN STATUS	YI-03-650	19	S04/	I:04/16
BFP-03-650 FAULT STATUS	XA-03-650	20	S04/	I:04/17
BFP-03-650 ESD TRIGGERED	HA-03-650	21	S04/	I:04/18
P-04-970 RUN STATUS	YI-04-970	22	S04/	I:04/19
P-04-970 FAULT STATUS	XA-04-970	23	S04/	I:04/20
P-04-970 AUTO STATUS	HI-04-970	24	S04/	I:04/21
P-04-970 MOTOR FAULT	UA-04-970	25	S04/	I:04/22
P-04-970 ESD TRIGGERED	HA-04-970	26	S04/	I:04/23
P-04-970 HIGH PRESSURE SWITCH	PAH-04-987	27	S04/	I:04/24
BFP POLYMER FQIT-04-999 FLOW TOTALIZATION PULSE	FQI-04-798	28	S04/	I:04/25
INCOMING POTABLE WATER FLOW TOTALIZATION PULSE	FQI-04-300	29	S04/	I:04/26
AIT-02-905 H2S GAS ANALYZER FAULT STATUS	XA-02-905	30	S04/	I:04/27
AIT-03-906 H2S GAS ANALYZER FAULT STATUS	XA-03-906	31	S04/	I:04/28
AIT-03-907 H2S GAS ANALYZER FAULT STATUS	XA-03-907	32	S04/	I:04/29
AIT-03-908 H2S GAS ANALYZER FAULT STATUS	XA-03-908	33	S04/	I:04/30
AIT-03-909 GAS ANALYZER FAULT STATUS	XA-03-909	34	S04/	I:04/31
		35	DC GND	GND-1
		36	COM4	GND-1
		FROM COM4 SEE DRAWING PAGE 9		

Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901 ----	Client / Customer: City of Iqaluit ----	Entreprises L.M. inc
Projeté Par / Proposed By: O. Chalifoux-Lauzon		Projet / Project: P103901 / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: IO	Page / de: 13 / 25	Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



DESCRIPTION	PLC TAG	TS05	DC INPUT MODULE 1756-IB32 SLOT 05
		FROM FUDC5 SEE DRAWING PAGE 9	
P-02-620 RUN STATUS	YI-02-620	1 FUDC5 S05/	TS05- 1 t:05/00
P-02-620 FAULT STATUS	XA-02-620	2 S05/	TS05- 2 t:05/01
P-02-620 AUTO STATUS	HI-02-620	3 S05/	TS05- 3 t:05/02
P-02-620 MOTOR FAULT	UA-02-620	4 S05/	TS05- 4 t:05/03
P-02-620 ESD TRIGGERED	HA-02-620	5 S05/	TS05- 5 t:05/04
TWAS PUMP #2 HIGH PRESSURE SWITCH	PAH-02-639	6 S05/	TS05- 6 t:05/05
T-03-640 TWAS AERATED TANK #2 LEVEL FAULT STATUS	XA-03-121	7 S05/	TS05- 7 t:05/06
T-03-640 TWAS AERATED TANK #2 HIGH HIGH LEVEL	LAHH-03-122	8 S05/	TS05- 8 t:05/07
T-03-640 TWAS AERATED TANK #2 LOW LOW LEVEL	LALL-03-123	9 S05/	TS05- 9 t:05/08
P-03-640 RUN STATUS	YI-03-640	10 S05/	TS05- 10 t:05/09
P-03-640 FAULT STATUS	XA-03-640	11 S05/	TS05- 11 t:05/10
P-03-640 AUTO STATUS	HI-03-640	12 S05/	TS05- 12 t:05/11
P-03-640 MOTOR FAULT	UA-03-640	13 S05/	TS05- 13 t:05/12
P-03-640 ESD TRIGGERED	HA-03-640	14 S05/	TS05- 14 t:05/13
BFP FEED PUMP #2 HIGH PRESSURE SWITCH	PAH-03-689	15 S05/	TS05- 15 t:05/14
PDS-04-900 RUN STATUS	YI-04-900	16 S05/	TS05- 16 t:05/15
			17 GND-0
			18 GND-0
PDS-04-900 FAULT STATUS	XA-04-900	33 S05/	TS05- 19 t:05/16
PDS-04-900 LOW LEVEL ALARM	LAL-04-900	34 S05/	TS05- 20 t:05/17
PDS-04-900 ESD TRIGGERED	HA-04-900	35 S05/	TS05- 21 t:05/18
P-04-980 RUN STATUS	YI-04-980	36 S05/	TS05- 22 t:05/19
P-04-980 FAULT STATUS	XA-04-980	37 S05/	TS05- 23 t:05/20
P-04-980 AUTO STATUS	HI-04-980	38 S05/	TS05- 24 t:05/21
P-04-980 MOTOR FAULT	UA-04-980	39 S05/	TS05- 25 t:05/22
P-04-980 ESD TRIGGERED	HA-04-980	40 S05/	TS05- 26 t:05/23
P-04-980 HIGH PRESSURE SWITCH	PAH-04-987	41 S05/	TS05- 27 t:05/24
GENERATOR RUN STATUS	YI-02-800	42 S05/	TS05- 28 t:05/25
GENERATOR FAULT STATUS	XA-02-800A	43 S05/	TS05- 29 t:05/26
GENERATOR AUTO STATUS	HI-02-800	44 S05/	TS05- 30 t:05/27
GENERATOR BATTERY CHARGER FAULT	XA-02-800B	45 S05/	TS05- 31 t:05/28
GENERATOR BATTERY VOLTAGE LOW	EAL-02-800	46 S05/	TS05- 32 t:05/29
GENERATOR FUEL LEVEL LOW	LAL-02-800	47 S05/	TS05- 33 t:05/30
AIT-03-909 GAS ANALYZER FAULT STATUS	XA-03-909	48 S05/	TS05- 34 t:05/31
		49 DC GND	TS05- 35 GND-1
		50 COM5	TS05- 36 GND-1
		FROM COM5 SEE DRAWING PAGE 9	


Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: IO	Page / de: 14 / 25	Projet / Project: P103901 / xxxxxx
			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG
			Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




DESCRIPTION	PLC TAG	TS06		DC INPUT MODULE 1756-IB32 SLOT 06	
			FROM FUDC6 SEE DRAWING PAGE 9		
		1	FUDC6		
UPS (CPL-901) FAULT STATUS	XA-02-961	2	S06/	1	I:06/00
UPS (CPL-901) BATTERY LOW	EAL-02-961	3	S06/	2	I:06/01
UPS (CPL-901) ON BYPASS	ES-02-961A	4	S06/	3	I:06/02
UPS (CPL-901) ON UTILITY	ES-02-961B	5	S06/	4	I:06/03
P-02-620 ESD TRIGGERED	HA-02-620	6	S06/	5	I:06/04
DC POWER SUPPLY #1 (CPL-901) DC VOLTAGE FAULT INDICATION	XA-02-970	7	S06/	6	I:06/05
DC POWER SUPPLY #2 (CPL-901) DC VOLTAGE FAULT INDICATION	XA-02-971	8	S06/	7	I:06/06
CPL-901 SURGE PROTECTION DEVICE SURGE INDICATION	XA-02-900	9	S06/	8	I:06/07
UPS BYPASS SWITCH (CPL-901) IN BYPASS MODE	ES-02-961	10	S06/	9	I:06/08
PANEL A FEEDER BREAKER STATUS INDICATION	ES-02-810	11	S06/	10	I:06/09
AUTOMATIC TRANSFER SWITCH UTILITY POWER AVAILABLE	EY-02-802A	12	S06/	11	I:06/10
AUTOMATIC TRANSFER SWITCH EMERGENCY POWER AVAILABLE	EY-02-802B	13	S06/	12	I:06/11
AUTOMATIC TRANSFER SWITCH ON UTILITY POWER	ES-02-802A	14	S06/	13	I:06/12
AUTOMATIC TRANSFER SWITCH ON EMERGENCY POWER	ES-02-802B	15	S06/	14	I:06/13
SPARE	–	16	S06/	15	I:06/14
SPARE	–	17	S06/	16	I:06/15
		18		17	GND-0
		19		18	GND-0
SPARE	–	20	S06/	19	I:06/16
SPARE	–	21	S06/	20	I:06/17
SPARE	–	22	S06/	21	I:06/18
SPARE	–	23	S06/	22	I:06/19
SPARE	–	24	S06/	23	I:06/20
SPARE	–	25	S06/	24	I:06/21
SPARE	–	26	S06/	25	I:06/22
SPARE	–	27	S06/	26	I:06/23
SPARE	–	28	S06/	27	I:06/24
SPARE	–	29	S06/	28	I:06/25
SPARE	–	30	S06/	29	I:06/26
SPARE	–	31	S06/	30	I:06/27
SPARE	–	32	S06/	31	I:06/28
SPARE	–	33	S06/	32	I:06/29
SPARE	–	34	S06/	33	I:06/30
SPARE	–	35	S06/	34	I:05/31
		36	DC GND	35	GND-1
		37	COM6	36	GND-1
			FROM COM6 SEE DRAWING PAGE 9		


Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: IO	Page / de: 15 / 25	Projet / Project: P103901 / xxxxxx
			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG

Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526





Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: IO	Page / de: 16 / 25	Projet / Project: P103901 / xxxxxx
			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG
			Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



DESCRIPTION	PLC TAG	TSOB
PROCESS AERATION BLOWER 2 RUN COMMAND	YC-02-120	SOB/
PROCESS AERATION BLOWER FAN 2 RUN COMMAND	YC-02-125	SOB/
T-02-220 PRIMARY EFFLUENT OUTFLOW KNIFE VALVE CLOSE COMMAND	ZCC-02-221	SOB/
T-02-220 PRIMARY EFFLUENT OUTFLOW KNIFE VALVE OPEN COMMAND	ZCO-02-221	SOB/
T-02-320 MIXED LIQUOR BFV CLOSE COMMAND	ZCC-02-332	SOB/
T-02-320 MIXED LIQUOR BFV OPEN COMMAND	ZCO-02-332	SOB/
DAF POLYMER DOSING PUMP 2 RUN COMMAND	YC-04-780	SOB/
TWAS PUMP 2 RUN COMMAND	YC-02-620	SOB/
BFP FEED PUMP 2 RUN COMMAND	YC-03-640	SOB/
BFP POLYMER DOSING PUMP 2 RUN COMMAND	YC-04-980	SOB/
BFP POLYMER DOSING SOLENOID VALVE OPEN COMMAND	ZCO-04-970	SOB/
PRIMARY EFFLUENT KNIFE VALVE OPEN COMMAND	ZCO-02-221	SOB/
LOWER SECONDARY TREATMENT BEACONS H2S ALARM	US-02-922	SOB/
UPPER SECONDARY TREATMENT BEACONS H2S ALARM	US-02-923	SOB/
SPARE	–	SOB/
SPARE	–	SOB/


TSOB 1 … 32 → RELAY OUTPUT MODULE 1756-OW16I SLOT 08 (1 … 32)

TSOB	RELAY OUTPUT MODULE 1756-OW16I SLOT 08
1	L1-0
2	O:08/00
3	L1-1
4	O:08/01
5	L1-2
6	O:08/02
7	L1-3
8	O:08/03
9	L1-4
10	O:08/04
11	L1-5
12	O:08/05
13	L1-6
14	O:08/06
15	L1-7
16	O:08/07
17	L1-8
18	O:08/08
19	L1-9
20	O:08/09
21	L1-10
22	O:08/10
23	L1-11
24	O:08/11
25	L1-12
26	O:08/12
27	L1-13
28	O:08/13
29	L1-14
30	O:08/14
31	L1-15
32	O:08/15
33	
34	
35	
36	

33 FUDCB → FROM FUDCB SEE DRAWING PAGE 9

34 COMB → FROM COMB SEE DRAWING PAGE 9


Dessiné Par / Drawn By: O. Chalifoux-Lauzon Préparé Par / Prepared By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901 ----	Client / Customer: City of Iqaluit ----	Entreprises L.M. inc 3006 Ste-Catherine est, Montréal, Québec, H1W 2B8 Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: IO Page / de: 17 / 25	Projet / Project: P103901 / xxxxxx Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG	



DESCRIPTION	PLC TAG	TS09		RELAY OUTPUT MODULE 1756-OW16I SLOT 09	
		1	S09/	1	L1-0
PROCESS AERATION BLOWER 3 RUN COMMAND	YC-02-130	2	S09/	2	O:09/00
		3	S09/	3	L1-1
PROCESS AERATION BLOWER FAN 3 RUN COMMAND	YC-02-135	4	S09/	4	O:09/01
		5	S09/	5	L1-2
DAF POLYMER DOSING PUMP 3 CLOSE COMMAND	YC-04-790	6	S09/	6	O:09/02
		7	S09/	7	L1-3
ALARM DIALER ALARM #1	XY-02-090	8	S09/	8	O:09/03
		9	S09/	9	L1-4
ALARM DIALER ALARM #2	XY-02-091	10	S09/	10	O:09/04
		11	S09/	11	L1-5
ALARM DIALER ALARM #3	XY-02-092	12	S09/	12	O:09/05
		13	S09/	13	L1-6
ALARM DIALER ALARM #4	XY-02-093	14	S09/	14	O:09/06
		15	S09/	15	L1-7
SPARE	-	16	S09/	16	O:09/07
		17	S09/	17	L1-8
SPARE	-	18	S09/	18	O:09/08
		19	S09/	19	L1-9
SPARE	-	20	S09/	20	O:09/09
		21	S09/	21	L1-10
SPARE	-	22	S09/	22	O:09/10
		23	S09/	23	L1-11
SPARE	-	24	S09/	24	O:09/11
		25	S09/	25	L1-12
SPARE	-	26	S09/	26	O:09/12
		27	S09/	27	L1-13
SPARE	-	28	S09/	28	O:09/13
		29	S09/	29	L1-14
SPARE	-	30	S09/	30	O:09/14
		31	S09/	31	L1-15
SPARE	-	32	S09/	32	O:09/15
		33	FUDC9	FROM FUDC9 SEE DRAWING PAGE 9	33
		34	COM9	FROM COM9 SEE DRAWING PAGE 9	34
					35
					36

Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
	Dessin De / Drawing Of: IO	Page / de: 18 / 25	Projet / Project: P103901 / xxxxxx
Dernière maj / Last update: 19 mars 2019			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG


3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




TYPICAL ACTIVE DEVICE
SIGNAL WIRING (0-4/20mA)




TYPICAL PASSIVE DEVICE
SIGNAL WIRING (0-4/20mA)



DESCRIPTION	PLC TAG
PROCES AERATION BLOWER 1 SPEED INDICATION	SI-02-110
PROCESS AIR MBBR 2 VALVE POSITION INDICATION	ZI-02-150
PROCESS AIR DAF 2 POSITION INDICATION	ZI-02-155
PROCESS AIR DAF 1 POSITION INDICATION	ZI-02-170
PROCESS AERATION BLOWER OUTLET PRESSURE INDICATION	PI-02-195
T-02-210 CELL 1-1 DISSOLVED OXYGEN INDICATION	AI-02-211
T-02-210 CELL 1-2 DISSOLVED OXYGEN INDICATION	AI-02-212
DAF POLYMER DOSING PUMP 1 SPEED INDICATION	SI-04-770
TWAS PUMP 1 SPEED INDICATION	SI-02-610
BFP FEED PUMP 1 SPEED INDICATION	SI-03-630
TWAS TANK #1 T-03-630 LEVEL INDICATION	LI-03-111
BFP-03-650 INLET FLOW INDICATION	FI-03-695
BFP-04-900 POLYMER LEVEL INDICATION	LI-04-900
BFP POLYMER DOSING PUMP 1 SPEED INDICATION	SI-04-970
DAF 1 POLYMER OUTLET FLOW INDICATION	FI-04-799
BFP POLYMER OUTLET FLOW INDICATION	FI-04-999



Dessiné Par / Drawn By: O. Chalifoux-Lauzon Préparé Par / Prepared By: O. Chalifoux-Lauzon Dernière maj / Last update: 19 mars 2019	Projet / Project: WWTP Upgrade/CPL-901 ---- Dessin De / Drawing Of: IO Page / de: 19 / 25	Client / Customer: City of Iqaluit ---- Projet / Project: P103901 / xxxxxx Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG	Entreprises L.M. inc 3006 Ste-Catherine est, Montréal, Québec, H1W 2B8 Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526




TYPICAL ACTIVE DEVICE
SIGNAL WIRING (0-4/20mA)




TYPICAL PASSIVE DEVICE
SIGNAL WIRING (0-4/20mA)





Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: IO	Page / de: 20 / 25	Projet / Project: P103901 / xxxxxx
			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG


3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



TYPICAL ACTIVE DEVICE
SIGNAL WIRING (0-4/20mA)





TYPICAL PASSIVE DEVICE
SIGNAL WIRING (0-4/20mA)




DESCRIPTION	PLC TAG
PROCES AERATION BLOWER 3 SPEED INDICATION	SI-02-130
MBBR H2S GAS INDICATION	AI-02-907
DAF 2 H2S GAS INDICATION	AI-02-908
DAF 1 H2S GAS INDICATION	AI-02-909
BFP H2S GAS INDICATION	AI-02-910
GENERATOR ROOM CO DETECTION	AI-02-801
POTABLE WATER INLET FLOW INDICATION	FI-04-300
DAF POLYMER DOSING PUMP 3 SPEED INDICATION	SI-04-790
SPARE	–
SPARE	–
SPARE	–
SPARE	–
SPARE	–
SPARE	–
SPARE	–
SPARE	–


Dessiné Par / Drawn By: O. Chalifoux-Lauzon Projeté Par / Prepared By: O. Chalifoux-Lauzon Dernière maj / Last update: 19 mars 2019	Projet / Project: WWTP Upgrade/CPL-901 ---- Dessin De / Drawing Of: IO Page / de: 21 / 25	Client / Customer: City of Iqaluit ---- Projet / Project: P103901 / xxxxxx Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG	Entreprises L.M. inc 3006 Ste-Catherine est, Montréal, Québec, H1W 2B8 Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526






Dessiné Par / Drawn By: O. Chalifoux-Lauzon Préparé Par / Prepared By: O. Chalifoux-Lauzon Dernière maj / Last update: 19 mars 2019	Projet / Project: WWTP Upgrade/CPL-901 ---- Dessin De / Drawing Of: IO Page / de: 22 / 25	Client / Customer: City of Iqaluit ---- Projet / Project: P103901 / xxxxxx Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG	Entreprises L.M. inc 3006 Ste-Catherine est, Montréal, Québec, H1W 2B8 Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526





Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901 ----	Client / Customer: City of Iqaluit ----	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon		Projet / Project: P103901 / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: IO	Page / de: 23 / 25	Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG	Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526



Dessiné Par / Drawn By: O. Chalifoux-Lauzon	Projet / Project: WWTP Upgrade/CPL-901	Client / Customer: City of Iqaluit	Entreprises L.M. inc.
Préparé Par / Prepared By: O. Chalifoux-Lauzon	----	----	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update: 19 mars 2019	Dessin De / Drawing Of: Communication	Page / de: 24 / 25	Projet / Project: P103901 / xxxxxx
			Dessin N° / Drawing N°: WWTP IQALUIT CPL901_R00.DWG
			Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526

Dessiné Par / Drawn By:	Projet / Project:	Client / Customer:	
O. Chalifoux-Lauzon	WWTP Upgrade/CPL-901	City of Iqaluit	Entreprises L.M. inc
Préparé Par / Prepared By:	----	----	
O. Chalifoux-Lauzon		Projet / Project: P103901 / xxxxxx	3006 Ste-Catherine est, Montréal, Québec, H1W 2B8
Dernière maj / Last update:	Dessin De / Drawing Of:	Page / de:	Dessin N° / Drawing N°:
19 mars 2019	FREE	25 / 25	WWTP IQALUIT CPL901_R00.DWG

Tél: (514) 523-2831 / 1-800-265-2831, Fax: 514-521-2526

REVIEWED BY CONTRACTOR

Kudlik Construction Ltd.

NAME: Sandra Rousseau P.Eng
DATE: Mai 13, 2019

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-MP-53 Belt filter press - LCP-03-650 as-built

Date : 2019-05-08

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Montée Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Hugo Chartier, Project Manager	E-mail: hchartier@norclair.ca
Phone : 450-688-4012 # 706	Cell. : 514-703-0263

Information, subcontractor or supplier	
Sub/supplier : Phoenix	
Contact : Jeremy Taylor	Phone : 502-499-6198 x181

Information on the equipment	
Speciality : **Process**	
Equipment : Belt filter press	
Drawing reference :	
Specification reference : **46 76 21**	Division :
Article :	Number of pages : 11

CONSULTANT APPROVAL

SHOP DRAWINGS ARE REVIEWED UNLESS NOTED OTHERWISE

REVIEWED AS MODIFIED	X
REVISE & RESUBMIT	
SEAL & SIGNATURE REQUIRED	

Stantec

DATE May 31, 2019

SIGNATURE

REVIEW BY STANTEC IS FOR THE SOLE PURPOSE OF ASCERTAINING GENERAL CONFORMITY WITH DESIGN. CONTRACTOR IS RESPONSIBLE FOR DIMENSIONS, FABRICATION AND CONSTRUCTION METHODS, COORDINATION OF SUB-TRADES, DETAIL DESIGN OF COMPONENTS, AND ERRORS OR OMISSIONS ON SHOP DRAWINGS.

- Include CSA approvals in O&M manual submission

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

IQALUIT NUNAVUT WWTP
LC1200LS BELT FILTER PRESS
SSUCP-48-600 CONTROL PANEL
ELECTRICAL & PNEUMATIC
DESIGN DRAWINGS

DRAWING SHEET INDEX

DRAWING #	DESCRIPTION	REVISION #
0418377D800	COVER SHEET / DRAWING INDEX	C
0418377D801	600V/120V SCHEMATIC	0
0418377D802	120VAC/24VDC SCHEMATIC	0
0418377D803	I/O SCHEMATIC	0
0418377D804	I/O SCHEMATIC	A
0418377D805	SPARE	0
0418377D806	SPARE	0
0418377D807	DEVICE SETUP PARAMETERS	A
0418377D808	SPARE	0
0418377D809	ENCLOSURE LAYOUT	C
0418377D810	TAG LAYOUT	0
0418377D811	PNEUMATIC SCHEMATIC	0
0418377D812	BILL OF MATERIALS	C

REV	DESCRIPTION	BY	DATE
C	804, 807, 809, 812	AMR	5/8/19
A	809, 812	AMR	10/11/18

PHOENIX
PHOENIX PROCESS EQUIPMENT CO.


FINAL AS BUILT	-	-	
SHOP AS BUILT	-	-	
RELEASE FOR FABRICATION	AMR	7/5/18	
ISSUED FOR SUBMITTAL	-	-	
DRAWING STATUS	BY	DATE	


DRAWN	ENGINEER	APPROVED	
AMR	AMR	-	
SCALE	FILE NO.	DATE	
N/A	0418377	9/21/18	


THE IDEAS, DESIGNS AND ARRANGEMENTS REPRESENTED HEREON ARE OWNED BY AND THE PROPERTY OF PHOENIX PROCESS EQUIPMENT CO. AND WERE CREATED AND DEVELOPED FOR USE IN CONNECTION WITH THE WORK, NOT TO BE USED, IN WHOLE OR IN PART, FOR ANY PURPOSE OTHER THAN THAT FOR WHICH THEY WERE SPECIFICALLY PREPARED AND DEVELOPED WITHOUT THE WRITTEN CONSENT OF PHOENIX PROCESS EQUIPMENT CO.


TITLE: SSUCP-48-600
COVER SHEET/DRAWING INDEX
FOR: IQALUIT - WWTP
NUNAVUT

DWG.NO. 0418377D800 REV: C


600VAC 3ø 60Hz
L1
L2
L3
G
#8 Awg.Min.
NOTE: GROUND WIRING TO BE GREEN W/YELLOW STRIPE
DS101
60A
JTD-60-ID
#6AWG BLACK
PDB103
2L1
2L2
2L3
MP104
104L1
104L2
104L3
5A
VFD104
MITSUBISHI
R
S
T
U
V
W
GND
TR-A860-00027-E1-H6
10471
10472
10473
BELT FILTER PRESS
1HP@1750RPM
2.1FLA
MINIMUM #12AWG BLACK
MP107
MS107
107L1
107L2
107L3
3.4A
(145)
3.4A
10771
10772
10773
AIR COMPRESSOR
2.0HP@1750RPM
3.4FLA
MINIMUM 12AWG BLACK
MP110
MS110
110L1
110L2
110L3
6.1A
(429)
X.XA
11071
11072
11073
WATER BOOST PUMP
5HP@1750RPM
6.1FLA
MINIMUM 12AWG BLACK
TO 125
FROM 124
CB126
127L3
10A
127L1
600V
H1
H6
H3
H2
H4
120V
T129
2.0 KVA
CB129
20A
#12AWG RED
1290
#12AWG WHITE
1291
N1
CONTROL POWER TRANSFORMER
CB133
5A
#16AWG RED (TYPICAL)
1331
SUP133
#16AWG WHITE (TYPICAL)
PLC POWER SURGE SUPPRESSOR
1341
1349
PS135
PLC POWER SUPPLY
TO 241
CB137
5A
1371
DR137
PLC POWER SURGE SUPPRESSOR
E-STOP
PB1401
1401
1002
TO 304
1402
1403
MASTER START
PB1402
1404
CR
MCR140
MASTER CONTROL RELAY TYPE 700P (142, 144, 302)
CONTROL POWER ON
CONSTANT POWER
TO 200
OFF ENABLE
SS145
OX
1451
AIR PRESSURE AT COMPRESSOR
1452
MS107
M
OL107
AIR COMPRESSOR MOTOR STARTER (107)
1003
TO 305
PC1471
PC1472
1471
1472
RFP PULLCORD
CONVEYOR PULLCORD
CR147
BELT PRESS PULLCORD CONTROL RELAY TYPE 700H (303, 431)
TO 425
SYMBOL LEGEND
INTERNAL CONNECT WIRING ALL CONTROL PANELS
PANEL WIRING TERMINAL SSUCP MASTER CONTROL PANEL
INTERNAL PANEL WIRING
PANEL WIRING TERMINAL POLYMER CONTROL PANEL
SHOP CONNECT WIRING
FIELD CONNECT WIRING
PHOENIX
PHOENIX PROCESS EQUIPMENT CO.
TITLE SSUCP-48-600
600V/120V SCHEMATIC
FOR IQALUIT - WWTP
NUNAVUT
DRAWING 041B377D801
REV 0
DRAWN AMR
ENGINEER AMR
APPROVED
SCALE N/A
FILE NO. 04185377
DATE 9/21/18
RELEASED FOR FABRICATION AMR 3/8/19
ISSUED FOR SUBMITTAL
DRAWING STATUS


120VAC
#16AWG RED
#16AWG WHITE
#16AWG RED
#16AWG WHITE
#16AWG BLUE
#16AWG BLUE W/WHITE
CB226
5A
PS226
L1
L2
24+
GND
24-
24VDC POWER SUPPLY
VFD104
CR229
CR
HM230
HM
BELT FILTER PRESS VFD INTERFACE WIRING
BELT FILTER PRESS RUNNING CONTROL RELAY 320
BELT FILTER PRESS RUNTIME HOUR METER
FREQUENCY SETTING POTENTIOMETER 2W 1k OHM
3 CONDUCTOR SHIELDED #18AWG MIN
PRX237
CR237
BELT PRESS LOWER BELT BREAK DETECT (306)
PRX239
CR239
BELT PRESS UPPER BELT BREAK DETECT (306)
ES241
+24
G
COM
ETHERNET SWITCH POWER
ETHERNET COMMS CABLE
HMI 245
PANELVIEW 800 CONTROL POWER
SYMBOL LEGEND
INTERNAL CONNECT WIRING ALL CONTROL PANELS
PANEL WIRING TERMINAL SSUCP MASTER CONTROL PANEL
INTERNAL PANEL WIRING
PANEL WIRING TERMINAL POLYMER CONTROL PANEL
SHOP CONNECT WIRING
FIELD CONNECT WIRING
PHOENIX
PHOENIX PROCESS EQUIPMENT CO.
SSUCP-46-600
120V/24VDC SCHEMATIC
IQALUIT - WWTP
NUNAVUT
04183770802
0


120VAC
#16AWG WHITE
#16AWG RED
MICROLOGIX 1400 1766-L32AWA INPUTS
MICROLOGIX 1400 1766-L32AWA OUTPUTS
MCR140
CR147
PS1
PS2
CR237
CR239
LAMP TEST
PB309
SILENCE
PB310
RESET
PB311
START
PB312
STOP
PB313
HAND OFF AUTO
SS314
PB316 JOG RUN
SS317 FWD OFF REV
SS318
CR229
MCR ON MASTER CONTROL RELAY
BELT PRESS PULLCORD RUN READY
MASTER EMERGENCY STOP RUN READY
AIR COMPRESSOR ENABLED
LOW AIR PRESSURE DETECT SWITCH
BELT TRACKING FAULT PRESSURE SWITCH
BELT BREAK DETECT
LAMP TEST PUSH BUTTON
ALARM SILENCE PUSHBUTTON
ALARM RESET PUSHBUTTON
SYSTEM AUTO START
SYSTEM AUTO STOP
BELT FILTER PRESS DRIVE AUTO CONTROL
BELT FILTER PRESS DRIVE HAND CONTROL
BELT FILTER PRESS DRIVE START
BFP ENABLE JOG/RUN
BFP JOG FORWARD
BFP JOG REVERSE
BELT FILTER PRESS RUNNING AUX
SPARE
SYSTEM WARNING ALERT HORN
BELT FILTER PRESS RUNNING LIGHT
LOW AIR PRESSURE FAULT DETECTED
BELT FILTER PRESS BELT FAULT DETECTED
AIR COMPRESSOR ENABLED
WATER BOOST PUMP RUNNING LIGHT
PREWASH CYCLE RUNNING
POSTWASH CYCLE RUNNING
SLUDGE PUMP RUNNING
POLYMER PUMP RUNNING
SPARE
JUMPER 416
SPARE
SYMBOL LEGEND
INTERNAL CONNECT WIRING ALL CONTROL PANELS
PANEL WIRING TERMINAL SSUCP MASTER CONTROL PANEL
INTERNAL PANEL WIRING
PANEL WIRING TERMINAL POLYMER CONTROL PANEL
SHOP CONNECT WIRING
FIELD CONNECT WIRING
PHOENIX PROCESS EQUIPMENT CO.
SSUCP-46-600
I/O SCHEMATIC
IQALUIT - WWTP
NUNAVUT
0416377D803


24VDC
120VAC
#16AWG BLUE
#16AWG BLUE W/WHITE
#16AWG RED
#16AWG WHITE
MICROLOGIX 1200 I/O 1762-IQ16
MICROLOGIX 1200 I/O 1762-OQ8
HAND OFF AUTO
START
MS110
PS408
SS404
PB406
PB408
TO 337
TO 342
TO 343
WATER BOOST PUMP AUTO CONTROL
WATER BOOST PUMP HAND CONTROL
WATER BOOST PUMP START
WATER BOOST PUMP RUNNING AUX
WATER BOOST PUMP PRESSURE SWITCH
SLUDGE FEED PUMP AUTO CONTROL
SLUDGE FEED PUMP HAND CONTROL
SLUDGE FEED PUMP START
JUMPER 416
POLYMER FEED PUMP AUTO CONTROL
POLYMER FEED PUMP HAND CONTROL
POLYMER FEED PUMP START
JUMPER WIRE FOR PLC OPTION WITH SLUDGE/POLY CONTROL
JUMPER WIRE FOR PLC OPTION WITH SLUDGE/POLY RUNNING INPUTS
SLUDGE FEED RUNNING
CAKE CONV RUNNING
POLYMER RUNNING
SLUDGE FEED PUMP RUNNING AUX
CAKE CONVEYOR RUNNING
POLYMER RUNNING AUX
JUMPER 417
DC COM 0
DC COM 1
NOTE: FOR JUMPERS 416 AND 417, WHEN JUMPER IS INSTALLED THE INPUTS TO THE PLC WHEN BECOME ACTIVE IN THE LOGIC WHEN THE JUMPER IS REMOVED THE INPUTS BECOME INACTIVE AND THE LOGIC WILL IGNORE THOSE VALUES AND INTERLOCKS
MP110
4291
CR147
4311
BOOST WATER PUMP MOTOR STARTER (110, 407)
BELT PRESS DRIVE PLC RUN FORWARD
BELT PRESS DRIVE PLC RUN REVERSE
TO 231
BLUE WIRE
SYSTEM READY TO RUN
SYSTEM FAULTED
ESTOP PRESSED
SYSTEM INTERLOCKS TO MCC
SYMBOL LEGEND
INTERNAL CONNECT WIRING ALL CONTROL PANELS
PANEL WIRING TERMINAL SSUCP MASTER CONTROL PANEL
INTERNAL PANEL WIRING
PANEL WIRING TERMINAL POLYMER CONTROL PANEL
SHOP CONNECT WIRING
FIELD CONNECT WIRING
PHOENIX PROCESS EQUIPMENT CO.
SSUCP-46-600
I/O SCHEMATIC
IQALUIT – WWTP
NUNAVUT
0418377D804

POWERFLEX 523 SERIES VFD

Parameter	Description	BELT PRESS Value
P031	MOTOR NP VOLTS	460
P032	MOTOR NP HERTZ	60
P033	MOTOR OL CUURENT	NAMEPLATE
P041	ACCEL TIME	2
P042	DECEL TIME	2
P043	MIN FREQ (IN Hz)	0
P044	MAX FREQ (IN Hz)	60
P045	STOP MODE	0 RAMP
P046	START SOURCE	2
P047	SPEED REF	5 0-10V
to76	RELAY OUT SELECT	2 RUNNING
to62	TWO WIRE FORWARD	48
to63	TWO WIRE REVERSE	50
J4	I/V JUMPER	V (VOLTAGE)
J8	SINK / SOURCE JUMPER	SINK

* NOTES: 1) THE ACTUAL NAMEPLATE FLA SHOULD BE USED FOR P#33. A TYPICAL VALUE IS SHOWN HERE.


REV	DESCRIPTION	BY	DATE
A	UPDATED PARAMETERS	AMR	5/8/19

PHOENIX PROCESS EQUIPMENT CO.

FINAL AS BUILT	-	DRAWN AMR	ENGINEER AMR
SHOP AS BUILT	-	SCALE N/A	FILE NO. 04118377
RELEASED FOR FABRICATION	AMR 5/8/19		DATE 9/21/18
ISSUED FOR SUBMITTAL	-		
DRAWING STATUS	BY DATE		

THIS DWG AND INFORMATION THEREON REMAINS THE PROPERTY OF PHOENIX PROCESS EQUIPMENT CO. AND SHALL NOT BE USED, REPRODUCED OR DISCLOSED TO OTHERS WITHOUT WRITTEN AUTHORIZATION FROM PHOENIX.

TITLE SSUCP-48-600
DEVICE SETUP PARAMETERS
FOR IQALUIT - WWTP
NUNAVUT
DWG.NO. 0418377D807
REV. A




	1	2	3	4	5	6	7	8	9	10
A										
B	56	56	56	56						
C	57	57	53	57	57	57	50	49	62	55
D	52	52	52	52	52	48	50	51	59	53
E			61							
F										

REV	DESCRIPTION	BY	DATE
C	ADDED TERMINALS, PDT AND PLUG	AMR	9/6/18
B	SWITCHED TRANSFORMER AND MTG TYPES	AMR	8/7/18
A	ADDED PANEL MCB, GCI	AMR	6/21/18

FINAL AS BUILT	--	DRAWN	ENGINEER
SHOP AS BUILT	--	AMR	AMR
RELEASE FOR FABRICATION	AMR 3/8/18	SCALE	FILE NO.
ISSUED FOR SUBMITTAL	--	N/A	0418377
DRAWING STATUS	BY DATE		

PHOENIX
PHOENIX PROCESS EQUIPMENT CO.

APPROVED	--
DATE	9/21/18
DWG.NO.	0418377DB09
REV.	C
TITLE	SSUCP-48-600
	ENCLOSURE LAYOUT
FOR	IQALUIT - WWTP
	NUNAVUT



ENGRAVING INSTRUCTIONS:

1.) ALL OPERATOR TAGS ARE STANDARD 30mm OPERATOR CUTOUTS AND 2-1/4" x 2-1/4" SQUARE, WHITE LAMACOID BACKGROUND ON BLACK PHENOLIC LETTERS.

2.) WARNING TAGS ARE DIMENSIONED AS SHOWN. ENGRAVE ON YELLOW LAMACOID BACKGROUND WITH BLACK PHENOLIC LETTERS.

3.) EMERGENCY STOP 30mm RING TAG SHALL BE YELLOW LAMACOID BACKGROUND WITH BLACK PHENOLIC LETTERS.

4.) THE ARC FLASH TAG IS MANUFACTURED BY PANDUIT AND IS A PEEL AND STICK TAG.

REV	DESCRIPTION	BY	DATE
–	–	–	–


PHOENIX
PHOENIX PROCESS EQUIPMENT CO.

FINAL AS BUILT	–	–	DRAWN	ENGINEER	APPROVED
SHOP AS BUILT	–	–	AMR	AMR	–
RELEASE FOR FABRICATION	AMR	3/8/18	SCALE	FILE NO.	DATE
ISSUED FOR SUBMITTAL	–	–	N/A	0418377	9/21/18
DRAWING STATUS	BY	DATE			

TITLE: SSUCP-48-600
TAG LAYOUT
FOR: IQALUIT – WWTP
NUNAVUT

DWG.NO. 0418377DB10 REV. 0

LC PIPING SCHEMATIC



PNEUMATIC BILL OF MATERIAL

NO.	REC'D	QNTY	MANUFACTURER	DESCRIPTION	PART NO.
1		1	PHOENIX	1/4" BRASS TEE	E2258
2		2	PHOENIX	1/4" BRASS CLOSE NIPPLE	E2259
3		1	PHOENIX	1/4" X 2" BRASS NIPPLE	E2259A
4		1	PHOENIX	FILTER/REG, 1/4" NPT, COALESCING, .3 MICRON	CH222B
5		1	PHOENIX	1/4" BRASS 90 ELBOW	E2266
6		4	PHOENIX	1/4" BULKHEAD NICKLE PLATED	E2260
7		4	PHOENIX	SEALING WASHER	E2260A
8		1	PHOENIX	1/4" X 1/4" RUN TEE	E2287
9		1	PHOENIX	1/4" X 1/4" CONNECTOR, FEMALE O DEG	E2282
10		1	PHOENIX	1/4" X 1/4" CONNECTOR, MALE O DEG	E2284
11		3	PHOENIX	1/4" X1/4" SWIVEL ELBOW 90 DEG	E2286
12		1	PHOENIX	1/8" NPT X 1/4" SWIVEL ELBOW 90 DEG	E2285
13		20'	PHOENIX	1/4" OD POLYURETHANE TUBE NATURAL	E2754
14		1	PHOENIX	1/4"NPT, 2.5"dia, 0-160 scale, Liquid Filled, Guage.	CH342
15		1	PHOENIX	0-160 PSIG GAUGE, 1/8" NPT	CH342A
16		1	PHOENIX	Panel Mounting Nut	CH221A
17		1	PHOENIX	Regulator, 1/4"NPT, Panel Nut, Standard Knob	CH221
18		1	PHOENIX	Pressure Switch, setpoint 50psig rising	CH294
19		1	PHOENIX	Pressure Switch, setpoint 60psig falling	CH295
20		1	PHOENIX	1/4" LUBRICATOR	CH225
21		.	.	.	.
22		1	PHOENIX	1/8" NPT PLUG	E2259C
23		.	.	.	.
24		.	.	.	.
25		.	.	.	.

NOTES:
1. ALL PNEUMATIC PARTS SUPPLIED BY PHOENIX PARTS DEPARTMENT.
2. THE KIT NUMBER IS (KIT-AIR-LC-CH221)
3. THE DASHED LINES DENOTE 1/4" TUBING RUNS IN THE SSUCP PANEL.

REV	DESCRIPTION	BY	DATE
-	-	-	-

FINAL AS BUILT	-	-	
SHOP AS BUILT	-	-	
RELEASED FOR FABRICATION	AMR	3/8/19	
ISSUED FOR SUBMITTAL	-	-	
DRAWING STATUS	BY	DATE	

DRAWN	ENGINEER	APPROVED	
AMR	AMR	-	
SCALE	FILE NO.	DATE	
N/A	0418377	9/21/18	

PHOENIX
PHOENIX PROCESS EQUIPMENT CO.

TITLE	SSUCP-48-600
	PNEUMATIC SCHEMATIC
FOR	IQALUIT - WWTP
	NUNAVUT
DWG.NO.	0418377D811
REV.	0

SSUCP-48-600 BILL OF MATERIAL

NO.	REC'D	QNTY	MANUFACTURER	DESCRIPTION	PART NO.
1		1	HOFFMAN	ENCLOSURE, SS NEMA 4X, SINGLE DOOR WALLMOUNT	A-48H3612SSLP
2		1	HOFFMAN	SUBPANEL, 45" X 33"	A-48P36
3		1	ALLEN BRADLEY	ROTARY DISCONNECT SWITCH, 60A	194R-J60-1753
4		1	ALLEN BRADLEY	NFPA 79 HANDLE KIT W/OPERATING SHAFT	194R-N2
5		1	ALLEN BRADLEY	DISCONNECT OPERATING HANDLE, NEMA 4X	194R-PY
6		.	.	.	.
7		.	.	.	.
8		.	.	.	.
9		.	.	.	.
10		.	.	.	.
11		2	ALLEN BRADLEY	140M Front Mounted Auxiliary Contact	140M-C-AFA11
12		1	ALLEN BRADLEY	MOTOR CIRCUIT PROTECTOR, 2.5-4.0A	140M-C2E-B40
13		2	ALLEN BRADLEY	MOTOR CIRCUIT PROTECTOR, 4.0-6.3A	140M-C2E-B63
14		2	ALLEN BRADLEY	CONTACTOR, IEC, 9A, 5HP, 120VAC	100-C09D10
15		.	.	.	.
16		.	.	.	.
17		.	.	.	.
18		.	.	.	.
19		1	AB	VARIABLE FREQUENCY DRIVE, 1 HP, 600V	25A-E1P7N104
20		1	ALLEN BRADLEY	CIRCUIT BREAKER, 2 POLE, 5A	1489-M2C050
21		.	.	.	.
22		3	ALLEN BRADLEY	CIRCUIT BREAKER, 1 POLE, 5A	1489-M1C050
23		1	ALLEN BRADLEY	CIRCUIT BREAKER, 1 POLE, 20A	1489-M1C200
24		3	ALLEN BRADLEY	CONTROL RELAY, TERMINAL, SPDT, 24VDC	700-HLT1Z24
25		.	.	.	.
26		1	ALLEN BRADLEY	CONTROL RELAY, 4 POLE, 120VAC	700-P400A1
27		1	ALLEN BRADLEY	CONTROL RELAY, PLUG-IN, 3PDT, 120VAC	700-HA33A1
28		1	ALLEN BRADLEY	RELAY SOCKET, 11 PIN	700-HN126
29		1	TRANSTECTOR	SURGE PROTECTOR W/BASE, 120V	DR-120
30		1	SOLA	DC POWER SUPPLY, 120VAC/24VDC, 3.8A	SDN 4-24-100LP
31		1	SOLAHD	TRANSFORMER, 600V/120V, 2KVA	CE2000ME
32		1	ALLEN BRADLEY	POWER DISTRIBUTION BLOCK	1492-PD3141
33		1	ALLEN BRADLEY	MICROLOGIX 1400 PLC, 20IN(120VAC), 12OUT(RELAY)	1766-L32AWA
34		1	ALLEN BRADLEY	INPUT MODULE, 16PT, 24VDC	1762-IQ16
35		1	ALLEN BRADLEY	OUTPUT MODULE, 6PT, ISOLATED RELAY	1762-OX6I
36		1	ALLEN BRADLEY	MEMORY MODULE	1766-MM1
37		A/R	ALLEN BRADLEY	DIN RAIL, 35mm	199-DR1
38		A/R	ALLEN BRADLEY	TERMINAL BLOCK, IEC	1492-J4
39		A/R	ALLEN BRADLEY	TERMINAL END BARRIER	1492-EBJ3
40		A/R	ALLEN BRADLEY	TERMINAL END ANCHOR	1492-EBJ35

SSUCP-48-600 BILL OF MATERIAL

NO.	REC'D	QNTY	MANUFACTURER	DESCRIPTION	PART NO.
41		A/R	ALLEN BRADLEY	TERMINAL CENTER JUMPER, 41 POLE	1492-CJUJ6-41
42		A/R	ALLEN BRADLEY	TERMINAL PARTITION PLATE	1492-EBJ16
43		A/R	ALLEN BRADLEY	TERMINAL MARKER CARD	1492-M6X12
44		A/R	ALLEN BRADLEY	TERMINAL BLOCK, FUSED FOR 1/4" X 1 1/4"	1492-H4
45		A/R	ALLEN BRADLEY	GROUND TERMINAL BLOCK	1492-WG4
46		1	ITE	GROUND BAR	GB10
47		1	AUTO DIRECT	PANEL INT CONN, 120VAC OUTLET RJ45 SGL-LVR	ZP-PSA-16-101
48		1	ALLEN BRADLEY	PUSHBUTTON, TWIST RELEASE, RED, MUSHROOM	800H-FRXT6A5
49		1	ALLEN BRADLEY	PUSHBUTTON, FLUSH, GREEN, 1 N.O.	800H-AR1D1
50		2	ALLEN BRADLEY	PUSHBUTTON, FLUSH, YELLOW, 1 N.O.	800H-AR9D1
51		1	ALLEN BRADLEY	PUSHBUTTON, EXTENDED, RED, 1 N.O. 1 N.C.	800H-BR6D1
52		5	ALLEN BRADLEY	SELECTOR SWITCH, 3 POSITION, MAINTAINED	800H-JR2A
53		2	ALLEN BRADLEY	SELECTOR SWITCH, 2 POSITION, MAINTAINED	800H-HR2A
54		.	.	.	.
55		1	ALLEN BRADLEY	PILOT LIGHT, AMBER, 120VAC	800H-PR16A
56		2	ALLEN BRADLEY	PILOT LIGHT, BLUE, 120VAC	800H-PR16B
57		5	ALLEN BRADLEY	PILOT LIGHT, GREEN, 120VAC	800H-PR16G
58		2	ALLEN BRADLEY	PILOT LIGHT, RED, 120VAC	800H-PR16R
59		1	ALLEN BRADLEY	PUSHBUTTON, FLUSH, BLACK, 1 N.O.	800H-AR2D1
60		.	.	.	.
61		1	ALLEN BRADLEY	POTENTIOMETER, 1K OHM, 2W	800H-UR13
62		1	HOFFMAN	HOLE SEAL, 304SS, 30mm	A-SPBSS
63		1	RED LION	HOUR METER	CUB7T
64		1	RED LION	MOUNTING BRACKET FOR CUB7T	BMK80000
65		1	ALLEN BRADLEY	5 PORT ETHERNET SWITCH, UNMANAGED	1783-US5T
66		23	BUSSMAN	FUSE FOR TERMINAL, 250V, 2A	
67		1	PANDUIT	ARC FLASH TAG	PPSC204W2100
68		1	ALLEN-BRADLEY	PANELVIEW 800 TOUCHSCREEN	2711R-T4T
69		1	FIBOX	INSPECTION PANEL, SMOKE	L 24 II
70		1	ILSCO	GROUND LUG, #4-14 AWG	TA-6S
71		1	FEDERAL SIGNAL	ALARM HORN, 120VAC, PANEL MOUNT	350-120
72		1	FEDERAL SIGNAL	GASKET KIT FOR 350 HORN	K8435666A
73		3	LITTELFUSE	FUSE, 600V, 60A, CLASS J INDICATIONG	JTD-60-ID
74		.	.	.	.
75		1	AS NEEDED	ETHERNET CAT6 CABLE	.

REV.	DESCRIPTION	BY	DATE
C	11, 12, 13	AMR	5/8/19
B	10,21	AMR	12/7/18
A	ADDED 68 69	AMR	10/17/18

PHOENIX
PHOENIX PROCESS EQUIPMENT CO.

FINAL AS BUILT	-	-	DRAWN AMR	ENGINEER AMR	APPROVED -
SHOP AS BUILT	-	-	SCALE N/A	FILE NO. 04183377	DATE 9/21/18
RELEASED FOR FABRICATION	AMR	3/8/19			
ISSUED FOR SUBMITTAL	-	-			
DRAWING STATUS	BY	DATE			

TITLE: SSUCP-48-600 BILL OF MATERIALS
FOR: IQALUIT - WWTP NUNAVUT
DWG.NO. 04183770812 REV. C

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 23, 2019

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-MP-57 Instrument air compressor package

Date : 2019-07-22

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Montée Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Hugo Chartier, Project Manager	E-mail: hchartier@norclair.ca
Phone : 450-688-4012 # 706	Cell. : 514-703-0263

Information, subcontractor or supplier	
Sub/supplier : ADEC Compressors	
Contact : Stéphane Hubert	Phone : 450-668-5050 poste 106

Information on the equipment	
Speciality : **Process**	
Equipment :	
Drawing reference :	
Specification reference : **CCN-18** (Page xx / xx)	Division :
Article :	Number of pages : 27

CONSULTANT APPROVAL

Ensure the air is regulated to 365cfm @ 80 psi.

SHOP DRAWINGS ARE REVIEWED UNLESS NOTED OTHERWISE

REVIEWED AS MODIFIED	X
REVISE & RESUBMIT	
SEAL & SIGNATURE REQUIRED	

Stantec

DATE July 29/20

SIGNATURE

REVIEW BY STANTEC IS FOR THE SOLE PURPOSE OF ASCERTAINING GENERAL CONFORMITY WITH DESIGN. CONTRACTOR IS RESPONSIBLE FOR DIMENSIONS, FABRICATION AND CONSTRUCTION METHODS, COORDINATION OF SUB-TRADES, DETAIL DESIGN OF COMPONENTS, AND ERRORS OR OMISSIONS ON SHOP DRAWINGS.

INSTRUMENTATION & CONTROLS

STANTEC PROJECT #: 110126045

SUBMITTAL # DA-MP-57-Instrumental air compressor package

This review by Stantec is for general conformance with the design concept of the:
- ☐ Architectural
- ☐ Structural
- ☐ Mechanical
- ☑ Electrical
- ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawings and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- ☑ REVIEWED
- ☐ REVIEWED, AS NOTED
- ☐ REVISE AND RESUBMIT
- ☐ NOT REVIEWED

DATE 2019-07-26

BY Konrad Goluch

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

KAESER COMPRESSORS®

Built for a lifetime.



Screw Compressors

S Series

Capacities from: 8.8 to 89 cfm
Pressures from: 80 to 217 psig

www.kaeser.com

36 scfm @ 80psi

SX, SM, and SK Series

Built for a lifetime.™

Kaeser Compressors' SX, SM, and SK series of rotary screw compressors are the perfect solution for smaller compressed air systems. Not only do these compressors deliver more compressed air for sustainable energy savings, they also combine ease of use with exceptional reliability and simple maintenance.

Innovation you can trust

With a cutting edge research and development team committed to building industry-leading products, Kaeser continues to deliver better solutions to meet our customers' compressed air needs. Kaeser's expertise and world-wide reputation for superior reliability and efficiency offer great performance and peace of mind.

Rugged reliability


Kaeser's screw compressors meet our rigorous "built for a lifetime" standard. Designed and built with Kaeser's generations of compressed air experience, you can rest assured that these compressors will continue to deliver the air you need with the exceptional reliability you expect from a Kaeser compressor.

Service-friendly

From the ground up, these compressors have been designed with the user in mind. Fewer wearing parts and using premium quality materials ensure reduced maintenance requirements, longer service intervals, and extended service life. A smart component layout with generously sized maintenance doors simplifies service and reduces downtime.

Guaranteed efficiency


In our systems design approach, Kaeser chooses the components that work together in the most energy efficient way possible. Each and every component — from inlet filter to discharge flange — has been carefully designed with performance in mind. In fact, the S series are up to 30% more efficient than the competition. With Kaeser's superior system controls, we guarantee an effective system with lower operating costs.



Service-friendly Design

The SX, SM, and SK series rotary screw compressors feature an open package layout. All of the major components are easily accessible, reducing preventive maintenance time by as much as 50% when compared to other similarly sized units.

When you consider the energy efficiency savings and the maintenance costs savings, it's clear that owning a Built for a lifetime™ Kaeser compressor will save you money, year after year.




Designed for Reliability, Simplicity, and Performance



Sigma Profile™ Airend

Our power-saving, proprietary airend design delivers pressures up to 217 psig. It is precision-machined to close tolerances and optimized in size and profile to match the low airend speeds with their best specific performance.



TEFC Motor with Reduced Voltage Starter

Premium-efficiency, totally enclosed, fan cooled (TEFC) motors with Class F insulation provide long life in harsh environments. Magnetic Wye-Delta reduced voltage starters ensure low starting current and smooth acceleration. Tri-voltage 208-230/460 or 575 V, 3-phase, 60 Hz is standard. Other voltages are available.



Double-flow Cooling Fan

Our patent-pending double-flow fan design increases air flow through the unit while reducing overall power requirements and sound levels.

Belt Drive with Automatic Tensioning



A ribbed single belt drive efficiently transfers power from motor to airend. The SM and SK series feature our unique automatic tensioning device that maintains proper tension to maximize energy efficiency, prolong belt life, and simplify routine maintenance. The belt tension can easily be verified through a window in the service panel.

High Efficiency Coolers with Filter Mat



Conveniently located on the outside of the unit, our standard high efficiency coolers provide maximum cooling resulting in approach temperatures as low as 11°F for more moisture separation at the compressor discharge and better air quality. A filter mat simplifies cooler maintenance. Dirt and dust build up on the outside of the filter, where it is easily seen and removed. This extends cooler service intervals and increases thermal reserve for harsher conditions.

Efficient Separator System



A three-stage separator (ASME or CRN) combines centrifugal action and a 2-stage coalescing filter to reduce fluid carry over to 2 ppm or less. Quick release fittings, drain and fill ports are arranged for fast and easy fluid changes from sump and cooler without any pumping device. The easy-to-read fluid level indicator can be safely checked through a window in the service panel while the compressor is running.

Enclosure

Our superior cabinet design reduces noise and footprint while offering easy access for service. A heavy-duty metal enclosure with a durable powder-coated finish keeps noise in but dirt and dust out. Thick sound insulation keeps sound levels as low as 61 dB(A), up to 10 dB(A) quieter than comparable units.

Lockable panels provide easy access to all maintenance items. Electrical components are housed in a spacious, ventilated control cabinet. Wiring is neatly arranged and terminals are clearly identified.

Internal and external vibration isolators eliminate stress on piping and wire connections, further increasing reliability.


Fluid Cooling System

All units are filled with Kaeser Premium Fluid to cool, clean, and lubricate the airend. A thermostatically controlled combination valve ensures perfect fluid temperature regulation and incorporates a cooler by-pass and spin-on fluid filter. Main air and fluid lines are made of rigid pipe with flexible connections. A 10 micron spin-on fluid filter is within easy reach of the front cover. This filter extends fluid life and protects the airend.

Optimized Air Flow Design

Air is drawn into separate cooling zones for the drive motor and coolers. This "split cooling" design eliminates pre-heating, increasing cooling efficiency without increasing power consumption. Cooler temperatures also promote longer lubricant and motor life. Cooling air is exhausted through a single port at the top of the cabinet. Ducting this air enables heat recovery and further reduces noise.

Air for compression enters through a separate grill on the right side of the cabinet. It is then filtered through a two-stage air intake filter. This filter protects the airend and extends fluid change intervals.



Fresh cooling air

Recirculated air

Exhaust air

The SX, SM, and SK units can be installed in a corner and still provide easy access for maintenance.



Intelligent control and protection

To protect your investment and ensure the most efficient operation possible, these compressors are available with our Sigma Control 2™. This intelligent controller comes standard with multiple pre-programmed control profiles so you can select the one that best fits your application. Sigma Control 2 monitors more than 20 critical operating parameters, shuts the unit down to prevent damage, and signals if immediate service is required. It also tracks preventive maintenance intervals and provides notice when PMs are due. An RFID sensor provides secure access and simplifies managing maintenance intervals. An SD card slot with included SD card enables fast, easy software updates, storing key operational parameters, and offers long-term data storage for analyzing energy consumption and compressor operation. Sigma Control 2 has superior communications capabilities. An Ethernet port and built-in web-server come standard in the controller making integration into the Sigma Network possible.

The optional Sigma Control 2 with communications port can be fitted with communication modules like ModBus, EtherNet/IP, Profibus®, Devicenet®, Profinet®, or other industrial communi-cations interfaces as a plug-in option for seamless integration into plant control/ monitoring systems.


See our Sigma Control 2 brochure for more information.

Integrated Dryer Option

Premium compressed air quality


The integrated dryer is perfectly sized for the full flow of the compressor. The dryer is located in a separate cabinet so it is not exposed to preheated air or contaminants from the compressor package.





Energy-saving control

The integrated refrigerated dryer in Kaeser units provides high efficiency performance thanks to its energy-saving control. The dryer is active only when compressed air actually needs to be dried. This approach achieves the required compressed air quality with maximum efficiency.



Stainless steel plate heat exchanger

The dryer's stainless steel plate heat exchanger is corrosion and contamination-resistant. The stainless moisture separator reliably removes the accumulating condensate from the air, even with fluctuating airflow.



Eco-Drain

The integrated refrigerated dryer also features a zero loss Eco-Drain. The advanced level-controlled condensate drain eliminates the compressed air losses associated with solenoid valve control. This saves energy and considerably enhances the reliability of the compressed air supply.

45

Complete Compressed Air Systems

Life just got easier

Whether you prefer separate components or fully integrated packages, Kaeser offers everything for a complete, high quality air system.

AIRCENTER

To simplify your compressed air system, Kaeser offers the AIRCENTER. This unit combines essential system components in one easy-to-install package. AIRCENTERS come completely assembled and include a refrigerated dryer with automatic condensate drain, receiver tank, and an optional filtration package. These super quiet and energy efficient units are compact and perfect for installations where space is limited.



Duplex AIRCENTER



SM AIRCENTER

Technical Specifications

Model	Operating Pressure (psig)	Capacity at Operating Pressure (cfm) (1)	Motor (hp)	Dimensions W x D x H (in.)	Weight (lb.)(2)	Sound Level (dB(A)) (3)
SX 3*	125	12.0	3	23¼ x 24⅞ x 38¼	309	61
SX 3T*	160*	9.2		23¼ x 36 x 38⅛	408	
SX 3 AIRCENTER*				23¼ x 42⅞ x 61⅜	628	
SX 4	125	15.9	4	23¼ x 24⅞ x 38¼	309	62
SX 4T	160	12.7		23¼ x 36 x 38⅛	408	
SX 4 AIRCENTER	217	8.8		23¼ x 42⅞ x 61⅜	628	
SX 5	125	21.2	5	23¼ x 24⅞ x 38¼	320	63
SX 5T	160	17.0		23¼ x 36 x 38⅛	419	
SX 5 AIRCENTER	217	12.7		23¼ x 42⅞ x 61⅜	639	
SX 7.5	125	28.3	7.5	23¼ x 24⅞ x 38¼	342	66
SX 7.5T	160	23.7		23¼ x 36 x 38⅛	441	
SX 7.5 AIRCENTER	217	18.7		23¼ x 42⅞ x 61⅜	661	
SM 7.5	125	32.5	7.5	24¾ x 30 x 43¼	485	65
SM 7.5T	160	26.5		24¾ x 43 x 43¼	650	
SM 7.5 AIRCENTER	217	19.4		24¾ x 48 x 67¾	926	
SM 10	125	45.9	10	24¾ x 30 x 43¼	529	67
SM 10T	160	37.1		24¾ x 43 x 43¼	695	
SM 10 AIRCENTER	217	27.5		24¾ x 48 x 67¾	970	
SM 15	125	55.4	15	24¾ x 30 x 43¼	529	68
SM 15T	160	45.9		24¾ x 43 x 43¼	695	
SM 15 AIRCENTER	217	35.7		24¾ x 48 x 67¾	970	
SK 15	125	70.6	15	29½ x 35¼ x 49½	686	67
SK 15T	160	59.0		29½ x 48¾ x 49½	853	
SK 15 AIRCENTER	217	45.9		29½ x 52½ x 74	1276	
SK 20	125	88.3	20	29½ x 35¼ x 49½	703	68
SK 20T	160	76.6		29½ x 48¾ x 49½	871	
SK 20 AIRCENTER	217	62.5		29½ x 52½ x 74	1294	

Specifications are subject to change without notice.

CAGI

Certified Performance

Our compressors' energy efficiency has been tested and confirmed by an independent laboratory as part of the Compressed Air and Gas Institute's ***Rotary Screw Compressor Performance Verification Program***. CAGI data sheets for our screw compressor units can be found at www.us.kaeser.com/cagi



**SX 3 pressure limited to 160 psig.*

(1) Performance rated in accordance with CAGI/ISO 1217 test code.

(2) Weights may vary slightly depending on airend model.

(3) Per ISO 2151 using ISO 9614-2.

Note: *Other pressures available from 80 to 217 psig.*

ensure air is regulated to 36 scfm @ 80 psi

KAESER COMPRESSORS®

Built for a lifetime.



www.kaeser.com

Kaeser Compressors, Inc.
511 Sigma Drive
Fredericksburg, VA 22408 USA
Telephone: 540-898-5500
Toll Free: 800-777-7873
info.usa@kaeser.com

Kaeser Compressors Canada Inc.
3760 La Verendrye Street
Boisbriand, QC J7H 1R5 CANADA
Telephone: (450) 971-1414
Toll free: (800) 477-1416
info.canada@kaeser.com

Kaeser Compresores de México S de RL de CV
Calle 2 #123
Parque Industrial Jurica
76100 Querétaro, Qro.
Telephone: 01 (442) 218 64 48
sales.mexico@kaeser.com

Kaeser Compresores de Guatemala y Cia. Ltda.
Calz. Atanasio Tzul 21-00, zona 12
El Cortijo II, Bodega 501
01012–Guatemala City
Telephone: +502 2412-6000
info.guatemala@kaeser.com

© 2018 Kaeser Compressors, Inc. All rights reserved. 05/18
USSXSMSK


4.6


2 units


Available voltage 203/230/460 (480 v. ok)/ 60 Hz.
With SIGMA Standard


AIRCENTER SM 10-TRIV Screw Compressor Packaged System Kaeser SC2
277/480V/3 PH/60 HZ, 42 CFM @ 125 PSI


36 cfm @ 80psi
















		A	B
F1	F8KE / F8KE	46 3/4	8 7/8
	F16KE	46 1/2	5 3/4
F7	F8KEA / F8KEA	46 3/4	8 7/8
	F16KEA	46 1/2	5 3/4











: Center of gravity
Position marginally dependent on design

Transport opening ≥ machine width + 3,9 inch

Dimensions shown in inches
ID : Internal thread

W1	prepared for ext. heat recov.
H1	Machine mountings
K1	Air cooling
F7	KAESER FILTER KEA / ECO-DRAIN
F1	KAESER FILTER KE / ECO-DRAIN


Change number	Projection	Scale 1:15		Date	Name
Document TZM 1036896 USE 00		Original A2	Drawn	21.08.2017	BTAMMS
			Edited	10.10.2017	BTAMMS
			Released	11.10.2017	BCHUBTG
Document TZD 1036896 D 00			Designation SM.3 AIRCENTER 7.5, 10, 15 AIRCOOLED		
Status Released			Dimension and connection dim.		

KAESER KOMPRESSOREN
Language USE
Sheet 1 / 1

ES

Model shown for reference only
Actual Duct size may vary with installation

A	Exhaust Fan
B	Exhaust Air Duct
Z	Inlet Air Opening



Recommended machine placement and dimensions		inches
L	Left side clearance =	8
R	Right side clearance =	40
F	Front clearance =	40
BK	Back clearance =	40
H	Height clearance =	120

2x, pre-filter, 55 cfm, 3/4in, auto-drain, installed at compressor outlet
+ filter-regulators located at instruments as per Veolia specs

KAESER COMPRESSORS

Built for a lifetime.



Compressed Air Filters

Particulate, Liquid, and Oil Removal

20 - 500 scfm

kaeser.com

WB

Compressed Air Filters: 20 - 500 scfm

Superior filtration

Proper filtration is necessary to ensure consistent air quality, but with it comes pressure drop. Every 2 psi of pressure drop increases power costs by 1%. Kaeser filters remove more contaminants with less pressure drop for lower operating costs. With a complete selection of application-specific filter types, sizes, technical service, and support, Kaeser offers a customized solution for all of your compressed air quality needs.

Why treat compressed air

Ambient air contains contaminants that are drawn into the compressor. These contaminants are concentrated during compression and can easily pass into the compressed air system. A typical compressed air system is contaminated with abrasive solid particles such as dirt, rust and pipe scale, compressor lubricants, condensed water droplets, and oil and hydrocarbon vapors.

Contaminated compressed air systems increase operating costs by reducing efficiency. This results in damaged pneumatic equipment, higher maintenance and repair costs, reduced production (due to downtime), and increased product rejections.


Meeting your air quality requirements

Properly sized and selected Kaeser filters in conjunction with the appropriate dryer will remove harmful contaminants. This allows the compressed air system to deliver the quality of air required—whether it's plant, instrument, or breathing air.

High performance filters and separators

Engineered and developed using the latest innovations and manufacturing techniques, Kaeser filter housings are designed with larger flow areas to ensure the lowest pressure drop and provide easier installation, operation, and maintenance. The result is consistent product quality with minimized operating costs.

Life cycle cost savings




Conventional Filters

Kaeser Filters

Particulate filter example:
Flow rate 485 scfm, 4800 hr/yr, $0.10 kWh, operating at 100 psig, over 10 years.


KAESER
SECOTEC TE 142

Key Features



Deep pleated filter elements

Kaeser's KB, KD, and KE dust and coalescing filter elements feature deep-pleated filter elements wrapped in stainless steel cages. The extra large surface area ensures superior filtration, increased efficiency, and reduced pressure drop.



High efficiency carbon matting

Unlike the granular material used in many other filters, Kaeser's KA filters use carbon impregnated matting to prevent channeling while also reducing pressure drop. This highly absorptive matting is also effective at preventing particles from escaping.



Minimized pressure losses

The generously-sized connection flanges help keep pressure losses to an absolute minimum. Additionally, all particulate and coalescing filters (KB, KD, KE) come standard with a differential pressure gauge to check filter efficiency at a glance.

Filter Accessories



FDPS sensor

Filter differential pressure sensor pressure gauge with volt-free contacts for remote alarm indication.



Modular connection kit

Available in multiple sizes for installation flexibility.



Wall mounting kit

Includes all the necessary hardware for fast and easy mounting.

Multiple NPT connection sizes


Threaded, modular connections for easy installation

Compressed air inlet

Optimized for air flow through housing to minimize pressure drop

Filter element

Push-on element for easy maintenance



Pressure differential indicator

Standard on particulate and coalescing filters

Compressed air outlet

Filters maintain rated efficiency down to ten percent of flow capacity

Safety locking screw

Bleeds off pressure before allowing disassembly for increased safety

Condensate outlet

(Internal automatic condensate drain not shown)



Installation flexibility

The optional Eco-Drain can rotate 360° to fit any installation requirement. Drain access is never a problem even when installed in tight corners or against a wall.

Superior Quality and Durability

- Top quality castings
- Powder coated exterior for added durability and corrosion resistance
- Salt spray corrosion tested
- Treated interior
- Continuously-welded, stainless steel inner and outer cages for filter elements
- 5-year warranty on filter head and housing

Enhanced Performance

- Latest filter media technology results in higher efficiencies and lower Delta P
- 150°F maximum inlet temperature
- 232 psig maximum working pressure
- Stainless steel support sleeves, oil and acid resistant coated collars, and end caps
- The tapered housing and non-turbulent lower filter zone prevent condensate from being picked up by the air flow

WB.

Filter Types


	KC [1] (Cyclone) Moisture Separator	KB [2] (Basic) Coalescing and Particulate	KE [2] (Extra Fine) Extra Coalescing and Particulate	KD (Dust) Particulate (Afterfilter)	KA (Adsorb) Vapor
Initial pressure differential at saturation	1.5 psi	2.0 psi	< 2.9 psi	< 0.5 psi (New, dry)	0.5 psi (New, dry)
Aerosol content at inlet	-/-	10 mg/m^3	10 mg/m^3	-/-	-/-
Remaining aerosol content at outlet as per ISO 12500-1:06-2007	-/-	< 0.1 mg/m^3	< 0.01 mg/m^3	-/-	-/-
Filter medium	-/-	Deep pleated with support structure and polyester drainage fiber		Deep pleated with support structure	High efficiency carbon fiber
Application	Bulk liquid separation	Filters solids, liquids, aerosols, and particulates	Same as KB, but for higher compressed air quality	Exclusively for filtering particulates	Exclusively for removing oil vapor



[1] *Eco-Drain 31 is standard.*
[2] *Float-type drain is standard. Available with optional zero-loss Eco-Drain 30 or 31 to save energy and prevent compressed air loss.*

Examples of Air Treatment Configurations with ISO 8573.1: 2010 Quality Classes Shown

These configurations don't depict every possible dryer-filter combination. Your Kaeser representative can help select the appropriate air treatment products for your application.



[1] *For compressors without an integrated moisture separator.*
[2] *Configuration meets ISO class when tested in an ISO 12500 certified facility per ISO 12500 testing directives.*
[3] *KB not needed if non-corrosive tank and piping are used before dryer*

ISO 8573.1:2010

SOLID PARTICLES / DUST			
Class	Max. particle count per m³ of a particle size with d* (µm)		
	0.1<d≤0.5	0.5<d≤1.0	1.0<d≤5.0
0	Consult Kaeser		
1	≤20,000	≤400	≤10
2	≤400,000	≤6,000	≤100
3	not specified	≤90,000	≤1,000
4	not specified	not specified	≤10,000
5	not specified	not specified	≤100,000
Class	Particle concentration* Cp (mg/m³)		
6	0 < Cp ≤5		
7	5 < Cp ≤10		
X	Cp > 10		

HUMIDITY AND LIQUID WATER		
Class	Pressure dew point	
0	Consult Kaeser	
1	≤70°C	≤-94°F
2	≤-40°C	≤-40°F
3	≤-20°C	≤-4°F
4	≤ 3°C	≤38°F
5	≤7°C	≤45°F
6	≤10°C	≤50°F
Class	Concentration of liquid water* Cw (g/m³)	
7	Cw ≤0.5	
8	0.5 < Cw ≤5	
9	5 < Cw ≤10	
X	Cw > 10	

OIL		
Class	Total oil concentration* (liquid, aerosol, and vapor)	
	(mg/m³)	(ppm w/w)
0	Consult Kaeser	
1	≤0.01	≤0.008
2	≤0.1	≤0.08
3	≤1.0	≤0.8
4	≤ 5.0	≤4
X	> 5.0	> 4

** At reference conditions: 68°F (20°C), 14.5 psia (1 bar), 0% relative humidity*

Technical Specifications

Model	Filter Type	Air Flow @100 psig (cfm)	Standard Conn. Size NPT(F)* (in.)	Max. Working Pressure (psig)	Housing Dimensions W x D x H (in.)	Weight (lbs.)
F6	KA, KB, KD, KE	20	1/2	232	6.1 x 3.4 x 14.1	7.5
F9	KA, KB, KC, KD, KE	30	3/4			
F16	KA, KB, KD, KE	55			6.5 x 3.9 x 15.4	8.8
F22	KA, KB, KD, KE	75	1		6.5 x 3.9 x 17.3	9.3
F26	KA, KB, KC, KD, KE	90				9.5
F46	KA, KB, KC, KD, KE	160	1-1/2		9.3 x 6.0 x 18.1	18.1
F83	KA, KB, KD, KE	290	2		9.3 x 6.0 x 21.5	20.1
F110	KA, KB, KD, KE	390			9.3 x 6.0 x 29.4	23.6
F142	KA, KB, KC, KD, KE	500				24.5

*** Other connection sizes available**

Specifications are subject to change without notice.

Proper Filter Sizing

To find the maximum flow for a filter size at pressures other than 100 psig, multiply the rated flow by the Correction Factor corresponding to the minimum pressure at the inlet of the filter. Do not select filters by pipe size. Use flow rate and operating pressure.

Correction Factors

Operating Pressure (psig)	30	40	60	80	100	120	140	160	180	200	220	230
Capacity Correction Factor	0.39	0.48	0.65	0.83	1.00	1.08	1.16	1.23	1.30	1.37	1.43	1.46

Note: Maximum inlet temperature is 150°F.



Silicone-free certification

Silicone-free versions of Kaeser filters are also available as an option. These filters are compliant with test standard PV-VW 3.10.7 and each one undergoes an individual coating test to confirm compliance. The supplied manufacturer's certificate attests that the product is silicone-free.

KAESER COMPRESSORS

Built for a lifetime.™



www.kaeser.com

Kaeser Compressors, Inc.
511 Sigma Drive
Fredericksburg, VA 22408 USA
Telephone: 540-898-5500
Toll Free: 800-777-7873
info.usa@kaeser.com


Kaeser Compressors Canada Inc.
3760 La Verendrye Street
Boisbriand, QC J7H 1R5 CANADA
Telephone: (450) 971-1414
Toll free: (800) 477-1416
info.canada@kaeser.com

Kaeser Compresores de México S de RL de CV
Calle 2 #123
Parque Industrial Jurica
76100 Querétaro, Qro.
Telephone: 01 (442) 218 64 48
sales.mexico@kaeser.com

Kaeser Compresores de Guatemala y Cia. Ltda.
Calz. Atanasio Tzul 21-00, zona 12
El Cortijo II, Bodega 501
01012–Guatemala City
Telephone: +502 2412-6000
info.guatemala@kaeser.com

© 2016 Kaeser Compressors, Inc. All rights reserved. 07/16
USKFILTER

Series 05
AIR LINE COMPRESSED AIR DISTRIBUTION SYSTEM



AIR LINE
AIR DISTRIBUTION SYSTEM





FEATURES AND BENEFITS

- **Installation ease:** AIR LINE installations can be carried out easily by the end-user, eliminating the need to employ expensive sub-contractor labour
- **Installation speed:** Push-to-connect fittings and rigid Nylon pipe allows installation of AIR LINE systems to be done much more quickly than conventional systems requiring welding, soldering and threading of heavy components
- **No waiting period:** An AIR LINE system can be put under pressure immediately following installation – no need to wait for glue to dry, for welds to cool or for leakage testing
- **Total flexibility:** The flexibility of the AIR LINE system ensures modifications and expansions can be carried out quickly and easily in seconds with very little cost or lost production. Integrates perfectly with existing conventional piping
- **Energy savings:** By eliminating leaks, AIR LINE can save up 20 to 40% of power consumption costs. Both the pipe and fittings are designed to reduce friction and pressure drop, further reducing power consumption
- **TOPRING AIR LINE** fittings and pipe are made of high quality Nylon, avoiding corrosion and contamination and ensuring high quality compressed air
- **Performance:** Achieves high flow rates and low pressure drops due to low frictional losses through smooth bore of pipe
- **Lightweight:** Only a small fraction of the weight of conventional Steel or black Iron
- **Completely reusable:** AIR LINE components are easy to remove and relocate to a new location, making moving an easier task

Régie du bâtiment Québec

The **AIR LINE** system is approved for installation as a compressed air system, by RBQ and meets the requirements of UL Norm 94 V2.

APPLICATIONS

The perfect system for air lines in workshops, garages and industry, also suitable for vacuum.

SPECIFICATIONS


Temperature Range: 0 °C to 70 °C
Working Pressure: 145 PSI (23 °C)
100 PSI (70 °C)

PROPER LINE SIZING FOR AN AIRLINE NETWORK

HOW TO DETERMINE PROPER LINE SIZING:

1. Identify type of network: closed loop or dead-end
2. Calculate total length of line (feet)
3. Determine total flow required
4. Use the chart below in order to identify the proper sizing

LINE SIZING FOR A CLOSED LOOP NETWORK




TOTAL LENGTH OF NETWORK (FEET)

TOTAL FLOW REQUIRED

SCFM \ FEET	100'	150'	200'	250'	300'	400'	500'	600'	700'	800'	900'	1000'	1250'	1500'	2000'
5	15	15	15	15	15	15	15	15	15	15	15	15	15	15	15
10	15	15	15	15	15	15	15	15	15	15	15	15	22	22	22
15	15	15	15	15	15	15	15	22	22	22	22	22	22	22	22
20	15	15	15	15	15	22	22	22	22	22	22	22	22	22	22
30	15	22	22	22	22	22	22	22	22	22	22	22	28	28	28
40	22	22	22	22	22	22	22	22	28	28	28	28	28	28	28
60	22	22	22	22	28	28	28	28	28	28	28	28	28	28	
80	22	22	28	28	28	28	28	28	28	28	28				
100	22	28	28	28	28	28	28	28							
125	28	28	28	28	28										
150	28	28	28	28			CONSULT SERIES 6 OR 7								
200	28	28													

LINE SIZING FOR A DEAD-END NETWORK



TOTAL LENGTH OF NETWORK (FEET)

TOTAL FLOW REQUIRED

SCFM \ FEET	25'	50'	75'	100'	150'	200'	250'	300'	400'	500'	600'	700'	800'	900'	1000'
5	15	15	15	15	15	15	15	15	15	15	15	22	22	22	22
10	15	15	15	15	15	22	22	22	22	22	22	22	22	22	22
15	15	15	22	22	22	22	22	22	22	22	28	28	28	28	28
20	15	22	22	22	22	22	22	22	28	28	28	28	28	28	28
30	22	22	22	22	28	28	28	28	28	28	28	28	28		
40	22	22	22	28	28	28	28	28	28						
60	22	28	28	28	28	28									
80	28	28	28	28											
100	28	28	28												
125	28														
150	28						CONSULT SERIES 6 OR 7								
200															


- Calculations based on total maximum pressure drop (△P) of no more than 3 PSIG for entire network, at 100 PSIG and 60 °F
- Total flow required takes account of all flows for all compressed air powered tools and equipment
- A typical compressor will produce approximately 4 SCFM per HP

AIR LINE
SEMI RIGID POLYAMIDE PIPE



FEATURES AND BENEFITS

- **AIR LINE pipes are available in 3 different bore sizes: 15 mm (1/2"), 22 mm (3/4") and 28 mm (1")**
- **Low friction for high flow**
- **Prevents the formation of rust**
- **Lightweight for ease of manipulation**
- **Calibrated pipe size for leak-proof connections**



- CALIBRATED
- LIGHTWEIGHT
- ANTI-CORROSION

MATERIALS

Polyamide 12 (PA12) - Self extinguishing

OK.

Product No	Lenght ft	Lenght m	Size mm	Approx. I.D. in	Weight lb
05.042	13	4	15 x 12	1/2	0.59
05.062	13	4	22 x 18	3/4	1.17
05.072	13	4	28 x 24	1	1.53

WATER TRAP TEE


Ideal for tapping air off a main line without allowing water to get into the drop



Product No	Size mm (A)	Size mm (B)
05.079	22	15
05.080	22	22
05.083	28	15
05.084	28	22
05.085	28	28




- Stops condensed water within the main air line from entering the vertical drop legs.
- It is important that the main air line be installed with the correct slope, and that water drain points be regularly vented



PREFORMED DROP BEND PIPE

Product No	Size mm
07.130	15
07.135	22

- Special Aluminium alloy
- Ideal for tapping air off a main line without allowing water to get into the drop



DEVIATION PIPE

Product No	D mm	Size mm
07.131	80	15
07.136	100	22

- Special Aluminium alloy
- Ideal for getting around obstacles and correcting minor alignment problems

4,B

PUSH-TO-CONNECT


Innovative push-to-connect technology makes assembly fast and easy

MATERIALS

Body: Black acetal copolymer
Seal: Nitrile rubber
Clamp: Black acetal copolymer with stainless steel teeth

FEATURES AND BENEFITS

- **Suitable for nylon and aluminium pipe**
- **Made of tough, resistant acetal copolymer plastic**
- **Push-to-connect design allows quick assembly**
- **Stainless steel gripping teeth for reliability and high pressure handling**
- **No soldering, no threading, no sealing required**
- **Full flow design**
- **Fully reusable**





PUSH-TO-CONNECT



MALE CONNECTOR (NPT)

Product No	Size mm	Thread (M) NPT
05.116	15	1/2
05.121	22	3/4
05.125	28	1



MALE CONNECTOR (BSPP)

Product No	Size mm	Thread (M) BSPP
05.115	15	1/2
05.120	22	3/4



UNION REDUCER TEE

Product No	Size mm (A)	Size mm (B)
05.170	22	15



« T » UNION

Product No	Size mm
05.160	15
05.165	22
05.168	28



WATER TRAP TEE

Product No	Size mm (A)	Size mm (B)
05.079	22	15
05.080	22	22
05.083	28	15
05.084	28	22
05.085	28	28



END CAP

Product No	Size mm
05.230	15
05.235	22



STRAIGHT UNION

Product No	Size mm
05.130	15
05.135	22
05.140	28



ELBOW UNION

Product No	Size mm
05.145	15
05.150	22
05.155	28



FEMALE REDUCER

Product No	Size mm (A)	Size mm (B)
05.210	15	22
05.212	15	28
05.215	22	28



MALE REDUCER

Product No	Size mm (A)	Thread (M) BSPP (B)
05.185	15	3/8
05.190	15	1/2
05.195	22	1/2
05.200	22	3/4
05.205 *	28	1 NPT

* Brass



PLUG

Product No	Size mm
05.220	15
05.225	22
05.227	28



STEM ELBOW

Product No	Size mm
05.365	15
05.370	22

COMPOSITE MANIFOLD

MATERIALS

Polyamide

SPECIFICATIONS

Maximum Working Pressure: 145 PSI
Temperature Range: 0 °C to 70 °C



Product No	Size mm Ⓐ	Outlet (F) NPT Ⓑ
05.450	15	3/8



Product No	Size mm Ⓐ	Outlet (F) NPT Ⓑ
05.455	15	3/8



Product No	Size mm Ⓐ	Outlet (F) NPT Ⓑ
05.470	15	1/2
05.475	22	1/2



Product No	Size mm Ⓐ	Outlet (F) NPT Ⓑ
05.480	22	1/2



Product No	Size mm Ⓐ	Outlet (F) NPT Ⓑ
05.487	15	1/2
05.489	22	1/2



SPACER



Product No	For Manifolds
47.120	47.108 - 47.112 - 07.470 - 07.480

ALUMINIUM MANIFOLD

MATERIALS

Aluminium

SPECIFICATIONS

Maximum Working Pressure: 145 PSI
Temperature Range: 0 °C to 70 °C




Product No	Size mm Ⓐ	Outlet (F) NPT Ⓑ
05.492	15	3/8 (2x)
05.496	22	3/8 (2x)



Product No	Size mm Ⓐ	Outlet (F) NPT Ⓑ
05.494	15	3/8 (3x)
05.498	22	3/8 (3x)



Product No	Size mm Ⓐ	Outlet (F) NPT Ⓑ
05.493	15	3/8 (2x)
05.497	22	3/8 (2x)



Product No	Size mm Ⓐ	Outlet (F) NPT Ⓑ
05.495	15	3/8 (3x)
05.499	22	3/8 (3x)

FACTS TO KNOW

For a complete selection of composite or aluminium manifolds, see Series 47





17_05_2016

CLIPS



PIPE CLIP FOR WALL MOUNTING

Product No	Size mm ○
05.325	15
05.330	22
05.335	28

Adding horizontal or vertical brackets can be done simply without having to cut the pipe



PIPE CLIP SPACER

Product No	Thickness
05.337	1/2" (12.7 mm)



CLIP WITH SPACER

PIPES CUTTER



RATCHET TYPE PIPE CUTTER

Product No	Description
36.200	Ratchet type Pipe cutter
36.205	Replacement blades (2)

- Allows effortless cutting of nylon pipe up to 41 mm (1-5/8") O.D.
- Straight, even, accurate cutting



PIPE CUTTER

Product No	Description
36.100	Pipe cutter
36.105	Replacement blades (2)

Allows effortless cutting of nylon pipe up to 41 mm (1-5/8") O.D. Straight, even, accurate cutting



BATTERY-OPERATED PIPE CUTTER

Product No	Description
36.020	Pipe cutter

Allows effortless cutting of nylon pipe and hose up to 42 mm

OTHER PRODUCTS



MANUAL DRAIN

Product No	Size mm ○	Fittings
05.500	15	Acetal
05.505	22	Brass

With ball valve, tube and fittings



MECHANICAL AUTOMATIC DRAIN

Product No	Size mm ○	Fittings
05.501	15	Acetal
05.506	22	Acetal

With ball valve, fittings and Y filter



HIGH FLOW SAFETY EXHAUST / LOCKOUT VALVE

Product No	Size mm ○	Fittings
07.430	15	Brass
07.435	22	Brass
07.440	28	Brass





BRASS BALL VALVE

Product No	Size mm ○	Fittings
05.400	15	Acetal
05.405	22	Brass
05.410	28	Brass



SAFETY EXHAUST/ LOCKOUT BRASS BALL VALVE

Product No	Size mm ○	Fittings
07.401	15	Brass
07.406	22	Brass
07.411	28	Brass

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jan 29, 2019

VEOLIA

SHOP DRAWINGS

Network Architecture Date : 2019-01-29

General Information			
Project	**WWTP UPGRADE - IQALUIT**		
Client:	Kudlik Construction Ltd.	Project Number	2018-062
To:	Sandra Rousseau P.Eng., Project Manger	E-mail:	srousseau@kudlik.biz
Contractor	Veolia Water Technologies Canad Inc.	Project Number	5000218036
Address	4105 Sartelon, Ville St. Laurent PQ, H4S 2B3		
Project Manger:	Clément Bekaert	E-mail:	clement.bekaert@veolia.com
Phone:	514-334-7230 x 3243	Cell:	514-246-6232

Information on the Equipment		
Specialty:	Electrical / automation	
Equipment:	Control panel(s)	
Drawing Reference:		
Specification reference:	46.71.24 46 36 11	
Article:		
Revision:	Rev02	
Titre:	Network Architecture	
Numero client:	DA-Veolia-CA-01-Network architecture	
Numero Veolia	5000218038_CA_0002_AU_VWT	
Envoyer pour:	Approbation/Information:	Approbation

Consultant Approval

Ensure connection between BFP Polymer control panel and Switch in CPL-901 via armoured Cat6 cable.

SHOP DRAWINGS ARE REVIEWED UNLESS NOTED OTHERWISE

REVIEWED AS MODIFIED	X	Stantec
REVISE & RESUBMIT		
SEAL & SIGNATURE REQUIRED		


DATE February 01/19

SIGNATURE Ellie Bron

REVIEW BY STANTEC IS FOR THE SOLE PURPOSE OF ASCERTAINING GENERAL CONFORMITY WITH DESIGN. CONTRACTOR IS RESPONSIBLE FOR DIMENSIONS, FABRICATION AND CONSTRUCTION METHODS, COORDINATION OF SUB-TRADES, DETAIL DESIGN OF COMPONENTS, AND ERRORS OR OMISSIONS ON SHOP DRAWINGS.

4105 Sartelon
Ville St. Laurent, PQ
H4S-2B3

Phone: 514-334-7230
Fax: 514-334-5070
www.veoliawatertechnologies.ca



MAIN PANEL
-Design and programming according to Veolia standards – PlantPAX Process Library 4.0
FactoryTalk View ME 10
Studio 5000 Logix Designer 31
The main panel is dedicated only for the equipment shown on this control architecture(not for future extension)
Veolia packages prewired Teck 90 /aluminium cable trays T&B Class E

		Spidflow #1	*Spidflow #2*
Switch:	10.8.20.11		
PLC:	10.8.20.25		
Panelview:	10.8.20.45	Eq #1: 10.8.20.43	Eq #1: 10.8.20.44
Int. Access	10.8.20.12		
Spare:	10.8.20.48		
Spare:	10.8.20.49		

NOTES :

All subnetmask are 255.255.255.0
All default gateway are 10.8.20.1
All DNS: n/a

Coax	HW	Hardwire
USB	REP	REP Network
RS232	FO	Fiber Optic
Profibus DP	DLR	Ethernet DLR
	Mod TCP	Modbus TCP/IP
	ETH	Panel Ethernet cables

VEOLIA

TITLE	Network Architecture Process					
CLIENT	Iqaluit WWTP Upgrade					
DATE	REV'D	CHK'D	APV'D	PROJECT	DRAWING	SHEET	REV
2019-01-28	DO	XM	-	5000218036	CA_0002_AU	1 OF 1	2

SUBMITTALS IDENTIFICATION SHEET

PROJECT: Wastewater Treatment Plant Upgrade
Iqaluit, Nunavut

NUNAMI
STANTEC LIMITED
1088C Noble House
Iqaluit NU
www.stantec.com

CONTRACTOR: Kudlik Construction Ltd, Project 2018-062

Telephone: 867-979-1166

E-mail: srousseau@kudlik.biz

SUBCONTRACTOR: Yvon Roy electrical

300, St-Jean Baptiste Nord, Princeville, Qubec, Qc G6L 5E 2

Person responsible: Cathy Brisson

Telephone: (819-505-1150) E-mail: cbrisson@yvonroyinc.com

PRODUCT SUBMITTED:

☐ As Specified

☐ Alternate

SUPPLIER or MANUFACTURER:

Person responsible:

Telephone:

DESCRIPTION OF SUBMITTAL:

# of pages:

Reference to drawings: I-201 note 1

Reference to specs:

Division: 47 Section: 47 30 01 2.2

REMARKS:

IJB-01-100 panel

REVIEW AND COMMENTS (for use by Consultants):

No comments

STANTEC PROJECT #: 110126045 SUBMITTAL # ROY-001 (2018-10-11)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☐ Electrical ☑ Other Instrumentation

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE 2018-OCT-11

BY David Hutchison, P.Eng.

Review of this submission is for compliance with general intent of the contract. This review does not relieve the Sub-Contractor, Supplier or Manufacturer of responsibility for error or omissions in the submission or the responsibility of meeting all requirements of the contract documents. Any deviation from the contract documents initiated by the Sub-Contractor, Supplier or Manufacturer shall be at their sole risk. QUANTITIES AND DETAIL DIMENSIONS ARE THE SUB-CONTRACTORS OR SUPPLIERS RESPONSIBILITY. VERIFY DATA WITH FIELD DIMENSIONS.

SUBMITTAL TRACKING No.: **ROY-001** 2018-10-11

AJBEW Cast Junction Boxes

Explosionproof, Dust-Ignitionproof

NEC/CEC:
Class I, Division 1 and 2, Groups B◊, C◊, D
Class I, Zone 1 and 2, Groups IIA, IIB◊+H_2◊
Class II, Division 1 and 2, Groups E, F, G
Class III
NEMA 4, 7B◊C◊D, 9EFG

ATEX/IECEx — Optional ①:
Zone 1 and 2 – 21 and 22
Ⓔx II 2 GD
IP66 – IK10

Application

- Explosionproof junction boxes are used where hazardous materials are handled or stored. These enclosures may be used for:
  - Terminals
  - Splicing wires
  - Pull boxes
  - Bus boxes

Features

- Precision machined flame path between box and cover.
- Bolt on stainless steel slotted mounting feet for horizontal or vertical mounting.
- Flexible hinge mounting either left or right side is standard on all boxes 12 x 12 x 06 and larger.
- External flange maximizes internal space.
- Wall thickness suitable for minimum of five full threads.
- Provision for mounting pan.
- Wide range of drilled and tapped outlets.
- Ground lug package and installation instructions for termination of ground wires enclosed.
- O-ring gasket insures watertight integrity.

Standard Materials

- Bodies and covers: sand cast copperfree (4/10 of 1% max.) aluminum
- Cover bolts: stainless steel
- O-ring: neoprene
- Hinges: stainless steel
- Mounting pan: galvanized steel

Standard Finishes

- Bodies and covers: shot blast finish standard

Options

- Custom drilling and tapping.
- Set of 4 standoffs 12.7 mm (0.50") high. For factory-installed option add suffix **-AB**.
- Breather, NEMA 4X (includes outlets and installation). For factory-installed option add suffix **-BR**, for field-installed option order catalog number **BRTB4X**.
- Drain, NEMA 4X (includes outlets and installation). For factory-installed option add suffix **-DN** for field-installed option order catalog number **ECD50B4X**.
- Desiccate package. For factory-installed option add suffix **-DP1**, for field-installed option order catalog number **AWG13/1CT**.
- External grounding stud 3/8"-16. For factory-installed option add suffix **-EGS**.
- Gray epoxy powder coat (outside). For factory-installed option add suffix **-G1**.
- Gray epoxy powder coat available to provide NEMA 4X rating (inside and outside). For factory-installed option add suffix **-G2**.
- Internal Ground Stud, #14 - #2. For factory-installed option add suffix **-GNDKIT**.
- Hinges: stainless steel hinge available for boxes up to 11 x 30 x 03. For factory-installed option add suffix **-H**.
- Hinge Kit, 2 light duty SS hinges. For field-installed option order catalog number **AHOF12SS**.
- Hinge Kit, 2 heavy duty SS hinges. For field-installed option order catalog number **AHOF22SS**.



- Hinge Kit, 3 heavy duty SS hinges. For field-installed option order catalog number **AHOF23SS**.
- Terminal blocks 600 Volt, 30 Amp Indicate number of points: example: 5 points = 5K. For factory-installed option add suffix **-K**.
- Plastic nameplate, 50.8 x 101.6 mm (2.00 x 4.00"), 3.3 mm (13") black letters on white surface, 3 lines max, specify legend. For factory-installed option add suffix **-NP**.
- SS captive Quad-Lead bolts. For factory-installed option add suffix **-Q**.
- ATEX complete product certification add suffix **-X** ①.
- ATEX U component certification add suffix **-XU** ①.
- Mounting pan. For factory-installed option add suffix **-Z**.

NEC/CEC Certifications and Compliances

- UL Standard: UL 1203
- cULus Listed: E85310
- CSA Standard: C22.2 No. 25, C22.2 No.30
- CSA Certified: 042129

ATEX/IECEx Certifications and Compliances

- Certification Type JBEW
  - Gas, Zones 1 and 2
    - Conforming to ATEX 94/9/CE: Ⓔx II 2 G
    - Type of Protection: Ex d IIB + H_2 GB
  - Dust, Zones 21 and 22
    - Conforming to ATEX 94/9/CE: Ⓔx II2 D
    - Type of Protection: Ex t Db
- Ambient Temperature: -40 °C to +55 °C (-40 °F to +131 °F)
- CE Declaration of Conformity: 5C239
- ATEX Certificate: LCIE 07 ATEX 6069X
- IECEx Certificate: IECEx LCI 07.0018X
- Internal Volume: > 2dm³ (122 in³) — 2 liters
- Index of Protection according EN/IEC 60529: IP66
- Impact Resistance (shock): IK10

EURASEC Certification

- Certification Type JBEW
  - EURASEC N° TC RU C-FR.ГБ05.B.00911

◊ For Groups B and C, all conduits must be sealed within 50.8 mm (2") of the enclosure.
① Ordering a product with any ATEX Certification nulls the UL, CSA and cULus Certifications.

Visit our website at **www.emerson.com** or contact us at **(800) 621-1506.**
© May 2017

EMERSON

AJBEW Cast Junction Boxes

Explosionproof, Dust-Ignitionproof

NEC/CEC:
Class I, Division 1 and 2, Groups B◊, C◊, D
Class I, Zone 1 and 2, Groups IIA, IIB◊+H_2◊
Class II, Division 1 and 2, Groups E, F, G
Class III
NEMA 4, 7B◊C◊D, 9EFG

ATEX/IECEx — Optional ①:
Zone 1 and 2 – 21 and 22
Ex II 2 GD
IP66 – IK10

Dimensions in Millimeters (Inches)												Max. Conduit Size Inches	Ship Weight kg (lb)	Mounting Hardware Catalog Number	Catalog Number
Overall Dimensions			Mounting Dimensions				Inside Dimensions								
F	E	G	A	AA	B	BB	W	H	Db	Dc	K				
416.1 (16.38)	889.0 (35.00)	260.4 (10.25)	241.3 (9.50)	384.3 (15.13)	835.2 (32.88)	692.2 (27.25)	285.8 (11.25)	759.0 (29.88)	157.2 (6.19)	47.8 (1.88)	106.4 (4.19)	3	51.3 (113)	AMH8	AJBEW113006
441.5 (17.38)	441.5 (17.38)	235 (9.25)	219.2 (8.63)	397.0 (15.63)	397.0 (15.63)	219.2 (8.63)	311.2 (12.25)	311.2 (12.25)	146.1 (5.75)	38.1 (1.50)	95.3 (3.75)	3	29.5 (65)	AMH8	AJBEW121206
441.5 (17.38)	441.5 (17.38)	292.1 (11.50)	219.2 (8.63)	397.0 (15.63)	397.0 (15.63)	219.2 (8.63)	311.2 (12.25)	311.2 (12.25)	196.9 (7.75)	38.1 (1.50)	120.7 (4.75)	3	31.8 (70)	AMH8	AJBEW121208
431.8 (17.00)	584.2 (23.00)	231.9 (9.13)	177.8 (7.00)	400.1 (15.75)	533.4 (21.00)	358.9 (14.13)	311.2 (12.25)	463.6 (18.25)	146.1 (5.75)	38.1 (1.50)	88.9 (3.50)	4	40.8 (90)	AMH5	AJBEW121806
431.8 (17.00)	584.2 (23.00)	282.7 (11.13)	177.8 (7.00)	400.1 (15.75)	533.4 (21.00)	358.9 (14.13)	311.2 (12.25)	463.6 (18.25)	222.3 (8.75)	38.1 (1.50)	108.0 (4.25)	4	45.8 (101)	AMH5	AJBEW121808
425.5 (16.75)	730.3 (28.75)	282.7 (11.13)	N/A	400.1 (15.75)	N/A	466.9 (18.38)	304.8 (12.00)	609.6 (24.00)	196.9 (7.75)	25.4 (1.00)	108.0 (4.25)	4	62.6 (138)	AMH4	AJBEW122408
425.5 (16.75)	1035.1 (40.75)	301.8 (11.88)	N/A	400.1 (15.75)	N/A	736.6 (29.00)	304.8 (12.00)	914.4 (36.00)	196.9 (7.75)	38.1 (1.50)	115.8 (4.56)	4	98.9 (218)	AMH5	AJBEW123608
457.2 (18.00)	1079.5 (42.50)	265.2 (10.44)	409.7 (16.13)	301.8 (11.88)	1035.1 (40.75)	857.3 (33.75)	346.2 (13.63)	962.2 (37.88)	155.7 (6.13)	38.1 (1.50)	109.5 (4.31)	3-1/2	86.2 (190)	AMH8	AJBEW133806
492.3 (19.38)	492.3 (19.38)	242.8 (9.56)	247.7 (9.75)	450.9 (17.75)	450.9 (17.75)	247.7 (9.75)	374.7 (14.75)	374.7 (14.75)	146.1 (5.75)	35.1 (1.38)	98.6 (3.88)	3-1/2	44.5 (98)	AMH8	AJBEW141406
492.3 (19.38)	492.3 (19.38)	293.6 (11.56)	247.7 (9.75)	450.9 (17.75)	450.9 (17.75)	247.7 (9.75)	374.7 (14.75)	374.7 (14.75)	196.9 (7.75)	35.1 (1.38)	101.6 (4.00)	3	47.6 (105)	AMH8	AJBEW141408
498.6 (19.63)	736.6 (29.00)	304.8 (12.00)	333.5 (13.13)	N/A	698.5 (27.50)	N/A	378 (14.88)	616.0 (24.25)	203.2 (8.00)	38.1 (1.50)	101.6 (4.00)	4	59.4 (131)	AMH6	AJBEW142408
539.8 (21.25)	1092.2 (43.00)	306.3 (12.06)	349.3 (13.75)	508.0 (20.00)	1057.4 (41.63)	812.8 (32.00)	397 (15.63)	946.2 (37.25)	189.0 (7.44)	38.1 (1.50)	133.4 (5.25)	4	113.4 (250)	AMH8	AJBEW153707
533.4 (21.00)	533.4 (21.00)	249.2 (9.81)	279.4 (11.00)	501.7 (19.75)	501.7 (19.75)	279.4 (11.00)	419.1 (16.50)	419.1 (16.50)	146.1 (5.75)	38.1 (1.50)	98.6 (3.88)	3-1/2	59.9 (132)	AMH8	AJBEW161606
533.4 (21.00)	533.4 (21.00)	314.7 (12.39)	279.4 (11.00)	501.7 (19.75)	501.7 (19.75)	279.4 (11.00)	419.1 (16.50)	419.1 (16.50)	212.9 (8.38)	38.1 (1.50)	124.0 (4.88)	4	63.5 (140)	AMH8	AJBEW161608
543.1 (21.38)	593.9 (23.38)	382.5 (15.06)	304.8 (12.00)	482.6 (19.00)	533.4 (21.00)	355.6 (14.00)	412.8 (16.25)	463.6 (18.25)	301.8 (11.88)	9.7 (0.38)	177.8 (7.00)	4	68.0 (150)	AMH8	AJBEW161812
546.1 (21.50)	693.7 (27.31)	230.1 (9.06)	330.2 (13.00)	505.0 (19.88)	641.4 (25.25)	393.7 (15.50)	417.6 (16.44)	571.5 (22.50)	146.1 (5.75)	31.8 (1.25)	84.1 (3.31)	3	59.0 (130)	AMH8	AJBEW162206
533.4 (21.00)	711.2 (28.00)	308.1 (12.13)	N/A	501.7 (19.75)	N/A	466.9 (18.38)	412.8 (16.25)	616.0 (24.25)	209.6 (8.25)	38.1 (1.50)	134.9 (5.31)	4	81.6 (180)	AMH6	AJBEW162408
527.1 (20.75)	831.9 (32.75)	219.2 (8.63)	330.2 (13.00)	N/A	781.1 (30.75)	N/A	412.8 (16.25)	717.6 (28.25)	146.1 (5.75)	38.1 (1.50)	79.5 (3.13)	3	68.0 (150)	AMH5	AJBEW162806
593.9 (23.38)	593.9 (23.38)	252.5 (9.94)	330.2 (13.00)	552.5 (21.75)	552.5 (21.75)	330.2 (13.00)	463.6 (18.25)	463.6 (18.25)	146.1 (5.75)	38.1 (1.50)	104.9 (4.13)	3-1/2	85.3 (188)	AMH8	AJBEW181806

◊ For Groups B and C, all conduits must be sealed within 50.8 mm (2") of the enclosure.
① Ordering a product with any ATEX Certification nulls the UL, CSA and cULus Certifications.

© May 2017

AJBEW Cast Junction Box Options and Accessories

Explosionproof, Dust-Ignitionproof

NEC/CEC:
Class I, Division 1 and 2, Groups B◊, C◊, D
Class I, Zone 1 and 2, Groups IIA, IIB◊+H_2◊
Class II, Division 1 and 2, Groups E, F, G
Class III
NEMA 4, 7B◊C◊D, 9EFG

ATEX/IECEx — Optional ①:
Zone 1 and 2 – 21 and 22
Ex II 2 GD
IP66 – IK10

Options

Factory–Installed Suffix	Field–Installed Catalog Number	Description
AB	Not Available	Set of 4 standoffs 12.7 mm (0.50") high
BR	BRTB4X	Breather, NEMA 4X (includes outlets and installation)
DN	ECD50B4X	Drain, NEMA 4X (includes outlets and installation)
DP1	AWG13/1CT	Desiccate package
EGS	EGSKIT	External grounding stud 3/8"-16
G1	Not Available	Gray powder coat epoxy (outside)
G2	Not Available	Gray powder coat epoxy (inside and outside)
GNDKIT		Internal Ground Stud, #14 - #2
H		Hinges stainless steel
	AHOF12SS	Hinge Kit, 2 light duty SS hinges
	AHOF22SS	Hinge Kit, 2 heavy duty SS hinges
	AHOF23SS	Hinge Kit, 3 heavy duty SS hinges
K	Not Available	Terminal blocks 600 Volt, 30 Amp *Indicate number of points: example: 5 points = 5K*
NP	Not Available	Plastic nameplate, 50.8 x 101.6 mm (2.00 x 4.00"), 3.3 mm (13") black letters on white surface, 3 lines max, specify legend.
Q	Not Available	SS captive Quad-Lead bolts
X	Not Available	ATEX Certification
XU	Not Available	ATEX Component Certification
Z	See table on following page	Mounting pan

Drill and Tap Options

(For drill and tap schedule, Drilling and Tapping Guidelines)

Symbol	Conduit Size (NPT) Inches	Symbol	Conduit Size (NPT) Inches
A	1/2	F	2
B	3/4	G	2-1/2
C	1	H	3
D	1-1/4	J	3-1/2
E	1-1/2	K	4

Blind Tapped Holes	
Suffix	Screw Size
BT1	#6 - 1/4"
BT2	5/16" - 1/2"

Mounting Hardware

Refer to ordering information for Enclosure-Mounting Hardware Correlation.

Factory–Installed Suffix	Field–Installed Catalog Number	Description
MH1	AMH1	1/4" - 20 x 1-1/4" Bolt, 1/4" - 20 Hex Nut, 1/4" Washers
MH2	AMH2	3/8" -16 x 1-1/4" Bolt, 3/8" -16 Hex Nut, 3/8" Washers
MH3	AMH3	7/16" - 14 x 1-3/4" Bolt, 7/16" - 14 Hex Nut, 7/16" Washers
MH4	AMH4	1/2" - 13 x 1-3/4" Bolt, 1/2" - 13 Hex Nut, 1/2" Washers
MH5	AMH5	1/2" - 13 x 2" Bolt, 1/2" - 13 Hex Nut, 1/2" Washers
MH6	AMH6	5/8" - 11 x 2" Bolt, 5/8" - 11 Hex Nut, 5/8" Washers
MH7	AMH7	1/2" - 13 x 1-1/4" Bolt, 1/2" - 13 Hex Nut, 1/2" Washers
MH8	AMH8	5/8" - 11 x 1-1/4" Bolt, 5/8" - 11 Hex Nut, 5/8" Washers

◊ For Groups B and C, all conduits must be sealed within 50.8 mm (2") of the enclosure.
① Ordering a product with any ATEX Certification nulls the UL, CSA and cULus Certifications.

© May 2017


AJBEW Cast Junction Box Drilling and Tapping Guidelines

Explosionproof, Dust-Ignitionproof

NEC/CEC:
Class I, Division 1 and 2, Groups B◊, C◊, D
Class I, Zone 1 and 2, Groups IIA, IIB◊+H_2◊
Class II, Division 1 and 2, Groups E, F, G
Class III
NEMA 4, 7B◊C◊D, 9EFG

ATEX/IECEx — Optional ①:
Zone 1 and 2 – 21 and 22
(Ex) II 2 GD
IP66 – IK10

Dimensions — See Catalog Number Tables



Drilling and Tapping Guidelines

Conduit Size (NPT)	Minimum Spacing For Conduit Centers in Millimeters (Inches)									
	1/2	3/4	1	1–1/4	1–1/2	2	2–1/2	3	3–1/2	4
1/2	54.1 (2.13)	54.1 (2.13)	57.2 (2.25)	66.8 (2.63)	71.4 (2.81)	79.5 (3.13)	92.2 (3.63)	101.6 (4.00)	114.3 (4.50)	114.3 (4.50)
3/4	54.1 (2.13)	54.1 (2.13)	57.2 (2.25)	66.8 (2.63)	71.4 (2.81)	79.5 (3.13)	92.2 (3.63)	101.6 (4.00)	114.3 (4.50)	114.3 (4.50)
1	57.2 (2.25)	57.2 (2.25)	60.5 (2.38)	71.4 (2.81)	76.2 (3.00)	82.6 (3.25)	95.3 (3.75)	104.9 (4.13)	114.3 (4.50)	117.6 (4.63)
1-1/4	66.8 (2.63)	66.8 (2.63)	71.4 (2.81)	79.5 (3.13)	84.1 (3.31)	92.2 (3.63)	104.9 (4.13)	114.3 (4.50)	120.7 (4.75)	127.0 (5.00)
1-1/2	71.4 (2.81)	71.4 (2.81)	76.2 (3.00)	84.1 (3.31)	88.9 (3.50)	96.8 (3.81)	109.5 (4.31)	117.6 (4.63)	125.5 (4.94)	133.4 (5.25)
2	79.5 (3.13)	79.5 (3.13)	82.6 (3.25)	92.2 (3.63)	96.8 (3.81)	104.9 (4.13)	117.6 (4.63)	127.0 (5.00)	148.1 (5.83)	146.1 (5.75)
2-1/2	92.2 (3.63)	92.2 (3.63)	95.3 (3.75)	104.9 (4.13)	109.5 (4.31)	117.6 (4.63)	130.3 (5.13)	84.1 (3.31)	146.1 (5.75)	155.7 (6.13)
3	101.6 (4.00)	101.6 (4.00)	104.9 (4.13)	114.3 (4.50)	117.6 (4.63)	127.0 (5.00)	84.1 (3.31)	146.1 (5.75)	152.4 (6.00)	158.8 (6.25)
3-1/2	114.3 (4.50)	114.3 (4.50)	114.3 (4.50)	120.7 (4.75)	125.5 (4.94)	136.7 (5.38)	146.1 (5.75)	152.4 (6.00)	158.8 (6.25)	165.1 (6.50)
4	114.3 (4.50)	114.3 (4.50)	117.6 (4.63)	127.0 (5.00)	133.4 (5.25)	146.1 (5.75)	155.7 (6.13)	158.8 (6.25)	165.1 (6.50)	171.5 (6.75)

◊ For Groups B and C, all conduits must be sealed within 50.8 mm (2") of the enclosure.
① Ordering a product with any ATEX Certification nulls the UL, CSA and cULus Certifications.

© May 2017

Stantec to confirm:
- Installation location
- Installation details
- Probe lenghts
* Possible conflict with roof for installation of longer probes.
HC, 2019-01-24

4x units:
LSHH-03-112 ✓
LSLL-03-113 ✓
LSHH-03-122 ✓
LSLL-03-123 ✓

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd
NAME: Sandra Rousseau P.Eng
DATE: Jan 30, 2019

NORCLAIR
MÉCANIQUE DE PROCÉDÉ

SHOP DRAWINGS

DA-IC-14 Vibronic level switch

Date : 2019-01-24

Information general	
Project : **WWTP UPGRADE - IQALUIT**	
Client : Kudlik Construction Ltd. To : Sandra Rousseau P.Eng., Project Manager	Project number : **2018-062** E-mail : srousseau@kudlik.biz
Contractor : **Norclair inc.**	Project number Norclair : **P1039**
Address : 1100, Mountain Masson, Laval, QC, Canada H7E 4P2	
Project Manager : Hugo Chartier, Project Manager	E-mail: hchartier@norclair.ca
Phone : 450-688-4012 # 706	Cell. : 514-703-0263

Information, subcontractor or supplier	
Sub/supplier : Endress & Hauder	
Contact : Stéphane Raymond	Phone : 514-940-2288

Information on the equipment	
Speciality : **Instrumentation and Control**	
Equipment : Vibronic level switch	
Drawing reference :	
Specification reference : 47 30 02 data sheets	Division :
Article :	Number of pages : 4

CONSULTANT APPROVAL

Installation Location: Level switches to be installed under the hatch above the tanks. See ISK-001 for location details.
Installation Detail: See attached engineering sketch ISK-001 for typical vibronic level switch detail. Each switch to have its own stand pipe.
Probe lengths: To be chosen such that LSLL-03-113 & LSLL-03-123 are 800mm above tank's bottom, and LSHH-03-112 & LSHH-03-122 are 3500mm above tank's bottom.

Ensure each instrument has appropriate amount of conduit fas. Contractor to power each instrument as necessary.

SHOP DRAWINGS ARE REVIEWED UNLESS NOTED OTHERWISE
REVIEWED AS MODIFIED ☒
REVISE & RESUBMIT ☐
SEAL & SIGNATURE REQUIRED ☐
Stantec
DATE February 8, 19
SIGNATURE Ellie Brion
REVIEW BY STANTEC IS FOR THE SOLE PURPOSE OF ASCERTAINING GENERAL CONFORMITY WITH DESIGN. CONTRACTOR IS RESPONSIBLE FOR DIMENSIONS, FABRICATION AND CONSTRUCTION METHODS, COORDINATION OF SUB-TRADES' DETAIL DESIGN OF COMPONENTS AND FOR OMISSIONS ON SHOP DRAWINGS.

1100, montée Masson
Laval, QC, Canada
H7E 4P2

Phone. : 450-688-4012
Fax : 450-661-6341
E-Mail : info@norclair.ca
www.norclair.ca

Endress+Hauser
People for Process Automation

DRAWING NUMBER	2002597302	PROJECT	Iqaluit
			Norclair Inc.

FTL51-C6UU0/0
FTL51-UAP2BB4E5A+Z1
Liquiphant M FTL51

Link to the product information:
www.ca.endress.com/FTL51

Point level/density, vibronic.
Extension tube.
Application: liquids.
Point level:
:: Millimeter precision switch point.
:: Application safety:
independent of liquid attribute,
independent of built up.
Density:
Continuous measurement.
:: Measure directly in the tank / pipe.
Certificate free, IS, NI, GP:Housing F17
Tag plate Stainless Steel 52006326

~~LSLL-02-122~~	LSHH-03-112
~~LSH-02-213~~	LSLL-03-113
~~LSH-02-214~~	LSHH-03-122
~~LSH-02-223~~	LSLL-03-123

U	Approval: CSA C/US General Purpose
AP2	Process Connection: NPS 4" Cl.150 RF, 316/316L flange ASME B16.5
BB	Probe Length; Type: 3,000 mm; 316L, Ra<3.2um/126uin
4	Electronics; Output: FEL54;SIL relay DPDT 19-253VAC/19-55VDC
E5	Housing; Cable Entry: F13 NEMA Type 4X/6P Encl. / F17 NEMA Type 4X Encl. Alu; NPT3/4 thread
A	Additional Option: Basic version
Z1	>>Marking: Tagging (TAG), see additional spec.

To be confirmed by Stantec for each unit

1100 Montee Masson
Laval, Qc
H7E 4P2

Hugo Chartier

Téléphone: **450-688-4012**
FAX **450-688-9123**
EMAIL hchartier@norclair.ca

SUPPLIER

Endress+hauser Canada Ltée
6800 Côte de liesse, suite 100
Ville Saint-Laurent, Québec, Canada
H4T 2A7

Téléphone: 514 733-0254 X2288
FAX 514 733-2924
EMAIL stephane.raymond@endress.com

ISSUED BY	Stéphane Raymond


ISSUED PRODUCT		DRAW.ISSUED FOR	
AS IS:	X	APPROUVAL:	X
Équivalent:		Information:	
Substitution:		Coordination:	


ENGINEER APPROUVAL STAMP

	Initiales	ISSUED DATE
	SR	December 18 2018

Tag: ~~LSLL-02-122~~
~~LSH-02-213~~
~~LSH-02-214~~

LSHH-03-112
LSLL-03-113
LSHH-03-122
LSLL-03-123





First Angle Projection

Disclaimer:

To ensure the accuracy of the information contained in this document every reasonable effort has been made. Endress+Hauser may not make any warranties,express or implied, with respect to the accuracy, the completeness or the technical or commercial usefulness of this document. Endress+Hauser may modify or replace this document any time.

© 18.12.2018 Endress+Hauser

Order Code :
FTL51-UAP2BB4E5A+Z1

Product Description :
Liquiphant M FTL51

www.addresses.endress.com


Endress+Hauser

People for Process Automation


Endress+Hauser
People for Process Automation

DRAWWING NUMBER	2002597302	PROJECT	Iqaluit


ELECTRICAL CONNECTIONS



100-FTL5xxxx-04-05-xx-xx-002



LEVEL INSTRUMENT PENETRATIONS
NO SCALE



TYPICAL VIBRONIC LEVEL SWITCH INSTALLATION
NO SCALE

ORIGINAL SHEET - ISO A1

C:\Users\vlarsen\Desktop\ISK-001.dwg
2019/05/28 - 9:18 PM By: Vlad

ORIGINAL SHEET - ISO A1

Consultants

Permit-Seal

NUNAMI
STANTEC LIMITED

1088C Nande House
Iqaluit NU
www.stantec.com

The Contractor shall verify and be responsible for all dimensions. DO NOT scale the drawing - any errors or omissions shall be reported to Stantec without delay.
The Copyrights to all designs and drawings are the property of Stantec. Reproduction or use for any purpose other than that authorized by Stantec is forbidden.

Client/Project
Iqaluit

IQALUIT WASTEWATER TREATMENT PLANT UPGRADE
City of Iqaluit, Nunavut

File Name: BX-001

	Dsgn.	Dwn.	Chkd.	Dept.
2017-10-05		VLA		YYMMDD

Title
INSTRUMENTATION SKETCH

Project No.
110126045

Scale 0 750 2250 3750mm
1:75

Drawing No.
ISK-001

Sheet
of

Revision
0

APPENDIX C

MAINTENANCE SCHEDULE

IQALUIT WWTP UPGRADE
ELECTRICAL EQUIPMENT MAINTENANCE SCHEDULE

EQUIPMENT	MAINTENANCE TASK	RECOMMENDED MAINTENANCE SCHEDULE
Emergency lighting systems	Functional test	Monthly
Fire alarm system	Functional test	Annually
Generator	Functional test	Monthly

IQALUIT WWTP UPGRADE
INSTRUMENTATION MAINTENANCE SCHEDULE

AREA LOCATION	EQUIPMENT / TAG	MAINTENANCE TASK	RECOMMENDED MAINTENANCE SCHEDULE
T-01-001 Influnet Pump Station Wet Well Instruments	Level Switches (LSLL-01-111, LSL-01-112, LSH-01-113, LSHH-01-114)	No special maintenace required other than cleaning the bulbs to remove grease build up on the bulbs.	As required.
	Level Element (LE-01-100)	Normally, the transducer requires no cleaning or maintenance. However, if performance changes are observed, immediately shut down the level measurement system and perform a thorough inspection, especially on the transducer.	As required.
	Level Transmitter (LIT-01-100)	SITRANS LUT400 requires no maintenance or cleaning under normal operating conditions. However, the following can be completed: firmware update, replace batter. See manuel for more details.	Battery has a life expectancy of 10 years.
	Flow Meter (FQIT-01-150)	No special maintenance work is required. Cleaning the exterior of the device is a good practice.	As required.
Fine Screens SCRN-01-210/220	Solenoid Valves (SV-01-120, SV-01-122, SV-01-124, SV-01-126)	*	
	Level Elements (LE-01-211, LE-01-221)	*	
	Level Transmitters (LIT-01-211, LIT-01-221)	*	
	Motorized Valve Actuators (FV-01-211, FV-01-221, FV-01-112, FV-01-112A)	*	
Primary Filters PF-01-310/320	Motorized Valve Acutaors (FV-01-111, FV-01-121, FV-01-001)	*	
	Solenoid Valves (SV-01-312, SV-01-322, SV-01-113, SV-01-313, SV-01-323, SV-01-123)	*	
	Level Element (LE-01-115, LE-01-125)	*	
	Level Transmitter (LIT-01-115, LIT-01-125)	*	
	Pressure Transmitter (PT-01-116, PT-01-126)	*	
Process Aeration Blowers B-02-110/120/130	Pressure Switch (PSL-02-108, PSL-02-143, PSL-02-146, PSH-02-118, PSH-02-128, PSH-02-138)	*	
	Pressure Transmitter (PT-02-195)	Keep the pressure compensation and GORE-TEX® filter (1) free from contamination. Cleaning the exterior of the device is a good practice. Clean diaphragm with clean cloth if build-up is noticed.	As required or if a change in measurement is noted.
	Thermal Mass Flow Meters (FQIT-02-152, FQIT-02-156, FQIT-02-172)	Clean sensor by applying a non-filming or oil-free type cleaning fluid to a soft brush or cloth and gently wiping over the surf	Sensor to be cleaned periodicaly at first, and schedule to be confirmed depending of impurities.
MBBR T-02-210/220	Motorized Valve Acutaors (FV-02-211, FV-02-221)	*	
	Level Switches (LSH-02-213, LSH-02-214, LSH-02-223, LSH-02-224)	*	
	DO Elemet (AE-02-211, AE-02-212, AE-02-221, AE-02-222)	Clean sensor, Replacing wear and tear materials (sealing ring, electrolyte, membrane cap) as necessary	Monthly
	DO Transmitter (AIT-02-211, AIT-02-212, AIT-02-221, AIT-02-222)	Recalibration, Check the measuring function	Monthly
DAF T-02-310/320	Motorized Valve Acutaors (FV-02-625, FV-02-645, FV-02-309, FV-02-310, FV-02-329, FV-02-330)	*	
	Motorized Valve Acutaors (FV-02-312, FV-02-332)	*	
	Level Switches (LSH-02-330, LSH-02-340, LSH-02-332, LSH-02-342, LSL-02-333, LSL-02-343)	*	
	TSS Element (AE-02-334, AE-02-344)	*	
	TSS Transmitter (AIT-02-334, AIT-02-344)	*	
	Level Element (LE-02-331, LE-02-341)	*	
	Level Transmitter (LIT-02-331, LIT-02-341)	*	
DAF White Water Strainers STR-02-530/540	Magnetic Flow Meter (FIT-02-317, FIT-02-327)	See Veolia O&M	
	Motorized Valve Acutaors (FV-02-511, FV-02-512, FV-02-521, FV-02-522, FV-02-531, FV-02-532, FV-02-541, FV-02-542)	See Veolia O&M	
	Pressure Transmitter (PT-02-527, PT-02-547)	See Veolia O&M	
DAF Polymer PDS-04-700	Solenoids (SV-04-713, SV-04-714)	*	
	Pressure Switch (PSL-04-711)	*	
	Level Switch (LSL-04-710)	*	
	Level Transmitter (LIT-04-742, LIT-04-746)	*	
	Polymer Transmitter (AIT-04-741. AIT-04-745)	*	
DAF Polymer Dosing P-04-770/780/790	Solenoids (FV-04-783, FV-04-784)	*	
	Pressure Switch (PSH-04-787, PSH-04-790, PSH-04-793)	*	
	Flow Meter (FIT-04-798, FIT-04-799)	No special maintenance work is required. Cleaning the exterior of the device is a good practice.	As required.
TWAS Tanks T-03-630/640	Pressure Switch (PSH-04-639, PSH-02-639)	*	
	Vibronic Level Switches (LSLL-03-113, LSLL-03-123, LSHH-03-112, LSHH-03-122)	Complete visual inspection and clean-up build-up on the sensor with water.	As required or when measuring device becomes faulty.
	Level Element (LE-03-111, LE-03-121)	Normally, the transducer requires no cleaning or maintenance. However, if performance changes are observed, immediately shut down the level measurement system and perform a thorough inspection, especially on the transducer.	As required.
	Level Transmitter (LIT-03-111, LIT-03-121)	The unit requires no maintenance or cleaning under normal operating conditions.	--
BFP-03-650	Pressure Switch (PSH-03-668, PSH-03-389)	*	
	Flow Meter (FIT-03-695)	No special maintenance work is required. Cleaning the exterior of the device is a good practice.	As required.
	Pressure Transmitter (PIT-03-606)	Keep the pressure compensation and GORE-TEX® filter (1) free from contamination. Cleaning the exterior of the device is a good practice. Clean diaphragm with clean cloth if build-up is noticed.	As required or if a change in measurement is noted.
BFP Polymer PSD-04-900	Solenoids (SV-04-913, SV-04-914)	*	
	Pressure Switch (PSL-04-911)	*	
	Level Switch (LSL-04-910)	*	
	Level Transmitter (LIT-04-942, LIT-04-946)	*	
	Polymer Transmitter (AIT-04-941. AIT-04-945)	*	
BFP Polymer Dosing P-04-970/980	Solenoids (FV-04-982)	*	
	Pressure Switch (PSH-04-987, PSH-04-990)	*	
	Flow Meter (FIT-04-999)	No special maintenance work is required. Cleaning the exterior of the device is a good practice.	As required.
Building	Gas Detection (AIT-900 series)	*	See Norclair O&M for cleaning instructions
	Tempertaure Transmitter (TT-940 series)	*	
	Smoke Detectors	*	
	Strobes and Horns	*	See Norclair O&M for cleaning instructions

***Note: Refer to Supplier Operation & Maintenance Manuals for more detailed information on equipment maintenance schedule.**

APPENDIX D

EQUIPMENT MAINTENANCE AND OPERATION MANUALS

SEE SUPPLIER O&M MANUAL (NORCLAIR AND VEOLIA)
FOR INSTRUMENTATION AND CONTROL EQUIPMNET
OPERATIONS AND MAINTENANCE MANUAL

Date: Dec 10, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-13

Attached are the following items:

- [ ] Drawings
- [ ] Prints
- [ ] Plans
- [ ] Specifications
- [x] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

OM Manual-Preliminary

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

Warranty

Training

Testing

Permits

List of Suppliers

26 05 21 – Wires and Cables (0-1000V)

26 05 36 – Cable Trays for Electrical Systems

26 12 17 – Dry Type Transformers up to 600V Primary

26 24 01 – Service Equipment

26 24 17 – Panelboards Breaker Type

26 24 19 – Motor Control Centres

26 29 23 – Variable Frequency Motor Controllers

26 32 14 – Power Generation Diesel

26 36 23 – Automatic Transfer Switch

26 50 00 – Lighting

26 52 01 – Unit Equipment for Emergency Lighting

26 53 00 – Exit Signs

28 16 05 – Intrusion Detection

28 31 01 – Fire Alarm Systems



PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

Warranty

Arctic Electrical Nunavut Ltd

PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

ARCTIC ELECTICAL NUNAVUT LTD.

LETTER OF WARRANTY

FOR

WASTEWATER TREATMENT PLANT UPGRADE

IQALUIT, NUNAVUT

The control system and electrical installation has been tested and found to be in proper working condition at the time of turnover, and it is guaranteed to be free from any defect in workmanship and material that may develop within a one-year period from date of acceptance.

Any parts or parts of the control system and electrical installation, as defined in the Control System and Electrical Specification, that prove defective within one-year period shall be replaced without charge, when subjected to examination by one of our representatives and, in our opinion, is due to faulty material or workmanship and not caused by tampering, abuse, or misapplication.

This warranty is limited to Divisions 26 and 28 materials and associated equipment, and in no event shall Arctic Electrical Nunavut Ltd. have any liability for consequential damages, expenses or lost revenue due an electrical system failure. Any alterations to the system without the expressed written consent from Arctic Electrical Nunavut Ltd. will render this warranty null and void.

Arctic Electrical Nunavut Ltd.



PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

Training

Arctic Electrical Nunavut Ltd

System: Automatic Transfer Switch

System Operation Training

The operation of the Automatic Transfer switch has been demonstrated to the local maintainer. This includes, but not limited to:

1. An overview of the entire system and location of all devices.
2. How to operate the system.
3. How to open, shutdown and reset the system for troubleshooting

Trained By: Tim Rex **Date:** Mar/14/19

I verify that I have been trained and understand my training on the System

Name:	Date:
Maria Farveli Eric Mowder	March 14, 2019 14 MARS 2019

Arctic Electrical Nunavut Ltd

System: _____

System Operation Training

The operation of the Generator has been demonstrated to the local maintainer. This includes, but not limited to:

1. An overview of the entire system and location of all devices.
2. How to operate the system.
3. How to open, shutdown and reset the system for troubleshooting

Trained By: Tim Rex **Date:** Mar/14/19

I verify that I have been trained and understand my training on the System

Name:	Date:
Maria Karveli	March 14, 2019
Eric Mueller	14 MARS, 2019
ERIC [illegible]NON	

Arctic Electrical Nunavut Ltd

System: _____

System Operation Training

The operation of the Main Distribution has been demonstrated to the local maintainer. This includes, but not limited to:

1. An overview of the entire system and location of all devices.
2. How to operate the system.
3. How to open, shutdown and reset the system for troubleshooting

Trained By: Tim Rex **Date:** Mar/14/19

I verify that I have been trained and understand my training on the System

Name:	Date:
Maria Karvelis	March 14, 2019
Eric Mumber	14 MARS 2019
ERIC [illegible]	

Arctic Electrical Nunavut Ltd

System: _____

System Operation Training

The operation of the MCC has been demonstrated to the local maintainer.
This includes, but not limited to:

1. An overview of the entire system and location of all devices.
2. How to operate the system.
3. How to open, shutdown and reset the system for troubleshooting

Trained By: Tim Rex **Date:** Mar/14/19

I verify that I have been trained and understand my training on the System

Name:	Date:
Maria Karveli	March 14, 2019
ERIC MUNGER	MARS 14 2019
ERIC GAGNON	MARS 14 2019

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

Testing

Arctic Electrical Nunavut Ltd

PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

Permits

26-Jul-2018

Government of Nunavut

Department of Community and Government Services

Baffin Region	Kivalliq Region	Kitikmeot Region
P.O. Box 1000 Station 610 Iqaluit, NU X0A 0H0 Phone: (867) 975-5423 Fax: (867) 975-5453	Bag 002 Rankin Inlet, NU X0C 0G0 Phone: (867) 645-8179 Fax: (867) 645-8196	Bag 200 Cambridge Bay, NU X0B 0C0 Phone: (867) 983-4157 Fax: (867) 983-4152

PERMIT FOR WIRING INSTALLATION

FOR USE BY QUALIFIED ELECTRICAL WORKERS

Permit Type: multi/commercial/industrial **Application Date:** 26-Jul-2018

LOCATION

Community: Iqaluit **Location:** Waste Water Treatment Plant **Lot:** **Block:**

OWNER

Name: City of Iqaluit, Eslam Maher **Address:** Iqaluit, Nu X0A0H0 **Phone:** (613) 216-4345 ext **Fax:**

INSTALLATION DETAILS

Construction Type: Addition Service Rating **Phase:** 3Phase
Plan Review # : RJK **Voltage:** 347/600
Power Connection Required: YES **Amperes:** 400
Work Description: Rewiring of Waste Water Plant

ELECTRICIAN

Name: Colin Molloy
#: E-0090 **Expiry:** 27-Oct-2018
Company: Arctic Electrical **Phone:** (867) 975-3494 ext
Address: Box 1381, Iqaluit, NU **Postal:** X0A 0H0 **Fax:** (867) 979-2496

Cost of Installation (Includes labour, travel, room _board)	**$610,000.00**
Permit Fee	**$12,852.00**

I (We) propose to install electrical wiring, apparatus, fittings or alterations, the particulars of which are set out above and hereby certify that this installation will be completed in accordance with the Canadian Electrical Code and Territorial Electrical Protection Act

OFFICE USE ONLY

PERMISSION IS HEREBY GRANTED TO DO THE ABOVE WORK PROVIDED IT IS COMMENCED BY Wednesday October 24, 2018 AND COMPLETED NO LATER THAN Friday July 26, 2019

RECEIPT No.	**GRN3650965**
PERMIT No.	**10186**

Issued By: Jessie Nikki — Issue Date: July 26, 2018

July 26, 2018

30-Jul-2018

Government of Nunavut

Department of Community and Government Services

Baffin Region	Kivalliq Region	Kitikmeot Region
P.O. Box 1000 Station 610 Iqaluit, NU X0A 0H0 Phone: (867) 975-5423 Fax: (867) 975-5453	Bag 002 Rankin Inlet, NU X0C 0G0 Phone: (867) 645-8179 Fax: (867) 645-8196	Bag 200 Cambridge Bay, NU X0B 0C0 Phone: (867) 983-4157 Fax: (867) 983-4152

ELECTRICAL INSPECTION REPORT

PERMIT: 10186

INSTALLATION

Location

Community: Iqaluit
Street: Waste Water Treatment Plant
Lot: Block:
Owner: CITY OF IQALUIT, Eslam Maher
Phone: (613) 216-4345 ext:
Fax:

Permit

PermitType: multi/commercial/industrial
Amperes: 400
Voltage: 347/600

Contractor

Name: Colin Molloy
#: E-0090
Company: Arctic Electrical
Address: Box 1381
Iqaluit, NU
Postal: X0A 0H0

INSPECTION

Date: 30-Jul-2018
Type: Power
Corrections Due By:
Inspector: Rick Kelly
Outcome: Not Complete
Fee: NO

DEFICIENCIES

CEC Section	Details	Status	Date
3-002	Power connection approval is granted	Open	30-Jul-2018

Please sign and return corrected deficiencies by the date listed above _____

Contractor Signature

10-Dec-2018

Government of Nunavut

Department of Community and Government Services

Baffin Region	Kivalliq Region	Kitikmeot Region
P.O. Box 1000 Station 610	Bag 002	Bag 200
Iqaluit, NU	Rankin Inlet, NU	Cambridge Bay, NU
X0A 0H0	X0C 0G0	X0B 0C0
Phone: (867) 975-5423	Phone: (867) 645-8179	Phone: (867) 983-4157
Fax: (867) 975-5453	Fax: (867) 645-8196	Fax: (867) 983-4152

ELECTRICAL INSPECTION REPORT

PERMIT: 10186

INSTALLATION

Location

Community: Iqaluit
Street: Waste Water Treatment Plant
Lot: Block:
Owner: CITY OF IQALUIT, Eslam Maher
Phone: (613) 216-4345 ext:
Fax:

Permit

PermitType: multi/commercial/industrial
Amperes: 400
Voltage: 347/600

Contractor

Name: Colin Molloy
E-0090
Company: Arctic Electrical
Address: Box 1381 Iqaluit, NU
Postal: X0A 0H0

INSPECTION

Date: 30-Jul-2018
Type: Power
Corrections Due By:
Inspector: Rick Kelly
Outcome: Not Complete
Fee: NO

DEFICIENCIES

CEC Section	Details	Status	Date
3-002	Power connection approval is granted	Corrected	30-Jul-2018

Please sign and return corrected deficiencies by the date listed above _____
Contractor Signature



PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

List of Suppliers

ARCTIC ELECTICAL NUNAVUT LTD.

LIST OF SUPPLIERS

FOR

WASTEWATER TREATMENT PLANT UPGRADE

IQALUIT, NUNAVUT

Power Load Bank & Automatic Transfer Switch
Frontier Power Products Ltd.
9204 – 37 Avenue
Edmonton, AB T6E 5L4
Contact: Will Osburn
P. 780-733-6427
F. 780-451-5469

Distribution & Emergency Lighting
Nedco – Rexel Group
130 Collins Street, R.R. #6
Perth, ON K7H 3C8
Contact: Murray Tulloch
P. 613-267-3560
F. 613-267-5546

Lighting
Guillevin International – Ottawa Branch
175 Richmond Road
Ottawa, ON K1Z 6W3
Contact: Robert Pollock
P. 613-880-5260
F. 613-722-0596

Fire Alarm & Security Systems
Chubb Edwards
8205 Boulevard du Golf
Anjou, QC H1J 0B2
Contact: Eric Genest
P. 514-826-3762
F. 514-328-7693

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 05 21 - Wires and Cables (0-1000V)

Date: Jan 21, 2019

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jan 21, 2019

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-14
PO-Guillevin-Quote-1135711

Attached are the following items:

- [ ] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 05 21 Wires and Cables (0-1000 V)-Fire Alarm Cable

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-014

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2019-01-24
BY Konrad Goluch

Minimum wire size as spec 26 05 21 2.4.2.4

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

Deca Cables Inc.
150 North Murray Street
P.O. Box 777
Trenton, Ontario K8V 5W6
Canada

Website: www.decacables.com
Telephone: (613) 392-3585
Facsimile: (613) 392-7908
Email: sales@decacables.com

ISO 9001:2008

PRODUCT DATA SHEET

Part No: 32-1805

CONSTRUCTION SPECIFICATIONS

Description	FIRE ALARM 5C 18 AWG UNSH AIA 300V
Conductor	18 AWG Solid Bare Copper
Conductor Diameter	0.0403"
Insulation Type	Semi Rigid PVC
Insulation Thickness	.015"
Conductor Identification	Black, Red, Green, Blue, Brown
Cable Assembly	Conductors are cabled together. A PVC jacket is applied over the cabled assembly. An aluminum armour is applied over the inner jacket. An outer PVC jacket is applied over the aluminum armour.
Ripcord	Polyester Ripcord included under the inner jacket
Inner Jacket	0.020" (minimum average), Flame Retardant Red PVC
Armour Type	Interlocked Aluminum Armour
Outer Jacket	0.045" (minimum average), Flame Retardant Red PVC
Overall Cable Diameter	0.509"
Jacket Print	"DECAGUARD" 5C18AWG 105C CSA FAS105 FT4 300V AIA SUN RES LL81646 ---- ROHS work order #, month, year, metre markings (every 1 metre)

ELECTRICALS

Voltage	300V	
Conductor Resistance	6.39	Ohms/Mft @20C

CERTIFICATIONS AND PHYSICAL PROPERTIES

CSA Certified	*CSA C22.2 No.208 Fire Alarm and Signal Cable	
Flame Test Rating	CSA FT4	
Temperature Rating	105C	
ROHS	Compliant	
Cable Weight	184	kg/km
Copper Content	37	kg/km
Max Pull Tension	41	kgs
Min Bending Radius	6.25	inches (installed)
Max Cable Length	8475	metres

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 36 05 Cable Trays for Electrical Systems

Date: July 11, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd
NAME: Sandra Rousseau P.Eng
DATE: Jul 11, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-10
PO-P18-162

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 26 05 36 Cable Trays for Electrical Systems

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-010

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-30
BY Konrad

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the

Responsibility remains with the contractor as per the contract documents.

Do not hesitate to contact me if you have any questions or concerns.

Engineering Cable Tray Specification (cont'd)

Table 3

Steel Load / Span Class Designation

Side Rail Height (in.)	Series	Load Depth (in.) Nominal	NEMA Class	CSA Class
3-5/8	SH13/SP13/SS13	2-5/8	12A	C/3m
4	SH14/SP14/SS14 SH34/SP34/SS34	3	12C 20A	D/3m D/6m
5	SH25/SP25/SS25 SH45/SP45/SS45 SH55/SP55	4	20A 20B 20C	D/6m E/6m
6	SH16/SP16/SS16 SH36/SP36/SS36 SH46/SP46/SS46	5	20A 20B 20C	D/6m E/6m –
7	SH37/SP37/SS37	6	20C	–

**Must Confirm Class of Tray Required-Quoted Series 1

Straight Lengths

6 in. Straight Sections
Series 1-6, 3-6, 4-6

Ladder, ventilated and solid trough

Straight Section Number Selection P/N- SH1624L12-3

SH3624L12-6

Material Prefix	Series	Side Rail Height	Width	Bottom Type	Length
SP • Pregalvanized SH • Hot-dipped galvanized after fabrication SS • Stainless Steel 316	1 • Series 1 3 • Series 3 4 • Series 4	6 • (6 in.)	06 • (6 in.) 09 • (9 in.) 12 • (12 in.) 18 • (18 in.) 24 • (24 in.) 30 • (30 in.) 36 • (36 in.) 42 • (42 in.)	L06 • 6 in. rung spacing L09 • 9 in. rung spacing L12 • 12 in. rung spacing V • Ventilated ** S • Solid trough	3 • (3 meters) 6 • (6 meters) 144 • (12 ft.) 288 • (24 ft.)

** For load ratings of CSA Class C/NEMA 8C or less, please see an alternative ventilated series of cable tray called - One-Piece found on pages A160 to A191 of this catalogue.

Technical Specifications

All calculations and data are based on 42 in. wide cable trays with rungs spaced on 12 in. centers with tray supported as simple spans with deflection measured at the midpoint. Continuous spans may reduce deflection by as much as 50%.

Deflection factor: For lighter loads, deflection at any length can be calculated by multiplying the load by the deflection factor.

For Fittings consult pages A50 to A91.

Series		Support Span (Feet)							
		6	8	10	12	14	16	18	20
SP1-6	Load (lb.)/ft.	556	313	200	139	102	78	62	50
SH1-6	Deflection (in.)	0.122	0.216	0.338	0.486	0.662	0.865	1.095	1.351
SS1-6	Deflection Factor	0.0002	0.0007	0.0017	0.0036	0.0065	0.0111	0.0177	0.0270
SP3-6	Load (lb.)/ft.	833	469	300	208	153	117	93	75
SH3-6	Deflection (in.)	0.151	0.268	0.419	0.603	0.821	1.072	1.357	1.675
SS3-6	Deflection Factor	0.0002	0.0006	0.0014	0.0030	0.0055	0.0092	0.0146	0.0223
SP4-6	Load (lb.)/ft.	–	728	466	324	238	182	144	117
SH4-6	Deflection (in.)	–	0.312	0.487	0.702	0.955	1.247	1.579	1.949
SS4-6	Deflection Factor	–	0.0004	0.0011	0.0022	0.0041	0.0069	0.0110	0.0167

Straight Lengths

6 in. Straight Sections
Series 1-6, 3-6, 4-6

Ladder, ventilated and solid trough








Dimensions

SP1-6, SH1-6, SS1-6, SP3-6, SH3-6, SS3-6, SP4-6, SH4-6, SS4-6	
W (in.)	**Wi (in.)**
6	3.34
9	6.34
12	9.34
18	15.34
24	21.34
30	27.34
36	33.34
42	39.34

Technical Specifications

LOAD RATINGS: 1.5 Safety factor. All tray sections will support an additional 200 lb. concentrated load on any portion of tray (side rail, rung, etc.) above and beyond published load class.

Series	Dimensions	Side Rail Design Factors • 1 Pair	Classifications			
			NEMA	CSA	UL	ABS
SP1-6 **SH1-6** **SS1-6**		Ix = 4.44 in.^{4} Sx = 1.39 in.^{3} Area = 0.874 in.^{2}	**20A**	**D/6M**	UL cross sectional Area : 0.70 in.^{2}	Stainless steel only
SP3-6 **SH3-6** **SS3-6**		Ix = 5.373 in.^{4} Sx = 1.70 in.^{3} Area = 1.229 in.^{2}	**20A**	**E/6M**	UL cross sectional Area : 1.00 in.^{2}	Stainless steel only
SP4-6 **SH4-6** **SS4-6**		Ix = 7.173 in.^{4} Sx = 2.250 in.^{3} Area = 1.471 in.^{2}	**20C**	**Exceeds E/6M**	UL cross sectional Area : 1.00 in.^{2}	Stainless steel only

Fittings

45° / 30° Horizontal Bends

Part Numbering System

SHF 4 24 L HB45 12

- SHF: Prefix (SPF, SHF, SSF)
- 4: Side rail height
- 24: Width
- L: Bottom style
- HB45: Fitting type
- 12: Angle
- Nominal radius


Selection Guide

Prefix: SPF (Pregalv.) ,SHF (Hot-Dip) ,SSF (Stainless Steel)
Inside Tray Widths: 6, 9, 12, 18, 24, 30, 36, 42
Angle: 45º, 30º
Nominal Radius: 12, 24, 36, 48
Bottom Styles: L– Ladder, V– Ventilated, S– Solid
Side Rail Heights: 3 in., 4 in., 5 in., 6 in., 7 in.

P/N - SHF624LHB9024

45º Horizontal BEND






Nominal		Cat. No.	Dimensions		
Radius	Width		X	Y	Z
12	6	Prefix(†)-06-(*)-HB45-12	13-5/8	5-5/8	8
	9	Prefix(†)-09-(*)-HB45-12	14-11/16	6-1/16	8-9/16
	12	Prefix(†)-12-(*)-HB45-12	15-3/4	6-1/2	9-3/16
	18	Prefix(†)-18-(*)-HB45-12	17-7/8	7-3/8	10-7/16
	24	Prefix(†)-24-(*)-HB45-12	20	8-1/4	11-11/16
	30	Prefix(†)-30-(*)-HB45-12	22-1/16	9-1/8	12-15/16
	36	Prefix(†)-36-(*)-HB45-12	24-3/16	10	14-3/16
	42	Prefix(†)-42-(*)-HB45-12	26-5/16	10-15/16	15-7/16
24	6	Prefix(†)-06-(*)-HB45-24	22-1/16	9-1/8	12-15/16
	9	Prefix(†)-09-(*)-HB45-24	23-1/8	9-9/16	13-9/16
	12	Prefix(†)-12-(*)-HB45-24	24-3/16	10	14-3/16
	18	Prefix(†)-18-(*)-HB45-24	26-5/16	10-15/16	15-7/16
	24	Prefix(†)-24-(*)-HB45-24	28-7/16	11-13/16	16-11/16
	30	Prefix(†)-30-(*)-HB45-24	30-9/16	12-11/16	17-15/16
	36	Prefix(†)-36-(*)-HB45-24	32-11/16	13-9/16	19-1/8
	42	Prefix(†)-42-(*)-HB45-24	34-13/16	14-7/8	20-3/8
36	6	Prefix(†)-06-(*)-HB45-36	30-9/16	12-11/16	17-15/16
	9	Prefix(†)-09-(*)-HB45-36	31-5/8	13-1/8	18-9/16
	12	Prefix(†)-12-(*)-HB45-36	32-11/16	13-9/16	19-1/8
	18	Prefix(†)-18-(*)-HB45-36	34-13/16	14-7/16	20-3/8
	24	Prefix(†)-24-(*)-HB45-36	36-15/16	15-5/16	21-5/8
	30	Prefix(†)-30-(*)-HB45-36	39-1/16	16-3/16	22-7/8
	36	Prefix(†)-36-(*)-HB45-36	41-3/16	17-1/16	24-1/8
	42	Prefix(†)-42-(*)-HB45-36	43-5/16	17-15/16	25-3/8
48	6	Prefix(†)-06-(*)-HB45-48	39-1/16	16-3/16	22-7/8
	9	Prefix(†)-09-(*)-HB45-48	40-1/8	16-3/8	23-1/2
	12	Prefix(†)-12-(*)-HB45-48	41-3/16	17-1/16	24-1/8
	18	Prefix(†)-18-(*)-HB45-48	43-5/16	17-15/16	25-3/8
	24	Prefix(†)-24-(*)-HB45-48	45-7/16	18-13/16	26-5/8
	30	Prefix(†)-30-(*)-HB45-48	47-9/16	19-11/16	27-7/8
	36	Prefix(†)-36-(*)-HB45-48	49-11/16	20-9/16	29-1/8
	42	Prefix(†)-42-(*)-HB45-48	51-13/16	21-7/16	30-5/16

30º Horizontal BEND





Nominal		Cat. No.	Dimensions		
Radius	Width		X	Y	Z
12	6	Prefix(†)-06-(*)-HB30-12	11-5/8	3-1/8	6-3/16
	9	Prefix(†)-09-(*)-HB30-12	12-3/8	3-5/16	6-5/8
	12	Prefix(†)-12-(*)-HB30-12	13-1/2	3-1/2	7
	18	Prefix(†)-18-(*)-HB30-12	14-5/8	3-15/16	7-13/16
	24	Prefix(†)-24-(*)-HB30-12	16-1/8	4-5/16	8-5/8
	30	Prefix(†)-30-(*)-HB30-12	17-5/8	4-11/16	9-7/16
	36	Prefix(†)-36-(*)-HB30-12	19-1/8	5-1/8	10-1/4
	42	Prefix(†)-42-(*)-HB30-12	20-5/8	5-1/2	11-1/16
24	6	Prefix(†)-06-(*)-HB30-24	17-5/8	4-11/16	9-7/16
	9	Prefix(†)-09-(*)-HB30-24	18-3/8	4-15/16	9-13/16
	12	Prefix(†)-12-(*)-HB30-24	19-1/8	5-2/16	10-4/16
	18	Prefix(†)-18-(*)-HB30-24	20-5/8	5-8/16	11-1/16
	24	Prefix(†)-24-(*)-HB30-24	22-1/8	5-15/16	11-13/16
	30	Prefix(†)-30-(*)-HB30-24	23-5/8	6-5/16	12-10/16
	36	Prefix(†)-36-(*)-HB30-24	25-1/8	6-12/16	13-7/16
	42	Prefix(†)-42-(*)-HB30-24	26-5/8	7-1/8	14-1/4
36	6	Prefix(†)-06-(*)-HB30-36	23-5/8	6-5/16	12-5/8
	9	Prefix(†)-09-(*)-HB30-36	24-3/8	6-1/2	13-1/16
	12	Prefix(†)-12-(*)-HB30-36	25-1/8	6-3/4	13-7/16
	18	Prefix(†)-18-(*)-HB30-36	26-5/8	7-1/4	14-1/4
	24	Prefix(†)-24-(*)-HB30-36	28-1/8	7-1/2	15-1/16
	30	Prefix(†)-30-(*)-HB30-36	29-5/8	7-15/16	15-7/8
	36	Prefix(†)-36-(*)-HB30-36	31-1/8	8-5/16	16-11/16
	42	Prefix(†)-42-(*)-HB30-36	32-5/8	8-3/4	17-1/2
48	6	Prefix(†)-06-(*)-HB30-48	29-5/8	7-15/16	15-7/8
	9	Prefix(†)-09-(*)-HB30-48	30-3/8	8-1/8	16-1/4
	12	Prefix(†)-12-(*)-HB30-48	31-1/8	8-5/16	16-11/16
	18	Prefix(†)-18-(*)-HB30-48	32-5/8	8-3/4	17-1/2
	24	Prefix(†)-24-(*)-HB30-48	34-1/8	9-1/8	18-1/4
	30	Prefix(†)-30-(*)-HB30-48	35-5/8	9-9/16	19-1/16
	36	Prefix(†)-36-(*)-HB30-48	37-1/8	9-15/16	19-7/8
	42	Prefix(†)-42-(*)-HB30-48	38-5/8	10-5/16	20-11/16

(†) Insert side rail height. (*) Insert bottom style to complete CAT. NO. Includes 1 pair of splice plates with hardware.

Fittings

Horizontal Tees, Crosses

Part Numbering System

SHF 4 24 L HT 12


- SHF — Prefix: SPF, SHF, SSF
- 4 — Side rail height
- 24 — Width
- L — Bottom style
- HT — Fitting type
- 12 — Nominal radius

Selection Guide

Prefix: SPF (Pregalv.), SHF (Hot-Dip) ,SSF (Stainless Steel)
Inside Tray Widths: 6, 9, 12, 18, 24, 30, 36, 42
Nominal Radius: 12, 24, 36, 48
Bottom Styles: L– Ladder, V– Ventilated, S– Solid
Side Rail Heights: 3 in., 4 in., 5 in., 6 in., 7 in.


P/N- SHF624LHT24

Horizontal TEE



Nominal		Cat. No.	Dimensions	
Radius	Width		X	Y
12	6	Prefix(†)-06-(*)-HT12	15	30
	9	Prefix(†)-09-(*)-HT12	16-1/2	33
	12	Prefix(†)-12-(*)-HT12	18	36
	18	Prefix(†)-18-(*)-HT12	21	42
	24	Prefix(†)-24-(*)-HT12	24	48
	30	Prefix(†)-30-(*)-HT12	27	54
	36	Prefix(†)-36-(*)-HT12	30	60
	42	Prefix(†)-42-(*)-HT12	33	66
24	6	Prefix(†)-06-(*)-HT24	27	54
	9	Prefix(†)-09-(*)-HT24	28-1/2	57
	12	Prefix(†)-12-(*)-HT24	30	60
	18	Prefix(†)-18-(*)-HT24	33	66
	24	Prefix(†)-24-(*)-HT24	36	72
	30	Prefix(†)-30-(*)-HT24	39	78
	36	Prefix(†)-36-(*)-HT24	42	84
	42	Prefix(†)-42-(*)-HT24	45	90
36	6	Prefix(†)-06-(*)-HT36	39	78
	9	Prefix(†)-09-(*)-HT36	40-1/2	81
	12	Prefix(†)-12-(*)-HT36	42	84
	18	Prefix(†)-18-(*)-HT36	45	90
	24	Prefix(†)-24-(*)-HT36	48	96
	30	Prefix(†)-30-(*)-HT36	51	102
	36	Prefix(†)-36-(*)-HT36	54	108
	42	Prefix(†)-42-(*)-HT36	57	114
48	6	Prefix(†)-06-(*)-HT48	51	102
	9	Prefix(†)-09-(*)-HT48	52-1/2	105
	12	Prefix(†)-12-(*)-HT48	54	108
	18	Prefix(†)-18-(*)-HT48	57	114
	24	Prefix(†)-24-(*)-HT48	60	120
	30	Prefix(†)-30-(*)-HT48	63	126
	36	Prefix(†)-36-(*)-HT48	66	132
	42	Prefix(†)-42-(*)-HT48	69	138

Horizontal CROSS



Nominal		Cat. No.	Dimensions	
Radius	Width		X	Y
12	6	Prefix(†)-06-(*)-HX12	15	30
	9	Prefix(†)-09-(*)-HX12	16-1/2	33
	12	Prefix(†)-12-(*)-HX12	18	36
	18	Prefix(†)-18-(*)-HX12	21	42
	24	Prefix(†)-24-(*)-HX12	24	48
	30	Prefix(†)-30-(*)-HX12	27	54
	36	Prefix(†)-36-(*)-HX12	30	60
	42	Prefix(†)-42-(*)-HX12	33	66
24	6	Prefix(†)-06-(*)-HX24	27	54
	9	Prefix(†)-09-(*)-HX24	28-1/2	57
	12	Prefix(†)-12-(*)-HX24	30	60
	18	Prefix(†)-18-(*)-HX24	33	66
	24	Prefix(†)-24-(*)-HX24	36	72
	30	Prefix(†)-30-(*)-HX24	39	78
	36	Prefix(†)-36-(*)-HX24	42	84
	42	Prefix(†)-42-(*)-HX24	45	90
36	6	Prefix(†)-06-(*)-HX36	39	78
	9	Prefix(†)-09-(*)-HX36	40-1/2	81
	12	Prefix(†)-12-(*)-HX36	42	84
	18	Prefix(†)-18-(*)-HX36	45	90
	24	Prefix(†)-24-(*)-HX36	48	96
	30¥	Prefix(†)-30-(*)-HX36	51	102
	36¥	Prefix(†)-36-(*)-HX36	54	108
	42¥	Prefix(†)-42-(*)-HX36	57	114
48¥	6	Prefix(†)-06-(*)-HX48	51	102
	9	Prefix(†)-09-(*)-HX48	52-1/2	105
	12	Prefix(†)-12-(*)-HX48	54	108
	18	Prefix(†)-18-(*)-HX48	57	114
	24	Prefix(†)-24-(*)-HX48	60	120
	30	Prefix(†)-30-(*)-HX48	63	126
	36	Prefix(†)-36-(*)-HX48	66	132
	42	Prefix(†)-42-(*)-HX48	69	138

(†) Insert side rail height. (*) Insert bottom style to complete CAT. NO. Tees include 2 pairs / Crosses include 3 pairs of splice plates with hardware.
¥ Shipped with SPW-3/8HXHWK hardware kit.

Splice Plates

Splice Plate




Packaged in pairs with zinc plated hardware. Kit contents
4 bolts, 4 nuts, 4 washers
3/8 in. diameter.

Provided as standard with each straight and/or fitting.

Cat. No.	Material Prefix	Side Rail Height
(Prefix)-3-SSP (Prefix)-4-SSP (Prefix)-5-SSP (Prefix)-6-SSP (Prefix)-7-SSP	SPW SHW SSW	4 5 6 7

P/N- SHW6SSP

Expansion Splice Plate



Allows for a 1 in. expansion or contraction of tray system.

Packaged in pairs with hardware. Kit contents
8 bolts, 8 stop nuts, 4 serrated flange nuts 3/8 in. diameter.

Cat. No.	Material Prefix	Side Rail Height
(Prefix)-3-ESP (Prefix)-4-ESP (Prefix)-5-ESP (Prefix)-6-ESP (Prefix)-7-ESP	SPW SHW SSW	3 4 5 6 7

Transition Splice Plate




Cat. No.	Material	Description	Side Rail Height
XNM-XP400-(*)-SS6	Polyester/Fiberglass	Designed to make the transition. from aluminum to steel cable tray Works for all 6 in. side rails.	6

Each pair of plate:
8 x carriage bolt (3/8 x 1 in.) SS316
8 x 3/8 in. serrated flange nut SS316

Step Down Splice Plate






Connects side rails of different heights. Hardware included.
Kit contents 8 bolts, 8 nuts, 8 washers 3/8 in. diameter.

Cat. No.	Material Prefix	Side Rail Width (in.)
(Prefix)-(*)-(**)-SDS	SPW SHW SSW	4 5 6 7

(*) Insert side rail height 1.
(**) Insert side rail height 2.
Note: Side rail height 1 is greater than side rail height 2.

Horizontal Adjustable Plate





Furnished in pairs with hardware.

Cat. No.	Material Prefix	Side Rail Height (in.)	Tray Width (in.)
(Prefix)-(*)06HBP (Prefix)-(*)09HBP (Prefix)-(*)12HBP (Prefix)-(*)18HBP (Prefix)-(*)24HBP (Prefix)-(*)30HBP (Prefix)-(*)36HBP (Prefix)-(*)42HBP	SPW SHW SSW	3 4 5 6 7	06 09 12 18 24 30 36 42

(*) Insert side rail height.

Clamps and Hardware


Self-drilling – tapping screw



Cat. No.	Material	Description
SPW-10-SCR	Zinc plated steel	Self-drilling – tapping screw
SSW-10-SCR	Stainless steel	Self-drilling – tapping screw

Hold Down Clamp





Cat. No.	Material Prefix	Side Rail Height (in.)
(Prefix)-3-HDC	SPW SHW SSW	3
(Prefix)-4-HDC		4
(Prefix)-5-HDC		5
(Prefix)-6-HDC		6
(Prefix)-7-HDC		7

Note: Hardware included. Kit contains 1 bolt and 1 channel nut.

PN- SPW6HDC


Hold Down Clamp



Cat. No.	Type	Material	Design Load
SPWHDCS	Single	Pregalvanized	800 lb./pair
SHWHDCS	Single	Hot-dipped galvanized	
SSWHDCS	Single	Stainless steel 316	
SPWHDCD	Double	Pregalvanized	1500 lb./pair
SHWHDCD	Double	Hot-dipped galvanized	
SSWHDCD	Double	Stainless steel 316	

Conduit Clamp





Cat. No.	Type	Material
PU100CC	1	Pregalvanized
PU125CC	1-1/4	
PU150CC	1-1/2	
PU200CC	2	
PU250CC	2-1/2	
PU300CC	3	
PU400CC	4	

Arctic Electrical Nunavut Ltd

PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 12 17 Dry Type Transformers up to 600V Primary

Date: June 11, 2019

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 11, 2019

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-16R2
PO-Guillevin-P19-078

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [x] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 12 17 Distribution Transformer

Provide a shop drawing for the 45kVA transformer

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-016-R2

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2019-06-12
BY Jamie McLeish

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

Hammond Power Solutions Inc.

HPS Sentinel ® K

Energy Efficient Distribution Transformer

Transformateur de Distribution à Bon Rendement Énergétique

Hammond Power Solutions
Guelph, ONT
Compton, CA
Baraboo, WI
Monterrey, MX

Part No. SK3A0112PB4KB


® LR 3902


DRY TYPE TRANSFORMER
77U5
E112313
LISTED

ALSO VERIFIED IN ACCORDANCE TO ENERGY STANDARD C802.2–12

Cust. Ref. / Ref. du Client		Serial No. / No. de Serie	
Phase	3	HV/HT	600V 108.3A
Type	K	BIL	10 kV
Cooling / Refroidissement	ANN	Term / Bornes	H1 H2 H3
kVA	112.5	LV/BT	208Y/120V 312A
Temp. Rise / Echauffement	80 °C	BIL	10 kV
Temp Class / Classe Temp	220 °C	Term / Bornes	X0 X1 X2 X3
Winding / Enroulement	CU	Energy Regulations	DOE 10 CFR PART 431:2016
Frequency / Frequence Hz	60	Reglements de Energetique	CEE ACT SOR/2018–201
Impedance % @ 100 °C	3.4	Suitable for non–sinusoidal current load with K–factor not to exceed / Convient à des courants non–sinusoïdaux avec facteur K n'excédant pas	4
Encl Type / Type De Coffrage	3R		
Wt LBS / Poids en lbs	950		

VOLTS	CURRENT / COURANT	% RATED VOLTAGE / % TENSION NOMINALE	CONNECTION EACH PHASE / CONNEXION PAR PHASE
630	103.1	105	1
615	105.6	102.5	2
600	108.3	100	3
585	111	97.5	4
570	114	95	5
555	117	92.5	6
540	120	90	7





SPACINGS BETWEEN ANY VENTILATED ENCLOSURE PANEL AND ANY ADJACENT WALL SHALL BE A MINIMUM OF 5 INCHES EXCEPT WHEN WALL MOUNTED USING APPROVED WALL MOUNTING KIT
ELECTROSTATIC SHIELD

SEISMIC QUALIFICATIONS, OSP–0136–10
AS FLOOR MOUNT ONLY
IBC 2012/ASCE 7–10
SDS<=2.0g Z/h=1 Ip=1.5

d0001887hb

TITLE: 3PH DISTRIBUTION TRANSFORMER
NAMEPLATE INFORMATION

NO.	DATE	BY	REVISION


SCALE: NTS
DATE: 19/05/24
DES.: PPICASSI

SHEET 1 OF 3


EDB SK3A0112PB4KB

0.0 ppicassinos 2019/05/24 09:34

FRONT VIEW



SIDE VIEW



All Dimensions in inches

ENCLOSURE COLOR :ANSI 61 GREY – OUTDOOR

HV TERMINAL DETAIL

MECHANICAL TYPE LUGS INCLUDED
SUITABLE FOR 250MCM–6 CU/AL
CONDUCTORS
1 CONDUCTOR PER PHASE

LV TERMINAL DETAIL

MECHANICAL TYPE LUGS INCLUDED
SUITABLE FOR 350MCM–6 CU/AL
CONDUCTORS
2 CONDUCTORS PER PHASE

CUSTOMER NOTES:

– HV TERMINATED AT TOP FRONT
– LV TERMINATED AT BOTTOM FRONT
200% RATED NEUTRAL X0 HAS QTY 2 LUGS

Hammond Power Solutions Inc.

TITLE: 3PH DISTRIBUTION TRANSFORMER

NO.	DATE	BY	REVISION


DES: PPICASSI
DATE: 19/05/24
SCALE: NTS

SHEET 2 OF 3

EDB SK3A0112PB4KB

0.0 ppicassinos 2019/05/24 09:34

ENCLOSURE BOTTOM VIEW



NOTE:
WHEN BOTTOM CABLE ENTRY IS OPTED, THE SPACE USED FOR CONDUITS IN THE FRONT OF THE TRANSFORMER SHOULD NOT OBSTRUCT MORE THAN 50% OF THE FRONT AIR INTAKE AREA DEFINED BETWEEN THE BOTTOM PLATE AND THE SUPPORTING LEGS.
SEE MANUAL FOR ADDITIONAL INFORMATION

Hammond Power Solutions Inc.

TITLE: 3PH DISTRIBUTION TRANSFORMER
ENCLOSURE BOTTOM VIEW

NO.	DATE	BY	REVISION

DES: PPICASSI
DATE: 19/05/24
SCALE: NTS

SHEET 3 OF 3

EDB SK3A0112PB4KB

0.0 ppicassinos 2019/05/24 09:34

ACCESSORIES (for transformers listed in sections 3, 4, 7, 10 and 11)

ANTI-VIBRATION PAD AND VIBRATION ISOLATOR KITS

All standard transformers come with installed internal vibration absorbing pads to minimize noise during operation. Optional external "anti-vibration" pad and "vibration isolator" (for higher noise dampening) kits can be used to reduce operating noise even further. All are resistant to industrial contaminants like oils, acids and alkalies.

ANTI-VIBRATION PAD KITS


Part No.	Case Style	Description
P1	NH Series	Set of four (4) rubber anti-vibration pads which replace the standard steel enclosure washers.
P2	NJ Series	



All Anti-Vibration Pad kits and Vibration Isolator kits contain a set of four (4) pads or isolators. Therefore only one kit is required per transformer.

VIBRATION ISOLATOR KITS

Part No.	Transformer Weight (Lb)	Description
NMP1	Up to 340 lbs	Set of four (4) molded neoprene and steel plate assemblies that virtually eliminate vibration noise between the transformer and the mounting surface.
NMP2	341 to 680 lbs	
NMP3	681 to 1040 lbs	
NMP4	1041 to 1740 lbs	
NMP5	1741 to 2330 lbs	
NMP6	2331 to 3450 lbs	
NMP7	3451 to 4690 lbs	



ACCESSORIES (for transformers listed in sections 8 and 10)


NQTW1 and NQTW2 Wall Mounting Kits

The **NQTW1 and NQTW2** wall mounting kits are specifically designed for HPS commercial or industrial encapsulated (potted) distribution transformer units up to a maximum of 45kVA or 800 pounds (363 kg). These mounting kits are designed for encapsulated (potted) units only, no drip plate is included/required. Please contact HPS customer service if you have any questions.

Note: Always measure and secure mounting brackets to the wall surface first, then lift the transformer (using appropriate lifting equipment) onto the brackets and attach using minimum Grade 8 hardware.

Enclosure Case Style	Mounting Type	Wall Mounting Kit Part Number
NQ0-NQ8	Wall	**Included**
NQS10	Wall or Floor	**NQTW2**
NQT3-NQT6	Wall	**Included**
NQT7-NQT8	Wall or Floor	**NQTW1**
NQT9A	Floor	**N/A**
NQT9*	Wall or Floor	**NQTW2**

*Applies to HPS Fortress line only.



© Hammond Power Solutions Inc.
Data subject to change without notice.

Hammond Power Solutions Inc.

HPS Sentinel ® G

Energy Efficient Distribution Transformer
Transformateur de Distribution à Bon Rendement Énergétique

Hammond Power Solutions
Guelph, ONT / Compton, CA
Baraboo, WI / Monterrey, MX


Part No. SG3A0045PK0CB

LR 3902
DRY TYPE TRANSFORMER 77US E112313
LISTED
ALSO VERIFIED IN ACCORDANCE TO ENERGY STANDARD C802.2-12

Cust. Ref. / Ref. du Client		Serial No. / No. de Serie	
Phase	3	HV/HT	600V
Type	K	BIL	10
Cooling / Refroidissement	ANN	Term / Bornes	H1 H2 H3
kVA	45	LV/BT	480Y/277V
Temp. Rise / Echauffement	80 °C	BIL	10
Temp Class / Classe Temp	220 °C	Term / Bornes	X0 X1 X2 X3
Winding / Enroulement	CU	Energy Regulations	DOE 10 CFR PART 431:2016
Frequency / Frequence Hz	60	Reglements de Energetique	CEE ACT SOR/2016-311 AMENDMENT 14
Impedance % @ 100 °C	1.8		
Encl Type / Type De Coffrage	3R		
Wt LBS / Poids en lbs	650		

VOLTS	CURRENT COURANT	% RATED VOLTAGE % TENSION NOMINALE	CONNECTION EACH PHASE CONNEXION PAR PHASE
630	41.2	105	1
615	42.2	102.5	2
600	43.3	100	3
585	44.4	97.5	4
570	45.6	95	5
555	46.8	92.5	6
540	48.1	90	7

SPACINGS BETWEEN ANY VENTILATED ENCLOSURE PANEL AND ANY ADJACENT WALL SHALL BE A MINIMUM OF 5 INCHES EXCEPT WHEN WALL MOUNTED USING APPROVED WALL MOUNTING KIT



SEISMIC QUALIFICATIONS, OSP-0136-10
AS FLOOR MOUNT ONLY
IBC 2012/ASCE 7-10
SDS<=2.0g Z/h=1 Ip=1.5

d0001886b

NO.	DATE	BY	REVISION
1	17/04/03	JW	ADDED ENCL BOTTOM DRAWING

TITLE: 3PH DISTRIBUTION TRANSFORMER
NAMEPLATE INFORMATION


SCALE: NTS
DATE: 15/11/09
DES.: JWEN

SHEET 1 OF 3


EDB SG3A0045PK0CB

1.1 jwen 2017/11/09 10:03

FRONT VIEW



SIDE VIEW



All Dimensions in inches

ENCLOSURE COLOR :ANSI 61 GREY – OUTDOOR

H.V.1. TERMINAL DETAIL

MECHANICAL TYPE LUGS INCLUDED
SUITABLE FOR #2/0–14 CU/AL
CONDUCTORS
1 CONDUCTOR PER PHASE

L.V.1. TERMINAL DETAIL

MECHANICAL TYPE LUGS INCLUDED
SUITABLE FOR #2/0–14 CU/AL
CONDUCTORS
1 CONDUCTOR PER PHASE

CUSTOMER NOTES:
- HV1 TERMINATED AT TOP FRONT
- LV1 TERMINATED AT BOTTOM FRONT

Hammond Power Solutions Inc.

TITLE: 3PH DISTRIBUTION TRANSFORMER

NO.	DATE	BY	REVISION
1	17/04/03	JW	ADDED ENCL BOTTOM DRAWING


DES: JWEN
DATE: 15/11/09
SCALE: NTS

SHEET 2 OF 3

EDB SC3A0045PKOCB

1.1 jwen 2017/11/09 10:03

ENCLOSURE BOTTOM VIEW



NOTE:
WHEN BOTTOM CABLE ENTRY IS OPTED, THE SPACE USED FOR CONDUITS IN THE FRONT OF THE TRANSFORMER SHOULD NOT OBSTRUCT MORE THAN 50% OF THE FRONT AIR INTAKE AREA DEFINED BETWEEN THE BOTTOM PLATE AND THE SUPPORTING LEGS.
SEE MANUAL FOR ADDITIONAL INFORMATION

Hammond Power Solutions Inc.

TITLE: 3PH DISTRIBUTION TRANSFORMER
ENCLOSURE BOTTOM VIEW

NO.	DATE	BY	REVISION	
1	17/04/03	JW	ADDED ENCL BOTTOM DRAWING	DES: JWEN
				DATE: 15/11/09
				SCALE: NTS

SHEET 3 OF 3

EDB SC3A0045PK0CB

1.1 jwen 2017/11/09 10:03

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 24 17 Panelboard Breaker Type

Date: Dec 06, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Déc 06, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-12R1 - SU-ELE-012R1
PO-Nedco

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [X] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [X] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 24 17 Panelboards-Panel 4A CCN-014

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-012R1

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-12-06
BY Konrad Goluch

Bus to be copper. Min S.C Rating to be 14k A.I.C. Fully rated

New Drawing showing Copper is added

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

Product data sheet
Characteristics

NF442L2C
NF Pnlbrd Interior 250A, 3 PH, 4 Wire, 42 CCT, Mn Lug, Cu



Main

Load center type	Main lugs
Circuit breaker type	EDB/EDG/EDJ
Material	Copper

Complementary

Number of spaces	42
Enclosure nominal height	56 in 44 in
Enclosure nominal width	20 in
Enclosure nominal depth	5.75 inFor NEMA 1 enclosure 6.5 inFor NEMA 3R/5/12 enclosure
Line Rated Current	250 A
Wiring configuration	4-wire
Phase	3 phases
System Voltage	480Y/277 V AC

Environment

Standards	CSA C22.2 UL 67


Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 1419 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity
REACh	Reference not containing SVHC above the threshold Reference not containing SVHC above the threshold
Product environmental profile	Available

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Product end of life instructions	Need no specific recycling operations


REV	DESCRIPTION	BY	DATE	–	----	--	--/--/--
–	----	--	--/--/--	–	----	--	--/--/--



KNOCKOUTS				
SYMBOL	CONDUIT SIZE		KNOCKOUT DIA	
	IN	MM	IN	MM
A	.50	13	.88	22
B	.75	19	1.12	28
D	1.25	32	1.75	44
E	1.50	38	2.00	51
F	2.00	51	2.50	64
G	2.50	64	3.00	76
H	3.00	76	3.62	92
I	3.50	89	4.12	105

Enclosure


DUAL DIMENSIONS: INCHES
MILLIMETERS



REFERENCE CATALOG NO	L		S		M	
	IN	MM	IN	MM	IN	MM
MH26	26.00	660	21.00	533	20.00	508
MH32	32.00	813	27.00	686	26.00	660
MH38	38.00	965	33.00	838	32.00	813
MH44	44.00	1118	39.00	991	38.00	965
MH50	50.00	1270	45.00	1143	44.00	1118
MH56	56.00	1422	51.00	1295	50.00	1270
MH62	62.00	1575	57.00	1448	56.00	1422
MH68	68.00	1727	63.00	1600	62.00	1575
MH74	74.00	1880	69.00	1753	68.00	1727
MH80	80.00	2032	75.00	1905	74.00	1880
MH86	86.00	2184	81.00	2057	80.00	2032
MH92	92.00	2337	87.00	2210	86.00	2184

JOB NAME:	---	EQUIPMENT DESIGNATION:	---
JOB LOCATION:	---	EQUIPMENT TYPE:	NEMA 1 BOXES
DRAWN BY:	---	DRAWING TYPE:	---
ENGR:	---		
DATE:	JULY 2018		
DRAWING STATUS:	---	DWG# PBA600	PG 1 OF 1 REV –

Surface Trim



CATALOG NUMBER	A		B		C	
	IN	MM	IN	MM	IN	MM
NC26S	26.12	663	17.70	436	6.16	156
NC32S	32.12	816	23.70	602	9.16	233
NC38S	38.12	968	29.70	754	12.16	309
NC44S	44.12	1121	35.70	907	15.16	385
NC50S	50.12	1273	41.70	1059	18.16	461
NC56S	56.12	1425	47.70	1212	21.16	537
NC62S	62.12	1578	53.70	1364	24.16	614
NC68S	68.12	1730	59.70	1516	27.16	690
NC74S	74.12	1883	65.70	1669	30.16	766
NC80S	80.12	2035	71.70	1821	33.16	842
NC26F	27.52	699	17.70	436	6.16	156
NC32F	33.52	851	23.70	602	9.16	233
NC38F	39.52	1004	29.70	754	12.16	309
NC44F	45.52	1156	35.70	907	15.16	385
NC50F	51.52	1309	41.70	1059	18.16	461
NC56F	57.52	1461	47.70	1212	21.16	537
NC62F	63.52	1613	53.70	1364	24.16	614
NC68F	69.52	1766	59.70	1516	27.16	690
NC74F	75.52	1918	65.70	1669	30.16	766
NC80F	81.52	2071	71.70	1821	33.16	842
NC86S	86.12	2187	77.70	1974	36.16	918
NC86F	87.52	2071	77.70	1974	36.16	918
NC35S	35.12	892	26.70	678	10.66	271
NC35F	36.52	928	26.70	678	10.66	271
NC41S	41.12	1044	32.70	831	13.66	347
NC41F	42.52	1080	32.70	831	13.66	347
NC92S	92.12	2340	83.70	2126	39.16	995

DUAL DIMENSIONS: INCHES
MILLIMETERS

PANELBOARD COVER
TRIM TYPE 1
SURFACE/FLUSH

SQUARE D™
by Schneider Electric

DWG# NO. PWFDS-SYTI-0164

Product data sheet
Characteristics

EDB14015
E-Frame Brkr 15A, 1P, 277V, 18/25kA, Bolt-on Mnt



Main

Range of product	125 A Frame EDB-EGB-EJB
Product or component type	Miniature circuit-breaker
Device short name	EDB
Module type	E-Frame
Trip unit rating	875 A

Complementary

Line Rated Current	15 A
System Voltage	277 V AC
AWG gauge	AWG 14...AWG 6 copper AWG 12...AWG 6 aluminium
Breaking capacity	18 kA 277 V AC 18 kA 240 V AC 25 kA 120 V AC 18 kA 120/240 V AC
Circuit breaker application	HACR rated Switching Duty rated HID rated
Depth	4.05 in
Electrical connection	Lugs aluminium
Height	5.66 in
Holding current	270 A
Local signalling	Trip indicator
Mounting mode	Bolt-on
Number of poles	1
Number of spaces	1
Number of spaces required	1
Product destination	Panelboard NF
Product weight	2 lb(US)

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Protection type	Short-circuit Overload
Width	0.98 in
Trip unit technology	Thermal-magnetic
Breaking capacity code	D

Environment

Product certifications	CULus IEC
Ambient air temperature for operation	104 °F (40 °C)

Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 1423 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity
REACh	Reference not containing SVHC above the threshold Reference not containing SVHC above the threshold
Product environmental profile	Available
Product end of life instructions	Need no specific recycling operations

Product data sheet
Characteristics

EDB34030
E-Frame Brkr 30A, 3P, 480Y/277V, 18/25kA, Bolt-on Mnt



Main

Range of product	125 A Frame EDB-EGB-EJB
Product or component type	Miniature circuit-breaker
Device short name	EDB
Module type	E-Frame
Trip unit rating	875 A

Complementary

Line Rated Current	30 A
System Voltage	480Y/277 V AC
AWG gauge	AWG 14...AWG 6 copper AWG 12...AWG 6 aluminium
Breaking capacity	18 kA 277 V AC 18 kA 480Y/277 V AC 25 kA 120 V AC 25 kA 120/240 V AC 25 kA 240 V AC
Circuit breaker application	HACR rated HID rated
Depth	4.05 in
Electrical connection	Lugs aluminium
Height	5.66 in
Holding current	270 A
Local signalling	Trip indicator
Mounting mode	Bolt-on
Number of poles	3
Number of spaces	3
Number of spaces required	3
Product destination	Panelboard NF
Product weight	4 lb(US)

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Protection type	Short-circuit Overload
Width	2.94 in
Trip unit technology	Thermal-magnetic
Breaking capacity code	D

Environment

Product certifications	CULus
Ambient air temperature for operation	104 °F (40 °C)

Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 1423 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity
REACh	Reference not containing SVHC above the threshold Reference not containing SVHC above the threshold
Product environmental profile	Available
Product end of life instructions	Need no specific recycling operations

Date: June 11, 2019

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 11, 2019

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-16R2
PO-Guillevin-P19-078

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [x] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 12 17 Distribution Transformer

Provide a shop drawing for the 45kVA transformer

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-016-R2

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2019-06-12
BY Jamie McLeish

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

Hammond Power Solutions Inc.

HPS Sentinel ® K

Energy Efficient Distribution Transformer

Transformateur de Distribution à Bon Rendement Énergétique

Hammond Power Solutions
Guelph, ONT
Compton, CA
Baraboo, WI
Monterrey, MX

Part No. SK3A0112PB4KB


® LR 3902


DRY TYPE TRANSFORMER
77U5
E112313
LISTED

ALSO VERIFIED IN ACCORDANCE TO ENERGY STANDARD C802.2–12

Cust. Ref. / Ref. du Client		Serial No. / No. de Serie	
Phase	3	HV/HT	600V 108.3A
Type	K	BIL	10 kV
Cooling / Refroidissement	ANN	Term / Bornes	H1 H2 H3
kVA	112.5	LV/BT	208Y/120V 312A
Temp. Rise / Echauffement	80 °C	BIL	10 kV
Temp Class / Classe Temp	220 °C	Term / Bornes	X0 X1 X2 X3
Winding / Enroulement	CU	Energy Regulations	DOE 10 CFR PART 431:2016
Frequency / Frequence Hz	60	Reglements de Energetique	CEE ACT SOR/2018–201
Impedance % @ 100 °C	3.4	Suitable for non–sinusoidal current load with K–factor not to exceed / Convient à des courants non–sinusoïdaux avec facteur K n'excédant pas	4
Encl Type / Type De Coffrage	3R		
Wt LBS / Poids en lbs	950		

VOLTS	CURRENT / COURANT	% RATED VOLTAGE / % TENSION NOMINALE	CONNECTION EACH PHASE / CONNEXION PAR PHASE
630	103.1	105	1
615	105.6	102.5	2
600	108.3	100	3
585	111	97.5	4
570	114	95	5
555	117	92.5	6
540	120	90	7





SPACINGS BETWEEN ANY VENTILATED ENCLOSURE PANEL AND ANY ADJACENT WALL SHALL BE A MINIMUM OF 5 INCHES EXCEPT WHEN WALL MOUNTED USING APPROVED WALL MOUNTING KIT
ELECTROSTATIC SHIELD

SEISMIC QUALIFICATIONS, OSP–0136–10
AS FLOOR MOUNT ONLY
IBC 2012/ASCE 7–10
SDS<=2.0g Z/h=1 Ip=1.5

d0001887hb

TITLE: 3PH DISTRIBUTION TRANSFORMER
NAMEPLATE INFORMATION

NO.	DATE	BY	REVISION


SCALE: NTS
DATE: 19/05/24
DES.: PPICASSI

SHEET 1 OF 3


EDB SK3A0112PB4KB

0.0 ppicassinos 2019/05/24 09:34

FRONT VIEW



SIDE VIEW



All Dimensions in inches

ENCLOSURE COLOR :ANSI 61 GREY – OUTDOOR

HV TERMINAL DETAIL

MECHANICAL TYPE LUGS INCLUDED
SUITABLE FOR 250MCM–6 CU/AL
CONDUCTORS
1 CONDUCTOR PER PHASE

LV TERMINAL DETAIL

MECHANICAL TYPE LUGS INCLUDED
SUITABLE FOR 350MCM–6 CU/AL
CONDUCTORS
2 CONDUCTORS PER PHASE

CUSTOMER NOTES:

– HV TERMINATED AT TOP FRONT
– LV TERMINATED AT BOTTOM FRONT
200% RATED NEUTRAL X0 HAS QTY 2 LUGS

Hammond Power Solutions Inc.

TITLE: 3PH DISTRIBUTION TRANSFORMER

NO.	DATE	BY	REVISION


DES: PPICASSI
DATE: 19/05/24
SCALE: NTS

SHEET 2 OF 3

EDB SK3A0112PB4KB

0.0 ppicassinos 2019/05/24 09:34

ENCLOSURE BOTTOM VIEW



NOTE:
WHEN BOTTOM CABLE ENTRY IS OPTED, THE SPACE USED FOR CONDUITS IN THE FRONT OF THE TRANSFORMER SHOULD NOT OBSTRUCT MORE THAN 50% OF THE FRONT AIR INTAKE AREA DEFINED BETWEEN THE BOTTOM PLATE AND THE SUPPORTING LEGS.
SEE MANUAL FOR ADDITIONAL INFORMATION

Hammond Power Solutions Inc.

TITLE: 3PH DISTRIBUTION TRANSFORMER
ENCLOSURE BOTTOM VIEW

NO.	DATE	BY	REVISION

DES: PPICASSI
DATE: 19/05/24
SCALE: NTS

SHEET 3 OF 3

EDB SK3A0112PB4KB

0.0 ppicassinos 2019/05/24 09:34

ACCESSORIES (for transformers listed in sections 3, 4, 7, 10 and 11)

ANTI-VIBRATION PAD AND VIBRATION ISOLATOR KITS

All standard transformers come with installed internal vibration absorbing pads to minimize noise during operation. Optional external "anti-vibration" pad and "vibration isolator" (for higher noise dampening) kits can be used to reduce operating noise even further. All are resistant to industrial contaminants like oils, acids and alkalies.

ANTI-VIBRATION PAD KITS


Part No.	Case Style	Description
P1	NH Series	Set of four (4) rubber anti-vibration pads which replace the standard steel enclosure washers.
P2	NJ Series	



All Anti-Vibration Pad kits and Vibration Isolator kits contain a set of four (4) pads or isolators. Therefore only one kit is required per transformer.

VIBRATION ISOLATOR KITS

Part No.	Transformer Weight (Lb)	Description
NMP1	Up to 340 lbs	Set of four (4) molded neoprene and steel plate assemblies that virtually eliminate vibration noise between the transformer and the mounting surface.
NMP2	341 to 680 lbs	
NMP3	681 to 1040 lbs	
NMP4	1041 to 1740 lbs	
NMP5	1741 to 2330 lbs	
NMP6	2331 to 3450 lbs	
NMP7	3451 to 4690 lbs	



ACCESSORIES (for transformers listed in sections 8 and 10)


NQTW1 and NQTW2 Wall Mounting Kits

The **NQTW1 and NQTW2** wall mounting kits are specifically designed for HPS commercial or industrial encapsulated (potted) distribution transformer units up to a maximum of 45kVA or 800 pounds (363 kg). These mounting kits are designed for encapsulated (potted) units only, no drip plate is included/required. Please contact HPS customer service if you have any questions.

Note: Always measure and secure mounting brackets to the wall surface first, then lift the transformer (using appropriate lifting equipment) onto the brackets and attach using minimum Grade 8 hardware.

Enclosure Case Style	Mounting Type	Wall Mounting Kit Part Number
NQ0-NQ8	Wall	**Included**
NQS10	Wall or Floor	**NQTW2**
NQT3-NQT6	Wall	**Included**
NQT7-NQT8	Wall or Floor	**NQTW1**
NQT9A	Floor	**N/A**
NQT9*	Wall or Floor	**NQTW2**

*Applies to HPS Fortress line only.



© Hammond Power Solutions Inc.
Data subject to change without notice.

Hammond Power Solutions Inc.

HPS Sentinel ® G

Energy Efficient Distribution Transformer
Transformateur de Distribution à Bon Rendement Énergétique

Hammond Power Solutions
Guelph, ONT / Compton, CA
Baraboo, WI / Monterrey, MX


Part No. SG3A0045PK0CB

LR 3902
DRY TYPE TRANSFORMER 77US E112313
LISTED
ALSO VERIFIED IN ACCORDANCE TO ENERGY STANDARD C802.2-12

Cust. Ref. / Ref. du Client		Serial No. / No. de Serie	
Phase	3	HV/HT	600V
Type	K	BIL	10
Cooling / Refroidissement	ANN	Term / Bornes	H1 H2 H3
kVA	45	LV/BT	480Y/277V
Temp. Rise / Echauffement	80 °C	BIL	10
Temp Class / Classe Temp	220 °C	Term / Bornes	X0 X1 X2 X3
Winding / Enroulement	CU	Energy Regulations	DOE 10 CFR PART 431:2016
Frequency / Frequence Hz	60	Reglements de Energetique	CEE ACT SOR/2016-311 AMENDMENT 14
Impedance % @ 100 °C	1.8		
Encl Type / Type De Coffrage	3R		
Wt LBS / Poids en lbs	650		

VOLTS	CURRENT COURANT	% RATED VOLTAGE % TENSION NOMINALE	CONNECTION EACH PHASE CONNEXION PAR PHASE
630	41.2	105	1
615	42.2	102.5	2
600	43.3	100	3
585	44.4	97.5	4
570	45.6	95	5
555	46.8	92.5	6
540	48.1	90	7

SPACINGS BETWEEN ANY VENTILATED ENCLOSURE PANEL AND ANY ADJACENT WALL SHALL BE A MINIMUM OF 5 INCHES EXCEPT WHEN WALL MOUNTED USING APPROVED WALL MOUNTING KIT



SEISMIC QUALIFICATIONS, OSP-0136-10
AS FLOOR MOUNT ONLY
IBC 2012/ASCE 7-10
SDS<=2.0g Z/h=1 Ip=1.5

d0001886b

NO.	DATE	BY	REVISION
1	17/04/03	JW	ADDED ENCL BOTTOM DRAWING

TITLE: 3PH DISTRIBUTION TRANSFORMER
NAMEPLATE INFORMATION


SCALE: NTS
DATE: 15/11/09
DES.: JWEN

SHEET 1 OF 3


EDB SG3A0045PK0CB

1.1 jwen 2017/11/09 10:03

FRONT VIEW



SIDE VIEW



All Dimensions in inches

ENCLOSURE COLOR :ANSI 61 GREY – OUTDOOR

H.V.1. TERMINAL DETAIL

MECHANICAL TYPE LUGS INCLUDED
SUITABLE FOR #2/0–14 CU/AL
CONDUCTORS
1 CONDUCTOR PER PHASE

L.V.1. TERMINAL DETAIL

MECHANICAL TYPE LUGS INCLUDED
SUITABLE FOR #2/0–14 CU/AL
CONDUCTORS
1 CONDUCTOR PER PHASE

CUSTOMER NOTES:
- HV1 TERMINATED AT TOP FRONT
- LV1 TERMINATED AT BOTTOM FRONT

Hammond Power Solutions Inc.

TITLE: 3PH DISTRIBUTION TRANSFORMER

NO.	DATE	BY	REVISION
1	17/04/03	JW	ADDED ENCL BOTTOM DRAWING


DES: JWEN
DATE: 15/11/09
SCALE: NTS

SHEET 2 OF 3

EDB SC3A0045PKOCB

1.1 jwen 2017/11/09 10:03

ENCLOSURE BOTTOM VIEW



NOTE:
WHEN BOTTOM CABLE ENTRY IS OPTED, THE SPACE USED FOR CONDUITS IN THE FRONT OF THE TRANSFORMER SHOULD NOT OBSTRUCT MORE THAN 50% OF THE FRONT AIR INTAKE AREA DEFINED BETWEEN THE BOTTOM PLATE AND THE SUPPORTING LEGS.
SEE MANUAL FOR ADDITIONAL INFORMATION

Hammond Power Solutions Inc.

TITLE: 3PH DISTRIBUTION TRANSFORMER
ENCLOSURE BOTTOM VIEW

NO.	DATE	BY	REVISION	
1	17/04/03	JW	ADDED ENCL BOTTOM DRAWING	DES: JWEN
				DATE: 15/11/09
				SCALE: NTS

SHEET 3 OF 3

EDB SC3A0045PK0CB

1.1 jwen 2017/11/09 10:03

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 24 19 Motor Control Centres

Date: July 11, 2019

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 11, 2019

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-18R4 SU-ELE18R4
PO-P19-108 Nedco

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [x] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 24 19 Motor Control Centres

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE 018-R4

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other _____

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2019-07-12
BY Jamie McLeish

Note, contractor remains responsible for the shop drawing content and coordination with other disciplines. Stantec's review does not relieve the contractor of their contractual responsibility.

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the contractor.

Do not hesitate to contact me if you have any questions or concerns.

SQUARE D
by Schneider Electric

Job Name:	IQALUIT WWTP MCC UPGRADES	Square D Quotation #:	41428112
Job Location:	SALABERRY–DE–VALLEYFIELD, QC	Quotation Revision #:	
		Sales Contact:	CURTIS DADSWELL
		Sales Contact Location:	817
Purchaser:	23010–NEDCO DIV OF REXEL CANADA	Customer:	ARCTIC ELECTRIC
Purchaser PO #:	(WR2)14265D	Customer PO #:	
User:		Architect:	
User Location:		Cons. Engineer:	
Drawing Status:	APPROVAL		

TABLE OF CONTENTS

SQUARE D FACTORY ORDER NUMBER: 41428112–001


Equipment Designation	Equipment Type	Drawing Type	Drawing Number	Page	Revision Level
MCC – 1	MODEL 6 MCC	ELEVATION	F41428112–001–01	1	C
			F41428112–001–01	2	C
			F41428112–001–01	3	C
		SEISMIC	S41428112–001–01	1	C
		ONE LINE DIAGRAM	O41428112–001–01	1	C
			O41428112–001–01	2	C
		UNIT INFORMATION	I41428112–001–01	1	C
			I41428112–001–01	2	C
			I41428112–001–01	3	C
			I41428112–001–01	4	C
			I41428112–001–01	5	C
		ELEMENTARY	E41428112–001–01	1	C
			E41428112–001–02	1	C
			E41428112–001–03	1	C
			E41428112–001–04	1	C
			E41428112–001–04	2	C
			E41428112–001–05	1	C
			E41428112–001–05	2	C
			E41428112–001–06	1	C
			E41428112–001–06	2	C
			E41428112–001–07	1	C
			E41428112–001–07	2	C
			E41428112–001–08	1	C
			E41428112–001–08	2	C
			E41428112–001–09	1	C
			E41428112–001–09	2	C
			E41428112–001–10	1	C
			E41428112–001–10	2	C
			E41428112–001–11	1	C
			E41428112–001–11	2	C
			E41428112–001–12	1	C
			E41428112–001–13	1	C

TABLE OF CONTENTS

SQUARE D FACTORY ORDER NUMBER: 41428112-001

Equipment Designation	Equipment Type	Drawing Type	Drawing Number	Page	Revision Level
			E41428112-001-13	2	C

REV	DESCRIPTION	BY	DATE								
–	----	--	--/--/--	A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019
				B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--




ANCHOR DETAIL


DUAL DIMENSIONS: INCHES
MILLIMETERS

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	**MCC – 1**
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEVATION
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	**F41428112-001-01** PG 1 OF 3 REV C

REV	DESCRIPTION	BY	DATE								
B	REAPPROVAL	TA	06/21/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--
				A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--



TOP VIEW



DUAL DIMENSIONS: INCHES
MILLIMETERS

FLOOR VIEW

CROSSED AREA REPRESENTS CONDUIT ENTRY AREA. NUMBERS IN BOXES INDICATE VERTICAL CLEARANCE TO NEAREST OBSTRUCTION.

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEVATION
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	F41428112-001-01

REV	DESCRIPTION	BY	DATE								
B	REAPPROVAL	TA	06/21/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--
				A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--

GENERAL NOTES

Class 1 Type B Wiring

PRODUCT DESCRIPTION AND RATINGS

POWER SYSTEM DATA:

600V 3PH 3W 60Hz
SHORT CIRCUIT RATING: 65kA
POWER ENTERS: Main Fusible Switch Top Section 1
CONTROL POWER: 120Vac

BUS SYSTEM DATA:

MAIN HORIZONTAL BUS: 800 Amp Copper/Tin Plated / 1.5"
BUS BRACING: 65kA
VERTICAL BUS: 300 Amp Tin Plated Copper
HORIZONTAL GROUND BUS: .25" X 1.0" (6.35mm X 25.4mm) Tin Plated Copper
Units Securely Grounded To Structure

ENCLOSURE DATA:

ENCLOSURE TYPE: 20" DEEP Type 1A
EXTERIOR COLOR: Electrodeposition Finish ANSI 49 Medium Light Grey
INTERIOR COLOR: Electrodeposition Finish White
REMOVABLE 3" [76mm] LIFTING ANGLE

STRUCTURE MODIFICATIONS:

Ground Bus Lug : Main Section
Rodent Barriers 1,12
Manual Bus Shutters 1,2,3,4,5,6,7,8,9,10,11,12
Premium Barrier System 1,2,3,4,5,6,7,8,9,10,11,12
Copper Vertical Ground Bus 1,2,3,4,5,6,7,8,9,10,11,12
Wire Retainers 1,2,3,4,5,6,7,8,9,10,11,12

EQUIPMENT WEIGHT:

SHIPPING SPLIT # 1: 2250.00 Lbs. (1020.60 Kg.)
SHIPPING SPLIT # 2: 2250.00 Lbs. (1020.60 Kg.)
SHIPPING SPLIT # 3: 2250.00 Lbs. (1020.60 Kg.)
SHIPPING SPLIT # 4: 2250.00 Lbs. (1020.60 Kg.)
TOTAL LINEUP WEIGHT (APPROX): 9000.00 Lbs. (4082.40 Kg.)

PRODUCT ACCESSORIES:

Seismic Qualified IBC/ASCE7
Drip Hoods

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEVATION
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	F41428112-001-01


REV	DESCRIPTION	BY	DATE								
B	REAPPROVAL	TA	06/21/2019	A	APPROVAL RESUBMIT	RN	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--


REQUIREMENTS FOR SEISMIC RATING

ANCHORING CONDITIONS:

To Maintain Seismic Qualifications, Equipment Must Be Installed Per Installation Manual 80459–641–XX And Per Any Seismic Anchoring Details Provided By Others. Do Not Install Equipment Before Approved Seismic Anchoring Details Have Been Obtained And Site Preparations Have Been Made In Accordance With The Approved Seismic Anchoring Details. All Post–Installed Anchors Shall Be Approved For Seismic Loads.

Consideration Must Be Made For Conduit Entry Into Each Section When Developing Mounting Pad Reinforcement Locations. See Conduit Entry Details For Dimensional Information.





Each MCC Section Must Be Anchored At Four Locations (See Above Details). Anchor Bolt Mounting Points Are .88/[22] Diameter Holes Located 1.50/[38] Above The Base Of The MCC Section. Use Dimensions From The Anchor Detail To Determine Mounting Locations.

The Belleville Washer (Shown In Detail Above) Used For Anchoring Connections Is A Tested Component And Is Required To Maintain Position Retention Of The Equipment. The Slip Critical Connection Performance Of The Bolted Connection Was Established To The Shake Table Tested Seismic Capacity Of The Equipment As Shown On The Equipment Seismic Certificate Supplied At The Time Of Order.

CENTER OF GRAVITY:

The CG Information Provided Below Should Only Be Used For Seismic Anchoring Calculations.

Elevation Center Of Gravity: 62.00/[1575] Up From Floor Except Masterpact NW Main Use 54.00/[1372] Up From Floor

Depth Center Of Gravity: 7.50/[191] or 10.00/[254] From Rear For 15.00/[381] or 20.00/[508] Deep Sections Respectively. Consult Factory For Sections Taller Than 94.50/[2400].

Vertical Center of Gravity: Use Centerline Of Section From Left To Right


SECTION WEIGHTS:

The Weights Shown Below Should Only Be Used For Calculating Seismic Anchoring Requirements And Do Not Represent Actual Section Weights As Shipped.

1200 Lbs. (544.3 Kg.)	35.00/[889] Wide Sections
1300 Lbs. (589.7 Kg.)	20.00/[508] Wide Sections
1500 Lbs. (680.4 Kg.)	25.00/[635] And 30.00/[762] Wide Sections*
*1900 Lbs. (861.8 Kg.)	30.00/[762] Wide Section With Masterpact NW Main
2250 Lbs. (1020.6 Kg.)	50.00/[1270] Wide Section With 18 Pulse Drive
2750 Lbs. (1247.4 Kg.)	65.00/[1651] Wide Section With 18 Pulse Drive


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	SEISMIC
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# S41428112–001–01	PG 1 OF 1 REV C

REV	DESCRIPTION	BY	DATE								
B	REAPPROVAL	TA	06/21/2019	A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	**MCC – 1**
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ONE LINE DIAGRAM
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	**041428112–001–01**

REV	DESCRIPTION	BY	DATE								
B	REAPPROVAL	TA	06/21/2019	A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	**MCC – 1**
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ONE LINE DIAGRAM
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# **041428112-001-01**	PG **2** OF **2** REV C

REV	DESCRIPTION	BY	DATE
–	----	--	--/--/--

A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019
B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--

UNIT LOC	UNIT NAMEPLATES (WHITE SURFACE/BLACK LETTERS)	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
1A	MAIN	MAIN SW			FU SW 600												3/0–500KCMIL 3 LUGS/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112–001–01
1U	SPACE	SPACE																
2A	SURGE PROTECTION DEVICE	SPD	160kA		SW 30												SOLIDLY GROUNDED, SURGE COUNTER	E41428112–001–02
2C	P–02–410	FVNR	NEMA 2	20	FU SW 60		CONTROL TRANSFORMER	100	.50	1.00	2	1	RED			HOA SS	#14 AWG MTW CONTROL WIRE, 600V SYSTEM, CLASS 10/20 O/L (SELECTABLE), CLASS J FUSE CLIPS,	E41428112–001–03
																	MOTOR LOGIC O/L NEMA SIZE 2, N.C. ISOLATED AUX O/L CONTACTS, STD WIRE LABELS	
2G	P–02–420	FVNR	NEMA 2	20	FU SW 60		CONTROL TRANSFORMER	100	.50	1.00	2	1	RED			HOA SS	#14 AWG MTW CONTROL WIRE, 600V SYSTEM, CLASS 10/20 O/L (SELECTABLE), CLASS J FUSE CLIPS,	E41428112–001–03
																	MOTOR LOGIC O/L NEMA SIZE 2, N.C. ISOLATED AUX O/L CONTACTS, STD WIRE LABELS	
2K	P–02–430	FVNR	NEMA 2	20	FU SW 60		CONTROL TRANSFORMER	100	.50	1.00	2	1	RED			HOA SS	#14 AWG MTW CONTROL WIRE, 600V SYSTEM, CLASS 10/20 O/L (SELECTABLE), CLASS J FUSE CLIPS,	E41428112–001–03
																	MOTOR LOGIC O/L NEMA SIZE 2, N.C. ISOLATED AUX O/L CONTACTS, STD WIRE LABELS	
2O	SPACE	SPACE																
2S	SPACE	SPACE																
2W	SPACE	SPACE																
3A	SPACE	SPACE																
3E	SPACE	SPACE																
3G	SPACE	SPACE																
UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	PRI	SEC	NO	NC	ON LIGHT	OFF LIGHT	ADDL P/L	SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
									FUSE SIZE		INTERLOCKS		PILOT DEVICES: LED 22 mm **					

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	UNIT INFORMATION
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	I41428112–001–01

REV	DESCRIPTION	BY	DATE								
B	REAPPROVAL	TA	06/21/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--
				A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--

UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
3K	P–03–640	ATV930	U40	5	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112–001–04
3S	ASD OUTPUT REACTOR FOR P–03–640	OUTPUT REACTOR																E41428112–001–04
3V	SPACE	SPACE																
4A	ASD LINE REACTOR FOR B–102–130	LINE REACTOR																E41428112–001–05
4D	B–102–130	ATV930	D22	25	FU SW 60		CONTROL TRANSFORMER	300	1.25	3.20			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112–001–05
4N	ASD OUTPUT REACTOR FOR B–102–130	OUTPUT REACTOR																E41428112–001–05
4Q	SPACE	SPACE																
4U	SPACE	SPACE																
5A	ASD LINE REACTOR FOR B–102–120	LINE REACTOR																E41428112–001–06
5D	B–102–120	ATV930	D22	25	FU SW 60		CONTROL TRANSFORMER	300	1.25	3.20			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112–001–06
5N	ASD OUTPUT REACTOR FOR B–102–120	OUTPUT REACTOR																E41428112–001–06
5Q	SPACE	SPACE																
5U	SPACE	SPACE																
6A	ASD LINE REACTOR FOR B–102–110	LINE REACTOR																E41428112–001–07
6D	B–102–110	ATV930	D22	25	FU SW 60		CONTROL TRANSFORMER	300	1.25	3.20			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112–001–07
6N	ASD OUTPUT REACTOR FOR B–102–110	OUTPUT REACTOR																E41428112–001–07
UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	PRI	SEC	NO	NC	ON LIGHT	OFF LIGHT	ADDL P/L	SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
									FUSE SIZE		INTERLOCKS		PILOT DEVICES: LED 22 mm **					

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	UNIT INFORMATION
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	I41428112–001–01

REV	DESCRIPTION	BY	DATE							
B	REAPPROVAL	TA	06/21/2019	A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--

UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE		INTERLOCKS		PILOT DEVICES: LED 22 mm **				OTHER UNIT FEATURES	ELEMENTARY #
									PRI	SEC	NO	NC	ON LIGHT	OFF LIGHT	ADDL P/L	SS / PB		
6Q	SPACE	SPACE																
6U	SPACE	SPACE																
7A	P–02–610	ATV930	U22	3	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112–001–08
7I	ASD OUTPUT REACTOR FOR P–02–610	OUTPUT REACTOR																E41428112–001–08
7L	P–02–620	ATV930	U22	3	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112–001–09
7T	ASD OUTPUT REACTOR FOR P–02–620	OUTPUT REACTOR																E41428112–001–09
7W	SPACE	SPACE																
8A	P–02–440	FVNR	NEMA 2	20	FU SW 60		CONTROL TRANSFORMER	100	.50	1.00	2	1	RED			HOA SS	#14 AWG MTW CONTROL WIRE, 600V SYSTEM, CLASS 10/20 O/L (SELECTABLE), CLASS J FUSE CLIPS,	E41428112–001–03
																	MOTOR LOGIC O/L NEMA SIZE 2, N.C. ISOLATED AUX O/L CONTACTS, STD WIRE LABELS	
8E	P–02–450	FVNR	NEMA 2	20	FU SW 60		CONTROL TRANSFORMER	100	.50	1.00	2	1	RED			HOA SS	#14 AWG MTW CONTROL WIRE, 600V SYSTEM, CLASS 10/20 O/L (SELECTABLE), CLASS J FUSE CLIPS,	E41428112–001–03
																	MOTOR LOGIC O/L NEMA SIZE 2, N.C. ISOLATED AUX O/L CONTACTS, STD WIRE LABELS	
8I	P–02–460	FVNR	NEMA 2	20	FU SW 60		CONTROL TRANSFORMER	100	.50	1.00	2	1	RED			HOA SS	#14 AWG MTW CONTROL WIRE, 600V SYSTEM, CLASS 10/20 O/L (SELECTABLE), CLASS J FUSE CLIPS,	E41428112–001–03
																	MOTOR LOGIC O/L NEMA SIZE 2, N.C. ISOLATED AUX O/L CONTACTS, STD WIRE LABELS	
8M	SPACE	SPACE																
8Q	SPACE	SPACE																
UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	PRI	SEC	NO	NC	ON LIGHT	OFF LIGHT	ADDL P/L	SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
									FUSE SIZE		INTERLOCKS		PILOT DEVICES: LED 22 mm **					

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	UNIT INFORMATION
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	I41428112–001–01

REV	DESCRIPTION	BY	DATE						
A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--		
B	REAPPROVAL	TA	06/21/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--

UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
8U	SPACE	SPACE																
9A	DDR–02–311	ATV930	U22	3	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112–001–10
9I	ASD OUTPUT REACTOR FOR DDR–02–311	OUTPUT REACTOR																E41428112–001–10
9L	DDR–02–321	ATV930	U22	3	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112–001–11
9T	ASD OUTPUT REACTOR FOR DDR–02–321	OUTPUT REACTOR																E41428112–001–11
9W	SPACE	SPACE																
10A	SPACE	SPACE																
10C	SPACE	SPACE																
10E	SPACE	SPACE																
10I	P–03–630	ATV930	U40	5	FU SW 30		CONTROL TRANSFORMER	100	.50	1.00			RED PTT			HOA SS SPD POT	#16 AWG MTW CONTROL WIRE, CLASS J FUSE CLIPS, STD WIRE LABELS	E41428112–001–12
10Q	ASD OUTPUT REACTOR FOR P–03–630	OUTPUT REACTOR																E41428112–001–12
10T	SPACE	SPACE																
11A	SPACE	SPACE																
11C	P–04–770	6" BRANCH SW			FU SW 30												14–2AWG 1 LUG/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112–001–13
11E	P–04–780	6" BRANCH SW			FU SW 30												14–2AWG 1 LUG/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112–001–13
UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	UNIT INFORMATION
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG#	I41428112–001–01


REV	DESCRIPTION	BY	DATE							
B	REAPPROVAL	TA	06/21/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--
				A	APPROVAL RESUBMIT	RN	06/19/2019	–	----	--	--/--/--

UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	FUSE SIZE PRI	FUSE SIZE SEC	INTERLOCKS NO	INTERLOCKS NC	PILOT DEVICES: LED 22 mm ** ON LIGHT	PILOT DEVICES: LED 22 mm ** OFF LIGHT	PILOT DEVICES: LED 22 mm ** ADDL P/L	PILOT DEVICES: LED 22 mm ** SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
11G	P-04-790	6" BRANCH SW			FU SW 30												14-2AWG 1 LUG/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112-001-13
11I	SPACE	SPACE																
11M	SPACE	SPACE																
11Q	SPACE	SPACE																
11U	SPACE	SPACE																
12A	SPACE	SPACE																
12E	P-04-970	6" BRANCH SW			FU SW 30												14-2AWG 1 LUG/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112-001-13
12G	P-04-980	6" BRANCH SW			FU SW 30												14-2AWG 1 LUG/PH, AL MECH LUG AL/CU CABLE, CLASS J FUSE CLIPS	E41428112-001-13
12I	SPACE	SPACE																
12M	SPACE	SPACE																
12Q	SPACE	SPACE																
12U	SPACE	SPACE																
UNIT LOC	UNIT NAMEPLATES	UNIT TYPE	SIZE	HP	FRAME AMPS	TRIP AMPS	CONTROL SOURCE	VA	PRI	SEC	NO	NC	ON LIGHT	OFF LIGHT	ADDL P/L	SS / PB	OTHER UNIT FEATURES	ELEMENTARY #
									FUSE SIZE		INTERLOCKS		PILOT DEVICES: LED 22 mm **					

JOB NAME:	IQALUIT WWTP MCC UPGRADES
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC
DRAWN BY:	CAD
ENGR:	MLC
DATE:	MAY 21, 2019
DRAWING STATUS:	APPROVAL

EQUIPMENT DESIGNATION:	MCC – 1
EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWING TYPE:	UNIT INFORMATION
DWG#	I41428112-001-01


REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019



POWER FUSES NOT INCLUDED

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-01	PG 1 OF 1 REV C


REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019



JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-02	PG 1 OF 1 REV C

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

14M




POWER FUSE NOT INCLUDED

HEAT SHRINK WIRE LABELS

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-03	PG 1 OF 1 REV C

REV	DESCRIPTION	BY	DATE								
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



DRIVE CATALOG NUMBER ATV930U40S6X


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-04	PG1 OF2 REVC

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–04	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE								
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



DRIVE CATALOG NUMBER ATV930D22Y6


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-05	PG1 OF2 REVC

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–05	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE							
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



DRIVE CATALOG NUMBER ATV930D22Y6


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-06	PG1 OF2 REVC

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–06	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE							
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



DRIVE CATALOG NUMBER ATV930D22Y6


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-07	PG 1 OF 2 REV C

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–07	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE								
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



HEAT SHRINK WIRE LABELS

DRIVE CATALOG NUMBER ATV930U22S6X


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-08	PG1 OF2 REVC

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–08	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE								
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



HEAT SHRINK WIRE LABELS

DRIVE CATALOG NUMBER ATV930U22S6X


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-09	PG1 OF2 REVC

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–09	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE								
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



HEAT SHRINK WIRE LABELS

DRIVE CATALOG NUMBER ATV930U22S6X


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-10	PG1 OF2 REVC

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–10	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE								
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



HEAT SHRINK WIRE LABELS

DRIVE CATALOG NUMBER ATV930U22S6X


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-11	PG1 OF2 REVC

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–11	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE								
A	APPROVAL RESUBMIT	RN	06/19/2019	B	REAPPROVAL	TA	06/21/2019	–	----	--	--/--/--
				C	APPROVAL RESUBMITAL	MLC	07/11/2019	–	----	--	--/--/--



HEAT SHRINK WIRE LABELS

DRIVE CATALOG NUMBER ATV930U40S6X


JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY-DE-VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112-001-12	PG1 OF2 REVC

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019

ATV930 FACTORY CONFIGURATION – NORMAL DUTY – VARIATIONS FROM DEFAULT HOA						
MENU	TAB	SUB–MENU	DESCRIPTION	SETTING	CODE	ADJ.
1	S.START	––––	2/3 WIRE CONTROL	2C	TCC	2C
1	S.START	––––	BASIC FREQUENCY	60Hz NEMA	BFR	60
1	S.START	––––	MAX FREQUENCY	60	TFR	60
1	S.START	––––	LOW SPEED	3	LSP	3
1	S.START	––––	ACCELERATION	10	ACC	10
1	S.START	––––	DECELERATION	10	DEC	10
5.2	–––	SWITCHING FREQUENCY	SWITCHING FREQUENCY	2.5	SFR	2.5
5.4	–––	––––	REF FREQ 1 CONFIG	AI1	FR1	AI1
5.4	–––	––––	FREQ SWITCH ASSIGN	DI3	RFC	DI3
5.4	–––	––––	2–WIRE TYPE	LEVEL	TCT	LEL
5.4	–––	––––	REF FREQ 2 CONFIG	AI3	FR2	AI3
5.4	–––	CONTROL MODE	CONTROL MODE	CONTROL MODE I/O PROFILE	CHCF	IO
5.4	–––	COMMAND SWITCHING	COMMAND SWITCHING	DI3	CCS	DI3
5.4	–––	CMD CHANNEL 1	CMD CHANNEL 1	TERMINAL	CD1	TER
5.4	–––	CMD CHANNEL 2	CMD CHANNEL 2	TERMINAL	CD2	TER
5.14	AI/AQ	AI3 CONFIGURATION	AI3 MIN VALUE	4	CLR3	4
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 ASSIGNMENT	MOTOR FREQUENCY	AO1	OFR
5.14	AI/AQ	AQ1 TYPE	AQ1 MIN OUTPUT	CURRENT	AO1T	0A
5.14	AI/AQ	AQ1 CONFIGURATION	AQ1 MIN OUTPUT	4	AOL1	4
5.14	RELAY	R1 CONFIGURATION	R1 ASSIGNMENT	OPERATING STATE	R1	FLT
5.14	RELAY	R2 CONFIGURATION	R2 ASSIGNMENT	DRIVE RUNNING	R2	RUN
5.16	–––	CATCH ON THE FLY	CATCH ON THE FLY	YES	FLR	YES

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–12	PG 2 OF 2 REV C

REV	DESCRIPTION	BY	DATE	B	REAPPROVAL	TA	06/21/2019
A	APPROVAL RESUBMIT	RN	06/19/2019	C	APPROVAL RESUBMITAL	MLC	07/11/2019



POWER FUSES NOT INCLUDED

JOB NAME:	IQALUIT WWTP MCC UPGRADES	EQUIPMENT DESIGNATION:	MCC – 1
JOB LOCATION:	SALABERRY–DE–VALLEYFIELD QC	EQUIPMENT TYPE:	MODEL 6 MOTOR CONTROL CENTER
DRAWN BY:	CAD	DRAWING TYPE:	ELEMENTARY
ENGR:	MLC		SQUARE D by Schneider Electric
DATE:	MAY 21, 2019		
DRAWING STATUS:	APPROVAL	DWG# E41428112–001–13	PG 1 OF 1 REV C

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 29 23 - Variable Frequency Motor Controllers

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 32 14 - Power Generation Diesel

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 32 14 - Power Generation Diesel

Date: June 4, 2019

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 04, 2019

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Waste Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-15R2 SU-ELE15R2
PO-Frontier Power

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [x] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

26 32 14 Power Generation Diesel-Silencer

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-15R2 (Generator Silencer)

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [x] Mechanical
- [ ] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec


- [x] REVIEWED
- [ ] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2019-06-05


BY Brendan Zrum, P.Eng


Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.




TOP VIEW





SIDE VIEW



OUTLET END VIEW

P/O # Quote#19710

Standard Specifications

- Material: CS-A36 (44W)
- Uninsulated
- Tolerance — 1/8"; ∠ ±2°
- Finish:
  1,100 F High Heat Black Paint
- Tolerance: ±1/8"
- Weight: 85 lbs

All dimensions are in inches (") unless otherwise stated. Do not scale.

Title: 5" Cylindrical Silencer -Standard- Critical Grade (25-30 dBA) Side In-End Out-Carbon Steel	Dwg.Nbr: SM2-5	Revision: 0	Plot Scale: NTS
			Format: A
			Date: 05/22/2019 09:01:39
Client/Project: Frontier Power WWTP W.O # Quote#19710			

SMS SILENCERS RESERVES THE PROPIETARY RIGHTS TO THIS DRAWING AND THE DATA SHOWN THEREON AND IS SUBMITTED IN CONFIDENCE ONLY. SAID DRAWING AND/OR DATA ARE NOT TO BE USED OR REPRODUCED FOR ANY PURPOSE WITHOUT WRITTEN CONSENT OF SMS SILENCERS

www.smssilencers.com
sales@smssilencers.com
Tel: 905-459-1512
Fax: 905-459-3138
15 Bramalea Raod Unit#7
Brampton, ON
L6T 2W4

SMS SILENCERS INC.

V.1.0 Dec 10 2016

Project ID# 26110-Brent | Dwg ID# 26111

SMS SILENCERS INC.

SMS Silencers Inc.
7-15 Bramalea Rd.
Brampton, ON, Canada L6T 2W4

Toll Free 800 459 1512
Phone 905 459 1512
Fax 905 459 3138

Company Info

Frontier Power Products Ltd.
7983 Progress Way
Delta, BC
V4G 1A3, Canada

Prepared by: Brent MacMillan

Contact info

Will Osburn
wosburn@frontierpower.com

WWTP

Genset Manufacturer:	Caterpillar
Genset Model:	G3306TA - 220bhp
Engine Manufacturer:	Caterpillar
Engine Model:	G3306TA

Engine Information

Exhaust Flow:	967.00 ACFM	**Max BP:**	27.00 in wg	**Temp:**	1000.00 Fahrenheit	**KW:**	165
Number of Outlets:	1	**Outlet Diameter:**	5.00	**Flex Length:**	18.00	**Fuel Type:**	Other

Engine Octave Band

Engine Exhaust: Sound Pressure Level (LP) measured @ 1.00 m in dB

60 Hz	125 Hz	250 Hz	500 Hz	1 KHz	2 KHz	4 KHz	8 KHz	dB	dBA
106.00	108.00	99.00	98.00	97.00	96.00	95.00	95.00	111.22	103.51

Catalytic Converter IL.

No Catalytic Converter sound data is given.

Exhaust Back Pressure Detail

No User Selection for Exhaust data is made.

Silencer(s) Sizing Result

Silencer(s) Results below is based on user Selection of One Silencer using SMS Default dBA correction & Near Field Distance attenuation:

Recommended Minimum Outlet Size 4"

Silencer Part #	Description	Outlet Size	Back Pressure
SM2-5-SIEO	5" Critical Grade Cylindrical Silencer (25-30 dBA)	5 in	5.13 in wg
Silencer(s)			**5.13 in wg**
Qty : 1 Flex Dia : 5.00 Flex Length 18.00"		Flex Connector :	0.20 in wg

Exhaust Velocity = 7,095.00 ft/min OR 36 m/s

Octave Band

Octave Band	63 Hz	125 Hz	250 Hz	500 Hz	1 kHz	2 kHz	4 kHz	8 kHz	dB	dBA
Engine SPL @ 1 m	106.00	108.00	99.00	98.00	97.00	96.00	95.00	95.00	111.22	103.51
Silencer #1 : SM2 dB @ 1 m	16.00	27.00	30.00	29.00	25.00	21.00	20.00	20.00	34.74	30.85
Catalytic Converter IL.	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00
dBA reduction correction	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00		
Resulting SPL @ 1 m	90.00	81.00	69.00	69.00	72.00	75.00	75.00	75.00	90.98	81.21
Distance Attenuation dB	10.14	10.14	10.14	10.14	10.14	10.14	10.14	10.14		
Resulting SPL @7.00 m	79.86	70.86	58.86	58.86	61.86	64.86	64.86	64.86	80.84	71.07

Calculated noise level is based on free field conditions.
No site conditions and no calculation safety factors are taken into consideration.
Typical resulting noise tolerance is +/- 5dBA. No noise result guarantees are implied.

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 36 23 - Automatic Transfer Switch

Date: Jun 18, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 18, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-03
PO-P18-120

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [X] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Drawing E-601-Automatic Transfer Switch

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

THOMSON™
POWER SYSTEMS

APPROVAL DRAWINGS

ATTACHED DOCUMENTS ARE DRAFT FOR REVIEW ONLY AND ARE SUBJECT TO CHANGE WITHOUT NOTICE.

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE STANDARD TERMS & CONDITIONS.

THE INFORMATION CONTAINED IN THESE DRAWINGS IS THE PROPERTY OF THOMSON POWER SYSTEMS, IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

NOTE:
ANY PROGRAM SETTINGS SHOWN REFLECT FACTORY DEFAULT SETTINGS ONLY. FINAL SETTINGS WILL BE REQUIRED TO BE SET BY THE COMMISSIONING AUTHORITY. FAILURE TO DO SO MAY RESULT IN EQUIPMENT FAILURE.

PROJECT NAME / REFERENCE : IQALUIT WTP

CUSTOMER : FRONTIER POWER PRODUCTS

THOMSON CUSTOMER ORDER : C–058937 REV# : 0

WORKORDER / SERIAL NUMBER : W–102489

MODEL NUMBER : TS873A0400A1CN5BKKAA

ATTACHED DRAWINGS :

PHYSICAL LAYOUT & INSTALLATION DETAILS	W–102489–10A	REV#	0
MCS AC SCHEMATIC	W–102489–20A	REV#	0
ATS AC CONTROL SCHEMATIC	W–102489–20B	REV#	0
ATS DC CONTROL SCHEMATIC	W–102489–20C	REV#	0
STANDARD OPTION SCHEMATIC – CTKIT0400A	W–102489–30A	REV#	0
STANDARD OPTION SCHEMATIC – PPR–10	W–102489–30B	REV#	0

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-003 Automatic Transfer Switch

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other _____

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED

☑ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Provide 4-position switch as per specifcations- Test, Auto, Manual, Engine Start.

FEATURES / RATINGS:

AMPERAGE :	400A
VOLTAGE :	347 / 600V (3PH, 4W, GROUNDED NEUTRAL)
POLES :	3–POLE
FREQUENCY :	60HZ
CONFIGURATION :	STANDARD ATS
APPLICATION :	STANDARD
OPERATION :	OPEN TRANSITION
ENCLOSURE :	NEMA 2, ASA # 61 GREY
ATS CONTROLLER :	TSC900 C/W GHC DISPLAY

UTILITY (OR SOURCE 1) SWITCHING DEVICE :	MOLDED CASE SWITCH
GENERATOR (OR SOURCE 2) SWITCHING DEVICE :	MOLDED CASE SWITCH
APPROVAL STANDARD :	UL1008 / CSA C22.2.NO 178

SYSTEM OPTIONS:

LPM :	TRANSFER SWITCH LOAD POWER METERING (0400A CT KIT)
PPR–10 :	PROGRAMMABLE POWER RELAY INCLUDES 10A FORM "C" CONTACT WIRED TO TERMINAL (EXTERNAL 24VDC REQ)
CUSTOM OPTION 1 :	NEMA 2 ENCLOSURE C/W DRIP SHIELD

SHOP DRAWING / SUBMITTAL REVIEW

☐ APPROVED ☐ APPROVED WITH CHANGES NOTED

☐ REVISE AND RESUBMIT ☐ REJECTED _____

SUBMITTAL WAS RECEIVED FOR DESIGN CONFORMITY AND GENERAL CONFORMANCE TO CONTRACT DOCUMENTS ONLY. THE CONTRACTOR FOR CONFIRMING AND CORRELATING DIMENSIONS AT JOB SITES FOR TOLERANCES, CLEARANCES, QUANTITIES, FABRICATION PROCESSES AND TECHNIQUES OF CONSTRUCTION, COORDINATION OF HIS WORK WITH OTHER TRADES AND FULL COMPLIANCE WITH CONTRACT


BY_____ DATE_____

COMPANY NAME_____


CITY_____STATE / PROV _____

9087A – 198TH STREET, LANGLEY, BC CANADA V1M 3B1
EMAIL : info@thomsonps.com, www.thomsonps.com


REGAL®




FRONT VIEW




LHS VIEW
(SIDE COVER REMOVED)



INTERIOR FRONT VIEW



VIEWED FROM REAR
(INSIDE) OF DOOR



INTERIOR FRONT VIEW
(DOOR NOT SHOWN)

BASIC MODEL TS87xA	STANDARD ATS				
	CLOSING AND WITHSTAND RATING AVAILABLE AMPS (RMS) CLOSING & WITHSTAND RATINGS SHOWN ARE ONLY FOR ATS UTILITY AND/OR GENERATOR POWER SWITCHING DEVICE(S) THAT ARE NOT FACTORY SUPPLIED WITH INTEGRAL OVERCURRENT PROTECTION. PLEASE REFER TO PRODUCT INSTRUCTION MANUAL FOR FURTHER INFORMATION ON UPSTREAM PROTECTION REQUIREMENT.				
	MAX. VOLTAGE	RATED CURRENT (A)	@240V	@480V	@600V
TS 873A-400	600	400	65,000	50,000	35,000

CONNECTION DATA		
400A ATS	UTILITY (SRC1)	1-2C, 2/0-500MCM Cu/Al PER PHASE
	GENERATOR (SRC2)	1-2C, 2/0-500MCM Cu/Al PER PHASE
	LOAD	1-2C, 2/0-500MCM Cu/Al PER PHASE
	NEUTRAL	1-2C, 2/0-500MCM Cu/Al PER SOURCE
	GROUND	6C, #6-250MCM Cu/Al

GENERAL NOTES	
1	POWER SWITCHING DEVICES ARE MECHANICALLY INTERLOCKED SO THAT ONLY ONE DEVICE IS CLOSED AT A TIME
2	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

2.5" x 5"

W1

DANGER
PELIGRO



Arc Flash and Shock Hazard
Will cause severe injury or death. More than one live circuit - see diagram. Disconnect all sources of supply before servicing. This equipment must be installed and serviced only by qualified electrical personnel utilizing safe work practices and appropriate Personal Protective Equipment (PPE). Failure to comply may result in injury or death! Refer to NFPA 70E for minimum PPE requirements.

Risque d'Arc Electrique et d'Electrocution
Peut causer des blessures graves oui la mort. Plus d'un circuit sous tension - voir schema. Couper toutes les sources d'alimentation avant de faire l'entretien et les réparations. Ce matériel doit être installé et entretenu uniquement par un électricien qualifié. Ce dernier doit connaitre les pratiques de travail sécuritaires et porter l'équipment de protection individuelle approprié. Le non respect mai entrainer des blessures ou la mort! Reportez-vous à NFPA 70E pour le manuel des exigences minimales PPE.

Riesgo de Arco y Choque Eléctrico
Se causarán lesiones graves o muerte. Más de un circuito energizado - ver diagrama. Desconectar todas las fuentes de suministro antes de hacer mantenimiento. Este equipo solo se debe instalar y mantener por personal calificado, usando medidas de seguridad y equipo de protección personal adecuados. No seguir estas recomendaciones puede causar lesiones o muerte! Consultar la NFPA 70E para los requisitos mínimos del equipo de protección personal (PPE)

QTY = 1

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
50C-C-1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS


No.	REVISIONS	BY	AUTH	DATE

THOMSON POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
PHYSICAL LAYOUT & INSTALLATION DETAILS
IQALUIT WTP

CUSTOMER	FRONTIER POWER PRODUCTS		
CUSTOMER ORDER No.	C-058937	WORK ORDER No.	W-102489
DRAWN BY	NS	AUTH BY	OG
DATE	18-06-12	REV	0
DRAWING/FILE No.	W-102489-10A	SHEET	10A

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.



COLOR KEY	
BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

GENERAL NOTES	
1	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
2	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
50C-C-1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE

THOMSON™ POWER SYSTEMS


AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
MCS AC SCHEMATIC
IQALUIT WTP

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER FRONTIER POWER PRODUCTS			
CUSTOMER ORDER No. C-058937		WORK ORDER No. W-102489	
DRAWN BY NS	AUTH BY OG	DATE 18-06-12	REV 0
DRAWING/FILE No. W-102489-20A		SHEET 20A	

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.



GENERAL NOTES	
1	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
2	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

VOLTAGE
(X DENOTES HIGH POLARITY MARKER)

PT TAP	208	240	380	400	416	480	600
H1	X	X			X	X	X
H2	X		X	X			
H3		X					
H4					X	X	
H5			X	X			X

COLOR KEY	
BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
50C-C-1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE

THOMSON™ POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH MODEL TS 873A0400A1CN5BKKAA ATS AC CONTROL SCHEMATIC

IQALUIT WTP


CUSTOMER FRONTIER POWER PRODUCTS

CUSTOMER ORDER No.	WORK ORDER No.
C-058937	W-102489

DRAWN BY	AUTH BY	DATE	REV
NS	OG	18-06-12	0

DRAWING/FILE No.	SHEET
W-102489-20B	20B

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.



PARAMETER	MODBUS RTU SETTINGS
SLAVE ID	1
PORT NAME	COM 4
BAUD RATE	57600
PARITY	NONE
STOP BUS	ONE

TSC900 FACTORY DEFAULT SETTINGS

NOTE : REFER TO OPTION DRAWINGS FOR APPLICABLE CHANGES TO FACTORY DEFAULT SETTINGS

PARAMETER	DEFAULT	RANGE
GENERATOR (SOURCE 2) START DELAY	3 SEC	0–60 SEC
GENERATOR (SOURCE 2) WARM UP DELAY	2 SEC	0–3600 SEC
GENERATOR (SOURCE 2) COOL DOWN DELAY	300 SEC	0–3600 SEC
UTILITY (SOURCE 1) RETURN DELAY	300 SEC	0–3600 SEC
TRANSFER NEUTRAL DELAY	3 SEC	0–120 SEC
TRANSFER FAIL DELAY	30 SEC	0–120 SEC
EXERCISE TIMER	PROG.	PROG.
GENERATOR (SOURCE 2) UNDER VOLTAGE DELAY	3 SEC	0–10 SEC
GENERATOR (SOURCE 2) UNDER FREQUENCY DELAY	5 SEC	0–10 SEC
GENERATOR (SOURCE 2) UNDER VOLTAGE PICK UP	90%	75–100%
GENERATOR (SOURCE 2) UNDER VOLTAGE DROP OUT	85%	70–95%
UTILITY (SOURCE 1) UNDER VOLTAGE DELAY	1 SEC	0–10 SEC
UTILITY (SOURCE 1) UNDER VOLTAGE PICK UP	90%	75–100%
UTILITY (SOURCE 1) UNDER VOLTAGE DROP OUT	85%	70–95%

ALL SETTINGS ARE FIELD ADJUSTABLE UNLESS NOTED. REFER TO THE TSC900 MANUAL FOR A COMPLETE LISTING OF ALL TSC900 SETTINGS.

GENERAL NOTES	
1	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
2	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

COLOR KEY	
BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
SOC – C – 1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE

THOMSON™ POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
ATS DC CONTROL SCHEMATIC
IQALUIT WTP


FOR REVIEW ONLY


DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER	FRONTIER POWER PRODUCTS
CUSTOMER ORDER No.	C–058937
WORK ORDER No.	W–102489
DRAWN BY	NS
AUTH BY	OG
DATE	18–06–12
REV	0
DRAWING/FILE No.	W–102489–20C
SHEET	20C


© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

☒ CTK0400A OPTION





ATS CONTROL PLATE



PART ID	OPTION KITS
CTK0100	100 AMPS
CTK0150	150 AMPS
CTK0250	200–250 AMPS
CTK0400	400 AMPS
CTK0600	600 AMPS
CTK0800	800 AMPS
CTK1200	1000–1200 AMPS
CTK1600	1600 AMPS
CTK2000	2000 AMPS

GENERAL NOTES	
1	CT'S TO BE MOUNTED ON THE LOAD SIDE OF THE ATS. CUSTOMER TO VERIFY POLARITY BEFORE CONNECTING THE CT SECONDARIES TO THE TRANSFER SWITCH CONTROLLER.
2	ATS CONTROL PLATE MOUNTED ON THE BACK SIDE OF DOOR FOR MCS / MOS AND FOR ICS MOUNTED ON THE BACKPAN.
3	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

BILL OF MATERIALS FOR CABLE HARNESS		
PART DESCRIPTION	PART ID	QTY
WIRE, 18AWG, GREY, TINNED, TEW, 600V,	002027	600 INCHES
TERM. BLK, RAIL MNT, 40A, 600V, WK4/U,	001861	6
TERM. BLK, ENDPLATE, WK 2.5–4/U,	001872	1
SCREW, SHT–MTL, RDH, ROB #6 X 5/8"	002070	2
MTG–RAIL, TYPE–35, SLOTTED(7.5X2–METERS)	002795	6
TERM. BLK, PARTITION PLATE, WK2.5–4/U,	004189	2
CONN, MINI–FIT, J, 94V–2, 2X1–WAY,FEMALE (J5/J6/J7)	012654	3
CONN, FEMALE CRIMP, MINI–FIT, JR, SERIES	010954	6
WIRE SLEEVE, 0.5", EXPANDO PT PLUS,	000456	175 INCHES
TERM BLK CROSS CONN.W SCRW WK4/U SR7	009677	3
TERM. BLK, EARTH TERMINAL, 10–24 AWG	005211	2

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
50C–C–1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE

THOMSON™ POWER SYSTEMS


AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
STANDARD OPTION SCHEMATIC – CTKIT0400A
IQALUIT WTP


CUSTOMER FRONTIER POWER PRODUCTS

CUSTOMER ORDER No.	WORK ORDER No.		
C–058937	W–102489		
DRAWN BY	AUTH BY	DATE	REV
NS	OG	18–06–12	0
DRAWING/FILE No.		SHEET	
W–102489–30A		30A	

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

☒ PPR–10 OPTION





PR1			
T1	TYPE	T2	REF
4	NO	7	A–5
1	NC		
5	NO	8	A–6
2	NC		
6	NO	9	A–7
3	NC		


PR2			
T1	TYPE	T2	REF
4	NO	7	B–5
1	NC		
5	NO	8	B–6
2	NC		
6	NO	9	B–7
3	NC		

PPR–10 OPTION NOTES	
1	FOR POWER RELAY FUNCTIONAL DESCRIPTION REFER TO FACTORY DEFAULT DIGITAL OUTPUT FUNCTION TABLE ON ATS DC CONTROL SCHEMATIC
2	THE NUMBER OF RELAYS SUPPLIED WILL BE PER ORDERED QUANTITY
3	CUSTOMER TO WIRE DIRECTLY TO RELAY TERMINALS
4	SPECIFIED QUANTITY OF PROGRAMMABLE POWER RELAYS ARE WIRED FOR CUSTOMER AS PER OPTION LIST
5	DC SUPPLY FOR THE RELAYS, BY DEFAULT IS 24VDC. PLEASE SPECIFY THE VOLTAGE RATING OTHER THAN 24VDC ON OPTION LIST

BILL OF MATERIALS		
PART DESCRIPTION	PART ID	QTY
RELAY, 24VDC COIL, 11 PIN SQ., /W LED	004095	2
RELAY SOCKET, 11 PIN, SQ., RAIL MOUNT	000399	2
FUSE HOLDER, 1P, 30A, 600V, 200KA, CC	002374	1
FUSE, 3A, 600VAC, CLASS CC	003633	1
TERM. BLK, RAIL MNT, 40A, 600V, WK4/U,	001861	10

GENERAL NOTES	
1	FOR MCS/MOS/PCS TYPE ATS, MOUNT THE RELAYS ON SIDE COVER WHERE SPACE PERMITS
2	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

PPR RELAY
[TYPICAL]



FOR REVIEW ONLY

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5OC–C–1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE

THOMSON™ POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 873A0400A1CN5BKKAA
STANDARD OPTION SCHEMATIC – PPR–10
IQALUIT WTP

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER	FRONTIER POWER PRODUCTS
CUSTOMER ORDER No.	C–058937
WORK ORDER No.	W–102489
DRAWN BY	NS
AUTH BY	OG
DATE	18–06–12
REV	0
DRAWING/FILE No.	W–102489–30B
SHEET	30B

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

Date: Jul 4, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 04, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-06
PO-P18-120

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Drawing E-601-Automatic Transfer Switch #2

Contractor to review and confirm this is meant to be E-603, Final SLD

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-006

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-10
BY Konrad Goluch

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Provide 4-position switch as per specification 26 36 23 2.3 .1

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Responsibility lies with the contractor as per the Contract.

Do not hesitate to contact me if you have any questions or concerns.

THOMSON™
POWER SYSTEMS

Approval Drawings

Project Name/Reference: IQALUIT WTP

Customer: FRONTIER POWER PRODUCTS

Thomson Customer Order: C-058937/1 Rev# 0

WorkOrder/Serial Number: W-102488

Model Number TS 873B0400A1CN5BKKAA

Attached Drawings:

Physical Drawing	MBS870M136	Rev#	0
AC Schematic	MBS870E100	Rev#	4
AC Control Schematic	TSC900E100	Rev#	4
DC Control Schematic	TSC900E101	Rev#	4

Option Drawings:

STANDARD OPTION SCHEMATIC - PPR-10	TSC900E300	Rev#	3
STANDARD OPTION SCHEMATIC - CTKXXXX	TSC900E304	Rev#	3
STANDARD OPTION SCHEMATIC - BYPASS AUX	TSC900E352	Rev#	3

Features/Ratings:

Amperage:	400A
Voltage:	347 - 600V 3 Phase (4 Wire)
Poles:	3POLE
Frequency:	60HZ
Configuration	Double Side Bypass
Application	Standard ATS
Operation	Open Transition Transfer
Enclosure Type	NEMA 2 Enclosure
ATS Controller	TSC900

Utility (or Source 1) Switching Device:	Moulded Case Switch
Generator (or Source 2) Switching Device:	Moulded Case Switch
Approval Standard:	CSA C22.2 No. 178/ UL1008 -non SE ATS

System Options:

CTK0400	400A Current Tranformer Kit
LPM	Transfer Switch Load Power Metering CT K
PPR-10	Programmable Power Relay c/w 10A Form C
AUX-BG	Bypass Auxiliary Contact - Generator Side
AUX-BU	Bypass Auxiliary Contact - Utility Side

ATTACHED DOCUMENTS ARE DRAFT FOR REVIEW ONLY AND ARE SUBJECT TO CHANGE WITHOUT NOTICE.

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE STANDARD TERMS AND CONDITIONS.

THE INFORMATION CONTAINED IN THESE DRAWINGS IS THE PROPERTY OF THOMSON POWER SYSTEMS, IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

NOTE:
ANY PROGRAM SETTINGS SHOWN REFLECT FACTORY DEFAULT SETTINGS ONLY. FINAL SETTINGS WILL BE REQUIRED TO BE SET BY THE COMMISSIONING AUTHORITY. FAILURE TO DO SO MAY RESULT IN EQUIPMENT FAILURE.

SHOP DRAWING / SUBMITTAL REVIEW

☐ APPROVED ☐ APPROVED WITH CHANGES NOTED

☐ REVISE AND RESUBMIT ☐ REJECTED _____

SUBMITTAL WAS RECEIVED FOR DESIGN CONFORMITY AND GENERAL CONFORMANCE TO CONTRACT DOCUMENTS ONLY. THE CONTRACTOR FOR CONFIRMING AND CORRELATING DIMENSIONS AT JOB SITES FOR TOLERANCES, CLEARANCES, QUANTITIES, FABRICATION PROCESSES AND TECHNIQUES OF CONSTRUCTION, COORDINATION OF HIS WORK WITH OTHER TRADES AND FULL COMPLIANCE WITH CONTRACT


BY _____ DATE _____

COMPANY NAME _____


CITY _____ STATE/PROV _____

9087A - 198th Street, Langley, BC Canada V1M 3B1
Email: info@thomsonps.com www.thomsonps.com


REGAL®




FRONT VIEW




LHS VIEW
(SIDE COVER REMOVED)



INTERIOR FRONT VIEW
(DOOR NOT SHOWN)



VIEWED FROM REAR OF DOOR
(INSIDE OF ATS SECTION)



BASIC MODEL TS87xA	STANDARD ATS				
	CLOSING AND WITHSTAND RATING AVAILABLE AMPS (RMS) CLOSING & WITHSTAND RATINGS SHOWN ARE ONLY FOR ATS UTILITY AND/OR GENERATOR POWER SWITCHING DEVICE(S) THAT ARE NOT FACTORY SUPPLIED WITH INTEGRAL OVERCURRENT PROTECTION. PLEASE REFER TO PRODUCT INSTRUCTION MANUAL FOR FURTHER INFORMATION ON UPSTREAM PROTECTION REQUIREMENT.				
	MAX. VOLTAGE	RATED CURRENT (A)	@240V	@480V	@600V
TS 87xA-400	600	400	65,000	50,000	35,000

SHORT CIRCUIT CURRENT RATING–BYPASS SECTION				
SHORT CIRCUIT CURRENT RATINGS – MCS STYLE (ABB) 3, 4 & 5–BREAKER SLIDEBAR INTERLOCKED "CANADIAN" BYPASS LOWEST KA RATINGS APPLICABLE TO MCS'S & MCCB'S THAT ARE USED IN BYPASSES (CERTIFIED TO CSA #31)				
ATS RATING (AMPS)	BYPASS BREAKER FRAME (ABB)	@240V	@480V	@600V
400	T6H	65,000	50,000	35,000

CONNECTION DATA		
400A ATS	UTILITY (SRC1)	1–2C, 2/0–500MCM Cu/Al PER PHASE
	GENERATOR (SRC2)	1–2C, 2/0–500MCM Cu/Al PER PHASE
	LOAD	1–2C, 2/0–500MCM Cu/Al PER PHASE
	NEUTRAL	1–2C, 2/0–500MCM Cu/Al PER SOURCE
	GROUND	6C, #6–250MCM Cu/Al

GENERAL NOTES	
1	POWER SWITCHING DEVICES ARE MECHANICALLY INTERLOCKED SO THAT ONLY ONE DEVICE IS CLOSED AT A TIME
2	BYPASS SWITCHING DEVICES ARE MECHANICALLY INTERLOCKED THROUGH A SLIDE BAR INTERLOCK. BYPASS IS CLOSED TRANSITION. REFER BELOW CHART
3	NEMA 2 ENCLOSURE C/W DRIPHOOD
4	NEMA 12 ENCLOSURE C/W GASKETING
5	FOR 1 PHASE, 3 WIRE SOLID NEUTRAL APPLICATION, CONNECT PHASE TO 'A' & 'B'. OMIT 'C'
6	FOR 1 PHASE, 3 WIRE SWITCHED NEUTRAL APPLICATION, CONNECT PHASE TO 'A' & 'B'. CONNECT NEUTRAL TO 'C'
7	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

2.5" x 5"

W1

DANGER
PELIGRO



Arc Flash and Shock Hazard
Will cause severe injury or death. Wire than one live circuit - see diagram. Disconnect all sources of supply before servicing. This equipment must be installed and serviced only by qualified electrical personnel utilizing safe work practices and appropriate Personal Protective Equipment (PPE). Failure to comply may result in injury or death! Refer to NFPA 70E for minimum PPE requirements.

Risque d'Arc Electrique et d'Electrocution
Peut causer des blessures graves ou la mort. Plus d'un circuit sous tension - voir schema. Couper toutes les sources d'alimentation avant de faire lentretien et les reparations. Ce materiel doit etre installé et entretenu uniquement par un electricien qualifié. Ce dernier doit connaitre les pratiques de travail sécuritaires et porter l'équipment de protection individuelle approprié. Le non respect mai entrainer des blessures ou la mort! Reportez-vous a NFPA 70E pour le manuel des exigences minimales PPE.


Riesgo de Arco y Choque Eléctrico
Se causarán lesiones graves o muerte. Más de un circuito energizado - ver diagrama. Desconectar todas las fuentes de suministro antes de hacer mantenimiento. Este equipo solo se debe instalar y mantener por personal calificado, usando medidas de seguridad y equipo de protección personal adecuados. No seguir estas recomendaciones puede causar lesiones o muerte! Consultar la NFPA 70E para los requisitos mínimos del equipo de protección personal (PPE).

QTY = 1

SWITCHING DEVICE	INTERLOCK POSITION				
	UTILITY BYPASS	TRANSITION INTERLOCKING			GENERATOR BYPASS
	1	2	3	4	5
NB	⊠	⊠			
NI		⊠	⊠		
LI		⊠	⊠	⊠	
GI			⊠	⊠	
GB				⊠	⊠

BYPASS SLIDE BAR INTERLOCK

⊠ = SWITCH CLOSURE ALLOWED



SINGLE LINE DIAGRAM

FOR REVIEW ONLY

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5OC–C–1
GRID COORDINATE
SHEET No.

DRAWING No.	REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
1	GENERAL NOTES AND LOGO UPDATED	AP	OG	17–10–24


THOMSON POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 870
PHYSICAL LAYOUT & INSTALLATION DETAILS
400A, 2P/3P, NEMA 1/2/12 SD, MCS DOUBLE BYPASS, STD

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER	THOMSON POWER SYSTEMS		
CUSTOMER ORDER No.	WORK ORDER No.		
C–XXXXX	W–XXXXX		
DRAWN BY	AUTH BY	DATE	REV
AP	OG	16–01–26	1
DRAWING/FILE No.		SHEET	
MBS870M136		10A	

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.



COLOR KEY	
BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

GENERAL NOTES	
1	FOR 1 PHASE, 3 WIRE SOLID NEUTRAL APPLICATION, CONNECT PHASE TO 'A' & 'B'. OMIT 'C'
2	FOR 1 PHASE, 3 WIRE SWITCHED NEUTRAL APPLICATION, CONNECT PHASE TO 'A' & 'B'. CONNECT NEUTRAL TO 'C'
3	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
4	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

FOR REVIEW ONLY

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
5 0 C – C – 1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
4	GENERAL NOTES AND LOGO UPDATED	AP	OG	17–10–24
3	REMOVED T–STYLE OPTION	SR	OG	17–08–16
2	PRODUCT RANGE CHANGED TO 100–800A	SR	OG	17–01–24
1	WIRE HARNESS UPDATED AS PER ECR–0114744	AP	OG	16–07–22


THOMSON POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 870
MCS BYPASS AC SCHEMATIC, T–STYLE / S–STYLE, STD
100 – 800A

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER THOMSON POWER SYSTEMS
CUSTOMER ORDER No. C–XXXXXX
WORK ORDER No. W–XXXXXX
DRAWN BY AP | AUTH BY OG | DATE 16–01–26 | REV 4
DRAWING/FILE No. MBS870E100
SHEET 20A

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.



GENERAL NOTES	
1	CONTROL TRANSFORMER IS RATED FOR 100VA FOR MCS ATS & 200VA FOR ATS MECHANISM USING TRIP & CLOSE COILS
2	100VA CONTROL TRANSFORMER DOES NOT INCLUDE A 2ND 120VAC SECONDARY WIRING (X3/X4)
3	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
4	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

VOLTAGE (X DENOTES HIGH POLARITY MARKER)

PT TAP	208	240	380	400	416	480	600
H1	X	X				X	X
H2			X	X			
H3	X						
H4					X	X	
H5		X			X		X

COLOR KEY	
BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
SOC-C-1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
4	TSC900 CONFIGURATION UPDATED	AP	OG	17-11-17
3	GENERAL NOTES AND LOGO UPDATED	AP	OG	17-10-24
2	UPDATED MOS CONTROL PLATE PID	SK	OG	17-08-16
1	WIRE HARNESS UPDATED AS PER ECR-0114744	AP	OG	16-07-22

THOMSON POWER SYSTEMS


AUTOMATIC TRANSFER SWITCH
TSC 900 TRANSFER SWITCH CONTROLLER
ATS AC CONTROL SCHEMATIC, STD
100 – 4000A

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER	THOMSON POWER SYSTEMS
CUSTOMER ORDER No.	C-XXXXXX
WORK ORDER No.	W-XXXXXX
DRAWN BY	AP
AUTH BY	OG
DATE	16-01-26
REV	4
DRAWING/FILE No.	TSC900E100
SHEET	20B

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.



TSC900 FACTORY DEFAULT SETTINGS

NOTE : REFER TO OPTION DRAWINGS FOR APPLICABLE CHANGES TO FACTORY DEFAULT SETTINGS

PARAMETER	DEFAULT	RANGE
GENERATOR (SOURCE 2) START DELAY	3 SEC	0–60 SEC
GENERATOR (SOURCE 2) WARM UP DELAY	2 SEC	0–3600 SEC
GENERATOR (SOURCE 2) COOL DOWN DELAY	300 SEC	0–3600 SEC
UTILITY (SOURCE 1) RETURN DELAY	300 SEC	0–3600 SEC
TRANSFER NEUTRAL DELAY	3 SEC	0–120 SEC
TRANSFER FAIL DELAY	30 SEC	0–120 SEC
EXERCISE TIMER	PROG.	PROG.
GENERATOR (SOURCE 2) UNDER VOLTAGE DELAY	3 SEC	0–10 SEC
GENERATOR (SOURCE 2) UNDER FREQUENCY DELAY	5 SEC	0–10 SEC
GENERATOR (SOURCE 2) UNDER VOLTAGE PICK UP	90%	75–100%
GENERATOR (SOURCE 2) UNDER VOLTAGE DROP OUT	85%	70–95%
UTILITY (SOURCE 1) UNDER VOLTAGE DELAY	1 SEC	0–10 SEC
UTILITY (SOURCE 1) UNDER VOLTAGE PICK UP	90%	75–100%
UTILITY (SOURCE 1) UNDER VOLTAGE DROP OUT	85%	70–95%

ALL SETTINGS ARE FIELD ADJUSTABLE UNLESS NOTED. REFER TO THE TSC900 MANUAL FOR A COMPLETE LISTING OF ALL TSC900 SETTINGS.

PARAMETER	MODBUS RTU SETTINGS
SLAVE ID	1
PORT NAME	COM 4
BAUD RATE	57600
PARITY	NONE
STOP BUS	ONE

GENERAL NOTES

1	"USD OPEN" AND "GSD OPEN" DIGITAL INPUTS ARE REQUIRED ONLY FOR ATS MECHANISMS USING TRIP AND CLOSE COILS. REFER TO SHEET 20A FOR DETAILS
2	"43TMS IN MANUAL MODE" DIGITAL INPUT IS REQUIRED ONLY FOR CLOSED TRANSITION ATS(s)
3	COLOR CODE: ALL WIRING IS GREY UNLESS NOTED. SAFETY GROUND WIRES ARE GREEN
4	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

COLOR KEY

BK	BLACK
BE	BLUE
BN	BROWN
GN	GREEN
GY	GREY
OR	ORANGE
PE	PURPLE
R	RED
W	WHITE
Y	YELLOW
V	VIOLET

FOR REVIEW ONLY

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
50C–C–1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
4	TSC900 CONFIGURATION UPDATED	AP	OG	17–11–17
3	GENERAL NOTES AND LOGO UPDATED	AP	OG	17–10–24
2	UPDATED MOS CONTROL PLATE PID	SK	OG	17–08–16
1	WIRE HARNESS UPDATED AS PER ECR–0114744	AP	OG	16–07–22

THOMSON™ POWER SYSTEMS


AUTOMATIC TRANSFER SWITCH
TSC 900 TRANSFER SWITCH CONTROLLER
ATS DC CONTROL SCHEMATIC, STD
100 – 4000A


DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER THOMSON POWER SYSTEMS
CUSTOMER ORDER No. C–XXXXXX
WORK ORDER No. W–XXXXXX
DRAWN BY AP | AUTH BY OG | DATE 16–01–26 | REV 4
DRAWING/FILE No. TSC900E101
SHEET 20C

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

☐ PPR–10 OPTION





PR1			
T1	TYPE	T2	REF
4	+h	7	A–5
1	-w		
5	+h	8	A–6
2	-w		
6	+h	9	A–7
3	-w		

PR2			
T1	TYPE	T2	REF
4	+h	7	B–5
1	-w		
5	+h	8	B–6
2	-w		
6	+h	9	B–7
3	-w		


PR3			
T1	TYPE	T2	REF
4	+h	7	C–5
1	-w		
5	+h	8	C–6
2	-w		
6	+h	9	C–7
3	-w		

PPR–10 OPTION NOTES	
1	FOR POWER RELAY FUNCTIONAL DESCRIPTION REFER TO FACTORY DEFAULT DIGITAL OUTPUT FUNCTION TABLE ON ATS DC CONTROL SCHEMATIC
2	THE NUMBER OF RELAYS SUPPLIED WILL BE PER ORDERED QUANTITY
3	CUSTOMER TO WIRE DIRECTLY TO RELAY TERMINALS
4	SPECIFIED QUANTITY OF PROGRAMMABLE POWER RELAYS ARE WIRED FOR CUSTOMER AS PER OPTION LIST
5	DC SUPPLY FOR THE RELAYS, BY DEFAULT IS 24VDC. PLEASE SPECIFY THE VOLTAGE RATING OTHER THAN 24VDC ON OPTION LIST

BILL OF MATERIALS		
PART DESCRIPTION	PART ID	QTY
RELAY, 24VDC COIL, 11 PIN SQ., /W LED	004095	3
RELAY SOCKET, 11 PIN, SQ., RAIL MOUNT	000399	3
FUSE HOLDER, 1P, 30A, 600V, 200KA, CC	002374	1
FUSE, 3A, 600VAC, CLASS CC	003633	1
TERM. BLK, RAIL MNT, 40A, 600V, WK4/U,	001881	10

GENERAL NOTES	
1	FOR MCS/MOS/PCS TYPE ATS, MOUNT THE RELAYS ON SIDE COVER WHERE SPACE PERMITS
2	FOR ICS ATS MOUNT THE RELAYS ON BACK PAN WHERE EVER THE SPACE PERMITS
3	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

PPR RELAY
[TYPICAL]



FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: ____ DATE: ____

CROSS REFERENCE LEGEND
50C – C – 1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
4	DRAWINGS UPDATED FOR TS970 PRODUCT LINE APPLICATION	SK	OG	18-03-08
3	GENERAL NOTES AND LOGO UPDATED	AP	OG	17-10-24
2	MOUNTING INSTRUCTION UPDATED	SK	OG	16-09-21
1	WIRE HARNESS UPDATED AS PER ECR-0114744	AP	OG	16-07-22


THOMSON POWER SYSTEMS™


AUTOMATIC TRANSFER SWITCH
MODEL TS 870 / 880 / 970
STANDARD OPTION SCHEMATIC – PPR–10
POWER AUX RELAY

CUSTOMER THOMSON POWER SYSTEMS
CUSTOMER ORDER No. C–XXXXXX
WORK ORDER No. W–XXXXXX
DRAWN BY AP | AUTH BY OG | DATE 16–01–26 | REV 4
DRAWING/FILE No. TSC900E300
SHEET 30A


© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

☐ CTKXXXX OPTION





ATS CONTROL PLATE



PART ID	OPTION KITS
CTK0100	100 AMPS
CTK0150	150 AMPS
CTK0250	200–250 AMPS
CTK0400	400 AMPS
CTK0600	600 AMPS
CTK0800	800 AMPS
CTK1200	1000–1200 AMPS
CTK1600	1600 AMPS
CTK2000	2000 AMPS

GENERAL NOTES	
1	CT'S TO BE MOUNTED ON THE LOAD SIDE OF THE ATS. CUSTOMER TO VERIFY POLARITY BEFORE CONNECTING THE CT SECONDARIES TO THE TRANSFER SWITCH CONTROLLER.
2	ATS CONTROL PLATE MOUNTED ON THE BACK SIDE OF DOOR FOR MCS / MOS / PCS AND FOR ICS MOUNTED ON THE BACKPAN.
3	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

BILL OF MATERIALS FOR CABLE HARNESS

PART DESCRIPTION	PART ID	QTY
WIRE, 18AWG, GREY, TINNED, TEW, 600V,	002027	600 INCHES
TERM. BLK, RAIL MNT, 40A, 600V, WK4/U,	001861	6
TERM. BLK, ENDPLATE, WK 2.5-4/U,	001872	1
SCREW, SHT-MTL, RDH, ROB #8 X 5/8"	002070	2
MTG-RAIL, TYPE-35, SLOTTED(7.5X2-METERS)	002795	6
TERM. BLK, PARTITION PLATE, WK2.5-4/U,	004189	2
CONN, MINI-FIT, J, 94V-2, 2X1-WAY,FEMALE (J5/J6/J7)	012654	3
CONN, FEMALE CRIMP, MINI-FIT, JR. SERIES	010954	6
WIRE SLEEVE, 0.5", EXPANDO PT PLUS,	000458	175 INCHES
TERM BLK CROSS CONN.W SCRW WK4/U SR7	009677	3
TERM. BLK, EARTH TERMINAL, 10-24 AWG	005211	2

FOR REVIEW ONLY

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: ____ DATE: ____

CROSS REFERENCE LEGEND
50C-C-1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
4	DRAWINGS UPDATED FOR TS970 PRODUCT LINE APPLICATION	SK	OG	18-03-08
3	GENERAL NOTES AND LOGO UPDATED	AP	OG	17-10-24
2	MOUNTING INSTRUCTION UPDATED	SK	OG	16-09-21
1	WIRE HARNESS UPDATED AS PER ECR-0114744	AP	OG	16-07-22


THOMSON POWER SYSTEMS™

AUTOMATIC TRANSFER SWITCH
MODEL TS 870 / 880 / 970
STANDARD OPTION SCHEMATIC – CTKXXXX
CURRENT TRANSFORMER KIT

CUSTOMER THOMSON POWER SYSTEMS
CUSTOMER ORDER No. C-XXXXXX | WORK ORDER No. W-XXXXXX
DRAWN BY AP | AUTH BY OG | DATE 16-01-26 | REV 4
DRAWING/FILE No. TSC900E304 | SHEET 30E


© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

☐ AUX BU/ BG OPTION




FOR MCS BYPASS ATS APPLICATION

☐ AUX BU OPTION



FOR MCS BYPASS ATS APPLICATION

☐ AUX BG OPTION




FOR MCS BYPASS ATS APPLICATION

BILL OF MATERIALS FOR MCS DOUBLE SIDE BYPASS			
PART DESCRIPTION	BREAKER	PART ID	QTY
BREAKER, 2-AUX CONTACT, TS3	100-200A	012350	5
BREAKER, AUX CONTACT CONN., TS3	100-200A	012357	5
BREAKER, 2-AUX CONTACT, T4-6	250-800A	012002	5


BILL OF MATERIALS FOR MCS SINGLE SIDE BYPASS			
PART DESCRIPTION	BREAKER	PART ID	QTY
BREAKER, 2-AUX CONTACT, TS3	100-200A	012350	3
BREAKER, AUX CONTACT CONN., TS3	100-200A	012357	3
BREAKER, 2-AUX CONTACT, T4-6	250-800A	012002	3

☐ AUX BU OPTION (ICS BYPASS – FIXED)




FOR DRAWOUT ATS SECTION AND FIXED BYPASS SECTION APPLICATION

☐ AUX BG OPTION (ICS BYPASS – FIXED)




FOR DRAWOUT ATS SECTION AND FIXED BYPASS SECTION APPLICATION

☐ AUX BU OPTION (ICS BYPASS – DRAWOUT)



FOR DRAWOUT ATS SECTION AND DRAWOUT BYPASS SECTION APPLICATION

☐ AUX BG OPTION (ICS BYPASS – DRAWOUT)



FOR DRAWOUT ATS SECTION AND DRAWOUT BYPASS SECTION APPLICATION

GENERAL NOTES	
1	GEN SIDE / UTILITY SIDE / DOUBLE SIDE BYPASS AUX OPTION FOR MCS ATS TYPE IS PROVIDED AS PER OPTION LIST
2	FOR MCS BYPASS, USE SUITABLE PART ID FOR AUX CONTACT BASED ON THE AMPERAGE RATING AS MENTIONED IN BILL OF MATERIAL
3	FOR MCS TS3 FRAME, USE AUX CONTACT AND ITS CONNECTION AS MENTIONED IN BILL OF MATERIAL. FOR T4-T6 FRAME, AUX. CONNECTION INCLUDED IN AUX CONTACT PART ID
4	FIXED / DRAW OUT BYPASS AUX OPTION FOR ICS ATS TYPE IS PROVIDED AS PER OPTION LIST
5	ICS ATS & BYPASS CONTACTS UTILIZED FROM EXISTING 4A-4B AUX CONTACTS WHICH ARE ORDERED WITHIN THE BREAKER
6	REFER COVER PAGE / SELECTED OPTION LIST FOR PROJECT SPECIFIC DETAILS

FOR REVIEW ONLY

☐ APPROVED FOR CONSTRUCTION
☐ MASTER COPY ☐ REFERENCE COPY ____ OF ____
☐ MULTIPLE UNIT WORK ORDER
☐ RELEASED FOR INFORMATION
AUTH. BY: _____ DATE: _____

CROSS REFERENCE LEGEND
SOC-C-1
GRID COORDINATE
SHEET No.

DRAWING No. | REFERENCE DRAWINGS

No.	REVISIONS	BY	AUTH	DATE
3	GENERAL NOTES AND LOGO UPDATED	AP	OG	17-10-24
2	MOUNTING INSTRUCTION UPDATED	SK	OG	16-09-21
1	WIRE HARNESS UPDATED AS PER ECR-0114744	AP	OG	16-07-22

THOMSON™ POWER SYSTEMS

AUTOMATIC TRANSFER SWITCH
MODEL TS 870 / 880
STANDARD OPTION SCHEMATIC – BYPASS AUX
ATS BYPASSED OPTION

DRAWINGS AND OR OTHER TECHNICAL INFORMATION SUPPLIED BY THOMSON POWER SYSTEMS AS A PART OF A SALE OF EQUIPMENT ARE FOR THE PURCHASER'S USE SOLELY IN CONJUNCTION WITH THAT EQUIPMENT, UNLESS SPECIFICALLY AGREED TO OTHERWISE AS A PART OF THE TERMS OF SALE.

CUSTOMER	THOMSON POWER SYSTEMS		
CUSTOMER ORDER No.	C-XXXXXX	WORK ORDER No.	W-XXXXXX
DRAWN BY	AP	AUTH BY	OG
DATE	16-01-26	REV	3
DRAWING/FILE No.	TSC900E352	SHEET	30M

© THE INFORMATION ON THIS DRAWING IS THE PROPERTY OF THOMSON POWER SYSTEMS. IT IS NOT TO BE USED DETRIMENTALLY TO OUR INTERESTS.

Date: Jun 12, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

SE-07R2 (ELE-007)
PO-P18-120 Frontier

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [X] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Drawing E601 Loadbank

These drawings have a slight change to them based on the engineers comments. There is an emergency stop located on the electrical and mechanical drawings. Please confirm these are good.
Also – the lead time is looking at 5 weeks currently.

Those were already returned to you. We did receive a resubmit on Friday but we're not sure why. Our last review did not require a resubmit. There is nothing additional for us to review.

In regards to the note we provided, it is the Contractor's responsibility to ensure the emergency stop button is provided as per the specs.

Arctic Electrical needs to coordinate with the supplier.

No further review on our end is required.

Kristen S. Smith, P.Eng.

Senior Associate, Electrical Team Lead Northern Canada

Direct: 709 576-1458 ext 5761242

Mobile: 867 765-8237

Kristen.Smith@stantec.com

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the contractor.

Do not hesitate to contact me if you have any questions or concerns.

Date: July 26, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 26, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-07R1 (ELE-007)
PO-P18-120 Frontier

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [X] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Drawing E-601-Load Bank

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-07R1

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec


- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-30
BY Konrad Goluch


Power bank shall have exterior emergency power off switch on enclosure as spec 26 32 14 2.7 .5

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the contractor.

Do not hesitate to contact me if you have any questions or concerns.



KEY	DESCRIPTION	MFR PART NUMBER
MOTOR	0.75 HP-1725-TEFC-600/3/60 F56	LEESON A0090178
FAN FRAME	EMERSON 24"	FRAME-EMERSON 2DVP24
FAN BLADE	ALUMINUM 24"	DAYTON 3GTG4 CAST AL
MF1-MF3	FUSE 5A, 600VAC FAST ACTIVE	LITTELFUSE ATM5
MC	MOTOR CONTACTOR 3P, 7.5HP, 600V	MC18-120
M.OL	MOTOR OVERLOAD 1-1.6A	CG GT32 1-1.6
AFS	AIR FLOW SWITCH SPDT 5A/120	KFR-1, 90 PA
CF1-CF2	FUSE 1A, 600VAC FAST ACTIVE	LITTELFUSE ATM1
CF3	FUSE 5A, 250VAC FAST ACTIVE	LITTELFUSE OTM5
F20	FUSE 20A, 600VAC FAST ACTIVE	LITTELFUSE ATM20
F25	FUSE 25A, 600VAC FAST ACTIVE	LITTELFUSE ATM25
C1-C18	LOAD CONTACTOR 3P, 40A, 600V	MC32-120AC
R1, R2	INDICATOR LIGHT	AUS 22 RED LED
TR	TRANSFORMER 600-120, 250VA	HAMMOND SP250ACP
LR26	LOAD RESISTOR	NICHROME 60-20-26
LR19.6	LOAD RESISTOR	NICHROME 60-16.5-19.6
TLS	TEMPERATURE LIMIT SWITCH	SRL-260 MANUAL RESET
HTS	HIGH TEMP. SHUTDOWN RELAY	CG RPY002-120AC
S	ON-OFF SWITCH	AUS 22 BLACK
S1-S7	ON-OFF SWITCH ILLUMINATED	AUS 22 AMBER LED
PB1	ILLUM. PUSH-BUTTON N.O.	AUS 22 MM GREEN LED-120AC
PB2	ILLUM. PUSH-BUTTON N.C.	AUS 22 MM RED LED-120AC
HT	HEATER 120 VAC, 100W	SAIPWELL HG 14003
TH	THERMOSTAT N/C 0-60C	STEGO 01146.9-99
CC	CONTROL CONTACTOR 3P, 18A, 600V	MC18-120
DM1, DM2	DAMPER MOTOR C/W LIMIT SWITCH	SIEMENS GCA226.1U-120
ES	EMERGENCY STOP SWITCH	IDEC 22 MM LATCHING
□ TB1	REMOTE CONTROL TERMINALS	PHOENIX UK3N
◇ TB2	LOAD BANK TERMINALS	PHOENIX UK3N
⬡ L	COPPER BUSBAR PLATED	8" X 1" X 0.25"



NOTES:

1. BROKEN LINE WIRING IS BY INSTALLER.
2. LBCB SUPPLY BY OTHERS.
3. INTER-CONNECTIONS TERM. 1 TO 15 - #14 AWG.
4. CHECK FAN ROTATION FOR CORRECT OPERATION OF AIRFLOW DIRECTION.

REV.	BY	DATE	DESCRIPTION

INFORMATION INCLUDED IN THIS DRAWING IS PROPRIETARY AND IS NOT TO BE REPRODUCED, DISTRIBUTED OR DISCLOSED EXCEPT AS SPECIFICALLY AUTHORIZED IN WRITING BY JP POWER TECHNOLOGY INC.

SERIAL NO	F802
PO# 52855, JUNE 19, 2018	
TESTED BY	XX
DATE	JULY 20, 2018
DWG. NO	F802-1


JP POWER TECHNOLOGY INC.
EDMONTON, ALBERTA, TEL. 780-456-9167, FAX 780-478-7135


SIZE B

TITLE: OUTDOOR RESISTIVE LOAD BANK
MODEL: SM-250D7
ELECTRICAL SCHEMATIC


CUSTOMER: FRONTIER POWER PRODUCT EDMONTON

FRONT VIEW






SIDE VIEW




REMOTE CONTROL
H-14" (356), W-12" (305), H-6 (152)

TOP VIEW



BOTTOM VIEW OF MOUNTING LEGS



NOTES:

1. ALL DIMENSIONS ARE SHOWN IN INCHES (MILLIMETERS)
2. WEIGHT-300 LBs, 136 KG
3. MAXIMUM AIR INLET TEMPERATURE IS 100F, 38C
4. MINIMUM CLEARANCE FOR AIR DISCHARGE-24 FT (7.3 MT)
5. REMOTE CONTROL PANEL- CEMA 1, GRAY 61 POWDER COAT PAINT
6. LOAD BANK ENCLOSURE- CEMA 3, 304 SS. GA18, NATURAL FINISH.

REV.	BY	DATE	DESCRIPTION

INFORMATION INCLUDED IN THIS DRAWING IS PROPRIETARY AND IS NOT TO BE REPRODUCED, DISTRIBUTED OR DISCLOSED EXCEPT AS SPECIFICALLY AUTHORIZED IN WRITING BY JP POWER TECHNOLOGY INC.

SERIAL NO F802	JP POWER TECHNOLOGY INC.
PO# 52855, JUNE 19, 2018	EDMONTON, ALBERTA, TEL. 780-456-9167, FAX 780-478-7135
TESTED BY XX	SIZE B — OUTDOOR RESISTIVE LOAD BANK
DATE JULY 20, 2018	MODEL: SM-250D7
DWG. NO F802-2	TITLE ENCLOSURE LAYOUT
CUSTOMER	FRONTIER POWER PRODUCT EDMONTON



PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 50 00 - Lighting

Date: Jun 25, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 26, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-04
PO-P18-124

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [x] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 26 50 00 Lighting

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.

BDA LIGHTING GROUP

Jun 25, 2018

Guillevin Ottawa
175 Richmond Road
Ottawa ON K1Z 6W3

RE: Iqaluit Water Treatment Plant

Qty	Type	MFG	Part
8	401	HUBBELL LIGHTING	QSP2-24L-50-5K7-4-UNV-BL
6	404	Peerless Electric	NSL-RA-4-60-50K-W-WG-347
19	405	Peerless Electric	NSL-RA-4-60-50K-W-WG-347
1	402		FMV11LCY/UNV34 76
21	403		VMV5L2A/UNV34
47	406		EGW/4/S/LED/HO/CW/UE

AEN Note: These are correct counts

Contractor to review quantity prior to ordering

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- ☐ Architectural
- ☐ Structural
- ☐ Mechanical
- ☑ Electrical
- ☐ Other

Stantec

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

- ☐ REVIEWED
- ☑ REVIEWED, AS NOTED
- ☐ REVISE AND RESUBMIT
- ☐ NOT REVIEWED

DATE June 26, 2018

BY Chester Martinez, E.I.T.

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** QSP2-24L-50-5K7-4-UNV-BL Notes:	**Type:** 401 BDA18-23511

GEOPAK SERIES SIZE 2 LED

Architectural Wallpack

TRP2/RDI2/QSP2 NEW

Cat.#

Job | Type

HUBBELL Outdoor Lighting

Approvals

SPECIFICATIONS

Applications:
Medium sized architectural wallpacks in three stylish shapes accentuate building architecture and provide excellent illumination and uniformity

Construction:
- Die-cast aluminum housing and door
- Seven powder coat standard finishes, plus custom color options

LED:
- 24 or 32 high power LEDs deliver up to 10,800 lumens
- Up to 146 Lumens per watt
- Different lenses offer a variety of distribution patterns - Type I, II, III and IV (Forward throw)
- 3000K - 70 CRI, 4000K - 70 CRI, and 5000K - 70 CRI, CCT nominal

Electrical:
- Optional Dual Drivers & Dual Power Feeds for 50, 70 and 90 watt versions
- 120-277, 347 and 480 voltage, 50/60Hz
- Power factor ≥ 90%
- THD (Total Harmonic Distortion) <20%
- Ambient operating temperature -40°C to 40°C
- 20kA surge protection (series); Automatically takes fixture off-line when device is consumed

Installation/Mounting:
- Quick-mount adapter with gasket seal provides easy installation to wall or to recessed junction box (4" square junction box). Fixture attaches by two Allen-head hidden fasteners for tamper resistance.
- Black box accessory available for surface conduit application
- Optional inverted/up mounting (must specify when ordering)

Options/Controls:
- Drivers are 0-10V dimming standard
- Universal button photocontrol for dusk to dawn energy savings
- Photocell and occupancy sensor options available for complete on/off and dimming control
- Occupancy sensor options available for complete on/off and dimming control
- In addition, GeoPak Size 2 can be specified with SiteSync™ wireless control system for reduction in energy and maintenance cost while optimizing light quality 24/7. See ordering information or visit www. hubbell-lighting.com/sitesync for more details

Listings:
- IP65 rated housing
- DesignLights Consortium® (DLC) qualified. Please refer to the DLC website for specific product qualifications at www.designlights.org
- Zero uplight (U0), dark sky, neighbor friendly
- Drivers IP66 and RoHS compliant


Battery Backup:
- Intergral Battery Backup provides emergency lighting for the required 90 minute path of egress.
- Includes a long-life Lithium Iron Phosphate battery with optional battery heater for cold temperature application.
- Utilizes 4 LEDs in emergency mode with 657 lumens. Each of the 4 LEDs in emergency are designed to function independently in the unlikely event of a single LED malfunction
- Spectron® self-testing/self-diagnostic electronics are included standard
- Independent dedicated driver and LED array for battery/emergency mode operation.

Warranty:
For more information visit:
http://www.hubbelloutdoor.com/resources warranty/

PRODUCT IMAGE(S)



DIMENSIONS



SHIPPING INFORMATION

Catalog Number	G.W(kg)/ CTN	Carton Dimensions		
		Length Inch (cm)	Width Inch (cm)	Height Inch (cm)
QSP2	17 (7.7)	20.5 (52)	10.5 (26)	11 (28)
RDI2	18 (8.2)	20.5 (52)	9.5 (24)	12 (30)
TRP2	16 (7.3)	18.5 (47)	9.5 (24)	11.5 (29)

CERTIFICATIONS/LISTINGS

c UL us

DLC QPL LISTED

ida

*3000K and warmer CCTs only

ORDERING INFORMATION

ORDERING EXAMPLE: TRP2-24L30-3K7-2-UNV-DB

____ - ____ - ____ - ____ - ____ - ____ - ____ - ____

FAMILY	LEDS - WATTAGE	CCT	DISTRIBUTION	VOLTAGE	FINISH	CONTROL OPTIONS	OPTIONS
TRP2 Trapezoid	24L-30 24 LEDs, 30 watts	3K7 3000K, 70CRI	1 Type I	UNV 120-277V	BL Black Textured	PC Button Photocontrol	SF[3] Single Fuse & Fuse Holder
RDI2 Radius	24L-50 24 LEDs, 50 watts	4K7 4000K, 70CRI	2 Type II	120 120V	DB Dark Bronze Textured	SCP[4,5] Programmable occupancy sensor, factory default is 10% light output	DF[3] Double Fuse & Fuse Holder
QSP2 Qtr-sphere	24L-70 24 LEDs, 70 watts	5K7 5000K, 70CRI	3 Type III	208 208V	GT Graphite Textured	SCO[4] Sensor Control, On/Off	E[3] Battery Pack (0ºC)
	24L-90 24 LEDs, 90 watts		4 Type IV	240 240V	GYS Light Gray Smooth	SWP[3,7] SiteSync Pre-Commission	EH[3] Battery Pack (-30oC) with heater
	32L-70 32 LEDs, 70 watts			277 277V	PS Platinum Silver Smooth	SWPM[3,4,7,8] SiteSync Pre-commission w/Occupancy Sensor	2DR[6] Dual Drivers
	32L-90 32 LEDs, 90 watts			UHV[1] 347/480V	WH White Textured	SPEC SCP/SCO & SWPM MOUNT HEIGHT	2PF[6] Dual Power Feeds
				347[1] 347V	CC Custom Color	-8F Up to 8ft mount height	CS Comfort Shield
				480[1] 480V		-20F Up to 20ft mount height	

SECONDARY MOUNTING
BLANK Downlight Only
NV[2] Inverted/Up Mounting

[1] 70 & 90 watt versions only
[2] Not available with SCP, SCO or SWPM sensor options
[3] Must specify voltage (120, 277 or 347V only for SWP & SWP, 120 or 277V only for E & EH)
[4] PCU option not applicable, included in sensor
[5] Must order minimum of one remote control to program dimming settings, 0-10V fully adjustable dimming with automatic daylight calibration and different time delay settings
[6] Not available with 30w version
[7] Must specify group and zone information at time or order. See www.HubbellLighting.com/products/sitesync for future details
[8] Specify time delay; dimming level and mounting height


© 2017 HUBBELL OUTDOOR LIGHTING, All Rights Reserved • For more information visit our website: **www.hubbelloutdoor.com** • Printed in USA

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** QSP2-24L-50-5K7-4-UNV-BL Notes:	**Type:** 401 BDA18-23511


ACCESSORIES (ORDER SEPARATELY)

Catalog Number	Description
SCP-REMOTE*	Remote control for SCP option. Order at least one per project to program and control dimming settings
BB-GEO-XX	Black box with 4 - 1/2" threaded conduit holes, specify finish by replacing "XX" with finish selection, eg. Dark Bronze "DB"
SWUSB**	SiteSync loaded on USB flash drive (Windows based only)
SWTAB**	SiteSync Windows Tablet
SWBRG+	SiteSync Wireless Bridge Node

* Must order minimum of one remote control to program dimming settings, 0-10V fully adjustable dimming with automatic daylight calibration and different time delay settings.
** When ordering with SiteSync, one of the following interface options must be chosen an ordered separately. Each option contains the SiteSync License, GUI and Bridge Node.
\+ If needed, an additional Bridge Node can be ordered.



BB-GEO-XX – Mounted to luminaire



INPUT POWER CONSUMPTION

# OF LEDS	DRIVE CURRENT (mA)	INPUT VOLTAGE (V)	CURRENT (Amps)	SYSTEM POWER (w)
24	350mA	120	0.23	28
		277	0.10	28
	625mA	120	0.41	49
		277	0.18	49
	900mA	120	0.59	71
		277	0.25	71
		347	0.20	71
		480	0.15	71
	1100mA	120	0.72	87
		277	0.31	87
		347	0.25	87
		480	0.18	87
32	650mA	120	0.56	67
		277	0.24	67
		347	0.19	67
		480	0.14	67
	850mA	120	0.69	83
		277	0.30	83
		347	0.24	83
		480	0.17	83

STANTEC PROJECT # 110126045

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

SUBMITTAL # ELE-004 Lighting

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 26, 2018

BY Chester Martinez, E.I.T.


PERFORMANCE DATA

# OF LEDS	DRIVE CURRENT	SYSTEM WATTS	DIST. TYPE	5K (5000K nominal, 70 CRI) LUMENS	LPW¹	B	U	G	4K (4000K nominal, 70 CRI) LUMENS	LPW¹	B	U	G	3K (3000K nominal, 70 CRI) LUMENS	LPW¹	B	U	G
24	350mA	28	1	4,075	146	1	0	0	4,065	146	1	0	0	3,660	131	0	0	0
			2	3,747	134	1	0	1	3,738	134	1	0	1	3,366	121	1	0	1
			3	3,756	135	1	0	1	3,747	134	1	0	1	3,374	121	1	0	1
			4	3,656	131	0	0	1	3,647	131	0	0	1	3,284	118	0	0	1
	625mA	49	1	6,329	130	1	0	0	6,313	130	1	0	0	5,685	117	1	0	0
			2	5,820	120	1	0	1	5,806	119	1	0	1	5,228	108	1	0	1
			3	5,833	120	1	0	2	5,819	120	1	0	2	5,240	108	1	0	2
			4	5,678	117	1	0	2	5,664	117	1	0	2	5,100	105	1	0	2
	900mA	71	1	8,613	122	1	0	1	8,592	122	1	0	1	7,737	110	1	0	1
			2	7,921	112	1	0	2	7,902	112	1	0	2	7,115	101	1	0	2
			3	7,939	112	1	0	2	7,920	112	1	0	2	7,131	101	1	0	2
			4	7,728	109	1	0	2	7,709	109	1	0	2	6,942	98	1	0	2
	1100mA	87	1	10,791	124	1	0	1	10,765	124	1	0	1	9,694	112	1	0	1
			2	9,924	114	2	0	2	9,900	114	1	0	2	8,915	103	1	0	2
			3	9,946	115	1	0	2	9,922	114	1	0	2	8,935	103	1	0	2
			4	9,682	112	1	0	2	9,659	111	1	0	2	8,696	100	1	0	2
32	650mA	67	1	8,621	129	1	0	1	8,600	128	1	0	1	7,744	116	1	0	1
			2	7,928	118	1	0	2	7,909	118	1	0	2	7,122	106	1	0	2
			3	7,946	119	1	0	2	7,927	118	1	0	2	7,137	107	1	0	2
			4	7,735	115	1	0	2	7,716	115	1	0	2	6,948	104	1	0	2
	850mA	83	1	10,806	130	1	0	1	10,780	130	1	0	1	9,705	117	1	0	1
			2	9,938	120	2	0	2	9,914	119	1	0	2	8,927	108	1	0	2
			3	9,960	120	1	0	2	9,936	120	1	0	2	8,947	108	1	0	2
			4	9,695	117	1	0	2	9,672	117	1	0	2	8,709	105	1	0	2


© 2016 HUBBELL OUTDOOR LIGHTING, All Rights Reserved • For more information visit our website: **www.hubbelloutdoor.com** • Printed in USA

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** QSP2-24L-50-5K7-4-UNV-BL Notes:	**Type:** 401 BDA18-23511


PHOTOMETRIC REPORTS




TRP2-24L-50-4K7-1
15" MOUNTING HEIGHT



TRP2-24L-50-4K7-2
15" MOUNTING HEIGHT




TRP2-24L-50-4K7-3
15" MOUNTING HEIGHT



TRP2-24L-50-4K7-4
15" MOUNTING HEIGHT

PHOTOMETRICS - BATTERY BACK UP




11' Mounting Height

Provides Life Safety Code average illuminance of 1.0 fc. Assumes open space with no obstructions and mounting height of 11'.

Diagrams for illustration purposes only, please consult factory for application layout.

E & EH EMERGENCY BATTERY BACKUP



24 or 32 high power LEDs generate up to 11,000 lumens in normal mode and use 4 LEDs for up to 700 lumens in emergency mode.

INVERTED MOUNTING



Inverted mounting capabilities for uplighting applications. Specially designed frosted acrylic diffuser softens output, improves uniformity and prevents water from collecting.

COMFORT SHIELD



Comfort shield option utilizes a frosted acrylic lens that softens output and improves uniformity. Available from the factory or as an accessory for field installation.

CONTROL OPTIONS



Programmable occupancy sensor offers greater control and energy savings with adjustable delay and dimming levels (Factory default is 10%)

Due to our continued efforts to improve our products, product specifications are subject to change without notice.
© 2017 HUBBELL OUTDOOR LIGHTING, All Rights Reserved • For more information visit our website: **www.hubbelloutdoor.com** • Printed in USA

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** NSL-RA-4-60-50K-W-WG-347 Notes:	**Type:** 404 BDA18-23511

PEERLESS electric·électrique

PROJECT:	DATE:
CAT. NO:	TYPE:
NOTES:	VOLTS:

NSL-RA

LED Narrow Strip Luminaire – Rounded Lens

LED

GENERAL DESCRIPTION

LED luminaire for surface or suspended installation, featuring a rounded extruded ribbed frosted acrylic lens. Available in 2ft, 4ft and 8ft models that provide uniform illumination with the narrow design. Available individually or for continuous-row mounting for uniform continuous lighting. Ideal for general utility applications, including commercial, residential, retail and also works well in cove applications.



SHIELDING

A rounded extruded ribbed frosted acrylic lens is standard.

CONSTRUCTION

Rigid one-piece body constructed from code gauge steel.

ELECTRICAL

L80 performance at 60,000 hours minimum.
120-270V or 347V
80 CRI Standard**

3000K 3500K 4000K 5000K

CERTIFICATION

Approved to UL1598 and
CSA C22.2 No. 250 standards*
Rated for damp locations.

Check the DLC Qualified Products List at *designlights.org* to confirm which versions are qualified.

FINISH

Standard finish is high gloss white polyester baked powder coat enamel.

GLOSSY / MATTE

*other colours available. Contact factory

MOUNTING

SURFACE MOUNTED

SUSPENDED

LENGTHS

NOMINAL (ft)	ACTUAL(in)
2 ft	22.459"
4 ft	44.584"
8 ft	88.928"

SENSOR

OC= On/Off Occupancy control
O5= 100%-50% Hi/Low Occupancy control
Consult factory

*Normal temperature: -20 degrees Celsius to +25 degrees Celsius.
**Other dimming options, lumen options, 90CRI and lengths available. Consult Factory.

V1-2018/01/09

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other


component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 26, 2018

BY Chester Martinez, E.I.T.



ORDERING INFORMATION

NSL – RA – – – – – – – – NO OPTION – NO OPTION –

OPTICAL DESIGN	LENGTH	LUMENS	CCT	FINISH	*OPTIONAL*	MOUNTING *OPTIONAL*	POWER CORD *OPTIONAL*	DRIVER
RA = Rounded Acrylic	**2** = 2'	**15** = 1500lm **23** = 2300lm **30** = 3000lm	**30K** = 3000K **35K** = 3500K **40K** = 4000K **50K** = 5000K	**GLOSSY** **W** = White Housing **B** = Black Housing **G** = Metallic Grey Housing **MATTE** **WM** = White Matte Housing **BM** = Black Matte Housing **GM** = Grey Matte Housing	**WG** = Wireguard	**A4** = Aircraft 48in **A5** = Aircraft 60in **A8** = Aircraft 96in **A12** = Aircraft 144in *for row mounting option, Consult factory	**C1** = Cord 5ft **C2** = Cord 6ft **C4** = Cord 9ft **C7** = Cord 13ft	**MV** = Standard 120V-277V Dimming (0-10v) **347** = Standard 347V Dimming (0-10v)
	4 = 4'	**29** = 2900lm **30** = 3000lm **40** = 4000lm **46** = 4600lm **60** = 6000lm						
	8 = 8'	**60** = 6000lm **80** = 8000lm **96** = 9600lm **120** = 12000lm						

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** NSL-RA-4-60-50K-W-WG-347 Notes:	**Type:** 404 BDA18-23511


PEERLESS electric·électrique


NSL-RA

LED Narrow Strip Luminaire – Rounded Lens


MODELS

NSL-RA-2






NSL-RA-4




NSL-RA-4-XX-XXK-X-WG-XX-XX
Optional: WG = Wireguard

NSL-RA-4



NSL-RA-8



Head Office - Montreal, Québec
Tel.: (514) 595-1671
Email: info@peerless-electric.com

Toronto, Ontario
Tel.: (416) 751-5644
Email: info@peerless-electric.com

Western Canada
Tel.: (403) 479-5943 / (514) 595-1671
Email: tkolody@peerless-electric.com

Specifications are subject to change. Please confirm latest specifications prior to placing order.

BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** NSL-RA-4-60-50K-W-WG-347 Notes:	**Type:** 405 BDA18-23511

PEERLESS electric·électrique

PROJECT:	DATE:
CAT. NO:	TYPE:
NOTES:	VOLTS:

NSL-RA

LED Narrow Strip Luminaire – Rounded Lens

LED

GENERAL DESCRIPTION

LED luminaire for surface or suspended installation, featuring a rounded extruded ribbed frosted acrylic lens. Available in 2ft, 4ft and 8ft models that provide uniform illumination with the narrow design. Available individually or for continuous-row mounting for uniform continuous lighting. Ideal for general utility applications, including commercial, residential, retail and also works well in cove applications.



SHIELDING

A rounded extruded ribbed frosted acrylic lens is standard.

ELECTRICAL

L80 performance at 60,000 hours minimum.
120-270V or 347V
80 CRI Standard**

3000K 3500K 4000K 5000K

FINISH

Standard finish is high gloss white polyester baked powder coat enamel.

GLOSSY / MATTE

*other colours available. Contact factory

LENGTHS

NOMINAL (ft)	ACTUAL(in)
2 ft	22.459"
4 ft	44.584"
8 ft	88.928"

CONSTRUCTION

Rigid one-piece body constructed from code gauge steel.

CERTIFICATION

Approved to UL1598 and
CSA C22.2 No. 250 standards*
Rated for damp locations.

Check the DLC Qualified Products List at *designlights.org* to confirm which versions are qualified.

MOUNTING

SURFACE MOUNTED

SUSPENDED

SENSOR

OC= On/Off Occupancy control
O5= 100%-50% Hi/Low Occupancy control
Consult factory

*Normal temperature: -20 degrees Celsius to +25 degrees Celsius.
**Other dimming options, lumen options, 90CRI and lengths available. Consult Factory.

V1-2018/01/09

SUSPENSION NOT INCLUDED
SUPPLIED BY OTHERS

ORDERING INFORMATION

NSL – RA – – – – – – NO OPTION – NO OPTION –

OPTICAL DESIGN	LENGTH	LUMENS	CCT	FINISH	*OPTIONAL*	MOUNTING *OPTIONAL*	POWER CORD *OPTIONAL*	DRIVER
RA = Rounded Acrylic	**2** = 2'	**15** = 1500lm	**30K** = 3000K	**GLOSSY**	**WG** = Wireguard	**A4** = Aircraft 48in	**C1** = Cord 5ft	**MV** = Standard 120V-277V Dimming (0-10v)
		23 = 2300lm	**35K** = 3500K	**W** = White Housing		**A5** = Aircraft 60in	**C2** = Cord 6ft	
		30 = 3000lm	**40K** = 4000K	**B** = Black Housing		**A8** = Aircraft 96in	**C4** = Cord 9ft	**347** = Standard 347V Dimming (0-10v)
	4 = 4'	**29** = 2900lm	**50K** = 5000K	**G** = Metallic Grey Housing		**A12** = Aircraft 144in	**C7** = Cord 13ft	
		30 = 3000lm		**MATTE**		*for row mounting option, Consult factory		
		40 = 4000lm		**WM** = White Matte Housing				
		46 = 4600lm		**BM** = Black Matte Housing				
		60 = 6000lm		**GM** = Grey Matte Housing				
	8 = 8'	**60** = 6000lm						
		80 = 8000lm						
		96 = 9600lm						
		120 = 12000lm						

STANTEC PROJECT #: 110 26045

SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED


☐ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE June 26, 2018

BY Chester Martinez, E.I.T.



BDA LIGHTING GROUP	**Project Name:** Iqaluit Water Treatment Plant	**Product Number:** NSL-RA-4-60-50K-W-WG-347 Notes:	**Type:** 405 BDA18-23511


PEERLESS electric·électrique


NSL-RA

LED Narrow Strip Luminaire – Rounded Lens


MODELS

NSL-RA-2






NSL-RA-4




NSL-RA-4-XX-XXK-X-WG-XX-XX
Optional: WG = Wireguard

NSL-RA-4



NSL-RA-8



Head Office - Montreal, Québec
Tel.: (514) 595-1671
Email: info@peerless-electric.com

Toronto, Ontario
Tel.: (416) 751-5644
Email: info@peerless-electric.com

Western Canada
Tel.: (403) 479-5943 / (514) 595-1671
Email: tkolody@peerless-electric.com

Specifications are subject to change. Please confirm latest specifications prior to placing order.

Hazardous Area LED Lighting
Champ® FMV LED Luminaires

GUILLEVIN OTTAWA
PO# 2010-RON971364D
drawings issued 2018-06-22

FMV11LCY/UNV34 76 page 6


CROUSE-HINDS SERIES

Champ® FMV

LED floodlights for harsh and hazardous areas









Type 402

EATON
Powering Business Worldwide



Champ® FMV LED floodlights

Type 402

Safe. Reliable. Efficient.

Featuring the industry's broadest range of LED luminaires for harsh, hazardous and industrial environments, Eaton's Crouse-Hinds can deliver a lighting solution that performs reliably in even the worst operating conditions. All the while reducing your energy, maintenance and manpower costs.

Why LED?

Energy efficiency
LED average energy consumption is significantly less than traditional fluorescent and HID fixtures

Start/restart time
Instant illumination vs. 10 minute restrike time for HID

Light quality
Higher color rendering compared to fluorescent and HID

Environmental benefits
Mercury-free LED eliminates disposal costs and lower energy consumption for a smaller carbon footprint

Why Crouse-Hinds?

Industry-best reliability
Built to withstand a wide array of applications

Thermal management
Effective heat sinking ensures longer life

Quality of light
Custom optics designed to maximize light distribution and intensity

Globally certified
Designed to global specifications for IEC and NEC applications

Serviceable drivers
Easy access to drivers for service or replacement

Why FMV LED?

Type 402

Reliable floodlights. FMV LED luminaires are engineered to deliver high lumen output and maintenance-free long life in the toughest conditions.

Versatile design

- Can be used for outdoor or indoor applications, and for a wide range of mounting heights depending on model and light level requirement

Smaller and lighter

- 25% smaller footprint than previous model
- 10 lbs. (4.5 kg) less weight than previous model

Full frame yoke

- Designed to utilize the SFA6 slipfitter and SWB6 wall mount bracket, making it ideal for retrofit or new installations



High lumen output:

- Up to 117 lumens per watt
- Up to 72% energy savings over traditional HID fixtures (compared to 400W MH)



Multiple lens options:

- Tempered clear glass lens standard
- Polycarbonate and diffused glass lens options available

Rugged heat sink


- Heat sink designed to perform and provide maximum light levels in high ambient temperatures up to +65°C and as low as -40°C
- Thick walled castings make for a tough, rugged housing that keeps the internal driver and LED temperature down

LED vs. HID savings at a glance


Why are so many facilities making the switch from HID to LED?

The numbers say it all.

FMV13L/UNV1 vs. 400 watt HID



72% REDUCTION IN ENERGY COSTS



75% LOWER TOTAL COST OF OWNERSHIP



100% MAINTENANCE REDUCTION

Assumptions: Calculations based on overall life of the LED system. Energy cost of $.09 per kilowatt; 24 hour per day operation; labor rate of $75 each for 2 workers; average time for fixture maintenance of 1 hour.

Features & specifications

Champ FMV LED floodlights

Champ FMV LED floodlights are designed to provide full-spectrum, crisp, white light. Seven versions of the Champ FMV are available, from 3,000 to 15,000 lumens, providing ideal solutions for a wide range of harsh and hazardous applications.

Up to 75% reduction in energy costs and 150,000 hours of continuous operation.

Model number	Nominal lumens*	Wattage	Lumens per watt	Equivalent HID luminaire
FMV3L	3,189	28	114	70W-100W
FMV5L	5,183	45	115	100W-150W
FMV7L	7,095	62	114	150W-175W
FMV9L	9,132	79	116	175W-250W
FMV11L	11,107	99	112	250W-400W
FMV13L	13,100	112	117	400W
FMV15L	15,181	131	116	450W

*Tolerance +/- 10%; @120 VAC, 25°C ambient, 7x6 optics.

Applications:

- Oil and gas refineries, drilling rigs, petrochemical facilities, food and beverage facilities, platforms, loading docks, tunnels, outdoor wall and stanchion mounted general area lighting, and where flammable vapors, gases, ignitable dusts, fibers or flyings are present
- Locations requiring continuous and consistent light levels in extreme ambient temperatures
- Where extremely corrosive, wet, dusty, hot and/or cold conditions exist
- IP66, Type 4X, marine, wet locations and hose-down environments
- Classified and hazardous locations

LED system:

- Cool white (5000K, 70 CRI) and warm white (3000K, 80 CRI)
- Custom designed optics – 7x6 standard, 3x3 optional (3L-11L)


Champ FMV LED benefits:

- Instant illumination and restrike
- Better visibility with crisp, white light
- Cold temperature operation / no warm-up required
- Minimum T3C temperature rating – safely operate in the most hazardous environments and any non-hazardous location
- Serviceable drivers
- Easy installation – yoke design to mount to SFA6
- Energy-efficient technology – up to 72% energy savings over HID fixtures
- 60,000 hours of rated life at 55°C – eliminates need for frequent lamp replacement
- Contains no mercury or other hazardous substances
- Shock- and vibration-resistant solid-state luminaires have no filaments or glass components that could break – greatly reduces the risk of premature failure
- Operating ambient -40°C to 65°C (NEC only; IEC -40°C to 55°C)
- 5 year fixture warranty‡

‡Extension of standard terms and conditions to five years. Refer to page 2 of the D-0914 authorized distributor price book for Crouse-Hinds standard Terms and Conditions.

LED system lifetime rated versus economic life:

Type 402



Economic life can range anywhere between 50,000 to 150,000 hours, or 5 to 20 years of maintenance-free operation.

Fixture life and years of maintenance-free operation

Ambient temperature	Fixture life (hours)	No. of years at 24 hours usage	No. of years at 12 hours usage
25°C	150,000	17	34
40°C	90,000	10	20
55°C	60,000	7	14

*50,000 hours of life at 65°C ambient.

Fixture life:

- Rated life of 60,000 hours @ 55°C operating ambient and 24/7 continuous operation for 365 days
- Economic life of 150,000 hours @ 25°C ambient
- L70 LED life >300,000 hours @ 55°C

Electrical ratings:

Model number	Input power (watts)	Input amps at 120-277 VAC
FMV3L	28.0 - 29.1	0.24 - 0.11
FMV5L	45.4 - 45.8	0.38 - 0.18
FMV7L	61.8 - 62.5	0.52 - 0.24
FMV9L	78.8 - 80.3	0.66 - 0.31
FMV11L	98.8 - 99.9	0.83 - 0.37
FMV13L	111.8 - 112.4	0.94 - 0.42
FMV15L	131.4 - 131.5	1.10 - 0.48

FMV3L - FMV15L	
Voltage range, VAC*	100-277V @ 50/60 Hz, 347-480V @ 50/60 Hz
Voltage range, VDC*	108-250V
Power factor	>0.9

*NEC voltage; see drivers below for IEC voltage.

Standard materials:

- Lamp housing and adapter – die cast aluminum with Corro-free™ epoxy powder coat
- Lens – heat- and impact-resistant glass (standard)
- Gaskets – silicone and neoprene
- External hardware – stainless steel

Qualifications and compliances:

- DesignLights Consortium® Qualified (some models are not DLC qualified)*

* Approved models include: FMV3L/UNV1; FMV5L/UNV1; FMV7L/UNV1; FMV9L/UNV1; FMV11L/UNV1; FMV13L/UNV1; FMV3L/UNV34; FMV5L/UNV34; FMV7L/UNV34; FMV9L/UNV34; FMV11L/UNV34; FMV13L/UNV34

7x6 optics on all approved models; 3x3 optics not DLC approved.

Refer to www.designlights.org Qualified Products List under family models for full listing details. Not all models are approved for all application categories.

Certifications and compliances:

Type 402

NEC and CEC:

- Class I, Division 2, Groups A, B, C, D; Class I, Zone 2; Class II, Groups E, F, G; Simultaneous Presence; Class III
- Type 4X, IP66

UL Standards:

- UL844; UL1598; UL1598A; UL8750

CSA Standard:

- CSA C22.2 No. 137

IEC Standards:

- IECEx UL 15.0029
- Ex nA IIC T5 Gc Tamb -40°C to +40°C
- Ex nA IIC T4 Gc Tamb -40°C to +55°C
- Ex tb IIIC T65 Db Tamb -40°C to +40°C
- Ex tb IIIC T80 Db Tamb -40°C to +55°C

ATEX/CE:

- CE 0359 DEMKO 15 ATEX 1377
- CE 0359 DEMKO 15 ATEX 1383
- Ex II 3 G Ex nA IIC T5 Gc Tamb -40°C to +40°C
- Ex II 3 G Ex nA IIC T4 Gc Tamb -40°C to +55°C
- Ex II 2 D Ex tb IIIC T65 Db Tamb -40°C to +40°C
- Ex II 2 D Ex tb IIIC T80 Db Tamb -40°C to +55°C



Temperature codes:


Model	Ambient temperature	Class I, Div. 2	Class II, Div. 1	Simultaneous rating Class I, Div. 2, Div. 1	Class I, Zone 2	ATEX 3G	ATEX 2D	Minimum wire temperature
FMV3L-FMV15L	40°C	T5	T4	T4	T5	T5	T65	90°C
	55°C	T4A	T3C	T3C	T4	T4	T80	90°C
	65°C	T4A	T3C	T3C	T4	–	–	90°C

Weights and dimensions:

Model number	Lbs.	Kg.	Width in.	Width mm.	Height in.	Height mm.	Depth in.	Depth mm.
FMV3L-FMV7L	30.7	13.9	15.5	393.7	12.0	304.8	7.0	177.8
FMV9L-FMV15L	31.8	14.4	15.5	393.7	12.0	304.8	7.0	177.8

Drivers:

Option	FMV3L - FMV15L
/UNV1	NEC: 100-277 VAC, 50/60 Hz; 108-250 VDC IEC: 100-252 VAC, 50/60 Hz; 111-227 VDC
/UNV34	NEC: 347-480 VAC, 50/60 Hz IEC: 385-436 VAC, 50/60 Hz



Ordering information

GUILLEVIN OTTAWA
PO# 2010-RON971364D
drawings issued 2018-06-22

FMV11LCY/UNV34 76

Part number example

~~FMV5LCY/UNV1D 76 S903~~

~~FMV 5L C Y /UNV1 D 76 S903~~

Model

FMV	NEC & IEC model

Mount

Y	Yoke

Options

S886	Two TMCX cable glands of like thread installed
S891	Diffused glass lens
S903	Polycarbonate lens

Light source/intensity

3L	3,189 nominal lumens*
5L	5,183 nominal lumens*
7L	7,095 nominal lumens*
9L	9,132 nominal lumens*
11L	11,107 nominal lumens*
13L	13,100 nominal lumens*
15L	15,181 nominal lumens*

*7x6 model.

Entries

BLANK	¾" NPT
M20	20mm entry
M25	25mm entry

Color temperature

C	5000K, 70 CRI (cool white)
W	3000K, 80 CRI (warm white)

Optical distribution

76	7x6 floodlight pattern optics
33*	3x3 floodlight pattern optics

*3L - 11L only.

Voltage

/UNV1	100-277 VAC, 50/60 Hz; 108-250 VDC
/UNV34	347-480 VAC 50/60 Hz

Dimming

D*	Dimmable driver
BLANK	Non-dimmable driver

*Dimmable driver option only available for NEC rated models.

Accessories (ordered separately)

DSV2	Bolt-on visor
P62	Bolt-on wire guard
SC831	Safety cable
SFA6	Floodlight slipfitter
SWB6	Slipfitter wall mount adapter

Type 402

STANTEC PROJECT #: 110126045

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

SUBMITTAL # ELE-004 Lighting

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 26, 2018


BY Chester Martinez, E.I.T.

Photometric data

Type 402

7x6 optics

FMV13L Height: 40 ft.; Tilt angle: 45°



Effective projected area (ft.-sq.):

Position	FMV3L - FMV15L
@ 0° Tilt	1.5
@ 45° Backwards tilt	1.1
@ 60° Forward tilt	0.8

Lumen output for glass lens models

Optic	FMV3L	FMV5L	FMV7L	FMV9L	FMV11L	FMV13L	FMV15L
7x6	3,189	5,183	7,095	9,132	11,107	13,100	15,181
3x3	3,064	5,038	7,000	8,962	10,917	–	–

Lumen output for diffused glass lens (S891) models


Optic	FMV3L	FMV5L	FMV7L	FMV9L	FMV11L	FMV13L	FMV15L
7x6	2,637	4,287	5,878	7,459	8,994	10,613	12,445
3x3	2,546	4,179	5,806	7,433	9,055	–	–

Lumen output for polycarbonate lens (S903) models

Optic	FMV3L	FMV5L	FMV7L	FMV9L	FMV11L	FMV13L	FMV15L
7x6	3,017	4,903	6,712	8,639	10,507	12,393	14,361
3x3	2,924	4,808	6,680	8,552	10,418	–	–

3x3 optics

FMV11L Height: 30 ft.; Tilt angle: 45°





Higher average footcandles/lux, uniformity and distribution coverage with 72% less energy consumption compared to 400W metal halide.

Type 402

U.S. (global headquarters): Eaton's Crouse-Hinds business

1201 Wolf Street
Syracuse, NY 13208

(866) 764-5454
FAX: (315) 477-5179
FAX Orders Only:
(866) 653-0640

crousecustomerctr@eaton.com

Canada

Toll Free: 800-265-0502
FAX: (800) 263-9504
FAX Orders only: (866) 653-0645

Eaton Middle East

9714-8066100
FAX: 9714-8894813

chmesales@eaton.com

Korea

82-2-3484-6783
82-2-3484-6778

CCHK-sales@
cooperindustries.com

Mexico/Latin America/Caribbean

52-555-804-4000
FAX: 52-555-804-4020

ventascentromex@eaton.com

Singapore

65-6645-9888
FAX: 65-6297-4819

chsi-sales@
cooperindustries.com

Australia

61-2-8787-2777
FAX: 61-2-9609-2342

CEASales@
cooperindustries.com

Europe (Germany)

49 (0) 6271 806-500
49 (0) 6271 806-476

sales.CCH.de@
cooperindustries.com

China

86-21-2899-3600
FAX: 86-21-2899-4055

cchsales@
cooperindustries.com

India

91-124-4683888
FAX: 91-124-4683899

cchindia@eaton.com

For more information:

If further assistance is required, please contact an authorized Eaton Distributor, Sales Office, or Customer Service Department.

Eaton's Crouse-Hinds
1201 Wolf Street
Syracuse, NY 13208
Crouse-Hinds.com

Eaton
1000 Eaton Boulevard
Cleveland, OH 44122
United States
Eaton.com

© 2015 Eaton
All Rights Reserved

Printed in USA
Publication No. 5242-1215
December 2015

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Powering Business Worldwide

GUILLEVIN OTTAWA
PO# 2010-RON971364D
drawings issued 2018-06-22

VMV5L2A/UNV34 page 8

Champ® VMV

LED luminaires for hazardous areas



3,000 to 25,000 lumen LED high bay luminaires



Type 403

EATON
Powering Business Worldwide



Champ® VMV LED

Safe. Reliable. Efficient.

Type 403

Featuring the industry's broadest range of LED luminaires for harsh, hazardous and industrial environments, Eaton's Crouse-Hinds can deliver a lighting solution that performs reliably in even the worst operating conditions. All the while reducing your energy, maintenance and manpower costs.

Why LED?

Useful life
Rated life is up to 60,000 hours of maintenance-free and safe operation

Energy efficiency
LED average energy consumption is significantly less than traditional fluorescent and HID fixtures

Start/restart time
Instant illumination versus 10 minute restrike time for HID

Light quality
Higher color rendering compared to fluorescent and HID

Environmental benefits
Mercury-free LED eliminates disposal costs and lower energy consumption for a smaller carbon footprint

Why Crouse-Hinds?

Rugged design
Built to withstand extreme temperatures, vibration, water and dust

High efficacy
Up to 124 lumens per watt (model dependent)

Thermal management
Effective heat sinking ensures longer life

Quality of light
Custom optics designed to maximize light distribution and intensity

Versatile mounting
LED fixtures are compatible with Crouse-Hinds' HID installed base

Why Champ VMV LED? Type 403

Rugged mid to high bay solutions. Champ VMV LED luminaires are engineered to provide maintenance-free operation while delivering long life and high lumen performance.



Built to last:

- Type 4X rated
- Impact-resistant lens sealed from the outside environment provides ingress protection against water and dust
- Die cast aluminum LED housing provides efficient thermal path to heat sink assembly
- Vertical fin design facilitates air flow and dust shedding

Simple installation and replacement:

- Contractor-friendly design is ideal for both retrofit and new construction
- Easy to retrofit using existing HID Champ mounting module
- Compact modular design for easy component replacement and future upgrades
- Available with lever lock connectors and standard three-pole terminal block



Custom optics:

- Type I, III and V optics designed to maximize light distribution and intensity*

* Type V optics standard.

Increased efficiency and durability:

- Up to 124 lumens per watt
- Economic life: 7-20 years



VMV3L-VMV11L

optimized for 8-30 foot mounting heights



VMV13L & VMV17L



VMV21L & VMV25L


optimized for 30-60 foot mounting heights

LED vs. HID savings at a glance


Why are so many facilities making the switch from HID to LED?

The numbers say it all.

VMV7L vs. 175 Watt MH



64% REDUCTION IN ENERGY COSTS



75% LOWER TOTAL COST OF OWNERSHIP



100% MAINTENANCE REDUCTION

Assumptions: Calculations based on overall life of the LED system. Energy cost of $.09 per kilowatt; 24 hour per day operation; labor rate of $75 each for 2 workers; average time for fixture maintenance of 1 hour.

Custom optics

Eaton's Crouse-Hinds continuously focuses on engineering product solutions tailored to our customers' unique needs and applications.

Champ VMV LED luminaires feature custom optics designed to maximize light distribution and intensity, providing flexibility for retrofits or new installations throughout the site.



Type III optics minimize light spillover onto the walls and direct light to the ground.

Three optical options to maximize light distribution and intensity



VMV3L - VMV11L



Type I



Type III



Type V



TYPE I

Long and rectangular for hallways, walkways, loading docks, catwalks.

Ideal for:

- Mining conveyor belts
- Aisleways and hallways
- Catwalks and walkways
- Ramps and loading docks
- Tunnels with overhead mounts

TYPE III

Wall mount light distribution, minimizing spillover on the wall.

Ideal for:

- Narrow crosswalks or passages with wall mounted fixtures
- Tunnels with wall mount
- Wall or stanchion mount requiring 180° forward throw beam patterns

TYPE V

Regular circular distribution pattern for high/low bay indoor and outdoor ceiling or pendant mount lighting.

Ideal for:

- Pendant, ceiling or stanchion mount overhead building mounts
- Processing mills, industrial plants, large buildings, warehouses, etc.

Colored LED options:

- Available in green and amber*
- Reduction in light pollution for night space observation and sky glow due to isolating blue wavelength in red and amber colors
- Wildlife-friendly
- Improves visibility for telescopes in observatories during night sky space exploration

* Custom optics not available with colored LEDs. One model per color, see assignment sheet.

Type 403

Case study: Type I optics

Type 403

Catwalk/conveyor lighting

Utilizing Eaton's Crouse-Hinds lighting layout services, Champ VMV luminaires with Type I optics and HID luminaires are shown installed on a catwalk to compare photometrics.

Comparison

Champ Type I LEDs have a wider linear pattern than equivalent HID luminaires and provide more efficient light dispersion, which fully illuminates the catwalk.


Results

Champ VMV LED with Type I optics provides superior illumination along the conveyor and walkway safely. With no gaps in illumination, the optical pattern allows for increased spacing of fixtures and a safer conveyor system.


Savings realized

- **Champ Type I pattern allows for greater fixture spacing** along the catwalk or conveyor system
- Increased visibility with no dark spots results in safer conditions for workers
- LED system provides between 7 to 20 years of maintenance-free operation
- Up to 64% energy savings over the life of the fixture

Champ® Gen III w/ Type I Optics




175W Metal Halide w/ Type I Optics



Luminaire	Calc. Type	Units	Avg.	Max.	Min.	Avg./Min.	Max./Min.
Champ VMV	Illuminance	Fc	26.91	36.9	17.4	1.55	2.12
175W MH	Illuminance	Fc	14.32	18.0	7.9	1.81	2.28

Champ VMV has broader coverage area, higher delivered footcandles and uniformity for a typical catwalk or conveyor application.



Lighting layout & design services:

Let us help you design your next big project!

Contact Crouse-Hinds Customer Service
crousecustomerctr@eaton.com
(866) 764-5454

Champ VMV Series LED Luminaires

Champ VMV Series LEDs are designed to provide full-spectrum, crisp, white light with custom IES Type I, III and V distribution.

Model	Typical lumens (Type V)*	Wattage	Lumens per watt	Equivalent HID luminaire	Typical energy savings / lifetime
VMV3L	3,531	29	122	70W-100W	Up to 77%
VMV5L	5,335	43	124	100W-150W	Up to 67%
VMV7L	7,195	62	116	150W-175W	Up to 67%
VMV9L	9,266	85	109	250W-320W	Up to 74%
VMV11L	11,440	113	101	320W-400W	Up to 74%
VMV13L	13,226	130	102	400W	Up to 68%
VMV17L	18,793	168	112	400W-600W	Up to 72%
VMV21L	22,110	196	113	600W-750W	Up to 74%
VMV25L	26,531	232	114	750W-1000W	Up to 77%

* Tolerance +/- 10%.

Applications:

- For areas with mounting heights of 8-60 feet
- Oil and gas refineries, drilling rigs, petrochemical facilities, food and beverage facilities, platforms, loading docks, tunnels, indoor/outdoor spotlighting, outdoor wall and stanchion mounted general area lighting, and where flammable vapors, gases, ignitable dusts, fibers or flyings are present
- Locations requiring continuous and consistent light levels in extreme ambient temperatures
- Where extremely corrosive, wet, dusty, hot and/or cold conditions exist
- Classified and hazardous locations

Champ VMV benefits:


- Instant illumination and restrike
- Cold temperature operation / no warm-up required
- Option for redundancy in drivers with multiple series circuits connected to each driver to avoid complete loss of illumination
- Easy installation - compact modular fixture attaches onto existing Champ mounting module
- Energy-efficient technology - up to 64% energy savings over HID fixtures
- Contains no mercury or other hazardous substances
- Shock- and vibration-resistant solid-state luminaires have no filaments or glass components that could break - greatly reduces the risk of premature failure
- Operating ambient: -40°C to 65°C (VMV3L-VMV11L models); -40°C to 55°C (VMV13L-VMV25L models)
- 5 year fixture warranty†

† Refer to page 2 of the D-0914 authorized distributor price book for Crouse-Hinds standard Terms and Conditions.

LED system:

- High intensity discrete power emitters
- Standard: cool white (5000K, 70 CRI)
  Optional: warm white, (3000K, 80 CRI)
- Custom Type I, III and V optics available
- Optics clocking in field to align Type I and Type III light patterns to illumination path for VMV13L-VMV25L

LED system lifetime rated versus economic life:



Economic life can range anywhere between 64,000 to 200,000 hours, or 7 to 20 years of maintenance-free operation.

Fixture life and years of maintenance-free operation

Ambient temperature	Fixture life (hours)	No. of years at 24 hours usage	No. of years at 12 hours usage
25°C	201,008	23	46
30°C	153,445	17	35
40°C	94,949	11	22
55°C	64,286	7	15

* 50,000 hrs of life at 65°C ambient for VMV3L-VMV11L/UNV1 models.

Fixture life:

- Rated life of 60,000 hours @ 55°C operating ambient and 24/7 continuous operation for 365 days
- Economic life of 200,000 hours @ 25°C ambient
- L70 >300,000 hours @ 55°C

Drivers

Option	Voltage: VMV3L-VMV25L
/UNV1	120-277 VAC, 50/60 Hz; 108-250 VDC, 50/60 Hz
/UNV34	347-480 VAC, 50/60 Hz

Standard materials:

- Lamp housing and adapter - die cast aluminum with Corro-free™ epoxy powder coat
- Lens - heat- and impact-resistant glass
- Gaskets - silicone
- External hardware - stainless steel
- Factory-sealed, no external seals required

Qualifications and compliances:

- DesignLights Consortium® Qualified (some models are not DLC qualified)*

Type 403

* Approved models include: VMV3L/UNV1; VMV5L/UNV1; VMV7L/UNV1; VMV9L/UNV1; VMV11L/UNV1; VMV13L/UNV1; VMV17L/UNV1; VMV21L/UNV1; VMV25L/UNV1; VMV3L/UNV34; VMV5L/UNV34; VMV7L/UNV34; VMV9L/UNV34; VMV11L/UNV34.

Refer to www.designlights.org Qualified Products List under family models for full listing details. Not all models are approved for all application categories.

Certifications and compliances:

Type 403

NEC and CEC

- Class I, Division 2, Groups A, B, C, D; Class I, Zone 2, nA nR; Class II, Groups E, F, G; Class III
- Zone 21 tb
- Simultaneous Presence
- Wet Locations, NEMA 4X, IP66

UL Standards

- UL844; UL1598 Luminaires; UL1598A Marine; UL8750; UL50; UL50E

CSA Standard

- cUL Listed to CSA Standard CSA C22.2 No. 137

IEC**

- IEC 60079-0:2011; IEC 60079-15:2010; IEC 60079-31:2008; IEC 60598-2-1:1979; IEC 60529:2001
- Ex nA nR IIC T* Gc -40 to +40
- Ex nA nR IIC T* Gc -40 to +55
- Ex nA nR IIC T* Gc -40 to +65
- Ex tb IIIC T*°C Db -40 to +40
- Ex tb IIIC T*°C Db -40 to +55
- Ex tb IIIC T*°C Db -40 to +65

VMV3L-VMV11L only

- IECEx UL 13.0052X

VMV13L-VMV25L only

- IECEx UL 14.0031X

ATEX/CE**

- EN 60079-0:2012; EN 60079-15:2010; EN 60079-31:2009; EN 60598-2-1:1989; EN 60929:1991 +A1:2001
- Ⓔx II 3 G Ex nA nR IIC T* Gc -40 to +40
- Ⓔx II 3 G Ex nA nR IIC T* Gc -40 to +55
- Ⓔx II 3 G Ex nA nR IIC T* Gc -40 to +65
- Ⓔx II 2 D Ex tb IIIC T*°C Db IP66 -40 to +40
- Ⓔx II 2 D Ex tb IIIC T*°C Db IP66 -40 to +55
- Ⓔx II 2 D Ex tb IIIC T*°C Db IP66 -40 to +65

VMV3L-VMV11L only

- DEMKO 13 ATEX 1475031X; DEMKO 13 ATEX 1305741X

VMV13L-VMV25L only

- DEMKO 14 ATEX 1324722X; DEMKO 14 ATEX 2274231X

* See temperature code table below.

** VMV3L-VMV11L rated to +65°C, VMV13L-VMV25L rated to +55°C.

Electrical ratings:

	VMV3L	VMV5L	VMV7L	VMV9L	VMV11L
Voltage range, VAC	120-277	120-277	120-277	120-277	120-277
Frequency	50/60 Hz	50/60 Hz	50/60 Hz	50/60 Hz	50/60 Hz
Input power (watts)	29	43	62	85	113
Input amps at 120-277 VAC	0.24-0.11	0.35-0.16	0.52-0.23	0.71-0.31	0.95-0.41
Voltage range, VDC	108-250	108-250	108-250	108-250	108-250
Power factor	>0.90	>0.90	>0.90	>0.90	>0.90
Total harmonic distortion (THD)	<20%	<20%	<20%	<20%	<20%
Nominal lumens† (Type V)	3,531	5,335	7,195	9,266	11,440

	VMV13L	VMV17L	VMV21L	VMV25L
Voltage range, VAC	120-277	120-277	120-277	120-277
Frequency	50/60 Hz	50/60 Hz	50/60 Hz	50/60 Hz
Input power (watts)	131	168	196	232
Input amps at 120-277 VAC	1.08-0.48	1.40-0.62	1.64-0.73	1.94-0.87
Voltage range, VDC	108-250	108-250	108-250	108-250
Power factor	>0.90	>0.90	>0.90	>0.90
Total harmonic distortion (THD)	<20%	<20%	<20%	<20%
Nominal lumens† (Type V)	13,226	18,793	22,110	26,531

† Tolerance +/- 10%.

Weights:

Luminaire	lbs.	kg.
VMV3L-VMV11L	21.8	8.07
VMV13L & VMV17L	36.0	16.32
VMV21L & VMV25L	44.0	19.95

Mounting module	lbs.	kg.
Pendant	1.25	0.57
Cone pendant	4.00	1.81
Flexible pendant	1.50	0.68
Ceiling	2.75	1.25
Wall	4.50	2.04
Angled stanchion*	3.50	1.59
Straight stanchion	4.50	2.04

* Angled stanchion for VMV3L-VMV11L models only.

Temperature codes:

Lamp/lumen output	Driver type	Ambient temperature	Class I, Div. 2	Class II, Div. I	Simultaneous rating Class I, Div. 2, Div. 1	Class I, Zone 2 AEx nA nR; Ex nA nR	Class III, Div. 1 Class II, Div. 1, Groups E, F, G Zone 21 AEx tb IIIC
3L, 5L, 7L, 9L, 11L	/UNV1	40°C	T5	T5	T3C	T6	T66°C
3L, 5L, 7L, 9L, 11L	/UNV1	55°C	T5	T4A	T3A	T5	T83°C
3L, 5L, 7L, 9L, 11L	/UNV1	65°C	T4A	T4A	T3A	T4	T92°C
3L, 5L, 7L, 9L, 11L	/UNV34	40°C	T3C	T5	T3C	T4	T70°C
3L, 5L, 7L, 9L, 11L	/UNV34	55°C	T3A	T4A	T3A	T4	T85°C
3L, 5L, 7L, 9L, 11L	/UNV34	65°C	T3A	T4A	T3A	T4	T92°C
13L, 17L	/UNV1; UNV34	40°C	T4A	T5	T4A	T6	T66°C
13L, 17L	/UNV1; UNV34	55°C	T4	T4A	T4	T5	T81°C
21L, 25L	/UNV1; UNV34	40°C	T4A	T5	T4A	T6	T71°C
21L, 25L	/UNV1; UNV34	55°C	T4	T4A	T4	T5	T86°C

Ordering information

GUILLEVIN OTTAWA
PO# 2010-RON971364D
drawings issued 2018-06-22

VMV5L2A/UNV34 page 8

Part number example
~~VMV17LW2AR1G/UNV1 S890~~

VMV 17L W 2A R1 G /UNV1 S890

Lamp/function

3L	3,531 lumen LED
5L	5,335 lumen LED
7L	7,195 lumen LED
9L	9,226 lumen LED
11L	11,440 lumen LED
13L	13,226 lumen LED
17L	18,793 lumen LED
21L	22,110 lumen LED
25L	26,531 lumen LED
GL*	Green (4,300 lumen LED)
AL*	Amber (5,000 lumen LED)

* Custom optics not available with colored LEDs.

Color temperature

BLANK	Cool (5000K), colored
W	Warm (3000K)

Mounting style

BLANK	No Cover
J*	1-½" stanchion, 25° angled
P	1-½" stanchion, straight
2A	¾" pendant
3A	1" pendant
20A	20mm pendant
25A	25mm pendant
2B	¾" cone pendant
3B	1" cone pendant
2C	¾" ceiling
3C	1" ceiling
20C	20mm ceiling
25C	25mm ceiling
2HA	¾" flexible pendant
2TW	¾" wall
3TW	1" wall
20TW	20mm wall
25TW	25mm wall

* For VMV3L-VMV11L only.

Suffixes

S812*	Trunnion mount kit with pin
S831**	Safety cable
S890	Quick clip
S891**	Diffused lens
S892***	Redundant driver
S896**	Teflon coated lens
S903	Polycarbonate lens
TB6	Six-pole terminal block

* Order with ceiling mount only.
** Not available for IEC.
*** Available for 5L & 7L only. Redundant driver standard on 9L - 25L models.
7L = 6,616 lumens with S892 suffix.

Voltage

/UNV1	120-277 VAC, 50/60 Hz; 108-250 VDC, 50/60 Hz
/UNV34	347-480 VAC, 50/60 Hz

Guard

BLANK	No guard
G	P3001 wire guard

Optics

BLANK	Type V optic standard *(all mounts)*
R1	Type I optic *(all mounts minus ceiling for 3L-11L, available with mounts for 13L-25L models)*
R1A*	Type I optic *(ceiling with conduit 45° counterclockwise or 135° clockwise from hinge)*
R1B*	Type I optic *(ceiling with conduit 45° clockwise or 135° counterclockwise from hinge)*
R3	Type III optic *(all mounts minus ceiling)*
R3AP*	Type III optic *(select when using Appleton® top hat adapter with Champ fixture)*
R3A1*	Type III optic *(ceiling with conduit 45° counterclockwise from top hat hinge)*
R3A2*	Type III optic *(ceiling with conduit 135° clockwise from top hat hinge)*
R3B1*	Type III optic *(ceiling with conduit 45° clockwise from top hat hinge)*
R3B2*	Type III optic *(ceiling with conduit 135° counterclockwise from top hat hinge)*

*For VMV3L-VMV11L only.

Type 403

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 26, 2018

BY Chester Martinez, E.I.T.


Accessories (ordered separately)

D2S20	Photocell, 120V, 50/60 Hz
D2S208 277	Photocell, 208-277V
VMVL S812 K1*	Trunnion mount kit with pin


* Order with ceiling mount only.

Mounting options and dimensions


Stanchion - 25° Angled




Stanchion - Straight




Pendant




Ceiling




Wall



Cone Pendant



Trunnion




Type 403


Photometric comparison at 15 ft. mounting height

Type 403

175W PSMH - Type I



VMV7L - Type I




Type I optical pattern

0.25 0.50 1.0 2.5 5.0


Calculation summary

Label	Calc. type (in Fc)	Avg.	Max.	Min.
VMV 175W MH Grid	Illuminance	0.45	2.8	0.0
VMV LED Grid	Illuminance	0.62	8.0	0.0

175W PSMH - Type III



VMV7L - Type III




Type III optical pattern

0.25 0.50 1.0 2.5 5.0


Calculation summary

Label	Calc. type (in Fc)	Avg.	Max.	Min.
VMV 175W MH Grid	Illuminance	0.53	3.2	0.1
VMV LED Grid	Illuminance	0.61	7.5	0.0

175W PSMH - Type V



VMV7L - Type V



Type V optical pattern

0.50 1.0 2.5 5.0 10.0

Calculation summary

Label	Calc. type (in Fc)	Avg.	Max.	Min.
VMV 175W MH Grid	Illuminance	0.51	2.8	0.1
VMV LED Grid	Illuminance	0.69	10.1	0.0

Higher average footcandles, uniformity and distribution coverage with less than half the lumens and energy consumption compared to 175W metal halide

Actual lumens (nominal†)	VMV3L	VMV5L	VMV7L	VMV9L	VMV11L
Type I	3,360	5,045	6,844	8,823	10,730
Type III	3,309	4,468	6,741	8,618	10,660
Type V	3,531	5,335	7,195	9,266	11,440

Actual lumens (nominal†)	VMV13L	VMV17L	VMV21L	VMV25L
Type I	12,842	18,194	21,404	25,685
Type III	12,493	17,699	20,822	24,987
Type V	13,266	18,793	22,110	26,531

† Tolerance +/- 10%.

Type 403

U.S. (global headquarters): Eaton's Crouse-Hinds business

1201 Wolf Street
Syracuse, NY 13208

(866) 764-5454
FAX: (315) 477-5179
FAX Orders Only:
(866) 653-0640

crousecustomerctr@eaton.com

Canada

Toll Free: 800-265-0502
FAX: (800) 263-9504
FAX Orders only: (866) 653-0645

Middle East (Dubai)

971 4 8066100
FAX: 971 4 8894813

chmesales@eaton.com

Korea

82-2-3484-6783
82-2-3484-6778

CCHK-sales@
cooperindustries.com

Mexico/Latin America/Caribbean

52-555-804-4000
FAX: 52-555-804-4020

ventascentromex@eaton.com

Singapore

65-6645-9888
FAX: 65-6297-4819

chsi-sales@
cooperindustries.com

Australia

61-2-8787-2777
FAX: 61-2-9609-2342

CEASales@
cooperindustries.com

Europe (Germany)

49 (0) 6271 806-500
49 (0) 6271 806-476

sales.CCH.de@
cooperindustries.com

China

86-21-2899-3600
FAX: 86-21-2899-4055

cchsales@
cooperindustries.com

India

91-124-4683888
FAX: 91-124-4683899

cchindia@
cooperindustries.com

For more information:

If further assistance is required, please contact an authorized Eaton Distributor, Sales Office, or Customer Service Department.

Eaton
1000 Eaton Boulevard
Cleveland, OH 44122
United States
Eaton.com

© 2018 Eaton
All Rights Reserved

Printed in USA
Publication No. 5123-0318
March 2018

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Powering Business Worldwide

LED WIDE ENCLOSED & GASKETED - EGW

Type 406



PRODUCT HIGHLIGHTS

- Vaportight design
- IP66, IP67 Certified (comparable to NEMA 6)
- NEMA 4X rated / NEMA 250-2003
- High pressure hose down (1500psi)
- NSF / ANSI Standard 2
- UL50E: standards for safety enclosures of electrical equipment
- 12 Point stainless steel latching and stainless hardware
- Sloped housing design promotes water displacement
- Optional stainless steel "V" bracket or "SB" surface bracket accessory
- RoHS Compliant

EXPECTED LIFE - Projected life of at least 60,000 hours. Contact factory for TM-21 detail.

LEDs - Use of closely-spaced medium-power, high-brightness chips minimizes pixelation and provides uniform lens luminance. Available in Cool White (5000K), Neutral White (4000K) and Warm White (3500K) color temperatures. CRI >= 80 (CW > 70). LM-80 reports available.

LENS - Frosted, injection molded, high impact acrylic is standard. An optional clear lens is also available.

HOUSING - The inner gear tray is constructed of code gauge steel. The outer housing is constructed of fiberglass reinforced polyester. Gasketing in the housing is constructed of closed cell polyurethane. Conduit entrance is provided at one end. All external hardware and hanging components are constructed of stainless steel.

ELECTRICAL - Universal voltage (120-277 Vac) input, 50/60Hz. Power factor > 0.9, THD < 20%, in-rush current < 15 Amps.

DRIVER - High-performance isolated driver features over-voltage, over-current and short-circuit (with auto-recovery) protection. Driver module is sealed to IP66 protection levels, with a Class A sound rating. 0-10 volt dimming standard.


OPERATING TEMPERATURE - -30°C to 45°C (-22°F to 113°F).

FINISH - All metal parts are painted after fabrication following treatment with phosphate rust inhibitor. Finish coating of housing reflecting surfaces is with high-reflectance (minimum 92%) polyester powder.

WARRANTY - Limited 5-year warranty

PHOTOMETRICS - Please visit our website at www.lsi-industries.com for detailed photometric data.

LISTING - Listed to UL 1598 and UL 8750



LIGHT OUTPUT - LED EGW

	Lumens (Nominal)			
	WW	NW	CW	Watts
HO	5930	5840	6540	57
VHO	9425	9590	11455	88
XHO	18972	20765	22005	164

LED Chips are frequently updated therefore values may increase.

This product, or selected versions of this product, meet the standards listed below. Please consult factory for your specific requirements.

MANUFACTURED IN USA

ARRA Funding Compliant

c UL us LISTED wet location

STANTEC PROJECT #: 110126045 SUBMITTAL # ELE-004 Lighting

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for [illegible] all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 26, 2018

BY: Chester Martinez, E.I.T.

ORDERING INFORMATION

TYPICAL ORDER EXAMPLE: **EGW 4 S LED HO CW UE**

Prefix	Length	Distribution	Light Source	Drive Current	Color Temperature	Line Voltage	Options
EGW - LED Wide Enclosed & Gasketed	4	S - Symmetric	LED	HO - High Output VHO - Very High Output XHO - Extreme High Output	CW - Cool White (5000K) NW - Neutral White (4000K) WW - Warm White (3500K)	UE - Universal Voltage (120-277V) 347 - 347V	CL - Clear Lens W6C163[1] - 6-foot, 16 gauge, 3 conductor cord with Wet Location fitting W6C164[1] - 6-foot, 16 gauge, 4 conductor cord with Wet Location fitting W6C165[1] - 6-foot, 16 gauge, 5 conductor cord with Wet Location fitting HUB - 3/4" N.P.T. HUB IN BACK / TOP (Damp Location Rated Only) LT - Lens Safety Teather EM - 1100 Lumen Emergency Battery Pack SD50 - Step Dimming to 50%

ACCESSORY ORDERING INFORMATION

Description	Order Number
Stainless Suspension Hangers ("V" Hook) (Pair)	EGWVB
Cable Hanging Set with Loop 10 ft. (pair)	LCH10
Cable Hanging Set with Loop 20 ft. (pair)	LCH20
Stainless Steel Surface Bracket	EGWSB

1- Specific voltage must be specified. Cord feed entrance available on housing end only.

Project Name Water treatment plant **Fixture Type** 406

Catalog # EGW 4 S LED HO CW 347V

© 2016 LSI INDUSTRIES INC.

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 52 01 - Unit Equipment for Emergency Lighting

Date: July 23, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 23, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-09R1 (ELE009)
PO-P18-152 Nedco52

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [X] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 26 52 01 Unit Equipment for Emergency Lighting

Section 26 53 00 Exit Signs

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-009-R1

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [ ] REVIEWED
- [x] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-30

BY Konrad Goluch

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the Contractor.

Do not hesitate to contact me if you have any questions or concerns.

WSA LIGHT ENERGY DESIGN LTD
101-5420 CANOTEK RD
OTTAWA, ON K1J 1E9
Phone: 613-745-0001
Fax: 613-745-0002
Contact: Strachan, Hayden

Iqaluit WWTP

18-21616-1

7/19/2018

Project 18-21616-1
Iqualuit WWTP

Submitted By
WSA LIGHT ENERGY DESIGN LTD

Type	Manufacturer/Brand	Catalog Number
DRH-XP	Aimlite	RMHZ-2112-24V6WLA/MR16/CM
BP1+2	Aimlite	EBHZ-2414411CD-2Z16WLA
EX-XP	Aimlite	RPZN21GRY
DRH	Aimlite	RMMD2-12-24V6WLA
BP# 3,5,6,7	Aimlite	EBST24144-2MD5WLA-WHT-ATD/AMP-VLT
BP #4	Aimlite	EBST24350-2MD5WLA-WHT-ATD/AMP-VLT
EX	Aimlite	RPSTUMWHT-UNVDC

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RMHZ-2112-24V6WLA/MR16/CM Notes 8-10 weeks	Type DRH-XP

RMHZ

Hazardous location remote fixture

6, 12 or 24VDC Models

Wall, Ceiling or Pendant Mount

Project: _____

Type: _____

Catalogue #: _____

Drawn by: _____

Date: _____

Designed to meet the strictest Codes, the RMHZ series of hazardous location remote fixtures provides safe and dependable operation. The RMHZ series housings are built with die cast, copper free aluminum, in a variety of Class and Division rated models. Available as 6V, 12V or 24V models with wall, ceiling or pendant mounted configuration.



FEATURES AND SPECIFICATIONS

CIRCUITRY - AC & AC/DC

- Single or double internal MR11 or MR16 lamp assemblies
- Quartz-halogen or LED lamps

MECHANICAL

- Die cast, copper free aluminum, grey finish
- Heavy-duty Pyrex glass lens
- Internal MR11 or MR16 lamp assembly is fully adjustable
- Wall, ceiling or pendant mounting (as specified)
- Wiring pre-pulled through fixture
- Wall and ceiling models c/w integrated die cast junction box
- Junction box c/w oversized integral mounting holes and tapped and plugged rigid holes
- Temperature code: T6

APPROVALS

- CSA Certified to C22.2 #137
- CSA Certified to C22.2 #141-15
- Class I, Division 1, Groups C & D
- Class I, Zone 1 & 2, Groups IIA & IIB

COMPLIANCE

- Meets requirements of ICES-005


LED

HAZARDOUS LOCATION


ICES 005

DIMENSIONS


PENDANT MOUNT



CEILING MOUNT



WALL MOUNT



OVERVIEW

Light source	Quartz or LED
DC voltage	6VDC, 12VDC or 24VDC

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RMHZ-2112-24V6WLA/MR16/CM Notes 8-10 weeks	Type DRH-XP

RMHZIII

ORDERING GUIDE - LED

RMHZ ____ ____ — ____ ____ ____ 1 1 CD / ____

Series	Head	Nbr of lamps	Voltage	Wattage	Lamp type	Mounting	Class	Div.	Group	Options
RMHZ	1 - Single 2 - Double (with J-Box)	1 - Single lamp per head 2 - Double lamp per head	06-24 - 6VDC to 24VDC operational 12-24 - 12VDC to 24VDC operational	4W - 4 watts 5W - 5 watts 6W - 6 watts 7W - 7 watts	LR - LED LA - LED	C - Ceiling mount P - Pendant mount M - Wall mount	1	1	C D	LGD - Die cast lens guard

ORDERING GUIDE - INCANDESCENT

RMHZ ____ ____ — ____ ____ WQ ____ 1 1 CD / ____

Series	Head	Nbr of lamps	Voltage	Lamp	Lamp type	Mounting	Class	Div.	Group	Options
RMHZ	1 - Single 2 - Double (with J-Box)	1 - Single lamp per head 2 - Double lamp per head	06 - 6VDC 12 - 12VDC 24 - 24VDC	See lamp selection	WQ - Quartz halogen	C - Ceiling mount P - Pendant mount M - Wall mount	1	1	C D	LGD - Die cast lens guard

LAMP SELECTION

	6 Volts	12 Volts	24 Volts
MR11 • Small head			
Quartz halogen	10WQ	20WQ	20WQ

MOUNTING SHALL BE TO SUIT LOCATION

All products are subject to change or may be discontinued any time without notice.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number EBHZ-2414411CD-2Z16WLA Notes 8-10 weeks	Type BP1+2

EBHZ

Hazardous location battery unit

6, 12 or 24VDC Models

120/347VAC Input

Project: _____

Type: _____

Catalogue #: _____

Drawn by: _____

Date: _____

Designed to meet the strictest codes and standards, the EBHZ series of hazardous location battery units provides safe and dependable operation. The EBHZ series housings are built with die cast, copper free aluminum, in a variety of Class and Division rated models. Available in 6, 12 and 24VDC models in a range of capacities from 36 to 320W, for 30 minutes duration.



FEATURES AND SPECIFICATIONS

CIRCUITRY

- Range of input voltages 120 or 347VAC
- Single or double internal MR11 or MR16 lamp assemblies
- 6VDC, 12VDC or 24VDC emergency power output versions (as specified)
- Wattage capacities from 36 to 320W
- 30 minutes emergency power duration standard
- Diagnostic/pilot LED for AC ON
- High efficiency, rapid recovery, precision control charging system
- Brownout and short circuit protection
- Temperature compensated
- Large magnum terminal screw type connectors for remote load connection
- Maintenance free, sealed lead acid battery

MECHANICAL

- Die cast, copper free aluminum housing - grey aluminum finish
- Housing cavity accessed via large circular screw on/off cover plate
- Standard stainless steel one-way breather valve for release of gases and/or moisture condensation
- Housing c/w tapped and plugged rigid holes
- Solid state design and construction
- Oversized integral mounting holes/forks accept heavy-duty mounting hardware
- Internal MR11 or MR16 lamp assembly is fully adjustable
- Temperature code: T6

APPROVALS

- CSA Certified to C22.2 #137
- CSA Certified to C22.2 #141-15
- Class I, Division 1, Groups C & D
- Class I, Zone 1 & 2, Groups IIA & IIB

COMPLIANCE


- Meets requirements of ICES-005

HAZARDOUS LOCATION


ICES 005

DIMENSIONS

ENCLOSURE A



ENCLOSURE B



Dimensions are subject to change according to exact Class, Division & Group specifications.

OVERVIEW

Input voltage	120 or 347V AC
DC voltage	6VDC, 12VDC or 24VDC
Output power	36W - 320W

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number EBHZ-2414411CD-2Z16WLA Notes 8-10 weeks	Type BP1+2

EBHZIII

ORDERING GUIDE

EBHZ			1	1	CD		—			

Series	Voltage	Wattage	Class	Div.	Group	Input voltage	Head	Lamp/Head	Lamp
EBHZ	**06 -** 6VDC **12 -** 12VDC **24 -** 24VDC	See model rating below	1	1	C D	**Blank -** 120/347V	**1Z -** Single **2Z -** Double	**1 -** Single lamp assembly **2 -** Double lamp assembly	See lamp selection below 6WLA

LAMP SELECTION

	6 Volts	12 Volts	24 Volts
MR11 • Small head			
Quartz halogen	10WQ	20WQ	20WQ
MR16			
LED	4WLR, 5WLA	4WLR, 5WLA, 6WLA, 7WLA	4WLR, 5WLA, 6WLA, 7WLA

MODEL RATINGS

Wattage capacities

Model	Enclosure	Voltage	30 min.	60 min.	90 min.	120 min.
EBHZ06036	A	6VDC	36	18	12	9
EBHZ06050	A	6VDC	50	25	16	12
EBHZ06072	A	6VDC	72	36	24	18
EBHZ12036	A	12VDC	36	18	12	9
EBHZ12050	A	12VDC	50	25	16	12
EBHZ12072	A	12VDC	72	36	24	18
EBHZ12100	A	12VDC	100	50	33	25
EBHZ12160	B	12VDC	160	80	53	40
EBHZ12200	B	12VDC	200	100	66	50
EBHZ24144	A	24VDC	144	72	48	36
EBHZ24320	B	24VDC	320	160	106	80

All products are subject to change or may be discontinued any time without notice.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RMMD2-12-24V6WLA Notes stock-2 weeks	Type DRH

RMMD

Project:

Contractor:

COMPACT REMOTE

MR16 Surface Mount
Single, Double or Triple
6V, 12V, & 24V Lamps




Approvals:
CSA Certified to C22.2 #141.15

DESCRIPTION

The RMMD series of commercial MR16 remotes provides exceptional light output in a compact, traditional design. The die cast, all metal housing is fully adjustable with a friction lock tilt and swivel that can be locked in place with a rear mounted set screw. The canopy is designed to mount directly to typical electrical junction boxes. Available in 6V, 12V and 24V models, all utilizing low glare, MR16 quartz halogen or LED lamps.

DIMENSIONS



MECHANICAL

- Die cast, solid metal housing with die cast, twist lock lamp collar
- Complete adjustablity - both tilt and swivel
- 5" diameter canopy standard
- Two canopy mounting holes designed to match standard electrical junction boxes
- White paint finish is standard, black colour is optional
- MR16 lamp designed with low glare reflector and available in 6VDC, 12VDC or 24VDC

ORDERING GUIDE – LED

RMMD ____ — ____ ____ ____ / ____

Series	Number of heads	Voltage	Wattage	Lamp type	Colour	Options†
RMMD	**1** - Single head **2** - Double head ~~**3** - Triple head~~ **4** - Quad head (require 12" dia. canopy)	**06 - 24** - 6VDC to 24VDC operational	**4W** - 4 watts	**LR** - LED	**WHT** - White (standard) ~~**BLK** - Black~~	**LCP, VDR, WRG, LXG**
			5W - 5 watts	**LA** - LED		
		12 - 24 - 12VDC to 24VDC operational	**6W** - 6 watts ~~**7W** - 7 watts~~	**LA** - LED		

ORDERING GUIDE – INCANDESCENT

RMMD ____ — ____ ____ ____ / ____

Series	Number of heads	Voltage	Lamp	Colour	Options†
RMMD	**1** - Single head **2** - Double head **3** - Triple head **4** - Quad head (require 12" dia. canopy)	**06V** - 6VDC **12V** - 12VDC **24V** - 24VDC	See lamp selection chart	**WHT** - White (standard) **BLK** - Black	**LCP, VDR, WRG, LXG**

INCANDESCENT LAMP SELECTION

	6 Volts	12 Volts	24 Volts
MR16 - Small head			
Quartz halogen	08Q, 10Q, 12Q, 20Q	08Q, 10Q, 12Q, 20Q, 35Q, 50Q	10Q, 12Q, 20Q, 35Q, 50Q

† For detailed options descriptions, please consult the options page.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number EBST24144-2MD5WLA-WHT-ATD/AMP-VLT Notes (please note AUD is not included not on spec sheet?) 2-3 weeks	Type BP# 3,5,6,7


EBST

Project:

Contractor:

STEEL BATTERY UNIT

6V, 12V or 24V Models
18-720W Capacity
120/347VAC Input





Approvals:
CSA Certified to C22.2 #141.15

DESCRIPTION


The EBST series of commercial steel battery units is designed to provide efficient and reliable emergency lighting. Utilizing a sturdy, all steel housing, the EBST presents a modern and unobtrusive design. On higher capacity models, the cabinet front is sloped to allow better internal access and superior low angle light distribution. The EBST series is available in 6VDC, 12VDC and 24VDC versions in a range of wattage capacities between 18 and 720W, for 30 minutes duration. Units are typically supplied with two top mounted PAR18 or PAR36 type heads, however a wide range of head type, number and placement are available including MR16 type. The EBST can also accommodate a wide variety of options, including auto-testing self-diagnostics and remote testing.

MECHANICAL

- Rugged steel cabinet with ultraguard rust-coating
- 120VAC line cord supplied standard
- Universal spider knockout pattern and keyhole mounting slots stamped into back of cabinet
- Multiple conduit entry knockouts
- White powder coat finish standard, other finishes and Colours optional
- Lamp heads include PAR18 small style, PAR36 large style and die cast metal MR16 type
- Top head mounting is standard, side mount is optional

CIRCUITRY

- 120/347VAC 60Hz Input, field selectable
- High efficiency, rapid recovery, precision control charging system
- 6VDC, 12VDC or 24VDC emergency power output versions (as specified)
- Wattage capacities from 18 to 720W
- 30 Minutes emergency power duration standard
- Momentary push button test switch
- Diagnostic/pilot LEDs for AC ON and CHARGE
- Fully automatic, current limited charger
- Line latched, low voltage protection
- Solid state design and construction
- Brownout and short circuit protection
- Temperature compensated
- Load connection 72W and above
- Complete battery recharge in 24 hours
- Maintenance free, sealed lead acid battery
- Optional automatic-testing, self-diagnostic charger board:
  - Continuously monitors the operational status of the battery unit
  - Automatically performs battery and lamp load testing at preset intervals
  - Indicates any component malfunctions or automated test failures



Type SM – PAR18 Thermoplastic 18W max.
Type MD – MR16 Die cast 35W max.
Type MB – MR16 Die cast 35W max.
Type LG – PAR36 Thermoplastic 70W max.

ORDERING GUIDE

EBST ____ ____ — ____ ____ / ____

Series	Voltage	Wattage	Head/Lamp		Lamp	Colour	Options†
EBST	**06** - 6VDC **12** - 12VDC **24** - 24VDC	See model rating below 144	**0** - No Heads **1SM** - One PAR18 **2SM** - Two PAR18 **1LG** - One PAR36 **2LG** - Two PAR36	**1MD** - One MR16 **2MD** - Two MR16 **1MB** - One MR16 **2MB** - Two MR16	See lamp list below 5WLA	**WHT** - White (standard) **BLK** - Black **GRY** - Grey	**ATD, TDL*, LPD, BTD, VLT, AMP, ACT, DCT, FS4, RDS*, NLC, TLP, CAB, VDR, MTS, WRG, IRT, IRC**

† For detailed options descriptions, please consult the options page. * Specify AC voltage.

LAMP SELECTION

	6 Volts	12 Volts	24 Volts
PAR18 - Small head or LED Lamp			
LED	3WLJ, 4WLJ, 5WLA	3WLJ, 4WLJ, 5WLA, 6WLA, 7WLA	4WLR, 5WLA, 6WLA, 7WLA
Quartz halogen	08WQ, 10WQ, 12WQ	10WQ, 12WQ	12WQ
Tungsten	09WT	09WT, 12WT, 18WT	09WT, 18WT
MR16 - Small head c/w MR16 or LED Lamp			
LED	4WLR, 5WLA	4WLR, 5WLA, 6WLA, 7WA	4WLR, 5WLA, 6WLA, 7WLA
Quartz halogen	08WQ, 10WQ, 12WQ, 20WQ	08WQ, 10WQ, 12WQ, 20WQ, 35WQ	10WQ, 12WQ, 20WQ
PAR36 - Large head			
Quartz halogen	08WQ, 10WQ, 12WQ, 20WQ	10WQ, 12WQ , 20WQ, 35WQ	12WQ
Tungsten	09WT, 18WT, 25WT	09WT, 18WT, 25WT	09WT, 18WT, 25WT
Quartz sealed beam	08WSBQ, 10WSBQ, 12WSBQ, 20WSBQ	08WSBQ, 12WSBQ, 35WSBQ, 55WSBQ	70WSBQ
Tungsten sealed beam	08WSBT, 09WSBT, 18WSBT	25WSBT	N/A

MODEL RATINGS

		Wattage Capacities				
Model	Voltage	30 min.	60 min.	90 min.	120 min.	Cabinet
EBST-06018	6V	18	9	N/A	N/A	A
EBST-06036	6V	36	18	12	9	A
EBST-06050	6V	50	25	16	12	A
EBST-06072	6V	72	36	24	18	B
EBST-06100	6V	100	50	33	25	B
EBST-06160	6V	160	80	53	40	C
EBST-06180	6V	180	90	60	45	C
EBST-12036	12V	36	18	12	9	A
EBST-12050	12V	50	25	16	12	A
EBST-12072	12V	72	36	24	18	A
EBST-12100	12V	100	50	33	25	B
EBST-12144	12V	144	72	48	36	C
EBST-12160	12V	160	80	53	40	C
EBST-12200	12V	200	100	66	50	C
EBST-12250	12V	250	125	83	62	D
EBST-12360	12V	360	180	120	90	D
EBST-24144	24V	144	72	48	36	C
EBST-24288	24V	288	144	96	72	D
EBST-24320	24V	320	160	106	80	D
EBST-24350	24V	350	175	116	87	E
EBST-24550	24V	550	275	183	137	E
EBST-24720	24V	720	360	240	180	E

NOTE: Due to cabinet/space limitations, not all options are available for all models in any given combination. Please consult with your factory representative regarding specific options and exact cabinet dimension information.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number EBST24350-2MD5WLA-WHT-ATD/AMP-VLT Notes (please note AUD is not included not on spec sheet?) 2-3 weeks	Type BP #4


EBST

Project: Contractor:

STEEL BATTERY UNIT

6V, 12V or 24V Models
18-720W Capacity
120/347VAC Input

Approvals:
CSA Certified to C22.2 #141.15





DESCRIPTION


The EBST series of commercial steel battery units is designed to provide efficient and reliable emergency lighting. Utilizing a sturdy, all steel housing, the EBST presents a modern and unobtrusive design. On higher capacity models, the cabinet front is sloped to allow better internal access and superior low angle light distribution. The EBST series is available in 6VDC, 12VDC and 24VDC versions in a range of wattage capacities between 18 and 720W, for 30 minutes duration. Units are typically supplied with two top mounted PAR18 or PAR36 type heads, however a wide range of head type, number and placement are available including MR16 type. The EBST can also accommodate a wide variety of options, including auto-testing self-diagnostics and remote testing.

MECHANICAL

- Rugged steel cabinet with ultraguard rust-coating
- 120VAC line cord supplied standard
- Universal spider knockout pattern and keyhole mounting slots stamped into back of cabinet
- Multiple conduit entry knockouts
- White powder coat finish standard, other finishes and Colours optional
- Lamp heads include PAR18 small style, PAR36 large style and die cast metal MR16 type
- Top head mounting is standard, side mount is optional

CIRCUITRY

- 120/347VAC 60Hz Input, field selectable
- High efficiency, rapid recovery, precision control charging system
- 6VDC, 12VDC or 24VDC emergency power output versions (as specified)
- Wattage capacities from 18 to 720W
- 30 Minutes emergency power duration standard
- Momentary push button test switch
- Diagnostic/pilot LEDs for AC ON and CHARGE
- Fully automatic, current limited charger
- Line latched, low voltage protection
- Solid state design and construction
- Brownout and short circuit protection
- Temperature compensated
- Load connection 72W and above
- Complete battery recharge in 24 hours
- Maintenance free, sealed lead acid battery
- Optional automatic-testing, self-diagnostic charger board:
  - Continuously monitors the operational status of the battery unit
  - Automatically performs battery and lamp load testing at preset intervals
  - Indicates any component malfunctions or automated test failures



Type SM – PAR18
Thermoplastic
18W max.

Type MD – MR16
Die cast
35W max.

Type MB – MR16
Die cast
35W max.

Type LG – PAR36
Thermoplastic
70W max.

ORDERING GUIDE

EBST — /

Series	Voltage	Wattage	Head/Lamp		Lamp	Colour	Options†
EBST	**06** - 6VDC **12** - 12VDC **24** - 24VDC	See model rating below 350	**0** - No Heads **1SM** - One PAR18 **2SM** - Two PAR18 **1LG** - One PAR36 **2LG** - Two PAR36	**1MD** - One MR16 **2MD** - Two MR16 **1MB** - One MR16 **2MB** - Two MR16	See lamp list below 5WLA	**WHT** - White (standard) **BLK** - Black **GRY** - Grey	**ATD, DL*, LPD, BTD, VLT, AMP, ACT, DCT, FS4, RDS*, NLC, TLP, CAB, VDR, MTS, WRG, IRT, IRC**

† For detailed options descriptions, please consult the options page. * Specify AC voltage.

LAMP SELECTION

	6 Volts	12 Volts	24 Volts
PAR18 - Small head or LED Lamp			
LED	3WLJ, 4WLJ, 5WLA	3WLJ, 4WLJ, 5WLA, 6WLA, 7WLA	4WLR, 5WLA, 6WLA, 7WLA
Quartz halogen	08WQ, 10WQ, 12WQ	10WQ, 12WQ	12WQ
Tungsten	09WT	09WT, 12WT, 18WT	09WT, 18WT
MR16 - Small head c/w MR16 or LED Lamp			
LED	4WLR, 5WLA	4WLR, 5WLA, 6WLA, 7WA	4WLR, 5WLA, 6WLA, 7WLA
Quartz halogen	08WQ, 10WQ, 12WQ, 20WQ	08WQ, 10WQ, 12WQ, 20WQ, 35WQ	10WQ, 12WQ, 20WQ
PAR36 - Large head			
Quartz halogen	08WQ, 10WQ, 12WQ, 20WQ	10WQ, 12WQ , 20WQ, 35WQ	12WQ
Tungsten	09WT, 18WT, 25WT	09WT, 18WT, 25WT	09WT, 18WT, 25WT
Quartz sealed beam	08WSBQ, 10WSBQ, 12WSBQ, 20WSBQ	08WSBQ, 12WSBQ, 35WSBQ, 55WSBQ	70WSBQ
Tungsten sealed beam	08WSBT, 09WSBT, 18WSBT	25WSBT	N/A

MODEL RATINGS

		Wattage Capacities				
Model	Voltage	30 min.	60 min.	90 min.	120 min.	Cabinet
EBST-06018	6V	18	9	N/A	N/A	A
EBST-06036	6V	36	18	12	9	A
EBST-06050	6V	50	25	16	12	A
EBST-06072	6V	72	36	24	18	B
EBST-06100	6V	100	50	33	25	B
EBST-06160	6V	160	80	53	40	C
EBST-06180	6V	180	90	60	45	C
EBST-12036	12V	36	18	12	9	A
EBST-12050	12V	50	25	16	12	A
EBST-12072	12V	72	36	24	18	A
EBST-12100	12V	100	50	33	25	B
EBST-12144	12V	144	72	48	36	C
EBST-12160	12V	160	80	53	40	C
EBST-12200	12V	200	100	66	50	C
EBST-12250	12V	250	125	83	62	D
EBST-12360	12V	360	180	120	90	D
EBST-24144	24V	144	72	48	36	C
EBST-24200	24V	200	100	66	50	C
EBST-24320	24V	320	160	106	80	D
EBST-24350	24V	350	175	116	87	E
EBST-24560	24V	560	285	190	137	E
EBST-24720	24V	720	360	240	180	E

NOTE: Due to cabinet/space limitations, not all options are available for all models in any given combination. Please consult with your factory representative regarding specific options and exact cabinet dimension information.

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

26 53 00 - Exit Signs

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RPSTUMWHT-UNVDC Notes stock-2 weeks	Type EX

RPST

Project:

Contractor:

STEEL
NBC2010 Compliant



Approvals:
CSA Certified to C22.2 #141.15 and C860


DESCRIPTION
The clean lines of the RPST series of commercial steel signs present a fully modern appearance. The steel provides for a rigid, durable and lightweight sign. Available in AC only, AC/DC and internally self-powered versions.

CIRCUITRY - AC & AC/DC
- LED ultra bright light source
- 120/347VAC Input, field selectable
- 1.9W power consumption single or double face
- Emergency DC wattages as follows:
  6VDC = 0.9W **12VDC** = 0.9W **24VDC** = 0.9W

CIRCUITRY - SELF-POWERED
- LED ultra bright light source
- 120/347VAC Input, field selectable
- 2.0W power consumption single or double face
- High-performance, Ni-Cad battery
- 90 or 120 minutes emergency duration
- Solid state transfer and battery charger

MECHANICAL
Supply and install AimLite Steel LED Running Man sign in accordance with NBC2010, C22.2 No. 141. The equipment shall operate with universal AC input of 120/347V at less than 2.0W and universal DC input voltage from 6V to 24V. The housing shall be constructed of rugged steel and have a maximum depth of 2-1/4". The faceplates shall be open face type with a steel contour. The light source shall be high performing light emitting diodes (LED) and the LED lamps shall provide illumination in normal and emergency operation and shall be mounted inside the Running Man housing. A white LED sensitive diffuser shall be used to provide an evenly illuminated green and white legend. Universal models include ceiling or end mount, field installable canopy kit c/w spider plate. Universal models include ceiling or end mount, field installable canopy kit c/w spider plate.

The Running Man in a self powered configuration shall be equipped with a nickel cadmium battery and shall stay illuminated during emergency operation for at least 90 or 120 minutes upon AC fail.

DIMENSIONS




Comes standard (single face) with three pictogram legends for direction selection.



Comes standard (double face) with two pictogram legends.



For double face no arrow options, select "0" on the options column.

ORDERING GUIDE

RPST		M		—		/	

Series	Nbr of faces	Mounting	Colour	DC Voltage	Options†
RPST	**U** - Universal faces **1** - Single face **2** - Double face	**M** - Universal	**WHT** - White (standard) **BLK** - Black **GRY** - Grey **CUS** - Custom colour (please specify)	**NDC** - AC only **UNVDC** - Universal DC backup voltage from 6 to 24VDC **BAT** - Self-powered for 90 minutes **BAT1** - Self-powered for 120 minutes	**ATD*, WRG**, K5, LXG, SPW, BKO, BNO** **0** - No indicators (double face only) **D U UR DR DL UL** **Note:** Indicators option available for single & double option only.

† For detailed options descriptions, please consult the options page.
* ATD available with BAT and BAT1.
** Specify mounting.

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RPZN21GRY Notes 2-4 weeks	Type EX-XP

RPZN2

Hazardous location

AC, AC/DC & Self-Powered

Project: _____

Type: _____

Catalogue #: _____

Drawn by: _____

Date: _____

The RPZN2 series of Class I, Division II / Zone 2 rated running man are designed to perform in demanding hazardous applications. The unit maintains its sealed interior with a continuous integral gasket. As well LED pilot light and test switch are sealed type.



(self powered version)

FEATURES AND SPECIFICATIONS

ELECTRICAL - AC/DC

- LED ultra bright light source
- 120/347VAC Input, field selectable
- 3.6 Watt power consumption
- Emergency DC wattages as follows:
  6VDC = 1.8W **12VDC** = 1.8W **24VDC** = 1.8W

ELECTRICAL - SELF-POWERED

- LED ultra bright light source
- 120/347VAC Input, field selectable
- 4 Watt power consumption
- High-performance, sealed Ni-Cad battery
- 90 minutes emergency duration (standard)
- Solid state transfer and battery charger

MECHANICAL

- Heavy-duty non-metallic, reinforced construction
- One piece, molded and gasketed lens
- Bottom hinged cover secured with two screws
- One-way breather valve for release of gases and/or moisture condensation
- All external metal hardware is stainless steel
- Single face, wall mount only
- Grey finish housing, white faceplate standard

APPROVALS

- CSA Certified to C22.2 #137
- CSA Certified to C22.2 #141-15
- CSA Certified to C860-11
- Class I, Division 2, Groups A, B, C, D
- Class I, Zone 2, Groups IIA, IIB, IIC

COMPLIANCE


- Meets requirements of ICES-005


LED

HAZARDOUS LOCATION

ICES 005

DIMENSIONS







Comes standard (single face) with three pictogram legends for direction selection.

OVERVIEW

Light source	LED
Input voltage	120/347V AC
Input power	3.6W AC/DC 4W self-powered
DC voltage	6VDC, 12VDC or 24VDC
DC power	1.8W

WSA LIGHT ▪ ENERGY ▪ DESIGN	Project 18-21616-1 Iqualuit WWTP Submitted By WSA LIGHT ENERGY DESIGN LTD	Catalog Number RPZN21GRY Notes 2-4 weeks	Type EX-XP

RPZN2

ORDERING GUIDE

RPZN2	1	GRY	—	/

Series	Nbr of faces	Colour	Operation	Options
RPZN2	1 - Single face	GRY - Grey	UNVDC - Universal DC backup voltage from 6 to 24VDC BAT - Self-powered for 90 minutes	D U UR DR DL UL

TEMPERATURE CODES

	25°C	40°C
UNVDC	T6	T6
BAT	T6	T5

EXIT SIGN AS SPEC 26 53 00 2.1 .8, SELF POWERED NOT ALOWED.

Comments

All products are subject to change or may be discontinued any time without notice.

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

28 16 05 - Intrusion Detection

Date: July 11, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jul 11, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

SE-01R2
PO-P18-123

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [ ] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [x] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 28 16 05 Intrusion Detection

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-001-R2

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

- [ ] Architectural
- [ ] Structural
- [ ] Mechanical
- [x] Electrical
- [ ] Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

- [x] REVIEWED
- [ ] REVIEWED, AS NOTED
- [ ] REVISE AND RESUBMIT
- [ ] NOT REVIEWED

DATE 2018-07-16

BY Konrad Goluch

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the contractor.


Do not hesitate to contact me if you have any questions or concerns.

B208 Octo-input Module

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- Programmable input point functions
- Easy to read switch addressing
- 2 interconnect wiring connectors
- Provides eight points

The B208 Octo-input Module is an 8 point expansion device that connects to the control panel through the SDI2 bus. This module is fully supervised and communicates back to the control panel all point status changes. The module expansion points operate the same as the points on the control panel. Industrial, commercial, and institutional facilities are typical installations for the B208 module. The B208 connects to the SDI2 bus on the control panel using SDI2 terminals, or using the interconnect cable. You can connect multiple B208 modules to a single control panel. The B208 address switches allow for ease of use in device addressing.

System overview

The B208 Octo-input Module connects to a control panel through the SDI2 bus. This module is supervised and communicates back to the control panel all point status changes. The module's expansion points operate the same as the points on the control panel.

Functions

Loop inputs
The B208 uses up to eight inputs which may be Normally Open (NO), or Normally Closed (NC) with 1k Ω EOL resistor(s) for supervision.

Certifications and approvals

Region	Certification	
Australia	RCM	ACMA
Europe	CE	EMC, RoHS
USA	UL	
	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 609 - Standard for Local Burglar Alarm Units and Systems
	UL	UL 636 - Holdup Alarm Units and Systems
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems
	UL	UL 985 - Household Fire Warning System Units
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL	UL 1610 - Central Station Burglar Alarm Units
	FM	FM 3010 - Fire Alarm Signaling Systems
	CSFM	see our website

28 16 05

Region	Certification	
	FCC	Part 15 Class B
	FDNY-CoA	6174
	FDNY-CoA	6196
Canada	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units
	ULC	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems
	IC	ICES-003 - Information Technology Equipment (ITE)

Installation/configuration notes

Wiring considerations

The module to the control panel using the PWR, A, B, COM terminals on the control panel using the screw terminal strip or the interconnect wiring connector. Use 12 AWG to 22 AWG (1.5 mm to 0.6 mm) wires from the module to the control panel.

Compatibility

For UL 864 compliance, use a UL commercial fire approved control panel.

Control panels	B9512G/B9512G-E (Up to 59 modules) B8512G/B8512G-E (Up to 9 modules) B6512 (Up to 9 modules) B5512/B5512E (Up to 4 modules) B4512/B4512E (Up to 2 modules) D9412GV4 (Up to 24 modules) D7412GV4 (Up to 7 modules) D7212GV4 (Up to 3 modules)

Parts included

Quantity	Component
1	Module
1	Hardware pack
1	Interconnect cable
1	Installation manual

Technical specifications

Properties

Dimensions	2.5 in x 3.8 in x 0.60 in (6.37 cm x 9.6 cm x 1.5 cm)

Environmental considerations

Relative humidity	5% to 93% at +32°C (+90°F)
Temperature (operating)	0°C to +49°C (+32°F to +120°F)

Power requirements

Current	35 mA
Voltage	12 VDC nominal

Wiring

SDI2 wiring	Maximum distance – Wire size (unshielded wire only): 1000 ft (305 m) – 22 AWG (0.65 mm) 1000 ft (305 m) – 18 AWG (1.02 mm) Unshielded wire only

Loop inputs

Loop Inputs	Up to eight inputs. Input contacts may be Normally Open (NO) or Normally Closed (NC) with 1kΩ EOL resistor(s) for supervision. Note: Normally Closed (NC) is not permitted in Fire installations.

Ordering information

B208 Octo-input Module
Provides 8 programmable inputs.
Order number **B208**

28 16 05

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia


© Bosch Security Systems 2017 | Data subject to change without notice
2536957579 | en, V25, 17. Feb 2017

B430 Plug-in Telephone Communicator

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- Provides a single telephone line with RJ-45 connection for central station reporting and remote programming
- Easily configured for communications from Remote Programming Software (RPS) or a keypad, eliminating the need for separate configuration
- Easy two-step plug-in installation, troubleshooting, and maintenance

The B430 provides communication over the PSTN (Public Switched Telephone Network) by connecting the PSTN to the control panel. The module provides a single telephone jack, and easily installs into the control panel on-board plug-in module connector.

Functions

Central station reporting
The B430 supports reporting to a central station receiver through the telephone lines.
Remote programming of Bosch control panels
The B430 supports secure RPS programming of compatible Bosch control panels.

Certifications and approvals

Region	FCC Details
USA	FCC Registration Number: ESVAL00BB430 Ringer Eq: 0.0B

Region	Certification	
Australia	RCM	ACMA
Europe	CE	EMC, RoHS
USA	UL	UL 365 - Police Station Connected Burglar Alarm Units

Region	Certification	
	UL	UL 636 - Holdup Alarm Units and Systems
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems
	UL	UL 985 - Household Fire Warning System Units
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL	UL 1610 - Central Station Burglar Alarm Units
	CSFM	see our website
	FCC	Part 15 Class B
	FCC	Part 68
	FDNY-CoA	6174
Canada	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	CAN/ULC S545 - Residential Fire Warning System Control Units

28 16 05

Region	Certification	
	ULC	CAN/ULC S559 - Fire Signal Receiving Centres and Systems
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units
	ULC	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems
	IC	ICES-003 - Information Technology Equipment (ITE)
Brazil	ANATEL	1709-13-1855 [B430]

Installation/configuration notes

Mounting considerations

Connect the B430 Plug-in Telephone Communicator to any compatible control panel or interface module, which can then be mounted in a variety of enclosures for optimal situations.

Wiring considerations

The B430 connects to the control panel or interface modules without tools or physical wiring for power. It has an RJ-45 jack for plugging in the phone line (PSTN).

Communication speed

The module communicates at 2400 baud maximum.

Compatibility

Control panels	B9512G/B9512G-E B6512 B8512G/B8512G-E B5512/B5512E B4512/B4512E B3512/B3512E
Phone cords	D161 Dual Modular Telephone Cord D162 Modular Telephone Cord
Phone jack	D166 Telephone Jack

Parts included

Quantity	Component
1	B430 Plug-in Telephone Communicator
1	Literature pack

Technical specifications

Properties

Dimensions	2 in x 3.68 in x 0.60 in (50 mm x 93.5 mm x 15.25 mm)
Weight	1.3 pounds (0.6 KG)

Environmental considerations

Relative humidity	5% to 93% at +32°C (+90°F)
Temperature (operating)	0°C to +49°C (+32°F to +120°F)

Power requirements

Current (maximum)	Standby: 24 mA Alarm: 24 mA
Voltage (operating)	12 VDC nominal

Ordering information

B430 Plug-in Telephone Communicator
Plug-in PSTN communication module for control panel to central station receiver communication.
Order number **B430**

28 16 05

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2017 | Data subject to change without notice
18964708491 | en, V8, 17. Feb 2017

B920 Two-line Alphanumeric Keypad (SDI2)

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- 2-line LCD display with up to 32 character point, user, and area names
- Simple menu-style user interface with dedicated function buttons for common commands, including status indication
- Situation sensitive on-screen help makes system operation simple and easy
- Highly visible on (arm)/alarm, ready to turn on (arm), power and gas alarm indicators
- Simple installation with self-locking base and chassis design, plus built-in bubble level

The B920 Two-line Alphanumeric Keypad (SDI2) is a SDI2 bus compatible device. Each keypad has user adjustable options such as volume and display brightness. The B920 shows two-line system messages for all areas.

System overview

- For commercial use, install the keypad in building entrances and areas with unrestricted access. Mounting a keypad near exterior doors in hotel or business lobbies allows people to identify the type and location of the emergency.
- For residential use, install the keypad near the front and rear entrances to the home. Install additional keypads in a kitchen or in a bedroom.
- Use multiple keypads in a large building with many separate areas of security. Program multiple keypads to control multiple areas.
- Audible tones from the keypad sounder alert personnel to fire events and assist fire fighters in locating the keypad.

Functions

LCD display
The keypad uses words, numbers, and symbols to show the status of the security system. When several events occur, the keypad shows each event in order of priority.

Keys
Each keypad has 10 number keys, 7 function keys, and 6 navigation keys. When pressed, keys turn on keypad backlighting and emit the keypress tone (short beep). The function keys include programmable function keys and keys to initiate arming and bypassing with one keypress.

Audible tones
The keypad has a built-in speaker that produces several distinct warning tones. The tones are differentiated so that the user can recognize an event simply by hearing its associated tone. The keypad backlight illuminates when it emits an audible tone. Users can use a passcode to silence the tone.

28 16 05

Status indicators
The status indicators on the keypad provide a quick visual reference for system status.

✓	The indicator lights when the system is ready to turn on (arm).
🔒	The indicator lights when the system is on (armed).
⚠	The indicator lights when there is a trouble condition.
GAS	The indicator lights when dangerous gases are present including carbon monoxide (NFPA 720).
🔌	The indicator lights when the system has power.

Certifications and approvals

Region	Certification	
Australia	RCM	ACMA
Europe	CE	EMC, RoHS
USA	UL	
	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 609 - Standard for Local Burglar Alarm Units and Systems
	UL	UL 636 - Holdup Alarm Units and Systems
	UL	UL 985 - Household Fire Warning System Units
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL	UL 1610 - Central Station Burglar Alarm Units
	CSFM	see our website
	FCC	Part 15 Class B
Canada	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	CAN/ULC S545 - Residential Fire Warning System Control Units
	ULC	CAN/ULC S559 - Fire Signal Receiving Centres and Systems
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units
	ULC	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems
	IC	ICES-003 - Information Technology Equipment (ITE)

Installation/configuration notes

Mounting considerations
Mount in indoor, dry locations.

Power supply
A compatible control panel supplies the power and data requirements to the keypad through a four-wire connection.

Enclosure and wiring
The sliding self-locking enclosure has an integrated bubble level and custom gap-free, lift-gate style terminal blocks to make installation easier.

Compatible control panels
B9512G/B9512G-E
B8512G/B8512G-E
B6512
B5512/B5512E firmware v2.02 and higher
B4512/B4512E firmware v2.02 and higher
B3512/B3512E firmware v2.02 and higher
D9412GV4/D7412GV4 firmware v2.02 and higher

Parts included

Quantity	Component
1	Keypad
1	Hardware pack
1	Set of ABC key labels
1	Installation Guide
1	User's Quick Reference Guide

Technical specifications

Properties

Dimensions	6.2 in x 4.7 in x 1 in (158 mm x 120 mm x 26 mm)
Weight	11.3 oz (0.32 kg)
Material	Acrylonitrile butadiene styrene (ABS) Poly(methyl methacrylate) (PMMA)
Display window	2 line display 18 characters per line
Indicators	Illuminated keys Status indicators Warning and indicating tones

Environmental considerations

Relative humidity	5% to 93% at +32°C (+90°F) non-condensing
Temperature (operating)	0°C to +50°C (+32°F to +122°F)

28 16 05

Power requirements

Current	Standby:35 mA Alarm: 70 mA
Voltage (input)	12 VDC nominal

Wiring

Terminal wire size	12 AWG to 22 AWG (2.0 mm to 0.65 mm)
SDI2 wiring	Maximum distance – wire size (unshielded wire only): 1000 ft (305 m) – 22 AWG (0.65 mm)

Ordering information

B920 Two-line Alphanumeric Keypad (SDI2)
Two-line alphanumeric keypad
Order number **B920**

Accessories

B56 Keypad Surface Mount Box
Surface mount box for mounting a keypad to concrete or block.
Order number **B56**

B96 Keypad Trim Bezel
Cover the wall footprint of previous keypads when replacing them with the new, slim design of B Series keypads. The white trim bezel is 8.6 in x 6.3 in x 0.12 in (22 mm x 16 mm x 3 mm).
Order number **B96**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2017 | Data subject to change without notice
9973643275 | en, V16, 17. Feb 2017

B8103 Enclosure

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- Easy-to-install standoff location for mounting supported modules
- Made with cold-rolled steel with a white semi-gloss finish
- Easy access locations for battery placement
- Optional tamper switch mounting location

The enclosure houses many control panels and modules by Bosch. It is compatible with an enclosure tamper switch and can hold up to two batteries. Use the enclosure for residential fire and burglary installations and commercial burglary applications that do not require attack resistance.

Certifications and approvals

Region	Certification	
USA	UL	UL 294 - Standard for Access Control Units and Systems
	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 609 - Standard for Local Burglar Alarm Units and Systems
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems
	UL	UL 985 - Household Fire Warning System Units
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1610 - Central Station Burglar Alarm Units
	UL	UL 1635 - Standard for Digital Alarm Communicator System Units
	CSFM	see our website
	FDNY-CoA	6196
Canada	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units

Installation/configuration notes

Compatible locksets
D101 (Key #1358)
D101F (Key #203)

Compatible tamper switches
D110
ICP-EZTS

28 16 05

Parts included

Quantity	Component
1	Enclosure
1	Hardware pack
1	Literature pack

Technical specifications

Dimensions	41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.)
Weight	4.5 kg (10 lb)
Material	Cold-rolled steel
Color	White

Ordering information

B8103 Enclosure
White steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).
Order number **B8103**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia


© Bosch Security Systems 2017 | Data subject to change without notice
18395968139 | en, V11, 21. Mar 2017

B8512G Control Panels

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- Fully integrated intrusion, fire, and access control allows users to interface with one system instead of three
- Provides up to 99 points using a combination of hardwired or wireless devices for installation flexibility, and up to 8 areas and 8 doors for up to 500 users
- On-board Ethernet port for Conettix IP alarm communication and remote programming, compatible with modern IP networks including IPv6/IPv4, Auto-IP, and Universal Plug and Play
- Installer-friendly features for simple installation and communications, including on-board USB for easy on-site RPS programming, plus support for Remote Connect Service (not available in Europe, the Middle East, or Africa), and plug-in PSTN and cellular communication modules for simple installation and communications
- Remote Security Control (RSC) app which allows users to control their security systems – and view system cameras - remotely from mobile devices such as phones and tablets

The B9512G Control Panel and the B8512G Control Panel are the new premier commercial control panels from Bosch. B8512G control panels integrate intrusion, fire, and access control providing one simple user interface for all systems.
With the ability to adapt to large and small applications, the B8512G provides up to 99 individually identified points that can be split into 8 areas.
The control panel can communicate through its built-in Ethernet port (not applicable to “E” control panels), or through compatible plug-in modules that can send events over the public switched telephone network (PSTN) or over cellular network communications.

For users, programmable keypad shortcuts, situation sensitive on-screen help, and a bilingual user interface make system operation simple and easy.
With the B8512G, you can:

- Monitor alarm points for intruder, gas, or fire alarms.
- Program all system functions local or remote using Remote Programming Software (RPS) or by using basic programming through the keypad.
- Add up to 8 doors of access control using the optional B901 Access Control Module or D9210C Access Control Interface Module.

The B8512G is a direct replacement for previous control panel models D7412GV4, D7412GV3, D7412GV2, and D7412G.

28 16 05

Functions

Programmable outputs
- Four alarm-output patterns
- Programmable bell test

Point response
- Selectable point response time
- Selectable EOL values and configuration
- Cross point capability
- Fire alarm verification
- Dangerous gas indicator includes carbon monoxide (NFPA 720)
- Watch mode
- Selectable point response time

User interface
- Supervision of up to 32 keypads
- Custom keypad text is fully programmable through RPS
- Full function menu including customizable shortcuts
- Authority by area and 32 character name for each user
- 14 custom authority levels to restrict system features that each user can access
- Programmable primary and secondary language by user and keypad; select from English, Spanish, French, and Portuguese

Area configurations
Link multiple areas to a shared area such as a lobby or common entryway. The shared area then automatically turns On (arms) when all associate areas are armed and turns Off (disarms) when any one associate area is disarmed. For higher security applications, the Area Re-Arm feature guarantees that areas are always rearmed, and are disarmed for no longer than a specific, configurable, amount of time (for example, service time).

Custom functions
For added convenience, the installer can program custom functions that allow customers to complete complex tasks with one simple action. For example, a custom function can bypass a group of points and arm the system, allowing the user to perform these functions with one easy command. Users can activate custom functions with a keypad, keyfob, token, or card, or the control panel can activate a function in reaction to a faulted point, or automatically through a scheduled event (SKED).

Passcode security
- Two-man rule. Requires two people with two unique passcodes to be present at the time of opening.
- Early ambush. Allows users to verify that the facility is safe by requiring two passcodes. The control panel sends a duress event if the user does not enter the passcode a second time after inspecting the premises.
- Dual authentication. Requires two forms of identification before processing certain system commands, including turning off the system and opening doors. A standard system user must have a passcode, a credential (token or card), and appropriate command authority permissions.

Door control
Using the B901 Access Control Module or D9210C Access Control Interface Module, the control panel provides a fully supervised access control solution. The solution offers 14 programmable levels of access authority. Authority for door access is controlled by the user level, the group of the user, the time of day, the door state, and the area armed (On/Off) state.

Easy exit control
The control panel changes from one On (armed) state to another without turning off (disarming) the system. For example, if you change the state from Part On (Perimeter Arm) to All On (Master Arm), the control panel complies and reports the change. Easy Exit Control reduces the number of keystrokes, simplifying system operation.

Programmable passcode-controlled menu list
Passcode-controlled shortcuts provide users only with the options and information pertinent to them, simplifying system operation.

Flexible control
The system provides the flexibility to choose added convenience or high security. For example, you can restrict to a keypad's immediate local area turning on (arming) and turning off (disarming) the system with a passcode, even if the user has access to other areas. This is particularly useful for high security areas, where a user may have access to the area, but would prefer to only turn off (disarm) the area individually rather than with the rest of the system.

Monitor Delay/Delayed Response
Create a special point index that delays the reaction of a point for a specified time (up to 1 hour in minutes and seconds). This delay provides time for the specified condition to reset before activating any annunciation. The system can annunciate locally and send a report, if desired. When the system is armed, the point can respond like a normal point – providing dual functionality. Use this feature to ensure that perimeter doors have not been propped open, or to monitor critical areas such as computer rooms and safes, for example.

System users
The system supports up to 500 users. Each user can have a personalized passcode, a wireless keyfob, and a credential to control the system. You can assign passcodes to one of 14 customized authority levels in each area that can be restricted to operate only during certain times. You can program a primary and secondary language for each user and by keypad (select from English, Spanish, French, and Portuguese). The keypad changes to the user's programmed language when the user enters his passcode or holds the Help key.

28 16 05

Communication formats
The control panel prioritizes and sends reports to four route groups. Network and phone communications can use one of two communication formats: Modem4, Contact ID. Each group has a programmable primary and backup destination.
The control panel provides flexible communications for most central stations with reporting capabilities such as:
- Individual point numbers
- Opening or closing reports by user and area number
- Remote programming attempts
- Diagnostic reports

IP communication
The control panel can use IP to communicate with a Conettix D6600 or a Conettix D6100IPv6 Communications Receiver/Gateway. Use one of the following for IP:
- The on-board Ethernet connection (the on-board Ethernet port is excluded on “E” versions).
- A B426.
- A plug-in cellular communicator (B440/B440-C/B441/B441-C/B442/B443/B444).

Conettix IP communication provides a secure path that includes anti-replay/anti-substitution features, and enhanced security with up to AES 256-bit encryption (using Cipher Block Chaining (CBC)).
The control panel supports Domain Name System (DNS) for both remote programming and central station communication. DNS provides ease of use, eliminating the need to use static IP addresses as your reporting destination, and accommodates a simple solution for central station disaster recovery. The control panel supports both IPv6 and IPv4 networks.

Communication paths
The control panel accommodates up to four separate phone and four separate network paths to the central station receiver. When resetting alarms or turning a system on and off, the user is identified by name and number.

Personal notification
The control panel can send text messages and emails for personal notification over Ethernet or using a cellular communicator. You can configure up to 32 destinations using a combination of cellular phone numbers and email addresses. The control panel sends notifications in the user’s programmed primary language.

Bosch Remote Connect (Cloud)
Remote Connect simplifies connections from RPS, and the Remote Security Control app, using Bosch Cloud services. This service creates a secure connection to the control panel without specific router settings or the need for a static IP address or DNS.

Notice
The Bosch Remote Connect service is not available in Europe, the Middle East, or Africa.

Firmware updates
The system allows remote firmware updates:
- Control panel updates. Remotely update the control panel firmware for easy feature enhancements without replacing ROM chips.
- Module update support. Remotely update the firmware on connected SDI2 modules for easy feature enhancements without visiting each individual module.

Firmware updates occur through Remote Programming Software (RPS) and the RPS Firmware Update Wizard. The Firmware Update Wizard uses the on-board USB connection or the on-board Ethernet (IP) connection (the on-board Ethernet port is excluded on “E” versions) to transfer firmware updates.
The control panel can optionally receive firmware updates from RPS. Use one of the following communication methods:
- B426
- Plug-in cellular communicator: B440/B440-C/B441/B441-C/B442/B443/B444

Notice
Data rate apply
Cellular firmware updates require more time than Ethernet updates and carrier data rates apply.

A wide variety of input options
Each point:
- Single 1 kΩ, single 2 kΩ, dual 1 kΩ (1 kΩ + 1 kΩ), and No EOL (end-of-line) (EOL) resistor options (for on-board and B208 inputs)
- Programmable for Fire, Intrusion, Access, Gas, and Supervisory devices
- Supports hardwired and wireless devices
- Supports IP cameras by Bosch as point and output devices

IP camera support
The control panel can integrate directly with Bosch IP cameras, using them as fully supervised points and outputs.
Integration of cameras allows the camera’s video motion detection to activate points on the control panel. The control panel’s virtual outputs can be configured to trigger camera actions, including sending video snapshots via email.

Security and fire detection
The control panel provides eight on-board points, and up to 91 additional off-board points (depending on model and expansion interfaces). You can program individual points to monitor some types of burglar alarms, fire alarms, and supervision devices.

28 16 05

Event log
The event log stores up to 2048 local and reported events. The event log includes time, date, event, area, point, and user. View the event log from a keypad or use RPS to remotely retrieve event information. When the event log reaches a programmed threshold of stored events, it can send an optional report to a receiver.

Scheduled events (SKEDs)
The internal clock and calendar start individually scheduled events (SKEDs). SKEDs perform several functions such as turn on or off, relay control, or point bypassing.
The control panel offers:
- 40 scheduled events with up to 31 different functions
- 8 opening windows and 8 closing windows
- 8 user group windows
- Day-of-week, date-of-month, or holiday only schedules
- 4 holiday schedules of 366 days (leap year)

Dual bus and SDI keypad retrofits
The dual SDI2 device bus design provides greater installation flexibility, such as bus isolation for Intrusion and Fire. To use popular SDI keypads (for example D1255 and D1260), program one of the two SDI2 buses for SDI operation.

ZONEX and POPEX retrofits
To retrofit legacy Bosch control panels that use ZONEX and POPEX devices, the control panel is compatible with the B600 Retrofit (ZONEX) Module. The B600 adds two ZONEX buses to the control panel which can connect to existing legacy point bus (POPEX) devices (for example, the D8125).

Programming
Installers can perform limited programming on-site with a keypad (critical parameters; such as account IDs, central station and RPS IP addresses and phone numbers, reporting formats, and more). They can also do full programming on-site or remotely (attended or unattended) with RPS. A programmable system passcode prevents unauthorized remote programming.

Diagnostics
Keypads and RPS offer diagnostic help for monitoring and troubleshooting. The diagnostics features allow you to view the status of the wired and wireless devices. The features provide the status of the control panel and its connected devices, such as firmware version, power, and missing conditions. View the status of each area.

Remote Security Control app
The Remote Security Control (RSC) app allows users to control their security systems remotely from their devices. Users can:
- Turn their security system On or Off
- Turn specific areas On or Off
- Control outputs for applications such as lighting control
- View live video from Bosch IP cameras
- Grant access remotely by unlocking and locking doors

The app requires the installing dealer to create a Remote Access Profile for users, and to install the profile on their devices.

Bosch Video Management System integration
With Bosch Video Management System (Bosch VMS) and an intrusion system, the VMS operator has a single user interface to monitor and control the intrusion system combined with video surveillance. With Bosch VMS and a control panel, the operator can, for example:
- View videos triggered by intrusion events, including all relevant information such as areas, point, and user show in the display with the event.
- View areas, points, outputs, and doors – with their statuses – on the Bosch VMS map, providing the exact location in the system.
- Turn on (arm) and turn off (disarm) areas.
- Bypass and unbypass points.
- Lock and unlock doors (Bosch VMS 6.0 and higher).

Requirements to integrate Bosch VMS with a control panel:
- A licensed Bosch VMS system using Professional Editions v5.5 or higher or Bosch VMS Enterprise Edition v5.5 or higher.
- Expansion license to integrate the intrusion control panel. One license needed per control panel. Order number MBX-XINT-xx for the expansion license added to a Bosch VMS base license. Refer to the Bosch Video Management Software product page on the Bosch website, www.boschsecurity.com.
- Access to Remote Programming Software (RPS).

Certifications and approvals

Region	Regulatory compliance/quality marks	
USA	ANSI-SIA	CP-01-2010-Control Panel Standard - Features for False Alarm Reduction
Australia	RCM	[B9512G]
	RCM	[B8512G]
	RCM	ACMA
Europe	CE	EMC, LVD, RoHS [B9512G, B9512G-E, B8512G, B8512G-E]
USA	UL	[B9512G, B9512G-E, B8512G, B8512G-E, B299, B600, B901, B925F, B926F]
	UL	UL 294 - Standard for Access Control Units and Systems
	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 609 - Standard for Local Burglar Alarm Units and Systems
	UL	UL 636 - Holdup Alarm Units and Systems
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems
	UL	UL 985 - Household Fire Warning System Units

28 16 05

Region	Regulatory compliance/quality marks	
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL	UL 1610 - Central Station Burglar Alarm Units
	UL	UL 1635 - Standard for Digital Alarm Communicator System Units
	FM	Central Station
	FM	Local Protective Signaling
	FM	Remote Station
	CSFM	California State Fire Marshal (see our website)
	FCC	Part 15 Class B
	FDNY-CoA	Fire Department of New York City [B9512G, B9512G-E, B8512G, B8512G-E]
Canada	ULC	[B9512G, B9512G-E, B8512G, B8512G-E, B299, B600, B901, B925F, B926F]
	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	CAN/ULC S545 - Residential Fire Warning System Control Units
	ULC	CAN/ULC S559 - Fire Signal Receiving Centres and Systems
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units
	ULC	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems
	IC	ICES-003 - Information Technology Equipment (ITE)
Brazil	ANATEL	04450-16-01855 [B9512G, B8512G when used with B430 or B442]

Installation/configuration notes

Notice
Not all products and features are available in all regions. Consult your local Bosch representative for availability details.

Compatible products

Keypads

B942/B942W Touch Screen Keypad (SDI2)

B930 ATM Style Alphanumeric Keypad (SDI2)

B926F Fire Keypad (SDI2)

B925F Fire Keypad (SDI2)

B921C Two-line Capacitive Keypad (SDI2)

B920 Two-line Alphanumeric Keypad (SDI2)

B915/B915I Basic Keypad (SDI2)

D1255 Series Keypads

D1260 Series Keypads

D1256RB Fire Keypad

D1257RB Remote Fire Alarm Annunciator

Power

D1640 16.5 VAC 40 VA Transformer

DE-45-18 Transformer

D126 Standby Battery (12 V, 7 Ah)

D1218 Battery (12 V, 18 Ah)

D122 Dual Battery Harness

D122L Dual Battery Harness with Long Leads

Enclosures

B8103 Universal Enclosure (White)

D8103 Universal Enclosure (Gray)

D8108A Attack Resistant Enclosure

D8108A-CE Attack Resistant Enclosure with Built-in Transformer

D8109 Fire Enclosure

Accessories

B56 Keypad Surface Mount Box

B96 Keypad Trim Bezel

B99 USB Direct Connect Cable

B501-10 Interconnect wiring cables (pack of 10)

D161 Dual Modular Telephone Cord (7 f)

D162 Modular Telephone Cord (2 ft)

D166 Telephone Jack (RJ31X)

Detectors

D7050 Series Addressable Photoelectric Smoke and Smoke Heat Detector Heads

F220-B6PM/S 12/24 VDC Addressable Detector Bases with POPITs

F220-B6 12/24 VDC Two-wire Base

F220-B6R Standard 12/24 VDC Four-wire Base)

F220-P Photoelectric Smoke Detector

28 16 05

F220-PTH Photoelectric Smoke Detector with +135°F (+57°C) Heat Sensor

F220-PTH Photoelectric Smoke Detector with +135°F (+57°C) Heat Sensor and Carbon Monoxide Sensors

F220-B6C 12/24 VDC Four-wire Base with Auxiliary Form C Relay

FCC-380 Carbon Monoxide Detector

FCH-T320 Heat Detector

FCP-OT320 Multisensor Detector Optical/Thermal

FCP-O320 Optical Smoke Detector

MX775i Addressable PIR Detector

MX794i Long Range Multiplex PIR Detector

MX934i Addressable PIR Detector

MX938i Addressable PIR Detector

ZX776Z PIR Detector

ZX794Z Long Range PIR Detector

ZX835 TriTech Microwave/PIR Detector

ZX935Z PIR Detector

ZX938Z PIR Detector

ZX970 PIR/Microwave Detector

Bosch conventional detectors, including Professional Series, Blue Line Gen2, Blue Line, Classic Line, Commercial Line, and Ceiling Mount motion detectors, as well as glass break, seismic, request-to-exit, photoelectric, heat, and smoke detectors.

Modules

B208 Octo-input Module

B299 POPEX Module

B308 Octo-output Module

B426 Conettix Ethernet Communication Module

B430 Plug-in Telephone Communicator

B440 Conettix Plug-in Cellular Communicator (using 3G)

B441 Conettix Plug-in Cellular Communicator (using CDMA)

B442 Conettix Plug-in Cellular Communicator (using GPRS)

B443 Conettix Plug-in Cellular Communicator (using HSPA+)

B450 Conettix Plug-in Communicator Interface

B520 Auxiliary Power Supply Module

B600 Retrofit (ZONEX) Module

B810 wireless receiver (RADION)

B820 SDI2 Inovonics Interface Module

B901 Access Control Module

D113 Battery Lead Supervision Module

D125B Dual Class B Initiating Module

D126 Standby Battery (12 V, 7 Ah)

D129 Class A Initiating Module

D130 Auxiliary Relay Module

D132A Smoke Detector Reversing Relay Module

D133 Single Relay Module

D134 Dual Relay Module

D185 Reverse Polarity Signaling Module

D192G Class “B”, Style Y Bell Circuit Supervision

D1218 Battery (12 V, 18 Ah)

D8125 Addressable Expansion Module

D8125MUX Multiplex Bus Interface

D8128D OctoPOPIT Eight-point Expander

D8129 Octo-relay Module

D8130 Door Release Module

D9127U/T POPIT Module

DS7461i Single-zone Input Module

DS7465i Input-output Module

D9210C Access Control Interface Module

ICP-EZTS Cover and Wall Tamper Switch

ICP-SDI-9114 SDI Splitter

Applications

Remote Programming Software (RPS or RPS-LITE) v6.03 and higher

Bosch Video Management System v5.5 and higher

Remote Security Control (RSC)

Conettix receivers
(Managed and configured with Conettix D6200 Programming/ Administration Software v2.10)

Conettix D6600 Communications Receiver/Gateway (with only D6641 line cards installed) with CPU version 01.10.00

Conettix D6100IPv6 Communications Receiver/Gateway with CPU version 61.10.00

Conettix D6100i Communications Receiver/Gateway with CPU version 61.10.00

RADION wireless from Bosch

B810 wireless receiver (RADION)

RFBT-A/RFBT bill trap

RFDL-11-A/RFDL-11 TriTech motion detector

RFDW-RM-A/RFDW-RM recessed mount door/window contact

28 16 05

RFDW-SM-A/RFDW-SM surface mount door/window contact

RFGB-A/RFGB glass break detector

RFKF-A/RFKF two-button keyfob

RFKF-FBS-A/RFKF-FBS four-button keyfob

RFKF-TBS-A/RFKF-TBS two-button keyfob

RFPB-SB-A/ RFPB-SB single-button panic

RFPB-TB-A/RFPB-TB two-button panic

RFRP-A/RFRP repeater

RFSM-A/RFSM smoke detector

RFPR-12-A/RFPR-12 PIR motion detector

RFPR-C12-A/RFPR-C12 PIR curtain motion detector

RFUN-A/RFUN universal transmitter

Inovonics Wireless

B820 SDI2 Inovonics Interface Module

ENKIT-SDI2 SDI2 Inovonics Interface and Receiver Kit. Includes B820 and EN4200

EN1210 Universal Transmitter (Single-input)

EN1210EOL Universal Transmitter with EOL Resistor

EN1210W Door-Window Transmitter with Reed Switch

EN1215EOL Universal Transmitter with Wall Tamper, Reed Switch, and EOL Resistor

EN1223D Water-resistant Pendant Transmitter (Double-button)

EN1223S Water-resistant Pendant Transmitter (Single-button)

EN1224-ON Multiple-Condition Pendant Transmitter

EN1233D Necklace Pendant Transmitter (Double-button)

EN1233S Necklace Pendant Transmitter (Single-button)

EN1235D Beltclip Pendant Transmitter (Double-button)

EN1235DF Fixed-location Transmitter (Double-button)

EN1235S Beltclip Pendant Transmitter (Single-button)

EN1235SF Fixed-location Transmitter (Single-button)

EN1247 Glass-break Detector Transmitter

EN1249 Bill Trap Transmitter

EN1242 Smoke Detector Transmitter

EN1260 Wall Mount Motion Detector

EN1261HT High Traffic Motion Detector

EN1262 Motion Detector with Pet Immunity

EN1265 360° Ceiling Mount Motion Detector

EN4200 Serial Receiver

EN5040-T High Power Repeater with Transformer

Technical specifications

Properties

Dimensions	10.625 in x 7.75in x 1.875 in (26.99 x 19.69 x 4.76 cm)
Weight	1.95 lbs (0.88 kg)

Communications

Ethernet	10/100 full duplex (N/A for “E” control panels)

Environmental considerations

Relative humidity	5% to 93% at +32°C (+90°F)
Temperature (operating)	0°C to +49°C (+32°F to +120°F)

Power requirements

Current (maximum)	Standby: 180 mA Alarm: 260 mA
Output (alarm)	2 A at 12 VDC
Output (auxiliary, continuous power, and switched auxiliary combined)	1.4 A at 12 VDC nominal
Voltage (operating)	12 VDC nominal
Voltage (AC)	16.5 VAC 40 VA plug-in transformer (D1640/D1640-CA)

Wiring

Terminal wire size	12 AWG to 22 AWG (2.0 mm to 0.65 mm)
SDI2 wiring	Maximum distance – Wire size (unshielded wire only): 7,500 ft (2,286 m) – 22 AWG (0.65 mm)

Number of...

Areas	8
Custom functions	8
Events	Up to 2048
Passcode users	500, plus 1 Installer passcode
Points	99 (8 on-board, up to 91 off-board and virtual)
Programmable outputs	99 (3 on-board, up to 96 off-board and virtual)
RF points	91

28 16 05

IP cameras	8
SKEDs	40

Ordering information

B8512G IP control panel, 8 areas, 99 points
Supports up to 99 points, 3 on-board outputs, and 8 areas for intrusion, commercial fire. On-board Ethernet.
Order number **B8512G**

B8512G-E Control panel, 8 areas, 99 points, no IP
The B8512G-E is available only in kits.
Order number **B8512G-E**

B901 Door Controller
Fully supervised, addressable SDI2/SDI bus device that allows access control integration for Bosch G and B Series Control Panels.
Order number **B901**

Accessories

B520 Auxiliary power supply module, 2A 12V
Provides auxiliary power to 12 VDC devices or to SDI2 modules.
Order number **B520**

B208 SDI2 8-Input Expansion Module
Provides 8 programmable inputs.
Order number **B208**

B308 SDI2 8-Output Expansion Module
Provides 8 programmable relays.
Order number **B308**

B810 RECEIVER-SDI2
Receives RF signals from RADION transmitters, repeaters, and glassbreaks. Operates at 433.42 MHz. For use with compatible SDI2 bus control panels.
Order number **B810**

D122 Dual battery harness, 17" 18AWG
Harness with circuit breaker. Connects two batteries (in parallel) to a compatible control panel.
Order number **D122**

D122L Dual battery harness, 35", 12V
Harness with circuit breaker and leads measuring 35 in. (89 cm). Connects two batteries (in parallel) to a compatible control panel in a separate enclosure.
Order number **D122L**

D126 Battery, 12V 7Ah
A rechargeable sealed lead-acid power supply used as a secondary power supply or in auxiliary or ancillary functions.
Order number **D126**

D1218 Battery, 12V 18Ah
The D1218 is a 12 V 18 Ah sealed lead-acid battery with two bolt-fastened terminals. It is used for standby and auxiliary power. It connects to a compatible control panel using a D122 or D122L Dual battery harness.
Order number **D1218**

D137 Accessory mounting bracket for enclosure
Used to mount accessory modules in B8103, D8103, D8108A, and D8109 enclosures.
Order number **D137**

D1640 Transformer plug-in, 16V 40VA
System transformer rated at 16.5 VAC, 40 VA.
Order number **D1640**

D1640-CA 16VAC 40VA xfmr Canada
For use in Canada. System transformer rated at 16.5 VAC, 40 VA.
Order number **D1640-CA**

D9002-5 Mounting plate, 6 location 3-hole, 5 pcs
5 pack of mounting skirts for B8103, D8103, D8108A, and D8109 enclosures. Each skirt can hold up to six standard 3-hole mounting modules.
Order number **D9002-5**

D101 Enclosure lock and key set
Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.
Order number **D101**

D110 TAMPER SWITCH 2/PKG
Screw-on tamper switch that fits all enclosures. Shipped in packages of two.
Order number **D110**

ICP-EZTS TAMPER SWITCH-DUAL
Combination tamper switch with a wire loop for additional tamper outputs.
Order number **ICP-EZTS**

B8103 Universal enclosure, white
White steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).
Order number **B8103**

D8103 Steel enclosure, large, grey
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).
Order number **D8103**

D8108A Attack resistant enclosure, large, grey
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes a lock and key set.
Order number **D8108A**

28 16 05

D8109 Fire enclosure, 16x16x3.5", red
Red enclosure measuring 16 in. x 16 in. x 3.5 in. (41 cm x 41 cm x 9 cm). Made from 16 gauge (1.5 mm) cold-rolled steel with a full-length hinge. Includes a lock and key set. UL Listed for commercial fire/ burglary alarm applications.
Order number **D8109**

D8004 Transformer enclosure kit, grey
For applications that might require a remote transformer in an enclosure. Can be used with B Series control panels and D9412GV4/D7412GV4 control panels.
Order number **D8004**

BATB-40 Battery box/enclosure, 22x20.75x7.25"
Holds two dry or wet cell batteries. Optional BATB-SHELF battery shelf increases number of batteries. Suitable for residential/commercial fire or burglary applications.
Order number **BATB-40**

BATB-80 Battery box/enclosure, 14x20.75x7.25"
Battery box/enclosure with shelf holds up to four dry or wet cell batteries. Suitable for residential/ commercial fire or burglary applications.
Order number **BATB-80**

B99 USB direct connect cable
Male A to Male A USB cable for local programming of control panels with on-board USB ports.
Order number **B99**

B915 Basic Keypad
Two-line alphanumeric basic keypad with English function keys.
Order number **B915**

B915I LCD keypad, icon keys, SDI2
Two-line alphanumeric basic keypad with icon function keys.
Order number **B915I**

B920 2 Line Alpha Numeric Keypad (SDI2)
Two-line alphanumeric keypad
Order number **B920**

B921C Two-line Keypad w/Touch keys, Inputs
Two-line alphanumeric keypad with inputs and capacitive touch keys in black.
Order number **B921C**

B930 ATM Style-Alpha Numeric Keypad (SD12)
Five-line ATM style alphanumeric keypad
Order number **B930**

B942 Touch Screen KP Prox/Input/Output, black
Black SDI2 touch screen keypad with inputs and one output.
Order number **B942**

B942W Touch screen KP, prox/input/output,white
White SDI2 touch screen keypad with inputs and one output.
Order number **B942W**

B925F Fire and intrusion keypad, SDI2
Two-line alphanumeric fire and intrusion keypad.
Order number **B925F**

B926F Fire keypad, SDI2
Two-line alphanumeric fire keypad
Order number **B926F**

Software Options

D5500C-USB Kit with DVD and USB security dongle
Account management and control panel programming software with USB security key (dongle).
Order number **D5500C-USB**

28 16 05

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2017 | Data subject to change without notice
13825824395 | en, V23, 22. Aug 2017

D101 Lock and Key Set

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.

Ordering information

D101 Lock and Key Set
Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.
Order number **D101**

D122L Dual Battery Harness with Long Leads

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



Color-coded wire harness with circuit breaker to protect the charging circuit when connecting multiple 12 V batteries to a control panel. The leads accommodate the installation of extra 12 V batteries in an adjacent enclosure.

Certifications and approvals

Region	Certification	
USA	UL	AOTX: Local Alarm Units (UL464, UL609), APAW: Police Station Alarm Units (UL365, UL464)
	CSFM	see our website

Parts included

Quantity	Component
1	D122L Battery Harness
1	Lit – Installation Manual

Ordering information

D122L Dual Battery Harness with Long Leads
Color-coded harness with circuit breaker and leads measuring 89 cm (35 in.). Connects 12 V batteries to compatible control panels.
Order number **D122L**

D161 Dual Modular Telephone Cord

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- Connects an RJ31X Telco block to an RJ38X Telco jack
- 2.1 m (7 ft.) for longer distances

Certifications and approvals

Region	Certification	
USA	CSFM	see our website

Parts included

Quantity	Component
1	Telephone cord

Technical specifications

Length	2.1 m (7 ft.)
Color	Gray

Ordering information

D161 Dual Modular Telephone Cord
A 2.1 m (7 ft.), 8-conductor fully modular plug-in cord.
Order number **D161**

D1640-CA Transformer

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- System transformer rated at 16.5 VAC, 40 VA
- Suitable for use on approved ULC and cUL applications in Canada

For use in Canada. System transformer rated at 16.5 VAC, 40 VA.

Parts included

Quantity	Component
1	Transformer

Technical specifications

Rating	16.5 VAC, 40 VA
Dimensions	3.2 in x 2.8 in x 2.2 in (81 mm x 70 mm x 56 mm)
Color	White

Ordering information

D1640-CA Transformer
For use in Canada. System transformer rated at 16.5 VAC, 40 VA.
Order number **D1640-CA**

D126 Standby Battery (12 V, 7 Ah)

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



- 12 VDC sealed lead-acid
- Fully rechargeable
- Maintenance-free
- For use as secondary power for accessory modules
- Long service life

A maintenance-free, sealed lead-acid, standby and auxiliary power supply that provides long service life and dependability.
The battery is for use only with charging circuits calibrated for lead-acid batteries. It is suitable for supplying backup power for fire, security, and access control systems during AC power failures.
The D126 fits in any of the currently offered enclosures and connects to the two color-coded battery leads supplied with the control panel or module. Use a D122 Dual Battery Harness to connect two D126 batteries in parallel and double the amp hour output.

Certifications and approvals

NYC/BSA	582-85-SA
DSI	CDFM

Region	Certification	
Europe	CE	Council Directive 89/336/EEC Electromagnetic Compatibility
USA	UL	ALVY: Access Control Systems Units (UL294), APOU: Proprietary Alarm Units (UL1076), UEHX7: Signaling Appliances, Miscellaneous Certified for Canada (cUL)

Region	Certification	
	FM	
	CSFM	7167-1615: 0100 CONTROL UNIT (HOUSEHOLD)
	CSFM	7165-1615: 0113 FIRE ALARM CONTROL UNIT (COMMERCIAL)
	CSFM	7167-1615:0124 7167 -- CONTROL UNIT (HOUSEHOLD)
	CSFM	7165-1615:0119 7165 -- FIRE ALARM CONTROL UNIT (COMMERCIAL)
	CSFM	7167-1615:0239 7167 -- CONTROL UNIT (HOUSEHOLD)

Installation/configuration notes

Standby Power Requirements
Refer to the appropriate control panel installation manual for information on calculating the standby battery requirements for the system. Total continuous and intermittent current requirements must not exceed the amp hour capacity of the battery.

Technical specifications

Capacity:	12 V, 7 Ah
Compatible Panels:	Compatible with all control panels

28 16 05

Dimensions:	15 cm x 8 cm (6 in. x 3 in.)
Height with Terminals:	10 cm (4 in.)
Weight:	2.5 kg (5.5 lb)

Ordering information

D126 Standby Battery (12 V, 7 Ah)
A rechargeable sealed lead-acid power supply used as a secondary power supply or in auxiliary or ancillary functions.
Order number **D126**

Represented by:

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com

© Bosch Security Systems 2013 | Data subject to change without notice
2548450571 | en, V4, 01. Oct 2013

D166 Telephone Jack

www.boschsecurity.com

28 16 05

BOSCH
Invented for life



Ordering information

D166 Telephone Jack
Standard Telco RJ31X Telephone Jack measuring approximately 5 cm (2 in.) square by 2.5 cm (1 in.) high.
Order number **D166**

Professional Series TriTech Curtain Motion Detectors

www.boschsecurity.com

28 16 05

BOSCH
Invented for life

Curtain type motion detector



- 30 m (100 ft) x 2.6 m (8.5 ft) standard coverage
- 2.1 m to 3 m (7 ft to 10 ft) mounting height, no adjustments required, optional lookdown masking
- Sensor data fusion technology
- Range adaptive radar and active white light suppression
- Dynamic temperature compensation

The Professional Series TriTech Curtain Detectors are exceptionally suited for commercial indoor applications. Sensor data fusion technology ensures that the detector sends alarm conditions based on precise information. The powerful combination of unique features in the Professional Series delivers superior catch performance and virtually eliminates false alarms.
The self-locking two-piece enclosure, built-in bubble level, flexible mounting height, and three optional mounting brackets simplify installation and reduce service time.

Functions

Sensor Data Fusion Technology
Sensor data fusion technology is a unique feature that uses a sophisticated software algorithm to gather signals from five sensors: two pyroelectric sensors, a range adaptive radar sensor, a room temperature sensor, and a white light level sensor. The microcontroller analyzes and compares the sensor data to make the most intelligent alarm decisions in the security industry.

Range Adaptive Radar
The microwave transceiver automatically adjusts its detection thresholds based on input from the PIR sensors. Integrating the target distance information from the PIR significantly reduces false alarms from the microwave Doppler radar.

Active White Light Suppression
An internal light sensor measures the level of light intensity directed at the face of the detector. Sensor data fusion technology uses this information to eliminate false alarms from bright light sources.

Dynamic Temperature Compensation
The detector automatically adjusts PIR sensitivity to identify human intruders at critical temperatures. Dynamic temperature compensation detects human body heat accurately, avoids false alarms, and delivers consistent catch performance at all operating temperatures.

Cover and Wall Tamper Switch
When an intruder removes the cover or attempts to separate the detector from the wall, a normally-closed contact opens to alert the control panel.

28 16 05

Self-adjusting LEDs
The LED brightness adjusts automatically to the surrounding light level. A blue light-emitting diode (LED) indicates TriTech+ alarms and activates during a walk test. A yellow LED indicates microwave detection, and a red LED indicates PIR detection.

Remote Walk Test LED
Users can enter a command through a keypad, a control center, or programming software to remotely enable or disable the walk test LED.

Alarm Memory
Alarm memory flashes the alarm LED to indicate stored alarms for use in multiple unit applications. A switched voltage from the control panel controls the alarm memory.

Solid State Relays
Solid state relays send silent alarm output signals to provide a higher level of security and reliability. An external magnet does not activate the relay. The solid state relay uses less current than a mechanical relay, providing longer standby capacity during a power loss.

Draft, Insect, and Small Animal Immunity
The sealed optic chamber provides immunity to drafts and insects, reducing false alarms. Small animal immunity reduces false alarms caused by animals less than 4.5 kg (10 lb), such as rodents.

Remote Self Test
A remote self test initiates when the walk test input switches to its true state. The alarm relay and alarm LED activate for four seconds following a successful test. The trouble relay activates, and the alarm LED flashes following a failed test.

Input Power Supervision
When the power is lower than 8 V, a low input power trouble condition activates the trouble relay and causes the LED to flash. The trouble condition clears automatically when power reaches or exceeds 8 V.

Trouble Memory
When the walk test input switches to its true state for less than two seconds, the LED flashes to indicate the most recent trouble condition. If there is no trouble in memory, the LED does not flash. After twelve hours, or after the detector receives a second walk test pulse for two seconds or less, the LED stops flashing and the trouble memory clears.

Cloak and Camouflage Detection Technology
Cloak and Camouflage Detection Technology (C^2DT) maximizes catch performance against intruders attempting to cover their infrared signal.

DIP Switch Programming
The following functions are all programmed using DIP switch settings:
- Local Walk Test LED
- Remote Walk Test Input Polarity
- Alarm Memory Polarity
- MANTIS Anti-mask On and Off


Certifications and approvals

Europe	WEEE	Waste Electrical and Electronic Equipment Directive
The detectors are designed to also comply with requirements of:		
USA	FCC	Complies with Part 15

Region	Regulatory compliance/quality marks	
Australia	RCM	[ISC-PDL1-WC30G]
USA	UL	[ISC-PDL1-WC30G]
Brazil	ANATEL	[ISC-PDL1-WC30G]

Installation/configuration notes

Coverage Patterns



Standard Curtain Coverage 30 m x 2.6 m (100 ft x 8.6 ft)

Mounting
The recommended mounting height is 2 m to 3 m (7 ft to 10 ft) with no adjustments required.
Mount the motion detector level, both horizontally and vertically.
Mounting options:
- On a flat wall (surface, semi-flush), with the optional B335-3 Swiveling low-profile mount, or with the optional B328 Gimbal-mount Bracket
- In a corner (the junction of two perpendicular walls)
- On the ceiling with the optional B338 Universal Ceiling-mount Bracket

Wiring Considerations
Recommended wire size is 0.2 mm^2 to 1 mm^2 (26 AWG to 16 AWG).

Technical specifications

Electrical

Power Requirements	
Voltage (Operating):	9 VDC to 15 VDC
Current (Maximum):	< 26 mA with alarm, trouble, and LEDs active.
Current (Standby):	18 mA at 12 VDC
Outputs for both Models	

28 16 05

Tamper:	Normally-closed (NC) contacts (with cover on) rated at 25 VDC, 125 mA maximum. Connect tamper circuit to 24-hour protection circuit.
Trouble:	Solid state relay normally-closed (NC) contacts.
Alarm:	Solid state relay, normally-closed (NC) contacts, power supervised. 3 W, 125 mA, 25 DC, resistance < 10 Ω.

Mechanical

Enclosure Design

Color:	White
Dimensions:	127 mm x 69 mm x 58 mm (5 in. x 2.75 in. x 2.25 in.)
Material:	High-impact ABS plastic

Indicators

Alarm Indicator:	• Blue LED for TriTech+ alarms • Yellow LED for microwave detection • Red LED for PIR detection

Zones

Zones:	28

Environmental

Relative Humidity:	0 to 95%, non-condensing
Temperature (Operating and Storage):	-30°C to +55°C (-22°F to +130°F) *For UL Certificated installations, 0°C to +49°C (+32°F to +120°F)*
Protection Rating (EN 60529, EN 50102):	IP41, IK04

Ordering information

ISC-PDL1-WC30G Motion detector, 100ft (30m), curtain
Provides PIR and microwave, 30 m x 3 m (100 ft x 10 ft) coverage.
Order number **ISC-PDL1-WC30G**

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

ISC-PDL1-WC30H Motion detector 30m curtain, 10.588GHz
Provides PIR and microwave, 30 m x 3 m (100 ft x 10 ft) coverage. For use in France and the United Kingdom.
Order number **ISC-PDL1-WC30H**

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

Accessories

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

28 16 05

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2018 | Data subject to change without notice
2610618763 | en, V44, 11. Jan 2018

Professional Series TriTech Motion Detectors

www.boschsecurity.com

BOSCH
Invented for life





- 18 m x 25 m (60 ft x 80 ft) coverage, field selectable to 8 m x 10 m (25 ft x 33 ft)
- Sensor data fusion technology
- Tri-focus optics technology
- Range adaptive radar
- Microwave anti-mask

The ISC-PDL1-W18x Professional Series TriTech Detectors are exceptionally suited for commercial indoor applications. Sensor data fusion technology ensures that the detectors send alarm conditions based on precise information. Tri-focus optics eliminate coverage gaps and respond efficiently to intruders. The powerful combination of unique features in the Professional Series delivers superior catch performance and virtually eliminates false alarms.
The self-locking two-piece enclosure, built-in bubble level, flexible mounting height, and three optional mounting brackets simplify installation and reduce service time.

Functions

Sensor Data Fusion Technology
Sensor data fusion technology is a unique feature that uses a sophisticated software algorithm to gather signals from five sensors: two pyroelectric sensors, range adaptive radar, a room temperature sensor, and a white light level sensor. The microcontroller analyzes and compares the sensor data to make the most intelligent alarm decisions in the security industry.

Tri-focus Optics Technology
Tri-focus optics technology uses optics with three specific focal lengths: long-range coverage, middle-range coverage, and short-range coverage. The detector applies the three focal lengths to 86 detection zones, which combine to make 11 solid curtains of detection. Tri-focus optics technology also includes two pyroelectric sensors, which deliver twice the standard optical gain. The sensors process multiple signals to deliver precise performance virtually free of false alarms.

Range Adaptive Radar
The microwave transceiver automatically adjusts its detection thresholds based on input from the PIR sensors. Integrating the target audience distance information from the PIR significantly reduces false alarms from the microwave Doppler radar.

Microwave Anti-mask
The detector sends a supervision-trouble signal if microwave reflective material is placed within 30.5 cm (1 ft) of the detector.

Supervised Microwave and PIR
The detector provides single technology coverage if the microwave subsystem fails.

Active White Light Suppression
An internal light sensor measures the level of light intensity directed at the face of the detector. Sensor data fusion technology uses this information to eliminate false alarms from bright light sources.

Field Selectable Coverage (18 m x 25 m or 8 m x 10 m)
Installers can use a DIP switch to select 18 m x 25 m or 8 m x 10 m (60 ft x 80 ft or 25 ft x 33 ft) coverage.

Dynamic Temperature Compensation
The detector automatically adjusts PIR sensitivity to identify human intruders at critical temperatures. Dynamic temperature compensation detects human body heat accurately, avoids false alarms, and delivers consistent catch performance at all operating temperatures.

Cover and Wall Tamper Switch
When an intruder removes the cover or attempts to separate the detector from the wall, a normally-closed contact opens to alert the control panel.

Self-adjusting LED
The LED brightness adjusts automatically to the surrounding light level. A blue light-emitting diode (LED) indicates dual alarms and activates during a walk test. A yellow LED indicates microwave detection, and a red LED indicates PIR detection.

Remote Walk Test LED
Users can type a command through a keypad, a control center, or programming software to remotely enable or disable the walk test LED. Users can locally enable or disable the walk test LED through the DIP switch.

Alarm Memory
Alarm memory flashes the alarm LED to indicate stored alarms for use in multiple unit applications. A switched voltage from the control panel controls the alarm memory.

Solid State Relays
Solid state relays send silent alarm output signals to provide a higher level of security and reliability. An external magnet does not activate the relay. The solid state relay uses less current than a mechanical relay, providing longer standby capacity during a power loss.

Draft, Insect, and Small Animal Immunity
The sealed optic chamber provides immunity to drafts and insects, reducing false alarms. Small animal immunity reduces false alarms caused by animals less than 4.5 kg (10 lb), such as rodents.

Remote Self Test
A remote self test initiates when the walk test input switches to its true state. The alarm relay and alarm LED activate for four seconds following a successful test. The trouble relay activates, and the alarm LED flashes following a failed test.

Input Power Supervision
When the power is lower than 8 V, a low input power trouble condition activates the trouble relay and causes the LED to flash. The trouble condition clears automatically when power reaches or exceeds 8 V.

Trouble Memory
When the walk test input switches to its true state for less than two seconds, LED flashes to indicate the most recent trouble condition. If there is no trouble in memory, the LED does not flash. After twelve hours, or after the detector receives a second walk test pulse for two seconds or less, the LED stops flashing and the trouble memory clears.

Cloak and Camouflage Detection Technology
Cloak and Camouflage Detection Technology (C^2DT) maximizes catch performance against intruders attempting to cover their infrared signal.


Certifications and approvals

The detectors are designed to also comply with the requirements of:


Australia C-Tick

Region	Regulatory compliance/quality marks	
Australia	SCEC	[ISC-PDL1-W18G, ISC-PDL1-WA18G]
USA	UL	[ISC-PDL1-W18G]
	UL	UL 639 - Standard for Intrusion Detection Units
	FCC	[ISC-PDL1-W18G]
Canada	IC	[ISC-PDL1-W18G]
China	CCC	2009031901000559 [ISC-PDL1-W18G-CHI]
Brazil	ANATEL	[ISC-PDL1-W18G]

Installation/configuration notes



Long-range Coverage 18 m x 25 m (60 ft x 80 ft)



Selectable Short-range Coverage 8 m x 10 m (25 ft x 33 ft)

Mounting

The recommended mounting height is 2 m to 3 m (7 ft to 10 ft) with no adjustments required.
Mount the motion detector level, both horizontally and vertically.
Mounting options:

- On a flat wall (surface, semi-flush), with the optional B335-3 Swiveling low-profile mount, or with the optional B328 Gimbal-mount Bracket
- In a corner (the junction of two perpendicular walls)
- On the ceiling with the optional B338 Universal Ceiling-mount Bracket

Wiring Considerations

Recommended wire size is 0.2 mm^2 to 1 mm^2 (26 AWG to 16 AWG).

Technical specifications

Electrical

Power Requirements	
Voltage (Operating):	9 VDC to 15 VDC
Current (Maximum):	< 25 mA
Current (Standby):	13 mA
Outputs	
Relay:	Solid state relay, normally-closed (NC) contacts power supervised. 3 W, 125 mA, 25 VDC, resistance < 10 Ω.
Tamper:	Normally-closed (NC) contacts (with cover on) rated at 25 VDC, 125 mA maximum. Connect tamper circuit to 24-hour protection circuit.
Trouble:	Solid-state relay normally-closed (NC) contacts.

Mechanical

Enclosure Design	
Color:	White
Dimensions:	136 mm x 69 mm x 58 mm (5.25 in. x 2.75 in. x 2.25 in.)
Material:	High-impact ABS plastic
Indicators	
Alarm Indicator:	• Blue LED for TriTech alarms • Yellow LED for microwave detection • Red LED for PIR detection
Zones	
Zones:	86

Frequency Information	
Radio Frequency Interference (RFI) immunity:	No alarm or setup on critical frequencies in the range from 26 MHz to 1 GHz at 50 V/m.

Environmental

Relative Humidity:	0 to 95%, non-condensing
Temperature (Operating and Storage):	-29°C to +55°C (-20°F to +130°F) *For UL Certificated installations, 0°C to +49°C (+32°F to +120°F)*
Protection Rating:	IP41, IK04 (EN 60529, EN 50102)

Ordering information

ISC-PDL1-W18G Motion detector, 60ft (18m)
Provides PIR and microwave, 18 m x 25 m (60 ft x 80 ft) coverage. 10.525 GHz frequency.
Order number **ISC-PDL1-W18G**

ISC-PDL1-W18H Motion detector, 18m, 10.588GHz
Provides PIR and microwave, 18 m x 25 m (60 ft x 80 ft) coverage. 10.588 GHz frequency. For use in France and United Kingdom.
Order number **ISC-PDL1-W18H**

Accessories

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2018 | Data subject to change without notice
2607960459 | en, V40, 04. Jan 2018

ISN-CSD70 and ISN-CSD80 Compact Contacts

www.boschsecurity.com

BOSCH
Invented for life



- Closed loop
- Sensitive non-stick rhodium reed
- Bent long leads keep solder off the glass of the reed
- Two solder points on the wire
- Thick plastic shell resists crushing

The contacts are available in brown or white. All models have a rugged, one-piece construction that eliminates the need for extra donut adapters. The compact (stubby) design allows you to use the contact in smaller spaces, without paying for a miniature design. Use on steel doors in standard or tight-fitting applications.

Notice
The photograph shows model ISN-CSD80-W.

Certifications and approvals

UL and

Region	Certification	
Europe	CE	73/23/EEC and 93/68/EEC, EN50131: 1997, EN50131-6: 1997, EN60950: 2000, EN60335-1: 1994 +A1: 1996 Annex B
USA	UL	cULus: AMQV: Connectors and Switches (UL 634), AMQV7: Connectors and Switches Certified for Canada (ULC/ ORD-C634) [-CSD70 Series]
	UL	cULus: AMQV: Connectors and Switches (UL 634), AMQV7: Connectors and Switches Certified for Canada (ULC/ ORD-C634) [-CSD80 Series]

Installation/configuration notes

Compatibility Information
All contact models are compatible with control panel models that accept contact inputs.

Parts included

Quantity Per Package	Component
10	Contacts
10	Magnets

Technical specifications

Specifications for All Models

Gap Width:	38 mm (1.5 in.)
Wire Lead Type:	0.8 mm (0.029 in.) 22 AWG, 7 stranded
Wire Lead Length:	46 cm (18 in.) standard leads
Switch Configuration Type:	Single pole single throw (SPST)
Operating Temperature Range:	7.2°C to -95.56°C (-45°F to -140°F)

Specifications for ISN-CSD70-B/W Models

Contact Dimensions:	19 mm x 20.3 mm (0.75 in. x 0.80 in.)
Maximum Contact Resistance:	150 µΩ (micro-ohm)
Minimum Breakdown Voltage:	250 VDC
Insulation Resistance:	10^{10} Ω
Electrostatic Cap:	0.3 PF
Contact Capacity:	10 VAC
Maximum Conductive Current:	1.0 A
Maximum Voltage:	100 V

Specifications for ISN-CSD80-B/W Models

Contact Dimensions:	25 mm x 20 mm (1 in. x 0.80 in.)
Maximum Contact Resistance:	150 µΩ (micro-ohm)
Minimum Breakdown Voltage:	250 VDC
Insulation Resistance:	10^{10} Ω
Electrostatic Cap:	0.3 PF
Contact Capacity:	10 VAC
Maximum Conductive Current:	1.0 A
Maximum Voltage:	100 V

Package Information

ATTENTION! Each package contains ten contacts and ten magnets.

Ordering information

Brown Compact Contact with Standard Magnet (19 mm)
Brown recessed contact with 19 mm (0.75 in.) diameter. Includes a standard magnet. **Package contains ten contacts and ten magnets.**
Order number **ISN-CSD70-B**

White Compact Contact with Standard Magnet (19 mm)
White recessed contact with 19 mm (0.75 in.) diameter. Includes a standard magnet. **Package contains ten contacts and ten magnets.**
Order number **ISN-CSD70-W**

White Compact Contact with Standard Magnet (25 mm)
White recessed contact with 25 mm (1 in.) diameter. Includes standard magnet. **Package contains ten contacts and ten magnets.**
Order number **ISN-CSD80-W**

Represented by:

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn


America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com

© Bosch Security Systems 2013 | Data subject to change without notice
2646726155 | en, V1, 01. Oct 2013

B520 Auxiliary Power Supply Module

www.boschsecurity.com

BOSCH
Invented for life



- Provides up to 2A of 12V standby current for Fire or Burglar Applications (4A of Burglary alarm current)
- Supervises up to two 12v 7-18Ah batteries independently for up to 36AH of capacity
- Provides up to 80 hours of standby time
- Uses the Bosch standard TR1850 plug-in transformer
- Easy to read rotary switch addressing

The B520 Auxiliary Power Supply Module is a fully supervised, addressable SDI2 bus device that provides an integrated auxiliary power supply solution for Bosch control panels.

System overview

The B520 Auxiliary Power Supply Module is an auxiliary power supply expansion device that connects to compatible control panels through the SDI2 bus. This module is supervised and communicates back to the control panel all status changes.
Industrial, commercial, and institutional facilities are typical installations for the B520 module. The B520 rotary switches allow for ease of use in device addressing. The SDI2 Out terminals provide auxiliary power for SDI2 expansion devices such as keypads. The AUX PWR terminals provides added auxiliary power capabilities for additional devices such as PIR's.

Functions

Supervision Monitoring
The module monitors and communicates status information over the SDI2 bus for the following:

- Operation (Heartbeat)
- Battery 1 (BATT 1)
- Battery 2 (BATT 2)
- AC input power (AC)
- Battery OK
- Low Battery
- Missing Battery

Indicators

- Heartbeat [icon]: Blue LED flashing On and Off when system is operating normally. A steady On or Off LED indicates a system error. Triple flash indicates communication failure.
- BATT 1 LED: Green steady On LED indicates the battery status of BATT 1 is operating normally. Flashing indicates low battery. Triple flash indicates battery charger failure. Off LED indicates a missing battery.
- BATT 2 LED: Green steady On LED indicates the battery status of BATT 2 is operating normally. Flashing indicates low battery. Triple flash indicates battery charger failure. Off LED indicates a missing battery.
- AC LED: Green steady On LED indicates the AC power is operational. A pulsating LED (3 pulses per sec.) occurs when a battery test is being performed. Flashing indicates low or failed AC.

Battery Charging
Fully charged batteries, connected to the battery terminals, sustain power to the B520 in the event that the AC power fails.

If AC power fails (is absent, or low) on the B520, the B520 automatically switches from primary power (AC) to secondary power (battery). When AC power is present, the B520 performs periodic battery tests to ensure battery life and usability.

Certifications and approvals

Region	
US	UL 365 – Police Station Connected Burglar Alarm Units and Systems
	UL 609 – Local Burglar Alarm Units and Systems
	UL 636 – Holdup Alarm Units and Systems
	UL 864 – Control Units and Accessories for Fire Alarm Systems
	UL 985 – Household Fire Warning System Units
	UL 1023 – Household Burglar Alarm System Units
	UL 1076 – Proprietary Burglar Alarm Units and Systems
	UL 1610 – Central Station Burglar Alarm Units
	FCC Part 15 Class B
Canada	CAN/ULC S303 – Local Burglar Alarm Units and Systems
	CAN/ULC S304 – Signal Receiving Centre and Premise Alarm Control Units
	ULC-ORD C1023 – Household Burglar Alarm System Units
	ULC-ORD C1076 – Propriety Burglar Alarm Units and Systems
	ICES-003 – Digital Apparatus

Region	Certification	
USA	UL	20121010-S5579
	CSFM	see our website

Installation/configuration notes

Mounting Considerations

You can mount the B520 Auxiliary Power Supply Module in a variety of enclosures for optimal situations.
Mounting in the D8103 requires the addition on the B12 Mounting plate.
The D8103 enclosure supports up to two 12V, 18Ah batteries. The B10 supports either one 12V, 18Ah or up to two 12V, 7Ah batteries.

Wiring Considerations

The B520 connects to a control panel using the SDI2 IN connections (PWR, A, B, COM). Use 12 AWG to 22 AWG (1.5 mm to 0.6 mm) wires from the power supply to the control panel.
The B520 provides auxiliary power to expansion modules via the SDI2 OUT (PWR, A, B, COM), or AUX Power (AUX PWR) connections using the screw terminal strip, or by using the interconnect wiring connection. Use 12 AWG to 22 AWG (1.5 mm to 0.6 mm) wires from the module to the SDI2 expansion module(s).

Parts included

Quantity	Component
1	B520 Auxiliary Power Supply module
1	Hardware pack
1	Literature pack

B520 Kit, B10 Enclosure

Kit contents include:
- B520 Aux Power Supply
- TR1850 transformer
- B10 white enclosure

Order number: **B520-B**

B520 Kit, D8103 Enclosure

Kit contents include:
- B520 Aux Power Supply
- TR1850 transformer
- B12 mounting plate
- D8103 gray, steel enclosure

Order number: **B520-C**

Technical specifications

Properties

Board Dimensions	11.43 cm x 17.62 cm x 2.9 cm (4.5 in x 6.94 in x 1.15 in)
Maximum Distance – Wire Size	305 m (1000 ft) - 0.65 mm (22 AWG) 305 m (1000 ft) – 2 mm (18 AWG) Unshielded wire only
Compatibility	GV4 Series control panels (Up to 8 B520 Auxiliary Power Supply Modules per control panel) D8103 Enclosure B10 Large Control Panel Enclosure B12 Mounting Plate for the D8103 Enclosure D8108A Attack Enclosure D2203 Enclosure BATB-40 Enclosure AE1, AE2 Enclosures D8004 Transformer Enclosure*
B501-10	Interconnect cables (10 per pack)

*The D8004 Transformer Enclosure is required when the B520 and TR1850 (18 VAC, 50 VA) Transformer are used in UL 864 Fire, or Combination Burg and Fire applications.

Power Input

Transformer Power Supply	TR1850 (18 VAC, 50 VA) TR1850-CA (18 VAC, 50 VA) for Canada

Power Output

Current Available (Maximum)	2.0 A SDI2 Out and AUX Power (Combined) (up to 4.0 A of alarm current for Burglar Applications)
Current Reserved for Charging Batteries	150 mA
Current Drawn from the Panel	15 mA
Voltage (rated range)	11.5 to 12.2 VDC (special application)
Battery Configuration	Supports two*, separate 12 V sealed lead acid batteries (7-18 Ah) for up to 36 amp. *Battery 1 is required for normal operations. Battery 2 is optional.

Enclosure Battery Considerations

D8103	Holds up to two 18 Ah, or two 7 Ah batteries
B10	Holds up to one 18 Ah, or two 7 Ah batteries

Environmental Considerations

Operating Temperature	+32° to +120° F (0° to +49°C)
Storage Temperature	-4° to 140° F (-20° to +60° C)
Relative Humidity	5% to 93% at +32° (+90°F) non-condensing
Use	Intended for indoor use.

Ordering information

B520 Auxiliary Power Supply Module
Provides auxiliary power to 12VDC devices or to SDI2 modules.
Order number **B520**

Accessories

B10 Medium Control Panel Enclosure
White, steel enclosure. Accepts an optional lock and tamper switch. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in x 12.5 in x 3 in).
Order number **B10**

D2203 Enclosure
Gray steel enclosure. Accepts an optional lock and tamper switch. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in x 12.5 in x 3 in).
Order number **D2203**

D8103 Enclosure
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).
Order number **D8103**

D8108A Attack Resistant Enclosure
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes lock and key set. B520, B4512, and B5512 require the B12 mounting plate.
Order number **D8108A**

AE1 Standard Enclosure (Gray)
Standard gray enclosure with keyed lock. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in x 12.5 in x 3 in).
Order number **AE1**

AE2 Standard Enclosure (Red)
Standard red enclosure with keyed lock. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in. x 12.5 in. x 3 in.).
Order number **AE2**

D8004 Transformer Enclosure
For applications such as fire alarm that might require a transformer enclosure.
Order number **D8004**

B12 Mounting Plate for D8103 Enclosure
Required for mounting select control panels and other devices in D8103, D8108A, D8109, or BATB Battery Box enclosures.
Order number **B12**

TR1850 Transformer
For use in North America. Plug-in transformer with input: 120 VAC, 60 Hz, 0.50 A; output 18 VAC, 50 VA output.
Order number **TR1850**

D101 Lock and Key Set
Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.
Order number **D101**

ICP-EZTS Dual Tamper Switch
Combination tamper switch with a wire loop for additional tamper outputs.
Order number **ICP-EZTS**

BATB-40 Battery Box\Enclosure
The BATB-40 Battery Box holds two dry or wet cell batteries. The box can be used with fire alarm systems or intrusion systems.
Order number **BATB-40**

B520 Kit, B10 Enclosure
B520 Auxiliary Power Supply kit. Includes a TR1850 transformer and a B10 White, steel enclosure.
Order number **B520-B**

B520 Kit, D8103 Enclosure
B520 Auxiliary Power Supply kit. Includes a TR1850 transformer, a B12 mounting plate, and a D8103 Gray, steel enclosure.
Order number **B520-C**

Represented by:

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn


America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com

© Bosch Security Systems 2014 | Data subject to change without notice
2536892171 | en, V6, 04. Nov 2014

DSC

A Tyco International Company

PowerSeries v4.6
Control Panels



Features That Make a Difference:

- Convenience of easy wireless device enrollment process
- Additional wireless zones – up to 64 in total
- Library of over 250 pre-configured labels
- Compatible with C24 Interactive

Standard PowerSeries Features:

- Template Programming
- Account Code Error Checking
- Alternate Communications via GPRS and IP
- Local and Remote Downloading
- Programmable Daylight Savings Time
- Automatic CID
- 2-way Audio
- 1 Time Use Code
- Keypad Lockout

PowerSeries v4.6 Control Panels: Simply Powerful

Introducing the new PowerSeries v4.6 Control Panel from DSC. This feature-rich and reliable intrusion alarm control panel easily integrates with an array of compatible components to deliver a scalable solution. PowerSeries v4.6 makes installation easy, simple and fast without compromising flexibility of design.

Even More Available Wireless Zones

To accommodate the move to more and more wireless devices and detectors, the PowerSeries PC 1864 has 64 wireless zones – double the capacity of earlier versions. This provides the scalability and flexibility a control panel needs to support requirements both now and in the future.

Label Programming Made Easy with Pre-loaded Library

With a library of over 250 commonly-used names in English, French and Spanish, label programming is now a snap with the PowerSeries v4.6. Installers can now assign a unique 3-digit code to display a full descriptive label (e.g., code 190 displays 'Window'), avoiding time and mistakes with more conventional keypad entry. For additional customization, other pertinent details can also be added, such as the zone or floor to make it easy for the owner to identify faults (e.g., 'Bedroom Window').

Convenient Wireless Device Enrollment Reduces Installation Time

Enrolling wireless devices and detectors is quick and easy with the PowerSeries v4.6 – reducing onsite installation time. With the wireless device enrollment process, installers are not required to manually program serial numbers or wireless attributes. Instead, enrollment is completed by confirming the confirm Electronic Serial Numbers (ESN), zone numbers and zone type through a series of user friendly screens.

STANTEC PROJECT #: 110126045
SUBMITTAL # ELE-08R2
This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other
component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.
Stantec
☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED
DATE 2019-11-08
BY Konrad Goluch

Contact your DSC distributor.
www.dsc.com | 1-888-888-7838

DSC

A Tyco International Company

Compatible with C24 Interactive

The PowerSeries v4.6 Control Panel is compatible with the innovative C24 Interactive product line. Integrating these two lines provides accountability and control to end users with a scalable solution. C24 Interactive offers a range of pre-defined security options from simple notification to automated 'control and connect'. Ideal for both new and existing end users, C24 Interactive options can be easily added as requirements evolve, creating long-term and entrenched revenue streams today and tomorrow – all supported by PowerSeries v4.6.

Simply Powerful

Put the PowerSeries v4.6 Control Panel to work at the centre of any security installation from small residential to medium-sized commercial installations. Designed with users in mind, installers now have an easy-to-install system with a range of features all backed by DSC's proven reputation. Simply powerful.

Compatibility

- User Interfaces - LED, Icon and Full Message LCD, NEW PTK Touchscreen
- C24 Interactive
- Wireless Receivers, Devices and Detectors
- Audio Alarm Verification
- Telephone Interface/Automation Control
- High & Low Current Output Expansion
- Alternate Communication Options
- Hardwired Expansion and Detectors
- Addressable Expansion and Detectors
- Windows™ Software for PC Downloading
- Access Control Integration

Specifications

Power Supply	16.5 VAC/40 VA @ 50/60 Hz
Current Draw (Panel)	110 mA (Nominal)
Auxiliary & Output	13.75 ± 5% Vdc /700 mA
Bell Output	13.75 ± 5% Vdc /700 mA
Operating Environment	32° to 120° F (0° to 49° C)
Relative Humidity	93%

PowerSeries v4.6 Features

Features	PC1616	PC1832	PC1864
On-Board Zones	6	8	8
Hardwired Zones	16 (1 x PC5108)	32 (1 x PC5108)	64 (1 x PC5108)
Wireless Zones	32	32	64
Keypad Zone Support	Yes	Yes	Yes
On-board PGM Outputs	PGM 1 = 50 mA PGM 2 = 300 mA	PGM 1 = 50 mA PGM 2 = 300 mA	PGM 1,3,4 = 50 mA PGM 2 = 300 mA
PGM Expansion	8 x 50 mA (PC5208) 4 x 500 mA (PC5204)	8 x 50 mA (PC5208) 4 x 500 mA (PC5204)	8 x 50 mA (PC5208) 4 x 500 mA (PC5204)
Keypads	8	8	8
Partitions	2	4	8
User Codes	47+ Master Codes	71+ Master Codes	94+ Master Codes
Event Buffer	500 Events	500 Events	500 Events
Battery Required	4 Ah / 7 Ah / 14 AHr	4 Ah / 7 Ah / 14 AHr	4 Ah / 7 Ah / 14 AHr
Bell Output	12 V / 700 mA (cont)	12 V / 700 mA (cont)	12 V / 700 mA (cont)

PN 30001422

For product information
www.dsc.com
Product specifications and availability subject to change without notice. Certain product names mentioned herein may be trade names and/or registered trademarks of other companies.
©2012 2012-06

PC1616/PC1832/PC1864 UL/ULC Wiring Diagram

APPLICABLE UL STANDARDS
UL FILE NO. S4019
UL1610 Central-Station Burglar Alarm Units
UL609 Local Burglar Alarm Units and Systems
UL365 Police Station Connected Burglar Alarm Units & Systems
UL985 Household Fire Warning System Units
UL1023 Household Burglar Alarm System Units
UL1635 Digital Alarm Communicator System Units
UL1637 Home Health Care Signaling Equipment
ANSI/SIA CP-01-2000


SIA-FAR Min System Requirements:
1 PC1616/1832/1864 Panel
1 Local annunciation device

Local annunciation devices may be any combination of the keypads: PKP-LCD, PKP-ICN, PK5500, PK5501, PK5508, PK5516

WARNING
Incorrect connections may result in PTC failure or improper operation. Inspect wiring and ensure connections are correct before applying power. Do not route any wiring over circuit boards. Maintain at least 25.4mm (1") separation.

WARNING
High voltage. Disconnect AC power and telephone lines prior to servicing.

All circuits are classified for UL installations as power limited/ClassII power limited, except for the battery leads which are not power limited. Do not route any wiring over circuit boards. Maintain at least 1" (25.4mm) separation. Please see Section 2. A minimum 1/4" (6.4mm) separation must be maintained at all points between power limited wiring and all other non-power limited wiring.




NOTE: Battery capacity for 4h standby is at least 4Ah. Battery capacity for 24h standby is 14Ah (Max. Aux current must not exceed 470mA). Recommended Batteries: DSC BD4-12 or DSC BD7-12.

***AUX Wiring**
Use No.14-22 AWG conductor. AUX+ and Keybus (RED) are internally connected. Total current draw from keypads, PGM Outputs and AUX circuits must not exceed 700mA.


RJ-31X Telephone Plug 26 AWG

NOTE: For ULC fire monitoring, please refer to the PC5700 Installation Instructions

POWER LIMITED



PGM CONNECTIONS



IMPORTANT: Minimum 6.4mm (1/4") separation must be maintained between RM-1 circuits and all other wiring

2-WIRE SMOKE DETECTORS

Compatibility Identifier: PC18-1
Maximum Operating Voltage: 13.8 Vdc
Maximum Circuit Resistance: 24 Ω (total)


DO NOT combine different models on the same circuit as operation may be impaired.

NAME	MODEL	COMPATIBILITY ID	MAX #	BASE
DSC	FSA-210B Series	FS200	SEE NOTE	NONE

NOTE: Refer to the FSA-210 Installation Manual for more details.


4-WIRE SMOKE DETECTORS

Smoke detector must be latching type (ex. DSC FSA-410B Series)
To reset smoke detector, enter [*][7][2]




NOTE: Refer to Installation Manual & Smoke Detector Instruction Sheet when locating detectors.


TYPICAL ZONE CIRCUITS



AUX INPUT WIRING



RESISTOR IDENTIFICATIONS



Circuit (zone)	Control Unit Delay - Sec.	Smoke Detector	
		Model	Delay - Sec. (a)

WARNING: Not to be removed by anyone except occupant. This equipment should be installed in accordance with the National Fire Code ANSI/NFPA 72 (National Fire Protection Association, Batterymarch Park, Quincy MA, 02269). Printed information describing proper installation, operation, testing, maintenance, evacuation planning, and repair service is to be provided with this equipment. For compliance with UL-985, at least one hardwired smoke detector is required.

This device complies with Parts 15 and 68 of the FCC rules. Operation is subject to the following 2 conditions: [1] this device may not cause harmful interference and [2] this device must accept any interference received, including interference that may cause undesired operation.
Model: PC1864 FCC Reg. No. F53AL01BPC1864
Model: PC1832 FCC Reg. No. F53AL01BPC1832
Model: PC1616 FCC Reg. No. F53AL01BPC1614
REN = 0.1B Plug Type: RJ-31X

MADE IN MEXICO

ULC NOTES
- For ULC Listed Fire Monitoring Installations & module requirements, please refer to the ULC Installation Information Sheet, part #29002157.
- Use a CSA/cUL transformer, hardwired.
- All tamper circuits may be connected to the same zone.
- Use ULC-LA for AC Power indication.

(a) The delay (power-up) time marked on the installation wiring diagram of the smoke detector or on the installed smoke detector(s) is to be used. Control panel is suitable for the following UL installations:


Installation Type	Signaling Means
Local Mercantile	DACT, PSDN (OT)
Central Station (Burglary)	PSDN Standard Line Security
Police Station Connected (Burglary)	PSDN Encrypted Line Security


Temperature Range: 0°C-49°C [32°F-120°F] / Maximum Humidity: 85% R.H.
For detailed installation and operating instructions, refer to the Installation Guide #29007916, and the User Manual #29007864. The PC1616/PC1832/PC1864 is UL Listed for limited energy installations per NEC Article 760. Recognized limited energy cable should be used. Observe NEC wiring requirements and local codes defined by the authority having jurisdiction. Security detection devices that require power from the control panel must be UL Listed for the intended application and operate over the range of 11.6-12.6VDC (residential), 12.0VDC (commercial). The DSC Bravo Series are recommended UL Listed motion detectors. Compatible system keypads: PC5508Z, KP5508Z, PC5516Z, KP5516Z, PC5532Z, KP5532Z, LCD5500Z, KP5500Z, LCD5501, LED5501, PKP-LCD, PKP-ICN, PK5500, PK5501, PK5508, PK5516, RFK5500-433, RFK5501-433, RFK5508-433, RFK5516-433.

Professional Series TriTech Curtain Motion Detectors

www.boschsecurity.com

BOSCH
Invented for life





- 30 m (100 ft) x 2.6 m (8.5 ft) standard coverage
- 2.1 m to 3 m (7 ft to 10 ft) mounting height, no adjustments required, optional lookdown masking
- Sensor data fusion technology
- Range adaptive radar and active white light suppression
- Dynamic temperature compensation

The Professional Series TriTech Curtain Detectors are exceptionally suited for commercial indoor applications. Sensor data fusion technology ensures that the detector sends alarm conditions based on precise information. The powerful combination of unique features in the Professional Series delivers superior catch performance and virtually eliminates false alarms.
The self-locking two-piece enclosure, built-in bubble level, flexible mounting height, and three optional mounting brackets simplify installation and reduce service time.

Functions

Sensor Data Fusion Technology
Sensor data fusion technology is a unique feature that uses a sophisticated software algorithm to gather signals from five sensors: two pyroelectric sensors, a range adaptive radar sensor, a room temperature sensor, and a white light level sensor. The microcontroller analyzes and compares the sensor data to make the most intelligent alarm decisions in the security industry.

Range Adaptive Radar
The microwave transceiver automatically adjusts its detection thresholds based on input from the PIR sensors. Integrating the target distance information from the PIR significantly reduces false alarms from the microwave Doppler radar.

Active White Light Suppression
An internal light sensor measures the level of light intensity directed at the face of the detector. Sensor data fusion technology uses this information to eliminate false alarms from bright light sources.

Dynamic Temperature Compensation
The detector automatically adjusts PIR sensitivity to identify human intruders at critical temperatures. Dynamic temperature compensation detects human body heat accurately, avoids false alarms, and delivers consistent catch performance at all operating temperatures.

Cover and Wall Tamper Switch
When an intruder removes the cover or attempts to separate the detector from the wall, a normally-closed contact opens to alert the control panel.

Self-adjusting LEDs
The LED brightness adjusts automatically to the surrounding light level. A blue light-emitting diode (LED) indicates TriTech+ alarms and activates during a walk test. A yellow LED indicates microwave detection, and a red LED indicates PIR detection.

Remote Walk Test LED
Users can enter a command through a keypad, a control center, or programming software to remotely enable or disable the walk test LED.

Alarm Memory
Alarm memory flashes the alarm LED to indicate stored alarms for use in multiple unit applications. A switched voltage from the control panel controls the alarm memory.

Solid State Relays
Solid state relays send silent alarm output signals to provide a higher level of security and reliability. An external magnet does not activate the relay. The solid state relay uses less current than a mechanical relay, providing longer standby capacity during a power loss.

Draft, Insect, and Small Animal Immunity
The sealed optic chamber provides immunity to drafts and insects, reducing false alarms. Small animal immunity reduces false alarms caused by animals less than 4.5 kg (10 lb), such as rodents.

Remote Self Test
A remote self test initiates when the walk test input switches to its true state. The alarm relay and alarm LED activate for four seconds following a successful test. The trouble relay activates, and the alarm LED flashes following a failed test.

Input Power Supervision
When the power is lower than 8 V, a low input power trouble condition activates the trouble relay and causes the LED to flash. The trouble condition clears automatically when power reaches or exceeds 8 V.

Trouble Memory
When the walk test input switches to its true state for less than two seconds, the LED flashes to indicate the most recent trouble condition. If there is no trouble in memory, the LED does not flash. After twelve hours, or after the detector receives a second walk test pulse for two seconds or less, the LED stops flashing and the trouble memory clears.

Cloak and Camouflage Detection Technology
Cloak and Camouflage Detection Technology (C^2DT) maximizes catch performance against intruders attempting to cover their infrared signal.

DIP Switch Programming
The following functions are all programmed using DIP switch settings:

- Local Walk Test LED
- Remote Walk Test Input Polarity
- Alarm Memory Polarity
- MANTIS Anti-mask On and Off

Certifications and approvals

Europe	WEEE	Waste Electrical and Electronic Equipment Directive


The detectors are designed to also comply with requirements of:

USA	FCC	Complies with Part 15

Region	Regulatory compliance/quality marks	
Australia	RCM	[ISC-PDL1-WC30G]
USA	UL	[ISC-PDL1-WC30G]
	UL	20190115; UL639 – Standard for Intrusion-Detection Units

Installation/configuration notes

Coverage Patterns



Standard Curtain Coverage 30 m x 2.6 m (100 ft x 8.6 ft)

Mounting
The recommended mounting height is 2 m to 3 m (7 ft to 10 ft) with no adjustments required.
Mount the motion detector level, both horizontally and vertically.
Mounting options:

- On a flat wall (surface, semi-flush), with the optional B335-3 Swiveling low-profile mount, or with the optional B328 Gimbal-mount Bracket
- In a corner (the junction of two perpendicular walls)
- On the ceiling with the optional B338 Universal Ceiling-mount Bracket

Wiring Considerations
Recommended wire size is 0.2 mm^2 to 1 mm^2 (26 AWG to 16 AWG).

Technical specifications

Electrical

Power Requirements

Voltage (Operating):	9 VDC to 15 VDC
Current (Maximum):	< 26 mA with alarm, trouble, and LEDs active.
Current (Standby):	18 mA at 12 VDC

Outputs for both Models

Tamper:	Normally-closed (NC) contacts (with cover on) rated at 25 VDC, 125 mA maximum. Connect tamper circuit to 24-hour protection circuit.
Trouble:	Solid state relay normally-closed (NC) contacts.
Alarm:	Solid state relay, normally-closed (NC) contacts, power supervised. 3 W, 125 mA, 25 DC, resistance < 10 Ω.

Mechanical

Enclosure Design	
Color:	White
Dimensions:	127 mm x 69 mm x 58 mm (5 in. x 2.75 in. x 2.25 in.)
Material:	High-impact ABS plastic
Indicators	
Alarm Indicator:	• Blue LED for TriTech+ alarms • Yellow LED for microwave detection • Red LED for PIR detection
Zones	
Zones:	28

Environmental

Relative Humidity:	0 to 95%, non-condensing
Temperature (Operating and Storage):	-30°C to +55°C (-22°F to +130°F) *For UL Certificated installations, 0°C to +49°C (+32°F to +120°F)*
Protection Rating (EN 60529, EN 50102):	IP41, IK04

Ordering information

ISC-PDL1-WC30G Motion detector, 100ft (30m), curtain
Provides PIR and microwave, 30 m x 3 m (100 ft x 10 ft) coverage.
Order number **ISC-PDL1-WC30G**

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

ISC-PDL1-WC30H Motion detector 30m curtain, 10.588GHz
Provides PIR and microwave, 30 m x 3 m (100 ft x 10 ft) coverage. For use in France and the United Kingdom.
Order number **ISC-PDL1-WC30H**

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

Accessories

B328 Mounting bracket, gimbal
Mounts on a single-gang box and allows rotation of a detector. Wires are hidden inside.
Order number **B328**

B335-3 Mounting bracket, swivel, low profile
Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°.
Order number **B335-3**

B338 Mounting bracket, ceiling, universal
Swiveling universal bracket for ceiling mounting. The vertical swivel range is +7° to -16°, while the horizontal swivel range is ±45°.
Order number **B338**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

© Bosch Security Systems 2019 | Data subject to change without notice
2610618763 | en, V50, 12. Feb 2019

amseco
A POTTER Brand

ODC-59 SERIES
OVERHEAD DOOR CONTACT



ODC-59 Mini shown

- UL and ULC listed
- 2" operating gap
- HG - 7" Horizontal gap
- 24" stainless steel armored cable
- Adjustable, aluminum L bracket
- Hermetically sealed reed switch

Application

The ODC-59 Series Overhead Door Contacts are exclusively designed for rugged high traffic installations. The reed switch is hermetically sealed with a PVC shock absorber enclosed within a solid aluminum housing. Installation wires are protected in a 24" stainless steel armored cable. The ODC-59 Series magnet is mounted on an adjustable L shaped bracket designed for greater flexibility, universal mounting, greater pulling power, and to provide a professional installation appearance.


The ODC-59-HG (horizontal gap) is designed as a solution for damaged or loose fitting doors.
The ODC-59 MINI offers all the same great features in a smaller size for greater installation flexibility. (Not ULC listed)

ODC-59 Wiring Designations


With Magnet Installed:

Red = Normally-Open (N.O.)	Black = Common (Com)	Green = Normally-Closed (N.C.)


Dimensions



ODC-59



ODC-59 Mini



ODC-59-HG

Ordering Information

Model	Stock Number	Contact	Contact Rating	Contact Type	Max. Carry Current	Max. Switching Current	Breakdown Voltage	Operating Gap	Temperature Range
ODC-59A	4410003	22AWG 24" Leads	10VA	Form A N.O.	2 Amp	.5 Amp	250VDC	2"	32°F - 120°F (0°C - 49°C)
ODC-59A-36	4410004	22AWG 36" Leads							
ODC-59B	4410006	22AWG 24" Leads	3VA	Form C N.O./N.C.	.5 Amp	.2 Amp	150VDC		
ODC-59A-HG	4410018		10VA	Form A N.O.	2 Amp	.5 Amp	250VDC		
ODC-59B-HG	4410019		3VA	Form C N.O./N.C.	.5 Amp	.2 Amp	200VDC		
ODC-59A-MINI	4410017		10VA	Form A N.O.	2 Amp	.5 Amp	250VDC		
Accessories	4350178	Magnet and L bracket							

DSC

A Tyco International Company

DSC PowerSeries Keypads




Features that make a difference:

Common to all Keypads:


- Modern, slim-line landscape keypad
- Large, backlit keypad buttons
- 5 programmable function keys
- Programmable Input/Output terminal
- Individual FAP keys
- Multiple door chime per zone
- Adjustable backlight and keypad buzzer
- Wire channel
- Dual wall-mount and front cover tamper
- Easy-to-install mounting hinge
- Surface or single-gang box mount

Security at your Fingertips


PowerSeries high-quality, slim-profile keypads achieve a clean, unobtrusive look that homeowners welcome and installers will appreciate for their easy programming and installation. The keypads feature an input/output terminal that can be programmed to operate as a zone input, programmable output or as a low temperature sensor. The keypads also include adjustable backlit keys that address low-light situations and five programmable keys for simple one button activation of system functions. PK5500/RFK5500 64-zone full-message keypads support eight languages, global partition status and full, 32-character programmable phrases.




PK5500 | RFK5500



PK5508 | RFK5508



PK5501 | RFK5501



PK5516 | RFK5516

DSC

A Tyco International Company

Easy To Use

To simplify usage, the keypads feature five programmable keys for easy one-button activation of system functions. The default tasks assigned to the five function keys are stay arming, away arming, door chime, smoke detector reset and quick exit. With the quick exit function there's no need to disarm and rearm the system every time an occupant leaves the house or lets the dog out, for example.

Flexibility

The keypads' integrated temperature sensor can be programmed to activate when room temperature dips below 43° F (6° C) and restores at 47° F (8° C). Built-in logic prevents the panel from cycling in and out of alarm mode during minor temperature fluctuations, helping to reduce false alarms.)

Wireless Convenience

RF versions of the keypads are available. They include all of the same features as their hardwired equivalents and are able to support 32 wireless zones and 16 wireless keys without taking up a wireless zone slot.

Full message LCD Keypad languages supported:

Croatian, Czech, Danish, Dutch, English, Estonian, Finnish, French, German, Greek, Hungarian, Italian, Latvian, Lithuanian, Norwegian, Polish, Portuguese, Slovak, Spanish, Swedish

Compatibility

The keypads are compatible with all PowerSeries control panels.

Specifications

Dimensions	6 1/16" x 4 7/16" x 13/16" (154 mm x 113 mm x 20.5 mm)
LCD Viewable Area	3 9/10" x 15/16" (99 mm x 24 mm)
Current Draw	125 mA (Max)
Voltage	12 VDC Nominal
Operating Environment	32° to 120° F (0° to 49° C)
Relative Humidity	5 to 93%

Ordering Information:

PK5500	64-Zone Full-Message LCD Keypad
RFK5500	Wireless 64-Zone Full-Message LCD Keypad
PK5501	64-Zone LCD Picture ICON Keypad
RFK5501	Wireless 64-Zone LCD Picture ICON Keypad
PK5516	16-Zone LED Keypad
RFK5516	Wireless 16-Zone LED Keypad
PK5508	8-Zone LED Keypad
RFK5508	Wireless 8-Zone LED Keypad


PN 3009 0954 REV2

For product information
www.dsc.com
Product specifications are subject to change without notice. Certain product names mentioned herein may be trade names and/or registered trademarks of their companies.
©2011 Tyco

SD-80

RECESSED CONTACTS

1"(25mm) Steel Door Recessed Type



- Contact Size: 1"×.84"(25mm×21.3mm)
- Standard Magnet Size: 1"×.84"(25mm×21.3mm)
- Standard Gap: 1.1"(28mm)
- Colors: White, Brown
- 12"(305mm) 22 AWG Leads Standard
- Longer leads available.

Specifications


Part Number	Gap Inch(mm)	Loop Open/Closed	Reed Form	Max. Contact Rating (W)	Max. Initial Contact Resistance (mΩ)	Max. Switching Voltage (V)	Max. Switching Current (A)
SD-80	1.1"(28)	CLOSED	Normally Open	10	100	AC110/DC100	0.5
SD-81B	1.1"(28)	OPEN	Normally Closed	3	100	AC30/DC30	0.2
SD-80 WG	1.26"(32)	CLOSED	Normally Open	10	100	AC110/DC100	0.5
SD-82C	1.1"(28)	SPDT	SPDT	3	100	AC30/DC30	0.2
SD-84C	.75"(19)	DPDT	DPDT	3	100	AC30/DC30	0.2


OPERATING TEMPERATURE:-40°C to +60°C


Outline Dimensions

Unit: inch(mm)

SD-80/SD-81B







"We Contact The World"®

The Best Guarantee Since 1984 : $50-1

TANE ALARM PRODUCTS

906 JERICHO TURNPIKE, NEW HYDE PARK, NY 11040
Tel: 800-852-5050 • 516-328-3351 • Fax: 516-326-9125
www.tanealarm.com • E-MAIL: info@tanealarm.com


SD-80

RECESSED CONTACTS


Outline Dimensions

Unit: inch(mm)


SD-80 WG



SD-82C




SD-84C




Wiring Diagram

SD-82C



SD-84C



"We Contact The World"®

The Best Guarantee Since 1984 : $50-1

TANE ALARM PRODUCTS

906 JERICHO TURNPIKE, NEW HYDE PARK, NY 11040
Tel: 800-852-5050 • 516-328-3351 • Fax: 516-326-9125
www.tanealarm.com • E-MAIL: info@tanealarm.com

Arctic Electrical Nunavut Ltd
PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

28 31 01 - Fire Alarm Systems

Date: Jun 12, 2018

REVIEWED BY CONTRACTOR
Kudlik Construction Ltd.
NAME: Sandra Rousseau P.Eng
DATE: Jun 12, 2018

Transmittal

Arctic Electrical Nunavut Ltd
PO Box 1381
Iqaluit, Nu.
X0A 0H0
Phone: 867-975-3494
From: Lee Pitcher

SE-02
PO-P18-123

Project **Waste Wate Treatment Plant**
Location Iqaluit NU
To Kudlik Construction
Contact: Sandra Rousseau P.Eng.
srousseau@kudlik.biz

Attached are the following items:

- [x] Drawings
- [ ] Prints
- [ ] Plans
- [x] Specifications
- [ ] Information
- [ ] Submittals

Other:

THESE ARE TRANSMITTED FOR:

- [ ] Prior Approval
- [X] Approval
- [ ] Approval as Submitted
- [ ] Approval as Noted
- [ ] Resubmittal for Approval
- [ ] Corrections
- [ ] Your Use
- [ ] Review and Comment
- [ ] Record

Bids due on:
Other:

Qty	Type	MFG	Part

Section 28 31 01 Fire Alarm System

Notes:
Please review the attached approval drawings carefully. Production cannot be scheduled until a signed copy of the final approved drawing are received. Be aware that once drawings are approved, any errors due to incorrect information are the responsibility of the client.

Do not hesitate to contact me if you have any questions or concerns.



C3779

Job Name: IQALUIT WASTE WATER TREATMENT PLANT

Prop Number: **27-218-3016-000**

Customer: ARCTIC ELECTRICAL

PO Number: P18-123

Date: 2018/06/12

Section 28 31 01 Fire Alarm System

Chubb EDWARDS

28 31 01

LIFE SAFETY & INCIDENT MANAGEMENT

Intelligent Fire Alarm Systems

iO64, iO1000



FDNY
COA 6227

7165-1657:
0244

S3000

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Overview

EDWARDS brand intelligent life safety systems offer the power of high-end intelligent processing in configurations that deliver uncomplicated solutions for small to mid-sized applications. With intelligent detection, electronic addressing, automatic device mapping, optional Ethernet® connectivity, and a full line of easily-configured option cards and modules, these flexible systems offer versatility that benefits building owners and contractors alike.

The iO64 provides one Class A or Class B intelligent device loop that supports up to 64 device addresses, and two Class B Notification Appliance Circuits (NACs). Optional Class A device wiring is available with the use of a module.

The iO1000 provides one Class A or Class B intelligent device loop that supports up to 250 device addresses. Loop controller modules may be added in combination to expand total system capacity in 250-point increments to up to 1,000 device addresses. The iO1000 panel includes four NACs that may be wired for either Class A or Class B operation.

The RZI16-2 module adds even more capacity to iO installations by adding up to 16 conventional device circuits and two additional notification appliance circuits. This makes them an ideal retrofit solution that can accommodate new intelligent detectors, as well as existing conventional devices.

iO Series supports a wide range of high-end features, including:

- Signature Series intelligent modules, detectors, and bases
- R-Series remote annunciators
- SIGA-REL Releasing Modules
- Fully integrated CO detection using Signature Series detectors with or without audible signaling

Features

- Auto-programming speeds installation time
- Supports Signature Series intelligent modules and detectors
- Combines the Signature intelligent releasing module with Signature multisensor detectors for reliable fire suppression
- Form C contacts for alarm and trouble, Form A for supervisory
- Electronic addressing with automatic device mapping
- Optional Ethernet port for diagnostics, programming and a variety of system reports
- Two programmable switches with LEDs and custom labeling
- Supports Genesis horn silence over two wires, and UL 1971-compliant strobe synchronization
- Class B or Class A wiring
- Ground fault detection by module
- Supports up to eight serial annunciators, (LCD, LED-only, and graphic interface)
- Can use existing wiring for most retrofit applications
- Upload/download remotely or locally
- Two-level maintenance alert reporting
- Pre-alarm and alarm verification by point
- Adjustable detector sensitivity
- 4 x 20 character backlit LCD display
- Optional earthquake hardening: seismic Importance Factor 1.5
- Standalone operation
- Transmission test frequency by hour

Application

28 31 01

EDWARDS iO Series life safety systems are powerful intelligent solutions for small to mid-sized buildings. Advanced intelligent technology delivers the benefits of flexible system installation, while clean and easy-to-operate user interfaces make panel operation and system maintenance quick and intuitive.

The smart choice

Signature Series electronic addressing eliminates the tedium of setting dipswitches, and automatic device mapping ensures that each device resides on the system at its correct location. Meanwhile, innovative programming allows the designer to customize the system to precisely suit the needs of the building owner.

Reliability you can count on

The inherent fault-tolerant characteristics of Analog/Addressable Technology boosts the reliability of EDWARDS fire alarm systems. When combined with iO Series smoke and heat detectors, these systems deliver a level of dependability not previously available for small to mid-sized applications. All EDWARDS systems are built to exacting reliability benchmarks and meet international standards for quality, in addition to agency listings for dependability.

Clear-cut remote annunciation

Remote annunciation is a strong suit of the iO Series fire alarm systems. Up to eight annunciators can be installed on a single system. Compatible annunciators include a range of LED and LCD models that provide zone or point annunciation, as well as common control capabilities. iO control panels also supports graphic annunciation with optional RA Graphic Annunciator interface modules. Each interface provides common control and 32 LEDs.

Flexibility built right in

Two fully-programmable front panel switch/LED combinations provide an added measure of flexibility. Their slide-in labels take the mystery out of custom applications, and present a clean finished appearance.

Perfect for retrofits

EDWARDS iO Series control panels are particularly well-suited to retrofit applications. All connections are made over standard wiring – no shielded cable required. This means that in most situations existing wiring can be used to upgrade a legacy control panel to iO technology without the expense or disruption of rewiring the entire building. iO control panels also support the ingenious RZI16-2 Zone Module, which adds up to 16 conventional circuits and two NACs. This combination easily accommodates new intelligent detection alongside existing conventional circuits, making it an superior solution in the retrofit market.

Signals with a difference

iO system NACs are configurable to fully support the advanced signaling technology of EDWARDS Genesis and Enhanced Integrity notification appliances. These devices offer precision synchronization of strobes to UL 1971 standards. For Genesis devices, enabling this feature allows horns to be silenced while strobes on the same two-wire circuit continue to flash until the panel is reset.

A complete line of accessories

iO Series life safety systems are supported by a complete line of analog/addressable detectors, modules and related equipment. Consult the Ordering Information section for details.

Programming and remote diagnostics

EDWARDS iO Series life safety systems are simple to set up, yet offer advanced programming features that put these small building panels into a class of their own. The auto programming feature quickly gets the panel operational using factory default settings. Basic zone and point settings can be programmed through the front panel interface, so the system is up and running in no time.


For more advanced system configuration and correlation groups programming, iO Series systems interface to a PC running compatible iO-CU software. This option offers full system configuration in the familiar Windows® operating environment. Connection is made to a laptop through the panel's optional RS-232 communications port, which can also be used to connect a system printer.

Among the many innovative features of iO Series control panels is the optional network card. This module provides a standard 10/100 Base T Ethernet® network connection that permits access to the control panel from any remote location with the correct communications protocols. The connection can be used to download to the panel from the iO-CU, or upload and view system reports using the iO-CU.

Available system reports include:

- Correlation groups
- Device maintenance
- Internal status
- System status
- Dialer
- Device details
- History
- System configuration
- Walk test
- CO runtime

Dimensions



(1) Surface Mounting Holes
(2) Semi-flush mounting Holes
(3) Backbox with Door Attached
(4) Backbox with door and trim kit attached.

Panel dimensions, in (cm)


Model	D1*	D2	D3	D4	D5*	D6	D7	D8	D9
iO1000	28.0 (71.1)	3.85 (9.8)	9.0 (22.8)	22.0 (55.8)	15.75 (40.0)	10.25 (26.0)	4.4 (11.1)	28.2 (71.6)	2.7 (6.8)
iO64	21.5 (54.6)	3.85 (9.8)	7.5 (19.0)	15.5 (39.4)	14.25 (36.2)	10.25 (26.0)	4.5 (11.4)	21.7 (55.1)	2.7 (6.8)

** Add 1-1/2 in. (3.81 cm) to D1 and D5 dimensions for trim kit. The trim kit provides 0.75 inches (1.9 cm) of trim to the top, bottom, and sides of the backbox.*

System Layout


28 31 01

iO1000




Each iO1000 panel has room for up to two Signature loop controller modules in any combination of single or dual 250-device loops. iO1000 loops support 125 detectors and 125 modules.

iO64



Each iO64 panel ships with one Signature loop controller that supports 64 devices of any type. This panel's device capacity cannot be expanded.

Panel Layout




1 Transformer
2 Main AC wiring block & fuse holder
3 RS-232 card connector (J3)
4 Dialer card connection (J8)
5 Ethernet card connector (J1)
6 Main circuit board
7 Panel backbox enclosure
8 Operator interface
9 SLC card connector (J7)
10 Class A card connector (J2)
11 Tie wrap mounts
12 LED expander connector (J6)
13 Standby batteries

28 31 01

Signature device loop

The system provides one Signature device loop circuit with a total capacity of 125 detectors and 125 module addresses. The loop circuit is supervised for opens, shorts, and grounds.


Circuit specifications	iO1000	iO64
Device loops	One Class B or A loop, supporting 125 detectors and 125 modules. Expandable to four loops.	One Class B or A loop, supporting 64 devices of any kind.
Communication line voltage	Maximum 20 V peak-to-peak	
Circuit current	0.5 A max	
Circuit impedance	66Ω total, 0.5 µF, max	
Isolators	64 maximum	
Signal Synchronization	Supported on a system-wide basis (all device loops) when using a SIGA-CC1S or SIGA-MCC1S module and Genesis or Enhanced Integrity notification appliances.	



Notification appliance circuits (TB2)

iO1000 control panels come equipped with four notification appliance circuits. iO64 control panels come with two NACs. Each circuit can be individually configured for continuous, temporal, synchronized, and coded output.

Specifications	iO1000	iO64
Circuit Type	4 Class B or 2 Class A	2 Class B or 2 Class A with SA-CLA module
Voltage	24 VFWR	
Current	6.0 A total, 2.5 A max. per circuit at 120/230 VAC 60 Hz. 5.0 A total, 2.5 A max. per circuit at 230 VAC 50 Hz.	3.75 A total, 2.5 A max. per circuit at 120/230 VAC 60 Hz. 3.0 A total, 2.5 A max. per circuit at 230 VAC 50 Hz.
Impedance	26 Ω total, 0.35 µF max	
EOLR	15 K Ω, ½ W	
Synchronization	Supported system-wide	




Marking indicates output signal polarity when the circuit is active. Polarity reverses when the circuit is not active. Wire notification appliances accordingly. Notification appliance polarity shown in active state.

Auxiliary & smoke power outputs (TB3)

The control panel provides two auxiliary power outputs that can be used for powering ancillary equipment such as remote annunciators and two wire smoke detectors. Aux 2 can be software selected to operate continuously. The circuit is supervised for shorts and grounds.

Circuit specifications	
Circuit voltage range	21.9 to 28.3 V
Resettable circuit (Aux power 2)	24 VDC nominal at 500 mA
Continuous circuit (Aux power 1)	24 VDC nominal at 500 mA. Use this circuit for powering two-wire smoke detectors.

Note: Any current above 0.5 amp connected to both Aux 1 and 2 will reduce the total available NAC power by that amount.



(1) Trouble
(2) Supervisory
(3) Alarm
(4) Smoke/Aux

Alarm, trouble, and supervisory relay (TB3)

The trouble relay is normally-open, held closed, and opens on any trouble event or when the panel is de-energized. The supervisory relay is normally-open, and closes on any supervisory event. The alarm relay changes over on any alarm event.

Relay specifications

	Alarm	Trouble	Supervisory
Type	Form C		Form A
Voltage	24 VDC at 1 A resistive	24 VDC at 1 A resistive	

Relay circuits can only be connected to power-limited sources.


Annunciator loop (TB4)

The control panel provides a connection for up to eight serially driven and supervised remote annunciators.


Circuit specifications

Device loops	Class B (Style Y) or Class A (Style Z)
Circuit voltage	2.55 V
Circuit current	30 mA max
Circuit impedance	Up to 8 annunciators or 4000 feet

Class B



Class A



Option Cards

28 31 01

EDWARDS iO Series panels are supported by a complete line of modules and related equipment that enhance performance and extend system capabilities. Option cards plug directly into the control panel main circuit board or are connected to it with a ribbon cable. After installation, terminals remain accessible. The cabinet provides ample room for wire routing, keeping wiring neat at all times.


Single and Dual Loop Controller Cards

The iO-SDC1 is a single loop controller card that can be used with the iO64 as a replacement for the standard 64-point loop, or with the iO1000 as a 250-point expansion module.

The iO-SDC2 is a 500-point dual loop controller card for the iO1000 that provides two SLC circuits, each with 125 detector addresses and 125 module addresses.

Specifications	iO-SDC1	iO-SDC2
Device Addresses	iO1000: one loop, 250 device addresses iO64: 64 addresses	iO1000: two loops, 500 device addresses
Wiring	Class B or Class A	
Operating Voltage	24 VDC	
Operating Current (fully loaded loop)	Standby: 55 mA Alarm: 80 mA	Standby: 45 mA Alarm: 70 mA
Note: These ratings do not include the use of two-wire smoke modules.		
Communication Line Voltage	Max. 20.6 V peak-to-peak	
Terminal Rating	12 to 18 AWG (0.75 to 2.5 mm^2)	
Circuit Current	0.5 A max.	
Max total loop resistance	66 Ω	
Max total loop capacitance	0.5 µF	
Isolators	64 isolators maximum per loop (total both isolator bases and modules)	
Ground Fault Impedance	0 to 5 kΩ	
Operating Environment	32 to 120°F (0 to 49°C) 0 to 93% noncondensing at 90°F (32°C)	

SA-ETH Ethernet Interface Card




The SA-ETH card provides a standard 10/100 Base T Ethernet network connection for connecting to an intranet, a local network, or the Internet. The card can be used to download configuration programming from the iO-CU to the panel.

The Ethernet card is installed on the plastic assembly and connects to the main circuit board via a ribbon cable.

SA-ETH specifications	
Ethernet	10/100 Base T
Operating environment	
Temperature	32 to 120°F (0 to 49°C)
Humidity	0 to 93% RH, noncondensing at 90°F (32°C)

RZI16-2 Remote Zone Interface Module



The RZI16-2 Addressable Remote Zone Interface Module is an addressable device that provides connections for sixteen Class B Initiating Device Circuits and two Class B Supervised Output Circuits. The inputs and outputs can be configured individually for several device types.


It requires 18 consecutive addresses on the Signaling Line Circuit (SLC). Addresses are assigned electronically. There are no address switches to set.

The RZI16-2 incorporates two 8-segment DIP switches that are used to select the Alarm or Supervisory default device type for each of the 16 IDC circuits. The module also includes one 4-segment DIP switch used to select the default Relay or NAC output device type. Device types other than the default are accomplished through programming.

RZI16-2 Specifications	
Voltage	
24V/Aux nominal:	24 VDC
Supervisory current:	250 mA at 24 VDC nominal
Alarm Current	1000 mA
24V/Aux minimum:	18.4 VDC
24V/Aux maximum:	26.4 VDC
NAC1, NAC2 nominal:	24 VDC
Current	
Standby current for 4.7 k EOL (U.S.)	4.8 mA/ circuit
Standby current for 3.9 k EOL (Canada)	5.7 mA/ circuit
Alarm current at nominal voltage	31.1 mA/ circuit
Relay outputs	
Quantity	2
Type Rating (pilot duty)	Programmable 24 VDC at 2.5 A
Input circuit wiring resistance	25 Ω per wire
Initiating device circuits	
Quantity	16
EOL resistor	4.7 kΩ (U.S.); 3.9 kΩ Canada
Zone voltage	22.78 V for 4.7 kΩ (U.S.) 22.08 V for 3.9 kΩ (Canada)
Alarm current	31.1 mA/ channel at nominal voltage
Alarm impedance range	< 680 Ω
Trouble impedance range	> 5.55 kΩ
Supervised output circuits	
EOL resistor	15 kΩ
Quantity	2
Short circuit detection	< 2.6 kΩ
Open circuit detection	> 61.9 kΩ
Contact ratings	24 VDC at 2.5 A (5 A for two NACs)
Compatible cabinets	MFC(A), iO1000, APS

SA-DACT Dialer

The SA-DACT provides communications between the control panel and the central station over a telephone line system. It transmits system status changes (events) to a compatible digital alarm communicator receiver over the public switched telephone network. The dialer is capable of single, dual, or split reporting of events to two different account and telephone numbers. The modem feature of the SA-DACT can also be used for uploading and downloading panel configuration, history, and current status to a PC running the iO-CU.



The dialer phone lines connect to connectors on the dialer's main circuit board. Phone line 1 connects to connector J4 and phone line 2 connects to connector J1.

The SA-DACT queues messages and transmits them based on priority (alarm, supervisory, trouble, and monitor). Activations are transmitted before restorations.


The SA-DACT is installed on the plastic assembly and connects to the main circuit board via a ribbon cable.

SA-DACT specifications	
Phone line type	One or two loop-start lines on a public, switched network
Phone line connector	RJ-31/38X (C31/38X)
Communication formats	Contact ID (SIA DC-05)
Operating environment	
Temperature	32 to 120°F (0 to 49°C)
Humidity	0 to 93% RH, noncondensing at 90°F (32°C)

Compatible DACRs		
Receiver	**Models**	**Formats**
Ademco	685	Contact ID
FBII	CP220	Contact ID
Osborne-Hoffman	OH 2000	Contact ID
Bosch	D6600	Contact ID
Silent Knight	9800	Contact ID
Sur-Gard	SG-MLR1, MLR2	Contact ID

SA-232 RS-232 interface

The SA-232 card provides an RS-232 interface with iO panels. It can be used for connecting a printer to the control panel to print system events. The card also can be used for connecting a computer to download a configuration program from the iO-CU to the control panel.



The RS-232 card is installed on the plastic assembly and connects to the main circuit board via a ribbon cable.

SA-232 specifications	
Operating voltage	Standard EIA-232
Terminal rating	12 to18 AWG (0.75 to 2.5 sq mm)
Operating environment	
Temperature	32 to 120°F (0 to 49°C)
Humidity	0 to 93% RH, noncondensing at 90°F (32°C)


SA-CLA Class A Module (iO64 only)

The SA-CLA card provides Class A capability for NAC wiring. Its terminal block provides the wiring connection for NAC return wiring. The card is required for annunciator Class A wiring even though this wiring does not return to the SA-CLA card. The SA-CLA is compatible with iO64 control panels only. iO1000 panels are Class A Ready. The SA-CLA is installed directly to the control panel circuit board using its plastic standoffs and plug connection.

SA-CLA specifications	
Operating voltage	24 VFWR
Operating current	3.75 A FWR total at 120/230 VAC 60 Hz 3.0 A FWR total at 230 VAC 50 Hz 2.5 A max per circuit
Circuit impedance	26 ohms, 0.35uF
Terminal rating	12 to18 AWG (0.75 to 2.5 sq mm)
Operating environment	
Temperature	32 to 120°F (0 to 49°C)
Humidity	0 to 93% RH, noncondensing at 90°F (32°C)

D16L-iO LED Display Expander (iO1000 only)

The D16L-iO LED Display Expanders provide LED annunciation for up to 16 zones. It provides two LEDs for each zone. Two D16L-iO LED display expanders can be installed in each iO1000 panel.



(1) LED 1
(2) LED 2
(3) LED Expander 1
(4) LED Expander 2
(5) Alarm/non-alarm and trouble zone LEDs

Specifications

	iO64	iO1000
Device loops	1 loop Class B or Class A (Styles 4, 6, 7) supporting up to 64 device addresses (any combination of detectors and modules) Maximum T-taps: 63 (each device can be on its own branch)	1 loop, expandable to 4, Class A or B (Styles 4, 6, 7), each loop supporting up to 250 device addresses (125 detectors and 125 modules max.). Addresses 1 to 125 are for detectors and addresses 126 to 250 are for modules Maximum T-taps/loop: 124
Notification appliance circuits	2 Class B (Style Y), Class A (Style Z) optional 3.75 A FWR total at 120/230 VAC 60 Hz 3.0 A FWR total at 230 VAC 50 Hz 2.5 A FWR each max. per circuit	4 Class B (Style Y) or 2 Class A (Style Z) 6.0 A FWR total at 120/230 VAC 60 Hz 5.0 A FWR total at 230 VAC 50 Hz 2.5 A FWR each max. per circuit
Primary power	120 VAC, 60 Hz, 1.3 A max. 230 VAC, 50-60 Hz, 0.62 A max.	120 VAC, 60 Hz, 2.0 A max. 230 VAC, 50-60 Hz, 0.97 A max.
Base panel current standby	155 mA	172 mA
Base panel current alarm	204 mA	267 mA
Input zones	16 max.	32 max.
Remote annunciator	8 drops max., RS-485 Class B, Class A is optional Data line length: 4,000 ft. (1,219 m)	8 drops max., RS-485 Class A or B Data line length: 4,000 ft. (1,219 m)
Operating voltage	24 VDC panel	
Auxiliary power output circuit	Aux power 1: 500 mA, 24 VDC Aux power 2: 500 mA, 24 VDC (1 A possible if you reduce total available NAC power by 500 mA) Output: 28.3 to 21.9 VDC, special application *Note: For a list of compatible devices, see the iO64 and iO1000 Series Compatibility List (P/N 3102353-EN)*	
Loop circuit	Maximum loop resistance: 66 Ω Maximum loop capacitance: 0.5 µF Communication line voltage: Maximum 20.6 V peak-to-peak Operating current (fully loaded loop) Stand by: 55 mA/45 mA Alarm: 125 mA/115 mA (not including two-wire smoke modules) Circuit current: 0.5 A max. Style 4, 6, and 7 wiring Max. resistance between isolators: Limited only by overall wire run lengths 64 isolators maximum per loop (total both isolator bases and modules)	
Batteries	Type: Sealed lead acid Voltage: 24 VDC Charging current: 2.47 A max. Amp hour capacity: 26 Ah Standby operation: 24 hour or 60 hour Placement: Up to two 10 Ah batteries will fit in the iO64 control panel cabinet and two 18 Ah batteries will fit in the iO1000 control panel cabinet. If larger batteries are required, use an EDWARDS battery cabinet.	
SA-DACT dialer	Phone line type: One or two loop-start lines on a public, switched network Phone line connector: RJ-31/38X (C31/38X) Communication formats: Contact ID (SIA DC-05) Operating current Standby/Alarm: 41 mA Max.: 100 mA FCC registration number: GESAL01BSADACT Industry Canada Registration number: 3944A-SADACT Ringer equivalence number: 0.1B	
Ground fault impedance	0 to 5 kΩ	
Alarm contact	Form C N.O. 24 VDC at 1 A (resistive load)	
Trouble contact	Form C 24 VDC at 1 A (resistive load)	
Supervisory contact	Form A N.O. 24 VDC at 1 A (resistive load)	
Environmental	Temperature: 0 to 49°C (32 to 120°F) Relative humidity: 0 to 93% noncondensing	
Terminal rating	All terminals rated for 12 to 18 AWG (0.75 to 2.5 mm^2)	

LIFE SAFETY & INCIDENT MANAGEMENT

Contact us...

Email: edwards.fire@fs.utc.com
Web: *Edwards-fire.com*

EDWARDS is a UTC brand.
1016 Corporate Park Drive
Mebane, NC 27302

© 2016 United Technologies Corporation.
All rights reserved.

Ordering Information

28 31 01

Part	Description
iO1000 Fire Alarm Systems	
IO1000G	Four loop system with one 250-point loop installed. 110v, gray door.
IO1000G-2	Four loop system with one 250-point loop installed. 230v, gray door.
IO1000G-2-PG	Four loop system with one 250-point loop installed. 230v, gray door, Portuguese.
IO1000G-2-SP	Four loop system with one 250-point loop installed. 230v, gray door, Spanish.
IO1000G-CA	Four loop system, one 250-point loop installed. 110v, gray door, LED strips, Canada.
IO1000GD	Four loop system, one 250-point loop installed. 110v, gray door, with dialer.
IO1000G-F	Four loop system, one 250-point loop. 110v, gray door, LED strips, French Canada.
IO1000G-PG	Four loop system with one 250-point loop installed. 110v, gray door, Portuguese.
IO1000G-SP	Four loop system with one 250-point loop installed. 110v, gray door, Spanish.
IO1000R	Four loop system with one 250-point loop installed. 110v, red door.
IO1000R-2	Four loop system with one 250-point loop installed. 230v, red door.
IO1000RD	Four loop system, one 250-point loop installed. 110v, red door, with dialer.
SA-TRIM2	iO1000 Flush mount trim, black.
iO64 Fire Alarm Systems	
IO64G	One loop system with one 64-point loop installed. 110v, gray door.
IO64G-2	One loop system with one 64-point loop installed. 230v, gray door.
IO64G-2-PG	One loop system with one 64-point loop installed. 230v, gray door, Portuguese.
IO64G-2-SP	One loop system with one 64-point loop installed. 230v, gray door, Spanish.
IO64GD	One loop system, one 64-point loop installed. 110v, gray door, with dialer.
IO64GL	One loop system, one 64-point loop installed. 110v, gray door, English Canada.
IO64GL-F	One loop system, one 64-point loop installed. 110v, gray door, French Canada.
IO64G-PG	One loop system with one 64-point loop installed. 110v, gray door, Portuguese.
IO64G-SP	One loop system with one 64-point loop installed. 110v, gray door, Spanish.
IO64R	One loop system with one 64-point loop installed. 110v, red door.
IO64R-2	One loop system with one 64-point loop installed. 230v, red door.
IO64RD	One loop system, one 64-point loop installed. 110v, red door, with dialer.
SA-TRIM1	iO64 Flush mount trim, black
Option Cards	
iO-SDC1	Expansion module, one 250-device loop.
iO-SDC2	Expansion module, two 250-device loops, 500 devices total. For iO1000 only.
RZI16-2	Remote Zone Interface Module. 16 Class B IDCs, 2 Class B Output. Includes bracket.
SA-DACT	Dual Line Dialer/Modem, supports Contact ID, mounts in cabinet on base plate.
SA-232	RS-232 Serial Port for connection to printers & computers, mounts in cabinet.
SA-ETH	Ethernet Port, Slave, mounts in cabinet on base plate.
SA-CLA	Class A adapter module. Provides Class A capacity on NACs. Mounts in cabinet on main board. iO64 systems only.
D16L-iO-2	LED Annunciator module, 16 X 2-LED zones (4 programmable for sup). Mounts in cabinet to right of LCD display for zones 17-32. For iO1000 only.
D16L-iO-1	LED Annunciator module, 16 X 2-LED zones (4 programmable for sup). Mounts in cabinet to left of LCD display for zones 1-16. For iO1000 only.
D8RY-iO-2	***Canada only:*** LED Annunciator module, two LEDs per zone, 16 zones (4 alarm only, 8 supervisory only, 4 alarm or supervisory). Mounts in cabinet. For iO1000 only.
D8RY-iO-1	***Canada only:*** LED Annunciator module, two LEDs per zone, 16 zones (4 alarm only, 8 supervisory only, 4 alarm or supervisory). Mounts in cabinet. For iO1000 only.
Accessories	
CTM	City Tie Module. 2-gang. Connection to a local energy fire alarm box.
MFC-A	Multifunction Fire Cabinet, 8" x 14" x 3.5" - red.
SIGA-REL	Releasing Module
PT-1S	System Printer
BC-1	Battery Cabinet. 14.0" x 18.25" x 7.25". Holds two 12V24A batteries.
BC-1R	Battery Cabinet - Red. 14.0" x 18.25" x 7.25". Holds two 12V24A batteries.
BC-1EQ	Seismic hardening Kit for iO series panels. Includes battery hardening for BC-1 enclosure and components to harden panel internal components.
Programming Tools	
iO-CU	IO Series configuration and diagnostics utility.
260097	RS232 cable, 4 conductor, DB9 PC interface

EDWARDS
United Technologies
LIFE SAFETY & INCIDENT MANAGEMENT

28 31 01

Intelligent Heat Detector

SIGA-HRD



S853

Overview

The SIGA-HRD is an intelligent fixed temperature/rate-of-rise fire detector. It monitors the temperature of the surrounding air and analyzes the data from the sensor to determine whether to initiate an alarm. The rate-of-rise heat function quickly detects a fast, flaming fire. The fixed-temperature heat function detects fire when the air temperature near the detector exceeds the alarm point.

The SIGA-HRD brings advanced sensing technology to a practical design that increases efficiency, saves installation time, cuts costs, and extends property protection capabilities. Continuous self-diagnostics ensures reliability over the long-haul, while the latest thermister technology makes these detectors ideal whereever dependable heat detection is required.

Standard Features

Note: *Some features described here may not be supported by all control systems. Check your control panel's Installation and Operation Guide for details.*

- Next Generation Heat Sensing Technology
- 15 °F (9 °C) per minute rate-of-rise alarm point
- 135 °F (57 °C) fixed temperature alarm point
- Uses existing wiring
- Automatic device mapping
- Sensor Markings Provide Easy Testing Identification
- Up To 250 Total Signature Devices Per Loop
- Non-volatile memory
- Electronic addressing
- Bicolor (green/red) status LED
- Standard, relay, fault isolator, and audible mounting bases
- 50 foot (15.2 meter) spacing

Provide detectors approved for the location in which they are installed as per the electrical drawings.

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Application


The SIGA-HRD combination fixed temperature/rate-of-rise heat detector provides a 15 °F (9 °C) per minute rate-of-rise heat sensor for the detection of fast-developing fires, as well as a 135°F (57°C) fixed temperature sensor for slow building-fires. The heat sensor monitors the temperature of the air and determines whether an alarm should be initiated.

Compatibility

The SIGA-HRD detector is compatible only with the Signature Loop Controller.

Installation

Signature Series detectors mount to North American 1-gang boxes, 3-1/2 inch or 4 inch octagon boxes, and to 4 inch square electrical boxes 1-1/2 inches (38 mm) deep. They mount to European BESA and 1-gang boxes with 60.3 mm fixing centers. See mounting base installation and wiring for more information.



Sensing and reporting technology

The microprocessor in each detector provides additional benefits - Self-diagnostics and History Log, Automatic Device Mapping, and Fast, Stable Communication.

Self-diagnostics and History Log - Each Signature Series detector constantly runs self-checks to provide important maintenance information. The results of the self-check are automatically updated and permanently stored in the detector's non-volatile memory.

Automatic Device Mapping - The loop controller learns where each device's serial number address is installed relative to other devices on the circuit. The mapping feature provides supervision of each device's installed location to prevent a detector from being reinstalled (after cleaning etc.) in a different location from where it was originally.

Fast Stable Communication - On-board intelligence means less information needs to be sent between the detector and the loop controller. Other than regular supervisory polling response, the detector only needs to communicate with the loop controller when it has something new to report.

Accessories 28 31 01

Detector mounting bases have wiring terminals that are accessible from the "room-side" after mounting the base to the electrical box. The bases mount to North American 1-gang boxes and to 3½ inch or 4 inch octagon boxes, 1½ inches (38 mm) deep. They also mount to European BESA and 1-gang boxes with 60.3 mm fixing centers. The SIGA-SB4, SIGA-RB4, and SIGA-IB4 mount to North American 4 inch sq. electrical boxes in addition to the above boxes. They include the SIGA-TS4 Trim Skirt, which is used to cover the "mounting ears" on the base. The SIGA-AB4G mounts to a 4 inch square box only.


SIGA-AB4G/T/LF
Audible Base


SIGA-SB
Standard Base


SIGA-IB
Isolator Base


SIGA-RB
Relay Base


SIGA-LED
Remote LED

Remote LED SIGA-LED - The remote LED connects to the SIGA-SB or SIGA-SB4 Standard Base only. It features a North American size 1-gang plastic faceplate with a white finish and red alarm LED.

SIGA-TS4 Trim Skirt - Supplied with 4 inch bases, it can also be ordered separately to use with the other bases to help hide surface imperfections not covered by the smaller bases.

Sounder Bases - Signature Series sounder bases are designed for use where localized or group alarm signaling is required.

- **SIGA-AB4G** bases provide sounder capability to Signature Series to heat and smoke detectors. They are not intended for use with combination carbon monoxide detectors in Fire-plus-CO mode.
- **SIGA-AB4GT** bases provide sounder capability to Signature Series smoke and heat detectors, as well as carbon monoxide detectors when used with a SIGA-TCDR Temporal Pattern Generator.
- **SIGA-AB4G-LF** bases provide 520 Hz low frequency sounder capability to Signature Series smoke and heat detectors, as well as carbon monoxide detectors when used with a SIGA-TCDR Temporal Pattern Generator. The SIGA-AB4G-LF is suitable for applications requiring low frequency audible tones.

Warnings & Cautions

- This detector does not operate without electrical power. As fires frequently cause power interruption, discuss further safeguards with the local fire protection specialist.
- This detector does not sense fires in areas where heat cannot reach the detector. Heat from fires in walls, roofs, or on the opposite side of closed doors may not reach the detector.
- This heat detector by itself does not provide life safety protection Use this detector with ionization and/or photoelectric smoke detectors.
- This detector does not detect oxygen levels, smoke, toxic gases, or flames. Use this device as part of a broad-based life safety program which includes a variety of information sources pertaining to heat and smoke levels, extinguishment systems, visual and audible devices, and other safety measures.
- Independent studies indicate that heat detectors should only be used when property protection alone is involved. Never rely on heat detectors as the sole means of fire protection.


Typical Wiring

The detector mounting bases accept #18 AWG (0.75mm^2), #16 (1.0mm^2), #14 AWG (1.5mm^2), and #12 AWG (2.5mm^2) wire sizes. Sizes #16 AWG (1.0mm^2) and #18 AWG (0.75mm^2) are preferred for ease of installation.

Standard Detector Base, SIGA-SB, SIGA-SB4

This is the basic mounting base for EDWARDS Signature Series detectors. The SIGA-LED Remote LED is supported by this Base.

Term	Description
1	Not Used
2	DATA IN/OUT (+)
3	Not Used
4	DATA IN (-)
4	Remote LED (-)
5	Remote LED (+)
6	Not Used
7	DATA OUT (-)




Isolator Detector Base, SIGA-IB, SIGA-IB4

This base includes a built-in line fault isolator for use on Class A circuits. A detector must be installed for it to operate. The isolator base does not support the SIGA-LED Remote LED.

The isolator operates as follows:

- a short on the line causes all isolators to open within 23 msec
- at 10 msec intervals, beginning on one side of the Class A circuit nearest the loop controller, the isolators close to provide the next isolator down the line with power
- when the isolator next to the short closes, it reopens within 10 msec.

The process repeats beginning on the other side of the loop controller.




Term	Description
1	Not Used
2	DATA IN/OUT (+)
3	DATA IN (-)
4	Not Used
5	Not Used
6	DATA OUT (-)
7	Not Used

28 31 01

Relay Detector Base, SIGA-RB, SIGA-RB4

This base includes a relay. Normally Open or Normally Closed operation is selected during installation. The dry contact is rated for 1 amp (pilot duty) @ 30 Vdc. The relay's position is supervised to avoid accidentally jarring it out of position. The SIGA-RB can be operated as a control relay if programmed to do so at the control panel. The relay base does not support the SIGA-LED Remote LED.




CONTACT RATING
1.0 Amp @ 30 VDC
(Pilot Duty)

Term	Description
1	Normally Open
2	DATA IN/OUT (+)
3	Common
4	DATA IN (-)
5	Not Used
6	Normally-Closed
7	DATA OUT (-)


Audible Sounder Bases, Fire Mode

AB4GT, AB4G, AB4G-LF sounder bases



28 31 01

Dimensions



Specifications

Operating voltage	15.20 to 19.95 VDC
Normal operating current	32 µA
Alarm current	32 µA
Vibration level	10 to 35 Hz, with an amplitude of 0.01 in.
Rate-of-rise rating	15°F/min (8°C/min)
Fixed temperature rating	135°F (57.2°C). Actual alarm point 129 to 141°F (53.9 to 60.6°C).
Maximum spacing	50 ft. (15.2 m) centers
Compatible bases	See Ordering Information
Compatible detector testers	Testifire 1000, Testifire 2000
Operating environment	32 to 100°F (0 to 38°C), 0 to 93% RH, noncondensing
Construction	High Impact Engineering Polymer, White
Storage temperature	-4 to 140°F (-20 to 60°C)
Agency Listings	CAN/ULC-S530, UL 521

Ordering Information

	Catalog Number	Description	Ship Wt. lbs (kg)
★	SIGA-HRD	Intelligent fixed temperature/Rate-of-rise heat detector	0.4 (0.16)
	Compatible Bases		
★	SIGA-SB	Detector Mounting Base - Standard	
	SIGA-SB4	4-inch Detector Mounting Base c/w Trim Skirt	
	SIGA-RB	Detector Mounting Base w/Relay	
	SIGA-RB4	4-inch Detector Mounting Base w/Relay, c/w Trim Skirt	0.2 (.09)
	SIGA-IB	Detector Mounting Base w/Fault Isolator	
	SIGA-IB4	4-inch Detector Mounting Base w/ Fault Isolator, c/w Trim Skirt	
	SIGA-LED	Remote Alarm LED (not for EN54 applications)	
	SIGA-AB4G	Audible (Sounder) Base for Fire Detectors	0.3 (0.15)
	SIGA-AB4G-LF	Low Frequency Audible (Sounder) Base for CO and Fire Detectors	0.3 (0.15)
	SIGA-AB4GT	Audible (Sounder) Base for CO and Fire Detectors	0.3 (0.15)
	SIGA-TS4	Trim Skirt (supplied with 4-inch bases)	0.1 (0.04)
	SIGA-TS	Trim Skirt - (optional for non 4-inch bases)	0.1 (0.04)
	SIGA-DMP	Detector Mounting Plate	3.0 (1.4)
	SIGA-RTA	Detector Removal Tool	

LIFE SAFETY & INCIDENT MANAGEMENT

Contact us...

Email: edwards.fire@fs.utc.com
Web: *Edwards-fire.com*

EDWARDS is a UTC brand.
1016 Corporate Park Drive
Mebane, NC 27302

© 2016 United Technologies Corporation.
All rights reserved.

28 31 01

LIFE SAFETY & INCIDENT MANAGEMENT

Intelligent Smoke Detector

SIGA-PD



S853

Overview

The Signature Series SIGA-PD optical smoke detector brings advanced sensing technology to a practical design that increases efficiency, saves installation time, cuts costs, and extends life safety and property protection capabilities. Continuous self-diagnostics ensure reliability over the long-haul, while environmental compensation helps reduce maintenance costs.

Like all Signature Series detectors, the SIGA-PD is an intelligent device that gathers analog information from its optical sensor, converting this data into digital signals. To make an alarm decision, the detector's on-board microprocessor measures and analyzes sensor readings and compares this information to historical data. Digital filters remove signal patterns that are not typical of fires, thus virtually eliminating unwanted alarms.

Standard Features

Note: *Some features described here may not be supported by all control systems. Check your control panel's Installation and Operation Guide for details.*

- Next Generation Optical Smoke Sensing Technology
- Wide 0.53 to 3.94 %/ft. (1.7 to 12.35 %/m) smoke obscuration
- Uses Existing Wiring
- Automatic Device Mapping
- Up To 250 Total Signature Addresses Per Loop
- Two Levels of Environmental Compensation
- Two Levels of Dirty Detector Warning
- Twenty Pre-Alarm Settings
- Five Sensitivity Settings
- Non-Volatile Memory
- Electronic Addressing
- Identification of Dirty or Defective Detectors
- Automatic Day/Night Sensitivity Adjustment
- Bicolor (Green/Red) Status Led
- Standard, Relay, Fault Isolator, and Audible Mounting Bases
- Sensor Markings Provide Easy Testing Identification

Provide detectors approved for the location in which they are installed as per the electrical drawings.

STANTEC PROJECT #: 110126045

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☑ Electrical
☐ Structural ☐ Other
☐ Mechanical

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

SUBMITTAL # ELE-002 Fire Alarm Systems

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Application


The SIGA-PD detects extremely small particles of combustion and triggers an alarm at the first sign of smoke. Thanks to its high-performance forward-scattering reflective response technology, the photoelectric smoke sensor responds quickly and reliably to a wide range of fire types, especially slow burning fires fuelled by combustibles typically found in modern multi-use buildings.

Compatibility

The SIGA-PD detector is compatible only with the Signature Loop Controller.

Installation

Signature Series detectors mount to North American 1-gang boxes, 3-1/2 inch or 4 inch octagon boxes, and to 4 inch square electrical boxes 1-1/2 inches (38 mm) deep. They mount to European BESA and 1-gang boxes with 60.3 mm fixing centers. See mounting base installation and wiring for more information.



Sensing and reporting technology

The microprocessor in each detector provides additional benefits - Self-diagnostics and History Log, Automatic Device Mapping, and Fast, Stable Communication.

Self-diagnostics and History Log - Each Signature Series detector constantly runs self-checks to provide important maintenance information. The results of the self-check are automatically updated and permanently stored in the detector's non-volatile memory

Automatic Device Mapping - The loop controller learns where each device's serial number address is installed relative to other devices on the circuit. The mapping feature provides supervision of each device's installed location to prevent a detector from being reinstalled (after cleaning etc.) in a different location from where it was originally.

Fast Stable Communication - On-board intelligence means less information needs to be sent between the detector and the loop controller. Other than regular supervisory polling response, the detector only needs to communicate with the loop controller when it has something new to report.

Testing & Maintenance 28 31 01

Each detector automatically identifies when it is dirty or defective and causes a "dirty detector" message. The detector's sensitivity measurement can also be transmitted to the loop controller. A sensitivity report may be printed to satisfy NFPA sensitivity measurements, which must be conducted at the end of the first year and every two years thereafter.

The user-friendly maintenance program shows the current state of each detector and other pertinent messages. Single detectors may be turned off temporarily from the control panel. Availability of maintenance features is dependent on the fire alarm system used.

Accessories

Detector mounting bases have wiring terminals that are accessible from the "room-side" after mounting the base to the electrical box. The bases mount to North American 1-gang boxes and to 3½ inch or 4 inch octagon boxes, 1½ inches (38 mm) deep. They also mount to European BESA and 1-gang boxes with 60.3 mm fixing centers. The SIGA-SB4, SIGA-RB4, and SIGA-IB4 mount to North American 4 inch sq. electrical boxes in addition to the above boxes. They include the SIGA-TS4 Trim Skirt, which is used to cover the "mounting ears" on the base. The SIGA-AB4G mounts to a 4 inch square box only.


SIGA-AB4G/T/LF
Audible Base


SIGA-SB
Standard Base


SIGA-IB
Isolator Base


SIGA-RB
Relay Base


SIGA-LED
Remote LED

Remote LED SIGA-LED - The remote LED connects to the SIGA-SB or SIGA-SB4 Standard Base only. It features a North American size 1-gang plastic faceplate with a white finish and red alarm LED.

SIGA-TS4 Trim Skirt - Supplied with 4 inch bases, it can also be ordered separately to use with the other bases to help hide surface imperfections not covered by the smaller bases.

Sounder Bases - Signature Series sounder bases are designed for use where localized or group alarm signaling is required.

- **SIGA-AB4G** bases provide sounder capability to Signature Series to heat and smoke detectors. They are not intended for use with combination carbon monoxide detectors in Fireplus-CO mode.
- **SIGA-AB4GT** bases provide sounder capability to Signature Series smoke and heat detectors, as well as carbon monoxide detectors when used with a SIGA-TCDR Temporal Pattern Generator.
- **SIGA-AB4G-LF** bases provide 520 Hz low frequency sounder capability to Signature Series smoke and heat detectors, as well as carbon monoxide detectors when used with a SIGA-TCDR Temporal Pattern Generator. The SIGA-AB4G-LF is suitable for applications requiring low frequency audible tones.


Typical Wiring

The detector mounting bases accept #18 AWG (0.75mm^2), #16 (1.0mm^2), #14 AWG (1.5mm^2), and #12 AWG (2.5mm^2) wire sizes. Sizes #16 AWG (1.0mm^2) and #18 AWG (0.75mm^2) are preferred for ease of installation.

Standard Detector Base, SIGA-SB, SIGA-SB4

This is the basic mounting base for EDWARDS Signature Series detectors. The SIGA-LED Remote LED is supported by this Base.

Term	Description
1	Not Used
2	DATA IN/OUT (+)
3	Not Used
4	DATA IN (-)
4	Remote LED (-)
5	Remote LED (+)
6	Not Used
7	DATA OUT (-)




Isolator Detector Base, SIGA-IB, SIGA-IB4

This base includes a built-in line fault isolator for use on Class A circuits. A detector must be installed for it to operate. The isolator base does not support the SIGA-LED Remote LED.

The isolator operates as follows:

- a short on the line causes all isolators to open within 23 msec
- at 10 msec intervals, beginning on one side of the Class A circuit nearest the loop controller, the isolators close to provide the next isolator down the line with power
- when the isolator next to the short closes, it reopens within 10 msec.


The process repeats beginning on the other side of the loop controller.



Term	Description
1	Not Used
2	DATA IN/OUT (+)
3	DATA IN (-)
4	Not Used
5	Not Used
6	DATA OUT (-)
7	Not Used

Relay Detector Base, SIGA-RB, SIGA-RB4

This base includes a relay. Normally Open or Normally Closed operation is selected during installation. The dry contact is rated for 1 amp (pilot duty) @ 30 Vdc. The relay's position is supervised to avoid accidentally jarring it out of position. The SIGA-RB can be operated as a control relay if programmed to do so at the control panel. The relay base does not support the SIGA-LED Remote LED.




CONTACT RATING
1.0 Amp @ 30 VDC
(Pilot Duty)

Term	Description
1	Normally Open
2	DATA IN/OUT (+)
3	Common
4	DATA IN (-)
5	Not Used
6	Normally-Closed
7	DATA OUT (-)

28 31 01

Audible Sounder Bases, Fire Mode

AB4GT, AB4G, AB4G-LF sounder bases



Warnings & Cautions

- This detector does not operate without electrical power. As fires frequently cause power interruption, discuss further safeguards with the local fire protection specialist.
- This detector does not sense fires in areas where smoke cannot reach the detector. Smoke from fires in walls, roofs, or on the opposite side of closed doors may not reach the detector.
- Photoelectric detectors have a wide range of fire-sensing capabilities and are best suited for detecting slow, smoldering fires.
- In Canada, install according to CAN/ULC-S524 Standard for the Installation of Fire Alarm Systems, CSA C22.1 Canadian Electrical Code, and the local authority having jurisdiction.

LIFE SAFETY & INCIDENT MANAGEMENT


Contact us...

Email: edwards.fire@fs.utc.com
Web: *Edwards-fire.com*

EDWARDS is a UTC brand.
1016 Corporate Park Drive
Mebane, NC 27302

© 2016 United Technologies Corporation.
All rights reserved.

Dimensions



Specifications

Operating voltage	15.20 to 19.95 VDC
Normal operating current	32 µA
Alarm current	32 µA
Smoke Sensitivity Range	UL/ULC: 0.53 to 3.94 %/ft. (1.7 to 12.35 %/m) obscuration
Vibration level	10 to 35 Hz, with an amplitude of 0.01 in.
Air velocity	0 to 4,000 ft./min (0 to 20 m/s)
Wall mounting	12 in. (305 mm) max. from ceiling
Compatible bases	See Ordering Information
Compatible detector testers	Testifire 1000, Testifire 2000
Operating environment	32 to 120°F (0 to 49°C), 0 to 93% RH, noncondensing
Construction	High Impact Engineering Polymer, White
Storage temperature	-4 to 140°F (-20 to 60°C)
Environmental compensation	Automatic
Agency Listings	CAN/ULC-S529, UL 268, UL 268A

Ordering Information

	Catalog Number	Description	Ship Wt. lbs (kg)
★	SIGA-PD	Intelligent Optical Smoke Detector	0.4 (0.16)
	Accessories		
★	SIGA-SB	Detector Mounting Base - Standard	
	SIGA-SB4	4-inch Detector Mounting Base c/w Trim Skirt	
	SIGA-RB	Detector Mounting Base w/Relay	
	SIGA-RB4	4-inch Detector Mounting Base w/Relay, c/w Trim Skirt	0.2 (.09)
	SIGA-IB	Detector Mounting Base w/Fault Isolator	
	SIGA-IB4	4-inch Detector Mounting Base w/ Fault Isolator, c/w Trim Skirt	
	SIGA-LED	Remote Alarm LED (not for EN54 applications)	
	SIGA-AB4G	Audible (Sounder) Base for Fire Detectors	0.3 (0.15)
	SIGA-AB4G-LF	Low Frequency Audible (Sounder) Base for CO and Fire Detectors	0.3 (0.15)
	SIGA-AB4GT	Audible (Sounder) Base for CO and Fire Detectors	0.3 (0.15)
	SIGA-TS4	Trim Skirt (supplied with 4-inch bases)	0.1 (0.04)
	SIGA-TS	Trim Skirt - (optional for non 4-inch bases)	0.1 (0.04)
	SIGA-DMP	Detector Mounting Plate	3.0 (1.4)
	SIGA-RTA	Detector Removal Tool	
	SIGA-VA	Detector Cleaning Tool	

EST™
Life Safety & Communications

28 31 01

Input Modules

SIGA-CT1, SIGA-CT1HT, SIGA-CT2, SIGA-MCT2

STANTEC PROJECT #: 110126045 SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☑ Electrical
☐ Structural ☐ Other
☐ Mechanical

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED
☐ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.


SIGA-MCT2


SIGA-CT1/2

MEA

Application Notes Available

Overview

The SIGA-CT1 Single Input Module, SIGA-CT1HT High Temperature Single Input Module and SIGA-CT2/SIGA-MCT2 Dual Input Modules are intelligent analog addressable devices used to connect one or two Class B normally-open Alarm, Supervisory, or Monitor type dry contact Initiating Device Circuits (IDC).

The actual function of these modules is determined by the "personality code" selected by the installer. This code is downloaded to the module from the Signature loop controller during system configuration.

The input modules gather analog information from the initiating devices connected to them and convert it into digital signals. The module's on-board microprocessor analyzes the signal and decides whether or not to input an alarm.

The SIGA-CT1, SIGA-CT1HT and SIGA-CT2 mount to standard North American 1-gang electrical boxes, making them ideal for locations where only one module is required. Separate I/O and data loop connections are made to each module.

The SIGA-CT1HT module operates at an expanded temperature range of 32 ºF to 158 ºF (0 ºC to 70 ºC) for those applications requiring more extreme environmental temperature variation.

The SIGA-MCT2 is part of the UIO family of plug-in Signature Series modules. It functions identically to the SIGA-CT2, but takes advantage of the modular flexibility and easy installation that characterizes all UIO modules. Two- and six-module UIO motherboards are available. All wiring connections are made to terminal blocks on the motherboard. UIO assemblies may be mounted in Edwards enclosures.

Standard Features

- **Multiple applications**
  Including Alarm, Alarm with delayed latching (retard) for waterflow applications, Supervisory, and Monitor. The installer selects one of four "personality codes" to be downloaded to the module through the loop controller.
- **SIGA-CT1HT rated for high temperature environments**
  Suitable for attic installation and monitoring high temperature heat detectors.
- **Plug-in (UIO) or standard 1-gang mount**
  UIO versions allow quick installation where multiple modules are required. The 1-gang mount version is ideal for remote locations that require a single module.
- **Automatic device mapping**
  Signature modules transmit information to the loop controller regarding their circuit locations with respect to other Signature devices on the wire loop.
- **Electronic addressing**
  Programmable addresses are downloaded from the loop controller, a PC, or the SIGA-PRO Signature Program/Service Tool. There are no switches or dials to set.
- **Stand-alone operation**
  The module makes decisions and inputs an alarm from initiating devices connected to it even if the loop controller's polling interrogation stops. (Function availability dependent upon control panel.)
- **Ground fault detection by address**
  Detects ground faults right down to the device level.

Signature Series Overview


The Signature Series intelligent analog-addressable system from Edwards Security is an entire family of multi-sensor detectors and mounting bases, multiple-function input and output modules, network and non-network control panels, and user-friendly maintenance and service tools. Analog information from equipment connected to Signature devices is gathered and converted into digital signals. An onboard microprocessor in each Signature device measures and analyzes the signal and decides whether or not to input an alarm. The microprocessor in each Signature device provides four additional benefits – Self-diagnostics and History Log, Automatic Device Mapping, Stand-alone Operation and Fast, Stable Communication.

Self-diagnostics and History Log – Each Signature Series device constantly runs self-checks to provide important maintenance information. The results of the self-check are automatically updated and permanently stored in its non-volatile memory. This information is accessible for review any time at the control panel, PC, or using the SIGA-PRO Signature Program/Service Tool.


Automatic Device Mapping –The Signature Data Controller (SDC) learns where each device's serial number address is installed relative to other devices on the circuit. The SDC keeps a map of all Signature Series devices connected to it. The Signature Series Data Entry Program also uses the mapping feature. With interactive menus and graphic support, the wired circuits between each device can be examined. Layout or "as-built" drawing information showing branch wiring (T-taps), device types and their address are stored on disk for printing hard copy.

Installation

SIGA-CT1, SIGA-CT1HT and SIGA-CT2: modules mount to North American 2½ inch(64 mm) deep 1-gang boxes and 1½ inch (38 mm) deep 4 inch square boxes with 1-gang covers and SIGA-MP mounting plates. The terminals are suited for #12 to #18 AWG (2.5 mm^2 to 0.75 mm^2) wire size.



SIGA-MCT2: mount the UIO motherboard inside a suitable Edwards enclosure with screws and washers provided. Plug the SIGA-MCT2 into any available position on the motherboard and secure the module to the motherboard with the captive screws. Wiring connections are made to the terminals on the motherboard (see wiring diagram). UIO motherboard terminals are suited for #12 to #18 AWG (2.5 mm^2 to 0.75 mm^2) wire size.



Electronic Addressing - The loop controller electronically addresses each module, saving valuable time during system commissioning. Setting complicated switches or dials is not required. Each module has its own unique serial number stored in its on-board memory. The loop controller identifies each device on the loop and assigns a "soft" address to each serial number. If desired, the modules can be addressed using the SIGA-PRO Signature Program/Service Tool.

Edwards recommends that this module be installed according to latest recognized edition of national and local fire alarm codes.

Application

The duty performed by the SIGA-CT1 and SIGA-CT2/MCT2 is determined by their sub-type code or "Personality Code". The code is selected by the installer depending upon the desired application and is downloaded from the loop controller.

One personality code can be assigned to the SIGA-CT1. Two personality codes can be assigned to the SIGA-CT2/MCT2. Codes 1, 2, 3 and 4 can be mixed on SIGA-CT2/MCT2 modules only. For example, personality code 1 can be assigned to the first address (circuit A) and code 4 can be assigned to the second address (circuit B).

NORMALLY-OPEN ALARM - LATCHING (Personality Code 1) - Assign to one or both circuits. Configures either circuit A or B or both for Class B normally open dry contact initiating devices such as Pull Stations, Heat Detectors, etc. An ALARM signal is sent to the loop controller when the input contact is closed. The alarm condition is latched at the module.

NORMALLY-OPEN ALARM - DELAYED LATCHING (Personality Code 2) - Assign to one or both circuits. Configures either circuit A or B or both for Class B normally-open dry contact initiating devices such as Waterflow Alarm Switches. An ALARM signal is sent to the loop controller when the input contact is closed for approximately 16 seconds. The alarm condition is latched at the module.

NORMALLY-OPEN ACTIVE - NON-LATCHING (Personality Code 3) - Assign to one or both circuits. Configures either circuit A or B or both for Class B normally-open dry contact monitoring input such as from Fans, Dampers, Doors, etc. An ACTIVE signal is sent to the loop controller when the input contact is closed. The active condition is not latched at the module.

NORMALLY-OPEN ACTIVE - LATCHING (Personality Code 4) - Assign to one or both circuits. Configures either circuit A or B or both for Class B normally open dry contact monitoring input such as from Supervisory and Tamper Switches. An ACTIVE signal is sent to the loop controller when the input contact is closed. The active condition is latched at the module.


Typical Wiring

28 31 01


Modules will accept #18 AWG (0.75mm²), #16 (1.0mm²), and #14AWG (1.50mm²), and #12 AWG (2.50mm²) wire sizes.

Note: Sizes #16 AWG (1.0mm²) and #18 AWG (0.75mm²) are preferred for ease of installation. See Signature Loop Controller catalog sheet for detailed wiring requirement specifications.

Initiating (Slave) Device Circuit Wire Specifications		
Maximum Allowable Wire Resistance	50 ohms (25 ohms per wire) per Circuit	
Maximum Allowable Wire Capacitance	0.1µF per Circuit	
For Design Reference:	**Wire Size**	**Maximum Distance to EOLR**
	#18 AWG (0.75 mm²)	4,000 ft (1,219 m)
	#16 AWG (1.00 mm²)	
	#14 AWG (1.50 mm²)	
	#12 AWG (1.50 mm²)	




SIGA-CT1, SIGA-CT1HT



SIGA-CT2

NOTES

1. Maximum 25 Ohm resistance per wire.
2. Maximum #12 AWG (2.5 mm²) wire; Minimum #18 AWG (0.75 mm2).
3. Refer to Signature controller installation sheet for wiring specifications.
4. Maximum 10 Vdc @ 350 µA
5. The SIGA-UIO6R and the SIGA-UIO2R do not come with TB14.
6. All wiring is supervised and power-limited.
7. These modules will not support 2-wire smoke detectors.



SIGA-MCT2

Warnings & Cautions

This module will not operate without electrical power. As fires frequently cause power interruption, we suggest you discuss further safeguards with your local fire protection specialist.

Compatibility

The Signature Series modules are compatible only with EST's Signature Loop Controller.

28 31 01

Specifications

Catalog Number	SIGA-CT1HT	SIGA-CT1	SIGA-CT2	SIGA-MCT2
Description	Single Input Module		Dual Input Module	
Type Code	48 (factory set) Four sub-types (personality codes) are available		49 (factory set) Four sub-types (personality codes) are available	
Address Requirements	Uses One Module Address		Uses Two Module Addresses	
Operating Current	Standby = 250µA; Activated = 400µA		Standby = 396µA; Activated = 680µA	
Operating Voltage	15.2 to 19.95 Vdc (19 Vdc nominal)			
Construction	High Impact Engineering Polymer			
Mounting	North American 2½ inch (64 mm) deep one-gang boxes and 1½ inch (38 mm) deep 4 inch square boxes with one-gang covers and SIGA-MP mounting plates			UIO2R/6R/6 Motherboard
Operating Environment	32°F to 158°F (0°C to 70°C)	32°F to 120°F (0°C to 49°C)		
Storage Environment	-4°F to 140°F (-20°C to 60°C); Humidity: 0 to 93% RH			
LED Operation	On-board Green LED - Flashes when polled; On-board Red LED - Flashes when in alarm/active. Both LEDs - Glow steady when in alarm (stand-alone)			
Compatibility	Use with Signature Loop Controller			
Agency Listings	UL, ULC, MEA, CSFM			

Ordering Information

Catalog Number	Description	Ship Wt. lbs (kg)
SIGA-CT1	Single Input Module — UL/ULC Listed	0.4 (0.15)
SIGA-CT1HT	Single Input Module High Teperature Operation UL/ULC Listed	0.4 (0.15)
★ SIGA-CT2	Dual Input Module — UL/ULC Listed	0.4 (0.15)
SIGA-MCT2	Dual Input Plug-in (UIO) Module — UL, ULC Listed	0.1 (0.05)

Related Equipment		
27193-11	Surface Mount Box - Red, 1-gang	1.0 (0.6)
27193-16	Surface Mount Box - White, 1-gang	1.0 (0.6)
SIGA-UIO2R	Universal Input-Output Module Board w/Riser Inputs — Two Module Positions	0.32 (0.15)
SIGA-UIO6R	Universal Input-Output Module Board w/Riser Inputs — Six Module Positions	0.62 (0.28)
SIGA-UIO6	Universal Input-Output Module Board — Six Module Positions	0.56 (0.25)
MFC-A	Multifunction Fire Cabinet — Red, supports Signature Module Mounting Plates	7.0 (3.1)
SIGA-MB4	Transponder Mounting Bracket (allows for mounting two 1-gang modules in a 2-gang box)	0.4 (0.15)
SIGA-MP1	Signature Module Mounting Plate, 1 footprint	1.5 (0.70)
SIGA-MP2	Signature Module Mounting Plate, 1/2 footprint	0.5 (0.23)
SIGA-MP2L	Signature Module Mounting Plate, 1/2 extended footprint	1.02 (0.46)

EDWARDS
A UTC Fire & Security Company

Detection & alarm since 1872

U.S.
T 888-378-2329
F 866-503-3996

Canada
Chubb Edwards
T 519 376 2430
F 519 376 7258

Southeast Asia
T : +65 6391 9300
F : +65 6391 9306

India
T : +91 80 4344 2000
F : +91 80 4344 2050

Australia
T +61 3 9239 1200
F +61 3 9239 1299

Europe
T +32 2 725 11 20
F +32 2 721 86 13

Latin America
T 305 593 4301
F 305 593 4300

utcfireandsecurity.com

© 2010 UTC Fire & Security.
All rights reserved.

EST™
Life Safety & Communications

28 31 01

Control Relay Modules

SIGA-CR, SIGA-MCR, SIGA-CRR, SIGA-MCRR



MEA

Overview

The Control Relay Module and the Polarity Reversal Relay Module are part of the Signature Series system. They are intelligent analog addressable devices available in either plug-in (UIO) versions, or standard 1-gang mount versions.

The SIGA-CR/MCR Control Relay Module provides a Form "C" dry relay contact to control external appliances such as door closers, fans, dampers etc. This device does not provide supervision of the state of the relay contact. Instead, the on-board microprocessor ensures that the relay is in the proper ON/OFF state. Upon command from the loop controller, the SIGA-CR/MCR relay activates the normally open or normally-closed contact.

The SIGA-CRR/MCRR Polarity Reversal Relay Module provides a Form "C" dry relay contact to power and activate a series of SIGA-AB4G Audible Sounder Bases. Upon command from the Signature loop controller, the SIGA-CRR reverses the polarity of its 24 Vdc output, thus activating all Sounder Bases on the data loop.

Standard-mount versions (SIGA-CR and SIGA-CRR) are installed to standard North American 1-gang electrical boxes, making them ideal for locations where only one module is required. Separate I/O and data loop connections are made to each module.


Plug-in UIO versions (SIGA-MCR and SIGA-MCRR) are part of the UIO family of plug-in Signature Series modules. They function identically to the standard mount versions, but take advantage of the modular flexibility and easy installation that characterizes all UIO modules. Two- and six-module UIO motherboards are available. All wiring connections are made to terminal blocks on the motherboard. UIO assemblies may be mounted in Edwards enclosures.

Standard Features


- **Provides one no/nc contact (SIGA-CR/MCR)**
  Form "C" dry relay contact can be used to control external appliances such as door closers, fans, dampers etc.
- **Allows group operation of sounder bases**
  The SIGA-CRR/MCRR reverses the polarity of its 24 Vdc output, thus activating all Sounder Bases on the data loop.
- **Plug-in (UIO) or standard 1-gang mount**
  UIO versions allow quick installation where multiple modules are required. The 1-gang mount version is ideal for remote locations that require a single module.
- **Automatic device mapping**
  Signature modules transmit information to the loop controller regarding their circuit locations with respect to other Signature devices on the wire loop.
- **Electronic addressing**
  Programmable addresses are downloaded from the loop controller, a PC, or the SIGA-PRO Signature Program/Service Tool; there are no switches or dials to set.
- **Intelligent device with microprocessor**
  All decisions are made at the module to allow lower communication speed with substantially improved control panel response time and less sensitivity to line noise and loop wiring properties; twisted or shielded wire is not required.
- **Ground fault detection by address**
  Detects ground faults right down to the device level.

Installation

SIGA-CR and SIGA-CRR: modules mount to North American 2½ inch (64 mm) deep 1-gang boxes and 1½ inch (38 mm) deep 4 inch square boxes with 1-gang covers and SIGA-MP mounting plates. The terminals are suited for #12 to #18 AWG (2.5 mm^2 to 0.75 mm^2) wire size.



SIGA-MCR and SIGA-MCRR: mount the UIO motherboard inside a suitable Edwards enclosure with screws and washers provided. Plug the module into any available position on the motherboard and secure the module to the motherboard with the captive screws. Wiring connections are made to the terminals on the motherboard (see wiring diagram). UIO motherboard terminals are suited for #12 to #18 AWG (2.5 mm^2 to 0.75 mm^2) wire size.



Electronic Addressing - The loop controller electronically addresses each module, saving valuable time during system commissioning. Setting complicated switches or dials is not required. Each module has its own unique serial number stored in its onboard memory. The loop controller identifies each device on the loop and assigns a "soft" address to each serial number. If desired, the modules can be addressed using the SIGA-PRO Signature Program/Service Tool.

Edwards recommends that this module be installed according to latest recognized edition of national and local fire alarm codes.

Application

The operation of Signature Series control relays is determined by their sub-type code or "Personality Code."

Personality Code 8: CONTROL RELAY (SIGA-CR/MCR) - Dry Contact Output. This setting configures the module to provide one Form "C" DRY RELAY CONTACT to control Door Closers, Fans, Dampers, etc. Contact rating is 2.0 amp @ 24 Vdc; 0.5 amp @ 120 Vac (or 220 Vac for non-UL applications). Personality Code 8 is assigned at the factory. No user configuration is required.

Personality Code 8: POLARITY REVERSAL RELAY MODULE (SIGA-CRR/MCRR). This setting configures the module to reverse the polarity of its 24 Vdc output. Contact rating is 2.0 amp @ 24 Vdc (pilot duty). Personality Code 8 is assigned at the factory. No user configuration is required.

Compatibility

The Signature Series modules are compatible only with EST's Signature Loop Controller.

Warnings & Cautions

This module will not operate without electrical power. As fires frequently cause power interruption, we suggest you discuss further safeguards with your local fire protection specialist.


Testing & Maintenance

The module's automatic self-diagnosis identifies when it is defective and causes a trouble message. The user-friendly maintenance program shows the current state of each module and other pertinent messages. Single modules may be turned off (deactivated) temporarily, from the control panel. Availability of maintenance features is dependent on the fire alarm system used. Scheduled maintenance (Regular or Selected) for proper system operation should be planned to meet the requirements of the Authority Having Jurisdiction (AHJ). Refer to current NFPA 72 and ULC CAN/ULC 536 standards.


Typical Wiring

Modules will accept #18 AWG (0.75mm²), #16 (1.0mm²), #14 AWG (1.50mm²) and #12 AWG (2.5mm²) wire sizes.

Note: Sizes #16 AWG (1.0mm²) and #18 AWG (0.75mm²) are preferred for ease of installation. See Signature Loop Controller catalog sheet for detailed wiring requirement specifications.



SIGA-CR Control Relay



SIGA-MCR Control Relay


Notes

1. Refer to Signature Loop Controller Installation Sheet for wiring specifications.
2. NFPA 72 requires that the SIGA-CR/SIGA-MCR be installed in the same room as the device it is controlling. This requirement may not apply in all markets. Check with your local AHJ for details.
3. The SIGA-UIO6R and the SIGA-UIO2R do not come with TB14.
4. The SIGA-UIO6 does not come with TB8 through TB13.
5. Supervised and power-limited.
6. If the source is nonpower-limited, maintain a space of 1/4 inch from power-limited wiring or use FPL, FPLP, FPLR, or an equivalent in accordance with the National Electrical Code.
7) Maximum #12 AWG (2.5mm²) wire. Min. #18 (0.75mm²).


Typical Wiring


Modules will accept #18 AWG (0.75mm²), #16 (1.0mm²), #14 AWG (1.50mm²) and #12 AWG (2.50mm²) wire sizes.


Note: Sizes #16 AWG (1.0mm²) and #18 AWG (0.75mm²) are preferred for ease of installation. See Signature Loop Controller catalog sheet for detailed wiring requirement specifications.



SIGA-MCRR







Notes

1. Refer to the Signature controller installation sheet for wiring.
2. One Pair of Wires (24 Vdc power).
3. One Pair of Wires (Signature Data).
4. Single Wire (24 Vdc power).
5. The SIGA-UIO6R and the SIGA-UIO2R do not come with TB14.
6. The SIGA-UIO6 does not come with TB8 through TB13.
7. Supervised and power-limited.
8. If the source is nonpower-limited, maintain a space of 1/4 inch from power-limited wiring or use FPL, FPLP, FPLR, or an equivalent in accordance with the National Electrical Code.
9. Maximum #12 AWG (2.5 mm²) wire; Minimum #18 AWG (0.75 mm²).
10. End-of-Line Relay must monitor and report power supply trouble to control panel.
11. Class B Data wiring may be “T-tapped.”

Specifications

28 31 01

Catalog Number	SIGA-CR	SIGA-MCR	SIGA-CRR	SIGA-MCRR
Description	Control Relay		Polarity Reversal Relay	
Type Code	Personality Code 8 (Factory Set)		Personality Code 8 (Factory Set)	
Address Requirements	Uses 1 Module Address			
Operating Current	Standby = 100µA Activated = 100µA			
Operating Voltage	15.2 to 19.95 Vdc (19 Vdc nominal)			
Relay Type and Rating	Form "C" 24 VDC = 2 amps (pilot duty) 120 Vac = 0.5 amps 220 Vac (non-UL) = 0.5 amps			
Mounting	North American 2½ inch (64 mm) deep 1-gang boxes and 1½ inch (38 mm) deep 4 inch square boxes with 1-gang covers and SIGA-MP mounting plates	Plugs into UIO2R, UIO6R or UIO6 Motherboards	North American 2½ inch (64 mm) deep 1-gang boxes and 1½ inch (38 mm) deep 4 inch square boxes with 1-gang covers and SIGA-MP mounting plates	Plugs into UIO2R, UIO6R or UIO6 Motherboards
Construction & Finish	High Impact Engineering Polymer			
Storage and Operating Environment	Operating Temperature: 32°F to 120°F (0°C to 49°C) Storage Temperature: -4°F to 140°F (-20°C to 60°C) Humidity: 0 to 93% RH			
LED Operation	On-board Green LED - Flashes when polled On-board Red LED - Flashes when in alarm/active			
Compatibility	Use With: Signature Loop Controller			
Agency Listings	UL, ULC, CSFM, MEA			

Ordering Information

Catalog Number	Description	Ship Weight - lbs (kg)
★ SIGA-CR	Control Relay Module (Standard Mount)	0.4 (0.15)
SIGA-MCR	Control Relay Module (UIO Mount)	0.18 (0.08)
SIGA-CRR	Polarity Reversal Relay Module (Standard Mount)	0.4 (0.15)
SIGA-MCRR	Polarity Reversal Relay Module (UIO Mount)	0.18 (0.08)
Related Equipment		
27193-11	Surface Mount Box - Red, 1-gang	1 (0.6)
27193-16	Surface Mount Box - White, 1-gang	1 (0.6)
SIGA-UIO2R	Universal Input-Output Module Board w/Riser Inputs - Two Module Positions	0.32 (0.15)
SIGA-UIO6R	Universal Input-Output Module Board w/Riser Inputs - Six Module Positions	0.62 (0.28)
SIGA-UIO6	Universal Input-Output Module Board - Six Module Positions	0.56 (0.25)
SIGA-AB4G	Audible (Sounder) Detector Base	0.3 (0.15)
Accessories		
MFC-A	Multifunction Fire Cabinet - Red, supports Signature Module Mounting Plates	7.0 (3.1)
SIGA-MB4	Transponder Mounting Bracket (allows for mounting two 1-gang modules in a 2-gang box)	0.4 (0.15)
SIGA-MP1	Signature Module Mounting Plate, 1 footprint	1.5 (0.70)
SIGA-MP2	Signature Module Mounting Plate, 1/2 footprint	0.5 (0.23)
SIGA-MP2L	Signature Module Mounting Plate, 1/2 extended footprint	1.02 (0.46)

EDWARDS
A UTC Fire & Security Company

Detection & alarm since 1872

U.S.
T 888-378-2329
F 866-503-3996

Canada
Chubb-Edwards
T 519 376 2430
F 519 376 7258

Southeast Asia
T : +65 6391 9300
F : +65 6391 9306

India
T : +91 80 4344 2000
F : +91 80 4344 2050

Australia
T +61 3 9239 1200
F +61 3 9239 1299

Europe
T +32 2 725 11 20
F +32 2 721 86 13

Latin America
T 305 593 4301
F 305 593 4300

utcfireandsecurity.com

© 2010 UTC Fire & Security.
All rights reserved.

Signature Series Overview

28 31 01

The Signature Series intelligent analog-addressable system from Edwards is an entire family of multi-sensor detectors and mounting bases, multiple-function input and output modules, network and non-network control panels, and user-friendly maintenance and service tools. Analog information from equipment connected to Signature devices is gathered and converted into digital signals. An onboard microprocessor in each Signature device measures and analyzes the signal and decides whether or not to input an alarm. The microprocessor in each Signature device provides four additional benefits – Self-diagnostics and History Log, Automatic Device Mapping, Stand-alone Operation and Fast, Stable Communication.

Self-diagnostics and History Log – Each Signature Series device constantly runs self-checks to provide important maintenance information. The results of the self-check are automatically updated and permanently stored in its non-volatile memory. This information is accessible for review any time at the control panel, PC, or using the SIGA-PRO Signature Program/Service Tool. The information stored in device memory includes:

- Device serial number, address, and type
- Time and date of last alarm
- Most recent trouble code logged by the detector — 32 possible trouble codes may be used to diagnose faults.

Automatic Device Mapping –The Signature Data Controller (SDC) learns where each device's serial number address is installed relative to other devices on the circuit. The SDC keeps a map of all Signature Series devices connected to it. The Signature Series Data Entry Program also uses the mapping feature. With interactive menus and graphic support, the wired circuits between each device can be examined. Layout or "as-built" drawing information showing branch wiring (T-taps), device types and their address are stored on disk for printing hard copy. This takes the mystery out of the installation. The preparation of as-built drawings is fast and efficient.

Device mapping allows the Signature Data Controller to discover:

- Unexpected additional device addresses
- Missing device addresses
- Changes to the wiring in the circuit.

Most Signature modules use a personality code selected by the installer to determine their actual function. Personality codes are downloaded from the SDC during system configuration and are indicated during device mapping.

Standalone Operation – A decentralized alarm decision by the device is guaranteed. Onboard intelligence permits the device to operate in standalone (degrade) mode. If Signature loop controller CPU communications fail for more than four seconds, all devices on that circuit go into standalone mode. The circuit acts like a conventional alarm receiving circuit. Each Signature device on the circuit continues to collect and analyze information from its slave devices. When connected to a panel utilizing standalone operation, modules with their "personality" set as alarm devices (IDC) will alarm should their slave alarm-initiating device activate.

Life Safety & Communications

28 31 01

Isolator Module

SIGA-IM



S3424

7300-1657: 0121

MEA

Application Notes Available

Patented

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☑ Electrical
☐ Structural ☐ Other
☐ Mechanical

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Provide isolators approved for the location in which they are installed as per the electrical drawings.

Overview

The SIGA-IM Isolator Module is part of EST's Signature Series system. This intelligent device enables part of the Signature data loop to continue operating should a short circuit occur. The module can be wired into a Class A data loop at any point.

If a fault occurs, the isolator cuts power to all devices beyond the isolator on the loop as follows:

- a short on the line causes all isolators to open within 23 msec.
- at 10 msec intervals, beginning on one side of the Class A circuit nearest the loop controller, the isolators close to provide the next isolator down the line with power.
- when the isolator next to the short closes, it reopens within 10 msec.

Once activated, the line fault isolator continuously checks the faulted side of the loop to determine if the short still exists. When the fault is corrected and system reset, the module automatically restores the entire data loop to the normal condition.

The microprocessor in every Signature module provides at least three important benefits — Self-diagnostics and History Log, Automatic Device Mapping, and Fast, Stable Communication.

Self-diagnostics and History Log - Each Signature Series module constantly runs self-checks to provide important maintenance information. This information is automatically updated and permanently stored in the module's non-volatile memory and is accessible for review any time using the SIGA-PRO Signature Program / Service Tool.

Automatic Device Mapping - The Signature loop controller learns keeps a map where each device's serial number address is installed relative to other devices on the data circuit.

Fast Stable Communication - Built-in intelligence means less information needs to be sent between the module and the loop controller. Other than regular supervisory polling response, the module only needs to communicate with the loop controller when it has something new to report.

Standard Features

- **Automatic device mapping**
  Each module transmits wiring information to the loop controller regarding its location with respect to other devices on the circuit.
- **Electronic addressing**
  Addresses are downloaded and permanently stored from a PC, or the SIGA-PRO Signature Program / Service Tool. There are no switches or dials to set.
- **Ground fault detection by address**
  Detects ground faults right down to the device level.
- **2-gang mounting**
- **Designed to ISO 9001 standards**

Testing & Maintenance

The module's automatic self-diagnosis identifies when it is defective and causes a trouble message. The user-friendly maintenance program shows the current state of each module and other pertinent messages. Single modules may be turned off (deactivated) temporarily, from the control panel. Availability of maintenance features is dependent on the fire alarm system used. Scheduled maintenance (Regular or Selected) for proper system operation should be planned to meet the requirements of the Authority Having Jurisdiction (AHJ). Refer to current NFPA 72 and ULC CAN/ ULC 536 standards.

Warnings & Cautions
This module will not operate without electrical power. As fires frequently cause power interruption, we suggest you discuss further safeguardwith your fire protection specialist.

Typical Wiring and Installation

The SIGA-IM module mounts to North American 2-1/2 inch (64 mm) deep 2-gang boxes and 1-1/2 inch (38 mm) deep 4 inch square boxes with 2 gang covers and SIGA-MP mounting plates. The module will accept #18 AWG (0.75mm^2), #16 (1.0mm^2), #14 AWG (1.50mm^2), and #12 AWG (2.50mm^2) wire sizes. *Note: Sizes #16 AWG (1.0mm^2) and #18 AWG (0.75mm^2) are preferred for ease of installation. See Signature Loop Controller catalog sheet for detailed wiring requirement specifications.*

Edwards recommends that this module be installed according to latest recognized edition of national and local fire alarm codes.


Application

This module should only be used on Class A circuits. The operation of the SIGA-IM is determined by its hardware type code and is assigned at the factory. No user configuration is required.

Compatibility

These modules are part of EST's Signature Series intelligent processing and control platform. They are compatible with EST3, EST3X and iO Series control panels.

Typical Wiring



1. For maximum wire resistance, refer to the appropriate manufacturer's documentation.
2. Max. #12 AWG (2.5mm²)wire.
3. Refer to Signature Loop Controller Installation Sheet for wiring specifications.
4. This module should be used only with Class A wiring.
5. Maximum circuit resistance between isolators is 6 ohms.
6. All wiring is power-limited and supervised.

Specifications

Description	Isolator Module - factory set hardware type code
Address Requirements	Uses One Detector Address
Circuit Resistance	Six ohms maximum between isolators
Operating Current	Standby = 45µA; Activated = 45µA
Operating Voltage	15.2 to 19.95 Vdc (19 Vdc nominal)
Construction & Finish	High Impact Engineering Polymer 2-gang front plate - White Finish
Storage Environment	Temperature: -4°F to 140°F (-20°C to 60°C)
Operating Environment	Temperature: 32°F to 120°F (0°C to 49°C); Humidity: 0 to 93% RH
LED Operation	On-board Green LED - Flashes when polled (normal)
Compatibility	Use with: Signature Loop Controller
Agency Listings	UL, ULC, CSFM, MEA, FM

Ordering Information 28 31 01

Catalog Number	Description	Ship Wt. lb (kg)
★ SIGA-IM	Fault Isolator Module - UL/ULC Listed	.5 (.23)
Accessories		
27193-21	Surface Mount Box - 2-gang RED	1 (.4)
27193-26	Surface Mount Box - 2-gang WHITE	
MFC-A	Multifunction Fire Cabinet - Red, supports Signature Module Mounting Plates	7.0 (3.1)
SIGA-MP1	Signature Module Mounting Plate, 1 footprint	1.5 (0.70)
SIGA-MP2	Signature Module Mounting Plate, 1/2 footprint	0.5 (0.23)
SIGA-MP2L	Signature Module Mounting Plate, 1/2 extended footprint	1.02 (0.46)

Contact us...

Email: edwards.fire@fs.utc.com
Web: *www.est-fire.com*

EST is an **EDWARDS** brand.

1016 Corporate Park Drive
Mebane, NC 27302

In Canada, contact Chubb Edwards...
Email: inquiries@chubbedwards.com
Web: *www.chubbedwards.com*

© 2013 UTC Fire & Security Americas Corporation, Inc. All rights reserved. Specifications subject to change without notice. Edwards is part of UTC Climate, Controls & Security, a unit of United Technologies Corporation.

28 31 01

Manual Pull Stations

SIGA-270, SIGA-270P, SIGA-278



SIGA-270 SERIES

MEA

Patented

STANTEC PROJECT #: 110126045 SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:
☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☐ REVIEWED
☑ REVIEWED, AS NOTED
☐ REVISE AND RESUBMIT
☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Provide pull stations approved for the location in which they are installed as per the electrical drawings.

Overview

The SIGA-270 and SIGA-278 series Manual Pull Stations are part of EST's Signature Series system. The SIGA-270 Fire Alarm Manual Pull Stations feature our very familiar teardrop shape. They are made from die-cast zinc and finished with red epoxy powder-coat paint complemented by aluminum colored stripes and markings. With positive pull-lever operation, one pull on the station handle breaks the glass rod and turns in a positive alarm, ensuring protection plus fool-proof operation. Presignal models (SIGA-270P) are equipped with a general alarm (GA) keyswitch for applications where two stage operation is required. The up-front highly visible glass rod discourages tampering, but is not required for proper operation.

EST's double action single stage SIGA-278 station is a contemporary style manual station made from durable red colored lexan. To initiate an alarm, first lift the upper door marked "LIFT THEN PULL HANDLE", then pull the alarm handle.

Standard Features

Note: *Some features described here may not be supported by all control systems. Check your control panel's Installation and Operation Guide for details.*

- **Traditional familiar appearance**
  SIGA-270 models feature our familiar teardrop design with simple positive pull action and sturdy die-cast metal body.
- **One stage (GA), two stage (pre-signal), and double action models**
  SIGA-270 models are available for one or two stage alarm systems. The single stage double action SIGA-278 features a rugged Lexan housing with keyed reset mechanism.
- **Break glass operation**
  An up-front visible glass rod on the SIGA-270 discourages tampering.
- **Intelligent device with integral microprocessor**
  All decisions are made at the station allowing lower communication speed while substantially improving control panel response time. Less sensitive to line noise and loop wiring properties; twisted or shielded wire is not required.
- **ADA Compliant**
  Meets ADA requirements for manual pull stations.
- **Electronic Addressing with Non-volatile memory**
  Permanently stores programmable address, serial number, type of device, and job number. Automatically updates historic information including hours of operation, last maintenance date, number of alarms and troubles, and time and date of last alarm.
- **Automatic device mapping**
  Each station transmits wiring information to the loop controller regarding its location with respect to other devices on the circuit.
- **Stand-alone operation**
  The station inputs an alarm even if the loop controller's polling interrogation stops.
- **Diagnostic LEDs**
  Status LEDs; flashing GREEN shows normal polling; flashing RED shows alarm state.
- **Designed for high ambient temperature operation**
  Install in ambient temperatures up to 120 °F (49 °C).

Application

The operating characteristics of the fire alarm stations are determined by their sub-type code or “Personality Code”. NORMALLY-OPEN ALARM - LATCHING (Pesonality Code 1**)** is assigned by the factory; no user configuration is required. The device is configured for Class B IDC operation. An ALARM signal is sent to the loop controller when the station’s pull lever is operated. The alarm condition is latched at the station.

Compatibility

Signature Series manual stations are compatible only with EST’s Signature Loop Controller.

Warnings & Cautions

This device will not operate without electrical power. As fires frequently cause power interruption, we suggest you discuss further safeguards with your local fire protection specialist.

Testing & Maintenance

To test (or reset) the station simply open the station and operate the exposed switch. The SIGA-270 series are opened with a tool; the SIGA-278 requires the key which is supplied with that station.

The station’s automatic self-diagnosis identifies when it is defective and causes a trouble message. The user-friendly maintenance program shows the current state of each Signature series device and other pertinent messages. Single devices may be deactivated temporarily, from the control panel. Availability of maintenance features is dependent on the fire alarm system used.

Scheduled maintenance (Regular or Selected) for proper system operation should be planned to meet the requirements of the Authority Having Jurisdiction (AHJ). Refer to current NFPA 72 and ULC CAN/ULC 536 standards.

Typical Wiring

28 31 01

The fire alarm station’s terminal block accepts #18 AWG (0.75mm^2) to #12 AWG (2.5mm^2) wire sizes. See Signature Loop Controller catalog sheet for detailed wiring requirement specifications.

Wiring Notes

1. Refer to Signature Loop Controller manual for maximum wire distance.
2. All wiring is power limited and supervised.




Figure 4. Single Stage Systems




Figure 5. Two Stage Systems

Single-stage Signature Series fire alarm manual pull stations mount to North American 2½ inch (64 mm) deep 1-gang boxes.

Two stage presignal (270P) models require 1½ inch (38 mm) deep 4-inch square boxes with 1-gang, ½-inch raised covers. Openings must be angular. *Rounded openings are not acceptable.* Recommended box: Steel City Model 52-C-13; in Canada, use Iberville Model CI-52-C-49-1/2.

All models include terminals are suited for #12 to #18 AWG (2.5 mm^2 to 0.75 mm^2) wire size. Edwards recommends that these fire alarm stations be installed according to latest recognized edition of national and local fire alarm codes.

Electronic Addressing: The loop controller electronically addresses each manual station, saving valuable time during system commissioning. Setting complicated switches or dials is not required. Each station has its own unique serial number stored in its on-board memory. The loop controller identifies each device on the loop and assigns a "soft" address to each serial number. If desired, the stations can be addressed using the SIGA-PRO Signature Program/Service Tool.




Figure 1. SIGA-278 installation




Figure 2. SIGA-270, SIGC-270F, SIGC-270B installation




Figure 3. SIGA-270P, SIGC-270PB installation

EDWARDS
A UTC Fire & Security Company

Detection & alarm since 1872

U.S.
T 888-378-2329
F 866-503-3996

Canada
Chubb-Edwards
T 519 376 2430
F 519 376 7258

Southeast Asia
T : +65 6391 9300
F : +65 6391 9306

India
T : +91 80 4344 2000
F : +91 80 4344 2050

Australia
T +61 3 9239 1200
F +61 3 9239 1299

Europe
T +32 2 725 11 20
F +32 2 721 86 13

Latin America
T 305 593 4301
F 305 593 4300

utcfireandsecurity.com

© 2010 UTC Fire & Security.
All rights reserved.

Specifications

Catalog Number	SIGA-270, SIGC-270F, SIGC-270B	SIGA-270P, SIGC-270PB	SIGA-278
Description	Single Action - One Stage	Single Action -Two Stage (Presignal)	Double Action - One Stage
Addressing Requirements	Uses 1 Module Address	Uses 2 Module Addresses	Uses 1 Module Address
Operating Current	Standby = 250µA Activated = 400µA	Standby = 396µA Activated = 680µA	Standby = 250µA Activated = 400µA
Construction & Finish	Diecast Zinc - Red Epoxy with aluminum markings		Lexan - Red with white markings
Type Code	Factory Set		
Operating Voltage	15.2 to 19.95 Vdc (19 Vdc nominal)		
Storage and Operating Environment	Operating Temperature: 32ºF to 120ºF (0ºC to 49ºC) Storage Temperature: -4ºF to 140ºF (-20ºC to 60ºC) Humidity: 0 to 93% RH		
LED Operation	On-board Green LED - Flashes when polled On-board Red LED - Flashes w hen in alarm Both LEDs - Glow steady when in alarm (stand-alone)		
Compatibility	Use With: Signature Loop Controller		
Agency Listings	UL, ULC (note 1), MEA, CSFM		

Note: *SIGC-270F, SIGC-270B and SIGC-270PB are ULC listed only. Suffix "F" indicates French markings. Suffix "B" indicates English/French biling ual markings.*

Ordering Information

	Catalog Number	Description	Ship Wt. lbs (kg)
★	SIGA-270	One Stage Fire Alarm Station, English Markings - UL/ULC Listed	1 (0.5)
	SIGC-270F	One Stage Fire Alarm Station, French Markings - ULC Listed	
	SIGC-270B	One Stage Fire Alarm Station, French/English Markings - ULC Listed	
	SIGA-270P	Two Stage (Presignal) Fire Alarm Station, English Markings - UL/ULC Listed	
	SIGC-270PB	Two Stage (Presignal) Fire Alarm Station, French/English Markings - ULC Listed	
	SIGA-278	Double Action (One Stage) Fire Alarm Station, English Markings - UL/ULC Listed	

Accessories		
32997	GA Key w/Tag - for pre-signal station (CANADA ONLY)	0.1 (.05)
276-K2	GA Key - for pre-signal station (USA ONLY)	
276-K1	Station Reset Key, Supplied with all Key Reset Stations	
27165	12 Glass Rods - for SIGA-270 series (CANADA ONLY)	
270-GLR	20 Glass Rods - for SIGA-270 series (USA ONLY)	
276-GLR	20 Glass Rods - for SIGA-278 series	
276B-RSB	Surface Mount Box, Red - for SIGA pull stations	1 (0.6)

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☐ Structural ☐ Mechanical ☑ Electrical ☐ Other

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED 28 31 01

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED


DATE June 20, 2018

BY Chester Martinez, E.I.T.

EST™ Life Safety & Communications

Field Configurable Horns and Strobes

Genesis Series



ECS/MNS appliances available with clear or amber lenses.



Overview

The Genesis line of fire alarm and mass notification/emergency communications (ECS/MNS) signals are among the smallest, most compact audible-visible life safety signaling devices in the world. About the size of a deck of playing cards, these devices are designed to blend with any decor.

Thanks to patented breakthrough technology, Edwards Genesis strobes do not require bulky specular reflectors and lenses. Instead, an exclusive cavity design conditions light to produce a highly controlled distribution pattern. Significant development efforts employing this new technology have given rise to a new benchmark in strobe performance – FullLight technology.

FullLight strobe technology produces a smooth light distribution pattern without the spikes and voids characteristic of specular reflectors. This ensures the entire coverage area receives consistent illumination from the strobe flash. As a result, Genesis strobes with FullLight technology go well beyond the UL-1971 and ULC-S526 light distribution requirements.

Genesis strobes and horn-strobes offer selectable candela output by means of a conveniently-located switch on the side of the device. Models are also available that offer fixed 15/75 cd output. The candela output setting remains clearly visible even after final installation, yet it stays locked in place to prevent unauthorized tampering.

Genesis ECS/MNS appliances offer emergency signaling with clear or amber lenses and with optional ALERT housing labels. They are ideal for applications that require differentiation between fire alarm and mass notification alerts.

Standard Features

- **Unique low-profile design**
  - The most compact UL-1971/ULC-S526 listed strobe available
  - Ultra-slim – protrudes less than one inch
  - Attractive appearance
  - No visible mounting screws
- **Four field-configurable options in one device**
  - Select 15, 30, 75, or 110 cd strobe output
  - Select high (default) or low dB horn output
  - Select temporal (default) or steady horn output
  - Select public mode flash rate (default) or private mode temporal flash
- **Fixed 15/75 cd model available**
- **ECS/MNS models available**
- **Easy to install**
  - Fits standard 1-gang electrical boxes – no trim plate needed
  - Optional trim plate accommodates oversized openings
  - Pre-assembled with captive hardware
  - #12 AWG terminals – ideal for long runs or existing wiring
- **Unparalleled performance**
  - Industry's most even light distribution
  - Meets tough synchronizing standards for strobes
  - Single microprocessor controls both horn and strobe
  - Independent horn control over a single pair of wires
  - Highly regulated in-rush current
  - Multiple frequency tone improves sound penetration
  - Field-programmable temporal strobe output option

Application

Genesis strobes are UL 1971-listed for use indoors as wall-mounted public-mode notification appliances for the hearing impaired. Prevailing codes require strobes to be used where ambient noise conditions exceed 105 dBA (87dBA in Canada), where occupants use hearing protection, and in areas of public accommodation as defined in the *Americans with Disabilities Act (see application notes – USA)*.

Combination horn-strobe signals must be installed in accordance with guidelines established for strobe devices. Consult with your Authority Having Jurisdiction for details.

All Genesis strobes exceed UL synchronization requirements (within 10 milliseconds over a two-hour period) when used with a synchronization source. Synchronization is important in order to avoid epileptic sensitivity.

WARNING: These devices will not operate without electrical power. As fires frequently cause power interruptions, further safeguards such as backup power supplies may be required.

Horns

Genesis horn output reaches as high as 99 dB and features a unique multiple frequency tone that results in excellent sound penetration and an unmistakable warning of danger. Horns may be configured for either coded or non-coded signal circuits. They can also be set for low dB output with a jumper cut that reduces horn output by about 5 dB. Horn-only models may be ceiling-mounted or wall-mounted.

The suggested sound pressure level for each signaling zone used with alarm signals is at least 15 dB above the average ambient sound level, or 5 dB above the maximum sound level having a duration of at least 60 seconds, whichever is greater, measured 5 feet (1.5 m) above the floor. The average ambient sound level is, A-weighted sound pressure measured over a 24-hour period.

Doubling the distance from the signal to the ear will theoretically result in a 6 dB reduction of the received sound pressure level. The actual effect depends on the acoustic properties of materials in the space. A 3 dBA difference represents a barely noticeable change in volume.

ECS/MNS Applications

Genesis ECS/MNS strobe appliances bring the same high-performance fire alarm features and unobtrusive design to mass notification applications. Available with amber lenses and optional ALERT housing labels, they are ideal for applications that require differentiation between fire alarm and mass notification alerts.

Installation

Genesis horns and strobes mount to any standard one-gang surface or flush electrical box. Matching optional trim plates are used to cover oversized openings and can accommodate one-gang, two-gang, four-inch square, or octagonal boxes, and European 100 mm square.



Genesis Horn/Strobe with optional trim plate

All Genesis signals come pre-assembled with captive mounting screws for easy installation. Two tabs at the top of the signal unlock the cover to reveal the mounting hardware. The shallow depth of Genesis devices leaves ample room behind the signal for extra wiring. Once installed with the cover in place, no mounting screws are visible.

Field Configuration

Temporal horn and horn-strobe models are factory set to sound in a **three-pulse temporal pattern**. Units may be configured for use with coded systems by cutting a jumper on the circuit board. This results in a **steady output** that can be turned on and off (coded) as the system applies and removes power to the signal circuit. A Genesis Signal Master is required when horn-strobe models are configured for coded systems. Non-temporal, horn-only models sound a steady tone.


Genesis clear strobes and horn-strobes are shipped from the factory ready for use as **UL 1971 compliant** signals for public mode operation. These signals may be configured for **temporal flash** by cutting a jumper on the circuit board. This battery-saving feature is intended for private mode signaling only.

Genesis clear strobes and horn-strobes may be set for **15, 30, 75, or 110 candela output**. The output setting is changed by simply opening the device and sliding the switch to the desired setting. The device does not have to be removed to change the output setting. The setting remains visible through a small window on the side of the device after the cover is closed.

Horns and horn-strobes are factory set for **high dB output**. **Low dB output** may be selected by cutting a jumper on the circuit board. This reduces the output by about 5 dB.

Wiring

Field wiring terminals accommodate #18 to #12 AWG (0.75 mm² to 2.5 mm²) wiring. Horns, strobes, and combination horn-strobes are interconnected with a single pair of wires as shown below.



Note: Strobes must have continuous voltage.

Current Draw

28 31 01

Strobes, Horn-Strobes

Multi-cd Wall Strobes (G1-VM)

UL Rating	15 cd* RMS	30 cd* RMS	15/75 cd** RMS	75 cd* RMS	110 cd* RMS
16 Vdc	103	141	152	255	311
16 Vfwr	125	179	224	346	392

*G1-VM multi-cd; **G1F-V1575 fixed 15/75 cd

Typical Current	15 cd RMS	30 cd RMS	15/75 RMS	75 cd RMS	110 cd RMS
16 Vdc	85	127	150	245	285
20 Vdc	71	98	123	188	240
24 Vdc	59	82	104	152	191
33 Vdc	46	64	84	112	137
16 Vfwr	119	169	223	332	376
20 Vfwr	103	143	189	253	331
24 Vfwr	94	129	169	218	262
33 Vfwr	87	112	148	179	205

Wall Temporal Horn-strobes – High dB Setting

UL Rating	15 cd* RMS	30 cd* RMS	15/75 cd** RMS	75 cd* RMS	110 cd* RMS
16 Vdc	129	167	172	281	337
16 Vfwr	176	230	269	397	443

*G1-HDVM multi-cd
**G1F-HDV1575 fixed 15/75 cd

Typical Current	15 cd RMS	30 cd RMS	15/75 RMS	75 cd RMS	110 cd RMS
16 Vdc	102	135	160	246	309
20 Vdc	88	109	137	193	248
24 Vdc	81	94	122	161	203
33 Vdc	74	72	106	124	154
16 Vfwr	144	182	247	352	393
20 Vfwr	141	162	220	274	362
24 Vfwr	136	152	203	235	282
33 Vfwr	125	144	196	201	232

Wall Temporal Horn-strobes – Low dB Setting

UL Rating	15 cd* RMS	30 cd* RMS	15/75 cd** RMS	75 cd* RMS	110 cd* RMS
16 Vdc	122	160	146	274	330
16 Vfwr	162	216	231	383	429

*G1-HDVM multi-cd
**G1F-HDV1575 fixed 15/75 cd

Typical Current	15 cd RMS	30 cd RMS	15/75 RMS	75 cd RMS	110 cd RMS
16 Vdc	96	130	158	243	302
20 Vdc	79	104	133	189	241
24 Vdc	68	88	119	156	197
33 Vdc	56	71	100	118	146
16 Vfwr	128	180	241	344	389
20 Vfwr	118	157	213	266	343
24 Vfwr	113	144	195	230	279
33 Vfwr	112	137	182	197	226

Horns

Wall or Ceiling Mounted Temporal Horns (G1-HD)

UL Rating	High dB (RMS)	Low dB (RMS)
16 Vdc	26	19
24 Vdc	36	27
33 Vdc	41	33
16 Vfwr	51	37
24 Vfwr	69	52
33 Vfwr	76	70

Typical Current	High dB RMS	Low dB RMS
16 Vdc	22	17
20 Vdc	24	19
24 Vdc	27	22
33 Vdc	32	26
16 Vfwr	34	30
20 Vfwr	40	34
24 Vfwr	45	38
33 Vfwr	52	47

Wall or Ceiling Mounted Horns (G1-P)

UL Designation	Voltage Range	Max. Current, RMS
Regulated 24 Vdc	16 - 33 Vdc	13 mA
24 fwr	16 - 33 Vfwr	11 mA

Typical Current	RMS
24 Vdc	10
24 Vdc	11
31 Vdc	12
20 Vfwr	9
24 Vfwr	10

Current values are shown in mA.

dBA output

Temporal Horns, Horn-strobes (G1-HD, G1-HDVM series)

High dB Setting	UL464		Average	Peak
	Temporal	Steady	Temporal/ Steady	Temporal/ Steady
16 Vdc	81.4	85.5	91.4	94.2
24 Vdc	84.4	88.6	94.5	97.6
33 Vdc	86.3	90.4	96.9	99.5

Low dB Setting	UL464		Average	Peak
	Temporal	Steady	Temporal/ Steady	Temporal/ Steady
16 Vdc	76.0	80.1	86.3	89.2
24 Vdc	79.4	83.5	89.8	92.5
33 Vdc	82.1	86.5	92.5	95.3

Steady Tone Horns (G1-P series)


	UL464	Average	Peak
16 Vdc	77 dBA, min	85 dBA	91 dBA
16 Vfwr	77 dBA, min	85 dBA	91 dBA

Notes

1. All values shown are dBA measured at 10 feet (3.01m).
2. UL464 values measured in reverberant room.
3. Average and Peak values are measured in anechoic chamber.


Average Sound Output (dBA)

(High dB setting, anechoic, 24V, measured at 10ft)



Light output - (effective cd)

Percent of UL rating versus angle



Specifications

Housing	Red or white textured UV stabilized, color impregnated engineered plastic. Exceeds 94V-0 UL flammability rating.
Lens	Optical grade polycarbonate (clear)
Mounting (indoor only)	Strobes and horn-strobes are for wall-mount installation only. Horn-only models may be ceiling- or wall-mounted. Flush mount: 2½ inch (64 mm) deep one-gang box Surface mount: Model 27193 surface mount box, wiremold box, or equivalent surface-mount box With optional trim plate: One-gang, two-gang, four-inch square, octagonal, or European single-gang box
Wire connections	Screw terminals: single input for both horn and strobe. #18 to #12 AWG (0.75 mm^2 to 2.5 mm^2) wire size
Operating environment	Indoor only: 32-120°F (0-49°C) ambient temperature. 93% relative humidity
Agency listings/approvals	UL 1971, UL 1638, UL 464, ULC S525, ULC S526, CSFM, CE, FCC, MEA. (All models comply with ADA Code of Federal Regulation Chapter 28 Part 36 Final Rule.)
Dimensions (HxWxD)	Signal: 4-1/2" x 2-3/4" x 13/16" (113 mm x 68 mm x 21 mm) Trimplate: 5" (127 mm); Height – 5-7/8" (149 mm); Depth – ½" (13 mm)
Operating voltage	G1-HD series temporal-tone horns: non-coded, filtered 16-33 Vdc or unfiltered 16-33 Vdc FWR (or coded when horn set to steady tone) G1-HDVM series temporal-tone horn-strobes: non-coded, filtered 16-33 Vdc or unfiltered 16-33 Vdc FWR (or coded (audible NAC only) when used with optional G1M Genesis Signal Master) G1-VM series strobes: non-coded, filtered 16 - 33 Vdc or unfiltered 16-33 Vdc FWR G1-P series steady-tone horns: coded or non-coded, filtered 20-31 Vdc or unfiltered 20-27 Vfwr
Strobe output rating	UL 1971, UL 1638, ULC S526: selectable 15 cd, 30 cd, 75 cd, or 110 cd output UL 1971: 15 cd (fixed 15/75 cd models) UL 1638, ULCS526: 75 cd (fixed 15/75 cd models)
Strobe flash rate	G1-VM strobes and G1-HDVM series temporal-tone horn-strobes: one flash per second synchronized with optional G1M Genesis Signal Master indefinitely within 10 milliseconds. Temporal setting (private mode only): synchronized to temporal output of horns on same circuit
Synchronization Sources	SIGA-CC1S, SIGA-MCC1S, SIGA-CC2A, SIGA-MCC2A, G1M-RM BPS6A, BPS10A, APS6A, APS10A, iO64, iO500, Fireshield Plus 3, 5 and 10 zone. Add G1M for G1-CVM &G1-HDVM devices only.
Horn pulse rate	G1-HD temporal-tone horns and G1-HDVM series temporal-tone horn-strobes: temporal rate synchronized with optional G1M Genesis Signal Master indefinitely within 10 milliseconds. G1-P steady-tone horns: continuous, steady tone only
Temporal audible pattern	½ sec ON, ½ sec OFF, ½ sec ON, ½ sec OFF, ½ sec ON, 1½ sec OFF, then repeat cycle

Candela Output

Lens Color	Rating	Switch Position A	Switch Position B	Switch Position C	Switch Position D
Amber	UL 1638	110 cd	75 cd	30 cd	15 cd
Amber	UL 1971*	88 cd	60 cd	24 cd	12 cd
Clear	UL 1971	110 cd	75 cd	30 cd	15 cd

** Equivalent Rating*

Fire appliances available with white or red housings.



ECS/MNS appliances available with clear or amber lenses.



Ordering Information

Model	Housing	Marking	Lens	Strobe	Horn	Ship Wt. lbs (kg)
Fire Alarm Appliances (c/w running man icon screen printed on housing)						
G1-VM	White	None	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
G1F-HD	White	FIRE	Clear	Horn only	Selectable high/low dB	0.25 (0.11)
G1F-HDV1575	White	FIRE	Clear	15/75 cd[1]	Temporal hi/lo dB-24V	0.25 (0.11)
G1F-HDVM	White	FIRE	Clear	Selectable 15, 30, 75, or 110 cd	Selectable high/low dB	0.25 (0.11)
G1F-P	White	FIRE	Clear	Steady Horn (not compatible with Genesis Signal Master)		0.25 (0.11)
G1F-V1575	White	FIRE	Clear	15/75 cd[1]	Strobe only	0.25 (0.11)
G1F-VM	White	FIRE	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
G1-HD	White	None	Clear	Horn only	Selectable high/low dB	0.25 (0.11)
G1-HDVM	White	None	Clear	Selectable 15, 30, 75, or 110 cd	Selectable high/low dB	0.25 (0.11)
G1-P	White	None	Clear	Steady Horn (not compatible with Genesis Signal Master)		0.25 (0.11)
G1RF-HD	Red	FIRE	Clear	Horn only	Selectable high/low dB	0.25 (0.11)
G1RF-HDV1575	Red	FIRE	Clear	15/75 cd[1]	Temporal hi/lo dB-24V	0.25 (0.11)
★ G1RF-HDVM	Red	FIRE	Clear	Selectable 15, 30, 75, or 110 cd	Selectable high/low dB	0.25 (0.11)
G1RF-P	Red	FIRE	Clear	Steady Horn (not compatible with Genesis Signal Master)		0.25 (0.11)
G1RF-V1575	Red	FIRE	Clear	15/75 cd[1]	Strobe only	0.25 (0.11)
G1RF-VM	Red	FIRE	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
G1R-HD	Red	None	Clear	Horn only	Selectable high/low dB	0.25 (0.11)
G1R-HDVM	Red	None	Clear	Selectable 15, 30, 75, or 110 cd	Selectable high/low dB	0.25 (0.11)
G1R-P	Red	None	Clear	Steady Horn (not compatible with Genesis Signal Master)		0.25 (0.11)
G1R-VM	Red	None	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
ECS/MNS Appliances (no running man icon on housing)						
G1WA-VMA	White	ALERT	Amber	Selectable A, B, C or D	Strobe only	0.25 (0.11)
G1WA-VMC	White	ALERT	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
G1WN-VMA	White	None	Amber	Selectable A, B, C or D	Strobe only	0.25 (0.11)
G1WN-VMC	White	None	Clear	Selectable 15, 30, 75, or 110 cd	Strobe only	0.25 (0.11)
Trim Plates						
G1T	White	None	Genesis Trim Plate (for two-gang or 4" square boxes)			0.15 (0.7)
G1RT	Red	None	Genesis Trim Plate (for two-gang or 4" square boxes)			0.15 (0.7)
G1T-FIRE	White	FIRE	Genesis Trim Plate (for two-gang or 4" square boxes)			0.15 (0.7)
G1RT-FIRE	Red	FIRE	Genesis Trim Plate (for two-gang or 4" square boxes)			0.15 (0.7)
G1WT-ALERT	White	ALERT	Genesis Trim Plate (for two-gang or 4" square boxes)			0.15 (0.7)
Surface Boxes						
27193-16	White	N/A	One-gang surface mount box			1 (0.4)
27193-11	Red	N/A	One-gang surface mount box			1 (0.4)

[1] These 15/75 cd models provide fixed output and are not multi-candela devices. The 15 cd output component complies with UL1971, while the 75 cd output component complies with UL 1638.

28 31 01

EDWARDS
A UTC Fire & Security Company

Detection & alarm since 1872

U.S.
T 888 378 2329
F 866 503 3996

Canada
Chubb Edwards
T 519 376 2430
F 519 376 7258

Southeast Asia
T : +65 6391 9300
F : +65 6391 9306

India
T : +91 80 4344 2000
F : +91 80 4344 2050

Australia
T +61 3 9239 1200
F +61 3 9239 1299

Europe
T +32 2 725 11 20
F +32 2 721 86 13

Latin America
T 305 593 4301
F 305 593 4300

utcfireandsecurity.com

© 2010 UTC Fire & Security.
All rights reserved.

EST Life Safety & Communications

28 31 01

Sealed Lead-Acid Batteries



Overview

Rechargeable sealed lead-acid batteries are ideal for use as a secondary (standby) power source as defined by ULC requirements for ULC listed fire alarm control panels. Their low maintenance and high energy density make them ideal for fire alarm signaling applications.

Standard Features

- Rechargeable
- Non-spillable
- Non-hazardous
- Low maintenance
- High energy density

Application

When multiple power supplies are provided, each power supply's battery requirements should be calculated individually. Consult the specific system manual to determine battery capacity requirements.

Safety Information

Due to a battery's low internal resistance and high power density, high levels of short circuit current can develop across battery terminals. Put on protective eye covering and remove all jewelry before working on batteries. Do not rest tools or cables on the battery, and only use insulated tools. Follow all manufacturers installation instructions and diagrams when installing or maintaining batteries.

STANTEC PROJECT #: 110126045

SUBMITTAL # ELE-002 Fire Alarm Systems

This review by Stantec is for general conformance with the design concept of Stantec's design of the:

☐ Architectural ☑ Electrical
☐ Structural ☐ Other
☐ Mechanical

component(s) only and does not mean that Stantec has verified or approves the shop drawing(s). The Contractor remains solely responsible for the shop drawing(s) and this review by Stantec does not relieve the Contractor of the Contractor's responsibility for errors or omissions in the shop drawing(s) or for meeting all requirements of the contract documents. This review does not mean that Stantec approves the detailed design inherent in the shop drawing, responsibility for which shall remain with the Contractor submitting same, nor does this review mean that Stantec accepts any deviation of the shop drawing(s) from the contract documents. The Contractor is responsible for confirming all dimensions and correlating them at the job site, for all construction means, methods and techniques, and for coordination of construction work of all trades, including coordination of all shop drawings.

Stantec

☑ REVIEWED

☐ REVIEWED, AS NOTED

☐ REVISE AND RESUBMIT

☐ NOT REVIEWED

DATE June 20, 2018

BY Chester Martinez, E.I.T.

Contact us...
Email: edwards.fire@fs.utc.com
Web: *www.est-fire.com*

EST is an **EDWARDS** brand.

1016 Corporate Park Drive
Mebane, NC 27302

In Canada, contact Chubb Edwards...
Email: inquiries@chubbedwards.com
Web: *www.chubbedwards.com*

© 2015 UTC Fire & Security Americas Corporation, Inc. All rights reserved. Specifications subject to change without notice. Edwards is part of UTC Climate, Controls & Security, a unit of United Technologies Corporation.

28 31 01

Specifications

Case material	ABS thermoplastic
Regulatory information	DOT Class 60, batteries, non-hazardous, non-spillable
Operating environment	32° F to 120° F (0° C to 49° C) 0 to 93% RH, non-condensing

Ordering Information

Catalogue Number	Description	Dimensions (mm)	Shipping weight (kg)
12V4A5	4.5 AH sealed lead acid battery - 12Vdc	4.21" h x 2.76" w x 3.54" L (107 x 70 x 90)	3.26lbs (1.48kg)
12V7A2	7.2 AH sealed lead acid battery - 12Vdc	4" h x 2.6" w x 6.0" L (102 x 66 x 152)	4.85lbs (2.2kg)
★ 12V10A5	10.5 AH sealed lead acid battery - 12Vdc	4.8" h x 2.6" w x 6" L (122 x 66 x 152)	7.05lbs (3.2kg)
12V13A	13 AH sealed lead acid battery - 12Vdc	6.5" h x 3.15" w x 5.28" L (166 x 80 x 135)	10.2lbs (4.62kg)
12V18A	18 AH sealed lead acid battery - 12Vdc	6.6" h x 3.0" w x 7.1" L (168 x 76 x 180)	11.73lbs (5.32kg)
12V26A	26 AH sealed lead acid battery - 12Vdc	7.17" h x 4.92" w x 6.5" L (182 x 125 x 165)	19.8lbs (9.0kg)
12V35A	35 AH sealed lead acid battery - 12Vdc	6.26" h x 5.16" w x 7.76" L (159 x 131 x 197)	24.3lbs (10.9kg)
12V40A	40 AH sealed lead acid battery - 12Vdc	6.69" h x 6.5" w x 7.76" L (170 x 165 x 197)	29.1lbs (13.2kg)
12V50A	50 AH sealed lead acid battery - 12Vdc	7.87" h x 5.19" w x 10.11" L (200 x 132 x 257)	35.3lbs (16kg)
12V65A	65 AH sealed lead acid battery - 12Vdc	7.01" h x 6.57" w x 13.70" L (178 x 167 x 348)	42.3lbs (19.2kg)

APPENDIX E

SPARE PART LIST

Item	Equipment	Spare part name	Quantity
1	Light fixture	LED driver for each type of luminaire	1
2	Light fixture	LED luminaire fixture type complete with driver	1
3	Motor starters	Spare fusesof each type and size used	3
4	Motor starters	Set of each type of adjustable thermal overload devices	1
5	Motor starters	Coil of each starter size	1
6	Motor starters	Control transformers	2
7	Motor starters	time delay device for each type used	1
8	Generator	Oil filter	6
9	Generator	Fuel filter	6
10	Generator	Air filter	6
11	Generator	Fuses of each type used in control panel	2
12	Generator	Accessory belts of each type used	2
13	Generator	Special tools used for servicing the unit	1
Provide additional spare arts recommended by the manufacturer of systems other than listed herein before			

Instrumentation and Controls Equipment Spare Parts (110126045)

Item	Equipment	Spare Parts Name	Qty. (sets)	Specification Section	Suppliers/Manufactors
1	Control Panel Equipment	Alarm Dialer Protalk Plus	1	47 10 01	Barnett Engineering Ltd.
		Ethernet Cables (2m)	4	47 10 02	
		Fuses	20 (each size and type used)	47 30 02	
		Indicating Lights	2 (each colour and type used)	47 30 02	
		Fuse Holders	2 (each type used)	47 30 02	
		Push Button	1 (each type used)	47 30 02	
		Selector Switch	1 (each type used)	47 30 02	
		I/O Cards	N/A	47 30 02	Rockwell Automation
2	Level Bulbs	N/A	-	47 30 03	ENM-10 Level Regulator
3	Level Switches	N/A	-	47 30 03	
4	Ultrasonic Level Transmitter/Transducer	N/A	-	47 30 03	Veolia (Mectron)/Napier-Reid
5	Strobes and Horns	N/A	-	47 30 03	AST Applied Strobe Technology; Rockwell
6	Ambinet Temperture Transmitters	N/A	-	47 30 03	Thermo Kinetics Measurement & Control
7	Ambient H2S Gas Detection	N/A	-	47 30 03	Contro-Valve
8	Magnetic Flow Meter	N/A	-	47 30 03	Endress + Hauser
9	Mass Flow Meter	N/A	-	47 30 03	
10	Dissolved Oxygen Analyzer	N/A	-	47 30 03	
11	CH4 Gas Detection	N/A	-	47 30 03	
12	Pressure Switches	N/A	-	47 30 03	
13	SCADA Equipment	SCADA Printer Toner Cartridge	-	47 30 03	

CONTRO VALVE

Contro Valve Equipment inc. / Les Équipements Contro Valve inc.
Brandon, MB • Brossard, QC • Burlington, ON • Fredericton, NB • Halifax, NS Québec, QC • Sarnia, ON • St. John's, NL • Sudbury, ON •Thunder Bay, ON • Vancouver, BC

Intertek

Soumission :	**19HA1029-1**
Date (aaaa/mm/jj)	**2019/11/05**

S'il vous plaît se référer à ce numéro lors de la commande
www.controvalve.com

À l'attention :	Hugo Chartier
Compagnie :	Norclair Inc.
Adresse :	3065 peugeot bureau 101 Laval QC Canada H7L 5C4
Référence :	IQA15-4964-C Iqaluit WWTP
Téléphone :	(450) 688-4012 ,706
Courriel :	hchartier@norclair.ca

Créer par :	Hugues Almeida
Courriel :	halmeida@controvalve.com
Adresse :	9610 B Ignace Brossard QC Canada, J4Y 2R4
Représentant :	Marc-André Ouellette & Hugues Joannis
Téléphone :	450-444-5858

Suite à votre demande, il nous fait plaisir de vous faire parvenir la présente soumission.

** Les commandes placées avant la date d'expiration seront facturées au prix soumissionné*

** Taxes sur la vente, frais de douanes ou tout autres frais ne sont pas inclus dans cette soumission*

** Prière de nous faire parvenir votre bon de commande ainsi que notre # de soumission comme référence au BrossardPO@controvalve.com*

LIVRAISON	VALIDE POUR	EX WORKS	TERMES
4-5 Sem.	30 Jours	Brossard, QC	Net 30
		** Collect*	** Sujet à l'approbation de crédit*

Sous réserve de vente

En espérant que cette soumission réponde à tous vos besoins. N'hésitez pas à nous contacter pour toutes autres demandes d'informations.Merci pour votre intérêt envers nos produits.Veuillez visiter notre site web afin de vous procurer une copie de nos termes et conditions.

CONTRO VALVE

Contro Valve Equipment inc. / Les Équipements Contro Valve inc.

Brandon, MB • Brossard, QC • Burlington, ON • Fredericton, NB • Halifax, NS Québec, QC • Sarnia, ON • St. John's, NL • Sudbury, ON •Thunder Bay, ON • Vancouver, BC

Intertek

Soumission : 19HA1029-1
Date (aaaa/mm/jj) : 2019/11/05

S'il vous plaît se référer à ce numéro lors de la commande
www.controvalve.com

* * SPARE PART ULTIMA X5000 * *

1 Pieces de Rechange pour Détecteur de gaz combiné double LEL et H2S — **Prix unitaire :** $4,330.00 **Qté :** 1 **Prix total :** $4,330.00

1.1 MSA modèle A-5K-SENS 210F00 — Prix unitaire : $925.00 Qté : 1 Prix total : $925.00

Desc. : ULTIMA X5000 Replacement Sensors for HYDROGEN SULFIDE 0-50 PPM

- Gas: 21 HYDROGEN SULFIDE 0-50 PPM
- Material: 0 STAINLESS STEEL
- Approvals: F FM/CSA
- Sensor Body Thread Type: 0 None
- Future Characteristic: 0 None

Note :
No need quick purchase, as warranty do not exceed 3 years from date of shipment.

1.2 MSA modèle A-5K-SENS AA0F10 — Prix unitaire : $1,835.00 Qté : 1 Prix total : $1,835.00

Desc. : ULTIMA X5000 Replacement Sensors for COMBUSTIBLE IR 5% METHANE

- Gas: AA COMBUSTIBLE IR 5% METHANE
- Material: 0 Stainless Steel
- Approval: F FM/CSA
- Sensor Body Thread Type: 1 3/4" NPT
- Future Characteristic: 0 None

Note :
No need quick purchase, as warranty do not exceed 5 years on electronics and 10 years on IR source bulb.

1.3 MSA modèle A-X5000-PCB-010 — Prix unitaire : $1,570.00 Qté : 1 Prix total : $1,570.00

Desc. : ULTIMA X5000 PCB Replacement Boards

Note :
No need quick purchase, as warranty do not exceed 2 years from date of shipment.

* * SPARE PART A-TRIGARD * *

1 Pieces de Rechange pour TRIGARD — **Prix unitaire :** $1,550.00 **Qté :** 1 **Prix total :** $1,550.00

1.1 MSA modèle A-ULTX-SENS-1600 — Prix unitaire : $775.00 Qté : 1 Prix total : $775.00

Desc. : Ultima X Series Hydrogen Sulfide 0-50 ppm Sensor

Note :
No need quick purchase, as warranty do not exceed 18 (eighteen) month from date of shipment.

1.2 MSA modèle A-ULTX-SENS-5700 — Prix unitaire : $775.00 Qté : 1 Prix total : $775.00

Desc. : Ultima X Series 57 Carbon Monoxide 0-1000ppm Sensor

Note :
No need quick purchase, as warranty do not exceed 18 (eighteen) month from date of shipment.

LIVRAISON	VALIDE POUR	FONDS	EX WORKS	TERMES	TAXES	GRAND TOTAL
4-5 Sem.	30 Jours	CAD	Brossard, QC ** Collect*	Net 30 ** Sujet à l'approbation de crédit*	Extra	

SPARE PART ULTIMA X5000 : $4,330.00 **SPARE PART A-TRIGARD : $1,550.00**

En espérant que cette soumission réponde à tous vos besoins. N'hésitez pas à nous contacter pour toutes autres demandes d'informations.Merci pour votre intérêt envers nos produits.Veuillez visiter notre site web afin de vous procurer une copie de nos termes et conditions.

Sous réserve de vente
En raison de l'extrême volatilité du taux du dollar US contre le dollar canadien, Contro Valve se réserve le droit d'ajuster les prix de vente final si la variance des taux de change est supérieure à +/- 5% à partir de la date de la proposition et la date d'expédition.

APPENDIX F

CONTACT SERVICE INFORMATION

Iqaluit WWTP
Instrumentation Supplier Contacts

Control Panel Equipment

Entreprise LM
3006 Ste-Catherine est, Montreal, Quebes, H1W 1B8
Contact: O. Chalifoux-Lauzon
Phone: (514) 523-2831
Fax: (514) 521-2526

SCADA Software, PCs, Printer

Entreprise LM
3006 Ste-Catherine est, Montreal, Quebes, H1W 1B8
Contact: Marion FLuery
Phone: (514)-521-0882
Scada Provider: Inductive Automation

Level FYLGT bulbs

Xylem
Contact: Hugo Chartier
Phone: _____
Model: ENM-10 Level Regulator

Ultrasonic Level Transmitter/Transducer

VISION Solutions de Procedes
364 Rue Mcarthur, Saint-Laurent, Quebec
Contact : Nacère Irid
Phone : 574-733-1800 #231
Maunfacture: Siemens,
Model: SITRANS LUT420 transmitter
& Echomac XPS transducers

Level Switch

Endress + Hauser Canada Ltée
1100 Montee Masson, Laval, Québec, Canada
Contact : Hugo Chartier
Phone : 450-688-4012
Manufacture: Endress + Hauser
Model: Liquiphant M FTL51

Strobes & Horns

Lumen
364 Rue Mcarthur, Saint-Laurent, Quebec
Contact : Anthony Nadji
Phone : 514-493-4127
Maunfacture: AST Applied Strobe Technology; Rockwell
Model: AST-14; 855H

Temperature Transmitters

Thermo Kinetics Measurement & Control
Contact: Normand Hadd
Phone: (514) 856-0370

Gas Detection

Contro-Valve
Contact : Marc-André Ouellette
Phone : (514) 217-5072
Model: Ultima X5000; Trigard

Magnetic Flow Meter

Endress + Hauser Canada Ltée
6800 Côte de liesse, suite 100, Ville Saint-Laurent, Québec, Canada, H4T 2A7
Contact : Éric Carpentier
Phone : 514-733-0254 x2286
Manufacture: Endress + Hauser
Model: Promag W 400

Thermal Mass Flow Meter

Endress + Hauser Canada Ltée
1100 Montee Masson, Laval, Québec, Canada
Contact : Hugo Chartier
Phone : 450-688-4012
Manufacture: Endress + Hauser
Model: T-Mass 651

Pressure Transmitter

Endress + Hauser Canada Ltée
1100 Montee Masson, Laval, Québec, Canada
Contact : Hugo Chartier
Phone : 450-688-4012
Manufacture: Endress + Hauser
Model: Cerabar M PMP55

Dissolved Oxygen Sensor

HACH
Contact :
Phone :
Manufacture: HACH
Model: 9020000, SC200

See Norclair O&M Section 1 for additional Equipment Contacts

APPENDIX G

WARRANTIES & CERTIFICATIONS

Arctic Electrical Nunavut Ltd

PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

ARCTIC ELECTICAL NUNAVUT LTD.

LETTER OF WARRANTY

FOR

WASTEWATER TREATMENT PLANT UPGRADE

IQALUIT, NUNAVUT

The control system and electrical installation has been tested and found to be in proper working condition at the time of turnover, and it is guaranteed to be free from any defect in workmanship and material that may develop within a one-year period from date of acceptance.

Any parts or parts of the control system and electrical installation, as defined in the Control System and Electrical Specification, that prove defective within one-year period shall be replaced without charge, when subjected to examination by one of our representatives and, in our opinion, is due to faulty material or workmanship and not caused by tampering, abuse, or misapplication.

This warranty is limited to Divisions 26 and 28 materials and associated equipment, and in no event shall Arctic Electrical Nunavut Ltd. have any liability for consequential damages, expenses or lost revenue due an electrical system failure. Any alterations to the system without the expressed written consent from Arctic Electrical Nunavut Ltd. will render this warranty null and void.

Arctic Electrical Nunavut Ltd.

Arctic Electrical Nunavut Ltd

PO Box 1381, Iqaluit, NU X0A 0H0 -P867-975-3494

Permits

26-Jul-2018

Government of Nunavut

Department of Community and Government Services

Baffin Region	Kivalliq Region	Kitikmeot Region
P.O. Box 1000 Station 610 Iqaluit, NU X0A 0H0 Phone: (867) 975-5423 Fax: (867) 975-5453	Bag 002 Rankin Inlet, NU X0C 0G0 Phone: (867) 645-8179 Fax: (867) 645-8196	Bag 200 Cambridge Bay, NU X0B 0C0 Phone: (867) 983-4157 Fax: (867) 983-4152

PERMIT FOR WIRING INSTALLATION

FOR USE BY QUALIFIED ELECTRICAL WORKERS

Permit Type: multi/commercial/industrial **Application Date:** 26-Jul-2018

LOCATION

Community: Iqaluit **Location:** Waste Water Treatment Plant **Lot:** **Block:**

OWNER

Name: City of Iqaluit, Eslam Maher **Address:** Iqaluit, Nu X0A0H0 **Phone:** (613) 216-4345 ext **Fax:**

INSTALLATION DETAILS

Construction Type: Addition Service Rating **Phase:** 3Phase
Plan Review # : RJK **Voltage:** 347/600
Power Connection Required: YES **Amperes:** 400
Work Description: Rewiring of Waste Water Plant

ELECTRICIAN

Name: Colin Molloy
#: E-0090 **Expiry:** 27-Oct-2018
Company: Arctic Electrical **Phone:** (867) 975-3494 ext
Address: Box 1381, Iqaluit, NU **Postal:** X0A 0H0 **Fax:** (867) 979-2496

Cost of Installation (Includes labour, travel, room _board)	**$610,000.00**
Permit Fee	**$12,852.00**

I (We) propose to install electrical wiring, apparatus, fittings or alterations, the particulars of which are set out above and hereby certify that this installation will be completed in accordance with the Canadian Electrical Code and Territorial Electrical Protection Act

OFFICE USE ONLY

PERMISSION IS HEREBY GRANTED TO DO THE ABOVE WORK PROVIDED IT IS COMMENCED BY Wednesday October 24, 2018 AND COMPLETED NO LATER THAN Friday July 26, 2019

RECEIPT No.	**GRN3650965**
PERMIT No.	**10186**

Issued By: Jessie Nikki — Issue Date: July 26, 2018

July 26, 2018

30-Jul-2018

Government of Nunavut

Department of Community and Government Services

Baffin Region	Kivalliq Region	Kitikmeot Region
P.O. Box 1000 Station 610 Iqaluit, NU X0A 0H0 Phone: (867) 975-5423 Fax: (867) 975-5453	Bag 002 Rankin Inlet, NU X0C 0G0 Phone: (867) 645-8179 Fax: (867) 645-8196	Bag 200 Cambridge Bay, NU X0B 0C0 Phone: (867) 983-4157 Fax: (867) 983-4152

ELECTRICAL INSPECTION REPORT

PERMIT: 10186

INSTALLATION

Location

Community: Iqaluit
Street: Waste Water Treatment Plant
Lot: Block:
Owner: CITY OF IQALUIT, Eslam Maher
Phone: (613) 216-4345 ext:
Fax:

Permit

PermitType: multi/commercial/industrial
Amperes: 400
Voltage: 347/600

Contractor

Name: Colin Molloy
#: E-0090
Company: Arctic Electrical
Address: Box 1381
Iqaluit, NU
Postal: X0A 0H0

INSPECTION

Date: 30-Jul-2018
Type: Power
Corrections Due By:
Inspector: Rick Kelly
Outcome: Not Complete
Fee: NO

DEFICIENCIES

CEC Section	Details	Status	Date
3-002	Power connection approval is granted	Open	30-Jul-2018

Please sign and return corrected deficiencies by the date listed above _____

Contractor Signature

10-Dec-2018

Government of Nunavut

Department of Community and Government Services

Baffin Region	Kivalliq Region	Kitikmeot Region
P.O. Box 1000 Station 610	Bag 002	Bag 200
Iqaluit, NU	Rankin Inlet, NU	Cambridge Bay, NU
X0A 0H0	X0C 0G0	X0B 0C0
Phone: (867) 975-5423	Phone: (867) 645-8179	Phone: (867) 983-4157
Fax: (867) 975-5453	Fax: (867) 645-8196	Fax: (867) 983-4152

ELECTRICAL INSPECTION REPORT

PERMIT: 10186

INSTALLATION

Location

Community: Iqaluit
Street: Waste Water Treatment Plant
Lot: Block:
Owner: CITY OF IQALUIT, Eslam Maher
Phone: (613) 216-4345 ext:
Fax:

Permit

PermitType: multi/commercial/industrial
Amperes: 400
Voltage: 347/600

Contractor

Name: Colin Molloy
E-0090
Company: Arctic Electrical
Address: Box 1381 Iqaluit, NU
Postal: X0A 0H0

INSPECTION

Date: 30-Jul-2018
Type: Power
Corrections Due By:
Inspector: Rick Kelly
Outcome: Not Complete
Fee: NO

DEFICIENCIES

CEC Section	Details	Status	Date
3-002	Power connection approval is granted	Corrected	30-Jul-2018

Please sign and return corrected deficiencies by the date listed above _____
Contractor Signature

CONTRO VALVE

Contro Valve Equipment inc. / Les Équipements Contro Valve inc.
Brandon, MB • Brossard, QC • Burlington, ON • Fredericton, NB • Halifax, NS Québec, QC • Sarnia, ON • St. John's, NL • Sudbury, ON •Thunder Bay, ON • Vancouver, BC

Intertek

Soumission :	**19HA1029-1**
Date (aaaa/mm/jj)	**2019/11/05**

S'il vous plaît se référer à ce numéro lors de la commande
www.controvalve.com

À l'attention :	Hugo Chartier
Compagnie :	Norclair Inc.
Adresse :	3065 peugeot bureau 101 Laval QC Canada H7L 5C4
Référence :	IQA15-4964-C Iqaluit WWTP
Téléphone :	(450) 688-4012 ,706
Courriel :	hchartier@norclair.ca

Créer par :	Hugues Almeida
Courriel :	halmeida@controvalve.com
Adresse :	9610 B Ignace Brossard QC Canada, J4Y 2R4
Représentant :	Marc-André Ouellette & Hugues Joannis
Téléphone :	450-444-5858

Suite à votre demande, il nous fait plaisir de vous faire parvenir la présente soumission.

** Les commandes placées avant la date d'expiration seront facturées au prix soumissionné*

** Taxes sur la vente, frais de douanes ou tout autres frais ne sont pas inclus dans cette soumission*

** Prière de nous faire parvenir votre bon de commande ainsi que notre # de soumission comme référence au BrossardPO@controvalve.com*

LIVRAISON	VALIDE POUR	EX WORKS	TERMES
4-5 Sem.	30 Jours	Brossard, QC	Net 30
		** Collect*	** Sujet à l'approbation de crédit*

Sous réserve de vente

En espérant que cette soumission réponde à tous vos besoins. N'hésitez pas à nous contacter pour toutes autres demandes d'informations.Merci pour votre intérêt envers nos produits.Veuillez visiter notre site web afin de vous procurer une copie de nos termes et conditions.

CONTRO VALVE

Contro Valve Equipment inc. / Les Équipements Contro Valve inc.

Brandon, MB • Brossard, QC • Burlington, ON • Fredericton, NB • Halifax, NS Québec, QC • Sarnia, ON • St. John's, NL • Sudbury, ON •Thunder Bay, ON • Vancouver, BC

Intertek

Soumission : 19HA1029-1
Date (aaaa/mm/jj) : 2019/11/05

S'il vous plaît se référer à ce numéro lors de la commande
www.controvalve.com

* * SPARE PART ULTIMA X5000 * *

1 Pieces de Rechange pour Détecteur de gaz combiné double LEL et H2S — **Prix unitaire :** $4,330.00 **Qté :** 1 **Prix total :** $4,330.00

1.1 MSA modèle A-5K-SENS 210F00 — Prix unitaire : $925.00 Qté : 1 Prix total : $925.00

Desc. : ULTIMA X5000 Replacement Sensors for HYDROGEN SULFIDE 0-50 PPM

- Gas: 21 HYDROGEN SULFIDE 0-50 PPM
- Material: 0 STAINLESS STEEL
- Approvals: F FM/CSA
- Sensor Body Thread Type: 0 None
- Future Characteristic: 0 None

Note :
No need quick purchase, as warranty do not exceed 3 years from date of shipment.

1.2 MSA modèle A-5K-SENS AA0F10 — Prix unitaire : $1,835.00 Qté : 1 Prix total : $1,835.00

Desc. : ULTIMA X5000 Replacement Sensors for COMBUSTIBLE IR 5% METHANE

- Gas: AA COMBUSTIBLE IR 5% METHANE
- Material: 0 Stainless Steel
- Approval: F FM/CSA
- Sensor Body Thread Type: 1 3/4" NPT
- Future Characteristic: 0 None

Note :
No need quick purchase, as warranty do not exceed 5 years on electronics and 10 years on IR source bulb.

1.3 MSA modèle A-X5000-PCB-010 — Prix unitaire : $1,570.00 Qté : 1 Prix total : $1,570.00

Desc. : ULTIMA X5000 PCB Replacement Boards

Note :
No need quick purchase, as warranty do not exceed 2 years from date of shipment.

* * SPARE PART A-TRIGARD * *

1 Pieces de Rechange pour TRIGARD — **Prix unitaire :** $1,550.00 **Qté :** 1 **Prix total :** $1,550.00

1.1 MSA modèle A-ULTX-SENS-1600 — Prix unitaire : $775.00 Qté : 1 Prix total : $775.00

Desc. : Ultima X Series Hydrogen Sulfide 0-50 ppm Sensor

Note :
No need quick purchase, as warranty do not exceed 18 (eighteen) month from date of shipment.

1.2 MSA modèle A-ULTX-SENS-5700 — Prix unitaire : $775.00 Qté : 1 Prix total : $775.00

Desc. : Ultima X Series 57 Carbon Monoxide 0-1000ppm Sensor

Note :
No need quick purchase, as warranty do not exceed 18 (eighteen) month from date of shipment.

LIVRAISON	VALIDE POUR	FONDS	EX WORKS	TERMES	TAXES	GRAND TOTAL
4-5 Sem.	30 Jours	CAD	Brossard, QC ** Collect*	Net 30 ** Sujet à l'approbation de crédit*	Extra	

SPARE PART ULTIMA X5000 : $4,330.00 **SPARE PART A-TRIGARD : $1,550.00**

En espérant que cette soumission réponde à tous vos besoins. N'hésitez pas à nous contacter pour toutes autres demandes d'informations.Merci pour votre intérêt envers nos produits.Veuillez visiter notre site web afin de vous procurer une copie de nos termes et conditions.

Sous réserve de vente
En raison de l'extrême volatilité du taux du dollar US contre le dollar canadien, Contro Valve se réserve le droit d'ajuster les prix de vente final si la variance des taux de change est supérieure à +/- 5% à partir de la date de la proposition et la date d'expédition.

Endress+Hauser
People for Process Automation

ENDRESS+HAUSER CANADA LTD/LTEE GENERAL TERMS AND CONDITIONS OF SALE

1. **Acceptance.** The Buyer's purchase order ("Order") constitutes an offer by Buyer to purchase Goods and/or Services in accordance with these Terms and Conditions. The Order shall be deemed to be accepted when Seller issues written acceptance of the Order at which point and on which date the Agreement shall come into existence. Any quotation given by the Seller shall not constitute an offer. It is only valid for a period of 30 days from the date of issue unless the Seller agrees in writing to extend that period.

2. **Buyer's Assent.** Shipment by Seller and acceptance by Buyer of, or payment for all or any part of the Goods (as defined below) and/or Services (as defined below) covered by the Order shall constitute Buyer's assent to all of the Terms herein. Prior to acceptance of Goods and Services by Buyer, Seller may withdraw or modify its conditional acceptance of the Order.

3. **Complete Agreement.** The Agreement along with these Terms (collectively referred to herein as the "Agreement") constitutes the entire agreement between the parties and supersedes all prior agreements with respect to the Goods and Services whether such agreements were written or oral. These Terms apply to the Agreement to the exclusion of any other terms that Buyer seeks to impose or incorporate, or which are implied by trade, custom, practice or course of dealing. These Terms are also available online at www.ca.endress.com. Seller may amend these Terms at any time at its discretion. These Terms shall apply to the supply of both Goods and Services except where application to one or the other is specified. Special terms may apply in respect of software support services and/or other specific services if agreed between the parties.

4. **Modification.** No modification, amendment, extension, renewal, rescission, discharge, abandonment, waiver or other change or alteration shall be valid, enforceable or binding on Seller unless agreed to in writing by Seller. Seller shall not be bound by any additional or different terms, whether printed or otherwise, in the Order or any other communication from Buyer to Seller unless specifically agreed to by Seller in writing. Prior courses of dealing, usage of the trade, and verbal agreements not reduced to writing and signed by Seller, to the extent that they modify, add to, or detract from the Agreement, shall not be binding on the Seller. Seller may, at its option, treat any attempted modification, termination or repudiation by Buyer to which Seller does not assent as a breach of the entire Agreement and claim all proper damages.

5. **Termination.** If all or part of the Agreement is terminated by agreement of the parties, and if there is no contrary written agreement between Seller and Buyer, Buyer shall pay termination charges in the amount equal to the greater of (I) ten (10) percent of the net sales price or (II) (a) the price provided in the Order for all Goods assembled and Services performed prior to the agreement by Seller to terminate, plus (b) the actual expenditures made and liabilities incurred by Seller in connection with any portion of the Goods and Services not yet completed (as evidenced in writing), plus (c) reasonable estimated profit on the not yet completed portion of the Goods and Services.

6. **Price, Payment Terms, and Security Interest.** The price for Goods shall be the price set out in the Order confirmation. The price of the Goods is exclusive of all costs and charges of packaging, insurance, and transport of the Goods. The charges for Services shall be on a time and materials basis and shall be calculated in accordance with Seller's standard daily fee rates and service rate schedule, which is available upon request. The price for Goods and Services are collectively hereinafter also referred to as the "Prices". Seller's Prices may be subject to change and are subject to Seller's standard annual price increases. Seller will notify Buyer of any Price increase. Unless provided otherwise on the face of this Agreement, Buyer shall pay the purchase price for the Goods and Services in full within 30 days from date of shipment. Buyer shall pay all amounts due under this Agreement in full without any set-off, counterclaim, deduction, or withholding except as required by law. Seller may, without limiting its other rights or remedies, set off any amount owing to it by Buyer against any amount payable by Seller to Buyer. All invoices not paid when due will thereafter be subject to a monthly service charge of one and a half percent (1½%) of the unpaid balance. If, in Seller's opinion, there is a material, adverse change in Buyer's financial condition or if Buyer has not, within the agreed time, fully paid for Goods shipped and Services performed under this or any other agreement with Seller, Seller reserves the right to revoke Buyer's credit, to require shipment of Goods C.O.D., and/or suspend performance on this and/or other agreements and/or future shipments. Buyer hereby grants Seller a purchase money security interest in the Goods until the full purchase price is paid, and Buyers appoints Seller as its attorney-in-fact for the purpose of filing any documents necessary or desirable to perfect such security interest in any applicable jurisdiction.

7. **Services**. In the event services are also provided to Buyer by Seller (including, but not limited to the licensing of software), Seller will provide services ("Services") to Buyer in accordance with the Buyer's service specifications and these Terms. However, Seller shall not be obligated to perform Services as a result of malfunctions of the Goods caused by: (a) the deliberate or negligent acts of persons other than the Seller; (b) inadequate facilities of Buyer; (c) systems or equipment outside Seller's control (such as those provided by vendors of utilities), and (d) modifications to the Goods made by a party other than the Seller. Seller shall have the right

to make any changes to the Services that are necessary to comply with any applicable law or safety requirement, or which do not materially affect the nature or quality of the Services, and the Seller shall notify the Buyer in any such event.
Buyer shall provide Seller with reasonable access to its premises as necessary for Seller to perform the Services. At all times Seller's personnel will comply with Buyer's safety and security precautions, procedures, and guidelines. Seller will immediately inform Buyer of any injury or accident occurring on Buyer's premises involving Seller's personnel. Seller will provide Services in a manner as to minimize interference with Buyer's operations. Buyer shall cooperate with the Seller in all matters relating to the Services and provide the Seller with such information and materials as the Seller may reasonably require to supply the Services, and ensure that such information is accurate in all material respects. Seller shall have the right to rely on information and materials provided by Buyer and Seller shall not be liable for Services performed, provided that such Services are provided in accordance with Buyer's specifications. Buyer shall obtain and maintain all necessary licenses, permissions and consents which may be required for the Services to be performed prior to the date on which the Services are to start, and keep and maintain all materials, equipment, documents and other property of the Seller ("Seller Materials") at the Buyer's premises in safe custody at its own risk, and in good condition until returned to the Supplier, and not dispose of or use the Seller Materials other than in accordance with the Seller's written instructions or authorization.

8. **Delivery/Shipment.** Seller shall deliver the Goods to the location as set out in the Order Confirmation (Delivery Location) and in accordance with the INCOTERM referred to in the Order Confirmation (in the absence of written agreement to the contrary) and shall be deemed complete pursuant to the agreed upon delivery terms. If no terms are specified, the delivery terms shall be CPT domestic site (Incoterms 2010). Buyer shall pay all shipping, packing and handling costs and shall bear the risk of loss after Seller completes delivery of the Goods to the carrier. Buyer shall have five (5) days after any full or partial delivery to notify Seller if Buyer's count of delivered Goods does not conform with Seller's count as identified in the itemized packing list accompanying the shipment.

9. **Title.** Title to the Goods shall only pass upon: Shipment of Goods.

10. **Sales or Use Taxes.** In compliance with various provincial sales tax statutes and regulations, Seller will add sales tax to the sale of a taxable order unless Buyer provides documentation that is complete, legally acceptable in form, and valid in accordance with applicable laws and regulations of the province that has jurisdiction over the sales transaction. The jurisdiction province shall be the province of Ontario. Buyer shall be held liable to Seller for monies due for sales tax if a subsequent tax audit determines that Buyer provided incomplete or invalid documentation, unless Buyer provides additional documentation to correct any deficiencies in the original documentation in accordance with applicable provincial laws and regulations and audit requirements.

11. **Time of Delivery.** Shipment and Service schedules are approximate and are based on conditions existing at the time of execution of the Agreement. Seller shall attempt to effect delivery or performance of Services in good faith by the date specified on the Order. Buyer agrees that Seller shall not be responsible or liable for any damages, including but not limited to, direct, indirect, special or consequential damages, arising from any shipment of nonconforming Goods, or any delay in delivery of Goods or performance of Services, or any failure to deliver Goods in quantities and at times specified. In such cases, Seller reserves the right to terminate the Agreement or to reschedule delivery within a reasonable time, and Buyer agrees that such termination or rescheduling shall not be considered a breach of the Agreement. In no event shall Seller be liable for incidental or consequential damages resulting from failure to meet requested delivery schedules. Goods and Services shall be deemed accepted when received by Buyer or upon completion of Services, respectively. Buyer's revocation of acceptance, if any, must be made in writing within fifteen (15) business days after receipt of the Goods or completion of the Services. The writing must specify Buyer's reason for revocation of acceptance. The terms of this section do not limit or affect Buyer's rights or Seller's warranty obligations specified hereunder.

12. **Returns.** Except for the return of nonconforming and defective Goods, all returns of Goods shall be made in strict compliance with Seller's Return Policy as may be in effect from time to time, a written copy of which is available to Buyer upon request.

13. **Storage Fees.** If Buyer requests deferral of shipment, or fails to provide information, material or documentation required by this Agreement and as a result Goods are placed in storage, storage fees will commence immediately following the scheduled ship date unless extended in writing. The Buyer will be charged a storage fee equal to Seller's actual cost to store the Goods. These charges will be invoiced to Buyer separately from the actual shipment and shall be paid in full by Buyer within thirty (30) days of date of invoice.

14. **Specifications.** Goods and Services shall be deemed to be in conformity herewith if they conform to the specifications provided by Buyer. In the event ambiguities, discrepancies, or express conflicts exist between the specifications and any other item purporting to describe or define the Goods or Services, including but not limited to drawings, photographs, models or other documentation, the specifications shall control unless otherwise agreed to in writing by Seller. Buyer agrees that Seller shall have no responsibility to identify or notify Buyer of any such ambiguity, discrepancy, or conflict. Seller reserves the right to amend the specification of the Goods if required by any applicable statutory or regulatory requirements.

15. **Nonconforming Goods.** Seller reserves the right to cure any shipment of nonconforming Goods. At the option of Seller, Buyer's remedies for nonconforming Goods shall be limited to the repair or replacement of the nonconforming Goods, and if repair or replacement is not possible, return of the nonconforming Goods and repayment of any portion of the purchase price paid.

16. **Seller's Express Warranty.** Seller warrants the Goods to meet the specifications provided in the Order and to be free from defects in materials and workmanship under normal use and service for a period of one year from time of shipment. Seller further warrants that for a period of one year from time of completion of Services, Services will conform to the specifications set forth in the Order and that Seller will perform Services in a professional and workmanlike manner in accordance with all applicable laws and regulations. Buyer agrees that it has the sole responsibility for the proper selection application, installation, use and instructions (concerning use, application, periodic maintenance, and cautions of the Goods) to ultimate users of the Goods and Services. Buyer agrees that the warranty provided herein shall not apply to any Goods or Services which: (1) have been repaired or altered outside of Seller's factory in any way so as, in Seller's judgment, to affect such Goods' or Services' reliability; (2) have been subject to misuse, negligence, or accident; (3) have been operated other than in accordance with the printed instructions prepared by Seller and provided by Seller with the Goods or Services; or (4) have been subject to abnormal wear of wetted parts caused by Buyer's application of the Goods. Furthermore, Buyer acknowledges that repairs performed by Buyer or others are not warranted by Seller, and that third party equipment shall be subject to the warranties provided therewith. Notwithstanding anything to the contrary herein, it is understood and agreed that the provisions of the Ontario Sale of Goods Act, the Ontario Consumer Protection Act, and similar legislation throughout Canada are hereby waived by the Customer.

17. **Seller's Exclusive Obligations under Warranty.** Seller shall re-perform, at Seller's sole cost and expense, any Services which do not comply with the applicable warranties specified hereof. At Seller's option, Seller may repair, replace, or refund the purchase price of Goods. Goods shall be returned to Seller no later than one month after the expiration of the applicable warranty period and in the manner set forth in this clause and in a manner in which Seller's examination shall disclose to Seller's satisfaction that Goods are defective as specified in the warranty clause hereof. All allegedly defective Goods shall be returned to the Seller at Buyer's expense and risk. All such defective or nonconforming Goods shall be returned to Seller at Burlington, Ontario, freight prepaid, unless otherwise agreed by the parties in writing, and shall be accompanied or preceded by a particularized statement of the claimed defect. Under such circumstances, freight charges to and from Seller and risk of loss shall be borne by Buyer. Seller shall bear the cost of repair or replacement and the risk of loss while the Goods are in Seller's possession at Seller's plant. If Goods are returned without being preceded or accompanied by a written statement of the claimed defect, Seller shall hold the Goods pending receipt of Buyer's statement of defect, provided that, prior to such receipt, risk of loss of the Goods shall remain with the Buyer.

18. **Limitation of Remedies**. SELLER'S OPTION TO REPAIR, REPLACE OR REFUND THE PURCHASE PRICE FOR GOODS OR RE-PERFORM SERVICES IS BUYER'S EXCLUSIVE REMEDY AGAINST SELLER WHETHER SUCH REMEDY ARISES OUT OF BUYER'S CLAIM FOR BREACH OF WARRANTY, BREACH OF CONTRACT OR ANY OTHER CLAIM WITH RESPECT TO THE GOODS AND SERVICES AND SELLER SHALL NOT BE LIABLE FOR ANY CONSEQUENTIAL OR INCIDENTAL DAMAGES, DIRECT, INDIRECT, SPECIAL, CONSEQUENTIAL (INCLUDING LOSS OR PROFIT OR OTHER ECONOMIC LOSS) OR OTHER DAMAGES, REGARDLESS OF THE FORM OF ACTION, WHETHER IN CONTRACT, TORT, STRICT PRODUCTS LIABILITY, OR OTHERWISE, EVEN IF BUYER HAS BEEN ADVISED OF THE POSSILITY OF SUCH DAMAGES ARISING OUT OF THE FURNISHING, PERFORMANCE, USE OF, OR PROVIDING THE GOODS AND/OR SERVICES IN CONNECTION WITH THIS AGREEMENT. THE PARTIES AGREE THAT CONSEQUENTIAL DAMAGES FOR PURPOSES OF THIS AGREEMENT REPRESENT ANY DAMAGES OTHER THAN THE COST TO REPAIR, REPLACE OR REFUND THE PURCHASE PRICE OF THE GOODS WITH RESPECT TO WHICH THE LOSS OCCURRED.

19. **Seller's Disclaimer of Implied Warranties.** SELLER'S EXPRESS WARRANTIES ARE IN LIEU OF ALL OTHER WARRANTIES, AND SELLER HEREBY DISCLAIMS ANY OTHER EXPRESS OR IMPLIED WARRANTIES, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. BUYER AGREES THAT MODELS OR SAMPLES SHOWN TO BUYER, IF ANY, WERE USED MERELY TO ILLUSTRATE THE GOODS AND NOT TO REPRESENT, PROMISE, OR GUARANTEE THAT ANY GOODS DELIVERED HEREUNDER WOULD CONFORM TO SUCH MODELS OR SAMPLES. SELLER'S AGENTS HAVE NO AUTHORITY TO GIVE WARRANTIES BEYOND THOSE PROVIDED IN THIS LIMITED EXPRESS WARRANTY.

20. **Indemnification.** Buyer agrees to indemnify and hold harmless Seller against all damages, costs, expenses and attorney's fees arising from claims of infringement of patents, designs, copyrights or trademarks with respect to all Goods manufactured or assembled either in whole or in part to Buyer's specifications. Buyer agrees that such infringement shall be deemed a breach of the Agreement. Seller further reserves the right to terminate the Agreement for Goods which, in the opinion of Seller, infringe upon any patent, design, copyright or trademark in their manufacture, sale and/or use, and Buyer agrees that such termination shall not be considered a breach by Seller of the Agreement. Buyer further agrees that Seller shall not be liable under this provision if the Goods or Services are

altered or modified in any manner after Seller delivers such Goods to the carrier for delivery to Buyer or completes performance of any Services.

21. **Import and Export Compliance.** Buyer is solely responsible for compliance with all applicable import and export control laws, in any jurisdiction, relating to the Goods and Services. Buyer shall undertake all necessary actions to comply with such laws, including, but not limited to, processing of all necessary customs procedures, payment of import/export duties and import/export taxes, completion and maintenance of documentation and provision of accurate information to all customs authorities. Buyer shall indemnify and hold harmless Seller against all damages, costs, expenses and attorney's fees arising from or alleged to arise from any violation, alleged violation, or failure to comply with, the terms of this provision by Buyer or any person for whom Buyer may be responsible.

22. **Buyer Default.** Seller shall have the unrestricted right, upon written notice to Buyer, to declare a default ("Buyer Default") hereunder and to terminate this Agreement if any of the following events occur: 1) Buyer's failure to comply with any of the provisions, terms and conditions of this Agreement, including without limitation, Buyer's failure to timely pay for any Goods or Services delivered to Buyer; 2) Seller's ability to perform of any of its obligations in respect of Services is prevented or delayed by any act or omission by Buyer or failure by Buyer to perform any relevant obligation, after a reasonable opportunity to cure such Buyer's failure to perform or act or omission; 3) Dissolution, insolvency, appointment of a receiver, assignment for the benefit of creditors or the commencement of any proceeding under any bankruptcy or insolvency laws by or against the Buyer; or 4) Seller's determination, in its sole discretion, that Buyer's financial condition is such as to endanger Buyer's performance hereunder.

23. **Remedies Upon Buyer's Default.** Upon Buyer's Default and Seller's written notice thereof to Buyer, every obligation of Seller hereunder shall immediately terminate and Seller shall have all rights and remedies existing at law or in equity, including but not limited to those provided by the Uniform Commercial Code as adopted in Ontario, and Buyer shall reimburse Seller on written demand for any costs or losses sustained or incurred by Seller arising directly or indirectly from the Buyer Default. Seller shall also have the right to suspend performance of any Services until Buyer remedies such Buyer Default, and to rely on the Buyer Default to relieve it from the performance of any of its obligations to the extent the Buyer Default prevents or delays Seller's performance of any of its obligations.

24. **Governing law**
This agreement and any dispute or claim arising out of or in connection with it or its subject matter or formation (including non-contractual disputes or claims) shall be governed by and construed in accordance with the laws of Ontario and Canada [law of your country].

25. **Jurisdiction**
Each party irrevocably agrees that the Ontario and Canada [courts of your country] shall have exclusive jurisdiction to settle any dispute or claim arising out of or in connection with this Contract or its subject matter or formation (including non-contractual disputes or claims).

26. **Reservation of Rights.** Buyer agrees that Seller's forbearance, delay or failure to exercise any right or remedy hereunder shall not constitute a waiver of such right or remedy and that Seller's exercise or partial exercise of any right or remedy shall not preclude further exercise of such right or remedy or any other right or remedy.

27. **Costs of Enforcement.** Buyer agrees to pay Seller's reasonable expenses, including reasonable attorney's fees and costs, incurred in enforcing the terms herein.

28. **Choice of Law and Venue.** The Agreement shall be governed by the laws of the province of Ontario, excluding its provisions on conflicts of law. Exclusive venue of any dispute or action arising out of this Agreement will lie in any province or federal court of competent jurisdiction in Burlington, Ontario.

29. **Severability of Clauses.** Buyer agrees that the invalidity or unenforceability of any of the clauses or terms herein shall not affect the validity or enforceability of any other clauses or terms hereof. Sections 15-20, 28 and 30, and any other clause as the context implies, shall survive the termination or expiration of this Agreement.

30. **Alternative Dispute Resolution.** If a dispute arises between the parties, the parties agree to use the following alternative dispute resolution ("ADR") procedure prior to either Party pursuing other available remedies:
1) A meeting shall be held promptly between the parties, attended by individuals with decision-making authority regarding the dispute, to attempt in good faith to negotiate a resolution of the dispute.

2) If, within thirty (30) days after such meeting, the parties have not succeeded in negotiating a resolution of the dispute, they will jointly appoint a mutually acceptable neutral person not affiliated with either of the parties to act as a mediator. If the parties are unable to agree on the neutral person within twenty (20) days, they shall seek assistance in such regard from ADR Chambers of Canada ("ADRCC"). The fees of the neutral person and all other common fees and expenses shall be shared equally by the parties.
3) The mediation may proceed in accordance with ADRCC's Mediation Rules. The parties shall pursue mediation in good faith and in a timely manner. In the event the mediation does not result in resolution of the dispute within sixty (60) days, then, upon seven (7) days' written notice to the other party either party may suggest another form of ADR, *e.g.*, arbitration, a mini-trial or a summary jury trial, or may pursue other available remedies.

31. **Confidentiality.** The parties agree to treat the Order, this Agreement, and any contract formed upon its acceptance as confidential and shall not disclose the existence or substance hereof to any third party. If in connection with the provision of goods or services hereunder a party (each one a "Recipient" as applicable to this provision) becomes aware of or receives any confidential information of the other party (each one a "Discloser" as applicable to this provision), Recipient agrees not to disclose such information to any third party or to make use of such information, except to the extent necessary to perform hereunder or as required by law. Upon Discloser's request, Recipient shall promptly return to Discloser all Confidential Information in tangible form. The parties agree that any disclosure or use of the other party's Confidential Information, except as otherwise authorized herein or by Discloser in writing, would be wrongful and cause immediate and irreparable injury to Discloser. Recipient agrees to immediately notify Discloser of any unauthorized disclosure or use of any Discloser's Confidential Information of which Recipient becomes aware. This clause shall survive termination of this Agreement.

32. **Independent Contractors.** In performing its obligations to Buyer, hereunder, Seller is acting as an independent contractor and neither party is an agent or representative of the other. Neither party is authorized to make any representations or assume or create any obligations on behalf of the other.

33. **Limitation of Liability.** NOT WITHSTANDING THE OTHER PROVISIONS OF THIS AGREEMENT TO THE CONTRARY, THE AGGREGATE LIABILITY OF EACH PARTY TO THE OTHER PARTY FOR ANY AND ALL CLAIMS AND LIABILITIES ARISING OUT OF OR RELATING TO THIS AGREEMENT OR TO THE BUYER'S OR SELLER'S RIGHTS AND OBLIGATIONS HEREUNDER, WHETHER BASED ON A THEORY OF CONTRACT, TORT, STRICT LIABILITY, OR OTHERWISE, SHALL NOT EXCEED THE PRICE OF THE GOODS OR SERVICES. IN NO EVENT SHALL SELLER'S LIABILITY TO BUYER EXTEND TO INCLUDE INCIDENTAL, INDIRECT, CONSEQUENTIAL OR PUNITIVE DAMAGES. THE TERM "CONSEQUENTIAL DAMAGES" SHALL INCLUDE BUT NOT BE LIMITED TO, LOSS OF ANTICIPATED PROFITS, REVENUE OR USE AND COSTS INCURRED. THIS CLAUSE SHALL SURVIVE TERMINATION OF THIS AGREEMENT.

34. **Compliance with Governing Laws and Regulations.** The Parties acknowledge and agree that all business activities shall be conducted ethically, with integrity, and in full compliance with both the letter and the spirit of the laws and regulations applicable to those activities. This commitment applies without limitation to the award of contracts/subcontracts on an impartial/competitive basis, personal business conduct, internal control systems, the offering/giving/receiving of gifts or anything of value, and correct documentation and registration of financial accounts. Neither Buyer nor its employees are authorized to operate on Seller's behalf in an illegal manner or in contrast with Seller's business-conduct policies and vice-versa. Should a Party ever receive, directly or indirectly from any of the other Party's representatives or agents, a request that the Party believes is contrary to the provisions of this clause, that Party shall immediately notify the other Party's general counsel.
Without limiting the generality of the foregoing or the effect of any other provision of this Agreement, and to the extent either Party performs any work or obtains or sells any of the products in relation to this Agreement in or from a foreign country:
a. Each Party represents and warrants that it is familiar with the Corruption of Foreign Public Officials Act ("the CFPOA"), and the Criminal code of Canada (the "Criminal Code"), as amended,. Each Party further represents that, in particular, it is familiar with the prohibitions of the CFPOA and the Criminal Code against offering, paying or giving anything of value, either directly or indirectly, to foreign or domestic officials (including employees of state-owned or controlled enterprises), candidates or political parties for the purpose of securing any improper advantage for a company, including assisting a company in obtaining or retaining business.
b. Each Party agrees that it shall not make any offer, payment, promise to pay, gift, or promise to give monies or anything of value; nor authorize any such offer, payment, promise to pay, gift, or promise to give by anyone acting for or on behalf of itself or the other Party; to any government official, any political party or official thereof, any candidate for political office, any official of a public international organization, or any other person that is contrary to the provisions of the CFPOA or the Criminal Code, as amended.
c. Each Party agrees that it shall not make any offer, payment, promise to pay, gift, or promise to give monies or anything of value; nor authorize any such offer, payment, promise to pay, gift, or promise to give by anyone acting for or on behalf of itself or the other Party; to any employee of a private company in order to improperly induce that employee to provide any competitive advantage to either Party in selling products or services or in otherwise doing business with that company.

d. Each Party agrees to maintain records for 5 years and present them for auditing upon demand by the other Party if there is any suspicion that a violation of this provision 33 may have occurred.
e. Both Parties represent that neither it nor any of its directors, officers, or employees is a government official, including without limitation an official or employee of any government, an official of a political party, or a candidate for political office, or a director, officer, employee, or "affiliate" (as defined in the CFPOA) of a government instrumentality. Both Parties understand that for purposes of this agreement, a "government official" may include an employee or official of a commercial entity or a university or institute of higher learning in which a government body has an ownership interest or exerts control over the activities of such entity, as well as officials and employees of public international organizations.
Each Party acknowledges that the representations and warranties provided in this clause are material to this Agreement. These representations shall be deemed to be continuing in effect throughout the term of the Agreement. Both Parties shall promptly advise each other of any change in circumstances which may affect the continuing validity of their representations. Either Party may terminate this Agreement at any time, without any liability or obligations to the other Party, if that Party believes, in good faith, that the other Party has violated any provisions of this clause. Any action by either Party which would or might constitute a violation of the CFPOA or the Criminal Code, as amended, or a request for such action from or by a representative of either Party shall result in immediate termination of this Agreement without further liability or obligation of the other Party.

35. **Force Majeure.** The Seller will not be responsible or liable in any way for delay or failure to effect delivery of Goods and Services pursuant to its obligations under this Agreement in which effectuation is hindered or prevented by conditions reasonably beyond its control, acts of God, fire, flood, other weather conditions, war, embargo, explosions, riots, laws, rules, regulations, or orders of any governmental authority.

36. **Assignment.** This Agreement may not be assigned by either Party to any third party without the prior written consent of the other Party hereto; provided, however, that a Party may assign its rights and obligations hereunder by written notice to the other Party to (a) any Affiliate or (b) a successor or transferee (whether by merger, consolidation, purchase or otherwise) of either (i) all or substantially all of the assets of the assignor, or (ii) all or substantially all of the assets of the business to which it pertains; and provided such party is not a competitor of the non-assignor. Any purported assignment in violation of the preceding shall be void. Any permitted assignee shall assume all obligations of its assignor under this Agreement. No assignment shall relieve a Party of responsibility for the performance of any obligation which accrued prior to the effective date of such assignment.

37. **Intellectual Property.** All Intellectual Property Rights in or arising out of or in connection with this Agreement and/or the Services shall be owned by Seller.

38. **General Definitions.**
a) Agreement: means the receipt and acceptance by Seller of the Order along with these Standard Sales and Service Terms and Conditions, Sellers' invoices, delivery forms, or other Seller documents related to the Order.
b) Goods: means any and all goods purchased by Buyer from Seller in connection with this Agreement and as specified in the Order.
c) Intellectual Property Rights: means patents, inventions, copyright and related rights, trademarks, trade names, business and domain names, goodwill, designs, database rights, processes, know-how, trade secrets, computer technical expertise, general product and process expertise, software and other intellectual property independently developed, owned, and/or controlled by Seller and any improvements thereto which are used, improved, modified, or further developed by Seller during its performance under this Agreement, in each case whether registered or unregistered and including all applications and rights to apply for and be granted, renewals or extensions of, and right to claim priority from, such rights and all similar or equivalent rights or forms of protection which subsist or will subsist now or in the future in any part of the world, shall be and remain the property of Seller.
d) Services: means any and all services, including any deliverables, purchased by Buyer from Seller in connection with this Agreement and as specified in the Order.

39. Language.
The parties acknowledge that they have required that the agreement evidenced hereby be drawn up in English. Les parties reconnaissent avoir exigé la rédaction en anglais du Contrat. In the event of a conflict between the English and other language versions, the English version will prevail.

Iqaluit WWTP, Fixed gas detectors warranty, Controvalve

ULTIMA X5000 spare sensors and PCB board warranty

Product Warranty

ITEM	WARRANTY PERIOD
ULTIMA X5000 Gas Monitor	MSA warrants that this product will be free from mechanical defects and faulty workmanship for the period specified in this table for each component, provided it is maintained and used in accordance with MSA's instructions and/or recommendations. Guarantee shall not exceed the indicated warranty period plus six months from the date of manufacture.
Main Transmitter Housing and PCBA	3 years if equipped with a Sunshield. 2 years if not equipped with a Sunshield.
XCell Sensors	3 years from date of shipment.
XIR PLUS	5 years on electronics. 10 years on IR source bulb.

For Hydrogen Sulfite 0-50 ppm sensor

For IR combustible 0-100% LEL – Methane (5%) sensor

This warranty does not cover filters, fuses, etc. Certain other accessories not specifically listed here may have different warranty periods. This warranty is valid only if the product is maintained and used in accordance with Seller's instructions and/or recommendations. The Seller shall be released from all obligations under this warranty in the event repairs or modifications are made by persons other than its own or authorized service personnel or if the warranty claim results from physical abuse or misuse of the product. No agent, employee or representative of the Seller has any authority to bind the Seller to any affirmation, representation or warranty concerning this product. Seller makes no warranty concerning components or accessories not manufactured by the Seller, but will pass on to the Purchaser all warranties of manufacturers of such components.

THIS WARRANTY IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED OR STATUTORY, AND IS STRICTLY LIMITED TO THE TERMS HEREOF. SELLER SPECIFICALLY DISCLAIMS ANY WARRANTY OF MERCHANTABILITY OR OF FITNESS FOR A PARTICULAR PURPOSE.

TRIGARD spare sensors Warranty

MSA Instrument Warranty

1. Warranty- Seller warrants that this product will be free from mechanical defect or faulty workmanship for a period of eighteen (18) months from date of shipment or one (1) year from installation, whichever occurs first, provided it is maintained and used in accordance with Seller's instructions and/or recommendations. This warranty does not apply to expendable or consumable parts whose normal life expectancy is less than one (1) year such as, but not limited to, non-rechargeable batteries, sensor elements, filter, lamps, fuses etc. The Seller shall be released from all obligations under this warranty in the event repairs or modifications are made by persons other than its own or authorized service personnel or if the warranty claim results from physical abuse or misuse of the product. No agent, employee or representative of the Seller has any authority to bind the Seller to any affirmation, representation or warranty concerning the goods sold under this contract. Seller makes no warranty concerning components or accessories not manufactured by the Seller, but will pass on to the Purchaser all warranties of manufacturers of such components. THIS WARRANTY IS IN LIEU OF ALL OTHER

   WARRANTIES, EXPRESSED, IMPLIED OR STATUTORY, AND IS STRICTLY LIMITED TO THE TERMS HEREOF. SELLER SPECIFICALLY DISCLAIMS ANY WARRANTY OF MERCHANTABILITY OR OF FITNESS FOR A PARTICULAR PURPOSE.

CERTIFICATION RECORD

The company named below has been authorized by CSA International to represent the products listed in this record as "CSA Certified" and to affix the CSA Mark to these products according to the terms and conditions of the CSA Service Agreement and applicable CSA program requirements (including additional Markings).

File No: 110537_0_000

Class No: 3211 09 INDUSTRIAL CONTROL EQUIPMENT Special (Custom) Industrial Control Assemblies

SUBMITTOR

4535527
Les Entreprises Electriques L.M. Inc.
3006 Ste Catherine Est
Montreal, QC H1W 2B8
Canada

FACTORIES

4535527
Les Entreprises Electriques L.M. Inc.
3006 Ste Catherine Est
Montreal, QC H1W 2B8
Canada

4883631
Les Entreprises Electriques LM
1450 rue Omer Ravary
Montreal, QC H1W 0A8
Canada

June 5, 2015 (Replaces: April 27, 2005)

- Special industrial control assemblies, enclosed, 600V ac max, 1- or 3-ph, 60Hz, 1200A max input; outputs: 600V ac max., 1- or 3-ph, 1200hp, 1200A, 60Hz, consisting of CSA certified components such as Type 1, 3, 3R, 4, 4X, 12 or open Type enclosures, fuses and circuit breakers, motor starters, contactors, ac/dc drives, programmable logic controllers, transformers, control relays and timers, auxiliary devices.

  - Full voltage and reduced voltage motor starter: 1200hp.
  - Relay-PLC controllers

Note: Open-type equipment is certified only for use in complete assemblies where the suitability of the combination is to be determined.

/ds

Certificat de Conformité

Certificat 1621047 **Contrat Principal:** 163905

Projet: 2809532 **Date d'émission:** 5 juin 2015

Émis à: **Les Entreprises Electriques L.M. Inc.**
3006 Ste Catherine Est
Montreal, QC H1W 2B8
Canada
Attention: Alexandre Fortin

Les produits énumérés ci-dessous peuvent porter la marque CSA tel qu'illustré

Pierre-Luc Avoine

Émis par: Pierre-Luc Avoine, ing.

PRODUITS

CLASSE 3211 09 - APPAREILLAGE INDUSTRIEL DE COMMANDE – assemblages spéciaux de contrôle industriel (sur commande)

Ensemble de commande spécial industriel, 600Vca/cc max., 1- ou 3ph, 60Hz, 1200A max à l'entrée; sortie: 600Vca/cc max., 1- ou 3ph, 60Hz, 1200A, 1200hp max., sous coffret CSA de type 1, 3, 4 ou 12 ou de type ouvert, comprenant des composants ordinaires fixes certifiés, notamment des disjoncteurs, des interrupteurs, des fusibles, des transformateurs, des contacteurs, des relais, des démarreurs, des minuteries et d'autres dispositifs auxiliaires.

- Commandes de moteur à tension pleine, 1200hp max.
- Commandes de moteur à tension réduite, 1200hp max.
- Panneaux de contrôles à automates programmables.

Note: Un ensemble de commande type ouvert (sans coffret) est certifié comme composant sujet à réévaluation dans l'application finale.

EXIGENCES PERTINENTES

CSA-C22.2 No. 14-13 - Appareillage industriel de commande

Endress+Hauser

People for Process Automation

Flow Calibration with Adjustment

30446576-4560784


3003322751	FCP-7.1.B
Purchase order number	Calibration rig
CA-3006072067-60 / Endress+Hauser Flowtec	2489.763 us.gal/min (≙ 100%)
Order N°/Manufacturer	Calibrated full scale
5W4C2H-CKL7/0	Service interface
Order code	Calibrated output
Promag W 400 8"	1.0819
Sensor/Transmitter	Calibration factor
N9035816000	1
Serial N°	Zero point
FQIT-01-150	77.4 °F
Tag N°	Water temperature

Flow [%]	Flow [us.gal/min]	Duration [s]	V target [us.gal]	V meas. [us.gal]	Δ o.r.* [%]	Outp.** [mA]
40.3	1003.41	50.1	837.280	837.098	-0.02	10.45
40.3	1003.38	50.1	837.125	837.240	0.01	10.45
101.0	2513.83	50.1	2097.69	2097.83	0.01	20.16
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–

*o.r.: of reading

**Calculated value (4 - 20 mA)

Measured error % o.r.



For detailed data concerning output specifications of the unit under test, see Technical Information (TI), chapter Performance characteristics.

The calibration is traceable to the N.I.S.T. through standards certified at preset intervals.

Endress+Hauser Flowtec operates ISO/IEC 17025 accredited calibration facilities in Reinach (CH), Cernay (FR), Greenwood (USA), Aurangabad (IN), Suzhou (CN) and Itatiba (BR).

Robert J. Kizzee

09-12-2018

Date of calibration

Joe Kizzee

Operator

Endress+Hauser Flowtec, Division USA
2330 Endress Place
Greenwood, IN 46143

Certified acc. to
ISO 9001, Reg.-N° 030502.2
ISO 14001, Reg.-N° EMS561046

Endress+Hauser

People for Process Automation

Flow Calibration with Adjustment

35007983-4800308


3003322751	FCP-17.A (Air)
Purchase order number	Calibration rig
3006184668-150 / Endress+Hauser Flowtec	3750.0 kg/h (≙ 100%)
Order N°/Manufacturer	Calibrated full scale
65I-20AA0AD5RABACA	Service interface
Order code	Calibrated output
t-mass 65 I	1.165 bar a
Transmitter/Sensor	Ambient pressure
P40A0A16000	7.1 %
Serial N°	Ambient relative humidity
FQIT-02-152	22.3 °C
Tag N°	Ambient temperature

Flow [%]	Flow target [kg/h]	Flow meas. [kg/h]	Pressure [bar a]	Temp.** [°C]	Δ o.r.* [%]	Outp.** [mA]
10.0	374.692	376.573	1.173	21.9	0.50	5.61
31.9	1197.67	1198.67	1.170	22.0	0.08	9.11
89.7	3364.24	3359.87	1.153	21.2	-0.13	18.34
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–

*o.r.: of reading

**Calculated value

Measured error % o.r.



For detailed data concerning output specifications of the unit under test, see Technical Information (TI), chapter Performance characteristics.

Traceability to the national standard for all test instruments used for the calibration is guaranteed.

Endress+Hauser Flowtec operates ISO/IEC 17025 accredited calibration facilities in Reinach (CH), Cernay (FR), Greenwood (USA), Aurangabad (IN), Suzhou (CN) and Itatiba (BR).

04-26-2019

Date of calibration

Derek Martin

Operator

Endress+Hauser Flowtec, Division USA
2330 Endress Place
Greenwood, IN 46143

Certified acc. to
ISO 9001, Reg.-N° 030502.2
ISO 14001, Reg.-N° EMS561046

Endress+Hauser

People for Process Automation

Flow Calibration with Adjustment

35007982-4800316


3003322751	FCP-17.A (Air)
Purchase order number	Calibration rig
3006184668-150 / Endress+Hauser Flowtec	3750.0 kg/h (≙ 100%)
Order N°/Manufacturer	Calibrated full scale
65I-20AA0AD5RABACA	Service interface
Order code	Calibrated output
t-mass 65 I	1.164 bar a
Transmitter/Sensor	Ambient pressure
P40A0C16000	7.8 %
Serial N°	Ambient relative humidity
FQIT-02-156	21.7 °C
Tag N°	Ambient temperature

Flow [%]	Flow target [kg/h]	Flow meas. [kg/h]	Pressure [bar a]	Temp.** [°C]	Δ o.r.* [%]	Outp.** [mA]
10.0	375.733	378.490	1.172	21.3	0.73	5.61
32.0	1199.59	1200.42	1.169	21.3	0.07	9.12
89.4	3351.31	3354.23	1.152	20.7	0.09	18.31
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–

*o.r.: of reading

**Calculated value

Measured error % o.r.



For detailed data concerning output specifications of the unit under test, see Technical Information (TI), chapter Performance characteristics.

Traceability to the national standard for all test instruments used for the calibration is guaranteed.

Endress+Hauser Flowtec operates ISO/IEC 17025 accredited calibration facilities in Reinach (CH), Cernay (FR), Greenwood (USA), Aurangabad (IN), Suzhou (CN) and Itatiba (BR).

04-26-2019

Date of calibration

Endress+Hauser Flowtec, Division USA
2330 Endress Place
Greenwood, IN 46143

Derek Martin

Operator

Certified acc. to
ISO 9001, Reg.-N° 030502.2
ISO 14001, Reg.-N° EMS561046

Endress+Hauser
People for Process Automation

Flow Calibration with Adjustment

30469876-4799699


3003322751	FCP-9.B
Purchase order number	Calibration rig
CA-3006184668-130 / Endress+Hauser Flowtec	7624.899 us.gal/min (≙ 100%)
Order N°/Manufacturer	Calibrated full scale
5W4C3F-4497/0	Service interface
Order code	Calibrated output
Promag W 400 14"	0.87138
Sensor/Transmitter	Calibration factor
P40A0216000	5.7
Serial N°	Zero point
FQIT-02-328	74.3 °F
Tag N°	Water temperature

Flow [%]	Flow [us.gal/min]	Duration [s]	V target [us.gal]	V meas. [us.gal]	Δ o.r.* [%]	Outp.** [mA]
40.2	3061.61	75.1	3830.35	3829.88	-0.01	10.42
40.2	3062.04	75.1	3830.92	3831.36	0.01	10.43
100.7	7675.58	75.1	9602.34	9606.07	0.04	20.11
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–

*o.r.: of reading

**Calculated value (4 - 20 mA)

Measured error % o.r.



For detailed data concerning output specifications of the unit under test, see Technical Information (TI), chapter Performance characteristics.

The calibration is traceable to the N.I.S.T. through standards certified at preset intervals.

Endress+Hauser Flowtec operates ISO/IEC 17025 accredited calibration facilities in Reinach (CH), Cernay (FR), Greenwood (USA), Aurangabad (IN), Suzhou (CN) and Itatiba (BR).

05-14-2019
Date of calibration

M. Horn
Operator

Endress+Hauser Flowtec, Division USA
2330 Endress Place
Greenwood, IN 46143

Certified acc. to
ISO 9001, Reg.-N° 030502.2
ISO 14001, Reg.-N° EMS561046

Endress+Hauser

People for Process Automation

Flow Calibration with Adjustment

30469175-4806060


3003322751	FCP-8.B
Purchase order number	Calibration rig
CA-3006184668-140 / Endress+Hauser Flowtec	398.3621 us.gal/min (≙ 100%)
Order N°/Manufacturer	Calibrated full scale
5W4C80-9F26/0	Service interface
Order code	Calibrated output
Promag W 400 3"	0.93141
Sensor/Transmitter	Calibration factor
P5004D16000	5.6
Serial N°	Zero point
FQIT-03-695	74.7 °F
Tag N°	Water temperature

Flow [%]	Flow [us.gal/min]	Duration [s]	V target [us.gal]	V meas. [us.gal]	Δ o.r.* [%]	Outp.** [mA]
40.0	159.499	35.1	93.215	93.201	-0.02	10.41
40.3	160.526	35.0	93.761	93.776	0.02	10.45
100.5	400.295	35.1	233.922	233.847	-0.03	20.07
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–

*o.r.: of reading

**Calculated value (4 - 20 mA)

Measured error % o.r.



For detailed data concerning output specifications of the unit under test, see Technical Information (TI), chapter Performance characteristics.

The calibration is traceable to the N.I.S.T. through standards certified at preset intervals.

Endress+Hauser Flowtec operates ISO/IEC 17025 accredited calibration facilities in Reinach (CH), Cernay (FR), Greenwood (USA), Aurangabad (IN), Suzhou (CN) and Itatiba (BR).

Robert J. Kizzee

05-06-2019	Joe Kizzee
Date of calibration	Operator
Endress+Hauser Flowtec, Division USA 2330 Endress Place Greenwood, IN 46143	Certified acc. to ISO 9001, Reg.-N° 030502.2 ISO 14001, Reg.-N° EMS561046

Endress+Hauser

People for Process Automation

Flow Calibration with Adjustment

30469794-4812066


3003322751	FCP-6.C
Purchase order number	Calibration rig
CA-3006188887-7 / Endress+Hauser Flowtec	3.983614 us.gal/min (≙ 100%)
Order N°/Manufacturer	Calibrated full scale
50H08-HAAA1RA0BAAD+	Service interface
Order code	Calibrated output
PROMAG 50 H DN08 / 5/16"	1.0317
Transmitter/Sensor	Calibration factor
P502E916000	-3
Serial N°	Zero point
FQIT-04-798	72.7 °F
Tag N°	Water temperature

Flow [%]	Flow [us.gal/min]	Duration [s]	V target [us.gal]	V meas. [us.gal]	Δ o.r.* [%]	Outp.** [mA]
40.3	1.6052	60.0	1.6063	1.6078	0.09	10.45
100.6	4.0059	85.1	5.6850	5.6846	-0.01	20.09
100.7	4.0100	85.1	5.6905	5.6907	0.00	20.11
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–

*o.r.: of reading

**Calculated value (4 - 20 mA)

Measured error % o.r.



For detailed data concerning output specifications of the unit under test, see Technical Information (TI), chapter Performance characteristics.

The calibration is traceable to the N.I.S.T. through standards certified at preset intervals.

Endress+Hauser Flowtec operates ISO/IEC 17025 accredited calibration facilities in Reinach (CH), Cernay (FR), Greenwood (USA), Aurangabad (IN), Suzhou (CN) and Itatiba (BR).

05-13-2019

Date of calibration

Davion Nash

Operator

Endress+Hauser Flowtec, Division USA
2330 Endress Place
Greenwood, IN 46143

Certified acc. to
ISO 9001, Reg.-N° 030502.2
ISO 14001, Reg.-N° EMS561046

Endress+Hauser

People for Process Automation

Flow Calibration with Adjustment

30469713-4812068


3003322751	FCP-6.C
Purchase order number	Calibration rig
CA-3006188887-7 / Endress+Hauser Flowtec	3.983614 us.gal/min (≙ 100%)
Order N°/Manufacturer	Calibrated full scale
50H08-HAAA1RA0BAAD+	Service interface
Order code	Calibrated output
PROMAG 50 H DN08 / 5/16"	1.0255
Transmitter/Sensor	Calibration factor
P502EB16000	1
Serial N°	Zero point
FQIT-04-799	77.6 °F
Tag N°	Water temperature

Flow [%]	Flow [us.gal/min]	Duration [s]	V target [us.gal]	V meas. [us.gal]	Δ o.r.* [%]	Outp.** [mA]
40.3	1.6066	60.1	1.6082	1.6090	0.05	10.46
99.5	3.9645	85.1	5.6247	5.6241	-0.01	19.92
99.6	3.9677	85.1	5.6305	5.6310	0.01	19.94
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–

*o.r.: of reading

**Calculated value (4 - 20 mA)

Measured error % o.r.



For detailed data concerning output specifications of the unit under test, see Technical Information (TI), chapter Performance characteristics.

The calibration is traceable to the N.I.S.T. through standards certified at preset intervals.

Endress+Hauser Flowtec operates ISO/IEC 17025 accredited calibration facilities in Reinach (CH), Cernay (FR), Greenwood (USA), Aurangabad (IN), Suzhou (CN) and Itatiba (BR).

Robert J. Kizzee

05-10-2019

Date of calibration

Joe Kizzee

Operator

Endress+Hauser Flowtec, Division USA
2330 Endress Place
Greenwood, IN 46143

Certified acc. to
ISO 9001, Reg.-N° 030502.2
ISO 14001, Reg.-N° EMS561046

Endress+Hauser

People for Process Automation

Flow Calibration with Adjustment

30469710-4812067


3003322751	FCP-6.C
Purchase order number	Calibration rig
CA-3006188887-25 / Endress+Hauser Flowtec	14.00492 us.gal/min (≙ 100%)
Order N°/Manufacturer	Calibrated full scale
50H15-HAAA1RA0BAAD+	Service interface
Order code	Calibrated output
PROMAG 50 H DN15 / 1/2"	1.1349
Transmitter/Sensor	Calibration factor
P502EA16000	-3
Serial N°	Zero point
FQIT-04-999	77.7 °F
Tag N°	Water temperature

Flow [%]	Flow [us.gal/min]	Duration [s]	V target [us.gal]	V meas. [us.gal]	Δ o.r.* [%]	Outp.** [mA]
40.2	5.6224	60.1	5.6353	5.6369	0.03	10.43
40.2	5.6252	60.1	5.6388	5.6375	-0.02	10.43
101.1	14.155	60.1	14.189	14.191	0.01	20.17
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–
–	–	–	–	–	–	–

*o.r.: of reading

**Calculated value (4 - 20 mA)

Measured error % o.r.



For detailed data concerning output specifications of the unit under test, see Technical Information (TI), chapter Performance characteristics.

The calibration is traceable to the N.I.S.T. through standards certified at preset intervals.

Endress+Hauser Flowtec operates ISO/IEC 17025 accredited calibration facilities in Reinach (CH), Cernay (FR), Greenwood (USA), Aurangabad (IN), Suzhou (CN) and Itatiba (BR).

Robert J. Kizzee

05-10-2019

Date of calibration

Joe Kizzee

Operator

Endress+Hauser Flowtec, Division USA
2330 Endress Place
Greenwood, IN 46143

Certified acc. to
ISO 9001, Reg.-N° 030502.2
ISO 14001, Reg.-N° EMS561046

Endress+Hauser SE+Co.
2340 Endress Place
Greenwood. In. 46143-9772

Final Inspection Report / Endprüfprotokoll

The manufacturer confirms that all measuring equipment used to assure the quality of the products has been calibrated and is traceable (e.g. DKD/DAkkS, NIST, NABL...) to national or international standards.

Der Hersteller bestätigt, dass die zu Qualitätsprüfungen des Erzeugnisses eingesetzten Messmittel gültig kalibriert waren und auf nationale (z.B. DKD/DAkkS, NIST, NABL...) bzw. internationale Normale rückführbar sind.

Prosonic S

TAG number	Messstellen-Nummer	LIT-03-111
Order code	Bestellcode	FMU90-N11CA111AA1A
Serial number	Seriennummer	P50043150E6
Extended order code	Erweiterter Bestellcode	FMU90-N11CA111AA1A
Output type	Ausgang	4 ... 20 mA HART
Software version	Softwareversion	02.01.06-EU2

Norclair Inc.

Customer order number	Auftragsnummer des Kunden	P1039-01001
E+H sales order number	E+H Auftragsnummer	3019431158 000110
Internal order number	Interne Auftragsnummer	3003322751/0110

Ambient temperature / Umgebungs- Temperatur

Test step	Testschritt	Test result	Testergebnisse
Sensor functionality	Sensorfunktionalität	Passed	Bestanden
HART and current output	HART- und Stromausgänge	Passed	Bestanden
Relay output(s)	Relaisausgang bzw. -ausgänge	Passed	Bestanden
Display and operation	Display und Vorortbedienung	Passed	Bestanden
HV test	Hochspannungstest	Passed	Bestanden

We confirm that all tests, according to the Quality Plan (QP), have been performed successfully.

Wir bestätigen, dass alle Tests aus dem Qualitätsplan (QP), erfolgreich durchgeführt wurden.

At the time of verification, the measuring points of the device indicated above were in compliance to the published valid technical specification (TI).
TI00397F

Das Gerät entsprach zum Zeitpunkt der Prüfung an den aufgeführten Messpunkten den gültigen technischen Spezifikationen (TI).

This document was generated electronically and is valid without signature.

Dieses Dokument wurde elektronisch erzeugt und ist ohne Unterschrift gültig.

Date of inspection / Prüfdatum 13. May 2019

– End of document –
– Ende des Dokumentes –

Endress+Hauser
People for Process Automation

Endress+Hauser SE+Co.
2340 Endress Place
Greenwood. In. 46143-9772

Final Inspection Report / Endprüfprotokoll

The manufacturer confirms that all measuring equipment used to assure the quality of the products has been calibrated and is traceable (e.g. DKD/DAkkS, NIST, NABL...) to national or international standards.

Der Hersteller bestätigt, dass die zu Qualitätsprüfungen des Erzeugnisses eingesetzten Messmittel gültig kalibriert waren und auf nationale (z.B. DKD/DAkkS, NIST, NABL...) bzw. internationale Normale rückführbar sind.

Prosonic S

TAG number	Messstellen-Nummer	LIT-03-121
Order code	Bestellcode	FMU90-N11CA111AA1A
Serial number	Seriennummer	P50044150E6
Extended order code	Erweiterter Bestellcode	FMU90-N11CA111AA1A
Output type	Ausgang	4 ... 20 mA HART
Software version	Softwareversion	02.01.06-EU2

Norclair Inc.

Customer order number	Auftragsnummer des Kunden	P1039-01001
E+H sales order number	E+H Auftragsnummer	3019431158 000110
Internal order number	Interne Auftragsnummer	3003322751/0110

Ambient temperature / Umgebungs- Temperatur

Test step	Testschritt	Test result	Testergebnisse
Sensor functionality	Sensorfunktionalität	Passed	Bestanden
HART and current output	HART- und Stromausgänge	Passed	Bestanden
Relay output(s)	Relaisausgang bzw. -ausgänge	Passed	Bestanden
Display and operation	Display und Vorortbedienung	Passed	Bestanden
HV test	Hochspannungstest	Passed	Bestanden

We confirm that all tests, according to the Quality Plan (QP), have been performed successfully.

Wir bestätigen, dass alle Tests aus dem Qualitätsplan (QP), erfolgreich durchgeführt wurden.

At the time of verification, the measuring points of the device indicated above were in compliance to the published valid technical specification (TI).
TI00397F

Das Gerät entsprach zum Zeitpunkt der Prüfung an den aufgeführten Messpunkten den gültigen technischen Spezifikationen (TI).

This document was generated electronically and is valid without signature.

Dieses Dokument wurde elektronisch erzeugt und ist ohne Unterschrift gültig.

Date of inspection / Prüfdatum 13. May 2019

– End of document –
– Ende des Dokumentes –

Endress+Hauser
People for Process Automation

Test Report

Endress+Hauser
People for Process Automation

Final Inspection Report

Order information

Customer name	Norclair Inc.
Customer purchase order	P1039-01001
Sales order number / Item	3003322751/0160
Internal order number / Item	3019480735000160

Device information

Description	Liquiphant M FTL51
TAG	LSHH-03-112
Serial number	P5008115027
Order code	FTL51-D74V3/0
Extended order code	FTL51-UAP2BB4E5A+Z1

Additional information

Output type	FEL54; Relais DPDT 19-253 V AC/19-55 V DC
Software version	01.00.01
Ambient temperature / - humidity / - pressure	23 °C ±5 °C / 60 % rel. ±40 % rel. / 990 mbar ±30 mbar
Probe length	1380 mm

Test result

Hereby we confirm that all tests according to the Quality plan (IP00017F) have been performed successfully.

Test	Procedure number	Test description
Contract review	TS00001F	As required in ISO 9001
Incoming goods inspection	TS00003F	Verification of conformance to the specified requirements
Printed circuit boards test	TS00009F	In-circuit test and functional test
Electronic insert test	TS00008F	Automatic test: high voltage and functional test of the electronic insert
High voltage test	TS00002F	The voltage used is chosen depending on operating voltage, terminals and approvals, in accordance to the valid national / international standards
Welding inspection	TS00010F	Quality and tightness of the welding seams
Leakage test	TS00004F	Tightness test with helium
Functional test of sensor	TS00034F	Measurement and adjustment of operating frequency and phase
Calibration of sensor	TS00036F	Verification of frequency and phase of the sensor
Final check of instrument	TS00035F	Verification of switching function
Outgoing visual check	TS00006F	Visual inspection of completeness and correctness of the instrument and the markings
Logistical verification	TS00005F	Automatic verification in the delivery phase via barcode that the instrument correspond to the order
Resonant Frequency uncovered		1068.62 Hz

Hereby we confirm that all measuring equipment used to assure the quality of the products has been calibrated and is traceable to national or international standards.

Execution

Greenwood, 2019-05-14, 155435

This document was generated electronically and is valid without signature.

Endress+Hauser SE+Co.
2340 Endress Place
Greenwood. In. 46143-9772
USA
www.endress.com

Test Report

Endress+Hauser
People for Process Automation

Final Inspection Report

Order information

Customer name	Norclair Inc.
Customer purchase order	P1039-01001
Sales order number / Item	3003322751/0160
Internal order number / Item	3019480735000160

Device information

Description	Liquiphant M FTL51
TAG	LSHH-03-122
Serial number	P5008215027
Order code	FTL51-D74V3/0
Extended order code	FTL51-UAP2BB4E5A+Z1

Additional information

Output type	FEL54; Relais DPDT 19-253 V AC/19-55 V DC
Software version	01.00.01
Ambient temperature / - humidity / - pressure	23 °C ±5 °C / 60 % rel. ±40 % rel. / 990 mbar ±30 mbar
Probe length	1380 mm

Test result

Hereby we confirm that all tests according to the Quality plan (IP00017F) have been performed successfully.

Test	Procedure number	Test description
Contract review	TS00001F	As required in ISO 9001
Incoming goods inspection	TS00003F	Verification of conformance to the specified requirements
Printed circuit boards test	TS00009F	In-circuit test and functional test
Electronic insert test	TS00008F	Automatic test: high voltage and functional test of the electronic insert
High voltage test	TS00002F	The voltage used is chosen depending on operating voltage, terminals and approvals, in accordance to the valid national / international standards
Welding inspection	TS00010F	Quality and tightness of the welding seams
Leakage test	TS00004F	Tightness test with helium
Functional test of sensor	TS00034F	Measurement and adjustment of operating frequency and phase
Calibration of sensor	TS00036F	Verification of frequency and phase of the sensor
Final check of instrument	TS00035F	Verification of switching function
Outgoing visual check	TS00006F	Visual inspection of completeness and correctness of the instrument and the markings
Logistical verification	TS00005F	Automatic verification in the delivery phase via barcode that the instrument correspond to the order
Resonant Frequency uncovered		996.79 Hz

Hereby we confirm that all measuring equipment used to assure the quality of the products has been calibrated and is traceable to national or international standards.

Execution

Greenwood, 2019-05-14, 155435

This document was generated electronically and is valid without signature.

Endress+Hauser SE+Co.
2340 Endress Place
Greenwood. In. 46143-9772
USA
www.endress.com

Test Report

Endress+Hauser
People for Process Automation

Final Inspection Report

Order information

Customer name	Norclair Inc.
Customer purchase order	P1039-01001
Sales order number / Item	3003322751/0170
Internal order number / Item	3019480735000170

Device information

Description	Liquiphant M FTL51
TAG	LSLL-03-113
Serial number	P5007F15027
Order code	FTL51-D74T9/0
Extended order code	FTL51-UAP2BB4E5A+Z1

Additional information

Output type	FEL54; Relais DPDT 19-253 V AC/19-55 V DC
Software version	01.00.01
Ambient temperature / - humidity / - pressure	23 °C ±5 °C / 60 % rel. ±40 % rel. / 990 mbar ±30 mbar
Probe length	4080 mm

Test result

Hereby we confirm that all tests according to the Quality plan (IP00017F) have been performed successfully.

Test	Procedure number	Test description
Contract review	TS00001F	As required in ISO 9001
Incoming goods inspection	TS00003F	Verification of conformance to the specified requirements
Printed circuit boards test	TS00009F	In-circuit test and functional test
Electronic insert test	TS00008F	Automatic test: high voltage and functional test of the electronic insert
High voltage test	TS00002F	The voltage used is chosen depending on operating voltage, terminals and approvals, in accordance to the valid national / international standards
Welding inspection	TS00010F	Quality and tightness of the welding seams
Leakage test	TS00004F	Tightness test with helium
Functional test of sensor	TS00034F	Measurement and adjustment of operating frequency and phase
Calibration of sensor	TS00036F	Verification of frequency and phase of the sensor
Final check of instrument	TS00035F	Verification of switching function
Outgoing visual check	TS00006F	Visual inspection of completeness and correctness of the instrument and the markings
Logistical verification	TS00005F	Automatic verification in the delivery phase via barcode that the instrument correspond to the order
Resonant Frequency uncovered		1079.42 Hz

Hereby we confirm that all measuring equipment used to assure the quality of the products has been calibrated and is traceable to national or international standards.

Execution

Greenwood, 2019-05-14, 155435

This document was generated electronically and is valid without signature.

Endress+Hauser SE+Co.
2340 Endress Place
Greenwood. In. 46143-9772
USA
www.endress.com

Test Report

Endress+Hauser
People for Process Automation

Final Inspection Report

Order information

Customer name	Norclair Inc.
Customer purchase order	P1039-01001
Sales order number / Item	3003322751/0170
Internal order number / Item	3019480735000170

Device information

Description	Liquiphant M FTL51
TAG	LSLL-03-123
Serial number	P5008015027
Order code	FTL51-D74T9/0
Extended order code	FTL51-UAP2BB4E5A+Z1

Additional information

Output type	FEL54; Relais DPDT 19-253 V AC/19-55 V DC
Software version	01.00.01
Ambient temperature / - humidity / - pressure	23 °C ±5 °C / 60 % rel. ±40 % rel. / 990 mbar ±30 mbar
Probe length	4080 mm

Test result

Hereby we confirm that all tests according to the Quality plan (IP00017F) have been performed successfully.

Test	Procedure number	Test description
Contract review	TS00001F	As required in ISO 9001
Incoming goods inspection	TS00003F	Verification of conformance to the specified requirements
Printed circuit boards test	TS00009F	In-circuit test and functional test
Electronic insert test	TS00008F	Automatic test: high voltage and functional test of the electronic insert
High voltage test	TS00002F	The voltage used is chosen depending on operating voltage, terminals and approvals, in accordance to the valid national / international standards
Welding inspection	TS00010F	Quality and tightness of the welding seams
Leakage test	TS00004F	Tightness test with helium
Functional test of sensor	TS00034F	Measurement and adjustment of operating frequency and phase
Calibration of sensor	TS00036F	Verification of frequency and phase of the sensor
Final check of instrument	TS00035F	Verification of switching function
Outgoing visual check	TS00006F	Visual inspection of completeness and correctness of the instrument and the markings
Logistical verification	TS00005F	Automatic verification in the delivery phase via barcode that the instrument correspond to the order
Resonant Frequency uncovered		1077.27 Hz

Hereby we confirm that all measuring equipment used to assure the quality of the products has been calibrated and is traceable to national or international standards.

Execution

Greenwood, 2019-05-14, 155435

This document was generated electronically and is valid without signature.

Endress+Hauser SE+Co.
2340 Endress Place
Greenwood. In. 46143-9772
USA
www.endress.com

CERTIFICATE OF CALIBRATION and CONFORMANCE

MSA North America
Cranberry Plant
1000 Cranberry Woods Drive
Cranberry Township, PA 16066

724.776.8600

MANUFACTURING DATE August 08, 2018
CUSTOMER ORDER NUMBER: **PO0440370**
MSA ORDER NUMBER: **401276083**

PART NUMBER	LINE ITEM NUMBER	QUANTITY SHIPPED	DESCRIPTION
A-TRIGARD	10	6	A-TRIGARD:-A-E-0-0-16-4-00-0-00-0-0-2-0

Serial Numbers: **H18-401276083-10-001, H18-401276083-10-002, H18-401276083-10-003, H18-401276083-10-004, H18-401276083-10-005, H18-401276083-10-006**

.
The instruments referenced above were calibrated for the detection of **0 – 50 PPM Hydrogen Sulfide**, with a span setting of **40 PPM H2S** (Cylinder Lot 160-401001873-1). The calibration and testing were performed using NST traceable equipment and were in accordance with our ISO 9001 certified quality system. As specified in the instrument instructions, a calibration check must be performed on the instrument following installation. Routine calibration checks must be performed to verify that the instrument is operating properly. Failure to perform a calibration check on a routine basis with specified gas calibration equipment may result in inaccurate readings.

Conformance Statement

MSA certifies that the materials, components, and/or instruments delivered in this shipment conform to all applicable specifications. The items delivered have been processed through the appropriate approved document controlled procedures for Receiving, Manufacturing and Inspection. The materials, components, and/or instruments were inspected, tested, and calibrated, as applicable, per the associated drawings, standards requirements, and/or specifications, and were deemed acceptable by appropriate authorized personnel.

All applicable inspections, testing, and calibrations were performed using NIST traceable equipment, where available, in accordance with MSA's ISO 9001 Certified Quality System. Each material, component, and/or instrument must be installed, operated and maintained in strict accordance with its labels, cautions, warnings, instructions, and within the limitations stated in the supplied instruction manual. Routine calibration checks, equipment inspections, and applicable preventative maintenance measures must be performed to verify that the materials, components, and/or instruments are operating properly. Failure to perform these tasks on a routine basis, or suggested intervals, with specified equipment or methods, may result in inaccurate readings.

Process Certified By:

John F. Dannhardt

JOHN DANNHARDT
QUALITY ENGINEER

Calibrated By:

JK

MSA Corporate Center
1000 Cranberry Woods Drive
Cranberry Township, PA 16066
800.MSA.2222
www.MSAnet.com

CERTIFICATE OF CALIBRATION and CONFORMANCE

MSA North America
Cranberry Plant
1000 Cranberry Woods Drive
Cranberry Township, PA 16066

724.776.8600

MANUFACTURING DATE August 08, 2018
CUSTOMER ORDER NUMBER: **PO0440370**
MSA ORDER NUMBER: **401276083**

PART NUMBER	LINE ITEM NUMBER	QUANTITY SHIPPED	DESCRIPTION
A-TRIGARD	20	1	A-TRIGARD:-A-E-0-0-57-4-00-0-00-0-0-2-0

Serial Numbers: **H18-401276083-20-001**

.
The instruments referenced above were calibrated for the detection of **0 – 1000 PPM Carbon Monoxide**, with a span setting of **300 PPM CO** (Cylinder Lot 32-400636068-1). The calibration and testing were performed using NST traceable equipment and were in accordance with our ISO 9001 certified quality system. As specified in the instrument instructions, a calibration check must be performed on the instrument following installation. Routine calibration checks must be performed to verify that the instrument is operating properly. Failure to perform a calibration check on a routine basis with specified gas calibration equipment may result in inaccurate readings.

Conformance Statement

MSA certifies that the materials, components, and/or instruments delivered in this shipment conform to all applicable specifications. The items delivered have been processed through the appropriate approved document controlled procedures for Receiving, Manufacturing and Inspection. The materials, components, and/or instruments were inspected, tested, and calibrated, as applicable, per the associated drawings, standards requirements, and/or specifications, and were deemed acceptable by appropriate authorized personnel.

All applicable inspections, testing, and calibrations were performed using NIST traceable equipment, where available, in accordance with MSA's ISO 9001 Certified Quality System. Each material, component, and/or instrument must be installed, operated and maintained in strict accordance with its labels, cautions, warnings, instructions, and within the limitations stated in the supplied instruction manual. Routine calibration checks, equipment inspections, and applicable preventative maintenance measures must be performed to verify that the materials, components, and/or instruments are operating properly. Failure to perform these tasks on a routine basis, or suggested intervals, with specified equipment or methods, may result in inaccurate readings.

Process Certified By:

John F. Dannhardt

JOHN DANNHARDT
QUALITY ENGINEER

Calibrated By:

JK

MSA Corporate Center
1000 Cranberry Woods Drive
Cranberry Township, PA 16066
800.MSA.2222
www.MSAnet.com

APPENDIX H

COMMISSIONING FORMS

DIGITAL INPUTS														
#	Signal Description	PLC Tag	Terminal Strip	PLC Termination	G/N	NC/CO	COMMENTS 1	COMMENTS 2	ALARM	PRIORITY	HH	H	L	LL	RESET REQ	ALARM MESSAGE
1	Wet Well Level Indication Fault Status	XA-01-100	TS01 - 1,2	Slot 01: IN0	N				ALARM	MEDIUM					NO	Wet Well Level Indication Fault Status
2	T-01-001 Wet Well Low Low Level Alarm	LALL-01-111	TS01 - 3,4	Slot 01: IN1	G	NO			ALARM	HIGH					NO	T-01-001 Wet Well Low Low Level Alarm
3	T-01-001 Wet Well Low Level Alarm	LAL-01-112	TS01 - 5,6	Slot 01: IN2	G	NO			ALARM	MEDIUM					NO	T-01-001 Wet Well Low Level Alarm
4	T-01-001 Wet Well High Level Alarm	LAH-01-113	TS01 - 7,8	Slot 01: IN3	G	NC			ALARM	MEDIUM					NO	T-01-001 Wet Well High Level Alarm
5	T-01-001 Wet Well High High Level Alarm	LAHH-01-114	TS01 - 9,10	Slot 01: IN4	G	NC			ALARM	HIGH					NO	T-01-001 Wet Well High High Level Alarm
6	P-01-110 Run Status	YI-01-110	TS01 - 11,12	Slot 01: IN5	G	NO			-	-						
7	P-01-110 Fault Status	XA-01-110	TS01 - 13,14	Slot 01: IN6	G	NC			ALARM	MEDIUM					NO	P-01-110 Fault Status
8	P-01-110 Auto Status	HI-01-110	TS01 - 15,16	Slot 01: IN7	G	NO			ALARM	MEDIUM					NO	P-01-110 Auto Status
9	P-01-110 Motor Fault	UA-01-110	TS01 - 17,18	Slot 01: IN8	G	NO	Minicas is driving a relay, breaks the Run Signal and sends PLC Motor fault signal		ALARM	MEDIUM					NO	P-01-110 Motor Fault
10	P-01-110 ESD Triggered	HA-01-110	TS01 - 19,20	Slot 01: IN9	G	NO			ALARM	MEDIUM					NO	P-01-110 ESD Triggered
11	T-01-001 Oulet Flow Totalization Pulse	FQI-01-150	TS01 - 21,22	Slot 01: IN10	G	NO	PULSE = 100L // 200ms	NEEDS TO BE SETUP	-	-						
12	UPS Fault [FROM UPS]	XA-01-960	TS01 - 23,24	Slot 01: IN11	G	NO	SIMULATED		ALARM	MEDIUM					NO	UPS Fault [FROM UPS]
13	UPS Battery Low	EAL-01-960	TS01 - 25,26	Slot 01: IN12	G	NO			ALARM	HIGH					NO	UPS Battery Low
14	UPS On Bypass ON UPS	ES-01-960A	TS01 - 27, 28	Slot 01: IN13	G	NC			ALARM	MEDIUM					N	UPS On Bypass ON UPS
15	CPL_900 UTILITY POWER LOSS - ON BATTERY	ES-01-960B	TS01 - 29, 30	Slot 01: IN14	G	NC			ALARM	HIGH					N	CPL_900 UTILITY POWER LOSS - ON BATTERY
16	UPS Bypass Switch In Bypass Mode [ALWAYS ON]	ES-01-962	TS01 - 31, 32	Slot 01: IN15	G	NO			ALARM	MEDIUM					N	UPS Bypass Switch In Bypass Mode [ALWAYS ON]
1	P-01-120 Run Status	YI-01-120	TS02 - 1,2	Slot 02: IN0	G	NO			-	-						
2	P-01-120 Fault Status	XA-01-120	TS02 - 3,4	Slot 02: IN1	G	NC			ALARM	MEDIUM					NO	P-01-120 Fault Status
3	P-01-120 Auto Status	HI-01-120	TS02 - 5,6	Slot 02: IN2	G	NO			ALARM	MEDIUM					NO	P-01-120 Auto Status
4	P-01-120 Motor Fault	UA-01-120	TS02 - 7,8	Slot 02: IN3	G	NO	Minicas is driving a relay, breaks the Run Signal and sends PLC Motor fault signal		ALARM	MEDIUM					NO	P-01-120 Motor Fault
5	P-01-120 ESD Triggered	HA-01-120	TS02 - 9,10	Slot 02: IN4	G	NO			ALARM	MEDIUM					NO	P-01-120 ESD Triggered
6	SCRN-01-210 Run Status	YI-01-210	TS02 - 11,12	Slot 02: IN5	G				-	-						SCRN-01-210 Run Status
7	SCRN-01-210 Fault Status	XA-01-210	TS02 - 13,14	Slot 02: IN6	G				ALARM	MEDIUM						SCRN-01-210 Fault Status
8	SCRN-01-210 Level High Alarm	LAH-01-210	TS02 - 15,16	Slot 02: IN7	G				ALARM	MEDIUM						SCRN-01-210 Level High Alarm
9	SCRN-01-210 Power Loss/ESD Triggered	HA-01-210	TS02 - 17,18	Slot 02: IN8	G	NO			ALARM	MEDIUM						SCRN-01-210 Power Loss/ESD Triggered
10	Disposal Trailer Motor Valve Open Status FV-112	ZSO-01-112	TS02 - 19,20	Slot 02: IN9	G	NO			-	-						Disposal Trailer Motor Valve Open Status FV-112
11	Disposal Trailer Motor Valve Closed Status FV-112	ZSC-01-112	TS02 - 21,22	Slot 02: IN10	G	NC			-	-						Disposal Trailer Motor Valve Closed Status FV-112
12	PF-01-310 Incoming Knive Valve Open Status	ZSO-01-111	TS02 - 23,24	Slot 02: IN11	G				-	-						PF-01-310 Incoming Knive Valve Open Status
13	PF-01-310 Incoming Knive Valve Closed Status	ZSC-01-111	TS02 - 25,26	Slot 02: IN12	G				-	-						PF-01-310 Incoming Knive Valve Closed Status
14	PF-01-310 Run Status	YI-01-310	TS02 - 27, 28	Slot 02: IN13	G	NO			-	-						PF-01-310 Run Status
15	PF-01-310 Fault Status	XA-01-310	TS02 - 29, 30	Slot 02: IN14	G	NO			ALARM	MEDIUM						PF-01-310 Fault Status
16	Bypass Outflow Knife Valve Opened Status	ZSO-01-001	TS02 - 31, 32	Slot 02: IN15	G	NO			-	-						Primary Effluent Outflow Knife Valve
17	Bypass Outflow Knife Valve Closed Status	ZSC-01-001	TS02 - 33,34	Slot 02: IN16	G	NC			-	-						Primary Effluent Outflow Knife Valve
18	Headworks Lower Gas Detection 1 Fault Status	XA-01-901	TS02 - 35,36	Slot 02: IN17	G				ALARM	MEDIUM					NO	Headworks Lower Gas Detection 1 Fault Status
19	Headworks Lower Gas Detection 2 Fault Status	XA-01-902	TS02 - 37,38	Slot 02: IN18	G				ALARM	MEDIUM					NO	Headworks Lower Gas Detection 2 Fault Status
20	Headworks Upper Gas Detection 1 Fault Status	XA-01-903	TS02 - 39,40	Slot 02: IN19	G				ALARM	MEDIUM					NO	Headworks Upper Gas Detection 1 Fault Status
21	Headworks Upper Gas Detection 2 Fault Status	XA-01-904	TS02 - 41,42	Slot 02: IN20	G				ALARM	MEDIUM					NO	Headworks Upper Gas Detection 2 Fault Status
22	Disposal Trailer Motor Valve Open Status FV-01-114	ZSO-01-114	TS02 - 43,44	Slot 02: IN21	G	NO			-	-						Disposal Trailer Motor Valve Open Status FV-01-114
23	Disposal Trailer Motor Valve Closed Status FV-01-114	ZSC-01-114	TS02 - 45,46	Slot 02: IN22	G	NC			-	-						Disposal Trailer Motor Valve Closed Status FV-01-114
24	Disposal Trailer Motor Valve Switch Position HS-01-114	HS-01-114	TS02 - 47,48	Slot 02: IN23	G	NC			-	-						Disposal Trailer Motor Valve Switch Position HS-01-114
	SPARE	-	TS02 - 47,65	Slot 02: IN24-IN32	-				-	-						SPARE
1	P-01-130 Run Status	YI-01-130	TS03 - 1,2	Slot 03: IN0	G	NO			-	-						P-01-130 Run Status
2	P-01-130 Fault Status	XA-01-130	TS03 - 3,4	Slot 03: IN1	G	NC			ALARM	MEDIUM					NO	P-01-130 Fault Status
3	P-01-130 Auto Status	HI-01-130	TS03 - 5,6	Slot 03: IN2	G	NO			-	-					NO	P-01-130 Auto Status
4	P-01-130 Motor Fault	UA-01-130	TS03 - 7,8	Slot 03: IN3	G	NC	Minicas is driving a relay, breaks the Run Signal and sends PLC Motor fault signal		ALARM	MEDIUM					NO	P-01-130 Motor Fault
5	P-01-130 ESD Triggered	HA-01-130	TS03 - 9,10	Slot 03: IN4	G	NO			ALARM	MEDIUM					NO	P-01-130 ESD Triggered
6	SCRN-01-220 Run Status	YI-01-220	TS03 - 11,12	Slot 03: IN5	G				-	-						SCRN-01-220 Run Status
7	SCRN-01-220 Fault Status	XA-01-220	TS03 - 13,14	Slot 03: IN6	G				ALARM	MEDIUM						SCRN-01-220 Fault Status
8	SCRN-01-220 Level High Alarm	LAH-01-220	TS03 - 15,16	Slot 03: IN7	G				ALARM	MEDIUM						SCRN-01-220 Level High Alarm
9	SCRN-01-220 Power Loss/ESD Triggered	HA-01-220	TS03 - 17,18	Slot 03: IN8	G	NO			ALARM	MEDIUM						SCRN-01-220 Power Loss/ESD Triggered
10	PF-01-320 Incoming Knive Valve Open Status	ZSO-01-121	TS03 - 19,20	Slot 03: IN9	G	NO			-	-						PF-01-320 Incoming Knive Valve Open Status
11	PF-01-320 Incoming Knive Valve Closed Status	ZSC-01-121	TS03 - 21,22	Slot 03: IN10	G	NC			-	-						PF-01-320 Incoming Knive Valve Closed Status
12	PF-01-320 Run Status	YI-01-320	TS03 - 23,24	Slot 03: IN11	G	NO		TROJEN	-	-						PF-01-320 Run Status
13	PF-01-320 Fault Status	XA-01-320	TS03 - 25,26	Slot 03: IN12	G	NO		TROJEN	ALARM	MEDIUM						PF-01-320 Fault Status
14	PLC-900 DC Power Supply #1 - DC Voltage Fault	XA-02-970	TS03 - 27,28	Slot 03: IN13	G	NC			ALARM	MEDIUM					NO	PLC-900 DC Power Supply #1 - DC Voltage Fault
15	PLC-900 DC Power Supply #2 - DC Voltage Fault	XA-02-971	TS03 - 29,30	Slot 03: IN14	G	NC			ALARM	MEDIUM					NO	PLC-900 DC Power Supply #2 - DC Voltage Fault
16	PLC -901 Surge Protection Device - Surge Indication	XA-02-900	TS03 - 31,32	Slot 03: IN15	N		CONTACT CARD NOT INSTALLED		ALARM	MEDIUM						PLC -901 Surge Protection Device - Surge Indication
17	SPARE		TS03 - 33,34	Slot 03: IN16	-		DUPLICATE DELETED	UPS Bypass Switch In Bypass Mode [DELETED]	-	-						UPS Bypass Switch In Bypass Mode [DELETED]
18			TS03 - 35,36	Slot 03: IN17	-		Panel A Feeder Breaker Status Indication	EAL-02-810	-	-						Panel A Feeder Breaker Status Indication

I/O CHECK COMPLETION STATUS		
DELAYED	0	
RFI	0	
G	106	
N	2	
Total [Without DELAYED & RFI]	108	98.15%
Total [With DELAYED & RFI]	108	100.00%

DIGITAL INPUTS									
#	Signal Description	PLC Tag	Terminal Strip	PLC Termination	G/N	NC/CO	COMMENTS 1	COMMENTS 2	COMMENTS 3
1	Spare		TS1 1,2	Slot 01: IN0	-		Duplicate Deleted	Process Aeration Blower Incoming Pressure Alarm	PAL_02_130
2	B02110 Run Status	YI_02_110	TS1 3,4	Slot 01: IN1	G	NO			
3	B02110 Fault Status	XA_02_110	TS1 5,6	Slot 01: IN2	G	NC			
4	B02110 Auto Status	HI_02_110	TS1 7,8	Slot 01: IN3	G	NO			
5	B02110 Motor Fault Status	UA_02_110	TS1 9,10	Slot 01: IN4	G	NC	WIRE IN PANEL BUT NO MOTOR FAULT IN VFD	B02110 Motor Fault	UA_02_110
6	B02110 Auto Status	HA_02_110	TS1 11,12	Slot 01: IN5	G	NC	NO ESD INSTALLED	B02110 ESD Triggered	HA_02_110
7	Spare		TS1 13,14	Slot 01: IN6	-		F02115 Run Status	YI_02_115	DELETED
8	Spare		TS1 15,16	Slot 01: IN7	-		F02115 Fault Status	XA_02_115	DELETED
9	Spare		TS1 17,18	Slot 01: IN8	-		F02115 Auto Status	HI_02_115	DELETED
10	Process Aeration Blower B02110 High Pressure Switch	PSH_02_118	TS1 19,20	Slot 01: IN9	G	NC	NOT INTERLOCKED WITH VFD		
11	Process Aeration Blower B02110 Low Pressure Switch	PAL_02_108	TS1 21,22	Slot 01: IN10	G	NO	NOT INTERLOCKED WITH VFD		
12	Process Aeration Blower B02110 High Temp Switch	TSH_02_180	TS1 23,24	Slot 01: IN11	G	NC	NOT INTERLOCKED WITH VFD		
13	Spare		TS1 25,26	Slot 01: IN12	-		VALVES DO NOT HAVE FAULT	Process Air MBBR 2 FV02150 Fault Status	XA_02_150
14	Process Air MBBR 2 FV02150 Auto Status	HI_02_150	TS1 27,28	Slot 01: IN13	G	NC			
15	Process Air MBBR 2 FQIT02152 Flow Totalization Pulse	FQI_02_152	TS1 29,30	Slot 01: IN14	G	NO	1M3 PER PULSE		
16	MBBR 1 Inlet Knife Valve Open Status	ZSO_02_211	TS1 31,32	Slot 01: IN15	G	NO			
17	MBBR 1 Inlet Knife Valve Closed Status	ZSC_02_211	TS1 33,34	Slot 01: IN16	G	NC			
18	MBBR 2 Inlet Knife Valve Open Status	ZSO_02_221	TS1 35,36	Slot 01: IN17	G	NO			
19	MBBR 2 Inlet Knife Valve Closed Status	ZSC_02_221	TS1 37,38	Slot 01: IN18	G	NC			
20	MBBR 1 Cell 11 Gas Analyzer Fault Status	XA_02_211	TS1 39,40	Slot 01: IN19	G	NO			
21	MBBR 1 Cell 11 High Level Alarm	LAH_02_213	TS1 41,42	Slot 01: IN20	G	NC			
22	MBBR 1 Cell 12 Gas Analyzer Fault Status	XA_02_212	TS1 43,44	Slot 01: IN21	G	NO			
23	MBBR 1 Cell 12 High Level Alarm	LAH_02_214	TS1 45,46	Slot 01: IN22	G	NC			
24	MBBR 1 Cell 12 H2S Gas Detection Fault Status	XA_02_909	TS1 47,48	Slot 01: IN23	G	NC			
25	MBBR H2S Gas Detection Fault Status	XA_02_907	TS1 49,50	Slot 01: IN24	G	NC			
26	Spare		TS1 51,52	Slot 01: IN25	-		Violia Panel is 120VAC output will get through ethernet	DAF #1 Run Status	YI_02_310
27	Spare		TS1 53,54	Slot 01: IN26	-		Violia Panel is 120VAC output will get through ethernet	DAF #1 Fault Status	XA_02_310
28	P04770 Run Status	YI_04_770	TS1 55,56	Slot 01: IN27	G	NO			
29	P04770 Fault Status	XA_04_770	TS1 57,58	Slot 01: IN28	G	NC			
30	P04770 Auto Status	HI_04_770	TS1 59,60	Slot 01: IN29	G	NO			
31	P04770 Motor Fault	UA_04_770	TS1 61,62	Slot 01: IN30	G	NO			
32	P04770 ESD Triggered	HA_04_770	TS1 63,64	Slot 01: IN31	G	NC			
1	B02120 Run Status	YI_02_120	TS2 1,2	Slot 02: IN0	G	NO			
2	B02120 Fault Status	XA_02_120	TS2 3,4	Slot 02: IN1	G	NC			
3	B02120 Auto Status	HI_02_120	TS2 5,6	Slot 02: IN2	G	NO			
4	B02120 Motor Fault Status	UA_02_120	TS2 7,8	Slot 02: IN3	G	NC	WIRE IN PANEL BUT NO MOTOR FAULT IN VFD	B02120 Motor Fault	UA_02_120
5	B02120 Auto Status	HA_02_120	TS2 9,10	Slot 02: IN4	G	NC	NO ESD INSTALLED	B02120 ESD Triggered	HA_A02_120
6	Spare		TS2 11,12	Slot 02: IN5	-		F02125 Run Status	YI_02_125	Deleted
7	Spare		TS2 13,14	Slot 02: IN6	-		F02125 Fault Status	XA_02_125	Deleted
8	Spare		TS2 15,16	Slot 02: IN7	-		F02125 Auto Status	HI_02_125	Deleted
9	Process Aeration Blower B02120 High Pressure Switch	PAH_02_128	TS2 17,18	Slot 02: IN8	G	NC	NOT INTERLOCKED WITH VFD		
10	Process Aeration Blower B02120 Low Pressure Switch	PAL_02_143	TS2 19,20	Slot 02: IN9	G	NO	NOT INTERLOCKED WITH VFD		
11	Process Aeration Blower B02120 High Temp Switch	TSH_02_185	TS2 21,22	Slot 02: IN10	G	NC	NOT INTERLOCKED WITH VFD		
12			TS2 23,24	Slot 02: IN11	-		VALVES DO NOT HAVE FAULT	Process Air MBBR 1 FV02155 Fault Status	XA_02_155
13	Process Air MBBR 1 FV02155 Auto Status	HI_02_155	TS2 25,26	Slot 02: IN12	G	NO			
14	Process Air MBBR 1 Flow Totalization Pulse	FQI_02_156	TS2 27,28	Slot 02: IN13	G	NO	1M3 PER PULSE		
15	T02220 Cell 21 Gas Analyzer Fault Status	XA_02_221	TS2 29,30	Slot 02: IN14	G	NO			
16	T02220 Cell 21 High Level Switch	LAH_02_223	TS2 31,32	Slot 02: IN15	G	NC			
17	T02220 Cell 22 Gas Analyzer Fault Status	XA_02_222	TS2 33,34	Slot 02: IN16	G	NO			
18	T02220 Cell 22 High Level Switch	LAH_02_224	TS2 35,36	Slot 02: IN17	G	NC			
19	DAF #2 H2S Gas Fault Status	XA_02_908	TS2 37,38	Slot 02: IN18	G	NC			
20	Spare		TS2 39,40	Slot 02: IN19	-		DAF #2 Run Status	XA_02_320	Violia Panel is 120VAC output will get through ethernet
21	Spare		TS2 41,42	Slot 02: IN20	-		DAF #2 Fault Status	YI_02_320	Violia Panel is 120VAC output will get through ethernet
22	DAF #1 Inlet Valve Opened Status	ZSO_02_312	TS2 43,44	Slot 02: IN21	G	NO			
23	DAF #1 Inlet Valve Closed Status	ZSC_02_312	TS2 45,46	Slot 02: IN22	G	NO			
24	Spare		TS2 47,48	Slot 02: IN23	-		T02310 DAF #1 High Level Alarm	LAH_02_330	Violia Panel is 120VAC output will get through ethernet
25	Spare		TS2 49,50	Slot 02: IN24	-		DAF #1 Thickened Water Low Level Alarm	LAL_02_333	Deleted
26	Spare		TS2 51,52	Slot 02: IN25	-		DAF #1 Thickened Water High Level Alarm	LAH_02_332	Violia Panel is 120VAC output will get through ethernet
27	Final Effluent Flow Totalization Pulse	FQI_02_328	TS2 53,54	Slot 02: IN26	G	NO	1 pulse = 100L		
28	P04780 Run Status	YI_04_780	TS2 55,56	Slot 02: IN27	G	NO			
29	P04780 Fault Status	XA_04_780	TS2 57,58	Slot 02: IN28	G	NC			
30	P04780 Auto Status	HI_04_780	TS2 59,60	Slot 02: IN29	G	NO			
31	P04780 Motor Fault	UA_04_780	TS2 61,62	Slot 02: IN30	G	NO			
32	P04780 ESD Triggered	HA_04_780	TS2 63,64	Slot 02: IN31	G	NC			
1	B02130 Run Status	YI_02_130	TS3 1,2	Slot 03: IN0	G	NO			
2	B02130 Fault Status	XA_02_130	TS3 3,4	Slot 03: IN1	G	NC			
3	B02130 Auto Status	HI_02_130	TS3 5,6	Slot 03: IN2	G	NO			
4	B02130 Motor Fault Status	UA_02_130	TS3 7,8	Slot 03: IN3	G	NC	WIRE IN PANEL BUT NO MOTOR FAULT IN VFD	B02130 Motor Fault	UA_02_130
5	B02130 Auto Status	HA_02_130	TS3 9,10	Slot 03: IN4	G	NC	NO ESD INSTALLED	B02130 ESD Triggered	HA_02_130
6	Spare		TS3 11,12	Slot 03: IN5	-		F02135 Run Status	YI_02_135	Deleted
7	Spare		TS3 13,14	Slot 03: IN6	-		F02135 Fault Status	XA_02_135	Deleted
8	Spare		TS3 15,16	Slot 03: IN7	-		F02135 Auto Status	HI_02_135	Deleted
9	Process Aeration Blower B02130 High Pressure Switch	PAH_02_138	TS3 17,18	Slot 03: IN8	G	NC	NOT INTERLOCKED WITH VFD		
10	Process Aeration Blower B02130 Low Pressure Switch	PAL_02_146	TS3 19,20	Slot 03: IN9	G	NO	NOT INTERLOCKED WITH VFD		
11	Process Aeration Blower B02130 High Temp Switch	TSH_02_190	TS3 21,22	Slot 03: IN10	G	NC	NOT INTERLOCKED WITH VFD		
12	Spare		TS3 23,24	Slot 03: IN11	-		VALVES DO NOT HAVE FAULT	Process Air TWAS FV02170 Fault Status	XA_02_170
13	Process Air TWAS FV02170 Auto Status	HI_02_170	TS3 25,26	Slot 03: IN12	G	NC	VALVES DO NOT HAVE AUTO - Engineer Required		
14	Process Air MBBR #2 FQIT02172 Flow Totalization Pulse	FQI_02_172	TS3 27,28	Slot 03: IN13	G	NO	1M3 PER PULSE		
15	DAF #2 Inlet Valve Opened Status	ZSO_02_332	TS3 29,30	Slot 03: IN14	G	NO			
16	DAF #2 Inlet Valve Closed Status	ZSC_02_332	TS3 31,32	Slot 03: IN15	G	NO			
17	Spare		TS3 33,34	Slot 03: IN16	-		T02310 DAF #2 High Level Alarm	LAH_03_342	Violia Panel is 120VAC output will get through ethernet
18	Spare		TS3 35,36	Slot 03: IN17	-		DAF #2 Thickened Water Low Level Alarm	LAL_02_343	Deleted
19	Spare		TS3 37,38	Slot 03: IN18	-		DAF #2 Thickened Water High Level Alarm	LAH_02_342	Violia Panel is 120VAC output will get through ethernet
20	Spare		TS3 39,40	Slot 03: IN19	-		Violia Panel does not produce	PDS04700 LCP Run Status	YI_04_700
21	PDS-04-700 LCP Fault Status	XA_04_700	TS3 41,42	Slot 03: IN20	G	NC			
22	PDS-04-700 LCP Low Level Alarm	LAL_04_700	TS3 43,44	Slot 03: IN21	G	NC	HIGH LEVEL WAS CHANGED TO LOW LEVEL		
23	PDS-04-700 LCP Low Pressure Alarm	PAL_04_700	TS3 45,46	Slot 03: IN22	G	NC			
24	PDS-04-700 LCP ESD Triggered	HA_04_700	TS3 47,48	Slot 03: IN23	G	NO			
25	AIT-3910 H2S Gas Detector Fault Status	XA_03_910	TS3 49,50	Slot 03: IN24	G	NO			
26	DAF #1 Polymer Flow Totalizer Pulse	FQI_04_798	TS3 51,52	Slot 03: IN25	G	NO	1 pulse = 1L / 0.001m3		
27	DAF #2 Polymer Flow Totalizer Pulse	FQI_04_799	TS3 53,54	Slot 03: IN26	G	NO	1 pulse = 1L / 0.001m3		
28	P-04-790 Run Status	YI_04_790	TS3 55,56	Slot 03: IN27	G	NO			
29	P-04-790 Fault Status	XA_04_790	TS3 57,58	Slot 03: IN28	G	NC			
30	P-04-790 Auto Status	HI_04_790	TS3 59,60	Slot 03: IN29	G	NO			
31	P-04-790 Motor Fault	UA_04_790	TS3 61,62	Slot 03: IN30	G	NO			
32	P-04-790 ESD Triggered	HA_04_790	TS3 63,64	Slot 03: IN31	G	NC			
1	P-02-610 Run Status	YI_02_610	TS4 1,2	Slot 04: IN0	G	NO			
2	P-02-610 Fault Status	XA_02_610	TS4 3,4	Slot 04: IN1	G	NC			
3	P-02-610 Auto Status	HI_02_610	TS4 5,6	Slot 04: IN2	G	NO			
4	P-02-610 Motor Fault	UA_02_610	TS4 7,8	Slot 04: IN3	G	NO			

5	P-02-610 TWAS Pump #1 ESD Triggered	HA_02_610	TS4 9,10	Slot 04: IN4	G	NC			
6	P-02-610 TWAS Pump #1 High Pressure Alarm	PAH_02_619	TS4 11,12	Slot 04: IN5	G	NC			
7	T03630 TWAS Aerated Tank #1 Level Fault Status	XA_03_111	TS4 13,14	Slot 04: IN6	G	NO			
8	T-03-630 TWAS Aerated Tank #1 High High Level	LAHH_03_112	TS4 15,16	Slot 04: IN7	G	NO			
9	T-03-630 TWAS Aerated Tank #1 Low Low Level	LALL_03_113	TS4 17,18	Slot 04: IN8	G	NO			
10	P-03-630 Run Status	YI_03_630	TS4 19,20	Slot 04: IN9	G	NO			
11	P-03-630 Fault Status	XA_03_630	TS4 21,22	Slot 04: IN10	G	NC			
12	P-03-630 Auto Status	HI_03_630	TS4 23,24	Slot 04: IN11	G	NO			
13	P-03-630 Motor Fault	UA_03_630	TS4 25,26	Slot 04: IN12	G	NO			
14	BFP-03-630 Feed Pump #1 ESD Triggered	HA_03_630	TS4 27, 28	Slot 04: IN13	G	NC			
15	BFP-03-630 Feed Pump #1 High Pressure Alarm	PAH_03_669	TS4 29, 30	Slot 04: IN14	G	NC			
16	BFP03650 Inlet Flow Totalization	FQI_03_695	TS4 31, 32	Slot 04: IN15	G	NO	1 pulse = 1L / 0.001m3		
17	BFP-03-650 Run Sludge Pump Cmd	YI_03_650	TS4 33,34	Slot 04: IN16	G	NO			
18	BFP-03-650 Fault Status	XA_03_650	TS4 35,36	Slot 04: IN17	G	NO			
19	BFP-03-650 ESD Triggered	HA_03_650	TS4 37,38	Slot 04: IN18	G	NO			
20	P-04-970 Run Status	YI_04_970	TS4 39,40	Slot 04: IN19	G	NO			
21	P-04-970 Fault Status	XA_04_970	TS4 41,42	Slot 04: IN20	G	NC			
22	P-04-970 Auto Status	HI_04_970	TS4 43,44	Slot 04: IN21	G	NO			
23	P-04-970 Motor Fault	UA_04_970	TS4 45,46	Slot 04: IN22	G	NO			
24	P-04-970 ESD Triggered	HA_04_970	TS4 47,48	Slot 04: IN23	G	NC			
25	P-04-970 High Pressure Alarm	PAH_04_987	TS4 49,50	Slot 04: IN24	G	NC			
26	BFP Polymer FQIT04999 Flow Totalizer	FQI_04_999	TS4 51,52	Slot 04: IN25	G	NO	1 pulse = 1L / 0.001m3		
27	Incoming Potable Water Flow Totalization	FQI_04_300	TS4 53,54	Slot 04: IN26	G	NO	1 pulse = .1 m3	Add AIT02801c2 because not on print	
28	AIT02905 H2S Gas Analyzer Fault Status	XA_02_905	TS4 55,56	Slot 04: IN27	G	NC			
29	AIT03906 H2S Gas Analyzer Fault Status	XA_03_906	TS4 57,58	Slot 04: IN28	G	NC			
30	AIT02801 Generator Room CO Indication	XA_02_801	TS4 59,60	Slot 04: IN29	G	NC	Add AIT02801c2 because not on print	AIT03907 H2S Gas Analyzer Fault Status duplicate	XA_03_907
31	Spare		TS4 61,62	Slot 04: IN30	-		Deleted	AIT03908 H2S Gas Analyzer Fault Status duplicate	XA_03_908
32	Spare		TS4 63,64	Slot 04: IN31	-		Deleted	AIT03909 H2S Gas Analyzer Fault Status duplicate	XA_03_909
1	P-02-620 Run Status	YI_02_620	TS5 1,2	Slot 05: IN0	G	NO			
2	P-02-620 Fault Status	XA_02_620	TS5 3,4	Slot 05: IN1	G	NC			
3	P-02-620 Auto Status	HI_02_620	TS5 5,6	Slot 05: IN2	G	NO			
4	P-02-620 Motor Fault	UA_02_620	TS5 7,8	Slot 05: IN3	G	NO			
5	P-02-620 TWAS Pump #2 ESD Triggered	HA_02_620	TS5 9,10	Slot 05: IN4	G	NC			
6	P-02-620 TWAS Pump #2 High Pressure Alarm	PAH_02_639	TS5 11,12	Slot 05: IN5	G	NC			
7	T03640 TWAS Aerated Tank #2 Level Fault Status	XA_03_121	TS5 13,14	Slot 05: IN6	G	NO			
8	T-03-640 TWAS Aerated Tank #2 High High Level	LAHH_03_122	TS5 15,16	Slot 05: IN7	G	NO	NOT CONFIRMED AT DEVICE		
9	T-03-640 TWAS Aerated Tank #2 Low Low Level	LALL_03_123	TS5 17,18	Slot 05: IN8	G	NO	NOT CONFIRMED AT DEVICE		
10	P-03-640 Run Status	YI_03_640	TS5 19,20	Slot 05: IN9	G	NO			
11	P-03-640 Fault Status	XA_03_640	TS5 21,22	Slot 05: IN10	G	NC			
12	P-03-640 Auto Status	HI_03_640	TS5 23,24	Slot 05: IN11	G	NO			
13	P-03-640 Motor Fault	UA_03_640	TS5 25,26	Slot 05: IN12	G	NO			
14	BFP-03-640 Feed Pump #1 ESD Triggered	HA_03_640	TS5 27, 28	Slot 05: IN13	G	NC			
15	BFP-03-640 Feed Pump #1 High Pressure Alarm	PAH_03_689	TS5 29, 30	Slot 05: IN14	G	NC			
16	Spare		TS5 31, 32	Slot 05: IN15	-		Violia Panel does not produce	PDS04900 LCP Run Status	YI_04_900
17	PDS-04-900 LCP Fault Status	XA_04_900	TS5 33,34	Slot 05: IN16	G	NC			
18	PDS-04-900 LCP Low Level Alarm	LAL_04_900	TS5 35,36	Slot 05: IN17	G	NC			
19	PDS-04-900 LCP ESD Triggered	HA_04_900	TS5 37,38	Slot 05: IN18	G	NC			
20	P-04-980 Run Status	YI_04_980	TS5 39,40	Slot 05: IN19	G	NO			
21	P-04-980 Fault Status	XA_04_980	TS5 41,42	Slot 05: IN20	G	NC			
22	P-04-980 Auto Status	HI_04_980	TS5 43,44	Slot 05: IN21	G	NO			
23	P-04-980 Motor Fault	UA_04_980	TS5 45,46	Slot 05: IN22	G	NO			
24	P-04-980 ESD Triggered	HA_04_980	TS5 47,48	Slot 05: IN23	G	NC			
25	P-04-980 High Pressure Alarm	PAH_04_990	TS5 49,50	Slot 05: IN24	G	NC			
26	Generator Run Status	YI_02_800	TS5 51,52	Slot 05: IN25	N		No Genset Installed		
27	Generator Fault Status	XA_02_800A	TS5 53,54	Slot 05: IN26	N		No Genset Installed		
28	Generator Auto Status	HI_02_800	TS5 55,56	Slot 05: IN27	N		No Genset Installed		
29	Generator Battery Charger Fault	XA_02_800B	TS5 57,58	Slot 05: IN28	N		No Genset Installed		
30	Generator Battery Voltage Low	EAL_02_800	TS5 59,60	Slot 05: IN29	N		No Genset Installed		
31	Generator Low Fuel Level	LAH_02_800	TS5 61,62	Slot 05: IN30	N		No Genset Installed		
32	SPARE		TS5 63,64	Slot 05: IN31	-		Deleted	AIT03909 Gas Analyzer Fault Status	XA_03_909
1	UPS (CPL901) Fault Status	XA_02_961	TS6 1,2	Slot 06: IN0	G	NO			
2	UPS (CPL901) Battery Low	EAL_02_961	TS6 3,4	Slot 06: IN1	G	NO			
3	UPS (CPL901) On Bypass	ES_02_961A	TS6 5,6	Slot 06: IN2	G	NO			
4	UPS (CPL901) On Utility	ES_02_961B	TS6 7,8	Slot 06: IN3	G	NO			
5	UPS (CPL901) On Battery	ES_02_961C	TS6 9,10	Slot 06: IN4	G	NO			
6	DC Power Supply #1 (CPL901) DC Voltage Fault Indication	XA_02_970	TS6 11,12	Slot 06: IN5	G	NC			
7	DC Power Supply #2 (CPL901) DC Voltage Fault Indication	XA_02_971	TS6 13,14	Slot 06: IN6	G	NC			
8	CPL907 Surge Protection Device Surge Indication	XA_02_900	TS6 15,16	Slot 06: IN7	N		Correct Part not installed		
9	UPS Bypass Switch (CPL901) In Bypass Mode	ES_02_961	TS6 17,18	Slot 06: IN8	G	NO			
10			TS6 19,20	Slot 06: IN9	-		Deleted		
11	Automatic Transfer Switch Utility Power Available	EY_02_802A	TS6 21,22	Slot 06: IN10	G	NO			
12	Automatic Transfer Switch Emergency Power Available	EY_02_802B	TS6 23,24	Slot 06: IN11	G	NO			
13	Automatic Transfer Switch On Utility Power Available	ES_02_802A	TS6 25,26	Slot 06: IN12	G	NO			
14	Automatic Transfer Switch On Emergency Power	ES_02_802B	TS6 27, 28	Slot 06: IN13	G	NO			
15	P-04-770 High Pressure Alarm	PAH_04_787	TS6 29, 30	Slot 06: IN14	G	NC			
16	P-04-780 High Pressure Alarm	PAH_04_793	TS6 31, 32	Slot 06: IN15	G	NC			
17	P-04-790 High Pressure Alarm	PAH_04_790	TS6 33,34	Slot 06: IN16	G	NC			
18	Air Compressor C02401 Fault Status	XA_02_401	TS6 35,36	Slot 06: IN17	G	NO			
19	Air Compressor C02402 Fault Status	XA_02_402	TS6 37,38	Slot 06: IN18	G	NO			
20	Air Compressor C02401 Run Status	YI02401	TS6 39,40	Slot 06: IN19	G	NO			
21	Air Compressor C02402 Run Status	YI02402	TS6 41,42	Slot 06: IN20	G	NO			
22	SPARE		TS6 43,44	Slot 06: IN21	-				
23	SPARE		TS6 45,46	Slot 06: IN22	-				
24	SPARE		TS6 47,48	Slot 06: IN23	-				
25	SPARE		TS6 49,50	Slot 06: IN24	-				
26	SPARE		TS6 51,52	Slot 06: IN25	-				
19	SPARE		TS6 53,54	Slot 06: IN26	-				
20	SPARE		TS6 55,56	Slot 06: IN27	-				
21	SPARE		TS6 57,58	Slot 06: IN28	-				
22	SPARE		TS6 59,60	Slot 06: IN29	-				
23	SPARE		TS6 61,62	Slot 06: IN30	-				
24	SPARE		TS6 63,64	Slot 06: IN31	-				
							RELAY OUTPUTS		
#	**Signal Description**	**PLC Tag**	**Terminal Strip**	**PLC Termination**	**G/N**	**NC/CO**	**COMMENTS 1**	**COMMENTS 2**	**COMMENTS 3**
1	B02110 Run Command	YC_02_110	TS7 1,2,3	Slot 07: DO0	G	NO			
2	Sludge Pump Running Signal to BFP		TS7 4,5,6	Slot 07: DO1	-		Deleted	F02115 Run Command	YC_02_115
3	T02210 Primary Effluent Outflow Knife Valve Close Command	ZCC_02_211	TS7 7,8,9	Slot 07: DO2	G	NO			
4	BAD OUTPUT		TS7 10,11,12	Slot 07: DO3	-		Contractor Blew Output		
5	T02310 Mixed Liqour BFV Open Command	ZCC_02_312	TS7 13,14,15	Slot 07: DO4	G	NO			
6	T02310 Mixed Liqour BFV Open Command	ZCO_02_312	TS7 16,17,18	Slot 07: DO5	G	NO			
7	P-04-770 Run Command	YC_04_770	TS7 19,20,21	Slot 07: DO6	G	NO	**NO VFD**		
8	P02610 Run Command	YC_02_610	TS7 22,23,24	Slot 07: DO7	G	NO			

9	P03630 Run Command	YC_03_630	TS7 25,26,27	Slot 07: DO8	G	NO			
10	P-04-970 Run Command	YC_04_970	TS7 28,29,30	Slot 07: DO9	G	NO	NO VFD		
11	T02310 Mixed Liqour BFV Open Command	ZCO_02_312	TS7 31,32,33	Slot 07: DO10	G	NO	deleted	Process Aeration Return Solenoid Valve Open Command	ZCO_02_180
12	Lower Secondary Treatment Alarm Horn #1 Gas Alarm	US_02_942	TS7 34,35,36	Slot 07: DO11	G	NO			
13	Upper Secondary Treatment Alarm Horn #1 Gas Alarm	US_02_943	TS7 37,38,39	Slot 07: DO12	G	NO			
14	Upper Secondary Treatment Alarm Horn #2 Gas Alarm	US_02_944	TS7 40,41,42	Slot 07: DO13	G	NO			
15	SPARE		TS7 43,44,45	Slot 07: DO14	-				
16	SPARE		TS7 46,47,48	Slot 07: DO15	-				
1	B02120 Run Command	YC_02_120	TS8 1,2,3	Slot 08: DO0	G	NO			
2	SPARE		TS8 4,5,6	Slot 08: DO1	-		Deleted	F02125 Run Command	YC_02_125
3	T02220 Primary Effluent Outflow Knife Valve Close Command	ZCC_02_221	TS8 7,8,9	Slot 08: DO2	G	NO			
4	BAD OUTPUT		TS8 10,11,12	Slot 08: DO3	-	NO	Contractor Blew Output		
5	T02320 Mixed Liqour BFV Close Command	ZCC_02_332	TS8 13,14,15	Slot 08: DO4	G	NO			
6	T02320 Mixed Liqour BFV Open Command	ZCO_02_332	TS8 16,17,18	Slot 08: DO5	G	NO			
7	P-04-780 Run Command	YC_04_780	TS8 19,20,21	Slot 08: DO6	G	NO	NO VFD		
8	P02620 Run Command	YC_02_620	TS8 22,23,24	Slot 08: DO7	G	NO			
9	P03640 Run Command	YC_03_640	TS8 25,26,27	Slot 08: DO8	G	NO			
10	P-04-980 Run Command	YC_04_980	TS8 28,29,30	Slot 08: DO9	G	NO	NO VFD		
11	BFP Polymer Dosing Solenoid Valve Open Command	ZCO_04_970	TS8 31,32,33	Slot 08: DO10	G	NO	Spring Close		
12	T02220 Primary Effluent Outflow Knife Valve Open Command	ZCO_02_221	TS8 34,35,36	Slot 08: DO11	G		Deleted	Primary Effluent Knife Valve Open Command	ZCO_02_221
13	Lower Secondary Treatment Beacons H2S Alarm	US_02_922	TS8 37,38,39	Slot 08: DO12	G	NO			
14	Upper Secondary Treatment Beacons H2S Alarm	US_02_923	TS8 40,41,42	Slot 08: DO13	G	NO			
15	SPARE		TS8 43,44,45	Slot 08: DO14	-				
16	SPARE		TS8 46,47,48	Slot 08: DO15	-				
1	B02130 Run Command	YC_02_130	TS9 1,2,3	Slot 09: DO0	G	NO			
2	SPARE		TS9 4,5,6	Slot 09: DO1	-		Deleted	F02135 Run Command	YC_02_135
3	P-04-790 Run Command	YC_04_790	TS9 7,8,9	Slot 09: DO2	G	NO	NO VFD		
4	Alarm Dialer #1	XY_02_990	TS9 10,11,12	Slot 09: DO3	G	NO			
5	Alarm Dialer #2	XY_02_991	TS9 13,14,15	Slot 09: DO4	G	NO			
6	Alarm Dialer #3	XY_02_992	TS9 16,17,18	Slot 09: DO5	G	NO			
7	Alarm Dialer #4	XY_02_993	TS9 19,20,21	Slot 09: DO6	G	NO			
8	SPARE		TS9 22,23,24	Slot 09: DO7	-				
8	SPARE		TS9 25,26,27	Slot 09: DO8	-				
8	SPARE		TS9 28,29,30	Slot 09: DO9	-				
8	SPARE		TS9 31,32,33	Slot 09: DO10	-				
8	SPARE		TS9 34,35,36	Slot 09: DO11	-				
8	SPARE		TS9 37,38,39	Slot 09: DO12	-				
8	SPARE		TS9 40,41,42	Slot 09: DO13	-				
8	SPARE		TS9 43,44,45	Slot 09: DO14	-				
8	SPARE		TS9 46,47,48	Slot 09: DO15	-				

ANALOG INPUTS

#	Signal Description	PLC Tag	Terminal Strip	PLC Termination	G/N	RANGE	COMMENTS 1	COMMENTS 2	COMMENTS 3
1	B02110 Speed Indication	SI_02_110	TS10 1,2,3	Slot 10: AI0	G	0-60 Hz			
2	FV02150 Position Indication	ZI_02_150	TS10 4,5,6	Slot 10: AI1	G	100%			
3	FV02155 Position Indication	ZI_02_155	TS10 7,8,9	Slot 10: AI2	G	100%			
4	FV02170 Position Indication	ZI_02_170	TS10 10,11,12	Slot 10: AI3	G	100%			
5	Process Aeration Blower Outlet Pressure Indication	PI_02_195	TS10 13,14,15	Slot 10: AI4	G	00 kPa0.72518914.5038	need to confirm with air and mech gage	PASSIVE	
6	MBBR 1 T02210 Cell 11 DO Indication	AI_02_211	TS10 16,17,18	Slot 10: AI5	G	020 mg/L			
7	MBBR 1 T02210 Cell 12 DO Indication	AI_02_212	TS10 19,20,21	Slot 10: AI6	G	020 mg/L			
8	P-04-770 Speed Indication	SI_04_770	TS10 22,23,24	Slot 10: AI7	G	0-60 Hz	NO VFD		
9	P02610 Speed Indication	SI_02_610	TS10 25,26,27	Slot 10: AI8	G	0-60 Hz	TWAS Pump 1		
10	P03630 Speed Indication	SI_03_630	TS10 28,29,30	Slot 10: AI9	G	0-60 Hz			
11	T03630 TWAS Tank #1 Level Indication	LI_03_111	TS10 31,32,33	Slot 10: AI10	G	0-4.235-.3m			
12	BFP03650 Inlet Flow Indication	FI_03_695	TS10 34,35,36	Slot 10: AI11	G	0-7200 L/hr	pulse 7.5 L // 100ms		
13	BFP-04-900 Level indication	LI_04_900	TS10 37,38,39	Slot 10: AI12	G	0.05-4.13m			
14	P-04-970 Speed Indication	SI_04_970	TS10 40,41,42	Slot 10: AI13	G	0-60 Hz	NO VFD		
15	DAF 2 Polymer Flow Indication	FI_04_799	TS10 43,44,45	Slot 10: AI14	G	0-150 L/hr	pulse 1L/ Pulse .001m3 // 100ms		
16	BFP Polymer Outlet Flow Indication	FI_04_999	TS10 46,47,48	Slot 10: AI15	G	0-750 L/hr	pulse 1L/ Pulse .001m3 // 100ms		
1	B02120 Speed Indication	SI_02_120	TS11 1,2,3	Slot 11: AI0	G	0-60 Hz			
2	Process Air MBBR 2 Flow Indication	FI_02_152	TS11 4,5,6	Slot 11: AI1	G	0-850 M3/HR	pulse 1m3 // 100ms		
3	Process Air DAF 2 Flow Indication	FI_02_156	TS11 7,8,9	Slot 11: AI2	G	0-850 M3/HR	pulse 1m3 // 100ms		
4	Process Air DAF 1 Flow Indication	FI_02_172	TS11 10,11,12	Slot 11: AI3	G	0-850 M3/HR	pulse 1m3 // 100ms		
5	Effluent Final Flow Indication	FI_02_328	TS11 13,14,15	Slot 11: AI4	G	0-200 L/sec	pulse 100L // 100ms		
6	MBBR 2 T02220 Cell 21 DO Indication	AI_02_221	TS11 16,17,18	Slot 11: AI5	G	0-20 mg/L			
7	MBBR 2 T02220 Cell 22 DO Indication	AI_02_222	TS11 19,20,21	Slot 11: AI6	G	0-20 mg/L			
8	P-04-780 Speed Indication	SI_04_780	TS11 22,23,24	Slot 11: AI7	G	0-60 Hz	NO VFD		
9	P02620 Speed Indication	SI_02_620	TS11 25,26,27	Slot 11: AI8	G	0-60 Hz	TWAS Pump 2		
10	P03640 Speed Indication	SI_03_640	TS11 28,29,30	Slot 11: AI9	G	060 Hz	BFP Feed Press pump 2		
11	T03630 TWAS Aerated Tank #2 Level Indication	LI_03_121	TS11 31,32,33	Slot 11: AI10	G	0-4.315-.3m			
12	DAF Lower H2S Gas indication	AI_02_905	TS11 34,35,36	Slot 11: AI11	G	050 PPM			
13	BFP H2S Gas Indication	AI_03_906	TS11 37,38,39	Slot 11: AI12	G	050 PPM			
14	P-04-980 Speed Indication	SI_04_980	TS11 40,41,42	Slot 11: AI13	G	0-60 Hz	NO VFD		
15	DAF 1 Polymer Flow Indication	FI_04_798	TS11 43,44,45	Slot 11: AI14	G	0150 L/hr	pulse 1L/ Pulse .001m3 // 100ms		
16	PDS-04-700 Level Indication	LI_04_700	TS11 46,47,48	Slot 11: AI15	G	0.05-4.13m			
1	B02130 Speed Indication	SI_02_130	TS12 1,2,3	Slot 12: AI0	G	060 Hz			
2	MBBR 2 H2S Gas Indication	AI_02_907	TS12 4,5,6	Slot 12: AI1	G	050 PPM			
3	DAF 2 H2S Gas Indication	AI_02_908	TS12 7,8,9	Slot 12: AI2	G	050 PPM			
4	MBBR 1 H2S Gas Indication	AI_02_909	TS12 10,11,12	Slot 12: AI3	G	050 PPM			
5	BFP HS2 Gas Indication	AI_03_910	TS12 13,14,15	Slot 12: AI4	G	050 PPM			
6	Generator Room CO Indication	AI_02_801	TS12 16,17,18	Slot 12: AI5	G	02000 PPM			
7	FQI04300 Potable Water Flow Indication	FI_04_300	TS12 19,20,21	Slot 12: AI6	G	1250GPM // 078.8625L	pulse 10m3 // 100ms		
8	P-04-790 Speed Indication	SI_04_790	TS12 22,23,24	Slot 12: AI7	G	0-60 Hz	NO VFD		
9	PDTI_03_630 TWAS Pressure Differential	PDT_03_630	TS12 25,26,27	Slot 12: AI8	G	0-10 psi		Pressure Indication PIT-03-630	PI_03_630
10	SPARE		TS12 28,29,30	Slot 12: AI9	-		Deleted	Pressure Indication PIT-03-640	PI_03_640
11	Temerapture Indicator TIT02953 Electrical Room	TI_02_953	TS12 31,32,33	Slot 12: AI10	G	5050 DegC	Added	PASSIVE	
12	Temerapture Indicator TIT02954 DAF Room	TI_02_954	TS12 34,35,36	Slot 12: AI11	G	5050 DegC	Added	PASSIVE	
13	Temerapture Indicator TIT02955 Belt Press Filter Door	TI_02_955	TS12 37,38,39	Slot 12: AI12	G	5050 DegC	Added	PASSIVE	
14	SPARE		TS12 40,41,42	Slot 12: AI13	-				
15	SPARE		TS12 43,44,45	Slot 12: AI14	-				
16	SPARE		TS12 46,47,48	Slot 12: AI15	-				

ANALOG OUTPUTS

#	Signal Description	PLC Tag	Terminal Strip	PLC Termination	G/N	RANGE	COMMENTS 1	COMMENTS 2	COMMENTS 3
1	B02110 Speed Command	SC_02_110	TS13 1,2	Slot 13: AO0	G	60			
2	B02120 Speed Command	SC_02_120	TS13 3,4	Slot 13: AO1	G	60			
3	B02130 Speed Command	SC_02_130	TS13 5,6	Slot 13: AO2	G	60			
4	FV02150 Position Command	ZC_02_150	TS13 7,8	Slot 13: AO3	G	100			
5	FV02155 Position Command	ZC_02_155	TS13 9,10	Slot 13: AO4	G	100			
6	FV02170 Position Command	ZC_02_170	TS13 11,12	Slot 13: AO5	G	100			
7	P-04-770 Speed Command	SC_04_770	TS13 13,14	Slot 13: AO6	G	60	NO VFD		
8	P-04-780 Speed Command	SC_04_780	TS13 15,16	Slot 13: AO7	G	60	NO VFD		
9	P-04-790 Speed Command	SC_04_790	TS14 1,2	Slot 14: AO0	G	60	NO VFD		
10	P02610 Speed Command	SC_02_610	TS14 3,4	Slot 14: AO1	G	60			

11	P02620 Speed Command	SC_02_620	TS14 5,6	Slot 14: AO2	G	60			
12	P03630 Speed Command	SC_03_630	TS14 7,8	Slot 14: AO3	G	60			
13	P03640 Speed Command	SC_03_640	TS14 9,10	Slot 14: AO4	G	60			
14	P-04-970 Speed Command	SC_04_970	TS14 11,12	Slot 14: AO5	G	60	NO VFD		
15	P-04-980 Speed Command	SC_04_980	TS14 13,14	Slot 14: AO6	G	60	NO VFD		
16	SPARE		TS14 15,16	Slot 14: AO7	-				

Custom Tags / Alarms

#	Signal Description	PLC Tag	Terminal Strip	PLC Termination	G/N	NC/CO	COMMENTS 1	COMMENTS 2	COMMENTS 3
	DAF #1 Run Status	YI_02_310			G				
	DAF #1 Fault Status	XA_02_310			G				
	DAF #2 Run Status	YI_02_320			G				
	DAF #2 Fault Status	XA_02_320			G				
	T02310 DAF #1 High Level Alarm	LAH_02_330			G				
	DAF #1 Thickened Water High Level Alarm	LAH_02_332			G				
	T02320 DAF #2 High Level Alarm	LAH_03_342			G				
	DAF #2 Thickened Water High Level Alarm	LAH_02_342			G				

I/O CHECK COMPLETION STATUS

DELAYED	0	
RFI	0	
G	234	
N	7	
Total [Without DELAYED & RFI]	241	97.10%
Total [With DELAYED & RFI]	241	100.00%